

Unix Programmer's Manual Reference Guide



Printed by the USENIX Association as a service to the UNIX Community. This material is copyrighted by The Regents of the University of California and/or Bell Telephone Laboratories, and is reprinted by permission. Permission for the publication or other use of these materials may be granted only by the Licensors and copyright holders.

Cover design by John Lassetter, Lucasfilm, Ltd.

4.2 BSD edition:

First Printing	July 1984
Second Printing	December 1984
Third Printing	September 1985
Fourth Printing	March 1986

4.3 BSD edition:

First Printing	November 1986
Second Printing	June 1987
Third Printing	June 1988

UNIX Programmer's Reference Manual (PRM)

4.3 Berkeley Software Distribution Virtual VAX-11 Version

April, 1986

**Computer Systems Research Group
Computer Science Division
Department of Electrical Engineering and Computer Science
University of California
Berkeley, California 94720**

Copyright 1979, 1980, 1983, 1986 Regents of the University of California. Permission to copy these documents or any portion thereof as necessary for licensed use of the software is granted to licensees of this software, provided this copyright notice and statement of permission are included.

Copyright 1979, AT&T Bell Laboratories, Incorporated. Holders of UNIXTM/32V, System III, or System V software licenses are permitted to copy these documents, or any portion of them, as necessary for licensed use of the software, provided this copyright notice and statement of permission are included.

This manual reflects system enhancements made at Berkeley and sponsored in part by the Defense Advanced Research Projects Agency (DoD), Arpa Order No. 4871 monitored by the Naval Electronics Systems Command under contract No. N00039-84-C-0089. The views and conclusions contained in these documents are those of the authors and should not be interpreted as representing official policies, either expressed or implied, of the Defense Research Projects Agency or of the US Government.

TABLE OF CONTENTS

2. System Calls

intro	introduction to system calls and error numbers
accept	accept a connection on a socket
access	determine accessibility of file
acct	turn accounting on or off
adjtime	correct the time to allow synchronization of the system clock
bind	bind a name to a socket
brk	change data segment size
chdir	change current working directory
chmod	change mode of file
chown	change owner and group of a file
chroot	change root directory
close	delete a descriptor
connect	initiate a connection on a socket
creat	create a new file
dup	duplicate a descriptor
execve	execute a file
exit	terminate a process
fcntl	file control
flock	apply or remove an advisory lock on an open file
fork	create a new process
fsync	synchronize a file's in-core state with that on disk
getdtablesize	get descriptor table size
getgid	get group identity
getgroups	get group access list
gethostid	get/set unique identifier of current host
gethostname	get/set name of current host
getitimer	get/set value of interval timer
getpagesize	get system page size
getpeername	get name of connected peer
getpgid	get process group
getpid	get process identification
getpriority	get/set program scheduling priority
getrlimit	control maximum system resource consumption
getrusage	get information about resource utilization
getsockname	get socket name
getsockopt	get and set options on sockets
gettimeofday	get/set date and time
getuid	get user identity
ioctl	control device
kill	send signal to a process
killpg	send signal to a process group
link	make a hard link to a file
listen	listen for connections on a socket
lseek	move read/write pointer
mkdir	make a directory file
mknod	make a special file
mount	mount or remove file system
open	open a file for reading or writing, or create a new file
pipe	create an interprocess communication channel
profil	execution time profile
ptrace	process trace
quota	manipulate disk quotas
read	read input

readlink	read value of a symbolic link
reboot	reboot system or halt processor
recv	receive a message from a socket
rename	change the name of a file
rmdir	remove a directory file
select	synchronous I/O multiplexing
send	send a message from a socket
setgroups	set group access list
setpgid	set process group
setquota	enable/disable quotas on a file system
setregid	set real and effective group ID
setreuid	set real and effective user ID's
shutdown	shut down part of a full-duplex connection
sigblock	block signals
sigpause	atomically release blocked signals and wait for interrupt
sigreturn	return from signal
sigsetmask	set current signal mask
sigstack	set and/or get signal stack context
sigvec	software signal facilities
socket	create an endpoint for communication
socketpair	create a pair of connected sockets
stat	get file status
swapon	add a swap device for interleaved paging/swapping
symlink	make symbolic link to a file
sync	update super-block
syscall	indirect system call
truncate	truncate a file to a specified length
umask	set file creation mode mask
unlink	remove directory entry
utimes	set file times
vfork	spawn new process in a virtual memory efficient way
vhangup	virtually "hangup" the current control terminal
wait	wait for process to terminate
write	write output

3. C Library Subroutines

intro	introduction to C library functions
abort	generate a fault
abs	integer absolute value
alarm	schedule signal after specified time
asinh	inverse hyperbolic functions
assert	program verification
atof	convert ASCII to numbers
bstring	bit and byte string operations
byteorder	convert values between host and network byte order
crypt	DES encryption
ctime	convert date and time to ASCII
ctype	character classification macros
curses	screen functions with "optimal" cursor motion
dbm	data base subroutines
directory	directory operations
ecvt	output conversion
end	last locations in program
erf	error functions
execl	execute a file
exit	terminate a process after flushing any pending output

exp	exponential, logarithm, power
fclose	close or flush a stream
ferror	stream status inquiries
floor	absolute value, floor, ceiling, and round-to-nearest functions
fopen	open a stream
fread	buffered binary input/output
frexp	split into mantissa and exponent
fseek	reposition a stream
getc	get character or word from stream
getdisk	get disk description by its name
getenv	value for environment name
getfsent	get file system descriptor file entry
getgrent	get group file entry
gethostbyname	get network host entry
getlogin	get login name
getnetent	get network entry
getopt	get option letter from argv
getpass	read a password
getprotoent	get protocol entry
getpw	get name from uid
getpwent	get password file entry
gets	get a string from a stream
getservent	get service entry
gettyent	get tty file entry
getusershell	get legal user shells
getwd	get current working directory pathname
hypot	Euclidean distance, complex absolute value
ieee	copysign, remainder, exponent manipulations
inet	Internet address manipulation routines
infnan	signals invalid floating-point operations on a VAX (temporary)
initgroups	initialize group access list
insque	insert/remove element from a queue
j0	bessel functions
lgamma	log gamma function
lib2648	subroutines for the HP 2648 graphics terminal
malloc	memory allocator
math	introduction to mathematical library functions
mktemp	make a unique file name
monitor	prepare execution profile
mp	multiple precision integer arithmetic
ndbm	data base subroutines
nice	set program priority
nlist	get entries from name list
ns	Xerox NS(tm) address conversion routines
pause	stop until signal
perror	system error messages
plot	graphics interface
popen	initiate I/O to/from a process
printf	formatted output conversion
psignal	system signal messages
putc	put character or word on a stream
puts	put a string on a stream
qsort	quicker sort
rand	random number generator
random	better random number generator; routines for changing generators
rcmd	routines for returning a stream to a remote command

regex	regular expression handler
resolver	resolver routines
rexec	return stream to a remote command
scandir	scan a directory
scanf	formatted input conversion
setbuf	assign buffering to a stream
setjmp	non-local goto
setuid	set user and group ID
siginterrupt	allow signals to interrupt system calls
signal	simplified software signal facilities
sin	trigonometric functions and their inverses
sinh	hyperbolic functions
sleep	suspend execution for interval
sqrt	cube root, square root
stdio	standard buffered input/output package
string	string operations
stty	set and get terminal state (defunct)
swab	swap bytes
syslog	control system log
system	issue a shell command
termcap	terminal independent operation routines
time	get date and time
times	get process times
ttyname	find name of a terminal
ualarm	schedule signal after specified time
ungetc	push character back into input stream
usleep	suspend execution for interval
utime	set file times
valloc	aligned memory allocator
varargs	variable argument list
vlimit	control maximum system resource consumption
vtimes	get information about resource utilization

3F. Fortran Library

intro	introduction to FORTRAN library functions
abort	abnormal termination
access	determine accessibility of a file
alarm	execute a subroutine after a specified time
bessel	of two kinds for integer orders
bit	and, or, xor, not, rshift, lshift bitwise functions
chdir	change default directory
chmod	change mode of a file
etime	return elapsed execution time
exit	terminate process with status
fdate	return date and time in an ASCII string
flmin	return extreme values
flush	flush output to a logical unit
fork	create a copy of this process
fseek	reposition a file on a logical unit
getarg	return command line arguments
getc	get a character from a logical unit
getcwd	get pathname of current working directory
getenv	get value of environment variables
getlog	get user's login name
getpid	get process id
getuid	get user or group ID of the caller

hostnm	get name of current host
idate	return date or time in numerical form
index	tell about character objects
ioinit	change f77 I/O initialization
kill	send a signal to a process
link	make a link to an existing file
loc	return the address of an object
long	integer object conversion
malloc	memory allocator
perror	get system error messages
plot	f77 library interface to <i>plot</i> (3X) libraries.
putc	write a character to a fortran logical unit
qsort	quick sort
rand	return random values
random	better random number generator
rename	rename a file
signal	change the action for a signal
sleep	suspend execution for an interval
stat	get file status
system	execute a UNIX command
time	return system time
topen	f77 tape I/O
traper	trap arithmetic errors
trapov	trap and repair floating point overflow
trpfpe	trap and repair floating point faults
ttynam	find name of a terminal port
unlink	remove a directory entry
wait	wait for a process to terminate

4. Special Files

intro	introduction to special files and hardware support
acc	ACC LH/DH IMP interface
ad	Data Translation A/D converter
arp	Address Resolution Protocol
autoconf	diagnostics from the autoconfiguration code
bk	line discipline for machine-machine communication (obsolete)
cons	VAX-11 console interface
crl	VAX 8600 console RL02 interface
css	DEC IMP-11A LH/DH IMP interface
ct	phototypesetter interface
ddn	DDN Standard Mode X.25 IMP interface
de	DEC DEUNA 10 Mb/s Ethernet interface
dh	DH-11/DM-11 communications multiplexer
dhu	DHU-11 communications multiplexer
dmc	DEC DMC-11/DMR-11 point-to-point communications device
dmf	DMF-32, terminal multiplexor
dmz	DMZ-32 terminal multiplexor
dn	DN-11 autocall unit interface
drum	paging device
dz	DZ-11 communications multiplexer
ec	3Com 10 Mb/s Ethernet interface
en	Xerox 3 Mb/s Ethernet interface
ex	Excelan 10 Mb/s Ethernet interface
fl	console floppy interface
hdh	ACC IF-11/HDH IMP interface
hk	RK6-11/RK06 and RK07 moving head disk

hp	MASSBUS disk interface
ht	TM-03/TE-16,TU-45,TU-77 MASSBUS magtape interface
hy	Network Systems Hyperchannel interface
icmp	Internet Control Message Protocol
idp	Xerox Internet Datagram Protocol
ik	Ikonas frame buffer, graphics device interface
il	Interlan NI1010 10 Mb/s Ethernet interface
imp	1822 network interface
imp	IMP raw socket interface
inet	Internet protocol family
ip	Internet Protocol
ix	Interlan Np100 10 Mb/s Ethernet interface
kg	KL-11/DL-11W line clock
lo	software loopback network interface
lp	line printer
mem	main memory
mt	TM78/TU-78 MASSBUS magtape interface
mtio	UNIX magtape interface
np	Interlan Np100 10 Mb/s Ethernet interface
ns	Xerox Network Systems(tm) protocol family
nsip	software network interface encapsulating ns packets in ip packets.
null	data sink
pcl	DEC CSS PCL-11 B Network Interface
ps	Evans and Sutherland Picture System 2 graphics device interface
pty	pseudo terminal driver
qe	DEC DEQNA Q-bus 10 Mb/s Ethernet interface
rx	DEC RX02 floppy disk interface
spp	Xerox Sequenced Packet Protocol
tb	line discipline for digitizing devices
tcp	Internet Transmission Control Protocol
tm	TM-11/TE-10 magtape interface
tmscp	DEC TMSCP magtape interface
ts	TS-11 magtape interface
tty	general terminal interface
tu	VAX-11/730 and VAX-11/750 TU58 console cassette interface
uda	UDA-50 disk controller interface
udp	Internet User Datagram Protocol
up	unibus storage module controller/drives
ut	UNIBUS TU45 tri-density tape drive interface
uu	TU58/DECtape II UNIBUS cassette interface
va	Benson-Varian interface
vp	Versatec interface
vv	Proteon proNET 10 Megabit ring

5. File Formats

a.out	assembler and link editor output
acct	execution accounting file
aliases	aliases file for sendmail
ar	archive (library) file format
core	format of memory image file
dbx	dbx symbol table information
dir	format of directories
disktab	disk description file
dump	incremental dump format
fs	format of file system volume
fstab	static information about the filesystems

gettytab	terminal configuration data base
group	group file
hosts	host name data base
L-devices	UUCP device description file
L-dialcodes	UUCP phone number index file
L.aliases	UUCP hostname alias file
L.cmds	UUCP remote command permissions file
L.sys	UUCP remote host description file
map3270	database for mapping ascii keystrokes into IBM 3270 keys
mtab	mounted file system table
networks	network name data base
passwd	password file
phones	remote host phone number data base
plot	graphics interface
printcap	printer capability data base
protocols	protocol name data base
remote	remote host description file
resolver	resolver configuration file
services	service name data base
stab	symbol table types
tar	tape archive file format
termcap	terminal capability data base
tp	DEC/mag tape formats
ttys	terminal initialization data
types	primitive system data types
USERFILE	UUCP pathname permissions file
utmp	login records
uencode	format of an encoded uencode file
vfont	font formats for the Benson-Varian or Versatec
vgrindfs	vgrind's language definition data base

NAME

intro - introduction to system calls and error numbers

SYNOPSIS

```
#include <sys/errno.h>
```

DESCRIPTION

This section describes all of the system calls. Most of these calls have one or more error returns. An error condition is indicated by an otherwise impossible return value. This is almost always -1; the individual descriptions specify the details. Note that a number of system calls overload the meanings of these error numbers, and that the meanings must be interpreted according to the type and circumstances of the call.

As with normal arguments, all return codes and values from functions are of type integer unless otherwise noted. An error number is also made available in the external variable *errno*, which is not cleared on successful calls. Thus *errno* should be tested only after an error has occurred.

The following is a complete list of the errors and their names as given in *<sys/errno.h>*.

- 0 Error 0
Unused.
- 1 EPERM Not owner
Typically this error indicates an attempt to modify a file in some way forbidden except to its owner or super-user. It is also returned for attempts by ordinary users to do things allowed only to the super-user.
- 2 ENOENT No such file or directory
This error occurs when a file name is specified and the file should exist but doesn't, or when one of the directories in a path name does not exist.
- 3 ESRCH No such process
The process or process group whose number was given does not exist, or any such process is already dead.
- 4 EINTR Interrupted system call
An asynchronous signal (such as interrupt or quit) that the user has elected to catch occurred during a system call. If execution is resumed after processing the signal and the system call is not restarted, it will appear as if the interrupted system call returned this error condition.
- 5 EIO I/O error
Some physical I/O error occurred during a *read* or *write*. This error may in some cases occur on a call following the one to which it actually applies.
- 6 ENXIO No such device or address
I/O on a special file refers to a subdevice that does not exist, or beyond the limits of the device. It may also occur when, for example, an illegal tape drive unit number is selected or a disk pack is not loaded on a drive.
- 7 E2BIG Arg list too long
An argument list longer than 20480 bytes (or the current limit, NCARGS in *<sys/param.h>*) is presented to *execve*.
- 8 ENOEXEC Exec format error
A request is made to execute a file that, although it has the appropriate permissions, does not start with a valid magic number, (see *a.out(5)*).
- 9 EBADF Bad file number
Either a file descriptor refers to no open file, or a read (resp. write) request is made to a file that is open only for writing (resp. reading).

- 10 ECHILD No children
Wait and the process has no living or unwaited-for children.
- 11 EAGAIN No more processes
 In a *fork*, the system's process table is full or the user is not allowed to create any more processes.
- 12 ENOMEM Not enough memory
 During an *execve* or *break*, a program asks for more core or swap space than the system is able to supply, or a process size limit would be exceeded. A lack of swap space is normally a temporary condition; however, a lack of core is not a temporary condition; the maximum size of the text, data, and stack segments is a system parameter. Soft limits may be increased to their corresponding hard limits.
- 13 EACCES Permission denied
 An attempt was made to access a file in a way forbidden by the protection system.
- 14 EFAULT Bad address
 The system encountered a hardware fault in attempting to access the arguments of a system call.
- 15 ENOTBLK Block device required
 A plain file was mentioned where a block device was required, e.g., in *mount*.
- 16 EBUSY Device busy
 An attempt to mount a device that was already mounted or an attempt was made to dismount a device on which there is an active file (open file, current directory, mounted-on file, or active text segment). A request was made to an exclusive access device that was already in use.
- 17 EEXIST File exists
 An existing file was mentioned in an inappropriate context, e.g., *link*.
- 18 EXDEV Cross-device link
 A hard link to a file on another device was attempted.
- 19 ENODEV No such device
 An attempt was made to apply an inappropriate system call to a device, e.g., to read a write-only device, or the device is not configured by the system.
- 20 ENOTDIR Not a directory
 A non-directory was specified where a directory is required, for example, in a path name or as an argument to *chdir*.
- 21 EISDIR Is a directory
 An attempt to write on a directory.
- 22 EINVAL Invalid argument
 Some invalid argument: dismounting a non-mounted device, mentioning an unknown signal in *signal*, or some other argument inappropriate for the call. Also set by math functions, (see *math(3)*).
- 23 ENFILE File table overflow
 The system's table of open files is full, and temporarily no more *opens* can be accepted.
- 24 EMFILE Too many open files
 As released, the limit on the number of open files per process is 64. *Getdtablesize(2)* will obtain the current limit. Customary configuration limit on most other UNIX systems is 20 per process.

- 25 **ENOTTY** Inappropriate ioctl for device
The file mentioned in an *ioctl* is not a terminal or one of the devices to which this call applies.
- 26 **ETXTBSY** Text file busy
An attempt to execute a pure-procedure program that is currently open for writing. Also an attempt to open for writing a pure-procedure program that is being executed.
- 27 **EFBIG** File too large
The size of a file exceeded the maximum (about 2^{31} bytes).
- 28 **ENOSPC** No space left on device
A *write* to an ordinary file, the creation of a directory or symbolic link, or the creation of a directory entry failed because no more disk blocks are available on the file system, or the allocation of an inode for a newly created file failed because no more inodes are available on the file system.
- 29 **ESPIPE** Illegal seek
An *lseek* was issued to a socket or pipe. This error may also be issued for other non-seekable devices.
- 30 **EROFS** Read-only file system
An attempt to modify a file or directory was made on a device mounted read-only.
- 31 **EMLINK** Too many links
An attempt to make more than 32767 hard links to a file.
- 32 **EPIPE** Broken pipe
A write on a pipe or socket for which there is no process to read the data. This condition normally generates a signal; the error is returned if the signal is caught or ignored.
- 33 **EDOM** Argument too large
The argument of a function in the math package (3M) is out of the domain of the function.
- 34 **ERANGE** Result too large
The value of a function in the math package (3M) is unrepresentable within machine precision.
- 35 **EWouldBlock** Operation would block
An operation that would cause a process to block was attempted on an object in non-blocking mode (see *fcntl(2)*).
- 36 **EINPROGRESS** Operation now in progress
An operation that takes a long time to complete (such as a *connect(2)*) was attempted on a non-blocking object (see *fcntl(2)*).
- 37 **EALREADY** Operation already in progress
An operation was attempted on a non-blocking object that already had an operation in progress.
- 38 **ENOTSOCK** Socket operation on non-socket
Self-explanatory.
- 39 **EDESTADDRREQ** Destination address required
A required address was omitted from an operation on a socket.
- 40 **EMSGSIZE** Message too long
A message sent on a socket was larger than the internal message buffer or some other network limit.

- 41 EPROTOTYPE Protocol wrong type for socket
A protocol was specified that does not support the semantics of the socket type requested. For example, you cannot use the ARPA Internet UDP protocol with type `SOCK_STREAM`.
- 42 ENOPROTOPT Option not supported by protocol
A bad option or level was specified in a *getsockopt(2)* or *setsockopt(2)* call.
- 43 EPROTONOSUPPORT Protocol not supported
The protocol has not been configured into the system or no implementation for it exists.
- 44 ESOCKTNOSUPPORT Socket type not supported
The support for the socket type has not been configured into the system or no implementation for it exists.
- 45 EOPNOTSUPP Operation not supported on socket
For example, trying to *accept* a connection on a datagram socket.
- 46 EPFNOSUPPORT Protocol family not supported
The protocol family has not been configured into the system or no implementation for it exists.
- 47 EAFNOSUPPORT Address family not supported by protocol family
An address incompatible with the requested protocol was used. For example, you shouldn't necessarily expect to be able to use NS addresses with ARPA Internet protocols.
- 48 EADDRINUSE Address already in use
Only one usage of each address is normally permitted.
- 49 EADDRNOTAVAIL Can't assign requested address
Normally results from an attempt to create a socket with an address not on this machine.
- 50 ENETDOWN Network is down
A socket operation encountered a dead network.
- 51 ENETUNREACH Network is unreachable
A socket operation was attempted to an unreachable network.
- 52 ENETRESET Network dropped connection on reset
The host you were connected to crashed and rebooted.
- 53 ECONNABORTED Software caused connection abort
A connection abort was caused internal to your host machine.
- 54 ECONNRESET Connection reset by peer
A connection was forcibly closed by a peer. This normally results from a loss of the connection on the remote socket due to a timeout or a reboot.
- 55 ENOBUFS No buffer space available
An operation on a socket or pipe was not performed because the system lacked sufficient buffer space or because a queue was full.
- 56 EISCONN Socket is already connected
A *connect* request was made on an already connected socket; or, a *sendto* or *sendmsg* request on a connected socket specified a destination when already connected.
- 57 ENOTCONN Socket is not connected
An request to send or receive data was disallowed because the socket is not connected and (when sending on a datagram socket) no address was supplied.

- 58 **ESHUTDOWN** Can't send after socket shutdown
A request to send data was disallowed because the socket had already been shut down with a previous *shutdown(2)* call.
- 59 *unused*
- 60 **ETIMEDOUT** Connection timed out
A *connect* or *send* request failed because the connected party did not properly respond after a period of time. (The timeout period is dependent on the communication protocol.)
- 61 **ECONNREFUSED** Connection refused
No connection could be made because the target machine actively refused it. This usually results from trying to connect to a service that is inactive on the foreign host.
- 62 **ELOOP** Too many levels of symbolic links
A path name lookup involved more than 8 symbolic links.
- 63 **ENAMETOOLONG** File name too long
A component of a path name exceeded 255 (**MAXNAMELEN**) characters, or an entire path name exceeded 1023 (**MAXPATHLEN-1**) characters.
- 64 **EHOSTDOWN** Host is down
A socket operation failed because the destination host was down.
- 65 **EHOSTUNREACH** Host is unreachable
A socket operation was attempted to an unreachable host.
- 66 **ENOTEMPTY** Directory not empty
A directory with entries other than "." and ".." was supplied to a remove directory or rename call.
- 69 **EDQUOT** Disc quota exceeded
A *write* to an ordinary file, the creation of a directory or symbolic link, or the creation of a directory entry failed because the user's quota of disk blocks was exhausted, or the allocation of an inode for a newly created file failed because the user's quota of inodes was exhausted.

DEFINITIONS**Process ID**

Each active process in the system is uniquely identified by a positive integer called a process ID. The range of this ID is from 0 to 30000.

Parent process ID

A new process is created by a currently active process; (see *fork(2)*). The parent process ID of a process is the process ID of its creator.

Process Group ID

Each active process is a member of a process group that is identified by a positive integer called the process group ID. This is the process ID of the group leader. This grouping permits the signaling of related processes (see *killpg(2)*) and the job control mechanisms of *cs(1)*.

Tty Group ID

Each active process can be a member of a terminal group that is identified by a positive integer called the tty group ID. This grouping is used to arbitrate between multiple jobs contending for the same terminal; (see *cs(1)* and *tty(4)*).

Real User ID and Real Group ID

Each user on the system is identified by a positive integer termed the real user ID.

Each user is also a member of one or more groups. One of these groups is distinguished from others and used in implementing accounting facilities. The positive integer corresponding to this distinguished group is termed the real group ID.

All processes have a real user ID and real group ID. These are initialized from the equivalent attributes of the process that created it.

Effective User Id, Effective Group Id, and Access Groups

Access to system resources is governed by three values: the effective user ID, the effective group ID, and the group access list.

The effective user ID and effective group ID are initially the process's real user ID and real group ID respectively. Either may be modified through execution of a set-user-ID or set-group-ID file (possibly by one its ancestors) (see *execve(2)*).

The group access list is an additional set of group ID's used only in determining resource accessibility. Access checks are performed as described below in "File Access Permissions".

Super-user

A process is recognized as a *super-user* process and is granted special privileges if its effective user ID is 0.

Special Processes

The processes with a process ID's of 0, 1, and 2 are special. Process 0 is the scheduler. Process 1 is the initialization process *init*, and is the ancestor of every other process in the system. It is used to control the process structure. Process 2 is the paging daemon.

Descriptor

An integer assigned by the system when a file is referenced by *open(2)* or *dup(2)*, or when a socket is created by *pipe(2)*, *socket(2)* or *socketpair(2)*, which uniquely identifies an access path to that file or socket from a given process or any of its children.

File Name

Names consisting of up to 255 (MAXNAMELEN) characters may be used to name an ordinary file, special file, or directory.

These characters may be selected from the set of all ASCII character excluding 0 (null) and the ASCII code for / (slash). (The parity bit, bit 8, must be 0.)

Note that it is generally unwise to use *, ?, [or] as part of file names because of the special meaning attached to these characters by the shell.

Path Name

A path name is a null-terminated character string starting with an optional slash (/), followed by zero or more directory names separated by slashes, optionally followed by a file name. The total length of a path name must be less than 1024 (MAXPATHLEN) characters.

If a path name begins with a slash, the path search begins at the *root* directory. Otherwise, the search begins from the current working directory. A slash by itself names the root directory. A null pathname refers to the current directory.

Directory

A directory is a special type of file that contains entries that are references to other files. Directory entries are called links. By convention, a directory contains at least two links, . and .., referred to as *dot* and *dot-dot* respectively. Dot refers to the directory itself and dot-dot refers to its parent directory.

Root Directory and Current Working Directory

Each process has associated with it a concept of a root directory and a current working directory for the purpose of resolving path name searches. A process's root directory

need not be the root directory of the root file system.

File Access Permissions

Every file in the file system has a set of access permissions. These permissions are used in determining whether a process may perform a requested operation on the file (such as opening a file for writing). Access permissions are established at the time a file is created. They may be changed at some later time through the *chmod(2)* call.

File access is broken down according to whether a file may be: read, written, or executed. Directory files use the execute permission to control if the directory may be searched.

File access permissions are interpreted by the system as they apply to three different classes of users: the owner of the file, those users in the file's group, anyone else. Every file has an independent set of access permissions for each of these classes. When an access check is made, the system decides if permission should be granted by checking the access information applicable to the caller.

Read, write, and execute/search permissions on a file are granted to a process if:

The process's effective user ID is that of the super-user.

The process's effective user ID matches the user ID of the owner of the file and the owner permissions allow the access.

The process's effective user ID does not match the user ID of the owner of the file, and either the process's effective group ID matches the group ID of the file, or the group ID of the file is in the process's group access list, and the group permissions allow the access.

Neither the effective user ID nor effective group ID and group access list of the process match the corresponding user ID and group ID of the file, but the permissions for "other users" allow access.

Otherwise, permission is denied.

Sockets and Address Families

A socket is an endpoint for communication between processes. Each socket has queues for sending and receiving data.

Sockets are typed according to their communications properties. These properties include whether messages sent and received at a socket require the name of the partner, whether communication is reliable, the format used in naming message recipients, etc.

Each instance of the system supports some collection of socket types; consult *socket(2)* for more information about the types available and their properties.

Each instance of the system supports some number of sets of communications protocols. Each protocol set supports addresses of a certain format. An Address Family is the set of addresses for a specific group of protocols. Each socket has an address chosen from the address family in which the socket was created.

SEE ALSO

intro(3), *perror(3)*

NAME

`accept` – accept a connection on a socket

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>

ns = accept(s, addr, addrlen)
int ns, s;
struct sockaddr *addr;
int *addrlen;
```

DESCRIPTION

The argument *s* is a socket that has been created with *socket(2)*, bound to an address with *bind(2)*, and is listening for connections after a *listen(2)*. *Accept* extracts the first connection on the queue of pending connections, creates a new socket with the same properties of *s* and allocates a new file descriptor, *ns*, for the socket. If no pending connections are present on the queue, and the socket is not marked as non-blocking, *accept* blocks the caller until a connection is present. If the socket is marked non-blocking and no pending connections are present on the queue, *accept* returns an error as described below. The accepted socket, *ns*, may not be used to accept more connections. The original socket *s* remains open.

The argument *addr* is a result parameter that is filled in with the address of the connecting entity, as known to the communications layer. The exact format of the *addr* parameter is determined by the domain in which the communication is occurring. The *addrlen* is a value-result parameter; it should initially contain the amount of space pointed to by *addr*; on return it will contain the actual length (in bytes) of the address returned. This call is used with connection-based socket types, currently with *SOCK_STREAM*.

It is possible to *select(2)* a socket for the purposes of doing an *accept* by selecting it for read.

RETURN VALUE

The call returns *-1* on error. If it succeeds, it returns a non-negative integer that is a descriptor for the accepted socket.

ERRORS

The *accept* will fail if:

- | | |
|---------------|--|
| [EBADF] | The descriptor is invalid. |
| [ENOTSOCK] | The descriptor references a file, not a socket. |
| [EOPNOTSUPP] | The referenced socket is not of type <i>SOCK_STREAM</i> . |
| [EFAULT] | The <i>addr</i> parameter is not in a writable part of the user address space. |
| [EWOULDBLOCK] | The socket is marked non-blocking and no connections are present to be accepted. |

SEE ALSO

bind(2), *connect(2)*, *listen(2)*, *select(2)*, *socket(2)*

NAME

access – determine accessibility of file

SYNOPSIS

```
#include <sys/file.h>

#define R_OK    4    /* test for read permission */
#define W_OK    2    /* test for write permission */
#define X_OK    1    /* test for execute (search) permission */
#define F_OK    0    /* test for presence of file */

accessible = access(path, mode)
int accessible;
char *path;
int mode;
```

DESCRIPTION

Access checks the given file *path* for accessibility according to *mode*, which is an inclusive or of the bits R_OK, W_OK and X_OK. Specifying *mode* as F_OK (i.e., 0) tests whether the directories leading to the file can be searched and the file exists.

The real user ID and the group access list (including the real group ID) are used in verifying permission, so this call is useful to set-UID programs.

Notice that only access bits are checked. A directory may be indicated as writable by *access*, but an attempt to open it for writing will fail (although files may be created there); a file may look executable, but *execve* will fail unless it is in proper format.

RETURN VALUE

If *path* cannot be found or if any of the desired access modes would not be granted, then a -1 value is returned; otherwise a 0 value is returned.

ERRORS

Access to the file is denied if one or more of the following are true:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] The named file does not exist.
- [EACCES] Search permission is denied for a component of the path prefix.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EROFS] Write access is requested for a file on a read-only file system.
- [ETXTBSY] Write access is requested for a pure procedure (shared text) file that is being executed.
- [EACCES] Permission bits of the file mode do not permit the requested access, or search permission is denied on a component of the path prefix. The owner of a file has permission checked with respect to the "owner" read, write, and execute mode bits, members of the file's group other than the owner have permission checked with respect to the "group" mode bits, and all others have permissions checked with respect to the "other" mode bits.
- [EFAULT] *Path* points outside the process's allocated address space.
- [EIO] An I/O error occurred while reading from or writing to the file system.

SEE ALSO

chmod(2), stat(2)

NAME

acct – turn accounting on or off

SYNOPSIS

```
acct(file)
char *file;
```

DESCRIPTION

The system is prepared to write a record in an accounting *file* for each process as it terminates. This call, with a null-terminated string naming an existing file as argument, turns on accounting; records for each terminating process are appended to *file*. An argument of 0 causes accounting to be turned off.

The accounting file format is given in *acct(5)*.

This call is permitted only to the super-user.

NOTES

Accounting is automatically disabled when the file system the accounting file resides on runs out of space; it is enabled when space once again becomes available.

RETURN VALUE

On error -1 is returned. The file must exist and the call may be exercised only by the super-user. It is erroneous to try to turn on accounting when it is already on.

ERRORS

Acct will fail if one of the following is true:

- | | |
|----------------|---|
| [EPERM] | The caller is not the super-user. |
| [ENOTDIR] | A component of the path prefix is not a directory. |
| [EINVAL] | The pathname contains a character with the high-order bit set. |
| [ENAMETOOLONG] | A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters. |
| [ENOENT] | The named file does not exist. |
| [EACCES] | Search permission is denied for a component of the path prefix, or the path name is not a regular file. |
| [ELOOP] | Too many symbolic links were encountered in translating the pathname. |
| [EROFS] | The named file resides on a read-only file system. |
| [EFAULT] | <i>File</i> points outside the process's allocated address space. |
| [EIO] | An I/O error occurred while reading from or writing to the file system. |

SEE ALSO

acct(5), sa(8)

BUGS

No accounting is produced for programs running when a crash occurs. In particular non-terminating programs are never accounted for.

NAME

adjtime – correct the time to allow synchronization of the system clock

SYNOPSIS

```
#include <sys/time.h>

adjtime(delta, olddelta)
struct timeval *delta;
struct timeval *olddelta;
```

DESCRIPTION

Adjtime makes small adjustments to the system time, as returned by *gettimeofday(2)*, advancing or retarding it by the time specified by the *timeval* *delta*. If *delta* is negative, the clock is slowed down by incrementing it more slowly than normal until the correction is complete. If *delta* is positive, a larger increment than normal is used. The skew used to perform the correction is generally a fraction of one percent. Thus, the time is always a monotonically increasing function. A time correction from an earlier call to *adjtime* may not be finished when *adjtime* is called again. If *olddelta* is non-zero, then the structure pointed to will contain, upon return, the number of microseconds still to be corrected from the earlier call.

This call may be used by time servers that synchronize the clocks of computers in a local area network. Such time servers would slow down the clocks of some machines and speed up the clocks of others to bring them to the average network time.

The call *adjtime(2)* is restricted to the super-user.

RETURN VALUE

A return value of 0 indicates that the call succeeded. A return value of -1 indicates that an error occurred, and in this case an error code is stored in the global variable *errno*.

ERRORS

The following error codes may be set in *errno*:

- [EFAULT] An argument points outside the process's allocated address space.
- [EPERM] The process's effective user ID is not that of the super-user.

SEE ALSO

date(1), *gettimeofday(2)*, *timed(8)*, *timedc(8)*,

TSP: The Time Synchronization Protocol for UNIX 4.3BSD, R. Gusella and S. Zatti

NAME

bind – bind a name to a socket

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>

bind(s, name, namelen)
int s;
struct sockaddr *name;
int namelen;
```

DESCRIPTION

Bind assigns a name to an unnamed socket. When a socket is created with *socket(2)* it exists in a name space (address family) but has no name assigned. *Bind* requests that *name* be assigned to the socket.

NOTES

Binding a name in the UNIX domain creates a socket in the file system that must be deleted by the caller when it is no longer needed (using *unlink(2)*).

The rules used in name binding vary between communication domains. Consult the manual entries in section 4 for detailed information.

RETURN VALUE

If the bind is successful, a 0 value is returned. A return value of -1 indicates an error, which is further specified in the global *errno*.

ERRORS

The *bind* call will fail if:

- | | |
|-----------------|--|
| [EBADF] | <i>S</i> is not a valid descriptor. |
| [ENOTSOCK] | <i>S</i> is not a socket. |
| [EADDRNOTAVAIL] | The specified address is not available from the local machine. |
| [EADDRINUSE] | The specified address is already in use. |
| [EINVAL] | The socket is already bound to an address. |
| [EACCES] | The requested address is protected, and the current user has inadequate permission to access it. |
| [EFAULT] | The <i>name</i> parameter is not in a valid part of the user address space. |
- The following errors are specific to binding names in the UNIX domain.
- | | |
|----------------|---|
| [ENOTDIR] | A component of the path prefix is not a directory. |
| [EINVAL] | The pathname contains a character with the high-order bit set. |
| [ENAMETOOLONG] | A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters. |
| [ENOENT] | A prefix component of the path name does not exist. |
| [ELOOP] | Too many symbolic links were encountered in translating the pathname. |
| [EIO] | An I/O error occurred while making the directory entry or allocating the inode. |
| [EROFS] | The name would reside on a read-only file system. |

[EISDIR] A null pathname was specified.

SEE ALSO

connect(2), listen(2), socket(2), getsockname(2)

NAME

brk, *sbrk* – change data segment size

SYNOPSIS

```
#include <sys/types.h>
```

```
char *brk(addr)
```

```
char *addr;
```

```
char *sbrk(incr)
```

```
int incr;
```

DESCRIPTION

Brk sets the system's idea of the lowest data segment location not used by the program (called the break) to *addr* (rounded up to the next multiple of the system's page size). Locations greater than *addr* and below the stack pointer are not in the address space and will thus cause a memory violation if accessed.

In the alternate function *sbrk*, *incr* more bytes are added to the program's data space and a pointer to the start of the new area is returned.

When a program begins execution via *execve* the break is set at the highest location defined by the program and data storage areas. Ordinarily, therefore, only programs with growing data areas need to use *sbrk*.

The *getrlimit*(2) system call may be used to determine the maximum permissible size of the data segment; it will not be possible to set the break beyond the *rlim_max* value returned from a call to *getrlimit*, e.g. "etext + rlp → rlim_max." (see *end*(3) for the definition of *etext*).

RETURN VALUE

Zero is returned if the *brk* could be set; -1 if the program requests more memory than the system limit. *Sbrk* returns -1 if the break could not be set.

ERRORS

Sbrk will fail and no additional memory will be allocated if one of the following are true:

[ENOMEM] The limit, as set by *setrlimit*(2), was exceeded.

[ENOMEM] The maximum possible size of a data segment (compiled into the system) was exceeded.

[ENOMEM] Insufficient space existed in the swap area to support the expansion.

SEE ALSO

execve(2), *getrlimit*(2), *malloc*(3), *end*(3)

BUGS

Setting the break may fail due to a temporary lack of swap space. It is not possible to distinguish this from a failure caused by exceeding the maximum size of the data segment without consulting *getrlimit*.

NAME

chdir - change current working directory

SYNOPSIS

```
chdir(path)
char *path;
```

DESCRIPTION

Path is the pathname of a directory. *Chdir* causes this directory to become the current working directory, the starting point for path names not beginning with "/".

In order for a directory to become the current directory, a process must have execute (search) access to the directory.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Chdir will fail and the current working directory will be unchanged if one or more of the following are true:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] The named directory does not exist.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EACCES] Search permission is denied for any component of the path name.
- [EFAULT] *Path* points outside the process's allocated address space.
- [EIO] An I/O error occurred while reading from or writing to the file system.

SEE ALSO

chroot(2)

NAME

chmod – change mode of file

SYNOPSIS

chmod(path, mode)

char *path;

int mode;

fchmod(fd, mode)

int fd, mode;

DESCRIPTION

The file whose name is given by *path* or referenced by the descriptor *fd* has its mode changed to *mode*. Modes are constructed by *or*'ing together some combination of the following, defined in *<sys/inode.h>*:

ISUID	04000	set user ID on execution
ISGID	02000	set group ID on execution
ISVTX	01000	'sticky bit' (see below)
IREAD	00400	read by owner
IWRITE	00200	write by owner
IEXEC	00100	execute (search on directory) by owner
	00070	read, write, execute (search) by group
	00007	read, write, execute (search) by others

If an executable file is set up for sharing (this is the default) then mode ISVTX (the 'sticky bit') prevents the system from abandoning the swap-space image of the program-text portion of the file when its last user terminates. Ability to set this bit on executable files is restricted to the super-user.

If mode ISVTX (the 'sticky bit') is set on a directory, an unprivileged user may not delete or rename files of other users in that directory. For more details of the properties of the sticky bit, see *sticky(8)*.

Only the owner of a file (or the super-user) may change the mode.

Writing or changing the owner of a file turns off the set-user-id and set-group-id bits unless the user is the super-user. This makes the system somewhat more secure by protecting set-user-id (set-group-id) files from remaining set-user-id (set-group-id) if they are modified, at the expense of a degree of compatibility.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Chmod will fail and the file mode will be unchanged if:

[ENOTDIR] A component of the path prefix is not a directory.

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG]

A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] The named file does not exist.

[EACCES] Search permission is denied for a component of the path prefix.

[ELOOP] Too many symbolic links were encountered in translating the pathname.

[EPERM] The effective user ID does not match the owner of the file and the effective user ID is not the super-user.

- [EROFS] The named file resides on a read-only file system.
- [EFAULT] *Path* points outside the process's allocated address space.
- [EIO] An I/O error occurred while reading from or writing to the file system.
- Fchmod* will fail if:
- [EBADF] The descriptor is not valid.
- [EINVAL] *Fd* refers to a socket, not to a file.
- [EROFS] The file resides on a read-only file system.
- [EIO] An I/O error occurred while reading from or writing to the file system.

SEE ALSO

`chmod(1)`, `open(2)`, `chown(2)`, `stat(2)`, `sticky(8)`

NAME

chown – change owner and group of a file

SYNOPSIS

chown(*path*, *owner*, *group*)

char **path*;

int *owner*, *group*;

fchown(*fd*, *owner*, *group*)

int *fd*, *owner*, *group*;

DESCRIPTION

The file that is named by *path* or referenced by *fd* has its *owner* and *group* changed as specified. Only the super-user may change the owner of the file, because if users were able to give files away, they could defeat the file-space accounting procedures. The owner of the file may change the group to a group of which he is a member.

On some systems, *chown* clears the set-user-id and set-group-id bits on the file to prevent accidental creation of set-user-id and set-group-id programs.

Fchown is particularly useful when used in conjunction with the file locking primitives (see *flock*(2)).

One of the owner or group id's may be left unchanged by specifying it as -1.

If the final component of *path* is a symbolic link, the ownership and group of the symbolic link is changed, not the ownership and group of the file or directory to which it points.

RETURN VALUE

Zero is returned if the operation was successful; -1 is returned if an error occurs, with a more specific error code being placed in the global variable *errno*.

ERRORS

Chown will fail and the file will be unchanged if:

[ENOTDIR] A component of the path prefix is not a directory.

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG]

A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] The named file does not exist.

[EACCES] Search permission is denied for a component of the path prefix.

[ELOOP] Too many symbolic links were encountered in translating the pathname.

[EPERM] The effective user ID is not the super-user.

[EROFS] The named file resides on a read-only file system.

[EFAULT] *Path* points outside the process's allocated address space.

[EIO] An I/O error occurred while reading from or writing to the file system.

Fchown will fail if:

[EBADF] *Fd* does not refer to a valid descriptor.

[EINVAL] *Fd* refers to a socket, not a file.

[EPERM] The effective user ID is not the super-user.

[EROFS] The named file resides on a read-only file system.

[EIO]

An I/O error occurred while reading from or writing to the file system.

SEE ALSO**chown(8), chgrp(1), chmod(2), flock(2)**

NAME

chroot - change root directory

SYNOPSIS

chroot(dirname)
char *dirname;

DESCRIPTION

Dirname is the address of the pathname of a directory, terminated by a null byte. *Chroot* causes this directory to become the root directory, the starting point for path names beginning with "/".

In order for a directory to become the root directory a process must have execute (search) access to the directory.

This call is restricted to the super-user.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate an error.

ERRORS

Chroot will fail and the root directory will be unchanged if one or more of the following are true:

[ENOTDIR] A component of the path name is not a directory.

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG]

A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] The named directory does not exist.

[EACCES] Search permission is denied for any component of the path name.

[ELOOP] Too many symbolic links were encountered in translating the pathname.

[EFAULT] *Path* points outside the process's allocated address space.

[EIO] An I/O error occurred while reading from or writing to the file system.

SEE ALSO

chdir(2)

NAME

close – delete a descriptor

SYNOPSIS

```
close(d)
int d;
```

DESCRIPTION

The *close* call deletes a descriptor from the per-process object reference table. If this is the last reference to the underlying object, then it will be deactivated. For example, on the last close of a file the current *seek* pointer associated with the file is lost; on the last close of a *socket*(2) associated naming information and queued data are discarded; on the last close of a file holding an advisory lock the lock is released (see further *flock*(2)).

A close of all of a process's descriptors is automatic on *exit*, but since there is a limit on the number of active descriptors per process, *close* is necessary for programs that deal with many descriptors.

When a process forks (see *fork*(2)), all descriptors for the new child process reference the same objects as they did in the parent before the fork. If a new process is then to be run using *execve*(2), the process would normally inherit these descriptors. Most of the descriptors can be rearranged with *dup2*(2) or deleted with *close* before the *execve* is attempted, but if some of these descriptors will still be needed if the *execve* fails, it is necessary to arrange for them to be closed if the *execve* succeeds. For this reason, the call "*fcntl*(*d*, *F_SETFD*, 1)" is provided, which arranges that a descriptor will be closed after a successful *execve*; the call "*fcntl*(*d*, *F_SETFD*, 0)" restores the default, which is to not close the descriptor.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and the global integer variable *errno* is set to indicate the error.

ERRORS

Close will fail if:

[EBADF] *D* is not an active descriptor.

SEE ALSO

accept(2), *flock*(2), *open*(2), *pipe*(2), *socket*(2), *socketpair*(2), *execve*(2), *fcntl*(2)

NAME

connect – initiate a connection on a socket

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>

connect(s, name, namelen)
int s;
struct sockaddr *name;
int namelen;
```

DESCRIPTION

The parameter *s* is a socket. If it is of type `SOCK_DGRAM`, then this call specifies the peer with which the socket is to be associated; this address is that to which datagrams are to be sent, and the only address from which datagrams are to be received. If the socket is of type `SOCK_STREAM`, then this call attempts to make a connection to another socket. The other socket is specified by *name*, which is an address in the communications space of the socket. Each communications space interprets the *name* parameter in its own way. Generally, stream sockets may successfully *connect* only once; datagram sockets may use *connect* multiple times to change their association. Datagram sockets may dissolve the association by connecting to an invalid address, such as a null address.

RETURN VALUE

If the connection or binding succeeds, then 0 is returned. Otherwise a -1 is returned, and a more specific error code is stored in *errno*.

ERRORS

The call fails if:

- | | |
|-----------------|---|
| [EBADF] | <i>S</i> is not a valid descriptor. |
| [ENOTSOCK] | <i>S</i> is a descriptor for a file, not a socket. |
| [EADDRNOTAVAIL] | The specified address is not available on this machine. |
| [EAFNOSUPPORT] | Addresses in the specified address family cannot be used with this socket. |
| [EISCONN] | The socket is already connected. |
| [ETIMEDOUT] | Connection establishment timed out without establishing a connection. |
| [ECONNREFUSED] | The attempt to connect was forcefully rejected. |
| [ENETUNREACH] | The network isn't reachable from this host. |
| [EADDRINUSE] | The address is already in use. |
| [EFAULT] | The <i>name</i> parameter specifies an area outside the process address space. |
| [EINPROGRESS] | The socket is non-blocking and the connection cannot be completed immediately. It is possible to <i>select(2)</i> for completion by selecting the socket for writing. |
| [EALREADY] | The socket is non-blocking and a previous connection attempt has not yet been completed. |

The following errors are specific to connecting names in the UNIX domain. These errors may not apply in future versions of the UNIX IPC domain.

- | | |
|-----------|--|
| [ENOTDIR] | A component of the path prefix is not a directory. |
|-----------|--|

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG]

A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] The named socket does not exist.

[EACCES] Search permission is denied for a component of the path prefix.

[EACCES] Write access to the named socket is denied.

[ELOOP] Too many symbolic links were encountered in translating the pathname.

SEE ALSO

accept(2), select(2), socket(2), getsockname(2)

NAME

creat – create a new file

SYNOPSIS

```
creat(name, mode)
char *name;
```

DESCRIPTION

This interface is made obsolete by `open(2)`.

Creat creates a new file or prepares to rewrite an existing file called *name*, given as the address of a null-terminated string. If the file did not exist, it is given mode *mode*, as modified by the process's mode mask (see *umask(2)*). Also see *chmod(2)* for the construction of the *mode* argument.

If the file did exist, its mode and owner remain unchanged but it is truncated to 0 length.

The file is also opened for writing, and its file descriptor is returned.

NOTES

The *mode* given is arbitrary; it need not allow writing. This feature has been used in the past by programs to construct a simple, exclusive locking mechanism. It is replaced by the `O_EXCL` open mode, or *flock(2)* facility.

RETURN VALUE

The value `-1` is returned if an error occurs. Otherwise, the call returns a non-negative descriptor that only permits writing.

ERRORS

Creat will fail and the file will not be created or truncated if one of the following occur:

- | | |
|----------------|--|
| [ENOTDIR] | A component of the path prefix is not a directory. |
| [EINVAL] | The pathname contains a character with the high-order bit set. |
| [ENAMETOOLONG] | A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters. |
| [ENOENT] | The named file does not exist. |
| [ELOOP] | Too many symbolic links were encountered in translating the pathname. |
| [EACCES] | Search permission is denied for a component of the path prefix. |
| [EACCES] | The file does not exist and the directory in which it is to be created is not writable. |
| [EACCES] | The file exists, but it is unwritable. |
| [EISDIR] | The file is a directory. |
| [EMFILE] | There are already too many files open. |
| [ENFILE] | The system file table is full. |
| [ENOSPC] | The directory in which the entry for the new file is being placed cannot be extended because there is no space left on the file system containing the directory. |
| [ENOSPC] | There are no free inodes on the file system on which the file is being created. |
| [EDQUOT] | The directory in which the entry for the new file is being placed cannot be extended because the user's quota of disk blocks on the file system containing the directory has been exhausted. |

- [EDQUOT]** The user's quota of inodes on the file system on which the file is being created has been exhausted.
- [EROFS]** The named file resides on a read-only file system.
- [ENXIO]** The file is a character special or block special file, and the associated device does not exist.
- [ETXTBSY]** The file is a pure procedure (shared text) file that is being executed.
- [EIO]** An I/O error occurred while making the directory entry or allocating the inode.
- [EFAULT]** *Name* points outside the process's allocated address space.
- [EOPNOTSUPP]** The file was a socket (not currently implemented).

SEE ALSO

open(2), write(2), close(2), chmod(2), umask(2)

NAME

dup, *dup2* – duplicate a descriptor

SYNOPSIS

```
newd = dup(oldd)
int newd, oldd;

dup2(oldd, newd)
int oldd, newd;
```

DESCRIPTION

Dup duplicates an existing object descriptor. The argument *oldd* is a small non-negative integer index in the per-process descriptor table. The value must be less than the size of the table, which is returned by *getdtablesize(2)*. The new descriptor returned by the call, *newd*, is the lowest numbered descriptor that is not currently in use by the process.

The object referenced by the descriptor does not distinguish between references using *oldd* and *newd* in any way. Thus if *newd* and *oldd* are duplicate references to an open file, *read(2)*, *write(2)* and *lseek(2)* calls all move a single pointer into the file, and append mode, non-blocking I/O and asynchronous I/O options are shared between the references. If a separate pointer into the file is desired, a different object reference to the file must be obtained by issuing an additional *open(2)* call. The close-on-exec flag on the new file descriptor is unset.

In the second form of the call, the value of *newd* desired is specified. If this descriptor is already in use, the descriptor is first deallocated as if a *close(2)* call had been done first.

RETURN VALUE

The value -1 is returned if an error occurs in either call. The external variable *errno* indicates the cause of the error.

ERRORS

Dup and *dup2* fail if:

[EBADF]	<i>Oldd</i> or <i>newd</i> is not a valid active descriptor
[EMFILE]	Too many descriptors are active.

SEE ALSO

accept(2), *open(2)*, *close(2)*, *fcntl(2)*, *pipe(2)*, *socket(2)*, *socketpair(2)*, *getdtablesize(2)*

NAME

`execve` – execute a file

SYNOPSIS

```
execve(name, argv, envp)
char *name, *argv[], *envp[];
```

DESCRIPTION

Execve transforms the calling process into a new process. The new process is constructed from an ordinary file called the *new process file*. This file is either an executable object file, or a file of data for an interpreter. An executable object file consists of an identifying header, followed by pages of data representing the initial program (text) and initialized data pages. Additional pages may be specified by the header to be initialized with zero data. See *a.out*(5).

An interpreter file begins with a line of the form “*#! interpreter*”. When an interpreter file is *execve*'d, the system *execve*'s the specified *interpreter*, giving it the name of the originally *exec*'d file as an argument and shifting over the rest of the original arguments.

There can be no return from a successful *execve* because the calling core image is lost. This is the mechanism whereby different process images become active.

The argument *argv* is a null-terminated array of character pointers to null-terminated character strings. These strings constitute the argument list to be made available to the new process. By convention, at least one argument must be present in this array, and the first element of this array should be the name of the executed program (i.e., the last component of *name*).

The argument *envp* is also a null-terminated array of character pointers to null-terminated strings. These strings pass information to the new process that is not directly an argument to the command (see *environ*(7)).

Descriptors open in the calling process remain open in the new process, except for those for which the close-on-exec flag is set (see *close*(2)). Descriptors that remain open are unaffected by *execve*.

Ignored signals remain ignored across an *execve*, but signals that are caught are reset to their default values. Blocked signals remain blocked regardless of changes to the signal action. The signal stack is reset to be undefined (see *sigvec*(2) for more information).

Each process has *real* user and group IDs and an *effective* user and group IDs. The *real* ID identifies the person using the system; the *effective* ID determines his access privileges. *Execve* changes the effective user and group ID to the owner of the executed file if the file has the “set-user-ID” or “set-group-ID” modes. The *real* user ID is not affected.

The new process also inherits the following attributes from the calling process:

process ID	see <i>getpid</i> (2)
parent process ID	see <i>getppid</i> (2)
process group ID	see <i>getpgrp</i> (2)
access groups	see <i>getgroups</i> (2)
working directory	see <i>chdir</i> (2)
root directory	see <i>chroot</i> (2)
control terminal	see <i>tty</i> (4)
resource usages	see <i>getrusage</i> (2)
interval timers	see <i>getitimer</i> (2)
resource limits	see <i>getrlimit</i> (2)
file mode mask	see <i>umask</i> (2)
signal mask	see <i>sigvec</i> (2), <i>sigmask</i> (2)

When the executed program begins, it is called as follows:

```
main(argc, argv, envp)
int argc;
char **argv, **envp;
```

where *argc* is the number of elements in *argv* (the "arg count") and *argv* is the array of character pointers to the arguments themselves.

Envp is a pointer to an array of strings that constitute the *environment* of the process. A pointer to this array is also stored in the global variable "environ". Each string consists of a name, an "=", and a null-terminated value. The array of pointers is terminated by a null pointer. The shell *sh*(1) passes an environment entry for each global shell variable defined when the program is called. See *environ*(7) for some conventionally used names.

RETURN VALUE

If *execve* returns to the calling process an error has occurred; the return value will be -1 and the global variable *errno* will contain an error code.

ERRORS

Execve will fail and return to the calling process if one or more of the following are true:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] The new process file does not exist.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EACCES] Search permission is denied for a component of the path prefix.
- [EACCES] The new process file is not an ordinary file.
- [EACCES] The new process file mode denies execute permission.
- [ENOEXEC] The new process file has the appropriate access permission, but has an invalid magic number in its header.
- [ETXTBSY] The new process file is a pure procedure (shared text) file that is currently open for writing or reading by some process.
- [ENOMEM] The new process requires more virtual memory than is allowed by the imposed maximum (*getrlimit*(2)).
- [E2BIG] The number of bytes in the new process's argument list is larger than the system-imposed limit. The limit in the system as released is 20480 bytes (NCARGS in *<sys/param.h>*).
- [EFAULT] The new process file is not as long as indicated by the size values in its header.
- [EFAULT] *Path*, *argv*, or *envp* point to an illegal address.
- [EIO] An I/O error occurred while reading from the file system.

CAVEATS

If a program is *setuid* to a non-super-user, but is executed when the real *uid* is "root", then the program has some of the powers of a super-user as well.

SEE ALSO

exit(2), *fork*(2), *execl*(3), *environ*(7)

NAME

_exit – terminate a process

SYNOPSIS

_exit(status)
int status;

DESCRIPTION

_exit terminates a process with the following consequences:

All of the descriptors open in the calling process are closed. This may entail delays, for example, waiting for output to drain; a process in this state may not be killed, as it is already dying.

If the parent process of the calling process is executing a *wait* or is interested in the SIGCHLD signal, then it is notified of the calling process's termination and the low-order eight bits of *status* are made available to it; see *wait(2)*.

The parent process ID of all of the calling process's existing child processes are also set to 1. This means that the initialization process (see *intro(2)*) inherits each of these processes as well. Any stopped children are restarted with a hangup signal (SIGHUP).

Most C programs call the library routine *exit(3)*, which performs cleanup actions in the standard I/O library before calling **_exit**.

RETURN VALUE

This call never returns.

SEE ALSO

fork(2), *sigvec(2)*, *wait(2)*, *exit(3)*

NAME

fcntl – file control

SYNOPSIS

#include <fcntl.h>

res = fcntl(fd, cmd, arg)

int res;

int fd, cmd, arg;

DESCRIPTION

Fcntl provides for control over descriptors. The argument *fd* is a descriptor to be operated on by *cmd* as follows:

- F_DUPFD** Return a new descriptor as follows:
- Lowest numbered available descriptor greater than or equal to *arg*.
 - Same object references as the original descriptor.
 - New descriptor shares the same file pointer if the object was a file.
 - Same access mode (read, write or read/write).
 - Same file status flags (i.e., both file descriptors share the same file status flags).
 - The close-on-exec flag associated with the new file descriptor is set to remain open across *execv*(2) system calls.
- F_GETFD** Get the close-on-exec flag associated with the file descriptor *fd*. If the low-order bit is 0, the file will remain open across *exec*, otherwise the file will be closed upon execution of *exec*.
- F_SETFD** Set the close-on-exec flag associated with *fd* to the low order bit of *arg* (0 or 1 as above).
- F_GETFL** Get descriptor status flags, as described below.
- F_SETFL** Set descriptor status flags.
- F_GETOWN** Get the process ID or process group currently receiving SIGIO and SIGURG signals; process groups are returned as negative values.
- F_SETOWN** Set the process or process group to receive SIGIO and SIGURG signals; process groups are specified by supplying *arg* as negative, otherwise *arg* is interpreted as a process ID.

The flags for the F_GETFL and F_SETFL flags are as follows:

- FNDELAY** Non-blocking I/O; if no data is available to a *read* call, or if a write operation would block, the call returns -1 with the error EWOULDBLOCK.
- FAPPEND** Force each write to append at the end of file; corresponds to the O_APPEND flag of *open*(2).
- FASYNC** Enable the SIGIO signal to be sent to the process group when I/O is possible, e.g., upon availability of data to be read.

RETURN VALUE

Upon successful completion, the value returned depends on *cmd* as follows:

- F_DUPFD** A new file descriptor.
- F_GETFD** Value of flag (only the low-order bit is defined).
- F_GETFL** Value of flags.
- F_GETOWN** Value of file descriptor owner.
- other** Value other than -1.

Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Fcntl will fail if one or more of the following are true:

- [EBADF] *Fildes* is not a valid open file descriptor.
- [EMFILE] *Cmd* is F_DUPFD and the maximum allowed number of file descriptors are currently open.
- [EINVAL] *Cmd* is F_DUPFD and *arg* is negative or greater than the maximum allowable number (see *getdtablesize(2)*).
- [ESRCH] *Cmd* is F_SETOWN and the process ID given as argument is not in use.

SEE ALSO

close(2), *execve(2)*, *getdtablesize(2)*, *open(2)*, *sigvec(2)*

BUGS

The asynchronous I/O facilities of FNDELAY and FASYNC are currently available only for tty and socket operations.

NAME

flock – apply or remove an advisory lock on an open file

SYNOPSIS

```
#include <sys/file.h>

#define LOCK_SH  1    /* shared lock */
#define LOCK_EX  2    /* exclusive lock */
#define LOCK_NB  4    /* don't block when locking */
#define LOCK_UN  8    /* unlock */

flock(fd, operation)
int fd, operation;
```

DESCRIPTION

Flock applies or removes an *advisory* lock on the file associated with the file descriptor *fd*. A lock is applied by specifying an *operation* parameter that is the inclusive or of **LOCK_SH** or **LOCK_EX** and, possibly, **LOCK_NB**. To unlock an existing lock *operation* should be **LOCK_UN**.

Advisory locks allow cooperating processes to perform consistent operations on files, but do not guarantee consistency (i.e., processes may still access files without using advisory locks possibly resulting in inconsistencies).

The locking mechanism allows two types of locks: *shared* locks and *exclusive* locks. At any time multiple shared locks may be applied to a file, but at no time are multiple exclusive, or both shared and exclusive, locks allowed simultaneously on a file.

A shared lock may be *upgraded* to an exclusive lock, and vice versa, simply by specifying the appropriate lock type; this results in the previous lock being released and the new lock applied (possibly after other processes have gained and released the lock).

Requesting a lock on an object that is already locked normally causes the caller to be blocked until the lock may be acquired. If **LOCK_NB** is included in *operation*, then this will not happen; instead the call will fail and the error **EWOLDBLOCK** will be returned.

NOTES

Locks are on files, not file descriptors. That is, file descriptors duplicated through *dup(2)* or *fork(2)* do not result in multiple instances of a lock, but rather multiple references to a single lock. If a process holding a lock on a file forks and the child explicitly unlocks the file, the parent will lose its lock.

Processes blocked awaiting a lock may be awakened by signals.

RETURN VALUE

Zero is returned if the operation was successful; on an error a **-1** is returned and an error code is left in the global location *errno*.

ERRORS

The *flock* call fails if:

- [EWOLDBLOCK]** The file is locked and the **LOCK_NB** option was specified.
- [EBADF]** The argument *fd* is an invalid descriptor.
- [EINVAL]** The argument *fd* refers to an object other than a file.

SEE ALSO

open(2), *close(2)*, *dup(2)*, *execve(2)*, *fork(2)*

NAME

fork – create a new process

SYNOPSIS

```
pid = fork()
int pid;
```

DESCRIPTION

Fork causes creation of a new process. The new process (child process) is an exact copy of the calling process except for the following:

The child process has a unique process ID.

The child process has a different parent process ID (i.e., the process ID of the parent process).

The child process has its own copy of the parent's descriptors. These descriptors reference the same underlying objects, so that, for instance, file pointers in file objects are shared between the child and the parent, so that an *lseek(2)* on a descriptor in the child process can affect a subsequent *read* or *write* by the parent. This descriptor copying is also used by the shell to establish standard input and output for newly created processes as well as to set up pipes.

The child processes resource utilizations are set to 0; see *setrlimit(2)*.

RETURN VALUE

Upon successful completion, *fork* returns a value of 0 to the child process and returns the process ID of the child process to the parent process. Otherwise, a value of -1 is returned to the parent process, no child process is created, and the global variable *errno* is set to indicate the error.

ERRORS

Fork will fail and no child process will be created if one or more of the following are true:

- [EAGAIN] The system-imposed limit on the total number of processes under execution would be exceeded. This limit is configuration-dependent.
- [EAGAIN] The system-imposed limit MAXUPRC (<*sys/param.h*>) on the total number of processes under execution by a single user would be exceeded.
- [ENOMEM] There is insufficient swap space for the new process.

SEE ALSO

execve(2), *wait(2)*

NAME

fsync – synchronize a file's in-core state with that on disk

SYNOPSIS

fsync(*fd*)
int *fd*;

DESCRIPTION

Fsync causes all modified data and attributes of *fd* to be moved to a permanent storage device. This normally results in all in-core modified copies of buffers for the associated file to be written to a disk.

Fsync should be used by programs that require a file to be in a known state, for example, in building a simple transaction facility.

RETURN VALUE

A 0 value is returned on success. A -1 value indicates an error.

ERRORS

The *fsync* fails if:

- [EBADF] *Fd* is not a valid descriptor.
- [EINVAL] *Fd* refers to a socket, not to a file.
- [EIO] An I/O error occurred while reading from or writing to the file system.

SEE ALSO

sync(2), *sync*(8), *update*(8)

NAME

`getdtablesize` – get descriptor table size

SYNOPSIS

```
nfds = getdtablesize()
int nfds;
```

DESCRIPTION

Each process has a fixed size descriptor table, which is guaranteed to have at least 20 slots. The entries in the descriptor table are numbered with small integers starting at 0. The call `getdtablesize` returns the size of this table.

SEE ALSO

`close(2)`, `dup(2)`, `open(2)`, `select(2)`

NAME

getgid, getegid - get group identity

SYNOPSIS

```
#include <sys/types.h>
```

```
gid = getgid()
```

```
gid_t gid;
```

```
egid = getegid()
```

```
gid_t egid;
```

DESCRIPTION

Getgid returns the real group ID of the current process, *getegid* the effective group ID.

The real group ID is specified at login time.

The effective group ID is more transient, and determines additional access permission during execution of a "set-group-ID" process, and it is for such processes that *getgid* is most useful.

SEE ALSO

getuid(2), setregid(2), setgid(3)

NAME

getgroups – get group access list

SYNOPSIS

```
#include <sys/param.h>
```

```
ngroups = getgroups(gidsetlen, gidset)  
int ngroups, gidsetlen, *gidset;
```

DESCRIPTION

Getgroups gets the current group access list of the user process and stores it in the array *gidset*. The parameter *gidsetlen* indicates the number of entries that may be placed in *gidset*. *Getgroups* returns the actual number of groups returned in *gidset*. No more than NGROUPS, as defined in *<sys/param.h>*, will ever be returned.

RETURN VALUE

A successful call returns the number of groups in the group set. A value of -1 indicates that an error occurred, and the error code is stored in the global variable *errno*.

ERRORS

The possible errors for *getgroup* are:

- | | |
|----------|--|
| [EINVAL] | The argument <i>gidsetlen</i> is smaller than the number of groups in the group set. |
| [EFAULT] | The argument <i>gidset</i> specifies an invalid address. |

SEE ALSO

setgroups(2), initgroups(3X)

BUGS

The *gidset* array should be of type *gid_t*, but remains integer for compatibility with earlier systems.

NAME

gethostid, sethostid – get/set unique identifier of current host

SYNOPSIS

```
hostid = gethostid()
long hostid;

sethostid(hostid)
long hostid;
```

DESCRIPTION

Sethostid establishes a 32-bit identifier for the current processor that is intended to be unique among all UNIX systems in existence. This is normally a DARPA Internet address for the local machine. This call is allowed only to the super-user and is normally performed at boot time.

Gethostid returns the 32-bit identifier for the current processor.

SEE ALSO

hostid(1), gethostname(2)

BUGS

32 bits for the identifier is too small.

NAME

gethostname, sethostname – get/set name of current host

SYNOPSIS

```
gethostname(name, namelen)
char *name;
int namelen;

sethostname(name, namelen)
char *name;
int namelen;
```

DESCRIPTION

Gethostname returns the standard host name for the current processor, as previously set by *sethostname*. The parameter *namelen* specifies the size of the *name* array. The returned name is null-terminated unless insufficient space is provided.

Sethostname sets the name of the host machine to be *name*, which has length *namelen*. This call is restricted to the super-user and is normally used only when the system is bootstrapped.

RETURN VALUE

If the call succeeds a value of 0 is returned. If the call fails, then a value of -1 is returned and an error code is placed in the global location *errno*.

ERRORS

The following errors may be returned by these calls:

- | | |
|----------|--|
| [EFAULT] | The <i>name</i> or <i>namelen</i> parameter gave an invalid address. |
| [EPERM] | The caller tried to set the hostname and was not the super-user. |

SEE ALSO

gethostid(2)

BUGS

Host names are limited to MAXHOSTNAMELEN (from *<sys/param.h>*) characters, currently 64.

NAME

getitimer, setitimer – get/set value of interval timer

SYNOPSIS

```
#include <sys/time.h>

#define ITIMER_REAL    0    /* real time intervals */
#define ITIMER_VIRTUAL 1    /* virtual time intervals */
#define ITIMER_PROF    2    /* user and system virtual time */
```

```
getitimer(which, value)
int which;
struct itimerval *value;

setitimer(which, value, ovalue)
int which;
struct itimerval *value, *ovalue;
```

DESCRIPTION

The system provides each process with three interval timers, defined in *<sys/time.h>*. The *getitimer* call returns the current value for the timer specified in *which* in the structure at *value*. The *setitimer* call sets a timer to the specified *value* (returning the previous value of the timer if *ovalue* is non-zero).

A timer value is defined by the *itimerval* structure:

```
struct itimerval {
    struct timeval it_interval; /* timer interval */
    struct timeval it_value;    /* current value */
};
```

If *it_value* is non-zero, it indicates the time to the next timer expiration. If *it_interval* is non-zero, it specifies a value to be used in reloading *it_value* when the timer expires. Setting *it_value* to 0 disables a timer. Setting *it_interval* to 0 causes a timer to be disabled after its next expiration (assuming *it_value* is non-zero).

Time values smaller than the resolution of the system clock are rounded up to this resolution (on the VAX, 10 milliseconds).

The ITIMER_REAL timer decrements in real time. A SIGALRM signal is delivered when this timer expires.

The ITIMER_VIRTUAL timer decrements in process virtual time. It runs only when the process is executing. A SIGVTALRM signal is delivered when it expires.

The ITIMER_PROF timer decrements both in process virtual time and when the system is running on behalf of the process. It is designed to be used by interpreters in statistically profiling the execution of interpreted programs. Each time the ITIMER_PROF timer expires, the SIGPROF signal is delivered. Because this signal may interrupt in-progress system calls, programs using this timer must be prepared to restart interrupted system calls.

NOTES

Three macros for manipulating time values are defined in *<sys/time.h>*. *Timerclear* sets a time value to zero, *timerisset* tests if a time value is non-zero, and *timercmp* compares two time values (beware that *>=* and *<=* do not work with this macro).

RETURN VALUE

If the calls succeed, a value of 0 is returned. If an error occurs, the value -1 is returned, and a more precise error code is placed in the global variable *errno*.

ERRORS

The possible errors are:

- [EFAULT] The *value* parameter specified a bad address.
[EINVAL] A *value* parameter specified a time was too large to be handled.

SEE ALSO

sigvec(2), gettimeofday(2)

NAME

getpagesize – get system page size

SYNOPSIS

```
pagesize = getpagesize()
int pagesize;
```

DESCRIPTION

Getpagesize returns the number of bytes in a page. Page granularity is the granularity of many of the memory management calls.

The page size is a *system* page size and may not be the same as the underlying hardware page size.

SEE ALSO

sbrk(2), pagesize(1)

NAME

getpeername – get name of connected peer

SYNOPSIS

```
getpeername(s, name, namelen)
int s;
struct sockaddr *name;
int *namelen;
```

DESCRIPTION

Getpeername returns the name of the peer connected to socket *s*. The *namelen* parameter should be initialized to indicate the amount of space pointed to by *name*. On return it contains the actual size of the name returned (in bytes). The name is truncated if the buffer provided is too small.

DIAGNOSTICS

A 0 is returned if the call succeeds, -1 if it fails.

ERRORS

The call succeeds unless:

- [EBADF] The argument *s* is not a valid descriptor.
- [ENOTSOCK] The argument *s* is a file, not a socket.
- [ENOTCONN] The socket is not connected.
- [ENOBUFS] Insufficient resources were available in the system to perform the operation.
- [EFAULT] The *name* parameter points to memory not in a valid part of the process address space.

SEE ALSO

accept(2), bind(2), socket(2), getsockname(2)

NAME

getpgrp – get process group

SYNOPSIS

```
pgrp = getpgrp(pid)
int pgrp;
int pid;
```

DESCRIPTION

The process group of the specified process is returned by *getpgrp*. If *pid* is zero, then the call applies to the current process.

Process groups are used for distribution of signals, and by terminals to arbitrate requests for their input: processes that have the same process group as the terminal are foreground and may read, while others will block with a signal if they attempt to read.

This call is thus used by programs such as *cs(1)* to create process groups in implementing job control. The *TIOCGPGRP* and *TIOCSPGRP* calls described in *tty(4)* are used to get/set the process group of the control terminal.

SEE ALSO

setpgrp(2), *getuid(2)*, *tty(4)*

NAME

getpid, getppid – get process identification

SYNOPSIS

```
pid = getpid()
int pid;
```

```
ppid = getppid()
int ppid;
```

DESCRIPTION

Getpid returns the process ID of the current process. Most often it is used to generate uniquely-named temporary files.

Getppid returns the process ID of the parent of the current process.

SEE ALSO

gethostid(2)

NAME

getpriority, setpriority – get/set program scheduling priority

SYNOPSIS

```
#include <sys/resource.h>

prio = getpriority(which, who)
int prio, which, who;

setpriority(which, who, prio)
int which, who, prio;
```

DESCRIPTION

The scheduling priority of the process, process group, or user, as indicated by *which* and *who* is obtained with the *getpriority* call and set with the *setpriority* call. *Which* is one of PRIO_PROCESS, PRIO_PGRP, or PRIO_USER, and *who* is interpreted relative to *which* (a process identifier for PRIO_PROCESS, process group identifier for PRIO_PGRP, and a user ID for PRIO_USER). A zero value of *who* denotes the current process, process group, or user. *Prio* is a value in the range -20 to 20. The default priority is 0; lower priorities cause more favorable scheduling.

The *getpriority* call returns the highest priority (lowest numerical value) enjoyed by any of the specified processes. The *setpriority* call sets the priorities of all of the specified processes to the specified value. Only the super-user may lower priorities.

RETURN VALUE

Since *getpriority* can legitimately return the value -1, it is necessary to clear the external variable *errno* prior to the call, then check it afterward to determine if a -1 is an error or a legitimate value. The *setpriority* call returns 0 if there is no error, or -1 if there is.

ERRORS

Getpriority and *setpriority* may return one of the following errors:

- [ESRCH] No process was located using the *which* and *who* values specified.
- [EINVAL] *Which* was not one of PRIO_PROCESS, PRIO_PGRP, or PRIO_USER.

In addition to the errors indicated above, *setpriority* may fail with one of the following errors returned:

- [EPERM] A process was located, but neither its effective nor real user ID matched the effective user ID of the caller.
- [EACCES] A non super-user attempted to lower a process priority.

SEE ALSO

nice(1), fork(2), renice(8)

NAME

getrlimit, setrlimit – control maximum system resource consumption

SYNOPSIS

```
#include <sys/time.h>
#include <sys/resource.h>

getrlimit(resource, rlp)
int resource;
struct rlimit *rlp;

setrlimit(resource, rlp)
int resource;
struct rlimit *rlp;
```

DESCRIPTION

Limits on the consumption of system resources by the current process and each process it creates may be obtained with the *getrlimit* call, and set with the *setrlimit* call.

The *resource* parameter is one of the following:

RLIMIT_CPU the maximum amount of cpu time (in seconds) to be used by each process.

RLIMIT_FSIZE the largest size, in bytes, of any single file that may be created.

RLIMIT_DATA the maximum size, in bytes, of the data segment for a process; this defines how far a program may extend its break with the *sbrk(2)* system call.

RLIMIT_STACK the maximum size, in bytes, of the stack segment for a process; this defines how far a program's stack segment may be extended. Stack extension is performed automatically by the system.

RLIMIT_CORE the largest size, in bytes, of a *core* file that may be created.

RLIMIT_RSS the maximum size, in bytes, to which a process's resident set size may grow. This imposes a limit on the amount of physical memory to be given to a process; if memory is tight, the system will prefer to take memory from processes that are exceeding their declared resident set size.

A resource limit is specified as a soft limit and a hard limit. When a soft limit is exceeded a process may receive a signal (for example, if the cpu time is exceeded), but it will be allowed to continue execution until it reaches the hard limit (or modifies its resource limit). The *rlimit* structure is used to specify the hard and soft limits on a resource,

```
struct rlimit {
    int    rlim_cur;    /* current (soft) limit */
    int    rlim_max;    /* hard limit */
};
```

Only the super-user may raise the maximum limits. Other users may only alter *rlim_cur* within the range from 0 to *rlim_max* or (irreversibly) lower *rlim_max*.

An "infinite" value for a limit is defined as **RLIM_INFINITY** (0x7fffffff).

Because this information is stored in the per-process information, this system call must be executed directly by the shell if it is to affect all future processes created by the shell; *limit* is thus a built-in command to *csh(1)*.

The system refuses to extend the data or stack space when the limits would be exceeded in the normal way: a *break* call fails if the data space limit is reached. When the stack limit is reached, the process receives a segmentation fault (SIGSEGV); if this signal is not caught by a handler using the signal stack, this signal will kill the process.

A file I/O operation that would create a file that is too large will cause a signal SIGXFSZ to be generated; this normally terminates the process, but may be caught. When the soft cpu time limit is exceeded, a signal SIGXCPU is sent to the offending process.

RETURN VALUE

A 0 return value indicates that the call succeeded, changing or returning the resource limit. A return value of -1 indicates that an error occurred, and an error code is stored in the global location *errno*.

ERRORS

The possible errors are:

- [EFAULT] The address specified for *rlp* is invalid.
- [EPERM] The limit specified to *setrlimit* would have raised the maximum limit value, and the caller is not the super-user.

SEE ALSO

csh(1), *quota*(2), *sigvec*(2), *sigstack*(2)

BUGS

There should be *limit* and *unlimit* commands in *sh*(1) as well as in *csh*.

NAME

getrusage – get information about resource utilization

SYNOPSIS

```
#include <sys/time.h>
#include <sys/resource.h>

#define RUSAGE_SELF      0      /* calling process */
#define RUSAGE_CHILDREN -1      /* terminated child processes */

getrusage(who, rusage)
int who;
struct rusage *rusage;
```

DESCRIPTION

Getrusage returns information describing the resources utilized by the current process, or all its terminated child processes. The *who* parameter is one of *RUSAGE_SELF* or *RUSAGE_CHILDREN*. The buffer to which *rusage* points will be filled in with the following structure:

```
struct rusage {
    struct timeval ru_utime; /* user time used */
    struct timeval ru_stime; /* system time used */
    int ru_maxrss;
    int ru_ixrss; /* integral shared text memory size */
    int ru_idrss; /* integral unshared data size */
    int ru_isrss; /* integral unshared stack size */
    int ru_minflt; /* page reclaims */
    int ru_majflt; /* page faults */
    int ru_nswap; /* swaps */
    int ru_inblock; /* block input operations */
    int ru_oublock; /* block output operations */
    int ru_msgsnd; /* messages sent */
    int ru_msgrcv; /* messages received */
    int ru_nsignals; /* signals received */
    int ru_nvcsw; /* voluntary context switches */
    int ru_nivcsw; /* involuntary context switches */
};
```

The fields are interpreted as follows:

ru_utime	the total amount of time spent executing in user mode.
ru_stime	the total amount of time spent in the system executing on behalf of the process(es).
ru_maxrss	the maximum resident set size utilized (in kilobytes).
ru_ixrss	an “integral” value indicating the amount of memory used by the text segment that was also shared among other processes. This value is expressed in units of kilobytes * seconds-of-execution and is calculated by summing the number of shared memory pages in use each time the internal system clock ticks and then averaging over 1 second intervals.
ru_idrss	an integral value of the amount of unshared memory residing in the data segment of a process (expressed in units of kilobytes * seconds-of-execution).
ru_isrss	an integral value of the amount of unshared memory residing in the stack segment of a process (expressed in units of kilobytes * seconds-of-execution).

<code>ru_minflt</code>	the number of page faults serviced without any I/O activity; here I/O activity is avoided by "reclaiming" a page frame from the list of pages awaiting reallocation.
<code>ru_majflt</code>	the number of page faults serviced that required I/O activity.
<code>ru_nswap</code>	the number of times a process was "swapped" out of main memory.
<code>ru_inblock</code>	the number of times the file system had to perform input.
<code>ru_outblock</code>	the number of times the file system had to perform output.
<code>ru_msgsnd</code>	the number of IPC messages sent.
<code>ru_msgrcv</code>	the number of IPC messages received.
<code>ru_nsignals</code>	the number of signals delivered.
<code>ru_nvcsw</code>	the number of times a context switch resulted due to a process voluntarily giving up the processor before its time slice was completed (usually to await availability of a resource).
<code>ru_nivcsw</code>	the number of times a context switch resulted due to a higher priority process becoming runnable or because the current process exceeded its time slice.

NOTES

The numbers `ru_inblock` and `ru_outblock` account only for real I/O; data supplied by the caching mechanism is charged only to the first process to read or write the data.

ERRORS

The possible errors for *getrusage* are:

[EINVAL]	The <i>who</i> parameter is not a valid value.
[EFAULT]	The address specified by the <i>usage</i> parameter is not in a valid part of the process address space.

SEE ALSO

`gettimeofday(2)`, `wait(2)`

BUGS

There is no way to obtain information about a child process that has not yet terminated.

NAME

getsockname – get socket name

SYNOPSIS

```
getsockname(s, name, namelen)
int s;
struct sockaddr *name;
int *namelen;
```

DESCRIPTION

Getsockname returns the current *name* for the specified socket. The *namelen* parameter should be initialized to indicate the amount of space pointed to by *name*. On return it contains the actual size of the name returned (in bytes).

DIAGNOSTICS

A 0 is returned if the call succeeds, -1 if it fails.

ERRORS

The call succeeds unless:

- [EBADF] The argument *s* is not a valid descriptor.
- [ENOTSOCK] The argument *s* is a file, not a socket.
- [ENOBUFS] Insufficient resources were available in the system to perform the operation.
- [EFAULT] The *name* parameter points to memory not in a valid part of the process address space.

SEE ALSO

bind(2), socket(2)

BUGS

Names bound to sockets in the UNIX domain are inaccessible; *getsockname* returns a zero length name.

NAME

getsockopt, setsockopt – get and set options on sockets

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>
```

```
getsockopt(s, level, optname, optval, optlen)
int s, level, optname;
char *optval;
int *optlen;
```

```
setsockopt(s, level, optname, optval, optlen)
int s, level, optname;
char *optval;
int optlen;
```

DESCRIPTION

Getsockopt and *setsockopt* manipulate *options* associated with a socket. Options may exist at multiple protocol levels; they are always present at the uppermost “socket” level.

When manipulating socket options the level at which the option resides and the name of the option must be specified. To manipulate options at the “socket” level, *level* is specified as `SOL_SOCKET`. To manipulate options at any other level the protocol number of the appropriate protocol controlling the option is supplied. For example, to indicate that an option is to be interpreted by the TCP protocol, *level* should be set to the protocol number of TCP; see *getprotoent*(3N).

The parameters *optval* and *optlen* are used to access option values for *setsockopt*. For *getsockopt* they identify a buffer in which the value for the requested option(s) are to be returned. For *getsockopt*, *optlen* is a value-result parameter, initially containing the size of the buffer pointed to by *optval*, and modified on return to indicate the actual size of the value returned. If no option value is to be supplied or returned, *optval* may be supplied as 0.

Optname and any specified options are passed uninterpreted to the appropriate protocol module for interpretation. The include file `<sys/socket.h>` contains definitions for “socket” level options, described below. Options at other protocol levels vary in format and name; consult the appropriate entries in section (4P).

Most socket-level options take an *int* parameter for *optval*. For *setsockopt*, the parameter should non-zero to enable a boolean option, or zero if the option is to be disabled. `SO_LINGER` uses a *struct linger* parameter, defined in `<sys/socket.h>`, which specifies the desired state of the option and the linger interval (see below).

The following options are recognized at the socket level. Except as noted, each may be examined with *getsockopt* and set with *setsockopt*.

<code>SO_DEBUG</code>	toggle recording of debugging information
<code>SO_REUSEADDR</code>	toggle local address reuse
<code>SO_KEEPAIVE</code>	toggle keep connections alive
<code>SO_DONTROUTE</code>	toggle routing bypass for outgoing messages
<code>SO_LINGER</code>	linger on close if data present
<code>SO_BROADCAST</code>	toggle permission to transmit broadcast messages
<code>SO_OOBINLINE</code>	toggle reception of out-of-band data in band
<code>SO_SNDBUF</code>	set buffer size for output
<code>SO_RCVBUF</code>	set buffer size for input
<code>SO_TYPE</code>	get the type of the socket (get only)
<code>SO_ERROR</code>	get and clear error on the socket (get only)

SO_DEBUG enables debugging in the underlying protocol modules. SO_REUSEADDR indicates that the rules used in validating addresses supplied in a *bind(2)* call should allow reuse of local addresses. SO_KEEPALIVE enables the periodic transmission of messages on a connected socket. Should the connected party fail to respond to these messages, the connection is considered broken and processes using the socket are notified via a SIGPIPE signal. SO_DONTROUTE indicates that outgoing messages should bypass the standard routing facilities. Instead, messages are directed to the appropriate network interface according to the network portion of the destination address.

SO_LINGER controls the action taken when unsent messages are queued on socket and a *close(2)* is performed. If the socket promises reliable delivery of data and SO_LINGER is set, the system will block the process on the *close* attempt until it is able to transmit the data or until it decides it is unable to deliver the information (a timeout period, termed the linger interval, is specified in the *setsockopt* call when SO_LINGER is requested). If SO_LINGER is disabled and a *close* is issued, the system will process the close in a manner that allows the process to continue as quickly as possible.

The option SO_BROADCAST requests permission to send broadcast datagrams on the socket. Broadcast was a privileged operation in earlier versions of the system. With protocols that support out-of-band data, the SO_OOBINLINE option requests that out-of-band data be placed in the normal data input queue as received; it will then be accessible with *recv* or *read* calls without the MSG_OOB flag. SO_SNDBUF and SO_RCVBUF are options to adjust the normal buffer sizes allocated for output and input buffers, respectively. The buffer size may be increased for high-volume connections, or may be decreased to limit the possible backlog of incoming data. The system places an absolute limit on these values. Finally, SO_TYPE and SO_ERROR are options used only with *setsockopt*. SO_TYPE returns the type of the socket, such as SOCK_STREAM; it is useful for servers that inherit sockets on startup. SO_ERROR returns any pending error on the socket and clears the error status. It may be used to check for asynchronous errors on connected datagram sockets or for other asynchronous errors.

RETURN VALUE

A 0 is returned if the call succeeds, -1 if it fails.

ERRORS

The call succeeds unless:

- | | |
|---------------|--|
| [EBADF] | The argument <i>s</i> is not a valid descriptor. |
| [ENOTSOCK] | The argument <i>s</i> is a file, not a socket. |
| [ENOPROTOOPT] | The option is unknown at the level indicated. |
| [EFAULT] | The address pointed to by <i>optval</i> is not in a valid part of the process address space. For <i>getsockopt</i> , this error may also be returned if <i>optlen</i> is not in a valid part of the process address space. |

SEE ALSO

ioctl(2), socket(2), getprotoent(3N)

BUGS

Several of the socket options should be handled at lower levels of the system.

NAME

gettimeofday, settimeofday – get/set date and time

SYNOPSIS

#include <sys/time.h>

gettimeofday(tp, tzp)

struct timeval *tp;

struct timezone *tzp;

settimeofday(tp, tzp)

struct timeval *tp;

struct timezone *tzp;

DESCRIPTION

The system's notion of the current Greenwich time and the current time zone is obtained with the *gettimeofday* call, and set with the *settimeofday* call. The time is expressed in seconds and microseconds since midnight (0 hour), January 1, 1970. The resolution of the system clock is hardware dependent, and the time may be updated continuously or in "ticks." If *tzp* is zero, the time zone information will not be returned or set.

The structures pointed to by *tp* and *tzp* are defined in <sys/time.h> as:

```
struct timeval {
    long    tv_sec;        /* seconds since Jan. 1, 1970 */
    long    tv_usec;      /* and microseconds */
};

struct timezone {
    int     tz_minuteswest; /* of Greenwich */
    int     tz_dsttime;     /* type of dst correction to apply */
};
```

The *timezone* structure indicates the local time zone (measured in minutes of time westward from Greenwich), and a flag that, if nonzero, indicates that Daylight Saving time applies locally during the appropriate part of the year.

Only the super-user may set the time of day or time zone.

RETURN

A 0 return value indicates that the call succeeded. A -1 return value indicates an error occurred, and in this case an error code is stored into the global variable *errno*.

ERRORS

The following error codes may be set in *errno*:

[EFAULT] An argument address referenced invalid memory.

[EPERM] A user other than the super-user attempted to set the time.

SEE ALSO

date(1), adjtime(2), ctime(3), timed(8)

NAME

getuid, geteuid – get user identity

SYNOPSIS

```
#include <sys/types.h>
```

```
uid = getuid()
```

```
uid_t uid;
```

```
euid = geteuid()
```

```
uid_t euid;
```

DESCRIPTION

Getuid returns the real user ID of the current process, *geteuid* the effective user ID.

The real user ID identifies the person who is logged in. The effective user ID gives the process additional permissions during execution of “set-user-ID” mode processes, which use *getuid* to determine the real-user-id of the process that invoked them.

SEE ALSO

getgid(2), *setreuid(2)*

NAME
 ioctl – control device

SYNOPSIS
 #include <sys/ioctl.h>
 ioctl(*d*, *request*, *argp*)
 int *d*;
 unsigned long *request*;
 char **argp*;

DESCRIPTION

ioctl performs a variety of functions on open descriptors. In particular, many operating characteristics of character special files (e.g. terminals) may be controlled with *ioctl* requests. The writeups of various devices in section 4 discuss how *ioctl* applies to them.

An *ioctl request* has encoded in it whether the argument is an “in” parameter or “out” parameter, and the size of the argument *argp* in bytes. Macros and defines used in specifying an *ioctl request* are located in the file <sys/ioctl.h>.

RETURN VALUE

If an error has occurred, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

ioctl will fail if one or more of the following are true:

- | | |
|----------|---|
| [EBADF] | <i>D</i> is not a valid descriptor. |
| [ENOTTY] | <i>D</i> is not associated with a character special device. |
| [ENOTTY] | The specified request does not apply to the kind of object that the descriptor <i>d</i> references. |
| [EINVAL] | <i>Request</i> or <i>argp</i> is not valid. |

SEE ALSO

execve(2), *fcntl*(2), *mt*(4), *tty*(4), *intro*(4N)

NAME

kill – send signal to a process

SYNOPSIS

```
kill(pid, sig)
int pid, sig;
```

DESCRIPTION

Kill sends the signal *sig* to a process, specified by the process number *pid*. *Sig* may be one of the signals specified in *sigvec*(2), or it may be 0, in which case error checking is performed but no signal is actually sent. This can be used to check the validity of *pid*.

The sending and receiving processes must have the same effective user ID, otherwise this call is restricted to the super-user. A single exception is the signal SIGCONT, which may always be sent to any descendant of the current process.

If the process number is 0, the signal is sent to all processes in the sender's process group; this is a variant of *killpg*(2).

If the process number is -1 and the user is the super-user, the signal is broadcast universally except to system processes and the process sending the signal. If the process number is -1 and the user is not the super-user, the signal is broadcast universally to all processes with the same uid as the user except the process sending the signal. No error is returned if any process could be signaled.

For compatibility with System V, if the process number is negative but not -1, the signal is sent to all processes whose process group ID is equal to the absolute value of the process number. This is a variant of *killpg*(2).

Processes may send signals to themselves.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Kill will fail and no signal will be sent if any of the following occur:

- | | |
|----------|---|
| [EINVAL] | <i>Sig</i> is not a valid signal number. |
| [ESRCH] | No process can be found corresponding to that specified by <i>pid</i> . |
| [ESRCH] | The process id was given as 0 but the sending process does not have a process group. |
| [EPERM] | The sending process is not the super-user and its effective user id does not match the effective user-id of the receiving process. When signaling a process group, this error was returned if any members of the group could not be signaled. |

SEE ALSO

getpid(2), getpgrp(2), killpg(2), sigvec(2)

NAME

killpg – send signal to a process group

SYNOPSIS

killpg(pgrp, sig)
int pgrp, sig;

DESCRIPTION

Killpg sends the signal *sig* to the process group *pgrp*. See *sigvec(2)* for a list of signals.

The sending process and members of the process group must have the same effective user ID, or the sender must be the super-user. As a single special case the continue signal SIGCONT may be sent to any process that is a descendant of the current process.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and the global variable *errno* is set to indicate the error.

ERRORS

Killpg will fail and no signal will be sent if any of the following occur:

- | | |
|----------|--|
| [EINVAL] | <i>Sig</i> is not a valid signal number. |
| [ESRCH] | No process can be found in the process group specified by <i>pgrp</i> . |
| [ESRCH] | The process group was given as 0 but the sending process does not have a process group. |
| [EPERM] | The sending process is not the super-user and one or more of the target processes has an effective user ID different from that of the sending process. |

SEE ALSO

kill(2), *getpgrp(2)*, *sigvec(2)*

NAME

link – make a hard link to a file

SYNOPSIS

```
link(name1, name2)
char *name1, *name2;
```

DESCRIPTION

A hard link to *name1* is created; the link has the name *name2*. *Name1* must exist.

With hard links, both *name1* and *name2* must be in the same file system. Unless the caller is the super-user, *name1* must not be a directory. Both the old and the new *link* share equal access and rights to the underlying object.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Link will fail and no link will be created if one or more of the following are true:

- [ENOTDIR] A component of either path prefix is not a directory.
- [EINVAL] Either pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of either pathname exceeded 255 characters, or entire length of either path name exceeded 1023 characters.
- [ENOENT] A component of either path prefix does not exist.
- [EACCES] A component of either path prefix denies search permission.
- [EACCES] The requested link requires writing in a directory with a mode that denies write permission.
- [ELOOP] Too many symbolic links were encountered in translating one of the pathnames.
- [ENOENT] The file named by *name1* does not exist.
- [EEXIST] The link named by *name2* does exist.
- [EPERM] The file named by *name1* is a directory and the effective user ID is not super-user.
- [EXDEV] The link named by *name2* and the file named by *name1* are on different file systems.
- [ENOSPC] The directory in which the entry for the new link is being placed cannot be extended because there is no space left on the file system containing the directory.
- [EDQUOT] The directory in which the entry for the new link is being placed cannot be extended because the user's quota of disk blocks on the file system containing the directory has been exhausted.
- [EIO] An I/O error occurred while reading from or writing to the file system to make the directory entry.
- [EROFS] The requested link requires writing in a directory on a read-only file system.
- [EFAULT] One of the pathnames specified is outside the process's allocated address space.

SEE ALSO

symlink(2), unlink(2)

NAME

`listen` – listen for connections on a socket

SYNOPSIS

```
listen(s, backlog)
int s, backlog;
```

DESCRIPTION

To accept connections, a socket is first created with `socket(2)`, a willingness to accept incoming connections and a queue limit for incoming connections are specified with `listen(2)`, and then the connections are accepted with `accept(2)`. The `listen` call applies only to sockets of type `SOCK_STREAM` or `SOCK_SEQPACKET`.

The `backlog` parameter defines the maximum length the queue of pending connections may grow to. If a connection request arrives with the queue full the client may receive an error with an indication of `ECONNREFUSED`, or, if the underlying protocol supports retransmission, the request may be ignored so that retries may succeed.

RETURN VALUE

A 0 return value indicates success; -1 indicates an error.

ERRORS

The call fails if:

[EBADF]	The argument <i>s</i> is not a valid descriptor.
[ENOTSOCK]	The argument <i>s</i> is not a socket.
[EOPNOTSUPP]	The socket is not of a type that supports the operation <code>listen</code> .

SEE ALSO

`accept(2)`, `connect(2)`, `socket(2)`

BUGS

The `backlog` is currently limited (silently) to 5.

NAME

lseek – move read/write pointer

SYNOPSIS

```
#include <sys/file.h>
```

```
#define L_SET    0    /* set the seek pointer */  
#define L_INCR  1    /* increment the seek pointer */  
#define L_XTND  2    /* extend the file size */
```

```
pos = lseek(d, offset, whence)  
off_t pos;  
int d;  
off_t offset;  
int whence;
```

DESCRIPTION

The descriptor *d* refers to a file or device open for reading and/or writing. *Lseek* sets the file pointer of *d* as follows:

If *whence* is *L_SET*, the pointer is set to *offset* bytes.

If *whence* is *L_INCR*, the pointer is set to its current location plus *offset*.

If *whence* is *L_XTND*, the pointer is set to the size of the file plus *offset*.

Upon successful completion, the resulting pointer location as measured in bytes from beginning of the file is returned. Some devices are incapable of seeking. The value of the pointer associated with such a device is undefined.

NOTES

Seeking far beyond the end of a file, then writing, creates a gap or “hole”, which occupies no physical space and reads as zeros.

RETURN VALUE

Upon successful completion, the current file pointer value is returned. Otherwise, a value of *-1* is returned and *errno* is set to indicate the error.

ERRORS

Lseek will fail and the file pointer will remain unchanged if:

[EBADF]	<i>Fildes</i> is not an open file descriptor.
[ESPIPE]	<i>Fildes</i> is associated with a pipe or a socket.
[EINVAL]	<i>Whence</i> is not a proper value.

SEE ALSO

dup(2), *open*(2)

BUGS

This document's use of *whence* is incorrect English, but maintained for historical reasons.

NAME

`mkdir` – make a directory file

SYNOPSIS

```
mkdir(path, mode)
char *path;
int mode;
```

DESCRIPTION

Mkdir creates a new directory file with name *path*. The mode of the new file is initialized from *mode*. (The protection part of the mode is modified by the process's mode mask; see *umask(2)*).

The directory's owner ID is set to the process's effective user ID. The directory's group ID is set to that of the parent directory in which it is created.

The low-order 9 bits of mode are modified by the process's file mode creation mask: all bits set in the process's file mode creation mask are cleared. See *umask(2)*.

RETURN VALUE

A 0 return value indicates success. A -1 return value indicates an error, and an error code is stored in *errno*.

ERRORS

Mkdir will fail and no directory will be created if:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] A component of the path prefix does not exist.
- [EACCES] Search permission is denied for a component of the path prefix.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EPERM] The *path* argument contains a byte with the high-order bit set.
- [EROFS] The named file resides on a read-only file system.
- [EEXIST] The named file exists.
- [ENOSPC] The directory in which the entry for the new directory is being placed cannot be extended because there is no space left on the file system containing the directory.
- [ENOSPC] The new directory cannot be created because there is no space left on the file system that will contain the directory.
- [ENOSPC] There are no free inodes on the file system on which the directory is being created.
- [EDQUOT] The directory in which the entry for the new directory is being placed cannot be extended because the user's quota of disk blocks on the file system containing the directory has been exhausted.
- [EDQUOT] The new directory cannot be created because the user's quota of disk blocks on the file system that will contain the directory has been exhausted.
- [EDQUOT] The user's quota of inodes on the file system on which the directory is being created has been exhausted.

- [EIO] An I/O error occurred while making the directory entry or allocating the inode.
- [EIO] An I/O error occurred while reading from or writing to the file system.
- [EFAULT] *Path* points outside the process's allocated address space.

SEE ALSO

chmod(2), stat(2), umask(2)

NAME

mknod – make a special file

SYNOPSIS

```
mknod(path, mode, dev)
char *path;
int mode, dev;
```

DESCRIPTION

Mknod creates a new file whose name is *path*. The mode of the new file (including special file bits) is initialized from *mode*. (The protection part of the mode is modified by the process's mode mask (see *umask(2)*)). The first block pointer of the i-node is initialized from *dev* and is used to specify which device the special file refers to.

If *mode* indicates a block or character special file, *dev* is a configuration dependent specification of a character or block I/O device. If *mode* does not indicate a block special or character special device, *dev* is ignored.

Mknod may be invoked only by the super-user.

RETURN VALUE

Upon successful completion a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Mknod will fail and the file mode will be unchanged if:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] A component of the path prefix does not exist.
- [EACCES] Search permission is denied for a component of the path prefix.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EPERM] The process's effective user ID is not super-user.
- [EPERM] The pathname contains a character with the high-order bit set.
- [EIO] An I/O error occurred while making the directory entry or allocating the inode.
- [ENOSPC] The directory in which the entry for the new node is being placed cannot be extended because there is no space left on the file system containing the directory.
- [ENOSPC] There are no free inodes on the file system on which the node is being created.
- [EDQUOT] The directory in which the entry for the new node is being placed cannot be extended because the user's quota of disk blocks on the file system containing the directory has been exhausted.
- [EDQUOT] The user's quota of inodes on the file system on which the node is being created has been exhausted.
- [EROFS] The named file resides on a read-only file system.
- [EEXIST] The named file exists.

[EFAULT] *Path* points outside the process's allocated address space.

SEE ALSO

chmod(2), stat(2), umask(2)

P
R
M
2

NAME

mount, umount – mount or remove file system

SYNOPSIS

```
mount(special, name, rwflag)
char *special, *name;
int rwflag;

umount(special)
char *special;
```

DESCRIPTION

Mount announces to the system that a removable file system has been mounted on the block-structured special file *special*; from now on, references to file *name* will refer to the root file on the newly mounted file system. *Special* and *name* are pointers to null-terminated strings containing the appropriate path names.

Name must exist already. *Name* must be a directory. Its old contents are inaccessible while the file system is mounted.

The *rwflag* argument determines whether the file system can be written on; if it is 0 writing is allowed, if non-zero no writing is done. Physically write-protected and magnetic tape file systems must be mounted read-only or errors will occur when access times are updated, whether or not any explicit write is attempted.

Umount announces to the system that the *special* file is no longer to contain a removable file system. The associated file reverts to its ordinary interpretation.

RETURN VALUE

Mount returns 0 if the action occurred, -1 if *special* is inaccessible or not an appropriate file, if *name* does not exist, if *special* is already mounted, if *name* is in use, or if there are already too many file systems mounted.

Umount returns 0 if the action occurred; -1 if the special file is inaccessible or does not have a mounted file system, or if there are active files in the mounted file system.

ERRORS

Mount will fail when one of the following occurs:

- | | |
|----------------|---|
| [ENAMETOOLONG] | A component of either pathname exceeded 255 characters, or the entire length of either path name exceeded 1023 characters. |
| [ELOOP] | Too many symbolic links were encountered in translating either pathname. |
| [EPERM] | The caller is not the super-user. |
| [ENOENT] | A component of <i>name</i> does not exist. |
| [ENODEV] | A component of <i>special</i> does not exist. |
| [ENOTBLK] | <i>Special</i> is not a block device. |
| [ENXIO] | The major device number of <i>special</i> is out of range (this indicates no device driver exists for the associated hardware). |
| [ENOTDIR] | A component of <i>name</i> is not a directory, or a path prefix of <i>special</i> is not a directory. |
| [EINVAL] | Either pathname contains a character with the high-order bit set. |
| [EINVAL] | The super block for the file system had a bad magic number or an out of range block size. |

- [EBUSY] Another process currently holds a reference to *name*, or *special* is already mounted.
- [EMFILE] No space remains in the mount table.
- [ENOMEM] Not enough memory was available to read the cylinder group information for the file system.
- [EIO] An I/O error occurred while reading the super block or cylinder group information.
- [EFAULT] *Special* or *name* points outside the process's allocated address space.
Umount may fail with one of the following errors:
- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EPERM] The caller is not the super-user.
- [ENODEV] *Special* does not exist.
- [ENOTBLK] *Special* is not a block device.
- [ENXIO] The major device number of *special* is out of range (this indicates no device driver exists for the associated hardware).
- [EINVAL] The requested device is not in the mount table.
- [EBUSY] A process is holding a reference to a file located on the file system.
- [EIO] An I/O error occurred while writing the super block or other cached file system information.
- [EFAULT] *Special* points outside the process's allocated address space.

SEE ALSO

mount(8), umount(8)

BUGS

Some of the error codes need translation to more obvious messages.

P
R
M
2

NAME

`open` – open a file for reading or writing, or create a new file

SYNOPSIS

```
#include <sys/file.h>
```

```
open(path, flags, mode)
```

```
char *path;
```

```
int flags, mode;
```

DESCRIPTION

Open opens the file *path* for reading and/or writing, as specified by the *flags* argument and returns a descriptor for that file. The *flags* argument may indicate the file is to be created if it does not already exist (by specifying the `O_CREAT` flag), in which case the file is created with mode *mode* as described in *chmod(2)* and modified by the process' *umask* value (see *umask(2)*).

Path is the address of a string of ASCII characters representing a path name, terminated by a null character. The flags specified are formed by *or'ing* the following values

<code>O_RDONLY</code>	open for reading only
<code>O_WRONLY</code>	open for writing only
<code>O_RDWR</code>	open for reading and writing
<code>O_NDELAY</code>	do not block on open
<code>O_APPEND</code>	append on each write
<code>O_CREAT</code>	create file if it does not exist
<code>O_TRUNC</code>	truncate size to 0
<code>O_EXCL</code>	error if create and file exists

Opening a file with `O_APPEND` set causes each write on the file to be appended to the end. If `O_TRUNC` is specified and the file exists, the file is truncated to zero length. If `O_EXCL` is set with `O_CREAT`, then if the file already exists, the open returns an error. This can be used to implement a simple exclusive access locking mechanism. If `O_EXCL` is set and the last component of the pathname is a symbolic link, the open will fail even if the symbolic link points to a non-existent name. If the `O_NDELAY` flag is specified and the open call would result in the process being blocked for some reason (e.g. waiting for carrier on a dialup line), the open returns immediately. The first time the process attempts to perform i/o on the open file it will block (not currently implemented).

Upon successful completion a non-negative integer termed a file descriptor is returned. The file pointer used to mark the current position within the file is set to the beginning of the file.

The new descriptor is set to remain open across *execve* system calls; see *close(2)*.

The system imposes a limit on the number of file descriptors open simultaneously by one process. *Getdtablesize(2)* returns the current system limit.

ERRORS

The named file is opened unless one or more of the following are true:

[ENOTDIR] A component of the path prefix is not a directory.

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG]

A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] `O_CREAT` is not set and the named file does not exist.

[ENOENT] A component of the path name that must exist does not exist.

[EACCES]	Search permission is denied for a component of the path prefix.
[EACCES]	The required permissions (for reading and/or writing) are denied for the named flag.
[EACCES]	O_CREAT is specified, the file does not exist, and the directory in which it is to be created does not permit writing.
[ELOOP]	Too many symbolic links were encountered in translating the pathname.
[EISDIR]	The named file is a directory, and the arguments specify it is to be opened for writing.
[EROFS]	The named file resides on a read-only file system, and the file is to be modified.
[EMFILE]	The system limit for open file descriptors per process has already been reached.
[ENFILE]	The system file table is full.
[ENXIO]	The named file is a character special or block special file, and the device associated with this special file does not exist.
[ENOSPC]	O_CREAT is specified, the file does not exist, and the directory in which the entry for the new file is being placed cannot be extended because there is no space left on the file system containing the directory.
[ENOSPC]	O_CREAT is specified, the file does not exist, and there are no free inodes on the file system on which the file is being created.
[EDQUOT]	O_CREAT is specified, the file does not exist, and the directory in which the entry for the new file is being placed cannot be extended because the user's quota of disk blocks on the file system containing the directory has been exhausted.
[EDQUOT]	O_CREAT is specified, the file does not exist, and the user's quota of inodes on the file system on which the file is being created has been exhausted.
[EIO]	An I/O error occurred while making the directory entry or allocating the inode for O_CREAT.
[ETXTBSY]	The file is a pure procedure (shared text) file that is being executed and the open call requests write access.
[EFAULT]	Path points outside the process's allocated address space.
[EEXIST]	O_CREAT and O_EXCL were specified and the file exists.
[EOPNOTSUPP]	An attempt was made to open a socket (not currently implemented).

SEE ALSO

chmod(2), close(2), dup(2), getdtablesize(2), lseek(2), read(2), write(2), umask(2)

NAME

pipe – create an interprocess communication channel

SYNOPSIS

```
pipe(fildes)
int fildes[2];
```

DESCRIPTION

The *pipe* system call creates an I/O mechanism called a pipe. The file descriptors returned can be used in read and write operations. When the pipe is written using the descriptor *fildes*[1] up to 4096 bytes of data are buffered before the writing process is suspended. A read using the descriptor *fildes*[0] will pick up the data.

It is assumed that after the pipe has been set up, two (or more) cooperating processes (created by subsequent *fork* calls) will pass data through the pipe with *read* and *write* calls.

The shell has a syntax to set up a linear array of processes connected by pipes.

Read calls on an empty pipe (no buffered data) with only one end (all write file descriptors closed) returns an end-of-file.

Pipes are really a special case of the *socketpair*(2) call and, in fact, are implemented as such in the system.

A signal is generated if a write on a pipe with only one end is attempted.

RETURN VALUE

The function value zero is returned if the pipe was created; -1 if an error occurred.

ERRORS

The *pipe* call will fail if:

- [EMFILE] Too many descriptors are active.
- [ENFILE] The system file table is full.
- [EFAULT] The *fildes* buffer is in an invalid area of the process's address space.

SEE ALSO

sh(1), read(2), write(2), fork(2), socketpair(2)

BUGS

Should more than 4096 bytes be necessary in any pipe among a loop of processes, deadlock will occur.

NAME

profil - execution time profile

SYNOPSIS

profil(buff, bufsiz, offset, scale)

char *buff;

int bufsiz, offset, scale;

DESCRIPTION

Buff points to an area of core whose length (in bytes) is given by *bufsiz*. After this call, the user's program counter (pc) is examined each clock tick (10 milliseconds); *offset* is subtracted from it, and the result multiplied by *scale*. If the resulting number corresponds to a word inside *buff*, that word is incremented.

The scale is interpreted as an unsigned, fixed-point fraction with 16 bits of fraction: 0x10000 gives a 1-1 mapping of pc's to words in *buff*; 0x8000 maps each pair of instruction words together.

Profiling is turned off by giving a *scale* of 0 or 1. It is rendered ineffective by giving a *bufsiz* of 0. Profiling is turned off when an *execve* is executed, but remains on in child and parent both after a *fork*. Profiling is turned off if an update in *buff* would cause a memory fault.

RETURN VALUE

A 0, indicating success, is always returned.

SEE ALSO

gprof(1), setitimer(2), monitor(3)

NAME

ptrace – process trace

SYNOPSIS

```
#include <sys/signal.h>
```

```
#include <sys/ptrace.h>
```

```
ptrace(request, pid, addr, data)
```

```
int request, pid, *addr, data;
```

DESCRIPTION

Ptrace provides a means by which a parent process may control the execution of a child process, and examine and change its core image. Its primary use is for the implementation of breakpoint debugging. There are four arguments whose interpretation depends on a *request* argument. Generally, *pid* is the process ID of the traced process, which must be a child (no more distant descendant) of the tracing process. A process being traced behaves normally until it encounters some signal whether internally generated like “illegal instruction” or externally generated like “interrupt”. See *sigvec(2)* for the list. Then the traced process enters a stopped state and its parent is notified via *wait(2)*. When the child is in the stopped state, its core image can be examined and modified using *ptrace*. If desired, another *ptrace* request can then cause the child either to terminate or to continue, possibly ignoring the signal.

The value of the *request* argument determines the precise action of the call:

PT_TRACE_ME

This request is the only one used by the child process; it declares that the process is to be traced by its parent. All the other arguments are ignored. Peculiar results will ensue if the parent does not expect to trace the child.

PT_READ_I, PT_READ_D

The word in the child process's address space at *addr* is returned. If I and D space are separated (e.g. historically on a pdp-11), request PT_READ_I indicates I space, PT_READ_D D space. *Addr* must be even on some machines. The child must be stopped. The input *data* is ignored.

PT_READ_U

The word of the system's per-process data area corresponding to *addr* is returned. *Addr* must be even on some machines and less than 512. This space contains the registers and other information about the process; its layout corresponds to the *user* structure in the system.

PT_WRITE_I, PT_WRITE_D

The given *data* is written at the word in the process's address space corresponding to *addr*, which must be even on some machines. No useful value is returned. If I and D space are separated, request PT_WRITE_I indicates I space, PT_WRITE_D D space. Attempts to write in pure procedure fail if another process is executing the same file.

PT_WRITE_U

The process's system data is written, as it is read with request PT_READ_U. Only a few locations can be written in this way: the general registers, the floating point status and registers, and certain bits of the processor status word.

PT_CONTINUE

The *data* argument is taken as a signal number and the child's execution continues at location *addr* as if it had incurred that signal. Normally the signal number will be either 0 to indicate that the signal that caused the stop should be ignored, or that value fetched out of the process's image indicating which signal caused the stop. If *addr* is (int *)1 then execution continues from where it stopped.

PT_KILL

The traced process terminates.

PT_STEP

Execution continues as in request **PT_CONTINUE**; however, as soon as possible after execution of at least one instruction, execution stops again. The signal number from the stop is **SIGTRAP**. (On the VAX-11 the T-bit is used and just one instruction is executed.) This is part of the mechanism for implementing breakpoints.

As indicated, these calls (except for request **PT_TRACE_ME**) can be used only when the subject process has stopped. The *wait* call is used to determine when a process stops; in such a case the "termination" status returned by *wait* has the value 0177 to indicate stoppage rather than genuine termination.

To forestall possible fraud, *ptrace* inhibits the set-user-id and set-group-id facilities on subsequent *execve*(2) calls. If a traced process calls *execve*, it will stop before executing the first instruction of the new image showing signal **SIGTRAP**.

On a VAX-11, "word" also means a 32-bit integer, but the "even" restriction does not apply.

RETURN VALUE

A 0 value is returned if the call succeeds. If the call fails then a -1 is returned and the global variable *errno* is set to indicate the error.

ERRORS

[EIO]	The request code is invalid.
[ESRCH]	The specified process does not exist.
[EIO]	The given signal number is invalid.
[EIO]	The specified address is out of bounds.
[EPERM]	The specified process cannot be traced.

SEE ALSO

wait(2), *sigvec*(2), *adb*(1)

BUGS

Ptrace is unique and arcane; it should be replaced with a special file that can be opened and read and written. The control functions could then be implemented with *ioctl*(2) calls on this file. This would be simpler to understand and have much higher performance.

The request **PT_TRACE_ME** call should be able to specify signals that are to be treated normally and not cause a stop. In this way, for example, programs with simulated floating point (which use "illegal instruction" signals at a very high rate) could be efficiently debugged.

The error indication, -1, is a legitimate function value; *errno*, (see *intro*(2)), can be used to disambiguate.

It should be possible to stop a process on occurrence of a system call; in this way a completely controlled environment could be provided.

NAME

quota – manipulate disk quotas

SYNOPSIS

```
#include <sys/quota.h>

quota(cmd, uid, arg, addr)
int cmd, uid, arg;
char *addr;
```

DESCRIPTION

The *quota* call manipulates disk quotas for file systems that have had quotas enabled with *set-quota(2)*. The *cmd* parameter indicates a command to be applied to the user ID *uid*. *Arg* is a command specific argument and *addr* is the address of an optional, command specific, data structure that is copied in or out of the system. The interpretation of *arg* and *addr* is given with each command below.

Q_SETDLIM

Set disc quota limits and current usage for the user with ID *uid*. *Arg* is a major-minor device indicating a particular file system. *Addr* is a pointer to a struct dqblk structure (defined in *<sys/quota.h>*). This call is restricted to the super-user.

Q_GETDLIM

Get disc quota limits and current usage for the user with ID *uid*. The remaining parameters are as for Q_SETDLIM.

Q_SETDUSE

Set disc usage limits for the user with ID *uid*. *Arg* is a major-minor device indicating a particular file system. *Addr* is a pointer to a struct dqusage structure (defined in *<sys/quota.h>*). This call is restricted to the super-user.

Q_SYNC

Update the on-disc copy of quota usages. *Arg* is a major-minor device indicating the file system to be sync'ed. If the *arg* parameter is specified as NODEV, all file systems that have disc quotas will be sync'ed. The *uid* and *addr* parameters are ignored.

Q_SETUID

Change the calling process's quota limits to those of the user with ID *uid*. The *arg* and *addr* parameters are ignored. This call is restricted to the super-user.

Q_SETWARN

Alter the disc usage warning limits for the user with ID *uid*. *Arg* is a major-minor device indicating a particular file system. *Addr* is a pointer to a struct dqwarn structure (defined in *<sys/quota.h>*). This call is restricted to the super-user.

Q_DOWARN

Warn the user with user ID *uid* about excessive disc usage. This call causes the system to check its current disc usage information and print a message on the terminal of the caller for each file system on which the user is over quota. If the user is under quota, his warning count is reset to MAX*_WARN (defined in *<sys/quota.h>*). If the *arg* parameter is specified as NODEV, all file systems that have disc quotas will be checked. Otherwise, *arg* indicates a specific major-minor device to be checked. This call is restricted to the super-user.

RETURN VALUE

A successful call returns 0, otherwise the value -1 is returned and the global variable *errno* indicates the reason for the failure.

ERRORS

A *quota* call will fail when one of the following occurs:

[EINVAL]	The kernel has not been compiled with the QUOTA option.
[EINVAL]	<i>Cmd</i> is invalid.
[ESRCH]	No disc quota is found for the indicated user.
[EPERM]	The call is privileged and the caller was not the super-user.
[ENODEV]	The <i>arg</i> parameter is being interpreted as a major-minor device and it indicates an unmounted file system.
[EFAULT]	An invalid <i>addr</i> is supplied; the associated structure could not be copied in or out of the kernel.
[EUSERS]	The quota table is full.

SEE ALSO

setquota(2), quotaon(8), quotacheck(8)

BUGS

There should be some way to integrate this call with the resource limit interface provided by *setrlimit(2)* and *getrlimit(2)*.

The Australian spelling of *disk* is used throughout the quota facilities in honor of the implementors.

NAME

read, readv – read input

SYNOPSIS

```
cc = read(d, buf, nbytes)
int cc, d;
char *buf;
int nbytes;

#include <sys/types.h>
#include <sys/uio.h>

cc = readv(d, iov, iovcnt)
int cc, d;
struct iovec *iov;
int iovcnt;
```

DESCRIPTION

Read attempts to read *nbytes* of data from the object referenced by the descriptor *d* into the buffer pointed to by *buf*. *Readv* performs the same action, but scatters the input data into the *iovcnt* buffers specified by the members of the *iov* array: *iov*[0], *iov*[1], ..., *iov*[*iovcnt* - 1].

For *readv*, the *iovec* structure is defined as

```
struct iovec {
    caddr_t iov_base;
    int     iov_len;
};
```

Each *iovec* entry specifies the base address and length of an area in memory where data should be placed. *Readv* will always fill an area completely before proceeding to the next.

On objects capable of seeking, the *read* starts at a position given by the pointer associated with *d* (see *lseek*(2)). Upon return from *read*, the pointer is incremented by the number of bytes actually read.

Objects that are not capable of seeking always read from the current position. The value of the pointer associated with such an object is undefined.

Upon successful completion, *read* and *readv* return the number of bytes actually read and placed in the buffer. The system guarantees to read the number of bytes requested if the descriptor references a normal file that has that many bytes left before the end-of-file, but in no other case.

If the returned value is 0, then end-of-file has been reached.

RETURN VALUE

If successful, the number of bytes actually read is returned. Otherwise, a -1 is returned and the global variable *errno* is set to indicate the error.

ERRORS

Read and *readv* will fail if one or more of the following are true:

- [EBADF] *D* is not a valid file or socket descriptor open for reading.
- [EFAULT] *Buf* points outside the allocated address space.
- [EIO] An I/O error occurred while reading from the file system.
- [EINTR] A read from a slow device was interrupted before any data arrived by the delivery of a signal.
- [EINVAL] The pointer associated with *d* was negative.

[EWOULDBLOCK]

The file was marked for non-blocking I/O, and no data were ready to be read.

In addition, *readv* may return one of the following errors:

- [EINVAL]** *iovcnt* was less than or equal to 0, or greater than 16.
- [EINVAL]** One of the *iov_len* values in the *iov* array was negative.
- [EINVAL]** The sum of the *iov_len* values in the *iov* array overflowed a 32-bit integer.
- [EFAULT]** Part of the *iov* points outside the process's allocated address space.

SEE ALSO

dup(2), *fcntl(2)*, *open(2)*, *pipe(2)*, *select(2)*, *socket(2)*, *socketpair(2)*

NAME

readlink – read value of a symbolic link

SYNOPSIS

```
cc = readlink(path, buf, bufsiz)
int cc;
char *path, *buf;
int bufsiz;
```

DESCRIPTION

Readlink places the contents of the symbolic link *name* in the buffer *buf*, which has size *bufsiz*. The contents of the link are not null terminated when returned.

RETURN VALUE

The call returns the count of characters placed in the buffer if it succeeds, or a -1 if an error occurs, placing the error code in the global variable *errno*.

ERRORS

Readlink will fail and the file mode will be unchanged if:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] The named file does not exist.
- [EACCES] Search permission is denied for a component of the path prefix.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EINVAL] The named file is not a symbolic link.
- [EIO] An I/O error occurred while reading from the file system.
- [EFAULT] *Buf* extends outside the process's allocated address space.

SEE ALSO

stat(2), *lstat(2)*, *symlink(2)*

NAME

reboot – reboot system or halt processor

SYNOPSIS

```
#include <sys/reboot.h>
```

```
reboot(howto)
```

```
int howto;
```

DESCRIPTION

Reboot reboots the system, and is invoked automatically in the event of unrecoverable system failures. *Howto* is a mask of options passed to the bootstrap program. The system call interface permits only RB_HALT or RB_AUTOBOOT to be passed to the reboot program; the other flags are used in scripts stored on the console storage media, or used in manual bootstrap procedures. When none of these options (e.g. RB_AUTOBOOT) is given, the system is rebooted from file "vmunix" in the root file system of unit 0 of a disk chosen in a processor specific way. An automatic consistency check of the disks is then normally performed.

The bits of *howto* are:

RB_HALT

the processor is simply halted; no reboot takes place. RB_HALT should be used with caution.

RB_ASKNAME

Interpreted by the bootstrap program itself, causing it to inquire as to what file should be booted. Normally, the system is booted from the file "xx(0,0)vmunix" without asking.

RB_SINGLE

Normally, the reboot procedure involves an automatic disk consistency check and then multi-user operations. RB_SINGLE prevents the consistency check, rather simply booting the system with a single-user shell on the console. RB_SINGLE is interpreted by the *init(8)* program in the newly booted system. This switch is not available from the system call interface.

Only the super-user may *reboot* a machine.

RETURN VALUES

If successful, this call never returns. Otherwise, a -1 is returned and an error is returned in the global variable *errno*.

ERRORS

[EPERM] The caller is not the super-user.

SEE ALSO

crash(8), halt(8), init(8), reboot(8)

BUGS

The notion of "console medium", among other things, is specific to the VAX.

NAME

recv, recvfrom, recvmsg – receive a message from a socket

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>

cc = recv(s, buf, len, flags)
int cc, s;
char *buf;
int len, flags;

cc = recvfrom(s, buf, len, flags, from, fromlen)
int cc, s;
char *buf;
int len, flags;
struct sockaddr *from;
int *fromlen;

cc = recvmsg(s, msg, flags)
int cc, s;
struct msghdr msg[];
int flags;
```

DESCRIPTION

Recv, *recvfrom*, and *recvmsg* are used to receive messages from a socket.

The *recv* call is normally used only on a *connected* socket (see *connect(2)*), while *recvfrom* and *recvmsg* may be used to receive data on a socket whether it is in a connected state or not.

If *from* is non-zero, the source address of the message is filled in. *Fromlen* is a value-result parameter, initialized to the size of the buffer associated with *from*, and modified on return to indicate the actual size of the address stored there. The length of the message is returned in *cc*. If a message is too long to fit in the supplied buffer, excess bytes may be discarded depending on the type of socket the message is received from (see *socket(2)*).

If no messages are available at the socket, the receive call waits for a message to arrive, unless the socket is nonblocking (see *ioctl(2)*) in which case a *cc* of -1 is returned with the external variable *errno* set to *EWOULDBLOCK*.

The *select(2)* call may be used to determine when more data arrives.

The *flags* argument to a *recv* call is formed by *or'ing* one or more of the values,

```
#define MSG_OOB      0x1    /* process out-of-band data */
#define MSG_PEEK     0x2    /* peek at incoming message */
```

The *recvmsg* call uses a *msghdr* structure to minimize the number of directly supplied parameters. This structure has the following form, as defined in *<sys/socket.h>*:

```
struct msghdr {
    caddr_t msg_name;        /* optional address */
    int msg_namelen;        /* size of address */
    struct iovec *msg_iov;    /* scatter/gather array */
    int msg_iovlen;         /* # elements in msg_iov */
    caddr_t msg_accrights;    /* access rights sent/received */
    int msg_accrightslen;
};
```

Here *msg_name* and *msg_namelen* specify the destination address if the socket is unconnected; *msg_name* may be given as a null pointer if no names are desired or required. The *msg_iov* and *msg_iovlen* describe the scatter gather locations, as described in *read(2)*. A

buffer to receive any access rights sent along with the message is specified in *msg_accrights*, which has length *msg_accrightslen*. Access rights are currently limited to file descriptors, which each occupy the size of an int.

RETURN VALUE

These calls return the number of bytes received, or -1 if an error occurred.

ERRORS

The calls fail if:

- [EBADF] The argument *s* is an invalid descriptor.
- [ENOTSOCK] The argument *s* is not a socket.
- [EWOULDBLOCK] The socket is marked non-blocking and the receive operation would block.
- [EINTR] The receive was interrupted by delivery of a signal before any data was available for the receive.
- [EFAULT] The data was specified to be received into a non-existent or protected part of the process address space.

SEE ALSO

fcntl(2), read(2), send(2), select(2), getsockopt(2), socket(2)

NAME

rename – change the name of a file

SYNOPSIS

```
rename(from, to)
char *from, *to;
```

DESCRIPTION

Rename causes the link named *from* to be renamed as *to*. If *to* exists, then it is first removed. Both *from* and *to* must be of the same type (that is, both directories or both non-directories), and must reside on the same file system.

Rename guarantees that an instance of *to* will always exist, even if the system should crash in the middle of the operation.

If the final component of *from* is a symbolic link, the symbolic link is renamed, not the file or directory to which it points.

CAVEAT

The system can deadlock if a loop in the file system graph is present. This loop takes the form of an entry in directory “a”, say “a/foo”, being a hard link to directory “b”, and an entry in directory “b”, say “b/bar”, being a hard link to directory “a”. When such a loop exists and two separate processes attempt to perform “rename a/foo b/bar” and “rename b/bar a/foo”, respectively, the system may deadlock attempting to lock both directories for modification. Hard links to directories should be replaced by symbolic links by the system administrator.

RETURN VALUE

A 0 value is returned if the operation succeeds, otherwise *rename* returns -1 and the global variable *errno* indicates the reason for the failure.

ERRORS

Rename will fail and neither of the argument files will be affected if any of the following are true:

- [EINVAL] Either pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of either pathname exceeded 255 characters, or the entire length of either path name exceeded 1023 characters.
- [ENOENT] A component of the *from* path does not exist, or a path prefix of *to* does not exist.
- [EACCES] A component of either path prefix denies search permission.
- [EACCES] The requested link requires writing in a directory with a mode that denies write permission.
- [EPERM] The directory containing *from* is marked sticky, and neither the containing directory nor *from* are owned by the effective user ID.
- [EPERM] The *to* file exists, the directory containing *to* is marked sticky, and neither the containing directory nor *to* are owned by the effective user ID.
- [ELOOP] Too many symbolic links were encountered in translating either pathname.
- [ENOTDIR] A component of either path prefix is not a directory.
- [ENOTDIR] *From* is a directory, but *to* is not a directory.
- [EISDIR] *To* is a directory, but *from* is not a directory.
- [EXDEV] The link named by *to* and the file named by *from* are on different logical devices (file systems). Note that this error code will not be returned if the

implementation permits cross-device links.

[ENOSPC] The directory in which the entry for the new name is being placed cannot be extended because there is no space left on the file system containing the directory.

[EDQUOT] The directory in which the entry for the new name is being placed cannot be extended because the user's quota of disk blocks on the file system containing the directory has been exhausted.

[EIO] An I/O error occurred while making or updating a directory entry.

[EROFS] The requested link requires writing in a directory on a read-only file system.

[EFAULT] *Path* points outside the process's allocated address space.

[EINVAL] *From* is a parent directory of *to*, or an attempt is made to rename "." or "..".

[ENOTEMPTY] *To* is a directory and is not empty.

SEE ALSO

`open(2)`

NAME

rmdir – remove a directory file

SYNOPSIS

rmdir(path)
char *path;

DESCRIPTION

Rmdir removes a directory file whose name is given by *path*. The directory must not have any entries other than “.” and “..”.

RETURN VALUE

A 0 is returned if the remove succeeds; otherwise a -1 is returned and an error code is stored in the global location *errno*.

ERRORS

The named file is removed unless one or more of the following are true:

- [ENOTDIR] A component of the path is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] The named directory does not exist.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [ENOTEMPTY] The named directory contains files other than “.” and “..” in it.
- [EACCES] Search permission is denied for a component of the path prefix.
- [EACCES] Write permission is denied on the directory containing the link to be removed.
- [EPERM] The directory containing the directory to be removed is marked sticky, and neither the containing directory nor the directory to be removed are owned by the effective user ID.
- [EBUSY] The directory to be removed is the mount point for a mounted file system.
- [EIO] An I/O error occurred while deleting the directory entry or deallocating the inode.
- [EROFS] The directory entry to be removed resides on a read-only file system.
- [EFAULT] *Path* points outside the process's allocated address space.

SEE ALSO

mkdir(2), **unlink**(2)

NAME

select – synchronous I/O multiplexing

SYNOPSIS

```
#include <sys/types.h>
#include <sys/time.h>

nfound = select(nfds, readfds, writefds, exceptfds, timeout)
int nfound, nfds;
fd_set *readfds, *writefds, *exceptfds;
struct timeval *timeout;

FD_SET(fd, &fdset)
FD_CLR(fd, &fdset)
FD_ISSET(fd, &fdset)
FD_ZERO(&fdset)
int fd;
fd_set fdset;
```

DESCRIPTION

Select examines the I/O descriptor sets whose addresses are passed in *readfds*, *writefds*, and *exceptfds* to see if some of their descriptors are ready for reading, are ready for writing, or have an exceptional condition pending, respectively. The first *nfds* descriptors are checked in each set; i.e. the descriptors from 0 through *nfds*-1 in the descriptor sets are examined. On return, *select* replaces the given descriptor sets with subsets consisting of those descriptors that are ready for the requested operation. The total number of ready descriptors in all the sets is returned in *nfound*.

The descriptor sets are stored as bit fields in arrays of integers. The following macros are provided for manipulating such descriptor sets: *FD_ZERO(&fdset)* initializes a descriptor set *fdset* to the null set. *FD_SET(fd, &fdset)* includes a particular descriptor *fd* in *fdset*. *FD_CLR(fd, &fdset)* removes *fd* from *fdset*. *FD_ISSET(fd, &fdset)* is nonzero if *fd* is a member of *fdset*, zero otherwise. The behavior of these macros is undefined if a descriptor value is less than zero or greater than or equal to *FD_SETSIZE*, which is normally at least equal to the maximum number of descriptors supported by the system.

If *timeout* is a non-zero pointer, it specifies a maximum interval to wait for the selection to complete. If *timeout* is a zero pointer, the *select* blocks indefinitely. To affect a poll, the *timeout* argument should be non-zero, pointing to a zero-valued *timeval* structure.

Any of *readfds*, *writefds*, and *exceptfds* may be given as zero pointers if no descriptors are of interest.

RETURN VALUE

Select returns the number of ready descriptors that are contained in the descriptor sets, or -1 if an error occurred. If the time limit expires then *select* returns 0. If *select* returns with an error, including one due to an interrupted call, the descriptor sets will be unmodified.

ERRORS

An error return from *select* indicates:

- | | |
|----------|--|
| [EBADF] | One of the descriptor sets specified an invalid descriptor. |
| [EINTR] | A signal was delivered before the time limit expired and before any of the selected events occurred. |
| [EINVAL] | The specified time limit is invalid. One of its components is negative or too large. |

SEE ALSO

accept(2), connect(2), read(2), write(2), recv(2), send(2), getdtablesize(2)

BUGS

Although the provision of *getdtablesize(2)* was intended to allow user programs to be written independent of the kernel limit on the number of open files, the dimension of a sufficiently large bit field for select remains a problem. The default size `FD_SETSIZE` (currently 256) is somewhat larger than the current kernel limit to the number of open files. However, in order to accommodate programs which might potentially use a larger number of open files with select, it is possible to increase this size within a program by providing a larger definition of `FD_SETSIZE` before the inclusion of `<sys/types.h>`.

Select should probably return the time remaining from the original timeout, if any, by modifying the time value in place. This may be implemented in future versions of the system. Thus, it is unwise to assume that the timeout value will be unmodified by the *select* call.

NAME

`send`, `sendto`, `sendmsg` – send a message from a socket

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>

cc = send(s, msg, len, flags)
int cc, s;
char *msg;
int len, flags;

cc = sendto(s, msg, len, flags, to, tolen)
int cc, s;
char *msg;
int len, flags;
struct sockaddr *to;
int tolen;

cc = sendmsg(s, msg, flags)
int cc, s;
struct msghdr msg[];
int flags;
```

DESCRIPTION

Send, *sendto*, and *sendmsg* are used to transmit a message to another socket. *Send* may be used only when the socket is in a *connected* state, while *sendto* and *sendmsg* may be used at any time.

The address of the target is given by *to* with *tolen* specifying its size. The length of the message is given by *len*. If the message is too long to pass atomically through the underlying protocol, then the error `EMSGSIZE` is returned, and the message is not transmitted.

No indication of failure to deliver is implicit in a *send*. Return values of `-1` indicate some locally detected errors.

If no messages space is available at the socket to hold the message to be transmitted, then *send* normally blocks, unless the socket has been placed in non-blocking I/O mode. The *select(2)* call may be used to determine when it is possible to send more data.

The *flags* parameter may include one or more of the following:

```
#define MSG_OOB      0x1    /* process out-of-band data */
#define MSG_DONTROUTE 0x4    /* bypass routing, use direct interface */
```

The flag `MSG_OOB` is used to send “out-of-band” data on sockets that support this notion (e.g. `SOCK_STREAM`); the underlying protocol must also support “out-of-band” data. `MSG_DONTROUTE` is usually used only by diagnostic or routing programs.

See *recv(2)* for a description of the *msghdr* structure.

RETURN VALUE

The call returns the number of characters sent, or `-1` if an error occurred.

ERRORS

[EBADF]	An invalid descriptor was specified.
[ENOTSOCK]	The argument <i>s</i> is not a socket.
[EFAULT]	An invalid user space address was specified for a parameter.
[EMSGSIZE]	The socket requires that message be sent atomically, and the size of the message to be sent made this impossible.

- [EWOULDBLOCK] The socket is marked non-blocking and the requested operation would block.
- [ENOBUFS] The system was unable to allocate an internal buffer. The operation may succeed when buffers become available.
- [ENOBUFS] The output queue for a network interface was full. This generally indicates that the interface has stopped sending, but may be caused by transient congestion.

SEE ALSO

fcntl(2), recv(2), select(2), getsockopt(2), socket(2), write(2)

NAME

setgroups – set group access list

SYNOPSIS

```
#include <sys/param.h>
```

```
setgroups(ngroups, gidset)
```

```
int ngroups, *gidset;
```

DESCRIPTION

Setgroups sets the group access list of the current user process according to the array *gidset*. The parameter *ngroups* indicates the number of entries in the array and must be no more than NGROUPS, as defined in *<sys/param.h>*.

Only the super-user may set new groups.

RETURN VALUE

A 0 value is returned on success, -1 on error, with a error code stored in *errno*.

ERRORS

The *setgroups* call will fail if:

[EPERM] The caller is not the super-user.

[EFAULT] The address specified for *gidset* is outside the process address space.

SEE ALSO

getgroups(2), initgroups(3X)

BUGS

The *gidset* array should be of type *gid_t*, but remains integer for compatibility with earlier systems.

NAME

setpgrp – set process group

SYNOPSIS

setpgrp(*pid*, *pgrp*)
int *pid*, *pgrp*;

DESCRIPTION

Setpgrp sets the process group of the specified process *pid* to the specified *pgrp*. If *pid* is zero, then the call applies to the current process.

If the invoker is not the super-user, then the affected process must have the same effective user-id as the invoker or be a descendant of the invoking process.

RETURN VALUE

Setpgrp returns when the operation was successful. If the request failed, -1 is returned and the global variable *errno* indicates the reason.

ERRORS

Setpgrp will fail and the process group will not be altered if one of the following occur:

- [ESRCH] The requested process does not exist.
- [EPERM] The effective user ID of the requested process is different from that of the caller and the process is not a descendant of the calling process.

SEE ALSO

getpgrp(2)

NAME

setquota – enable/disable quotas on a file system

SYNOPSIS

```
setquota(special, file)
char *special, *file;
```

DESCRIPTION

Disc quotas are enabled or disabled with the *setquota* call. *Special* indicates a block special device on which a mounted file system exists. If *file* is nonzero, it specifies a file in that file system from which to take the quotas. If *file* is 0, then quotas are disabled on the file system. The quota file must exist; it is normally created with the *quotacheck*(8) program.

Only the super-user may turn quotas on or off.

SEE ALSO

quota(2), quotacheck(8), quotaon(8)

RETURN VALUE

A 0 return value indicates a successful call. A value of -1 is returned when an error occurs and *errno* is set to indicate the reason for failure.

ERRORS

Setquota will fail when one of the following occurs:

- [ENOTDIR] A component of either path prefix is not a directory.
- [EINVAL] Either pathname contains a character with the high-order bit set.
- [EINVAL] The kernel has not been compiled with the QUOTA option.
- [ENAMETOOLONG] A component of either pathname exceeded 255 characters, or the entire length of either path name exceeded 1023 characters.
- [ENODEV] *Special* does not exist.
- [ENOENT] *File* does not exist.
- [ELOOP] Too many symbolic links were encountered in translating either pathname.
- [EPERM] The caller is not the super-user.
- [ENOTBLK] *Special* is not a block device.
- [ENXIO] The major device number of *special* is out of range (this indicates no device driver exists for the associated hardware).
- [EROFS] *File* resides on a read-only file system.
- [EACCES] Search permission is denied for a component of either path prefix.
- [EACCES] *File* resides on a file system different from *special*.
- [EACCES] *File* is not a plain file.
- [EIO] An I/O error occurred while reading from or writing to the file containing the quotas.
- [EFAULT] *Special* or *path* points outside the process's allocated address space.

BUGS

The error codes are in a state of disarray; too many errors appear to the caller as one value.

NAME

setregid – set real and effective group ID

SYNOPSIS

```
setregid(rgid, egid)
int rgid, egid;
```

DESCRIPTION

The real and effective group ID's of the current process are set to the arguments. Unprivileged users may change the real group ID to the effective group ID and vice-versa; only the super-user may make other changes.

Supplying a value of -1 for either the real or effective group ID forces the system to substitute the current ID in place of the -1 parameter.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

[EPERM] The current process is not the super-user and a change other than changing the effective group-id to the real group-id was specified.

SEE ALSO

getgid(2), setreuid(2), setgid(3)

NAME

setreuid – set real and effective user ID's

SYNOPSIS

setreuid(ruid, euid)
int ruid, euid;

DESCRIPTION

The real and effective user ID's of the current process are set according to the arguments. If *ruid* or *euid* is -1, the current uid is filled in by the system. Unprivileged users may change the real user ID to the effective user ID and vice-versa; only the super-user may make other changes.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

[EPERM] The current process is not the super-user and a change other than changing the effective user-id to the real user-id was specified.

SEE ALSO

getuid(2), setregid(2), setuid(3)

NAME

shutdown – shut down part of a full-duplex connection

SYNOPSIS

```
shutdown(s, how)
int s, how;
```

DESCRIPTION

The *shutdown* call causes all or part of a full-duplex connection on the socket associated with *s* to be shut down. If *how* is 0, then further receives will be disallowed. If *how* is 1, then further sends will be disallowed. If *how* is 2, then further sends and receives will be disallowed.

DIAGNOSTICS

A 0 is returned if the call succeeds, -1 if it fails.

ERRORS

The call succeeds unless:

[EBADF] *S* is not a valid descriptor.

[ENOTSOCK] *S* is a file, not a socket.

[ENOTCONN] The specified socket is not connected.

SEE ALSO

connect(2), socket(2)

NAME

sigblock – block signals

SYNOPSIS

```
#include <signal.h>
```

```
sigblock(mask);  
int mask;
```

```
mask = sigmask(signum)
```

DESCRIPTION

Sigblock causes the signals specified in *mask* to be added to the set of signals currently being blocked from delivery. Signals are blocked if the corresponding bit in *mask* is a 1; the macro *sigmask* is provided to construct the mask for a given *signum*.

It is not possible to block SIGKILL, SIGSTOP, or SIGCONT; this restriction is silently imposed by the system.

RETURN VALUE

The previous set of masked signals is returned.

SEE ALSO

kill(2), sigvec(2), sigsetmask(2)

NAME

`sigpause` – atomically release blocked signals and wait for interrupt

SYNOPSIS

```
sigpause(sigmask)
int sigmask;
```

DESCRIPTION

Sigpause assigns *sigmask* to the set of masked signals and then waits for a signal to arrive; on return the set of masked signals is restored. *Sigmask* is usually 0 to indicate that no signals are now to be blocked. *Sigpause* always terminates by being interrupted, returning -1 with *errno* set to EINTR.

In normal usage, a signal is blocked using *sigblock*(2), to begin a critical section, variables modified on the occurrence of the signal are examined to determine that there is no work to be done, and the process pauses awaiting work by using *sigpause* with the mask returned by *sigblock*.

SEE ALSO

`sigblock`(2), `sigvec`(2)

NAME

sigreturn - return from signal

SYNOPSIS

```
#include <signal.h>
```

```
struct sigcontext {  
    int    sc_onstack;  
    int    sc_mask;  
    int    sc_sp;  
    int    sc_fp;  
    int    sc_ap;  
    int    sc_pc;  
    int    sc_ps;  
};
```

```
sigreturn(scp);  
struct sigcontext *scp;
```

DESCRIPTION

Sigreturn allows users to atomically unmask, switch stacks, and return from a signal context. The processes signal mask and stack status are restored from the context. The system call does not return; the users stack pointer, frame pointer, argument pointer, and processor status longword are restored from the context. Execution resumes at the specified pc. This system call is used by the trampoline code, and *longjmp*(3) when returning from a signal to the previously executing program.

NOTES

This system call is not available in 4.2BSD, hence it should not be used if backward compatibility is needed.

RETURN VALUE

If successful, the system call does not return. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Sigreturn will fail and the process context will remain unchanged if one of the following occurs.

- | | |
|----------|--|
| [EFAULT] | <i>Scp</i> points to memory that is not a valid part of the process address space. |
| [EINVAL] | The process status longword is invalid or would improperly raise the privilege level of the process. |

SEE ALSO

sigvec(2), setjmp(3)

NAME

sigsetmask – set current signal mask

SYNOPSIS

```
#include <signal.h>
```

```
sigsetmask(mask);  
int mask;
```

```
mask = sigmask(signum)
```

DESCRIPTION

Sigsetmask sets the current signal mask (those signals that are blocked from delivery). Signals are blocked if the corresponding bit in *mask* is a 1; the macro *sigmask* is provided to construct the mask for a given *signum*.

The system quietly disallows SIGKILL, SIGSTOP, or SIGCONT to be blocked.

RETURN VALUE

The previous set of masked signals is returned.

SEE ALSO

kill(2), sigvec(2), sigblock(2), sigpause(2)

NAME

sigstack – set and/or get signal stack context

SYNOPSIS

```
#include <signal.h>

struct sigstack {
    caddr_t  ss_sp;
    int      ss_onstack;
};

sigstack(ss, oss);
struct sigstack *ss, *oss;
```

DESCRIPTION

Sigstack allows users to define an alternate stack on which signals are to be processed. If *ss* is non-zero, it specifies a *signal stack* on which to deliver signals and tells the system if the process is currently executing on that stack. When a signal's action indicates its handler should execute on the signal stack (specified with a *sigvec(2)* call), the system checks to see if the process is currently executing on that stack. If the process is not currently executing on the signal stack, the system arranges a switch to the signal stack for the duration of the signal handler's execution. If *oss* is non-zero, the current signal stack state is returned.

NOTES

Signal stacks are not “grown” automatically, as is done for the normal stack. If the stack overflows unpredictable results may occur.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Sigstack will fail and the signal stack context will remain unchanged if one of the following occurs.

[EFAULT] Either *ss* or *oss* points to memory that is not a valid part of the process address space.

SEE ALSO

sigvec(2), setjmp(3)

NAME

sigvec – software signal facilities

SYNOPSIS

#include <signal.h>

```
struct sigvec {
    int    (*sv_handler)();
    int    sv_mask;
    int    sv_flags;
};
```

sigvec(sig, vec, ovec)

int sig;

struct sigvec *vec, *ovec;

DESCRIPTION

The system defines a set of signals that may be delivered to a process. Signal delivery resembles the occurrence of a hardware interrupt: the signal is blocked from further occurrence, the current process context is saved, and a new one is built. A process may specify a *handler* to which a signal is delivered, or specify that a signal is to be *blocked* or *ignored*. A process may also specify that a default action is to be taken by the system when a signal occurs. Normally, signal handlers execute on the current stack of the process. This may be changed, on a per-handler basis, so that signals are taken on a special *signal stack*.

All signals have the same *priority*. Signal routines execute with the signal that caused their invocation *blocked*, but other signals may yet occur. A global *signal mask* defines the set of signals currently blocked from delivery to a process. The signal mask for a process is initialized from that of its parent (normally 0). It may be changed with a *sigblock(2)* or *sigsetmask(2)* call, or when a signal is delivered to the process.

When a signal condition arises for a process, the signal is added to a set of signals pending for the process. If the signal is not currently *blocked* by the process then it is delivered to the process. When a signal is delivered, the current state of the process is saved, a new signal mask is calculated (as described below), and the signal handler is invoked. The call to the handler is arranged so that if the signal handling routine returns normally the process will resume execution in the context from before the signal's delivery. If the process wishes to resume in a different context, then it must arrange to restore the previous context itself.

When a signal is delivered to a process a new signal mask is installed for the duration of the process' signal handler (or until a *sigblock* or *sigsetmask* call is made). This mask is formed by taking the current signal mask, adding the signal to be delivered, and *or'ing* in the signal mask associated with the handler to be invoked.

Sigvec assigns a handler for a specific signal. If *vec* is non-zero, it specifies a handler routine and mask to be used when delivering the specified signal. Further, if the SV_ONSTACK bit is set in *sv_flags*, the system will deliver the signal to the process on a *signal stack*, specified with *sigstack(2)*. If *ovec* is non-zero, the previous handling information for the signal is returned to the user.

The following is a list of all signals with names as in the include file <signal.h>:

SIGHUP	1	hangup
SIGINT	2	interrupt
SIGQUIT	3*	quit
SIGILL	4*	illegal instruction
SIGTRAP	5*	trace trap
SIGIOT	6*	IOT instruction
SIGEMT	7*	EMT instruction

SIGFPE	8*	floating point exception
SIGKILL	9	kill (cannot be caught, blocked, or ignored)
SIGBUS	10*	bus error
SIGSEGV	11*	segmentation violation
SIGSYS	12*	bad argument to system call
SIGPIPE	13	write on a pipe with no one to read it
SIGALRM	14	alarm clock
SIGTERM	15	software termination signal
SIGURG	16●	urgent condition present on socket
SIGSTOP	17†	stop (cannot be caught, blocked, or ignored)
SIGTSTP	18†	stop signal generated from keyboard
SIGCONT	19●	continue after stop (cannot be blocked)
SIGCHLD	20●	child status has changed
SIGTTIN	21†	background read attempted from control terminal
SIGTTOU	22†	background write attempted to control terminal
SIGIO	23●	i/o is possible on a descriptor (see <i>fcntl(2)</i>)
SIGXCPU	24	cpu time limit exceeded (see <i>setrlimit(2)</i>)
SIGXFSZ	25	file size limit exceeded (see <i>setrlimit(2)</i>)
SIGVTALRM	26	virtual time alarm (see <i>setitimer(2)</i>)
SIGPROF	27	profiling timer alarm (see <i>setitimer(2)</i>)
SIGWINCH	28●	window size change
SIGUSR1	30	user defined signal 1
SIGUSR2	31	user defined signal 2

The starred signals in the list above cause a core image if not caught or ignored.

Once a signal handler is installed, it remains installed until another *sigvec* call is made, or an *execve(2)* is performed. The default action for a signal may be reinstated by setting *sv_handler* to *SIG_DFL*; this default is termination (with a core image for starred signals) except for signals marked with ● or †. Signals marked with ● are discarded if the action is *SIG_DFL*; signals marked with † cause the process to stop. If *sv_handler* is *SIG_IGN* the signal is subsequently ignored, and pending instances of the signal are discarded.

If a caught signal occurs during certain system calls, the call is normally restarted. The call can be forced to terminate prematurely with an *EINTR* error return by setting the *SV_INTERRUPT* bit in *sv_flags*. The affected system calls are *read(2)* or *write(2)* on a slow device (such as a terminal; but not a file) and during a *wait(2)*.

After a *fork(2)* or *vfork(2)* the child inherits all signals, the signal mask, the signal stack, and the restart/interrupt flags.

Execve(2) resets all caught signals to default action and resets all signals to be caught on the user stack. Ignored signals remain ignored; the signal mask remains the same; signals that interrupt system calls continue to do so.

NOTES

The mask specified in *vec* is not allowed to block *SIGKILL*, *SIGSTOP*, or *SIGCONT*. This is done silently by the system.

The *SV_INTERRUPT* flag is not available in 4.2BSD, hence it should not be used if backward compatibility is needed.

RETURN VALUE

A 0 value indicated that the call succeeded. A -1 return value indicates an error occurred and *errno* is set to indicated the reason.

ERRORS

Sigvec will fail and no new signal handler will be installed if one of the following occurs:

- [EFAULT] Either *vec* or *ovec* points to memory that is not a valid part of the process address space.
- [EINVAL] *Sig* is not a valid signal number.
- [EINVAL] An attempt is made to ignore or supply a handler for SIGKILL or SIGSTOP.
- [EINVAL] An attempt is made to ignore SIGCONT (by default SIGCONT is ignored).

SEE ALSO

kill(1), ptrace(2), kill(2), sigblock(2), sigsetmask(2), sigpause(2), sigstack(2), sigvec(2), setjmp(3), siginterrupt(3), tty(4)

NOTES (VAX-11)

The handler routine can be declared:

```
handler(sig, code, scp)
int sig, code;
struct sigcontext *scp;
```

Here *sig* is the signal number, into which the hardware faults and traps are mapped as defined below. *Code* is a parameter that is either a constant as given below or, for compatibility mode faults, the code provided by the hardware (Compatibility mode faults are distinguished from the other SIGILL traps by having PSL_CM set in the psl). *Scp* is a pointer to the *sigcontext* structure (defined in *<signal.h>*), used to restore the context from before the signal.

The following defines the mapping of hardware traps to signals and codes. All of these symbols are defined in *<signal.h>*:

Hardware condition	Signal	Code
Arithmetic traps:		
Integer overflow	SIGFPE	FPE_INTOVF_TRAP
Integer division by zero	SIGFPE	FPE_INTDIV_TRAP
Floating overflow trap	SIGFPE	FPE_FLTOVF_TRAP
Floating/decimal division by zero	SIGFPE	FPE_FLTDIV_TRAP
Floating underflow trap	SIGFPE	FPE_FLTUND_TRAP
Decimal overflow trap	SIGFPE	FPE_DECOVF_TRAP
Subscript-range	SIGFPE	FPE_SUBRNG_TRAP
Floating overflow fault	SIGFPE	FPE_FLTOVF_FAULT
Floating divide by zero fault	SIGFPE	FPE_FLTDIV_FAULT
Floating underflow fault	SIGFPE	FPE_FLTUND_FAULT
Length access control	SIGSEGV	
Protection violation	SIGBUS	
Reserved instruction	SIGILL	ILL_RESAD_FAULT
Customer-reserved instr.	SIGEMT	
Reserved operand	SIGILL	ILL_PRIVIN_FAULT
Reserved addressing	SIGILL	ILL_RESOP_FAULT
Trace pending	SIGTRAP	
Bpt instruction	SIGTRAP	
Compatibility-mode	SIGILL	hardware supplied code
Chme	SIGSEGV	
Chms	SIGSEGV	
Chmu	SIGSEGV	

BUGS

This manual page is still confusing.

NAME

socket – create an endpoint for communication

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>

s = socket(domain, type, protocol)
int s, domain, type, protocol;
```

DESCRIPTION

Socket creates an endpoint for communication and returns a descriptor.

The *domain* parameter specifies a communications domain within which communication will take place; this selects the protocol family which should be used. The protocol family generally is the same as the address family for the addresses supplied in later operations on the socket. These families are defined in the include file *<sys/socket.h>*. The currently understood formats are

PF_UNIX	(UNIX internal protocols),
PF_INET	(ARPA Internet protocols),
PF_NS	(Xerox Network Systems protocols), and
PF_IMPLINK	(IMP "host at IMP" link layer).

The socket has the indicated *type*, which specifies the semantics of communication. Currently defined types are:

```
SOCK_STREAM
SOCK_DGRAM
SOCK_RAW
SOCK_SEQPACKET
SOCK_RDM
```

A *SOCK_STREAM* type provides sequenced, reliable, two-way connection based byte streams. An out-of-band data transmission mechanism may be supported. A *SOCK_DGRAM* socket supports datagrams (connectionless, unreliable messages of a fixed (typically small) maximum length). A *SOCK_SEQPACKET* socket may provide a sequenced, reliable, two-way connection-based data transmission path for datagrams of fixed maximum length; a consumer may be required to read an entire packet with each read system call. This facility is protocol specific, and presently implemented only for *PF_NS*. *SOCK_RAW* sockets provide access to internal network protocols and interfaces. The types *SOCK_RAW*, which is available only to the super-user, and *SOCK_RDM*, which is planned, but not yet implemented, are not described here.

The *protocol* specifies a particular protocol to be used with the socket. Normally only a single protocol exists to support a particular socket type within a given protocol family. However, it is possible that many protocols may exist, in which case a particular protocol must be specified in this manner. The protocol number to use is particular to the "communication domain" in which communication is to take place; see *protocols(3N)*.

Sockets of type *SOCK_STREAM* are full-duplex byte streams, similar to pipes. A stream socket must be in a *connected* state before any data may be sent or received on it. A connection to another socket is created with a *connect(2)* call. Once connected, data may be transferred using *read(2)* and *write(2)* calls or some variant of the *send(2)* and *recv(2)* calls. When a session has been completed a *close(2)* may be performed. Out-of-band data may also be transmitted as described in *send(2)* and received as described in *recv(2)*.

The communications protocols used to implement a *SOCK_STREAM* insure that data is not lost or duplicated. If a piece of data for which the peer protocol has buffer space cannot be successfully transmitted within a reasonable length of time, then the connection is considered

broken and calls will indicate an error with `-1` returns and with `ETIMEDOUT` as the specific code in the global variable `errno`. The protocols optionally keep sockets "warm" by forcing transmissions roughly every minute in the absence of other activity. An error is then indicated if no response can be elicited on an otherwise idle connection for an extended period (e.g. 5 minutes). A `SIGPIPE` signal is raised if a process sends on a broken stream; this causes naive processes, which do not handle the signal, to exit.

`SOCK_SEQPACKET` sockets employ the same system calls as `SOCK_STREAM` sockets. The only difference is that `read(2)` calls will return only the amount of data requested, and any remaining in the arriving packet will be discarded.

`SOCK_DGRAM` and `SOCK_RAW` sockets allow sending of datagrams to correspondents named in `send(2)` calls. Datagrams are generally received with `recvfrom(2)`, which returns the next datagram with its return address.

An `fcntl(2)` call can be used to specify a process group to receive a `SIGURG` signal when the out-of-band data arrives. It may also enable non-blocking I/O and asynchronous notification of I/O events via `SIGIO`.

The operation of sockets is controlled by socket level *options*. These options are defined in the file `<sys/socket.h>`. `setsockopt(2)` and `getsockopt(2)` are used to set and get options, respectively.

RETURN VALUE

A `-1` is returned if an error occurs, otherwise the return value is a descriptor referencing the socket.

ERRORS

The *socket* call fails if:

[EPROTONOSUPPORT]

The protocol type or the specified protocol is not supported within this domain.

[EMFILE]

The per-process descriptor table is full.

[ENFILE]

The system file table is full.

[EACCESS]

Permission to create a socket of the specified type and/or protocol is denied.

[ENOBUFS]

Insufficient buffer space is available. The socket cannot be created until sufficient resources are freed.

SEE ALSO

`accept(2)`, `bind(2)`, `connect(2)`, `getsockname(2)`, `getsockopt(2)`, `ioctl(2)`, `listen(2)`, `read(2)`, `recv(2)`, `select(2)`, `send(2)`, `shutdown(2)`, `socketpair(2)`, `write(2)`

"An Introductory 4.3BSD Interprocess Communication Tutorial." (reprinted in UNIX Programmer's Supplementary Documents Volume 1, PS1:7) "An Advanced 4.3BSD Interprocess Communication Tutorial." (reprinted in UNIX Programmer's Supplementary Documents Volume 1, PS1:8)

NAME

socketpair – create a pair of connected sockets

SYNOPSIS

```
#include <sys/types.h>
#include <sys/socket.h>

socketpair(d, type, protocol, sv)
int d, type, protocol;
int sv[2];
```

DESCRIPTION

The *socketpair* call creates an unnamed pair of connected sockets in the specified domain *d*, of the specified *type*, and using the optionally specified *protocol*. The descriptors used in referencing the new sockets are returned in *sv*[0] and *sv*[1]. The two sockets are indistinguishable.

DIAGNOSTICS

A 0 is returned if the call succeeds, -1 if it fails.

ERRORS

The call succeeds unless:

- [EMFILE] Too many descriptors are in use by this process.
- [EAFNOSUPPORT] The specified address family is not supported on this machine.
- [EPROTONOSUPPORT] The specified protocol is not supported on this machine.
- [EOPNOSUPPORT] The specified protocol does not support creation of socket pairs.
- [EFAULT] The address *sv* does not specify a valid part of the process address space.

SEE ALSO

read(2), write(2), pipe(2)

BUGS

This call is currently implemented only for the UNIX domain.

NAME

stat, lstat, fstat – get file status

SYNOPSIS

#include <sys/types.h>

#include <sys/stat.h>

stat(path, buf)

char *path;

struct stat *buf;

lstat(path, buf)

char *path;

struct stat *buf;

fstat(fd, buf)

int fd;

struct stat *buf;

DESCRIPTION

Stat obtains information about the file *path*. Read, write or execute permission of the named file is not required, but all directories listed in the path name leading to the file must be reachable.

Lstat is like *stat* except in the case where the named file is a symbolic link, in which case *lstat* returns information about the link, while *stat* returns information about the file the link references.

Fstat obtains the same information about an open file referenced by the argument descriptor, such as would be obtained by an *open* call.

Buf is a pointer to a *stat* structure into which information is placed concerning the file. The contents of the structure pointed to by *buf*

```

struct stat {
    dev_t    st_dev;    /* device inode resides on */
    ino_t    st_ino;    /* this inode's number */
    u_short  st_mode;    /* protection */
    short    st_nlink;   /* number of hard links to the file */
    short    st_uid;     /* user-id of owner */
    short    st_gid;     /* group-id of owner */
    dev_t    st_rdev;    /* the device type, for inode that is device */
    off_t    st_size;    /* total size of file */
    time_t   st_atime;    /* file last access time */
    int      st_spare1;
    time_t   st_mtime;    /* file last modify time */
    int      st_spare2;
    time_t   st_ctime;    /* file last status change time */
    int      st_spare3;
    long     st_blksize; /* optimal blocksize for file system i/o ops */
    long     st_blocks;  /* actual number of blocks allocated */
    long     st_spare4[2];
};

```

st_atime Time when file data was last read or modified. Changed by the following system calls: *mknod(2)*, *utimes(2)*, *read(2)*, and *write(2)*. For reasons of efficiency, *st_atime* is not set when a directory is searched, although this would be more logical.

st_mtime Time when data was last modified. It is not set by changes of owner, group, link count, or mode. Changed by the following system calls: *mknod(2)*, *utimes(2)*, *write(2)*.

st_ctime Time when file status was last changed. It is set both both by writing and changing the i-node. Changed by the following system calls: *chmod(2)*, *chown(2)*, *link(2)*, *mknod(2)*, *rename(2)*, *unlink(2)*, *utimes(2)*, *write(2)*.

The status information word *st_mode* has bits:

```
#define S_IFMT      0170000    /* type of file */
#define S_IFDIR     0040000    /* directory */
#define S_IFCHR     0020000    /* character special */
#define S_IFBLK     0060000    /* block special */
#define S_IFREG     0100000    /* regular */
#define S_IFLNK     0120000    /* symbolic link */
#define S_IFSOCK    0140000    /* socket */
#define S_ISUID     0004000    /* set user id on execution */
#define S_ISGID     0002000    /* set group id on execution */
#define S_ISVTX     0001000    /* save swapped text even after use */
#define S_IREAD     0000400    /* read permission, owner */
#define S_IWRITE    0000200    /* write permission, owner */
#define S_IXEXEC    0000100    /* execute/search permission, owner */
```

The mode bits 0000070 and 0000007 encode group and others permissions (see *chmod(2)*).

RETURN VALUE

Upon successful completion a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Stat and *lstat* will fail if one or more of the following are true:

[ENOTDIR] A component of the path prefix is not a directory.

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] The named file does not exist.

[EACCES] Search permission is denied for a component of the path prefix.

[ELOOP] Too many symbolic links were encountered in translating the pathname.

[EFAULT] *Buf* or *name* points to an invalid address.

[EIO] An I/O error occurred while reading from or writing to the file system.

Fstat will fail if one or both of the following are true:

[EBADF] *Fildes* is not a valid open file descriptor.

[EFAULT] *Buf* points to an invalid address.

[EIO] An I/O error occurred while reading from or writing to the file system.

CAVEAT

The fields in the *stat* structure currently marked *st_spare1*, *st_spare2*, and *st_spare3* are present in preparation for inode time stamps expanding to 64 bits. This, however, can break certain programs that depend on the time stamps being contiguous (in calls to *utimes(2)*).

SEE ALSO

chmod(2), chown(2), utimes(2)

BUGS

Applying *fstat* to a socket (and thus to a pipe) returns a zero'd buffer, except for the blocksize field, and a unique device and inode number.

NAME

swapon – add a swap device for interleaved paging/swapping

SYNOPSIS

```
swapon(special)
char *special;
```

DESCRIPTION

Swapon makes the block device *special* available to the system for allocation for paging and swapping. The names of potentially available devices are known to the system and defined at system configuration time. The size of the swap area on *special* is calculated at the time the device is first made available for swapping.

RETURN VALUE

If an error has occurred, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Swapon succeeds unless:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] The named device does not exist.
- [EACCES] Search permission is denied for a component of the path prefix.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EPERM] The caller is not the super-user.
- [ENOTBLK] *Special* is not a block device.
- [EBUSY] The device specified by *special* has already been made available for swapping
- [EINVAL] The device configured by *special* was not configured into the system as a swap device.
- [ENXIO] The major device number of *special* is out of range (this indicates no device driver exists for the associated hardware).
- [EIO] An I/O error occurred while opening the swap device.
- [EFAULT] *Special* points outside the process's allocated address space.

SEE ALSO

swapon(8), config(8)

BUGS

There is no way to stop swapping on a disk so that the pack may be dismounted.
This call will be upgraded in future versions of the system.

NAME

symlink – make symbolic link to a file

SYNOPSIS

```
symlink(name1, name2)
char *name1, *name2;
```

DESCRIPTION

A symbolic link *name2* is created to *name1* (*name2* is the name of the file created, *name1* is the string used in creating the symbolic link). Either name may be an arbitrary path name; the files need not be on the same file system.

RETURN VALUE

Upon successful completion, a zero value is returned. If an error occurs, the error code is stored in *errno* and a -1 value is returned.

ERRORS

The symbolic link is made unless on or more of the following are true:

- [ENOTDIR] A component of the *name2* prefix is not a directory.
- [EINVAL] Either *name1* or *name2* contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of either pathname exceeded 255 characters, or the entire length of either path name exceeded 1023 characters.
- [ENOENT] The named file does not exist.
- [EACCES] A component of the *name2* path prefix denies search permission.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EEXIST] *Name2* already exists.
- [EIO] An I/O error occurred while making the directory entry for *name2*, or allocating the inode for *name2*, or writing out the link contents of *name2*.
- [EROFS] The file *name2* would reside on a read-only file system.
- [ENOSPC] The directory in which the entry for the new symbolic link is being placed cannot be extended because there is no space left on the file system containing the directory.
- [ENOSPC] The new symbolic link cannot be created because there there is no space left on the file system that will contain the symbolic link.
- [ENOSPC] There are no free inodes on the file system on which the symbolic link is being created.
- [EDQUOT] The directory in which the entry for the new symbolic link is being placed cannot be extended because the user's quota of disk blocks on the file system containing the directory has been exhausted.
- [EDQUOT] The new symbolic link cannot be created because the user's quota of disk blocks on the file system that will contain the symbolic link has been exhausted.
- [EDQUOT] The user's quota of inodes on the file system on which the symbolic link is being created has been exhausted.
- [EIO] An I/O error occurred while making the directory entry or allocating the inode.
- [EFAULT] *Name1* or *name2* points outside the process's allocated address space.

SEE ALSO

link(2), ln(1), unlink(2)

NAME

sync – update super-block

SYNOPSIS

sync()

DESCRIPTION

Sync causes all information in core memory that should be on disk to be written out. This includes modified super blocks, modified i-nodes, and delayed block I/O.

Sync should be used by programs that examine a file system, for example *fsck*, *df*, etc. *Sync* is mandatory before a boot.

SEE ALSO

fsync(2), sync(8), update(8)

BUGS

The writing, although scheduled, is not necessarily complete upon return from *sync*.

NAME

syscall – indirect system call

SYNOPSIS

#include <syscall.h>

syscall(number, arg, ...) (VAX-11)

DESCRIPTION

Syscall performs the system call whose assembly language interface has the specified *number*, register arguments *r0* and *r1* and further arguments *arg*. Symbolic constants for system calls can be found in the header file <syscall.h>.

The *r0* value of the system call is returned.

DIAGNOSTICS

When the C-bit is set, *syscall* returns -1 and sets the external variable *errno* (see *intro(2)*).

BUGS

There is no way to simulate system calls such as *pipe(2)*, which return values in register *r1*.

NAME

truncate – truncate a file to a specified length

SYNOPSIS

```
truncate(path, length)
```

```
char *path;
```

```
off_t length;
```

```
ftruncate(fd, length)
```

```
int fd;
```

```
off_t length;
```

DESCRIPTION

Truncate causes the file named by *path* or referenced by *fd* to be truncated to at most *length* bytes in size. If the file previously was larger than this size, the extra data is lost. With *ftruncate*, the file must be open for writing.

RETURN VALUES

A value of 0 is returned if the call succeeds. If the call fails a -1 is returned, and the global variable *errno* specifies the error.

ERRORS

Truncate succeeds unless:

[ENOTDIR] A component of the path prefix is not a directory.

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG]

A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] The named file does not exist.

[EACCES] Search permission is denied for a component of the path prefix.

[EACCES] The named file is not writable by the user.

[ELOOP] Too many symbolic links were encountered in translating the pathname.

[EISDIR] The named file is a directory.

[EROFS] The named file resides on a read-only file system.

[ETXTBSY] The file is a pure procedure (shared text) file that is being executed.

[EIO] An I/O error occurred updating the inode.

[EFAULT] *Path* points outside the process's allocated address space.

Ftruncate succeeds unless:

[EBADF] The *fd* is not a valid descriptor.

[EINVAL] The *fd* references a socket, not a file.

[EINVAL] The *fd* is not open for writing.

SEE ALSO

open(2)

BUGS

These calls should be generalized to allow ranges of bytes in a file to be discarded.

NAME

umask – set file creation mode mask

SYNOPSIS

```
oumask = umask(numask)  
int oumask, numask;
```

DESCRIPTION

Umask sets the process's file mode creation mask to *numask* and returns the previous value of the mask. The low-order 9 bits of *numask* are used whenever a file is created, clearing corresponding bits in the file mode (see *chmod*(2)). This clearing allows each user to restrict the default access to his files.

The value is initially 022 (write access for owner only). The mask is inherited by child processes.

RETURN VALUE

The previous value of the file mode mask is returned by the call.

SEE ALSO

chmod(2), *mknod*(2), *open*(2)

NAME

unlink – remove directory entry

SYNOPSIS

```
unlink(path)
char *path;
```

DESCRIPTION

Unlink removes the entry for the file *path* from its directory. If this entry was the last link to the file, and no process has the file open, then all resources associated with the file are reclaimed. If, however, the file was open in any process, the actual resource reclamation is delayed until it is closed, even though the directory entry has disappeared.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

The *unlink* succeeds unless:

- [ENOTDIR] A component of the path prefix is not a directory.
- [EINVAL] The pathname contains a character with the high-order bit set.
- [ENAMETOOLONG] A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.
- [ENOENT] The named file does not exist.
- [EACCES] Search permission is denied for a component of the path prefix.
- [EACCES] Write permission is denied on the directory containing the link to be removed.
- [ELOOP] Too many symbolic links were encountered in translating the pathname.
- [EPERM] The named file is a directory and the effective user ID of the process is not the super-user.
- [EPERM] The directory containing the file is marked sticky, and neither the containing directory nor the file to be removed are owned by the effective user ID.
- [EBUSY] The entry to be unlinked is the mount point for a mounted file system.
- [EIO] An I/O error occurred while deleting the directory entry or deallocating the inode.
- [EROFS] The named file resides on a read-only file system.
- [EFAULT] *Path* points outside the process's allocated address space.

SEE ALSO

close(2), link(2), rmdir(2)

NAME

utimes – set file times

SYNOPSIS

#include <sys/time.h>

utimes(file, tvp)

char *file;

struct timeval tvp[2];

DESCRIPTION

The *utimes* call uses the “accessed” and “updated” times in that order from the *tvp* vector to set the corresponding recorded times for *file*.

The caller must be the owner of the file or the super-user. The “inode-changed” time of the file is set to the current time.

RETURN VALUE

Upon successful completion, a value of 0 is returned. Otherwise, a value of -1 is returned and *errno* is set to indicate the error.

ERRORS

Utime will fail if one or more of the following are true:

[ENOTDIR] A component of the path prefix is not a directory.

[EINVAL] The pathname contains a character with the high-order bit set.

[ENAMETOOLONG]

A component of a pathname exceeded 255 characters, or an entire path name exceeded 1023 characters.

[ENOENT] The named file does not exist.

[ELOOP] Too many symbolic links were encountered in translating the pathname.

[EPERM] The process is not super-user and not the owner of the file.

[EACCES] Search permission is denied for a component of the path prefix.

[EROFS] The file system containing the file is mounted read-only.

[EFAULT] *File* or *tvp* points outside the process's allocated address space.

[EIO] An I/O error occurred while reading or writing the affected inode.

SEE ALSO

stat(2)

NAME

vfork – spawn new process in a virtual memory efficient way

SYNOPSIS

```
pid = vfork()
int pid;
```

DESCRIPTION

Vfork can be used to create new processes without fully copying the address space of the old process, which is horrendously inefficient in a paged environment. It is useful when the purpose of *fork(2)* would have been to create a new system context for an *execve*. *Vfork* differs from *fork* in that the child borrows the parent's memory and thread of control until a call to *execve(2)* or an exit (either by a call to *exit(2)* or abnormally.) The parent process is suspended while the child is using its resources.

Vfork returns 0 in the child's context and (later) the pid of the child in the parent's context.

Vfork can normally be used just like *fork*. It does not work, however, to return while running in the child's context from the procedure that called *vfork* since the eventual return from *vfork* would then return to a no longer existent stack frame. Be careful, also, to call *_exit* rather than *exit* if you can't *execve*, since *exit* will flush and close standard I/O channels, and thereby mess up the parent processes standard I/O data structures. (Even with *fork* it is wrong to call *exit* since buffered data would then be flushed twice.)

SEE ALSO

fork(2), *execve(2)*, *sigvec(2)*, *wait(2)*,

DIAGNOSTICS

Same as for *fork*.

BUGS

This system call will be eliminated when proper system sharing mechanisms are implemented. Users should not depend on the memory sharing semantics of *vfork* as it will, in that case, be made synonymous to *fork*.

To avoid a possible deadlock situation, processes that are children in the middle of a *vfork* are never sent SIGTTOU or SIGTTIN signals; rather, output or *ioctl*s are allowed and input attempts result in an end-of-file indication.

NAME

vhangup – virtually “hangup” the current control terminal

SYNOPSIS

vhangup()

DESCRIPTION

Vhangup is used by the initialization process *init*(8) (among others) to arrange that users are given “clean” terminals at login, by revoking access of the previous users’ processes to the terminal. To effect this, *vhangup* searches the system tables for references to the control terminal of the invoking process, revoking access permissions on each instance of the terminal that it finds. Further attempts to access the terminal by the affected processes will yield i/o errors (EBADF). Finally, a hangup signal (SIGHUP) is sent to the process group of the control terminal.

SEE ALSO

init (8)

BUGS

Access to the control terminal via */dev/tty* is still possible.

This call should be replaced by an automatic mechanism that takes place on process exit.

NAME

`wait`, `wait3` – wait for process to terminate

SYNOPSIS

```
#include <sys/wait.h>

pid = wait(status)
int pid;
union wait *status;

pid = wait(0)
int pid;

#include <sys/time.h>
#include <sys/resource.h>

pid = wait3(status, options, rusage)
int pid;
union wait *status;
int options;
struct rusage *rusage;
```

DESCRIPTION

Wait causes its caller to delay until a signal is received or one of its child processes terminates. If any child has died since the last *wait*, return is immediate, returning the process id and exit status of one of the terminated children. If there are no children, return is immediate with the value -1 returned.

On return from a successful *wait* call, *status* is nonzero, and the high byte of *status* contains the low byte of the argument to *exit* supplied by the child process; the low byte of *status* contains the termination status of the process. A more precise definition of the *status* word is given in *<sys/wait.h>*.

Wait3 provides an alternate interface for programs that must not block when collecting the status of child processes. The *status* parameter is defined as above. The *options* parameter is used to indicate the call should not block if there are no processes that wish to report status (WNOHANG), and/or that children of the current process that are stopped due to a SIGTTIN, SIGTTOU, SIGTSTP, or SIGSTOP signal should also have their status reported (WUNTRACED). If *rusage* is non-zero, a summary of the resources used by the terminated process and all its children is returned (this information is currently not available for stopped processes).

When the WNOHANG option is specified and no processes wish to report status, *wait3* returns a *pid* of 0. The WNOHANG and WUNTRACED options may be combined by *or'ing* the two values.

NOTES

See *sigvec(2)* for a list of termination statuses (signals); 0 status indicates normal termination. A special status (0177) is returned for a stopped process that has not terminated and can be restarted; see *ptrace(2)*. If the 0200 bit of the termination status is set, a core image of the process was produced by the system.

If the parent process terminates without waiting on its children, the initialization process (process ID = 1) inherits the children.

Wait and *wait3* are automatically restarted when a process receives a signal while awaiting termination of a child process.

RETURN VALUE

If *wait* returns due to a stopped or terminated child process, the process ID of the child is returned to the calling process. Otherwise, a value of -1 is returned and *errno* is set to

indicate the error.

Wait3 returns -1 if there are no children not previously waited for; 0 is returned if WNOHANG is specified and there are no stopped or exited children.

ERRORS

Wait will fail and return immediately if one or more of the following are true:

- [ECHILD] The calling process has no existing unwaited-for child processes.
- [EFAULT] The *status* or *usage* arguments point to an illegal address.

SEE ALSO

exit(2)

NAME

write, writev – write output

SYNOPSIS

```
cc = write(d, buf, nbytes)
int cc, d;
char *buf;
int nbytes;
```

```
#include <sys/types.h>
#include <sys/uio.h>
```

```
cc = writev(d, iov, iovcnt)
int cc, d;
struct iovec *iov;
int iovcnt;
```

DESCRIPTION

Write attempts to write *nbytes* of data to the object referenced by the descriptor *d* from the buffer pointed to by *buf*. *Writev* performs the same action, but gathers the output data from the *iovcnt* buffers specified by the members of the *iov* array: *iov*[0], *iov*[1], ..., *iov*[*iovcnt* - 1].

For *writev*, the *iovec* structure is defined as

```
struct iovec {
    caddr_t iov_base;
    int      iov_len;
};
```

Each *iovec* entry specifies the base address and length of an area in memory from which data should be written. *Writev* will always write a complete area before proceeding to the next.

On objects capable of seeking, the *write* starts at a position given by the pointer associated with *d*, see *lseek*(2). Upon return from *write*, the pointer is incremented by the number of bytes actually written.

Objects that are not capable of seeking always write from the current position. The value of the pointer associated with such an object is undefined.

If the real user is not the super-user, then *write* clears the set-user-id bit on a file. This prevents penetration of system security by a user who "captures" a writable set-user-id file owned by the super-user.

When using non-blocking I/O on objects such as sockets that are subject to flow control, *write* and *writev* may write fewer bytes than requested; the return value must be noted, and the remainder of the operation should be retried when possible.

RETURN VALUE

Upon successful completion the number of bytes actually written is returned. Otherwise a -1 is returned and the global variable *errno* is set to indicate the error.

ERRORS

Write and *writev* will fail and the file pointer will remain unchanged if one or more of the following are true:

- [EBADF] *D* is not a valid descriptor open for writing.
- [EPIPE] An attempt is made to write to a pipe that is not open for reading by any process.
- [EPIPE] An attempt is made to write to a socket of type SOCK_STREAM that is not connected to a peer socket.

- [EFBIG] An attempt was made to write a file that exceeds the process's file size limit or the maximum file size.
- [EFAULT] Part of *iov* or data to be written to the file points outside the process's allocated address space.
- [EINVAL] The pointer associated with *d* was negative.
- [ENOSPC] There is no free space remaining on the file system containing the file.
- [EDQUOT] The user's quota of disk blocks on the file system containing the file has been exhausted.
- [EIO] An I/O error occurred while reading from or writing to the file system.
- [EWOULDBLOCK] The file was marked for non-blocking I/O, and no data could be written immediately.

In addition, *writew* may return one of the following errors:

- [EINVAL] *iovcnt* was less than or equal to 0, or greater than 16.
- [EINVAL] One of the *iov_len* values in the *iov* array was negative.
- [EINVAL] The sum of the *iov_len* values in the *iov* array overflowed a 32-bit integer.

SEE ALSO

`fcntl(2)`, `lseek(2)`, `open(2)`, `pipe(2)`, `select(2)`

NAME

intro – introduction to C library functions

DESCRIPTION

This section describes functions that may be found in various libraries. The library functions are those other than the functions which directly invoke UNIX system primitives, described in section 2. Most of these functions are accessible from the C library, *libc*, which is automatically loaded by the C compiler *cc*(1), and the Pascal compiler *pc*(1). The link editor *ld*(1) searches this library under the '-lc' option. The C library also includes all the functions described in section 2.

A subset of these functions are available from Fortran; they are described separately in *intro*(3F).

The functions described in this section are grouped into various sections:

- (3) The straight "3" functions are the standard C library functions.
- (3N) These functions constitute the internet network library.
- (3S) These functions constitute the 'standard I/O package', see *stdio*(3S) for more details. Declarations for these functions may be obtained from the include file *<stdio.h>*.
- (3C) These routines are included for compatibility with other systems. In particular, a number of system call interfaces provided in previous releases of 4BSD have been included for source code compatibility. Use of these routines should, for the most part, be avoided. The manual page entry for each compatibility routine indicates the proper interface to use.
- (3M) These functions constitute the math library, *libm*. When functions in the math library (see *math*(3M)) are passed values that are undefined or would generate answers that are out of range, they call the *infnan* routine. By default this routine returns the VAX reserved floating point value which causes the process to get a floating point exception (see *sigvec*(2)). Programs that wish to take other action should define their own version of *infnan* (see *infnan*(3M) for details). The math library is loaded as needed by the Pascal compiler *pc*(1). C programs that wish to use this library need to specify the "-lm" option.
- (3X) These functions constitute minor libraries and other miscellaneous run-time facilities. Most are available only when programming in C. These functions include libraries that provide device independent plotting functions, terminal independent screen management routines for two dimensional non-bitmap display terminals, and functions for managing data bases with inverted indexes. These functions are located in separate libraries indicated in each manual entry.

FILES

/lib/libc.a	the C library
/usr/lib/libm.a	the math library
/usr/lib/libc_p.a	the C library compiled for profiling
/usr/lib/libm_p.a	the math library compiled for profiling

SEE ALSO

stdio(3S), *math*(3M), *intro*(2), *cc*(1), *ld*(1), *nm*(1)

LIST OF FUNCTIONS

Name	Appears on Page	Description
abort	abort.3	generate a fault
abs	abs.3	integer absolute value
acos	sin.3m	inverse trigonometric function
acosh	asinh.3m	inverse hyperbolic function

P
R
M
3

alarm	alarm.3c	schedule signal after specified time
alloca	malloc.3	memory allocator
arc	plot.3x	graphics interface
asctime	ctime.3	convert date and time to ASCII
asin	sin.3m	inverse trigonometric function
asinh	asinh.3m	inverse hyperbolic function
assert	assert.3x	program verification
atan	sin.3m	inverse trigonometric function
atanh	asinh.3m	inverse hyperbolic function
atan2	sin.3m	inverse trigonometric function
atof	atof.3	convert ASCII to numbers
atoi	atof.3	convert ASCII to numbers
atol	atof.3	convert ASCII to numbers
bcmp	bstring.3	bit and byte string operations
bcopy	bstring.3	bit and byte string operations
bzero	bstring.3	bit and byte string operations
cabs	hypot.3m	complex absolute value
calloc	malloc.3	memory allocator
cbrt	sqrt.3m	cube root
ceil	floor.3m	integer no less than
circle	plot.3x	graphics interface
clearerr	ferror.3s	stream status inquiries
closedir	directory.3	directory operations
closelog	syslog.3	control system log
closepl	plot.3x	graphics interface
cont	plot.3x	graphics interface
copysign	ieee.3m	copy sign bit
cos	sin.3m	trigonometric function
cosh	sinh.3m	hyperbolic function
crypt	crypt.3	DES encryption
ctime	ctime.3	convert date and time to ASCII
curses	curses.3x	screen functions with "optimal" cursor motion
dbminit	dbm.3x	data base subroutines
delete	dbm.3x	data base subroutines
drem	ieee.3m	remainder
ecvt	ecvt.3	output conversion
edata	end.3	last locations in program
encrypt	crypt.3	DES encryption
end	end.3	last locations in program
endfsent	getfsent.3x	get file system descriptor file entry
endgrent	getgrent.3	get group file entry
endhostent	gethostbyname.3n	get network host entry
endnetent	getnetent.3n	get network entry
endprotoent	getprotoent.3n	get protocol entry
endpwent	getpwent.3	get password file entry
endservent	getservent.3n	get service entry
environ	execl.3	execute a file
erase	plot.3x	graphics interface
erf	erf.3m	error function
erfc	erf.3m	complementary error function
etext	end.3	last locations in program
exec	execl.3	execute a file
exece	execl.3	execute a file

execl	execl.3	execute a file
execle	execle.3	execute a file
execlp	execlp.3	execute a file
exec	exec.3	execute a file
execv	execv.3	execute a file
execvp	execv.3	execute a file
exit	exit.3	terminate a process after flushing any pending output
exp	exp.3m	exponential
expm1	exp.3m	exp(x)-1
fabs	floor.3m	absolute value
fclose	fclose.3s	close or flush a stream
fcvt	ecvt.3	output conversion
feof	ferror.3s	stream status inquiries
ferror	ferror.3s	stream status inquiries
fetch	dbm.3x	data base subroutines
fflush	fclose.3s	close or flush a stream
ffs	bstring.3	bit and byte string operations
fgetc	getc.3s	get character or word from stream
fgets	gets.3s	get a string from a stream
fileno	ferror.3s	stream status inquiries
firstkey	dbm.3x	data base subroutines
floor	floor.3m	integer no greater than
fopen	fopen.3s	open a stream
fprintf	printf.3s	formatted output conversion
fputc	putc.3s	put character or word on a stream
fputs	puts.3s	put a string on a stream
fread	fread.3s	buffered binary input/output
free	malloc.3	memory allocator
frexp	frexp.3	split into mantissa and exponent
fscanf	scanf.3s	formatted input conversion
fseek	fseek.3s	reposition a stream
ftell	fseek.3s	reposition a stream
ftime	time.3c	get date and time
fwrite	fread.3s	buffered binary input/output
gcvt	ecvt.3	output conversion
getc	getc.3s	get character or word from stream
getchar	getc.3s	get character or word from stream
getdiskbyname	getdisk.3x	get disk description by its name
getenv	getenv.3	value for environment name
getfsent	getfsent.3x	get file system descriptor file entry
getfsfile	getfsent.3x	get file system descriptor file entry
getfsspec	getfsent.3x	get file system descriptor file entry
getfstype	getfsent.3x	get file system descriptor file entry
getgrent	getgrent.3	get group file entry
getgrgid	getgrent.3	get group file entry
getgrnam	getgrent.3	get group file entry
gethostbyaddr	gethostbyname.3n	get network host entry
gethostbyname	gethostbyname.3n	get network host entry
gethostent	gethostbyname.3n	get network host entry
getlogin	getlogin.3	get login name
getnetbyaddr	getnetent.3n	get network entry
getnetbyname	getnetent.3n	get network entry
getnetent	getnetent.3n	get network entry

getpass	getpass.3	read a password
getprotobyname	getprotoent.3n	get protocol entry
getprotobynumber	getprotoent.3n	get protocol entry
getprotoent	getprotoent.3n	get protocol entry
getpw	getpw.3	get name from uid
getpwent	getpwent.3	get password file entry
getpwnam	getpwent.3	get password file entry
getpwuid	getpwent.3	get password file entry
gets	gets.3s	get a string from a stream
getservbyname	getservent.3n	get service entry
getservbyport	getservent.3n	get service entry
getservent	getservent.3n	get service entry
getw	getc.3s	get character or word from stream
getwd	getwd.3	get current working directory pathname
gmtime	ctime.3	convert date and time to ASCII
gtty	stty.3c	set and get terminal state (defunct)
htonl	byteorder.3n	convert values between host and network byte order
htons	byteorder.3n	convert values between host and network byte order
hypot	hypot.3m	Euclidean distance
index	string.3	string operations
inet_addr	inet.3n	Internet address manipulation routines
inet_lnaof	inet.3n	Internet address manipulation routines
inet_makeaddr	inet.3n	Internet address manipulation routines
inet_netof	inet.3n	Internet address manipulation routines
inet_network	inet.3n	Internet address manipulation routines
infnan	infnan.3m	signals exceptions
initgroups	initgroups.3x	initialize group access list
initstate	random.3	better random number generator
insque	insque.3	insert/remove element from a queue
isalnum	ctype.3	character classification macros
isalpha	ctype.3	character classification macros
isascii	ctype.3	character classification macros
isatty	ttyname.3	find name of a terminal
iscntrl	ctype.3	character classification macros
isdigit	ctype.3	character classification macros
islower	ctype.3	character classification macros
isprint	ctype.3	character classification macros
ispunct	ctype.3	character classification macros
isspace	ctype.3	character classification macros
isupper	ctype.3	character classification macros
j0	j0.3m	bessel function
j1	j0.3m	bessel function
jn	j0.3m	bessel function
label	plot.3x	graphics interface
ldexp	frexp.3	split into mantissa and exponent
lgamma	lgamma.3m	log gamma function; (formerly gamma.3m)
lib2648	lib2648.3x	subroutines for the HP 2648 graphics terminal
line	plot.3x	graphics interface
linemod	plot.3x	graphics interface
localtime	ctime.3	convert date and time to ASCII
log	exp.3m	natural logarithm
logb	ieee.3m	exponent extraction
log10	exp.3m	logarithm to base 10

loglp	exp.3m	log(1+x)
longjmp	setjmp.3	non-local goto
malloc	malloc.3	memory allocator
mktemp	mktemp.3	make a unique file name
modf	frexp.3	split into mantissa and exponent
moncontrol	monitor.3	prepare execution profile
monitor	monitor.3	prepare execution profile
monstartup	monitor.3	prepare execution profile
move	plot.3x	graphics interface
nextkey	dbm.3x	data base subroutines
nice	nice.3c	set program priority
nlist	nlist.3	get entries from name list
ntohl	byteorder.3n	convert values between host and network byte order
ntohs	byteorder.3n	convert values between host and network byte order
opendir	directory.3	directory operations
openlog	syslog.3	control system log
openpl	plot.3x	graphics interface
pause	pause.3c	stop until signal
pclose	popen.3	initiate I/O to/from a process
perror	perror.3	system error messages
point	plot.3x	graphics interface
popen	popen.3	initiate I/O to/from a process
pow	exp.3m	exponential x**y
printf	printf.3s	formatted output conversion
psignal	psignal.3	system signal messages
putc	putc.3s	put character or word on a stream
putchar	putc.3s	put character or word on a stream
puts	puts.3s	put a string on a stream
putw	putc.3s	put character or word on a stream
qsort	qsort.3	quicker sort
rand	rand.3c	random number generator
random	random.3	better random number generator
rcmd	rcmd.3x	routines for returning a stream to a remote command
re_comp	regex.3	regular expression handler
re_exec	regex.3	regular expression handler
readdir	directory.3	directory operations
realloc	malloc.3	memory allocator
remque	insque.3	insert/remove element from a queue
rewind	fseek.3s	reposition a stream
rewinddir	directory.3	directory operations
rexec	rexec.3x	return stream to a remote command
rindex	string.3	string operations
rint	floor.3m	round to nearest integer
rresvport	rcmd.3x	routines for returning a stream to a remote command
ruserok	rcmd.3x	routines for returning a stream to a remote command
scalb	ieee.3m	exponent adjustment
scandir	scandir.3	scan a directory
scanf	scanf.3s	formatted input conversion
seekdir	directory.3	directory operations
setbuf	setbuf.3s	assign buffering to a stream
setbuffer	setbuf.3s	assign buffering to a stream
setgid	setuid.3	set user and group ID
setuid	setuid.3	set user and group ID

setfsent	getfsent.3x	get file system descriptor file entry
setgid	setuid.3	set user and group ID
setgrent	getgrent.3	get group file entry
sethostent	gethostbyname.3n	get network host entry
setjmp	setjmp.3	non-local goto
setkey	crypt.3	DES encryption
setlinebuf	setbuf.3s	assign buffering to a stream
setnetent	getnetent.3n	get network entry
setprotoent	getprotoent.3n	get protocol entry
setpwent	getpwent.3	get password file entry
setrgid	setuid.3	set user and group ID
setruid	setuid.3	set user and group ID
setservent	getservent.3n	get service entry
setstate	random.3	better random number generator
setuid	setuid.3	set user and group ID
signal	signal.3	simplified software signal facilities
sin	sin.3m	trigonometric function
sinh	sinh.3m	hyperbolic function
sleep	sleep.3	suspend execution for interval
space	plot.3x	graphics interface
sprintf	printf.3s	formatted output conversion
sqrt	sqrt.3m	square root
srand	rand.3c	random number generator
random	random.3	better random number generator
sscanf	scanf.3s	formatted input conversion
stdio	intro.3s	standard buffered input/output package
store	dbm.3x	data base subroutines
strcat	string.3	string operations
strcmp	string.3	string operations
strcpy	string.3	string operations
strlen	string.3	string operations
strncat	string.3	string operations
strncmp	string.3	string operations
strncpy	string.3	string operations
stty	stty.3c	set and get terminal state (defunct)
swab	swab.3	swap bytes
sys_errlist	perror.3	system error messages
sys_nerr	perror.3	system error messages
sys_siglist	psignal.3	system signal messages
syslog	syslog.3	control system log
system	system.3	issue a shell command
tan	sin.3m	trigonometric function
tanh	sinh.3m	hyperbolic function
telldir	directory.3	directory operations
tgetent	termcap.3x	terminal independent operation routines
tgetflag	termcap.3x	terminal independent operation routines
tgetnum	termcap.3x	terminal independent operation routines
tgetstr	termcap.3x	terminal independent operation routines
tgoto	termcap.3x	terminal independent operation routines
time	time.3c	get date and time
times	times.3c	get process times
timezone	ctime.3	convert date and time to ASCII
tputs	termcap.3x	terminal independent operation routines

ttynname	ttynname.3	find name of a terminal
ttyslot	ttynname.3	find name of a terminal
ungetc	ungetc.3s	push character back into input stream
utime	utime.3c	set file times
valloc	valloc.3	aligned memory allocator
varargs	varargs.3	variable argument list
vlimit	vlimit.3c	control maximum system resource consumption
vtimes	vtimes.3c	get information about resource utilization
y0	j0.3m	bessel function
y1	j0.3m	bessel function
yn	j0.3m	bessel function

NAME

abort – generate a fault

DESCRIPTION

Abort executes an instruction which is illegal in user mode. This causes a signal that normally terminates the process with a core dump, which may be used for debugging.

SEE ALSO

adb(1), sigvec(2), exit(2)

DIAGNOSTICS

Usually “Illegal instruction – core dumped” from the shell.

BUGS

The abort() function does not flush standard I/O buffers. Use *fflush*(3S).

P
R
M
3

NAME

abs – integer absolute value

SYNOPSIS

abs(i)
int i;

DESCRIPTION

Abs returns the absolute value of its integer operand.

SEE ALSO

floor(3M) for *fabs*

BUGS

Applying the *abs* function to the most negative integer generates a result which is the most negative integer. That is,

abs(0x80000000)

returns 0x80000000 as a result.

NAME

alarm – schedule signal after specified time

SYNOPSIS

alarm(seconds)
unsigned seconds;

DESCRIPTION

This interface is made obsolete by `setitimer(2)`.

Alarm causes signal `SIGALRM`, see `sigvec(2)`, to be sent to the invoking process in a number of seconds given by the argument. Unless caught or ignored, the signal terminates the process.

Alarm requests are not stacked; successive calls reset the alarm clock. If the argument is 0, any alarm request is canceled. Because of scheduling delays, resumption of execution of when the signal is caught may be delayed an arbitrary amount. The longest specifiable delay time is 2147483647 seconds.

The return value is the amount of time previously remaining in the alarm clock.

SEE ALSO

`sigpause(2)`, `sigvec(2)`, `signal(3C)`, `sleep(3)`, `ualarm(3)`, `usleep(3)`

P
R
M 3

NAME

asinh, acosh, atanh – inverse hyperbolic functions

SYNOPSIS

```
#include <math.h>
```

```
double asinh(x)
```

```
double x;
```

```
double acosh(x)
```

```
double x;
```

```
double atanh(x)
```

```
double x;
```

DESCRIPTION

These functions compute the designated inverse hyperbolic functions for real arguments.

ERROR (due to Roundoff etc.)

These functions inherit much of their error from `log1p` described in `exp(3M)`. On a VAX, `acosh` is accurate to about 3 *ulps*, `asinh` and `atanh` to about 2 *ulps*. An *ulp* is one *Unit* in the *Last Place* carried.

DIAGNOSTICS

`Acosh` returns the reserved operand on a VAX if the argument is less than 1.

`Atanh` returns the reserved operand on a VAX if the argument has absolute value bigger than or equal to 1.

SEE ALSO

`math(3M)`, `exp(3M)`, `infnan(3M)`

AUTHOR

W. Kahan, Kwok-Choi Ng

NAME

assert – program verification

SYNOPSIS

```
#include <assert.h>
```

```
assert(expression)
```

DESCRIPTION

Assert is a macro that indicates *expression* is expected to be true at this point in the program. It causes an *exit(2)* with a diagnostic comment on the standard output when *expression* is false (0). Compiling with the *cc(1)* option *-DNDEBUG* effectively deletes *assert* from the program.

DIAGNOSTICS

'Assertion failed: file *f* line *n*.' *F* is the source file and *n* the source line number of the *assert* statement.

P
R
M
3

NAME

atof, atoi, atol – convert ASCII to numbers

SYNOPSIS

```
double atof(nptr)
```

```
char *nptr;
```

```
atoi(nptr)
```

```
char *nptr;
```

```
long atol(nptr)
```

```
char *nptr;
```

DESCRIPTION

These functions convert a string pointed to by *nptr* to floating, integer, and long integer representation respectively. The first unrecognized character ends the string.

Atof recognizes an optional string of spaces, then an optional sign, then a string of digits optionally containing a decimal point, then an optional 'e' or 'E' followed by an optionally signed integer.

Atoi and *atol* recognize an optional string of spaces, then an optional sign, then a string of digits.

SEE ALSO

scanf(3S)

BUGS

There are no provisions for overflow.

NAME

bcopy, *bcmp*, *bzero*, *ffs* – bit and byte string operations

SYNOPSIS

bcopy(*src*, *dst*, *length*)

char **src*, **dst*;

int *length*;

bcmp(*b1*, *b2*, *length*)

char **b1*, **b2*;

int *length*;

bzero(*b*, *length*)

char **b*;

int *length*;

ffs(*i*)

int *i*;

DESCRIPTION

The functions *bcopy*, *bcmp*, and *bzero* operate on variable length strings of bytes. They do not check for null bytes as the routines in *string*(3) do.

Bcopy copies *length* bytes from string *src* to the string *dst*.

Bcmp compares byte string *b1* against byte string *b2*, returning zero if they are identical, non-zero otherwise. Both strings are assumed to be *length* bytes long.

Bzero places *length* 0 bytes in the string *b1*.

Ffs find the first bit set in the argument passed it and returns the index of that bit. Bits are numbered starting at 1. A return value of 0 indicates the value passed is zero.

BUGS

The *bcopy* routine take parameters backwards from *strcpy*.

NAME

htonl, htons, ntohl, ntohs – convert values between host and network byte order

SYNOPSIS

```
#include <sys/types.h>
#include <netinet/in.h>

netlong = htonl(hostlong);
u_long netlong, hostlong;

netshort = htons(hostshort);
u_short netshort, hostshort;

hostlong = ntohl(netlong);
u_long hostlong, netlong;

hostshort = ntohs(netshort);
u_short hostshort, netshort;
```

DESCRIPTION

These routines convert 16 and 32 bit quantities between network byte order and host byte order. On machines such as the SUN these routines are defined as null macros in the include file *<netinet/in.h>*.

These routines are most often used in conjunction with Internet addresses and ports as returned by *gethostbyname(3N)* and *getservent(3N)*.

SEE ALSO

gethostbyname(3N), *getservent(3N)*

BUGS

The VAX handles bytes backwards from most everyone else in the world. This is not expected to be fixed in the near future.

NAME

crypt, *setkey*, *encrypt* – DES encryption

SYNOPSIS

```
char *crypt(key, salt)
char *key, *salt;

setkey(key)
char *key;

encrypt(block, edflag)
char *block;
```

DESCRIPTION

Crypt is the password encryption routine. It is based on the NBS Data Encryption Standard, with variations intended (among other things) to frustrate use of hardware implementations of the DES for key search.

The first argument to *crypt* is normally a user's typed password. The second is a 2-character string chosen from the set [a-zA-Z0-9./]. The *salt* string is used to perturb the DES algorithm in one of 4096 different ways, after which the password is used as the key to encrypt repeatedly a constant string. The returned value points to the encrypted password, in the same alphabet as the salt. The first two characters are the salt itself.

The other entries provide (rather primitive) access to the actual DES algorithm. The argument of *setkey* is a character array of length 64 containing only the characters with numerical value 0 and 1. If this string is divided into groups of 8, the low-order bit in each group is ignored, leading to a 56-bit key which is set into the machine.

The argument to the *encrypt* entry is likewise a character array of length 64 containing 0's and 1's. The argument array is modified in place to a similar array representing the bits of the argument after having been subjected to the DES algorithm using the key set by *setkey*. If *edflag* is 0, the argument is encrypted; if non-zero, it is decrypted.

SEE ALSO

passwd(1), *passwd*(5), *login*(1), *getpass*(3)

BUGS

The return value points to static data whose content is overwritten by each call.

NAME

ctime, localtime, gmtime, asctime, timezone – convert date and time to ASCII

SYNOPSIS

```
char *ctime(clock)
long *clock;

#include <time.h>

struct tm *localtime(clock)
long *clock;

struct tm *gmtime(clock)
long *clock;

char *asctime(tm)
struct tm *tm;

char *timezone(zone, dst)
```

DESCRIPTION

Ctime converts a time pointed to by *clock* such as returned by *time(2)* into ASCII and returns a pointer to a 26-character string in the following form. All the fields have constant width.

Sun Sep 16 01:03:52 1973\n\0

Localtime and *gmtime* return pointers to structures containing the broken-down time. *Localtime* corrects for the time zone and possible daylight savings time; *gmtime* converts directly to GMT, which is the time UNIX uses. *Asctime* converts a broken-down time to ASCII and returns a pointer to a 26-character string.

The structure declaration from the include file is:

```
struct tm {
    int tm_sec;      /* 0-59 seconds */
    int tm_min;      /* 0-59 minutes */
    int tm_hour;     /* 0-23 hour */
    int tm_mday;     /* 1-31 day of month */
    int tm_mon;      /* 0-11 month */
    int tm_year;     /* 0- year - 1900 */
    int tm_wday;     /* 0-6 day of week (Sunday = 0) */
    int tm_yday;     /* 0-365 day of year */
    int tm_isdst;    /* flag: daylight savings time in effect */
};
```

When local time is called for, the program consults the system to determine the time zone and whether the U.S.A., Australian, Eastern European, Middle European, or Western European daylight saving time adjustment is appropriate. The program knows about various peculiarities in time conversion over the past 10-20 years; if necessary, this understanding can be extended.

Timezone returns the name of the time zone associated with its first argument, which is measured in minutes westward from Greenwich. If the second argument is 0, the standard name is used, otherwise the Daylight Saving version. If the required name does not appear in a table built into the routine, the difference from GMT is produced; e.g., in Afghanistan *timezone(-60*4+30, 0)* is appropriate because it is 4:30 ahead of GMT and the string GMT+4:30 is produced.

SEE ALSO

gettimeofday(2), time(3)

BUGS

The return values point to static data whose content is overwritten by each call.

NAME

isalpha, *isupper*, *islower*, *isdigit*, *isxdigit*, *isalnum*, *isspace*, *ispunct*, *isprint*, *isgraph*, *isctrl*, *isascii*, *toupper*, *tolower*, *toascii* – character classification macros

SYNOPSIS

```
#include <ctype.h>
```

```
isalpha(c)
```

```
...
```

DESCRIPTION

These macros classify ASCII-coded integer values by table lookup. Each is a predicate returning nonzero for true, zero for false. *isascii* and *toascii* are defined on all integer values; the rest are defined only where *isascii* is true and on the single non-ASCII value EOF (see *stdio(3S)*).

<i>isalpha</i>	<i>c</i> is a letter
<i>isupper</i>	<i>c</i> is an upper case letter
<i>islower</i>	<i>c</i> is a lower case letter
<i>isdigit</i>	<i>c</i> is a digit
<i>isxdigit</i>	<i>c</i> is a hex digit
<i>isalnum</i>	<i>c</i> is an alphanumeric character
<i>isspace</i>	<i>c</i> is a space, tab, carriage return, newline, vertical tab, or formfeed
<i>ispunct</i>	<i>c</i> is a punctuation character (neither control nor alphanumeric)
<i>isprint</i>	<i>c</i> is a printing character, code 040(8) (space) through 0176 (tilde)
<i>isgraph</i>	<i>c</i> is a printing character, similar to <i>isprint</i> except false for space.
<i>isctrl</i>	<i>c</i> is a delete character (0177) or ordinary control character (less than 040).
<i>isascii</i>	<i>c</i> is an ASCII character, code less than 0200
<i>tolower</i>	<i>c</i> is converted to lower case. Return value is undefined if not <i>isupper(c)</i> .
<i>toupper</i>	<i>c</i> is converted to upper case. Return value is undefined if not <i>islower(c)</i> .
<i>toascii</i>	<i>c</i> is converted to be a valid ascii character.

SEE ALSO

ascii(7)

NAME

curses – screen functions with “optimal” cursor motion

SYNOPSIS

`cc [ flags ] files -lcurses -ltermcap [ libraries ]`

DESCRIPTION

These routines give the user a method of updating screens with reasonable optimization. They keep an image of the current screen, and the user sets up an image of a new one. Then the *refresh()* tells the routines to make the current screen look like the new one. In order to initialize the routines, the routine *initscr()* must be called before any of the other routines that deal with windows and screens are used. The routine *endwin()* should be called before exiting.

SEE ALSO

Screen Updating and Cursor Movement Optimization: A Library Package, Ken Arnold, *ioctl(2)*, *getenv(3)*, *tty(4)*, *termcap(5)*

AUTHOR

Ken Arnold

FUNCTIONS

<code>addch(ch)</code>	add a character to <i>stdscr</i>
<code>addstr(str)</code>	add a string to <i>stdscr</i>
<code>box(win,vert,hor)</code>	draw a box around a window
<code>cbreak()</code>	set cbreak mode
<code>clear()</code>	clear <i>stdscr</i>
<code>clearok(scr,boolf)</code>	set clear flag for <i>scr</i>
<code>clrtobot()</code>	clear to bottom on <i>stdscr</i>
<code>clrtoeol()</code>	clear to end of line on <i>stdscr</i>
<code>delch()</code>	delete a character
<code>deleteln()</code>	delete a line
<code>delwin(win)</code>	delete <i>win</i>
<code>echo()</code>	set echo mode
<code>endwin()</code>	end window modes
<code>erase()</code>	erase <i>stdscr</i>
<code>flushok(win,boolf)</code>	set flush-on-refresh flag for <i>win</i>
<code>getch()</code>	get a char through <i>stdscr</i>
<code>getcap(name)</code>	get terminal capability <i>name</i>
<code>getstr(str)</code>	get a string through <i>stdscr</i>
<code>gettmode()</code>	get tty modes
<code>getyx(win,y,x)</code>	get (y,x) co-ordinates
<code>inch()</code>	get char at current (y,x) co-ordinates
<code>initscr()</code>	initialize screens
<code>insch(c)</code>	insert a char
<code>insertln()</code>	insert a line
<code>leaveok(win,boolf)</code>	set leave flag for <i>win</i>
<code>longname(termbuf,name)</code>	get long name from <i>termbuf</i>
<code>move(y,x)</code>	move to (y,x) on <i>stdscr</i>
<code>mvcur(lasty,lastx,newy,newx)</code>	actually move cursor
<code>newwin(lines,cols,begin_y,begin_x)</code>	create a new window
<code>nl()</code>	set newline mapping
<code>nocbreak()</code>	unset cbreak mode
<code>noecho()</code>	unset echo mode
<code>nonl()</code>	unset newline mapping
<code>noraw()</code>	unset raw mode

overlay(win1,win2)	overlay win1 on win2
overwrite(win1,win2)	overwrite win1 on top of win2
printw(fmt,arg1,arg2,...)	printf on <i>stdscr</i>
raw()	set raw mode
refresh()	make current screen look like <i>stdscr</i>
resetty()	reset tty flags to stored value
savetty()	stored current tty flags
scanw(fmt,arg1,arg2,...)	scanf through <i>stdscr</i>
scroll(win)	scroll <i>win</i> one line
scrollok(win,boolf)	set scroll flag
setterm(name)	set term variables for name
standend()	end standout mode
standout()	start standout mode
subwin(win,lines,cols,begin_y,begin_x)	create a subwindow
touchline(win,y,sx,ex)	mark line <i>y</i> <i>sx</i> through <i>sy</i> as changed
touchoverlap(win1,win2)	mark overlap of <i>win1</i> on <i>win2</i> as changed
touchwin(win)	"change" all of <i>win</i>
unctrl(ch)	printable version of <i>ch</i>
waddch(win,ch)	add char to <i>win</i>
waddstr(win,str)	add string to <i>win</i>
wclear(win)	clear <i>win</i>
wclrto bot(win)	clear to bottom of <i>win</i>
wclrtoeol(win)	clear to end of line on <i>win</i>
wdelch(win,c)	delete char from <i>win</i>
wdeleteln(win)	delete line from <i>win</i>
werase(win)	erase <i>win</i>
wgetch(win)	get a char through <i>win</i>
wgetstr(win,str)	get a string through <i>win</i>
winch(win)	get char at current (<i>y,x</i>) in <i>win</i>
winsch(win,c)	insert char into <i>win</i>
winsertln(win)	insert line into <i>win</i>
wmove(win,y,x)	set current (<i>y,x</i>) co-ordinates on <i>win</i>
wprintw(win,fmt,arg1,arg2,...)	printf on <i>win</i>
wrefresh(win)	make screen look like <i>win</i>
wscanw(win,fmt,arg1,arg2,...)	scanf through <i>win</i>
wstandend(win)	end standout mode on <i>win</i>
wstandout(win)	start standout mode on <i>win</i>

NAME

dbminit, fetch, store, delete, firstkey, nextkey – data base subroutines

SYNOPSIS

```
#include <dbm.h>
```

```
typedef struct {
    char *dptr;
    int dsize;
}
```

```
    datum;
```

```
dbminit(file)
```

```
char *file;
```

```
datum fetch(key)
```

```
datum key;
```

```
store(key, content)
```

```
datum key, content;
```

```
delete(key)
```

```
datum key;
```

```
datum firstkey()
```

```
datum nextkey(key)
```

```
datum key;
```

DESCRIPTION

Note: the dbm library has been superceded by ndbm(3), and is now implemented using ndbm. These functions maintain key/content pairs in a data base. The functions will handle very large (a billion blocks) databases and will access a keyed item in one or two file system accesses. The functions are obtained with the loader option `-ldbm`.

Keys and *contents* are described by the *datum* typedef. A *datum* specifies a string of *dsize* bytes pointed to by *dptr*. Arbitrary binary data, as well as normal ASCII strings, are allowed. The data base is stored in two files. One file is a directory containing a bit map and has `‘.dir’` as its suffix. The second file contains all data and has `‘.pag’` as its suffix.

Before a database can be accessed, it must be opened by *dbminit*. At the time of this call, the files *file.dir* and *file.pag* must exist. (An empty database is created by creating zero-length `‘.dir’` and `‘.pag’` files.)

Once open, the data stored under a key is accessed by *fetch* and data is placed under a key by *store*. A key (and its associated contents) is deleted by *delete*. A linear pass through all keys in a database may be made, in an (apparently) random order, by use of *firstkey* and *nextkey*. *Firstkey* will return the first key in the database. With any key *nextkey* will return the next key in the database. This code will traverse the data base:

```
for (key = firstkey(); key.dptr != NULL; key = nextkey(key))
```

DIAGNOSTICS

All functions that return an *int* indicate errors with negative values. A zero return indicates ok. Routines that return a *datum* indicate errors with a null (0) *dptr*.

SEE ALSO

ndbm(3)

BUGS

The `‘.pag’` file will contain holes so that its apparent size is about four times its actual content. Older UNIX systems may create real file blocks for these holes when touched. These files cannot be copied by normal means (cp, cat, tp, tar, ar) without filling in the holes.

Dptr pointers returned by these subroutines point into static storage that is changed by subsequent calls.

The sum of the sizes of a key/content pair must not exceed the internal block size (currently 1024 bytes). Moreover all key/content pairs that hash together must fit on a single block. *Store* will return an error in the event that a disk block fills with inseparable data.

Delete does not physically reclaim file space, although it does make it available for reuse.

The order of keys presented by *firstkey* and *nextkey* depends on a hashing function, not on anything interesting.

P
R
M
3

NAME

opendir, readdir, telldir, seekdir, rewinddir, closedir – directory operations

SYNOPSIS

```
#include <sys/types.h>
#include <sys/dir.h>

DIR *opendir(filename)
char *filename;

struct direct *readdir(dirp)
DIR *dirp;

long telldir(dirp)
DIR *dirp;

seekdir(dirp, loc)
DIR *dirp;
long loc;

rewinddir(dirp)
DIR *dirp;

closedir(dirp)
DIR *dirp;
```

DESCRIPTION

Opendir opens the directory named by *filename* and associates a *directory stream* with it. *Opendir* returns a pointer to be used to identify the *directory stream* in subsequent operations. The pointer NULL is returned if *filename* cannot be accessed, or if it cannot *malloc*(3) enough memory to hold the whole thing.

Readdir returns a pointer to the next directory entry. It returns NULL upon reaching the end of the directory or detecting an invalid *seekdir* operation.

Telldir returns the current location associated with the named *directory stream*.

Seekdir sets the position of the next *readdir* operation on the *directory stream*. The new position reverts to the one associated with the *directory stream* when the *telldir* operation was performed. Values returned by *telldir* are good only for the lifetime of the DIR pointer from which they are derived. If the directory is closed and then reopened, the *telldir* value may be invalidated due to undetected directory compaction. It is safe to use a previous *telldir* value immediately after a call to *opendir* and before any calls to *readdir*.

Rewinddir resets the position of the named *directory stream* to the beginning of the directory.

Closedir closes the named *directory stream* and frees the structure associated with the DIR pointer.

Sample code which searches a directory for entry "name" is:

```
len = strlen(name);
dirp = opendir(".");
for (dp = readdir(dirp); dp != NULL; dp = readdir(dirp))
    if (dp->d_namlen == len && !strcmp(dp->d_name, name)) {
        closedir(dirp);
        return FOUND;
    }
closedir(dirp);
return NOT_FOUND;
```

SEE ALSO

open(2), close(2), read(2), lseek(2), dir(5)

NAME

ecvt, fcvt, gcvt – output conversion

SYNOPSIS

```
char *ecvt(value, ndigit, decpt, sign)
double value;
int ndigit, *decpt, *sign;

char *fcvt(value, ndigit, decpt, sign)
double value;
int ndigit, *decpt, *sign;

char *gcvt(value, ndigit, buf)
double value;
char *buf;
```

DESCRIPTION

Ecvt converts the *value* to a null-terminated string of *ndigit* ASCII digits and returns a pointer thereto. The position of the decimal point relative to the beginning of the string is stored indirectly through *decpt* (negative means to the left of the returned digits). If the sign of the result is negative, the word pointed to by *sign* is non-zero, otherwise it is zero. The low-order digit is rounded.

Fcvt is identical to *ecvt*, except that the correct digit has been rounded for Fortran F-format output of the number of digits specified by *ndigits*.

Gcvt converts the *value* to a null-terminated ASCII string in *buf* and returns a pointer to *buf*. It attempts to produce *ndigit* significant digits in Fortran F format if possible, otherwise E format, ready for printing. Trailing zeros may be suppressed.

SEE ALSO

printf(3)

BUGS

The return values point to static data whose content is overwritten by each call.

NAME

end, *etext*, *edata* – last locations in program

SYNOPSIS

extern *end*;
extern *etext*;
extern *edata*;

DESCRIPTION

These names refer neither to routines nor to locations with interesting contents. The address of *etext* is the first address above the program text, *edata* above the initialized data region, and *end* above the uninitialized data region.

When execution begins, the program break coincides with *end*, but it is reset by the routines *brk(2)*, *malloc(3)*, standard input/output (*stdio(3S)*), the profile (*-p*) option of *cc(1)*, etc. The current value of the program break is reliably returned by '*sbrk(0)*', see *brk(2)*.

SEE ALSO

brk(2), *malloc(3)*

NAME

erf, erfc – error functions

SYNOPSIS

```
#include <math.h>
```

```
double erf(x)
```

```
double x;
```

```
double erfc(x)
```

```
double x;
```

DESCRIPTION

Erf(x) returns the error function of x; where $\text{erf}(x) := (2/\sqrt{\pi}) \int_0^x \exp(-t^2) dt$.

Erfc(x) returns $1.0 - \text{erf}(x)$.

The entry for erfc is provided because of the extreme loss of relative accuracy if erf(x) is called for large x and the result subtracted from 1. (e.g. for x = 10, 12 places are lost).

SEE ALSO

math(3M)

P
R
M
3

NAME

execl, execv, execlx, execlp, execvp, exec, execve, exect, environ – execute a file

SYNOPSIS

```
execl(name, arg0, arg1, ..., argn, 0)
char *name, *arg0, *arg1, ..., *argn;

execv(name, argv)
char *name, *argv[];

execlx(name, arg0, arg1, ..., argn, 0, envp)
char *name, *arg0, *arg1, ..., *argn, *envp[];

exect(name, argv, envp)
char *name, *argv[], *envp[];

extern char **environ;
```

DESCRIPTION

These routines provide various interfaces to the *execve* system call. Refer to *execve*(2) for a description of their properties; only brief descriptions are provided here.

Exec in all its forms overlays the calling process with the named file, then transfers to the entry point of the core image of the file. There can be no return from a successful *exec*; the calling core image is lost.

The *name* argument is a pointer to the name of the file to be executed. The pointers *arg*[0], *arg*[1] ... address null-terminated strings. Conventionally *arg*[0] is the name of the file.

Two interfaces are available. *execl* is useful when a known file with known arguments is being called; the arguments to *execl* are the character strings constituting the file and the arguments; the first argument is conventionally the same as the file name (or its last component). A 0 argument must end the argument list.

The *execv* version is useful when the number of arguments is unknown in advance; the arguments to *execv* are the name of the file to be executed and a vector of strings containing the arguments. The last argument string must be followed by a 0 pointer.

The *exect* version is used when the executed file is to be manipulated with *ptrace*(2). The program is forced to single step a single instruction giving the parent an opportunity to manipulate its state. On the VAX-11 this is done by setting the trace bit in the process status longword.

When a C program is executed, it is called as follows:

```
main(argc, argv, envp)
int argc;
char **argv, **envp;
```

where *argc* is the argument count and *argv* is an array of character pointers to the arguments themselves. As indicated, *argc* is conventionally at least one and the first member of the array points to a string containing the name of the file.

Argv is directly usable in another *execv* because *argv*[*argc*] is 0.

Envp is a pointer to an array of strings that constitute the *environment* of the process. Each string consists of a name, an "=", and a null-terminated value. The array of pointers is terminated by a null pointer. The shell *sh*(1) passes an environment entry for each global shell variable defined when the program is called. See *environ*(7) for some conventionally used names. The C run-time start-off routine places a copy of *envp* in the global cell *environ*, which is used by *execv* and *execl* to pass the environment to any subprograms executed by the current program.

Execlp and *execvp* are called with the same arguments as *execl* and *execv*, but duplicate the shell's actions in searching for an executable file in a list of directories. The directory list is obtained from the environment.

FILES

/bin/sh shell, invoked if command file found by *execlp* or *execvp*

SEE ALSO

execve(2), *fork*(2), *environ*(7), *csh*(1)

DIAGNOSTICS

If the file cannot be found, if it is not executable, if it does not start with a valid magic number (see *a.out*(5)), if maximum memory is exceeded, or if the arguments require too much space, a return constitutes the diagnostic; the return value is -1. Even for the super-user, at least one of the execute-permission bits must be set for a file to be executed.

BUGS

If *execvp* is called to execute a file that turns out to be a shell command file, and if it is impossible to execute the shell, the values of *argv*[0] and *argv*[-1] will be modified before return.

NAME

exit – terminate a process after flushing any pending output

SYNOPSIS

```
exit(status)
int status;
```

DESCRIPTION

Exit terminates a process after calling the Standard I/O library function *_cleanup* to flush any buffered output. *Exit* never returns.

SEE ALSO

exit(2), intro(3)

NAME

exp, expm1, log, log10, log1p, pow – exponential, logarithm, power

SYNOPSIS

```
#include <math.h>
```

```
double exp(x)
```

```
double x;
```

```
double expm1(x)
```

```
double x;
```

```
double log(x)
```

```
double x;
```

```
double log10(x)
```

```
double x;
```

```
double log1p(x)
```

```
double x;
```

```
double pow(x,y)
```

```
double x,y;
```

DESCRIPTION

Exp returns the exponential function of x .

Expm1 returns $\exp(x)-1$ accurately even for tiny x .

Log returns the natural logarithm of x .

Log10 returns the logarithm of x to base 10.

Log1p returns $\log(1+x)$ accurately even for tiny x .

Pow(x,y) returns x^y .

ERROR (due to Roundoff etc.)

$\exp(x)$, $\log(x)$, $\expm1(x)$ and $\log1p(x)$ are accurate to within an *ulp*, and $\log10(x)$ to within about 2 *ulps*; an *ulp* is one *Unit in the Last Place*. The error in $\text{pow}(x,y)$ is below about 2 *ulps* when its magnitude is moderate, but increases as $\text{pow}(x,y)$ approaches the over/underflow thresholds until almost as many bits could be lost as are occupied by the floating-point format's exponent field; that is 8 bits for VAX D and 11 bits for IEEE 754 Double. No such drastic loss has been exposed by testing; the worst errors observed have been below 20 *ulps* for VAX D, 300 *ulps* for IEEE 754 Double. Moderate values of pow are accurate enough that $\text{pow}(\text{integer}, \text{integer})$ is exact until it is bigger than 2^{56} on a VAX, 2^{53} for IEEE 754.

DIAGNOSTICS

Exp, expm1 and pow return the reserved operand on a VAX when the correct value would overflow, and they set *errno* to ERANGE. Pow(x,y) returns the reserved operand on a VAX and sets *errno* to EDOM when $x < 0$ and y is not an integer.

On a VAX, *errno* is set to EDOM and the reserved operand is returned by log unless $x > 0$, by log1p unless $x > -1$.

NOTES

The functions $\exp(x)-1$ and $\log(1+x)$ are called expm1 and log1p in BASIC on the Hewlett-Packard HP-71B and APPLE Macintosh, EXP1 and LN1 in Pascal, exp1 and log1 in C on APPLE Macintoshes, where they have been provided to make sure financial calculations of $((1+x)^n-1)/x$, namely $\expm1(n \cdot \log1p(x))/x$, will be accurate when x is tiny. They also provide accurate inverse hyperbolic functions.

$\text{Pow}(x,0)$ returns $x^{**}0 = 1$ for all x including $x = 0, \infty$ (not found on a VAX), and NaN (the reserved operand on a VAX). Previous implementations of pow may have defined $x^{**}0$ to be undefined in some or all of these cases. Here are reasons for returning $x^{**}0 = 1$ always:

- (1) Any program that already tests whether x is zero (or infinite or NaN) before computing $x^{**}0$ cannot care whether $0^{**}0 = 1$ or not. Any program that depends upon $0^{**}0$ to be invalid is dubious anyway since that expression's meaning and, if invalid, its consequences vary from one computer system to another.
- (2) Some Algebra texts (e.g. Sigler's) define $x^{**}0 = 1$ for all x , including $x = 0$. This is compatible with the convention that accepts $a[0]$ as the value of polynomial

$$p(x) = a[0]*x^{**}0 + a[1]*x^{**}1 + a[2]*x^{**}2 + \dots + a[n]*x^{**}n$$
 at $x = 0$ rather than reject $a[0]*0^{**}0$ as invalid.
- (3) Analysts will accept $0^{**}0 = 1$ despite that $x^{**}y$ can approach anything or nothing as x and y approach 0 independently. The reason for setting $0^{**}0 = 1$ anyway is this:
 If $x(z)$ and $y(z)$ are *any* functions analytic (expandable in power series) in z around $z = 0$, and if there $x(0) = y(0) = 0$, then $x(z)^{**}y(z) \rightarrow 1$ as $z \rightarrow 0$.
- (4) If $0^{**}0 = 1$, then $\infty^{**}0 = 1/0^{**}0 = 1$ too; and then $NaN^{**}0 = 1$ too because $x^{**}0 = 1$ for all finite and infinite x , i.e., independently of x .

SEE ALSO

`math(3M)`, `infman(3M)`

AUTHOR

Kwok-Choi Ng, W. Kahan

NAME

fclose, fflush – close or flush a stream

SYNOPSIS

```
#include <stdio.h>
```

```
fclose(stream)
```

```
FILE *stream;
```

```
fflush(stream)
```

```
FILE *stream;
```

DESCRIPTION

Fclose causes any buffers for the named *stream* to be emptied, and the file to be closed. Buffers allocated by the standard input/output system are freed.

Fclose is performed automatically upon calling *exit*(3).

Fflush causes any buffered data for the named output *stream* to be written to that file. The stream remains open.

SEE ALSO

close(2), *fopen*(3S), *setbuf*(3S)

DIAGNOSTICS

These routines return EOF if *stream* is not associated with an output file, or if buffered data cannot be transferred to that file.

NAME

ferror, feof, clearerr, fileno – stream status inquiries

SYNOPSIS

#include <stdio.h>

feof(stream)

FILE *stream;

ferror(stream)

FILE *stream

clearerr(stream)

FILE *stream

fileno(stream)

FILE *stream;

DESCRIPTION

Feof returns non-zero when end of file is read on the named input *stream*, otherwise zero. Unless cleared by *clearerr*, the end-of-file indication lasts until the stream is closed.

Error returns non-zero when an error has occurred reading or writing the named *stream*, otherwise zero. Unless cleared by *clearerr*, the error indication lasts until the stream is closed.

Clearerr resets the error and end-of-file indicators on the named *stream*.

Fileno returns the integer file descriptor associated with the *stream*, see *open(2)*.

Currently all of these functions are implemented as macros; they cannot be redeclared.

SEE ALSO

fopen(3S), *open(2)*

NAME

fabs, floor, ceil, rint – absolute value, floor, ceiling, and round-to-nearest functions

SYNOPSIS

```
#include <math.h>
```

```
double floor(x)
```

```
double x;
```

```
double ceil(x)
```

```
double x;
```

```
double fabs(x)
```

```
double x;
```

```
double rint(x)
```

```
double x;
```

DESCRIPTION

Fabs returns the absolute value $|x|$.

Floor returns the largest integer no greater than x .

Ceil returns the smallest integer no less than x .

Rint returns the integer (represented as a double precision number) nearest x in the direction of the prevailing rounding mode.

NOTES

On a VAX, rint(x) is equivalent to adding half to the magnitude and then rounding towards zero.

In the default rounding mode, to nearest, on a machine that conforms to IEEE 754, rint(x) is the integer nearest x with the additional stipulation that if $|\text{rint}(x) - x| = 1/2$ then rint(x) is even. Other rounding modes can make rint act like floor, or like ceil, or round towards zero.

Another way to obtain an integer near x is to declare (in C)

```
double x;    int k;    k = x;
```

Most C compilers round x towards 0 to get the integer k , but some do otherwise. If in doubt, use floor, ceil, or rint first, whichever you intend. Also note that, if x is larger than k can accommodate, the value of k and the presence or absence of an integer overflow are hard to predict.

SEE ALSO

abs(3), ieee(3M), math(3M)

NAME

fopen, freopen, fdopen – open a stream

SYNOPSIS

```
#include <stdio.h>
```

```
FILE *fopen(filename, type)
char *filename, *type;
```

```
FILE *freopen(filename, type, stream)
char *filename, *type;
FILE *stream;
```

```
FILE *fdopen(fildes, type)
char *type;
```

DESCRIPTION

Fopen opens the file named by *filename* and associates a stream with it. *Fopen* returns a pointer to be used to identify the stream in subsequent operations.

Type is a character string having one of the following values:

"r" open for reading

"w" create for writing

"a" append: open for writing at end of file, or create for writing

In addition, each *type* may be followed by a "+" to have the file opened for reading and writing. "r+" positions the stream at the beginning of the file, "w+" creates or truncates it, and "a+" positions it at the end. Both reads and writes may be used on read/write streams, with the limitation that an *fseek*, *rewind*, or reading an end-of-file must be used between a read and a write or vice-versa.

Freopen substitutes the named file in place of the open *stream*. It returns the original value of *stream*. The original stream is closed.

Freopen is typically used to attach the preopened constant names, *stdin*, *stdout*, *stderr*, to specified files.

Fdopen associates a stream with a file descriptor obtained from *open*, *dup*, *creat*, or *pipe(2)*. The *type* of the stream must agree with the mode of the open file.

SEE ALSO

open(2), *fclose(3)*

DIAGNOSTICS

Fopen and *freopen* return the pointer NULL if *filename* cannot be accessed, if too many files are already open, or if other resources needed cannot be allocated.

BUGS

Fdopen is not portable to systems other than UNIX.

The read/write *types* do not exist on all systems. Those systems without read/write modes will probably treat the *type* as if the "+" was not present. These are unreliable in any event.

In order to support the same number of open files as does the system, *fopen* must allocate additional memory for data structures using *calloc* after 20 files have been opened. This confuses some programs which use their own memory allocators. An undocumented routine, *f_prealloc*, may be called to force immediate allocation of all internal memory except for buffers.

NAME

fread, *fwrite* – buffered binary input/output

SYNOPSIS

```
#include <stdio.h>
```

```
fread(ptr, sizeof(*ptr), nitems, stream)
```

```
FILE *stream;
```

```
fwrite(ptr, sizeof(*ptr), nitems, stream)
```

```
FILE *stream;
```

DESCRIPTION

Fread reads, into a block beginning at *ptr*, *nitems* of data of the type of **ptr* from the named input *stream*. It returns the number of items actually read.

If *stream* is *stdin* and the standard output is line buffered, then any partial output line will be flushed before any call to *read(2)* to satisfy the *fread*.

Fwrite appends at most *nitems* of data of the type of **ptr* beginning at *ptr* to the named output *stream*. It returns the number of items actually written.

SEE ALSO

read(2), *write(2)*, *fopen(3S)*, *getc(3S)*, *putc(3S)*, *gets(3S)*, *puts(3S)*, *printf(3S)*, *scanf(3S)*

DIAGNOSTICS

Fread and *fwrite* return 0 upon end of file or error.

NAME

frexp, ldexp, modf – split into mantissa and exponent

SYNOPSIS

```
double frexp(value, eptr)
double value;
int *eptr;

double ldexp(value, exp)
double value;

double modf(value, iptr)
double value, *iptr;
```

DESCRIPTION

Frexp returns the mantissa of a double *value* as a double quantity, *x*, of magnitude less than 1 and stores an integer *n* such that $value = x * 2^n$ indirectly through *eptr*.

Ldexp returns the quantity $value * 2^{exp}$.

Modf returns the positive fractional part of *value* and stores the integer part indirectly through *iptr*.

NAME

fseek, *ftell*, *rewind* – reposition a stream

SYNOPSIS

```
#include <stdio.h>
```

```
fseek(stream, offset, ptrname)
```

```
FILE *stream;
```

```
long offset;
```

```
long ftell(stream)
```

```
FILE *stream;
```

```
rewind(stream)
```

DESCRIPTION

Fseek sets the position of the next input or output operation on the *stream*. The new position is at the signed distance *offset* bytes from the beginning, the current position, or the end of the file, according as *ptrname* has the value 0, 1, or 2.

Fseek undoes any effects of *ungetc*(3S).

Ftell returns the current value of the offset relative to the beginning of the file associated with the named *stream*. It is measured in bytes on UNIX; on some other systems it is a magic cookie, and the only foolproof way to obtain an *offset* for *fseek*.

Rewind(*stream*) is equivalent to *fseek*(*stream*, 0L, 0).

SEE ALSO

lseek(2), *fopen*(3S)

DIAGNOSTICS

Fseek returns -1 for improper seeks, otherwise zero.

NAME

`getc`, `getchar`, `fgetc`, `getw` – get character or word from stream

SYNOPSIS

```
#include <stdio.h>
```

```
int getc(stream)
```

```
FILE *stream;
```

```
int getchar()
```

```
int fgetc(stream)
```

```
FILE *stream;
```

```
int getw(stream)
```

```
FILE *stream;
```

DESCRIPTION

Getc returns the next character from the named input *stream*.

Getchar() is identical to *getc(stdin)*.

Fgetc behaves like *getc*, but is a genuine function, not a macro; it may be used to save object text.

Getw returns the next `int` (a 32-bit integer on a VAX-11) from the named input *stream*. It returns the constant `EOF` upon end of file or error, but since that is a good integer value, *feof* and *feof(3S)* should be used to check the success of *getw*. *Getw* assumes no special alignment in the file.

SEE ALSO

`clearerr(3S)`, `fopen(3S)`, `putc(3S)`, `gets(3S)`, `scanf(3S)`, `fread(3S)`, `ungetc(3S)`

DIAGNOSTICS

These functions return the integer constant `EOF` at end of file, upon read error, or if an attempt is made to read a file not opened by *fopen*. The end-of-file condition is remembered, even on a terminal, and all subsequent attempts to read will return `EOF` until the condition is cleared with *clearerr(3S)*.

BUGS

Because it is implemented as a macro, *getc* treats a *stream* argument with side effects incorrectly. In particular, '`getc(*f++);`' doesn't work sensibly.

NAME

getdiskbyname – get disk description by its name

SYNOPSIS

```
#include <disktab.h>
```

```
struct disktab *
getdiskbyname(name)
char *name;
```

DESCRIPTION

Getdiskbyname takes a disk name (e.g. rm03) and returns a structure describing its geometry information and the standard disk partition tables. All information obtained from the *disktab(5)* file.

<disktab.h> has the following form:

```
/*
 * Copyright (c) 1983 Regents of the University of California.
 * All rights reserved. The Berkeley software License Agreement
 * specifies the terms and conditions for redistribution.
 *
 *    @(#)disktab.h  5.2 (Berkeley) 10/1/85
 */

/*
 * Disk description table, see disktab(5)
 */
#define DISKTAB        "/etc/disktab"

struct disktab {
    char    *d_name;           /* drive name */
    char    *d_type;           /* drive type */
    int     d_sectsize;        /* sector size in bytes */
    int     d_ntracks;         /* # tracks/cylinder */
    int     d_nsectors;        /* # sectors/track */
    int     d_ncylinders;      /* # cylinders */
    int     d_rpm;             /* revolutions/minute */
    int     d_badsectforw;     /* supports DEC bad144 std */
    int     d_sectoffset;      /* use sect rather than cyl offsets */
    struct  partition {
        int     p_size;        /* #sectors in partition */
        short   p_bsize;       /* block size in bytes */
        short   p_fsize;       /* frag size in bytes */
    } d_partitions[8];
};
```

```
struct disktab *getdiskbyname();
```

SEE ALSO

disktab(5)

BUGS

This information should be obtained from the system for locally available disks (in particular, the disk partition tables).

NAME

getenv – value for environment name

SYNOPSIS

```
char *getenv(name)
char *name;
```

DESCRIPTION

Getenv searches the environment list (see *environ(7)*) for a string of the form *name=value* and returns a pointer to the string *value* if such a string is present, otherwise *getenv* returns the value 0 (NULL).

SEE ALSO

environ(7), *execve(2)*

NAME

getfsent, *getfsspec*, *getfsfile*, *getfstype*, *setfsent*, *endfsent* – get file system descriptor file entry

SYNOPSIS

```
#include <fstab.h>

struct fstab *getfsent()
char *spec;

struct fstab *getfsfile(file)
char *file;

struct fstab *getfstype(type)
char *type;

int setfsent()

int endfsent()
```

DESCRIPTION

Getfsent, *getfsspec*, *getfstype*, and *getfsfile* each return a pointer to an object with the following structure containing the broken-out fields of a line in the file system description file, <fstab.h>.

```
struct fstab {
    char    *fs_spec;
    char    *fs_file;
    char    *fs_type;
    int     fs_freq;
    int     fs_passno;
};
```

The fields have meanings described in *fstab(5)*.

Getfsent reads the next line of the file, opening the file if necessary.

Setfsent opens and rewinds the file.

Endfsent closes the file.

Getfsspec and *getfsfile* sequentially search from the beginning of the file until a matching special file name or file system file name is found, or until EOF is encountered. *Getfstype* does likewise, matching on the file system type field.

FILES

/etc/fstab

SEE ALSO

fstab(5)

DIAGNOSTICS

Null pointer (0) returned on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved.

NAME

getgrent, getgrgid, getgrnam, setgrent, endgrent – get group file entry

SYNOPSIS

```
#include <grp.h>

struct group *getgrent()
struct group *getgrgid(gid)
int gid;
struct group *getgrnam(name)
char *name;
setgrent()
endgrent()
```

DESCRIPTION

Getgrent, *getgrgid* and *getgrnam* each return pointers to an object with the following structure containing the broken-out fields of a line in the group file.

```
/*      grp.h      4.1      83/05/03      */

struct  group { /* see getgrent(3) */
    char  *gr_name;
    char  *gr_passwd;
    int    gr_gid;
    char  **gr_mem;
};

struct group *getgrent(), *getgrgid(), *getgrnam();
```

The members of this structure are:

gr_name The name of the group.
gr_passwd The encrypted password of the group.
gr_gid The numerical group-ID.
gr_mem Null-terminated vector of pointers to the individual member names.

Getgrent simply reads the next line while *getgrgid* and *getgrnam* search until a matching *gid* or *name* is found (or until EOF is encountered). Each routine picks up where the others leave off so successive calls may be used to search the entire file.

A call to *setgrent* has the effect of rewinding the group file to allow repeated searches. *Endgrent* may be called to close the group file when processing is complete.

FILES

/etc/group

SEE ALSO

getlogin(3), getpwent(3), group(5)

DIAGNOSTICS

A null pointer (0) is returned on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved.

NAME

gethostbyname, gethostbyaddr, gethostent, sethostent, endhostent – get network host entry

SYNOPSIS

```
#include <netdb.h>

extern int h_errno;

struct hostent *gethostbyname(name)
char *name;

struct hostent *gethostbyaddr(addr, len, type)
char *addr; int len, type;

struct hostent *gethostent()

sethostent(stayopen)
int stayopen;

endhostent()
```

DESCRIPTION

Gethostbyname and *gethostbyaddr* each return a pointer to an object with the following structure. This structure contains either the information obtained from the name server, *named*(8), or broken-out fields from a line in */etc/hosts*. If the local name server is not running these routines do a lookup in */etc/hosts*.

```
struct hostent {
    char    *h_name;        /* official name of host */
    char    **h_aliases;    /* alias list */
    int     h_addrtype;     /* host address type */
    int     h_length;       /* length of address */
    char    **h_addr_list;  /* list of addresses from name server */
};
#define h_addr h_addr_list[0] /* address, for backward compatibility */
```

The members of this structure are:

h_name Official name of the host.

h_aliases A zero terminated array of alternate names for the host.

h_addrtype The type of address being returned; currently always AF_INET.

h_length The length, in bytes, of the address.

h_addr_list A zero terminated array of network addresses for the host. Host addresses are returned in network byte order.

h_addr The first address in *h_addr_list*; this is for backward compatibility.

Sethostent allows a request for the use of a connected socket using TCP for queries. If the *stayopen* flag is non-zero, this sets the option to send all queries to the name server using TCP and to retain the connection after each call to *gethostbyname* or *gethostbyaddr*.

Endhostent closes the TCP connection.

DIAGNOSTICS

Error return status from *gethostbyname* and *gethostbyaddr* is indicated by return of a null pointer. The external integer *h_errno* may then be checked to see whether this is a temporary failure or an invalid or unknown host.

h_errno can have the following values:

HOST_NOT_FOUND No such host is known.

TRY_AGAIN

This is usually a temporary error and means that the local server did not receive a response from an authoritative server. A retry at some later time may succeed.

NO_RECOVERY

This is a non-recoverable error.

NO_ADDRESS

The requested name is valid but does not have an IP address; this is not a temporary error. This means another type of request to the name server will result in an answer.

FILES

/etc/hosts

SEE ALSO

hosts(5), resolver(3), named(8)

CAVEAT

Gethostent is defined, and *sethostent* and *endhostent* are redefined, when *libc* is built to use only the routines to lookup in */etc/hosts* and not the name server.

Gethostent reads the next line of */etc/hosts*, opening the file if necessary.

Sethostent is redefined to open and rewind the file. If the *stayopen* argument is non-zero, the hosts data base will not be closed after each call to *gethostbyname* or *gethostbyaddr*. *Endhostent* is redefined to close the file.

BUGS

All information is contained in a static area so it must be copied if it is to be saved. Only the Internet address format is currently understood.

NAME

getlogin – get login name

SYNOPSIS

char *getlogin()

DESCRIPTION

Getlogin returns a pointer to the login name as found in */etc/utmp*. It may be used in conjunction with *getpwnam* to locate the correct password file entry when the same userid is shared by several login names.

If *getlogin* is called within a process that is not attached to a terminal, or if there is no entry in */etc/utmp* for the process's terminal, *getlogin* returns a NULL pointer (0). A reasonable procedure for determining the login name is to first call *getlogin* and if it fails, to call *getpwuid(getuid())*.

FILES

/etc/utmp

SEE ALSO

getpwent(3), *utmp(5)*, *ttyslot(3)*

DIAGNOSTICS

Returns a NULL pointer (0) if name not found.

BUGS

The return values point to static data whose content is overwritten by each call.

P
R
M
3

NAME

getnetent, getnetbyaddr, getnetbyname, setnetent, endnetent – get network entry

SYNOPSIS

```
#include <netdb.h>

struct netent *getnetent()
struct netent *getnetbyname(name)
char *name;

struct netent *getnetbyaddr(net, type)
long net;
int type;

setnetent(stayopen)
int stayopen;

endnetent()
```

DESCRIPTION

Getnetent, *getnetbyname*, and *getnetbyaddr* each return a pointer to an object with the following structure containing the broken-out fields of a line in the network data base, */etc/networks*.

```
struct netent {
    char      *n_name;      /* official name of net */
    char      **n_aliases;  /* alias list */
    int       n_addrtype;   /* net number type */
    unsigned long n_net;    /* net number */
};
```

The members of this structure are:

n_name The official name of the network.
n_aliases A zero terminated list of alternate names for the network.
n_addrtype The type of the network number returned; currently only AF_INET.
n_net The network number. Network numbers are returned in machine byte order.

Getnetent reads the next line of the file, opening the file if necessary.

Setnetent opens and rewinds the file. If the *stayopen* flag is non-zero, the net data base will not be closed after each call to *getnetbyname* or *getnetbyaddr*.

Endnetent closes the file.

Getnetbyname and *getnetbyaddr* sequentially search from the beginning of the file until a matching net name or net address and type is found, or until EOF is encountered. Network numbers are supplied in host order.

FILES

/etc/networks

SEE ALSO

networks(5)

DIAGNOSTICS

Null pointer (0) returned on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved. Only Internet network numbers are currently understood. Expecting network numbers to fit in no more than 32 bits is probably naive.

NAME

getopt – get option letter from argv

SYNOPSIS

```
int getopt(argc, argv, optstring)
int argc;
char **argv;
char *optstring;
```

```
extern char *optarg;
extern int optind;
```

DESCRIPTION

Getopt returns the next option letter in *argv* that matches a letter in *optstring*. *Optstring* is a string of recognized option letters; if a letter is followed by a colon, the option is expected to have an argument that may or may not be separated from it by white space. *Optarg* is set to point to the start of the option argument on return from *getopt*.

Getopt places in *optind* the *argv* index of the next argument to be processed. Because *optind* is external, it is normally initialized to zero automatically before the first call to *getopt*.

When all options have been processed (i.e., up to the first non-option argument), *getopt* returns EOF. The special option *--* may be used to delimit the end of the options; EOF will be returned, and *--* will be skipped.

DIAGNOSTICS

Getopt prints an error message on *stderr* and returns a question mark (?) when it encounters an option letter not included in *optstring*.

EXAMPLE

The following code fragment shows how one might process the arguments for a command that can take the mutually exclusive options *a* and *b*, and the options *f* and *o*, both of which require arguments:

```
main(argc, argv)
int argc;
char **argv;
{
    int c;
    extern int optind;
    extern char *optarg;
    .
    .
    .
    while ((c = getopt(argc, argv, "abf:o:")) != EOF)
        switch (c) {
            case 'a':
                if (bflg)
                    errflg++;
                else
                    aflg++;
                break;
            case 'b':
                if (aflg)
                    errflg++;
                else
                    bproc();
                break;
```

```

        case 'f':
            ifile = optarg;
            break;
        case 'o':
            ofile = optarg;
            break;
        case '?':
        default:
            errflg++;
            break;
    }
    if (errflg) {
        fprintf(stderr, "Usage: ...");
        exit(2);
    }
    for (; optind < argc; optind++) {
        .
        .
        .
    }
    .
    .
    .
}

```

HISTORY

Written by Henry Spencer, working from a Bell Labs manual page. Modified by Keith Bostic to behave more like the System V version.

BUGS

It is not obvious how '-' standing alone should be treated; this version treats it as a non-option argument, which is not always right.

Option arguments are allowed to begin with '-'; this is reasonable but reduces the amount of error checking possible.

Getopt is quite flexible but the obvious price must be paid: there is much it could do that it doesn't, like checking mutually exclusive options, checking type of option arguments, etc.

NAME

getpass – read a password

SYNOPSIS

```
char *getpass(prompt)
char *prompt;
```

DESCRIPTION

Getpass reads a password from the file */dev/tty*, or if that cannot be opened, from the standard input, after prompting with the null-terminated string *prompt* and disabling echoing. A pointer is returned to a null-terminated string of at most 8 characters.

FILES

/dev/tty

SEE ALSO

crypt(3)

BUGS

The return value points to static data whose content is overwritten by each call.

P
R
M
3

NAME

getprotoent, *getprotobynumber*, *getprotobynname*, *setprotoent*, *endprotoent* – get protocol entry

SYNOPSIS

```
#include <netdb.h>

struct protoent *getprotoent()
struct protoent *getprotobynname(name)
char *name;
struct protoent *getprotobynumber(proto)
int proto;
setprotoent(stayopen)
int stayopen
endprotoent()
```

DESCRIPTION

Getprotoent, *getprotobynname*, and *getprotobynumber* each return a pointer to an object with the following structure containing the broken-out fields of a line in the network protocol data base, */etc/protocols*.

```
struct protoent {
    char    *p_name;      /* official name of protocol */
    char    **p_aliases;  /* alias list */
    int     p_proto;      /* protocol number */
};
```

The members of this structure are:

p_name The official name of the protocol.

p_aliases A zero terminated list of alternate names for the protocol.

p_proto The protocol number.

Getprotoent reads the next line of the file, opening the file if necessary.

Setprotoent opens and rewinds the file. If the *stayopen* flag is non-zero, the net data base will not be closed after each call to *getprotobynname* or *getprotobynumber*.

Endprotoent closes the file.

Getprotobynname and *getprotobynumber* sequentially search from the beginning of the file until a matching protocol name or protocol number is found, or until EOF is encountered.

FILES

/etc/protocols

SEE ALSO

protocols(5)

DIAGNOSTICS

Null pointer (0) returned on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved. Only the Internet protocols are currently understood.

NAME

getpw – get name from uid

SYNOPSIS

```
getpw(uid, buf)
char *buf;
```

DESCRIPTION

Getpw is made obsolete by getpwuid(3).

Getpw searches the password file for the (numerical) *uid*, and fills in *buf* with the corresponding line; it returns non-zero if *uid* could not be found. The line is null-terminated.

FILES

/etc/passwd

SEE ALSO

getpwent(3), passwd(5)

DIAGNOSTICS

Non-zero return on error.

P
R
M
3

NAME

getpwent, getpwuid, getpwnam, setpwent, endpwent, setpwfile – get password file entry

SYNOPSIS

```
#include <pwd.h>

struct passwd *getpwuid(uid)
int uid;

struct passwd *getpwnam(name)
char *name;

struct passwd *getpwent()

setpwent()

endpwent()

setpwfile(name)
char *name;
```

DESCRIPTION

Getpwent, *getpwuid* and *getpwnam* each return a pointer to an object with the following structure containing the broken-out fields of a line in the password file.

```
/*      pwd.h  4.1      83/05/03      */

struct passwd { /* see getpwent(3) */
    char    *pw_name;
    char    *pw_passwd;
    int     pw_uid;
    int     pw_gid;
    int     pw_quota;
    char    *pw_comment;
    char    *pw_gecos;
    char    *pw_dir;
    char    *pw_shell;
};
```

```
struct passwd *getpwent(), *getpwuid(), *getpwnam();
```

The fields *pw_quota* and *pw_comment* are unused; the others have meanings described in *passwd(5)*.

Searching of the password file is done using the *ndbm* database access routines. *Setpwent* opens the database; *endpwent* closes it. *Getpwuid* and *getpwnam* search the database (opening it if necessary) for a matching *uid* or *name*. EOF is returned if there is no entry.

For programs wishing to read the entire database, *getpwent* reads the next line (opening the database if necessary). In addition to opening the database, *setpwent* can be used to make *getpwent* begin its search from the beginning of the database.

Setpwfile changes the default password file to *name* thus allowing alternate password files to be used. Note that it does *not* close the previous file. If this is desired, *endpwent* should be called prior to it.

FILES

/etc/passwd

SEE ALSO

getlogin(3), getgrent(3), passwd(5)

DIAGNOSTICS

The routines *getpwent*, *getpwuid*, and *getpwnam*, return a null pointer (0) on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved.

NAME

gets, *fgets* – get a string from a stream

SYNOPSIS

```
#include <stdio.h>
```

```
char *gets(s)
```

```
char *s;
```

```
char *fgets(s, n, stream)
```

```
char *s;
```

```
FILE *stream;
```

DESCRIPTION

Gets reads a string into *s* from the standard input stream *stdin*. The string is terminated by a newline character, which is replaced in *s* by a null character. *Gets* returns its argument.

Fgets reads *n*–1 characters, or up through a newline character, whichever comes first, from the *stream* into the string *s*. The last character read into *s* is followed by a null character. *Fgets* returns its first argument.

SEE ALSO

puts(3S), *getc*(3S), *scanf*(3S), *fread*(3S), *ferror*(3S)

DIAGNOSTICS

Gets and *fgets* return the constant pointer *NULL* upon end of file or error.

BUGS

Gets deletes a newline, *fgets* keeps it, all in the name of backward compatibility.

NAME

getservent, getservbyport, getservbyname, setservent, endservent – get service entry

SYNOPSIS

```
#include <netdb.h>

struct servent *getservent()
struct servent *getservbyname(name, proto)
char *name, *proto;

struct servent *getservbyport(port, proto)
int port; char *proto;

setservent(stayopen)
int stayopen

endservent()
```

DESCRIPTION

Getservent, *getservbyname*, and *getservbyport* each return a pointer to an object with the following structure containing the broken-out fields of a line in the network services data base, */etc/services*.

```
struct servent {
    char    *s_name;        /* official name of service */
    char    **s_aliases;    /* alias list */
    int     s_port;         /* port service resides at */
    char    *s_proto;       /* protocol to use */
};
```

The members of this structure are:

- s_name** The official name of the service.
- s_aliases** A zero terminated list of alternate names for the service.
- s_port** The port number at which the service resides. Port numbers are returned in network byte order.
- s_proto** The name of the protocol to use when contacting the service.

Getservent reads the next line of the file, opening the file if necessary.

Setservent opens and rewinds the file. If the *stayopen* flag is non-zero, the net data base will not be closed after each call to *getservbyname* or *getservbyport*.

Endservent closes the file.

Getservbyname and *getservbyport* sequentially search from the beginning of the file until a matching protocol name or port number is found, or until EOF is encountered. If a protocol name is also supplied (non-NULL), searches must also match the protocol.

FILES

/etc/services

SEE ALSO

getprotoent(3N), services(5)

DIAGNOSTICS

Null pointer (0) returned on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved. Expecting port numbers to fit in a 32 bit quantity is probably naive.

NAME

gettyent, gettynam, setttyent, endttyent – get ttys file entry

SYNOPSIS

```
#include <ttyent.h>

struct ttyent *gettyent()

struct ttyent *gettynam(name)
char *name;

setttyent()

endttyent()
```

DESCRIPTION

Gettyent, and *gettynam* each return a pointer to an object with the following structure containing the broken-out fields of a line from the tty description file.

```
/*
 * Copyright (c) 1983 Regents of the University of California.
 * All rights reserved. The Berkeley software License Agreement
 * specifies the terms and conditions for redistribution.
 *
 * @(#)ttyent.h 5.1 (Berkeley) 5/30/85
 */

struct ttyent { /* see gettyent(3) */
    char *ty_name; /* terminal device name */
    char *ty_getty; /* command to execute, usually getty */
    char *ty_type; /* terminal type for termcap (3X) */
    int ty_status; /* status flags (see below for defines) */
    char *ty_window; /* command to start up window manager */
    char *ty_comment; /* usually the location of the terminal */
};

#define TTY_ON 0x1 /* enable logins (startup getty) */
#define TTY_SECURE 0x2 /* allow root to login */

extern struct ttyent *gettyent();
extern struct ttyent *gettynam();
```

ty_name is the name of the character-special file in the directory “/dev”. For various reasons, it must reside in the directory “/dev”.

ty_getty is the command (usually *getty*(8)) which is invoked by *init* to initialize tty line characteristics. In fact, any arbitrary command can be used; a typical use is to initiate a terminal emulator in a window system.

ty_type is the name of the default terminal type connected to this tty line. This is typically a name from the *termcap*(5) data base. The environment variable ‘TERM’ is initialized with this name by *getty*(8) or *login*(1).

ty_status is a mask of bit fields which indicate various actions to be allowed on this tty line. The following is a description of each flag.

TTY_ON Enables logins (i.e., *init*(8) will start the specified “getty” command on this entry).

TTY_SECURE Allows root to login on this terminal. Note that ‘TTY_ON’ must be included for this to be useful.

ty_window is the command to execute for a window system associated with the line. The window system will be started before the command specified in the *ty_getty* entry is executed. If none is specified, this will be null.

ty_comment is the trailing comment field, if any; a leading delimiter and white space will be removed.

Getttyent reads the next line from the ttys file, opening the file if necessary; *setttyent* rewinds the file; *endttyent* closes it.

Getttynam searches from the beginning of the file until a matching *name* is found (or until EOF is encountered).

P
R
M
3

FILES

/etc/ttys

SEE ALSO

login(1), ttyslot(3), ttys(5), gettytab(5), termcap(5), getty(8), init(8)

DIAGNOSTICS

Null pointer (0) returned on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved.

NAME

getusershell, *setusershell*, *endusershell* – get legal user shells

SYNOPSIS

char **getusershell*()

***setusershell*()**

***endusershell*()**

DESCRIPTION

Getusershell returns a pointer to a legal user shell as defined by the system manager in the file */etc/shells*. If */etc/shells* does not exist, the two standard system shells */bin/sh* and */bin/csh* are returned.

Getusershell reads the next line (opening the file if necessary); *setusershell* rewinds the file; *endusershell* closes it.

FILES

/etc/shells

DIAGNOSTICS

The routine *getusershell* returns a null pointer (0) on EOF or error.

BUGS

All information is contained in a static area so it must be copied if it is to be saved.

P
R
M 3

NAME

getwd – get current working directory pathname

SYNOPSIS

```
char *getwd(pathname)
char *pathname;
```

DESCRIPTION

Getwd copies the absolute pathname of the current working directory to *pathname* and returns a pointer to the result.

LIMITATIONS

Maximum pathname length is MAXPATHLEN characters (1024), as defined in *<sys/param.h>*.

DIAGNOSTICS

Getwd returns zero and places a message in *pathname* if an error occurs.

P
R
M
3

NAME

hypot, cabs – Euclidean distance, complex absolute value

SYNOPSIS

```
#include <math.h>

double hypot(x,y)
double x,y;

double cabs(z)
struct {double x,y;} z;
```

DESCRIPTION

Hypot(x,y) and cabs(x,y) return $\sqrt{x^2+y^2}$ computed in such a way that underflow will not happen, and overflow occurs only if the final result deserves it.

$\text{hypot}(\infty, v) = \text{hypot}(v, \infty) = +\infty$ for all v , including *NaN*.

ERROR (due to Roundoff, etc.)

Below 0.97 *ulps*. Consequently $\text{hypot}(5.0, 12.0) = 13.0$ exactly; in general, hypot and cabs return an integer whenever an integer might be expected.

The same cannot be said for the shorter and faster version of hypot and cabs that is provided in the comments in cabs.c; its error can exceed 1.2 *ulps*.

NOTES

As might be expected, $\text{hypot}(v, \text{NaN})$ and $\text{hypot}(\text{NaN}, v)$ are *NaN* for all *finite* v ; with "reserved operand" in place of "*NaN*", the same is true on a VAX. But programmers on machines other than a VAX (it has no ∞) might be surprised at first to discover that $\text{hypot}(\pm\infty, \text{NaN}) = +\infty$. This is intentional; it happens because $\text{hypot}(\infty, v) = +\infty$ for *all* v , finite or infinite. Hence $\text{hypot}(\infty, v)$ is independent of v . Unlike the reserved operand on a VAX, the IEEE *NaN* is designed to disappear when it turns out to be irrelevant, as it does in $\text{hypot}(\infty, \text{NaN})$.

SEE ALSO

math(3M), sqrt(3M)

AUTHOR

W. Kahan

NAME

copysign, drem, finite, logb, scalb – copysign, remainder, exponent manipulations

SYNOPSIS

```
#include <math.h>

double copysign(x,y)
double x,y;

double drem(x,y)
double x,y;

int finite(x)
double x;

double logb(x)
double x;

double scalb(x,n)
double x;
int n;
```

DESCRIPTION

These functions are required for, or recommended by the IEEE standard 754 for floating-point arithmetic.

Copysign(x,y) returns x with its sign changed to y's.

Drem(x,y) returns the remainder $r := x - n*y$ where n is the integer nearest the exact value of x/y; moreover if $|n - x/y| = 1/2$ then n is even. Consequently the remainder is computed exactly and $|r| \leq |y|/2$. But drem(x,0) is exceptional; see below under DIAGNOSTICS.

Finite(x) = 1 just when $-\infty < x < +\infty$,
 = 0 otherwise (when $|x| = \infty$ or x is NaN or
 x is the VAX's reserved operand.)

Logb(x) returns x's exponent n, a signed integer converted to double-precision floating-point and so chosen that $1 \leq |x|/2^{**n} < 2$ unless $x = 0$ or (only on machines that conform to IEEE 754) $|x| = \infty$ or x lies between 0 and the Underflow Threshold; see below under "BUGS".

Scalb(x,n) = $x*(2^{**n})$ computed, for integer n, without first computing 2^{**n} .

DIAGNOSTICS

IEEE 754 defines drem(x,0) and drem(∞ ,y) to be invalid operations that produce a NaN. On a VAX, drem(x,0) returns the reserved operand. No ∞ exists on a VAX.

IEEE 754 defines $\text{logb}(\pm\infty) = +\infty$ and $\text{logb}(0) = -\infty$, and requires the latter to signal Division-by-Zero. But on a VAX, $\text{logb}(0) = 1.0 - 2.0^{**31} = -2,147,483,647.0$. And if the correct value of $\text{scalb}(x,n)$ would overflow on a VAX, it returns the reserved operand and sets *errno* to ERANGE.

SEE ALSO

floor(3M), math(3M), infnan(3M)

AUTHOR

Kwok-Choi Ng

BUGS

Should drem(x,0) and logb(0) on a VAX signal invalidity by setting *errno* = EDOM? Should logb(0) return $-1.7e38$?

IEEE 754 currently specifies that $\text{logb}(\text{denormalized no.}) = \text{logb}(\text{tiniest normalized no.} > 0)$ but the consensus has changed to the specification in the new proposed IEEE standard p854, namely that $\text{logb}(x)$ satisfy

$$1 \leq \text{scalb}(|x|, -\text{logb}(x)) < \text{Radix} \quad \dots = 2 \text{ for IEEE 754}$$

for every x except 0 , ∞ and NaN . Almost every program that assumes 754's specification will work correctly if logb follows 854's specification instead.

IEEE 754 requires $\text{copysign}(x, \text{NaN}) = \pm x$ but says nothing else about the sign of a NaN . A NaN (Not a Number) is similar in spirit to the VAX's reserved operand, but very different in important details. Since the sign bit of a reserved operand makes it look negative,

$\text{copysign}(x, \text{reserved operand}) = -x$;

should this return the reserved operand instead?

NAME

inet_addr, *inet_network*, *inet_ntoa*, *inet_makeaddr*, *inet_lnaof*, *inet_netof* – Internet address manipulation routines

SYNOPSIS

```
#include <sys/socket.h>
#include <netinet/in.h>
#include <arpa/inet.h>

unsigned long inet_addr(cp)
char *cp;

unsigned long inet_network(cp)
char *cp;

char *inet_ntoa(in)
struct in_addr in;

struct in_addr inet_makeaddr(net, lna)
int net, lna;

int inet_lnaof(in)
struct in_addr in;

int inet_netof(in)
struct in_addr in;
```

DESCRIPTION

The routines *inet_addr* and *inet_network* each interpret character strings representing numbers expressed in the Internet standard “.” notation, returning numbers suitable for use as Internet addresses and Internet network numbers, respectively. The routine *inet_ntoa* takes an Internet address and returns an ASCII string representing the address in “.” notation. The routine *inet_makeaddr* takes an Internet network number and a local network address and constructs an Internet address from it. The routines *inet_netof* and *inet_lnaof* break apart Internet host addresses, returning the network number and local network address part, respectively.

All Internet address are returned in network order (bytes ordered from left to right). All network numbers and local address parts are returned as machine format integer values.

INTERNET ADDRESSES

Values specified using the “.” notation take one of the following forms:

```
a.b.c.d
a.b.c
a.b
a
```

When four parts are specified, each is interpreted as a byte of data and assigned, from left to right, to the four bytes of an Internet address. Note that when an Internet address is viewed as a 32-bit integer quantity on the VAX the bytes referred to above appear as “d.c.b.a”. That is, VAX bytes are ordered from right to left.

When a three part address is specified, the last part is interpreted as a 16-bit quantity and placed in the right most two bytes of the network address. This makes the three part address format convenient for specifying Class B network addresses as “128.net.host”.

When a two part address is supplied, the last part is interpreted as a 24-bit quantity and placed in the right most three bytes of the network address. This makes the two part address format convenient for specifying Class A network addresses as “net.host”.

When only one part is given, the value is stored directly in the network address without any byte rearrangement.

All numbers supplied as "parts" in a "." notation may be decimal, octal, or hexadecimal, as specified in the C language (i.e., a leading 0x or 0X implies hexadecimal; otherwise, a leading 0 implies octal; otherwise, the number is interpreted as decimal).

SEE ALSO

gethostbyname(3N), getnetent(3N), hosts(5), networks(5),

DIAGNOSTICS

The value -1 is returned by *inet_addr* and *inet_network* for malformed requests.

BUGS

The problem of host byte ordering versus network byte ordering is confusing. A simple way to specify Class C network addresses in a manner similar to that for Class B and Class A is needed. The string returned by *inet_ntoa* resides in a static memory area. *Inet_addr* should return a struct *in_addr*.

NAME

infnan – signals invalid floating-point operations on a VAX (temporary)

SYNOPSIS

```
#include <math.h>
```

```
double infnan(iarg)
```

```
int iarg;
```

DESCRIPTION

At some time in the future, some of the useful properties of the Infinities and NaNs in the IEEE standard 754 for Binary Floating-Point Arithmetic will be simulated in UNIX on the DEC VAX by using its Reserved Operands. Meanwhile, the Invalid, Overflow and Divide-by-Zero exceptions of the IEEE standard are being approximated on a VAX by calls to a procedure *infnan* in appropriate places in *libm*. When better exception-handling is implemented in UNIX, only *infnan* among the codes in *libm* will have to be changed. And users of *libm* can design their own *infnan* now to insulate themselves from future changes.

Whenever an elementary function code in *libm* has to simulate one of the aforementioned IEEE exceptions, it calls *infnan*(iarg) with an appropriate value of *iarg*. Then a reserved operand fault stops computation. But *infnan* could be replaced by a function with the same name that returns some plausible value, assigns an apt value to the global variable *errno*, and allows computation to resume. Alternatively, the Reserved Operand Fault Handler could be changed to respond by returning that plausible value, etc. instead of aborting.

In the table below, the first two columns show various exceptions signaled by the IEEE standard, and the default result it prescribes. The third column shows what value is given to *iarg* by functions in *libm* when they invoke *infnan*(iarg) under analogous circumstances on a VAX. Currently *infnan* stops computation under all those circumstances. The last two columns offer an alternative; they suggest a setting for *errno* and a value for a revised *infnan* to return. And a C program to implement that suggestion follows.

IEEE Signal	IEEE Default	<i>iarg</i>	<i>errno</i>	<i>infnan</i>
Invalid	NaN	EDOM	EDOM	0
Overflow	$\pm\infty$	ERANGE	ERANGE	HUGE
Div-by-0	$\pm\infty$	$\pm$ ERANGE	ERANGE or EDOM	$\pm$ HUGE

(HUGE = 1.7e38 ... nearly 2.0**127)

ALTERNATIVE *infnan*:

```
#include <math.h>
#include <errno.h>
extern int errno ;
double infnan(iarg)
int iarg ;
{
    switch(iarg) {
    case ERANGE: errno = ERANGE; return(HUGE);
    case -ERANGE: errno = EDOM; return(-HUGE);
    default:      errno = EDOM; return(0);
    }
}
```

SEE ALSO

math(3M), intro(2), signal(3).

ERANGE and EDOM are defined in <errno.h>. See intro(2) for explanation of EDOM and ERANGE.

NAME

initgroups – initialize group access list

SYNOPSIS

initgroups(name, basegid)

char *name;

int basegid;

DESCRIPTION

Initgroups reads through the group file and sets up, using the *setgroups(2)* call, the group access list for the user specified in *name*. The *basegid* is automatically included in the groups list. Typically this value is given as the group number from the password file.

FILES

/etc/group

SEE ALSO

setgroups(2)

DIAGNOSTICS

Initgroups returns -1 if it was not invoked by the super-user.

BUGS

Initgroups uses the routines based on *getgrent(3)*. If the invoking program uses any of these routines, the group structure will be overwritten in the call to *initgroups*.

P
R
M
3

NAME

insque, remque – insert/remove element from a queue

SYNOPSIS

```
struct qelem {
    struct qelem *q_forw;
    struct qelem *q_back;
    char q_data[];
};

insque(elem, pred)
struct qelem *elem, *pred;

remque(elem)
struct qelem *elem;
```

DESCRIPTION

Insque and *remque* manipulate queues built from doubly linked lists. Each element in the queue must in the form of "struct qelem". *Insque* inserts *elem* in a queue immediately after *pred*; *remque* removes an entry *elem* from a queue.

SEE ALSO

"VAX Architecture Handbook", pp. 228-235.

P
R
M
3

NAME

j0, j1, jn, y0, y1, yn – bessel functions

SYNOPSIS

```
#include <math.h>
```

```
double j0(x)
```

```
double x;
```

```
double j1(x)
```

```
double x;
```

```
double jn(n,x)
```

```
int n;
```

```
double x;
```

```
double y0(x)
```

```
double x;
```

```
double y1(x)
```

```
double x;
```

```
double yn(n,x)
```

```
int n;
```

```
double x;
```

DESCRIPTION

These functions calculate Bessel functions of the first and second kinds for real arguments and integer orders.

DIAGNOSTICS

On a VAX, negative arguments cause y0, y1 and yn to return the reserved operand and set *errno* to EDOM.

SEE ALSO

math(3M), infnan(3M)

NAME

lgamma - log gamma function

SYNOPSIS

```
#include <math.h>
```

```
double lgamma(x)
```

```
double x;
```

DESCRIPTION

Lgamma returns $\ln |\Gamma(x)|$ where $\Gamma(x) = \int_0^\infty t^{x-1} e^{-t} dt$ for $x > 0$ and $\Gamma(x) = \pi/(\Gamma(1-x)\sin(\pi x))$ for $x < 1$.

The external integer signgam returns the sign of $\Gamma(x)$.

IDIOSYNCRASIES

Do not use the expression `signgam*exp(lgamma(x))` to compute $g := \Gamma(x)$. Instead use a program like this (in C):

```
lg = lgamma(x); g = signgam*exp(lg);
```

Only after lgamma has returned can signgam be correct. Note too that $\Gamma(x)$ must overflow when x is large enough, underflow when $-x$ is large enough, and spawn a division by zero when x is a nonpositive integer.

Only in the UNIX math library for C was the name gamma ever attached to $\ln \Gamma$. Elsewhere, for instance in IBM's FORTRAN library, the name GAMMA belongs to Γ and the name ALGAMA to $\ln \Gamma$ in single precision; in double the names are DGAMMA and DLGAMA. Why should C be different?

Archaeological records suggest that C's gamma originally delivered $\ln(\Gamma(|x|))$. Later, the program gamma was changed to cope with negative arguments x in a more conventional way, but the documentation did not reflect that change correctly. The most recent change corrects inaccurate values when x is almost a negative integer, and lets $\Gamma(x)$ be computed without conditional expressions. Programmers should not assume that lgamma has settled down.

At some time in the future, the name *gamma* will be rehabilitated and used for the gamma function, just as is done in FORTRAN. The reason for this is not so much compatibility with FORTRAN as a desire to achieve greater speed for smaller values of $|x|$ and greater accuracy for larger values.

Meanwhile, programmers who have to use the name *gamma* in its former sense, for what is now *lgamma*, have two choices:

- 1) Use the old math library, *libom*.
- 2) Add the following program to your others:

```
#include <math.h>
double gamma(x)
double x;
{
    return (lgamma(x));
}
```

DIAGNOSTICS

The reserved operand is returned on a VAX for negative integer arguments, *errno* is set to ERANGE; for very large arguments over/underflows will occur inside the *lgamma* routine.

SEE ALSO

math(3M), infnan(3M)

NAME

lib2648 – subroutines for the HP 2648 graphics terminal

SYNOPSIS

```
#include <stdio.h>
```

```
typedef char *bitmat;
FILE *trace;
```

```
cc file.c -l2648
```

DESCRIPTION

Lib2648 is a general purpose library of subroutines useful for interactive graphics on the Hewlett-Packard 2648 graphics terminal. To use it you must call the routine *ttyinit()* at the beginning of execution, and *done()* at the end of execution. All terminal input and output must go through the routines *rawchar*, *readline*, *outchar*, and *outstr*.

Lib2648 does the necessary *^E/^F* handshaking if *getenv("TERM")* returns "hp2648", as it will if set by *tset(1)*. Any other value, including for example "2648", will disable handshaking.

Bit matrix routines are provided to model the graphics memory of the 2648. These routines are generally useful, but are specifically useful for the *update* function which efficiently changes what is on the screen to what is supposed to be on the screen. The primitive bit matrix routines are *newmat*, *mat*, and *setmat*.

The file *trace*, if non-null, is expected to be a file descriptor as returned by *fopen*. If so, *lib2648* will trace the progress of the output by writing onto this file. It is provided to make debugging output feasible for graphics programs without messing up the screen or the escape sequences being sent. Typical use of trace will include:

```
switch (argv[1][1]) {
    case 'T':
        trace = fopen("trace", "w");
        break;
    ...
    if (trace)
        fprintf(trace, "x is %d, y is %s\n", x, y);
    ...
    dumpmat("before update", xmat);
```

ROUTINES

agoto(x, y)

Move the alphanumeric cursor to position (x, y), measured from the upper left corner of the screen.

aoff() Turn the alphanumeric display off.

aon() Turn the alphanumeric display on.

areaclear(rmin, cmin, rmax, cmax)

Clear the area on the graphics screen bordered by the four arguments. In normal mode the area is set to all black, in inverse video mode it is set to all white.

beep() Ring the bell on the terminal.

bitcopy(dest, src, rows, cols) bitmat dest,

Copy a *rows* by *cols* bit matrix from *src* to (user provided) *dest*.

cleara()

Clear the alphanumeric display.

- clearg()**
Clear the graphics display. Note that the 2648 will only clear the part of the screen that is visible if zoomed in.
- curoff()** Turn the graphics cursor off.
- curon()** Turn the graphics cursor on.
- dispmsg(str, x, y, maxlen) char *str;**
Display the message *str* in graphics text at position (x, y) . The maximum message length is given by *maxlen*, and is needed for *dispmsg* to know how big an area to clear before drawing the message. The lower left corner of the first character is at (x, y) .
- done()** Should be called before the program exits. Restores the tty to normal, turns off graphics screen, turns on alphanumeric screen, flushes the standard output, etc.
- draw(x, y)**
Draw a line from the pen location to (x, y) . As with all graphics coordinates, (x, y) is measured from the bottom left corner of the screen. (x, y) coordinates represent the first quadrant of the usual Cartesian system.
- drawbox(r, c, color, rows, cols)**
Draw a rectangular box on the graphics screen. The lower left corner is at location (r, c) . The box is *rows* rows high and *cols* columns wide. The box is drawn if *color* is 1, erased if *color* is 0. (r, c) absolute coordinates represent row and column on the screen, with the origin at the lower left. They are equivalent to (x, y) except for being reversed in order.
- dumpmat(msg, m, rows, cols) char *msg; bitmat m;**
If *trace* is non-null, write a readable ASCII representation of the matrix *m* on *trace*. *Msg* is a label to identify the output.
- emptyrow(m, rows, cols, r) bitmat m;**
Returns 1 if row *r* of matrix *m* is all zero, else returns 0. This routine is provided because it can be implemented more efficiently with a knowledge of the internal representation than a series of calls to *mat*.
- error(msg) char *msg;**
Default error handler. Calls *message(msg)* and returns. This is called by certain routines in *lib2648*. It is also suitable for calling by the user program. It is probably a good idea for a fancy graphics program to supply its own error procedure which uses *setjmp(3)* to restart the program.
- gdefault()**
Set the terminal to the default graphics modes.
- goff()** Turn the graphics display off.
- gon()** Turn the graphics display on.
- koff()** Turn the keypad off.
- kon()** Turn the keypad on. This means that most special keys on the terminal (such as the alphanumeric arrow keys) will transmit an escape sequence instead of doing their function locally.
- line(x1, y1, x2, y2)**
Draw a line in the current mode from $(x1, y1)$ to $(x2, y2)$. This is equivalent to *move(x1, y1); draw(x2, y2);* except that a bug in the terminal involving repeated lines from the same point is compensated for.

lowleft()

Move the alphanumeric cursor to the lower left (home down) position.

mat(m, rows, cols, r, c) bitmat m;

Used to retrieve an element from a bit matrix. Returns 1 or 0 as the value of the *r, c* element of the *rows* by *cols* matrix *m*. Bit matrices are numbered (*r, c*) from the upper left corner of the matrix, beginning at (0, 0). *R* represents the row, and *c* represents the column.

message(str) char *str;

Display the text message *str* at the bottom of the graphics screen.

minmax(g, rows, cols, rmin, cmin, rmax, cmax) bitmat g;**int *rmin, *cmin, *rmax, *cmax;**

Find the smallest rectangle that contains all the 1 (on) elements in the bit matrix *g*. The coordinates are returned in the variables pointed to by *rmin*, *cmin*, *rmax*, *cmax*.

move(x, y)

Move the pen to location (*x, y*). Such motion is internal and will not cause output until a subsequent *sync()*.

movecurs(x, y)

Move the graphics cursor to location (*x, y*).

bitmat newmat(rows, cols)

Create (with *malloc(3)*) a new bit matrix of size *rows* by *cols*. The value created (e.g. a pointer to the first location) is returned. A bit matrix can be freed directly with *free*.

outchar(c) char c;

Print the character *c* on the standard output. All output to the terminal should go through this routine or *outstr*.

outstr(str) char *str;

Print the string *str* on the standard output by repeated calls to *outchar*.

printg()

Print the graphics display on the printer. The printer must be configured as device 6 (the default) on the HPIB.

char rawchar()

Read one character from the terminal and return it. This routine or *readline* should be used to get all input, rather than *getchar(3)*.

rboff() Turn the rubber band line off.**rbon()** Turn the rubber band line on.**char *rdchar(c) char c;**

Return a readable representation of the character *c*. If *c* is a printing character it returns itself, if a control character it is shown in the ^X notation, if negative an apostrophe is prepended. Space returns ^, rubout returns ^?.

NOTE: A pointer to a static place is returned. For this reason, it will not work to pass *rdchar* twice to the same *sprintf/sprintf* call. You must instead save one of the values in your own buffer with *strcpy*.

readline(prompt, msg, maxlen) char *prompt, *msg;

Display *prompt* on the bottom line of the graphics display and read one line of text from the user, terminated by a newline. The line is placed in the buffer *msg*, which has size *maxlen* characters. Backspace processing is supported.

setclear()

Set the display to draw lines in erase mode. (This is reversed by inverse video mode.)

setmat(m, rows, cols, r, c, val) bitmat *m*;

The basic operation to store a value in an element of a bit matrix. The *[r, c]* element of *m* is set to *val*, which should be either 0 or 1.

setset() Set the display to draw lines in normal (solid) mode. (This is reversed by inverse video mode.)

setxor()

Set the display to draw lines in exclusive or mode.

sync() Force all accumulated output to be displayed on the screen. This should be followed by *fflush(stdout)*. The cursor is not affected by this function. Note that it is normally never necessary to call *sync*, since *rawchar* and *readline* call *sync()* and *fflush(stdout)* automatically.

togvid()

Toggle the state of video. If in normal mode, go into inverse video mode, and vice versa. The screen is reversed as well as the internal state of the library.

ttyinit()

Set up the terminal for processing. This routine should be called at the beginning of execution. It places the terminal in CBREAK mode, turns off echo, sets the proper modes in the terminal, and initializes the library.

update(mold, mnew, rows, cols, baser, basec) bitmat *mold*, *mnew*;

Make whatever changes are needed to make a window on the screen look like *mnew*. *Mold* is what the window on the screen currently looks like. The window has size *rows* by *cols*, and the lower left corner on the screen of the window is *[baser, basec]*. Note: *update* was not intended to be used for the entire screen. It would work but be very slow and take 64K bytes of memory just for *mold* and *mnew*. It was intended for 100 by 100 windows with objects in the center of them, and is quite fast for such windows.

vidinv()

Set inverse video mode.

vidnorm()

Set normal video mode.

zermat(m, rows, cols) bitmat *m*;

Set the bit matrix *m* to all zeros.

zoomn(size)

Set the hardware zoom to value *size*, which can range from 1 to 15.

zoomoff()

Turn zoom off. This forces the screen to zoom level 1 without affecting the current internal zoom number.

zoomon()

Turn zoom on. This restores the screen to the previously specified zoom size.

DIAGNOSTICS

The routine *error* is called when an error is detected. The only error currently detected is overflow of the buffer provided to *readline*.

Subscripts out of bounds to *setmat* return without setting anything.

FILES

/usr/lib/lib2648.a

SEE ALSO

fed(1)

AUTHOR

Mark Horton

BUGS

This library is not supported. It makes no attempt to use all of the features of the terminal, only those needed by fed. Contributions from users will be accepted for addition to the library.

The HP 2648 terminal is somewhat unreliable at speeds over 2400 baud, even with the ^E/^F handshaking. In an effort to improve reliability, handshaking is done every 32 characters. (The manual claims it is only necessary every 80 characters.) Nonetheless, I/O errors sometimes still occur.

There is no way to control the amount of debugging output generated on *trace* without modifying the source to the library.

P
R
M
3

NAME

malloc, *free*, *realloc*, *calloc*, *alloca* – memory allocator

SYNOPSIS

```
char *malloc(size)
    unsigned size;

free(ptr)
    char *ptr;

char *realloc(ptr, size)
    char *ptr;
    unsigned size;

char *calloc(nelem, elsize)
    unsigned nelem, elsize;

char *alloca(size)
    int size;
```

DESCRIPTION

Malloc and *free* provide a general-purpose memory allocation package. *Malloc* returns a pointer to a block of at least *size* bytes beginning on a word boundary.

The argument to *free* is a pointer to a block previously allocated by *malloc*; this space is made available for further allocation, but its contents are left undisturbed.

Needless to say, grave disorder will result if the space assigned by *malloc* is overrun or if some random number is handed to *free*.

Malloc maintains multiple lists of free blocks according to size, allocating space from the appropriate list. It calls *sbrk* (see *brk(2)*) to get more memory from the system when there is no suitable space already free.

Realloc changes the size of the block pointed to by *ptr* to *size* bytes and returns a pointer to the (possibly moved) block. The contents will be unchanged up to the lesser of the new and old sizes.

In order to be compatible with older versions, *realloc* also works if *ptr* points to a block freed since the last call of *malloc*, *realloc* or *calloc*; sequences of *free*, *malloc* and *realloc* were previously used to attempt storage compaction. This procedure is no longer recommended.

Calloc allocates space for an array of *nelem* elements of size *elsize*. The space is initialized to zeros.

Alloca allocates *size* bytes of space in the stack frame of the caller. This temporary space is automatically freed on return.

Each of the allocation routines returns a pointer to space suitably aligned (after possible pointer coercion) for storage of any type of object. If the space is of *pagesize* or larger, the memory returned will be page-aligned.

SEE ALSO

brk(2), *pagesize(2)*

DIAGNOSTICS

Malloc, *realloc* and *calloc* return a null pointer (0) if there is no available memory or if the arena has been detectably corrupted by storing outside the bounds of a block. *Malloc* may be recompiled to check the arena very stringently on every transaction; those sites with a source code license may check the source code to see how this can be done.

BUGS

When *realloc* returns 0, the block pointed to by *ptr* may be destroyed.

The current implementation of *malloc* does not always fail gracefully when system memory limits are approached. It may fail to allocate memory when larger free blocks could be broken up, or when limits are exceeded because the size is rounded up. It is optimized for sizes that are powers of two.

Alloc is machine dependent; its use is discouraged.

NAME

math - introduction to mathematical library functions

DESCRIPTION

These functions constitute the C math library, *libm*. The link editor searches this library under the "-lm" option. Declarations for these functions may be obtained from the include file *<math.h>*. The Fortran math library is described in "man 3f intro".

LIST OF FUNCTIONS

Name	Appears on Page	Description	Error Bound (ULPs)
acos	sin.3m	inverse trigonometric function	3
acosh	asinh.3m	inverse hyperbolic function	3
asin	sin.3m	inverse trigonometric function	3
asinh	asinh.3m	inverse hyperbolic function	3
atan	sin.3m	inverse trigonometric function	1
atanh	asinh.3m	inverse hyperbolic function	3
atan2	sin.3m	inverse trigonometric function	2
cabs	hypot.3m	complex absolute value	1
cbrt	sqrt.3m	cube root	1
ceil	floor.3m	integer no less than	0
copysign	ieee.3m	copy sign bit	0
cos	sin.3m	trigonometric function	1
cosh	sinh.3m	hyperbolic function	3
drem	ieee.3m	remainder	0
erf	erf.3m	error function	???
erfc	erf.3m	complementary error function	???
exp	exp.3m	exponential	1
expm1	exp.3m	exp(x)-1	1
fabs	floor.3m	absolute value	0
floor	floor.3m	integer no greater than	0
hypot	hypot.3m	Euclidean distance	1
infnan	infnan.3m	signals exceptions	
j0	j0.3m	bessel function	???
j1	j0.3m	bessel function	???
jn	j0.3m	bessel function	???
lgamma	lgamma.3m	log gamma function; (formerly gamma.3m)	
log	exp.3m	natural logarithm	1
logb	ieee.3m	exponent extraction	0
log10	exp.3m	logarithm to base 10	3
log1p	exp.3m	log(1+x)	1
pow	exp.3m	exponential x**y	60-500
rint	floor.3m	round to nearest integer	0
scalb	ieee.3m	exponent adjustment	0
sin	sin.3m	trigonometric function	1
sinh	sinh.3m	hyperbolic function	3
sqrt	sqrt.3m	square root	1
tan	sin.3m	trigonometric function	3
tanh	sinh.3m	hyperbolic function	3
y0	j0.3m	bessel function	???
y1	j0.3m	bessel function	???
yn	j0.3m	bessel function	???

NOTES

In 4.3 BSD, distributed from the University of California in late 1985, most of the foregoing functions come in two versions, one for the double-precision "D" format in the DEC

VAX-11 family of computers, another for double-precision arithmetic conforming to the IEEE Standard 754 for Binary Floating-Point Arithmetic. The two versions behave very similarly, as should be expected from programs more accurate and robust than was the norm when UNIX was born. For instance, the programs are accurate to within the numbers of *ulps* tabulated above; an *ulp* is one Unit in the Last Place. And the programs have been cured of anomalies that afflicted the older math library *libm* in which incidents like the following had been reported:

```
sqrt(-1.0) = 0.0 and log(-1.0) = -1.7e38.
cos(1.0e-11) > cos(0.0) > 1.0.
pow(x,1.0) ≠ x when x = 2.0, 3.0, 4.0, ..., 9.0.
pow(-1.0,1.0e10) trapped on Integer Overflow.
sqrt(1.0e30) and sqrt(1.0e-30) were very slow.
```

However the two versions do differ in ways that have to be explained, to which end the following notes are provided.

DEC VAX-11 D_floating-point:

This is the format for which the original math library *libm* was developed, and to which this manual is still principally dedicated. It is *the* double-precision format for the PDP-11 and the earlier VAX-11 machines; VAX-11s after 1983 were provided with an optional "G" format closer to the IEEE double-precision format. The earlier DEC MicroVAXs have no D format, only G double-precision. (Why? Why not?)

Properties of D_floating-point:

Wordsize: 64 bits, 8 bytes. Radix: Binary.

Precision: 56 significant bits, roughly like 17 significant decimals.

If x and x' are consecutive positive D_floating-point numbers (they differ by 1 *ulp*), then

$1.3e-17 < 0.5**56 < (x'-x)/x \leq 0.5**55 < 2.8e-17$.

Range: Overflow threshold = $2.0**127 = 1.7e38$.

Underflow threshold = $0.5**128 = 2.9e-39$.

NOTE: THIS RANGE IS COMPARATIVELY NARROW.

Overflow customarily stops computation.

Underflow is customarily flushed quietly to zero.

CAUTION:

It is possible to have $x \neq y$ and yet $x-y = 0$ because of underflow.

Similarly $x > y > 0$ cannot prevent either $x*y = 0$ or $y/x = 0$ from happening without warning.

Zero is represented ambiguously.

Although $2**55$ different representations of zero are accepted by the hardware, only the obvious representation is ever produced. There is no -0 on a VAX.

∞ is not part of the VAX architecture.

Reserved operands:

of the $2**55$ that the hardware recognizes, only one of them is ever produced.

Any floating-point operation upon a reserved operand, even a MOVF or MOVD, customarily stops computation, so they are not much used.

Exceptions:

Divisions by zero and operations that overflow are invalid operations that customarily stop computation or, in earlier machines, produce reserved operands that will stop computation.

Rounding:

Every rational operation (+, -, *, /) on a VAX (but not necessarily on a PDP-11), if not an over/underflow nor division by zero, is rounded to within half an *ulp*, and when the rounding error is exactly half an *ulp* then rounding

is away from 0.

Except for its narrow range, `D_floating-point` is one of the better computer arithmetics designed in the 1960's. Its properties are reflected fairly faithfully in the elementary functions for a VAX distributed in 4.3 BSD. They over/underflow only if their results have to lie out of range or very nearly so, and then they behave much as any rational arithmetic operation that over/underflowed would behave. Similarly, expressions like `log(0)` and `atanh(1)` behave like 1/0; and `sqrt(-3)` and `acos(3)` behave like 0/0; they all produce reserved operands and/or stop computation! The situation is described in more detail in manual pages.

This response seems excessively punitive, so it is destined to be replaced at some time in the foreseeable future by a more flexible but still uniform scheme being developed to handle all floating-point arithmetic exceptions neatly. See `infnan(3M)` for the present state of affairs.

How do the functions in 4.3 BSD's new `libm` for UNIX compare with their counterparts in DEC's VAX/VMS library? Some of the VMS functions are a little faster, some are a little more accurate, some are more puritanical about exceptions (like `pow(0.0,0.0)` and `atan2(0.0,0.0)`), and most occupy much more memory than their counterparts in `libm`. The VMS codes interpolate in large table to achieve speed and accuracy; the `libm` codes use tricky formulas compact enough that all of them may some day fit into a ROM.

More important, DEC regards the VMS codes as proprietary and guards them zealously against unauthorized use. But the `libm` codes in 4.3 BSD are intended for the public domain; they may be copied freely provided their provenance is always acknowledged, and provided users assist the authors in their researches by reporting experience with the codes. Therefore no user of UNIX on a machine whose arithmetic resembles VAX `D_floating-point` need use anything worse than the new `libm`.

IEEE STANDARD 754 Floating-Point Arithmetic:

This standard is on its way to becoming more widely adopted than any other design for computer arithmetic. VLSI chips that conform to some version of that standard have been produced by a host of manufacturers, among them ...

Intel i8087, i80287	National Semiconductor 32081
Motorola 68881	Weitek WTL-1032, ... , -1165
Zilog Z8070	Western Electric (AT&T) WE32106.

Other implementations range from software, done thoroughly in the Apple Macintosh, through VLSI in the Hewlett-Packard 9000 series, to the ELXSI 6400 running ECL at 3 Megaflops. Several other companies have adopted the formats of IEEE 754 without, alas, adhering to the standard's way of handling rounding and exceptions like over/underflow. The DEC VAX `G_floating-point` format is very similar to the IEEE 754 Double format, so similar that the C programs for the IEEE versions of most of the elementary functions listed above could easily be converted to run on a MicroVAX, though nobody has volunteered to do that yet.

The codes in 4.3 BSD's `libm` for machines that conform to IEEE 754 are intended primarily for the National Semi. 32081 and WTL 1164/65. To use these codes with the Intel or Zilog chips, or with the Apple Macintosh or ELXSI 6400, is to forego the use of better codes provided (perhaps freely) by those companies and designed by some of the authors of the codes above. Except for `atan`, `cabs`, `cbt`, `erf`, `erfc`, `hypot`, `j0-jn`, `lgamma`, `pow` and `y0-yn`, the Motorola 68881 has all the functions in `libm` on chip, and faster and more accurate; it, Apple, the i8087, Z8070 and WE32106 all use 64 significant bits. The main virtue of 4.3 BSD's `libm` codes is that they are intended for the public domain; they may be copied freely provided their provenance is always acknowledged, and provided users assist the authors in their researches by reporting experience with the codes. Therefore no user of UNIX on a machine that conforms to IEEE 754 need use anything worse than the new `libm`.

Properties of IEEE 754 Double-Precision:

Wordsize: 64 bits, 8 bytes. Radix: Binary.

Precision: 53 significant bits, roughly like 16 significant decimals.

If x and x' are consecutive positive Double-Precision numbers (they differ by 1 *ulp*), then

$$1.1e-16 < 0.5**53 < (x'-x)/x \leq 0.5**52 < 2.3e-16.$$

Range: Overflow threshold = $2.0**1024 = 1.8e308$

Underflow threshold = $0.5**1022 = 2.2e-308$

Overflow goes by default to a signed ∞ .

Underflow is *Gradual*, rounding to the nearest integer multiple of $0.5**1074 = 4.9e-324$.

Zero is represented ambiguously as +0 or -0.

Its sign transforms correctly through multiplication or division, and is preserved by addition of zeros with like signs; but $x-x$ yields +0 for every finite x . The only operations that reveal zero's sign are division by zero and `copysign(x,±0)`. In particular, comparison ($x > y$, $x \geq y$, etc.) cannot be affected by the sign of zero; but if finite $x = y$ then $\infty = 1/(x-y) \neq -1/(y-x) = -\infty$.

∞ is signed.

it persists when added to itself or to any finite number. Its sign transforms correctly through multiplication and division, and $(\text{finite})/\pm\infty = \pm 0$ ($\text{nonzero}/0 = \pm\infty$). But $\infty-\infty$, $\infty*0$ and ∞/∞ are, like $0/0$ and $\text{sqrt}(-3)$, invalid operations that produce *NaN*. ...

Reserved operands:

there are $2**53-2$ of them, all called *NaN* (*Not a Number*). Some, called *Signaling NaNs*, trap any floating-point operation performed upon them; they are used to mark missing or uninitialized values, or nonexistent elements of arrays. The rest are *Quiet NaNs*; they are the default results of Invalid Operations, and propagate through subsequent arithmetic operations. If $x \neq x$ then x is *NaN*; every other predicate ($x > y$, $x = y$, $x < y$, ...) is FALSE if *NaN* is involved.

NOTE: Trichotomy is violated by *NaN*.

Besides being FALSE, predicates that entail ordered comparison, rather than mere (in)equality, signal Invalid Operation when *NaN* is involved.

Rounding:

Every algebraic operation (+, -, *, /, $\sqrt{}$) is rounded by default to within half an *ulp*, and when the rounding error is exactly half an *ulp* then the rounded value's least significant bit is zero. This kind of rounding is usually the best kind, sometimes provably so; for instance, for every $x = 1.0, 2.0, 3.0, 4.0, \dots, 2.0**52$, we find $(x/3.0)*3.0 == x$ and $(x/10.0)*10.0 == x$... despite that both the quotients and the products have been rounded. Only rounding like IEEE 754 can do that. But no single kind of rounding can be proved best for every circumstance, so IEEE 754 provides rounding towards zero or towards + ∞ or towards - ∞ at the programmer's option. And the same kinds of rounding are specified for Binary-Decimal Conversions, at least for magnitudes between roughly $1.0e-10$ and $1.0e37$.

Exceptions:

IEEE 754 recognizes five kinds of floating-point exceptions, listed below in declining order of probable importance.

Exception	Default Result
Invalid Operation	<i>NaN</i> , or FALSE

P
R
M
3

Overflow	$\pm\infty$
Divide by Zero	$\pm\infty$
Underflow	Gradual Underflow
Inexact	Rounded value

NOTE: An Exception is not an Error unless handled badly. What makes a class of exceptions exceptional is that no single default response can be satisfactory in every instance. On the other hand, if a default response will serve most instances satisfactorily, the unsatisfactory instances cannot justify aborting computation every time the exception occurs.

For each kind of floating-point exception, IEEE 754 provides a Flag that is raised each time its exception is signaled, and stays raised until the program resets it. Programs may also test, save and restore a flag. Thus, IEEE 754 provides three ways by which programs may cope with exceptions for which the default result might be unsatisfactory:

- 1) Test for a condition that might cause an exception later, and branch to avoid the exception.
- 2) Test a flag to see whether an exception has occurred since the program last reset its flag.
- 3) Test a result to see whether it is a value that only an exception could have produced.

CAUTION: The only reliable ways to discover whether Underflow has occurred are to test whether products or quotients lie closer to zero than the underflow threshold, or to test the Underflow flag. (Sums and differences cannot underflow in IEEE 754; if $x \neq y$ then $x-y$ is correct to full precision and certainly nonzero regardless of how tiny it may be.) Products and quotients that underflow gradually can lose accuracy gradually without vanishing, so comparing them with zero (as one might on a VAX) will not reveal the loss. Fortunately, if a gradually underflowed value is destined to be added to something bigger than the underflow threshold, as is almost always the case, digits lost to gradual underflow will not be missed because they would have been rounded off anyway. So gradual underflows are usually *provably* ignorable. The same cannot be said of underflows flushed to 0.

At the option of an implementor conforming to IEEE 754, other ways to cope with exceptions may be provided:

- 4) ABORT. This mechanism classifies an exception in advance as an incident to be handled by means traditionally associated with error-handling statements like "ON ERROR GO TO ...". Different languages offer different forms of this statement, but most share the following characteristics:
 - No means is provided to substitute a value for the offending operation's result and resume computation from what may be the middle of an expression. An exceptional result is abandoned.
 - In a subprogram that lacks an error-handling statement, an exception causes the subprogram to abort within whatever program called it, and so on back up the chain of calling subprograms until an error-handling statement is encountered or the whole task is aborted and memory is dumped.
- 5) STOP. This mechanism, requiring an interactive debugging environment, is more for the programmer than the program. It classifies an exception in advance as a symptom of a programmer's error; the exception suspends execution as near as it can to the offending operation so that the programmer can look around to see how it happened. Quite often the first several exceptions turn out to be quite

unexceptionable, so the programmer ought ideally to be able to resume execution after each one as if execution had not been stopped.

6) ... Other ways lie beyond the scope of this document.

The crucial problem for exception handling is the problem of Scope, and the problem's solution is understood, but not enough manpower was available to implement it fully in time to be distributed in 4.3 BSD's *libm*. Ideally, each elementary function should act as if it were indivisible, or atomic, in the sense that ...

- i) No exception should be signaled that is not deserved by the data supplied to that function.
- ii) Any exception signaled should be identified with that function rather than with one of its subroutines.
- iii) The internal behavior of an atomic function should not be disrupted when a calling program changes from one to another of the five or so ways of handling exceptions listed above, although the definition of the function may be correlated intentionally with exception handling.

Ideally, every programmer should be able *conveniently* to turn a debugged subprogram into one that appears atomic to its users. But simulating all three characteristics of an atomic function is still a tedious affair, entailing hosts of tests and saves-restores; work is under way to ameliorate the inconvenience.

Meanwhile, the functions in *libm* are only approximately atomic. They signal no inappropriate exception except possibly ...

Over/Underflow

when a result, if properly computed, might have lain barely within range, and

Inexact in *cabs*, *cbrt*, *hypot*, *log10* and *pow*

when it happens to be exact, thanks to fortuitous cancellation of errors.

Otherwise, ...

Invalid Operation is signaled only when

any result but *NaN* would probably be misleading.

Overflow is signaled only when

the exact result would be finite but beyond the overflow threshold.

Divide-by-Zero is signaled only when

a function takes exactly infinite values at finite operands.

Underflow is signaled only when

the exact result would be nonzero but tinier than the underflow threshold.

Inexact is signaled only when

greater range or precision would be needed to represent the exact result.

BUGS

When signals are appropriate, they are emitted by certain operations within the codes, so a subroutine-trace may be needed to identify the function with its signal in case method 5) above is in use. And the codes all take the IEEE 754 defaults for granted; this means that a decision to trap all divisions by zero could disrupt a code that would otherwise get correct results despite division by zero.

SEE ALSO

An explanation of IEEE 754 and its proposed extension p854 was published in the IEEE magazine MICRO in August 1984 under the title "A Proposed Radix- and Word-length-independent Standard for Floating-point Arithmetic" by W. J. Cody et al. The manuals for Pascal, C and BASIC on the Apple Macintosh document the features of IEEE 754 pretty well. Articles in the IEEE magazine COMPUTER vol. 14 no. 3 (Mar. 1981), and in the ACM SIGNUM Newsletter Special Issue of Oct. 1979, may be helpful although they pertain to superseded drafts of the standard.

AUTHOR

W. Kahan, with the help of Z-S. Alex Liu, Stuart I. McDonald, Dr. Kwok-Choi Ng, Peter Tang.

P
R
M

3

NAME

mktemp – make a unique file name

SYNOPSIS

char *mktemp(template)

char *template;

mkstemp(template)

char *template;

DESCRIPTION

Mktemp creates a unique file name, typically in a temporary filesystem, by replacing *template* with a unique file name, and returns the address of the template. The template should contain a file name with six trailing X's, which are replaced with the current process id and a unique letter. *Mkstemp* makes the same replacement to the template but returns a file descriptor for the template file open for reading and writing. *Mkstemp* avoids the race between testing whether the file exists and opening it for use.

SEE ALSO

getpid(2), open(2)

DIAGNOSTICS

Mkstemp returns an open file descriptor upon success. It returns -1 if no suitable file could be created.

NAME

monitor, monstartup, moncontrol – prepare execution profile

SYNOPSIS

```
monitor(lowpc, highpc, buffer, bufsize, nfunc)
int (*lowpc)(), (*highpc)();
short buffer[];
```

```
monstartup(lowpc, highpc)
int (*lowpc)(), (*highpc)();
```

```
moncontrol(mode)
```

DESCRIPTION

There are two different forms of monitoring available: An executable program created by:

```
cc -p . . .
```

automatically includes calls for the *profil*(1) monitor and includes an initial call to its start-up routine *monstartup* with default parameters; *monitor* need not be called explicitly except to gain fine control over profil buffer allocation. An executable program created by:

```
cc -pg . . .
```

automatically includes calls for the *gprofil*(1) monitor.

Monstartup is a high level interface to *profil*(2). *Lowpc* and *highpc* specify the address range that is to be sampled; the lowest address sampled is that of *lowpc* and the highest is just below *highpc*. *Monstartup* allocates space using *sbrk*(2) and passes it to *monitor* (see below) to record a histogram of periodically sampled values of the program counter, and of counts of calls of certain functions, in the buffer. Only calls of functions compiled with the profiling option *-p* of *cc*(1) are recorded.

To profile the entire program, it is sufficient to use

```
extern etext();
. . .
monstartup((int) 2, etext);
```

Etext lies just above all the program text, see *end*(3).

To stop execution monitoring and write the results on the file *mon.out*, use

```
monitor(0);
```

then *profil*(1) can be used to examine the results.

Moncontrol is used to selectively control profiling within a program. This works with either *profil*(1) or *gprofil*(1) type profiling. When the program starts, profiling begins. To stop the collection of histogram ticks and call counts use *moncontrol*(0); to resume the collection of histogram ticks and call counts use *moncontrol*(1). This allows the cost of particular operations to be measured. Note that an output file will be produced upon program exit regardless of the state of *moncontrol*.

Monitor is a low level interface to *profil*(2). *Lowpc* and *highpc* are the addresses of two functions; *buffer* is the address of a (user supplied) array of *bufsize* short integers. At most *nfunc* call counts can be kept. For the results to be significant, especially where there are small, heavily used routines, it is suggested that the buffer be no more than a few times smaller than the range of locations sampled. *Monitor* divides the buffer into space to record the histogram of program counter samples over the range *lowpc* to *highpc*, and space to record call counts of functions compiled with the *-p* option to *cc*(1).

To profile the entire program, it is sufficient to use

```
extern etext();
```

```
...
```

```
monitor((int) 2, etext, buf, bufsize, nfunc);
```

FILES

mon.out

SEE ALSO

cc(1), prof(1), gprof(1), profil(2), sbrk(2)

NAME

madd, msub, mult, mdiv, pow, gcd, invert, rpow, msqrt, mcmp, move, min, omin, fmin, m_in, mout, omout, fmout, m_out, sdiv, itom - multiple precision integer arithmetic

SYNOPSIS

```
#include <mp.h>
#include <stdio.h>

typedef struct mint { int len; short *val; } MINT;

madd(a, b, c)
msub(a, b, c)
mult(a, b, c)
mdiv(a, b, q, r)
pow(a, b, m, c)
gcd(a, b, c)
invert(a, b, c)
rpow(a, n, c)
msqrt(a, b, r)
mcmp(a, b)
move(a, b)
min(a)
omin(a)
fmin(a, f)
m_in(a, n, f)
mout(a)
omout(a)
fmout(a, f)
m_out(a, n, f)
MINT *a, *b, *c, *m, *q, *r;
FILE *f;
int n;

sdiv(a, n, q, r)
MINT *a, *q;
short n;
short *r;

MINT *itom(n)
```

DESCRIPTION

These routines perform arithmetic on integers of arbitrary length. The integers are stored using the defined type *MINT*. Pointers to a *MINT* can be initialized using the function *itom* which sets the initial value to *n*. After that, space is managed automatically by the routines.

madd, *msub* and *mult* assign to *c* the sum, difference and product, respectively, of *a* and *b*. *mdiv* assigns to *q* and *r* the quotient and remainder obtained from dividing *a* by *b*. *sdiv* is like *mdiv* except that the divisor is a short integer *n* and the remainder is placed in a short whose address is given as *r*. *msqrt* produces the integer square root of *a* in *b* and places the remainder in *r*. *rpow* calculates in *c* the value of *a* raised to the ("regular" integral) power *n*, while *pow* calculates this with a full multiple precision exponent *b* and the result is reduced modulo *m*. *gcd* returns the greatest common denominator of *a* and *b* in *c*, and *invert* computes *c* such that $a*c \bmod b = 1$, for *a* and *b* relatively prime. *mcmp* returns a negative, zero or positive integer value when *a* is less than, equal to or greater than *b*, respectively. *move* copies *a* to *b*. *min* and *mout* do decimal input and output while *omin* and *omout* do octal input and output. More generally, *fmin* and *fmout* do decimal input and output using file *f*, and *m_in* and *m_out* do I/O with arbitrary radix *n*. On input, records should have the form of strings of digits terminated by a newline; output records have a similar form.

Programs which use the multiple-precision arithmetic library must be loaded using the loader flag *-lmp*.

FILES

<code>/usr/include/mp.h</code>	include file
<code>/usr/lib/libmp.a</code>	object code library

SEE ALSO

`dc(1)`, `bc(1)`

DIAGNOSTICS

Illegal operations and running out of memory produce messages and core images.

BUGS

Bases for input and output should be ≤ 10 .

`dc(1)` and `bc(1)` don't use this library.

The input and output routines are a crock.

`pow` is also the name of a standard math library routine.

NAME

dbm_open, dbm_close, dbm_fetch, dbm_store, dbm_delete, dbm_firstkey, dbm_nextkey, dbm_error, dbm_clearerr – data base subroutines

SYNOPSIS

```
#include <ndbm.h>

typedef struct {
    char *dptr;
    int dsize;
} datum;

DBM *dbm_open(file, flags, mode)
    char *file;
    int flags, mode;

void dbm_close(db)
    DBM *db;

datum dbm_fetch(db, key)
    DBM *db;
    datum key;

int dbm_store(db, key, content, flags)
    DBM *db;
    datum key, content;
    int flags;

int dbm_delete(db, key)
    DBM *db;
    datum key;

datum dbm_firstkey(db)
    DBM *db;

datum dbm_nextkey(db)
    DBM *db;

int dbm_error(db)
    DBM *db;

int dbm_clearerr(db)
    DBM *db;
```

DESCRIPTION

These functions maintain key/content pairs in a data base. The functions will handle very large (a billion blocks) databases and will access a keyed item in one or two file system accesses. This package replaces the earlier *dbm(3x)* library, which managed only a single database.

Keys and *contents* are described by the *datum* typedef. A *datum* specifies a string of *dsize* bytes pointed to by *dptr*. Arbitrary binary data, as well as normal ASCII strings, are allowed. The data base is stored in two files. One file is a directory containing a bit map and has '.dir' as its suffix. The second file contains all data and has '.pag' as its suffix.

Before a database can be accessed, it must be opened by *dbm_open*. This will open and/or create the files *file.dir* and *file.pag* depending on the flags parameter (see *open(2)*).

Once open, the data stored under a key is accessed by *dbm_fetch* and data is placed under a key by *dbm_store*. The *flags* field can be either **DBM_INSERT** or **DBM_REPLACE**. **DBM_INSERT** will only insert new entries into the database and will not change an existing entry with the same key. **DBM_REPLACE** will replace an existing entry if it has the same

key. A key (and its associated contents) is deleted by *dbm_delete*. A linear pass through all keys in a database may be made, in an (apparently) random order, by use of *dbm_firstkey* and *dbm_nextkey*. *Dbm_firstkey* will return the first key in the database. *Dbm_nextkey* will return the next key in the database. This code will traverse the data base:

```
for (key = dbm_firstkey(db); key.dptr != NULL; key = dbm_nextkey(db))
```

Dbm_error returns non-zero when an error has occurred reading or writing the database. *Dbm_clearerr* resets the error condition on the named database.

DIAGNOSTICS

All functions that return an *int* indicate errors with negative values. A zero return indicates ok. Routines that return a *datum* indicate errors with a null (0) *dptr*. If *dbm_store* called with a *flags* value of **DBM_INSERT** finds an existing entry with the same key it returns 1.

BUGS

The '.pag' file will contain holes so that its apparent size is about four times its actual content. Older UNIX systems may create real file blocks for these holes when touched. These files cannot be copied by normal means (cp, cat, tp, tar, ar) without filling in the holes.

Dptr pointers returned by these subroutines point into static storage that is changed by subsequent calls.

The sum of the sizes of a key/content pair must not exceed the internal block size (currently 4096 bytes). Moreover all key/content pairs that hash together must fit on a single block. *Dbm_store* will return an error in the event that a disk block fills with inseparable data.

Dbm_delete does not physically reclaim file space, although it does make it available for reuse.

The order of keys presented by *dbm_firstkey* and *dbm_nextkey* depends on a hashing function, not on anything interesting.

SEE ALSO

dbm(3X)

NAME

`nice` – set program priority

SYNOPSIS

`nice(incr)`

DESCRIPTION

This interface is obsoleted by `setpriority(2)`.

The scheduling priority of the process is augmented by *incr*. Positive priorities get less service than normal. Priority 10 is recommended to users who wish to execute long-running programs without flak from the administration.

Negative increments are ignored except on behalf of the super-user. The priority is limited to the range -20 (most urgent) to 20 (least).

The priority of a process is passed to a child process by *fork(2)*. For a privileged process to return to normal priority from an unknown state, *nice* should be called successively with arguments -40 (goes to priority -20 because of truncation), 20 (to get to 0), then 0 (to maintain compatibility with previous versions of this call).

SEE ALSO

`nice(1)`, `setpriority(2)`, `fork(2)`, `renice(8)`

P
R
M
3

NAME

nlist – get entries from name list

SYNOPSIS

```
#include <nlist.h>

nlist(filename, nl)
char *filename;
struct nlist nl[];
```

DESCRIPTION

Nlist examines the name list in the given executable output file and selectively extracts a list of values. The name list consists of an array of structures containing names, types and values. The list is terminated with a null name. Each name is looked up in the name list of the file. If the name is found, the type and value of the name are inserted in the next two fields. If the name is not found, both entries are set to 0. See *a.out(5)* for the structure declaration.

This subroutine is useful for examining the system name list kept in the file */vmunix*. In this way programs can obtain system addresses that are up to date.

SEE ALSO

a.out(5)

DIAGNOSTICS

If the file cannot be found or if it is not a valid namelist -1 is returned; otherwise, the number of unfound namelist entries is returned.

The type entry is set to 0 if the symbol is not found.

NAME

ns_addr, *ns_ntoa* – Xerox NS(tm) address conversion routines

SYNOPSIS

```
#include <sys/types.h>
#include <netns/ns.h>

struct ns_addr ns_addr(cp)
char *cp;

char *ns_ntoa(ns)
struct ns_addr ns;
```

DESCRIPTION

The routine *ns_addr* interprets character strings representing XNS addresses, returning binary information suitable for use in system calls. *ns_ntoa* takes XNS addresses and returns ASCII strings representing the address in a notation in common use in the Xerox Development Environment:

<network number>.<host number>.<port number>

Trailing zero fields are suppressed, and each number is printed in hexadecimal, in a format suitable for input to *ns_addr*. Any fields lacking super-decimal digits will have a trailing “H” appended.

Unfortunately, no universal standard exists for representing XNS addresses. An effort has been made to insure that *ns_addr* be compatible with most formats in common use. It will first separate an address into 1 to 3 fields using a single delimiter chosen from period (“.”), colon (“:”) or pound-sign (“#”). Each field is then examined for byte separators (colon or period). If there are byte separators, each subfield separated is taken to be a small hexadecimal number, and the entirety is taken as a network-byte-ordered quantity to be zero extended in the high-network-order bytes. Next, the field is inspected for hyphens, in which case the field is assumed to be a number in decimal notation with hyphens separating the millennia. Next, the field is assumed to be a number: It is interpreted as hexadecimal if there is a leading “0x” (as in C), a trailing “H” (as in Mesa), or there are any super-decimal digits present. It is interpreted as octal if there is a leading “0” and there are no super-octal digits. Otherwise, it is converted as a decimal number.

SEE ALSO

hosts(5), *networks(5)*,

DIAGNOSTICS

None (see *BUGS*).

BUGS

The string returned by *ns_ntoa* resides in a static memory area. *ns_addr* should diagnose improperly formed input, and there should be an unambiguous way to recognize this.

NAME

pause – stop until signal

SYNOPSIS

pause()

DESCRIPTION

Pause never returns normally. It is used to give up control while waiting for a signal from *kill(2)* or an interval timer, see *setitimer(2)*. Upon termination of a signal handler started during a *pause*, the *pause* call will return.

RETURN VALUE

Always returns -1.

ERRORS

Pause always returns:

[EINTR] The call was interrupted.

SEE ALSO

kill(2), select(2), sigpause(2)

NAME

`perror`, `sys_errlist`, `sys_nerr` – system error messages

SYNOPSIS

```
perror(s)
char *s;

int sys_nerr;
char *sys_errlist[];
```

DESCRIPTION

Perror produces a short error message on the standard error file describing the last error encountered during a call to the system from a C program. First the argument string *s* is printed, then a colon, then the message and a new-line. Most usefully, the argument string is the name of the program which incurred the error. The error number is taken from the external variable *errno* (see *intro(2)*), which is set when errors occur but not cleared when non-erroneous calls are made.

To simplify variant formatting of messages, the vector of message strings *sys_errlist* is provided; *errno* can be used as an index in this table to get the message string without the new-line. *Sys_nerr* is the number of messages provided for in the table; it should be checked because new error codes may be added to the system before they are added to the table.

SEE ALSO

intro(2), *psignal(3)*

NAME

plot: openpl, erase, label, line, circle, arc, move, cont, point, linemod, space, closepl – graphics interface

SYNOPSIS

```
openpl()
erase()
label(s)
char s[];
line(x1, y1, x2, y2)
circle(x, y, r)
arc(x, y, x0, y0, x1, y1)
move(x, y)
cont(x, y)
point(x, y)
linemod(s)
char s[];
space(x0, y0, x1, y1)
closepl()
```

DESCRIPTION

These subroutines generate graphic output in a relatively device-independent manner. See *plot(5)* for a description of their effect. *Openpl* must be used before any of the others to open the device for writing. *Closepl* flushes the output.

String arguments to *label* and *linemod* are null-terminated, and do not contain newlines.

Various flavors of these functions exist for different output devices. They are obtained by the following *ld(1)* options:

- lplot device-independent graphics stream on standard output for *plot(1)* filters
- l300 GSI 300 terminal
- l300s GSI 300S terminal
- l450 GSI 450 terminal
- l4013 Tektronix 4013 terminal
- l4014 Tektronix 4014 and 4015 terminals with the Enhanced Graphics Module (Use -l4013 for 4014's or 4015's without the Enhanced Graphics Module)
- lplotaed AED 512 color graphics terminal
- lplotbg BBN bitgraph graphics terminal
- lplotdumb Dumb terminals without cursor addressing or line printers
- lplot DEC Gigi terminals
- lvt0 DEC vt100 terminals
- lplot2648 Hewlett Packard 2648 graphics terminal
- lplot7221 Hewlett Packard 7221 graphics terminal
- lplotimagen Imagen laser printer (default 240 dots-per-inch resolution).

On many devices, it is necessary to pause after *erase()*, otherwise plotting commands are lost. The pause is normally done by the tty driver if at login time, *tset* found a *df* field in the *termcap*(5) entry for the terminal. If a pause is needed but not automatically being generated, add

```
flush(stdout);
sleep(1);
after each erase().
```

SEE ALSO

plot(5), *plot*(1G), *plot*(3F), *graph*(1G)

NAME

popen, *pclose* – initiate I/O to/from a process

SYNOPSIS

```
#include <stdio.h>
```

```
FILE *popen(command, type)
```

```
char *command, *type;
```

```
pclose(stream)
```

```
FILE *stream;
```

DESCRIPTION

The arguments to *popen* are pointers to null-terminated strings containing respectively a shell command line and an I/O mode, either "r" for reading or "w" for writing. It creates a pipe between the calling process and the command to be executed. The value returned is a stream pointer that can be used (as appropriate) to write to the standard input of the command or read from its standard output.

A stream opened by *popen* should be closed by *pclose*, which waits for the associated process to terminate and returns the exit status of the command.

Because open files are shared, a type "r" command may be used as an input filter, and a type "w" as an output filter.

SEE ALSO

pipe(2), *fopen*(3S), *fclose*(3S), *system*(3), *wait*(2), *sh*(1)

DIAGNOSTICS

Popen returns a null pointer if files or processes cannot be created, or the shell cannot be accessed.

Pclose returns -1 if *stream* is not associated with a 'popened' command.

BUGS

Buffered reading before opening an input filter may leave the standard input of that filter mispositioned. Similar problems with an output filter may be forestalled by careful buffer flushing, for instance, with *fflush*, see *fclose*(3S).

Popen always calls *sh*, never calls *csh*.

NAME

printf, fprintf, sprintf – formatted output conversion

SYNOPSIS

```
#include <stdio.h>

printf(format [, arg ] ... )
char *format;

fprintf(stream, format [, arg ] ... )
FILE *stream;
char *format;

sprintf(s, format [, arg ] ... )
char *s, format;

#include <varargs.h>
_doprnt(format, args, stream)
char *format;
va_list *args;
FILE *stream;
```

DESCRIPTION

Printf places output on the standard output stream *stdout*. *Fprintf* places output on the named output *stream*. *Sprintf* places ‘output’ in the string *s*, followed by the character ‘\0’. All of these routines work by calling the internal routine *_doprnt*, using the variable-length argument facilities of *varargs*(3).

Each of these functions converts, formats, and prints its arguments after the first under control of the first argument. The first argument is a character string which contains two types of objects: plain characters, which are simply copied to the output stream, and conversion specifications, each of which causes conversion and printing of the next successive *arg* *printf*.

Each conversion specification is introduced by the character %. The remainder of the conversion specification includes in the following order

- Zero or more of following flags:
 - a ‘#’ character specifying that the value should be converted to an “alternate form”. For *c*, *d*, *s*, and *u*, conversions, this option has no effect. For *o* conversions, the precision of the number is increased to force the first character of the output string to a zero. For *x*(*X*) conversion, a non-zero result has the string *0x*(*0X*) prepended to it. For *e*, *E*, *f*, *g*, and *G*, conversions, the result will always contain a decimal point, even if no digits follow the point (normally, a decimal point only appears in the results of those conversions if a digit follows the decimal point). For *g* and *G* conversions, trailing zeros are not removed from the result as they would otherwise be.
 - a minus sign ‘-’ which specifies *left adjustment* of the converted value in the indicated field;
 - a ‘+’ character specifying that there should always be a sign placed before the number when using signed conversions.
 - a space specifying that a blank should be left before a positive number during a signed conversion. A ‘+’ overrides a space if both are used.
- an optional digit string specifying a *field width*; if the converted value has fewer characters than the field width it will be blank-padded on the left (or right, if the left-adjustment indicator has been given) to make up the field width; if the field width begins with a zero, zero-padding will be done instead of blank-padding;

- an optional period '.' which serves to separate the field width from the next digit string;
- an optional digit string specifying a *precision* which specifies the number of digits to appear after the decimal point, for e- and f-conversion, or the maximum number of characters to be printed from a string;
- the character l specifying that a following d, o, x, or u corresponds to a long integer *arg*.
- a character which indicates the type of conversion to be applied.

A field width or precision may be '*' instead of a digit string. In this case an integer *arg* supplies the field width or precision.

The conversion characters and their meanings are

- d** **o** **x** The integer *arg* is converted to decimal, octal, or hexadecimal notation respectively.
- f** The float or double *arg* is converted to decimal notation in the style '[−]ddd.ddd' where the number of d's after the decimal point is equal to the precision specification for the argument. If the precision is missing, 6 digits are given; if the precision is explicitly 0, no digits and no decimal point are printed.
- e** The float or double *arg* is converted in the style '[−]d.ddde±dd' where there is one digit before the decimal point and the number after is equal to the precision specification for the argument; when the precision is missing, 6 digits are produced.
- g** The float or double *arg* is printed in style d, in style f, or in style e, whichever gives full precision in minimum space.
- c** The character *arg* is printed.
- s** *Arg* is taken to be a string (character pointer) and characters from the string are printed until a null character or until the number of characters indicated by the precision specification is reached; however if the precision is 0 or missing all characters up to a null are printed.
- u** The unsigned integer *arg* is converted to decimal and printed (the result will be in the range 0 through MAXUINT, where MAXUINT equals 4294967295 on a VAX-11 and 65535 on a PDP-11).
- %** Print a '%'; no argument is converted.

In no case does a non-existent or small field width cause truncation of a field; padding takes place only if the specified field width exceeds the actual width. Characters generated by *printf* are printed by *putc*(3S).

Examples

To print a date and time in the form 'Sunday, July 3, 10:02', where *weekday* and *month* are pointers to null-terminated strings:

```
printf("%s, %s %d, %02d:%02d", weekday, month, day, hour, min);
```

To print π to 5 decimals:

```
printf("pi = %.5f", 4*atan(1.0));
```

SEE ALSO

putc(3S), *scanf*(3S), *ecvt*(3)

BUGS

Very wide fields (>128 characters) fail.

NAME

psignal, sys_siglist – system signal messages

SYNOPSIS

psignal(sig, s)

unsigned sig;

char *s;

char *sys_siglist[];

DESCRIPTION

Psignal produces a short message on the standard error file describing the indicated signal. First the argument string *s* is printed, then a colon, then the name of the signal and a newline. Most usefully, the argument string is the name of the program which incurred the signal. The signal number should be from among those found in *<signal.h>*.

To simplify variant formatting of signal names, the vector of message strings *sys_siglist* is provided; the signal number can be used as an index in this table to get the signal name without the newline. The define *NSIG* defined in *<signal.h>* is the number of messages provided for in the table; it should be checked because new signals may be added to the system before they are added to the table.

SEE ALSO

sigvec(2), perror(3)

NAME

putc, putchar, fputc, putw – put character or word on a stream

SYNOPSIS

```
#include <stdio.h>
```

```
int putc(c, stream)
```

```
char c;
```

```
FILE *stream;
```

```
int putchar(c)
```

```
int fputc(c, stream)
```

```
FILE *stream;
```

```
int putw(w, stream)
```

```
FILE *stream;
```

DESCRIPTION

Putc appends the character *c* to the named output *stream*. It returns the character written.

Putchar(c) is defined as *putc(c, stdout)*.

Fputc behaves like *putc*, but is a genuine function rather than a macro.

Putw appends word (that is, int) *w* to the output *stream*. It returns the word written. *Putw* neither assumes nor causes special alignment in the file.

SEE ALSO

fopen(3S), fclose(3S), getc(3S), puts(3S), printf(3S), fread(3S)

DIAGNOSTICS

These functions return the constant EOF upon error. Since this is a good integer, *ferror(3S)* should be used to detect *putw* errors.

BUGS

Because it is implemented as a macro, *putc* treats a *stream* argument with side effects improperly. In particular

```
putc(c, *f++);
```

doesn't work sensibly.

Errors can occur long after the call to *putc*.

NAME

puts, fputs – put a string on a stream

SYNOPSIS

#include <stdio.h>

puts(s)

char *s;

fputs(s, stream)

char *s;

FILE *stream;

DESCRIPTION

Puts copies the null-terminated string *s* to the standard output stream *stdout* and appends a newline character.

Fputs copies the null-terminated string *s* to the named output *stream*.

Neither routine copies the terminal null character.

SEE ALSO

fopen(3S), gets(3S), putc(3S), printf(3S), ferror(3S)
fread(3S) for *fwrite*

BUGS

Puts appends a newline, *fputs* does not, all in the name of backward compatibility.

NAME

qsort – quicker sort

SYNOPSIS

```
qsort(base, nel, width, compar)
char *base;
int (*compar)();
```

DESCRIPTION

Qsort is an implementation of the quicker-sort algorithm. The first argument is a pointer to the base of the data; the second is the number of elements; the third is the width of an element in bytes; the last is the name of the comparison routine to be called with two arguments which are pointers to the elements being compared. The routine must return an integer less than, equal to, or greater than 0 according as the first argument is to be considered less than, equal to, or greater than the second.

SEE ALSO

sort(1)

P
R
M
3

NAME

rand, *srand* – random number generator

SYNOPSIS

srand(seed)

int seed;

rand()

DESCRIPTION

The newer *random*(3) should be used in new applications; *rand* remains for compatibility.

Rand uses a multiplicative congruential random number generator with period 2^{32} to return successive pseudo-random numbers in the range from 0 to $2^{31} - 1$.

The generator is reinitialized by calling *srand* with 1 as argument. It can be set to a random starting point by calling *srand* with whatever you like as argument.

SEE ALSO

random(3)

NAME

random, srandom, initstate, setstate – better random number generator; routines for changing generators

SYNOPSIS

```
long random()
srandom(seed)
int seed;

char *initstate(seed, state, n)
unsigned seed;
char *state;
int n;

char *setstate(state)
char *state;
```

DESCRIPTION

Random uses a non-linear additive feedback random number generator employing a default table of size 31 long integers to return successive pseudo-random numbers in the range from 0 to $2^{31}-1$. The period of this random number generator is very large, approximately $16 \times (2^{31}-1)$.

Random/srandom have (almost) the same calling sequence and initialization properties as *rand/srand*. The difference is that *rand(3)* produces a much less random sequence — in fact, the low dozen bits generated by *rand* go through a cyclic pattern. All the bits generated by *random* are usable. For example, “*random()&01*” will produce a random binary value.

Unlike *srand*, *srandom* does not return the old seed; the reason for this is that the amount of state information used is much more than a single word. (Two other routines are provided to deal with restarting/changing random number generators). Like *rand(3)*, however, *random* will by default produce a sequence of numbers that can be duplicated by calling *srandom* with *l* as the seed.

The *initstate* routine allows a state array, passed in as an argument, to be initialized for future use. The size of the state array (in bytes) is used by *initstate* to decide how sophisticated a random number generator it should use -- the more state, the better the random numbers will be. (Current “optimal” values for the amount of state information are 8, 32, 64, 128, and 256 bytes; other amounts will be rounded down to the nearest known amount. Using less than 8 bytes will cause an error). The seed for the initialization (which specifies a starting point for the random number sequence, and provides for restarting at the same point) is also an argument. *Initstate* returns a pointer to the previous state information array.

Once a state has been initialized, the *setstate* routine provides for rapid switching between states. *Setstate* returns a pointer to the previous state array; its argument state array is used for further random number generation until the next call to *initstate* or *setstate*.

Once a state array has been initialized, it may be restarted at a different point either by calling *initstate* (with the desired seed, the state array, and its size) or by calling both *setstate* (with the state array) and *srandom* (with the desired seed). The advantage of calling both *setstate* and *srandom* is that the size of the state array does not have to be remembered after it is initialized.

With 256 bytes of state information, the period of the random number generator is greater than 2^{69} , which should be sufficient for most purposes.

AUTHOR

Earl T. Cohen

DIAGNOSTICS

If *initstate* is called with less than 8 bytes of state information, or if *setstate* detects that the state information has been garbled, error messages are printed on the standard error output.

SEE ALSO

rand(3)

BUGS

About 2/3 the speed of *rand*(3C).

NAME

rcmd, *rresvport*, *ruserok* – routines for returning a stream to a remote command

SYNOPSIS

```
rem = rcmd(ahost, inport, locuser, remuser, cmd, fd2p);
char **ahost;
int inport;
char *locuser, *remuser, *cmd;
int *fd2p;

s = rresvport(port);
int *port;

ruserok(rhost, superuser, ruser, luser);
char *rhost;
int superuser;
char *ruser, *luser;
```

DESCRIPTION

Rcmd is a routine used by the super-user to execute a command on a remote machine using an authentication scheme based on reserved port numbers. *Rresvport* is a routine which returns a descriptor to a socket with an address in the privileged port space. *Ruserok* is a routine used by servers to authenticate clients requesting service with *rcmd*. All three functions are present in the same file and are used by the *rshd*(8C) server (among others).

Rcmd looks up the host **ahost* using *gethostbyname*(3N), returning -1 if the host does not exist. Otherwise **ahost* is set to the standard name of the host and a connection is established to a server residing at the well-known Internet port *inport*.

If the connection succeeds, a socket in the Internet domain of type *SOCK_STREAM* is returned to the caller, and given to the remote command as *stdin* and *stdout*. If *fd2p* is non-zero, then an auxiliary channel to a control process will be set up, and a descriptor for it will be placed in **fd2p*. The control process will return diagnostic output from the command (unit 2) on this channel, and will also accept bytes on this channel as being UNIX signal numbers, to be forwarded to the process group of the command. If *fd2p* is 0, then the *stderr* (unit 2 of the remote command) will be made the same as the *stdout* and no provision is made for sending arbitrary signals to the remote process, although you may be able to get its attention by using out-of-band data.

The protocol is described in detail in *rshd*(8C).

The *rresvport* routine is used to obtain a socket with a privileged address bound to it. This socket is suitable for use by *rcmd* and several other routines. Privileged Internet ports are those in the range 0 to 1023. Only the super-user is allowed to bind an address of this sort to a socket.

Ruserok takes a remote host's name, as returned by a *gethostbyaddr*(3N) routine, two user names and a flag indicating whether the local user's name is that of the super-user. It then checks the files */etc/hosts.equiv* and, possibly, *.rhosts* in the current working directory (normally the local user's home directory) to see if the request for service is allowed. A 0 is returned if the machine name is listed in the "hosts.equiv" file, or the host and remote user name are found in the ".rhosts" file; otherwise *ruserok* returns -1. If the *superuser* flag is 1, the checking of the "host.equiv" file is bypassed. If the local domain (as obtained from *gethostname*(2)) is the same as the remote domain, only the machine name need be specified.

SEE ALSO

rlogin(1C), *rsh*(1C), *intro*(2), *rexec*(3), *rexecd*(8C), *rlogind*(8C), *rshd*(8C)

DIAGNOSTICS

Rcmd returns a valid socket descriptor on success. It returns -1 on error and prints a diagnostic message on the standard error.

Rresvport returns a valid, bound socket descriptor on success. It returns -1 on error with the global value *errno* set according to the reason for failure. The error code EAGAIN is overloaded to mean "All network ports in use."

P
R
M
3

NAME

re_comp, *re_exec* – regular expression handler

SYNOPSIS

*char *re_comp(s)*

*char *s;*

re_exec(s)

*char *s;*

DESCRIPTION

Re_comp compiles a string into an internal form suitable for pattern matching. *Re_exec* checks the argument string against the last string passed to *re_comp*.

Re_comp returns 0 if the string *s* was compiled successfully; otherwise a string containing an error message is returned. If *re_comp* is passed 0 or a null string, it returns without changing the currently compiled regular expression.

Re_exec returns 1 if the string *s* matches the last compiled regular expression, 0 if the string *s* failed to match the last compiled regular expression, and -1 if the compiled regular expression was invalid (indicating an internal error).

The strings passed to both *re_comp* and *re_exec* may have trailing or embedded newline characters; they are terminated by nulls. The regular expressions recognized are described in the manual entry for *ed(1)*, given the above difference.

SEE ALSO

ed(1), *ex(1)*, *egrep(1)*, *fgrep(1)*, *grep(1)*

DIAGNOSTICS

Re_exec returns -1 for an internal error.

Re_comp returns one of the following strings if an error occurs:

No previous regular expression,

Regular expression too long,

unmatched \,

missing],

too many \(\) pairs,

unmatched \.

P
R
M
3

NAME

res_mkquery, res_send, res_init, dn_comp, dn_expand – resolver routines

SYNOPSIS

```
#include <sys/types.h>
#include <netinet/in.h>
#include <arpa/nameser.h>
#include <resolv.h>
```

res_mkquery(op, dname, class, type, data, datalen, newrr, buf, buflen)

```
int op;
char *dname;
int class, type;
char *data;
int datalen;
struct rrec *newrr;
char *buf;
int buflen;
```

res_send(msg, msglen, answer, anslen)

```
char *msg;
int msglen;
char *answer;
int anslen;
```

res_init()

dn_comp(exp_dn, comp_dn, length, dnptrs, lastdnptr)

```
char *exp_dn, *comp_dn;
int length;
char **dnptrs, **lastdnptr;
```

dn_expand(msg, eomorig, comp_dn, exp_dn, length)

```
char *msg, *eomorig, *comp_dn, exp_dn;
int length;
```

DESCRIPTION

These routines are used for making, sending and interpreting packets to Internet domain name servers. Global information that is used by the resolver routines is kept in the variable `_res`. Most of the values have reasonable defaults and can be ignored. Options stored in `_res.options` are defined in `resolv.h` and are as follows. Options are a simple bit mask and are or'ed in to enable.

RES_INIT

True if the initial name server address and default domain name are initialized (i.e., `res_init` has been called).

RES_DEBUG

Print debugging messages.

RES_AAONLY

Accept authoritative answers only. `Res_send` will continue until it finds an authoritative answer or finds an error. Currently this is not implemented.

RES_USEVC

Use TCP connections for queries instead of UDP.

RES_STAYOPEN

Used with `RES_USEVC` to keep the TCP connection open between queries. This is useful only in programs that regularly do many queries. UDP should be the normal mode used.

RES_IGNTC

Unused currently (ignore truncation errors, i.e., don't retry with TCP).

RES_RECURSE

Set the recursion desired bit in queries. This is the default. (*res_send* does not do iterative queries and expects the name server to handle recursion.)

RES_DEFNAMES

Append the default domain name to single label queries. This is the default.

Res_init

reads the initialization file to get the default domain name and the Internet address of the initial hosts running the name server. If this line does not exist, the host running the resolver is tried. *Res_mkquery* makes a standard query message and places it in *buf*. *Res_mkquery* will return the size of the query or -1 if the query is larger than *buflen*. *Op* is usually QUERY but can be any of the query types defined in *nameser.h*. *Dname* is the domain name. If *dname* consists of a single label and the RES_DEFNAMES flag is enabled (the default), *dname* will be appended with the current domain name. The current domain name is defined in a system file and can be overridden by the environment variable LOCALDOMAIN. *Newrr* is currently unused but is intended for making update messages.

Res_send sends a query to name servers and returns an answer. It will call *res_init* if RES_INIT is not set, send the query to the local name server, and handle timeouts and retries. The length of the message is returned or -1 if there were errors.

Dn_expand expands the compressed domain name *comp_dn* to a full domain name. Expanded names are converted to upper case. *Msg* is a pointer to the beginning of the message, *exp_dn* is a pointer to a buffer of size *length* for the result. The size of compressed name is returned or -1 if there was an error.

Dn_comp compresses the domain name *exp_dn* and stores it in *comp_dn*. The size of the compressed name is returned or -1 if there were errors. *length* is the size of the *comp_dn*. *Dnptrs* is a list of pointers to previously compressed names in the current message. The first pointer points to the beginning of the message and the list ends with NULL. *lastdnptr* is a pointer to the end of the array pointed to *dnptrs*. A side effect is to update the list of pointers for labels inserted into the message by *dn_comp* as the name is compressed. If *dnptr* is NULL, we don't try to compress names. If *lastdnptr* is NULL, we don't update the list.

FILES

/etc/resolv.conf see resolver(5)

SEE ALSO

named(8), resolver(5), RFC882, RFC883, RFC973, RFC974, SMM:11 Name Server Operations Guide for BIND

NAME

rexec - return stream to a remote command

SYNOPSIS

```
rem = rexec(ahost, inport, user, passwd, cmd, fd2p);  
char **ahost;  
int inport;  
char *user, *passwd, *cmd;  
int *fd2p;
```

DESCRIPTION

Rexec looks up the host **ahost* using *gethostbyname(3N)*, returning -1 if the host does not exist. Otherwise **ahost* is set to the standard name of the host. If a username and password are both specified, then these are used to authenticate to the foreign host; otherwise the environment and then the user's *.netrc* file in his home directory are searched for appropriate information. If all this fails, the user is prompted for the information.

The port *inport* specifies which well-known DARPA Internet port to use for the connection; the call "*getservbyname*(*exec*, *tcp*)" (see *getservent(3N)*) will return a pointer to a structure, which contains the necessary port. The protocol for connection is described in detail in *rexecd(8C)*.

If the connection succeeds, a socket in the Internet domain of type *SOCK_STREAM* is returned to the caller, and given to the remote command as *stdin* and *stdout*. If *fd2p* is non-zero, then an auxiliary channel to a control process will be setup, and a descriptor for it will be placed in **fd2p*. The control process will return diagnostic output from the command (unit 2) on this channel, and will also accept bytes on this channel as being UNIX signal numbers, to be forwarded to the process group of the command. The diagnostic information returned does not include remote authorization failure, as the secondary connection is set up after authorization has been verified. If *fd2p* is 0, then the *stderr* (unit 2 of the remote command) will be made the same as the *stdout* and no provision is made for sending arbitrary signals to the remote process, although you may be able to get its attention by using out-of-band data.

SEE ALSO

rcmd(3), *rexecd(8C)*

P
R
M
3

NAME

scandir, alphasort – scan a directory

SYNOPSIS

```
#include <sys/types.h>
#include <sys/dir.h>

scandir(dirname, namelist, select, compar)
char *dirname;
struct direct *(*namelist[]);
int (*select)();
int (*compar)();

alphasort(d1, d2)
struct direct **d1, **d2;
```

DESCRIPTION

Scandir reads the directory *dirname* and builds an array of pointers to directory entries using *malloc(3)*. It returns the number of entries in the array and a pointer to the array through *namelist*.

The *select* parameter is a pointer to a user supplied subroutine which is called by *scandir* to select which entries are to be included in the array. The select routine is passed a pointer to a directory entry and should return a non-zero value if the directory entry is to be included in the array. If *select* is null, then all the directory entries will be included.

The *compar* parameter is a pointer to a user supplied subroutine which is passed to *qsort(3)* to sort the completed array. If this pointer is null, the array is not sorted. *Alphasort* is a routine which can be used for the *compar* parameter to sort the array alphabetically.

The memory allocated for the array can be deallocated with *free* (see *malloc(3)*) by freeing each pointer in the array and the array itself.

SEE ALSO

directory(3), malloc(3), qsort(3), dir(5)

DIAGNOSTICS

Returns -1 if the directory cannot be opened for reading or if *malloc(3)* cannot allocate enough memory to hold all the data structures.

NAME

scanf, fscanf, sscanf – formatted input conversion

SYNOPSIS

```
#include <stdio.h>

scanf(format [ , pointer ] . . . )
char *format;

fscanf(stream, format [ , pointer ] . . . )
FILE *stream;
char *format;

sscanf(s, format [ , pointer ] . . . )
char *s, *format;
```

DESCRIPTION

Scanf reads from the standard input stream *stdin*. *Fscanf* reads from the named input *stream*. *Sscanf* reads from the character string *s*. Each function reads characters, interprets them according to a format, and stores the results in its arguments. Each expects as arguments a control string *format*, described below, and a set of *pointer* arguments indicating where the converted input should be stored.

The control string usually contains conversion specifications, which are used to direct interpretation of input sequences. The control string may contain:

1. Blanks, tabs or newlines, which match optional white space in the input.
2. An ordinary character (not %) which must match the next character of the input stream.
3. Conversion specifications, consisting of the character %, an optional assignment suppression character *, an optional numerical maximum field width, and a conversion character.

A conversion specification directs the conversion of the next input field; the result is placed in the variable pointed to by the corresponding argument, unless assignment suppression was indicated by *. An input field is defined as a string of non-space characters; it extends to the next inappropriate character or until the field width, if specified, is exhausted.

The conversion character indicates the interpretation of the input field; the corresponding pointer argument must usually be of a restricted type. The following conversion characters are legal:

- % a single '%' is expected in the input at this point; no assignment is done.
- d a decimal integer is expected; the corresponding argument should be an integer pointer.
- o an octal integer is expected; the corresponding argument should be an integer pointer.
- x a hexadecimal integer is expected; the corresponding argument should be an integer pointer.
- s a character string is expected; the corresponding argument should be a character pointer pointing to an array of characters large enough to accept the string and a terminating '\0', which will be added. The input field is terminated by a space character or a newline.
- c a character is expected; the corresponding argument should be a character pointer. The normal skip over space characters is suppressed in this case; to read the next non-space character, try '%1s'. If a field width is given, the corresponding argument should refer to a character array, and the indicated number of characters is read.
- e a floating point number is expected; the next field is converted accordingly and stored through the corresponding argument, which should be a pointer to a *float*. The input format for floating point numbers is an optionally signed string of digits possibly containing a decimal point, followed by an optional exponent field consisting of an E or e followed
- f

by an optionally signed integer.

- [indicates a string not to be delimited by space characters. The left bracket is followed by a set of characters and a right bracket; the characters between the brackets define a set of characters making up the string. If the first character is not circumflex (^), the input field is all characters until the first character not in the set between the brackets; if the first character after the left bracket is ^, the input field is all characters until the first character which is in the remaining set of characters between the brackets. The corresponding argument must point to a character array.

The conversion characters *d*, *o* and *x* may be capitalized or preceded by *l* to indicate that a pointer to **long** rather than to **int** is in the argument list. Similarly, the conversion characters *e* or *f* may be capitalized or preceded by *l* to indicate a pointer to **double** rather than to **float**. The conversion characters *d*, *o* and *x* may be preceded by *h* to indicate a pointer to **short** rather than to **int**.

The *scanf* functions return the number of successfully matched and assigned input items. This can be used to decide how many input items were found. The constant EOF is returned upon end of input; note that this is different from 0, which means that no conversion was done; if conversion was intended, it was frustrated by an inappropriate character in the input.

For example, the call

```
int i; float x; char name[50];
scanf("%d%f%s", &i, &x, name);
```

with the input line

```
25 54.32E-1 thompson
```

will assign to *i* the value 25, *x* the value 5.432, and *name* will contain 'thompson\0'. Or,

```
int i; float x; char name[50];
scanf("%2d%f%*d%[1234567890]", &i, &x, name);
```

with input

```
56789 0123 56a72
```

will assign 56 to *i*, 789.0 to *x*, skip '0123', and place the string '56\0' in *name*. The next call to *getchar* will return 'a'.

SEE ALSO

atof(3), *getc*(3S), *printf*(3S)

DIAGNOSTICS

The *scanf* functions return EOF on end of input, and a short count for missing or illegal data items.

BUGS

The success of literal matches and suppressed assignments is not directly determinable.

NAME

setbuf, setbuffer, setlinebuf – assign buffering to a stream

SYNOPSIS

```
#include <stdio.h>

setbuf(stream, buf)
FILE *stream;
char *buf;

setbuffer(stream, buf, size)
FILE *stream;
char *buf;
int size;

setlinebuf(stream)
FILE *stream;
```

DESCRIPTION

The three types of buffering available are unbuffered, block buffered, and line buffered. When an output stream is unbuffered, information appears on the destination file or terminal as soon as written; when it is block buffered many characters are saved up and written as a block; when it is line buffered characters are saved up until a newline is encountered or input is read from stdin. *Fflush* (see *fclose*(3S)) may be used to force the block out early. Normally all files are block buffered. A buffer is obtained from *malloc*(3) upon the first *getc* or *putc*(3S) on the file. If the standard stream *stdout* refers to a terminal it is line buffered. The standard stream *stderr* is always unbuffered.

Setbuf is used after a stream has been opened but before it is read or written. The character array *buf* is used instead of an automatically allocated buffer. If *buf* is the constant pointer NULL, input/output will be completely unbuffered. A manifest constant BUFSIZ tells how big an array is needed:

```
char buf[BUFSIZ];
```

Setbuffer, an alternate form of *setbuf*, is used after a stream has been opened but before it is read or written. The character array *buf* whose size is determined by the *size* argument is used instead of an automatically allocated buffer. If *buf* is the constant pointer NULL, input/output will be completely unbuffered.

Setlinebuf is used to change *stdout* or *stderr* from block buffered or unbuffered to line buffered. Unlike *setbuf* and *setbuffer* it can be used at any time that the file descriptor is active.

A file can be changed from unbuffered or line buffered to block buffered by using *freopen* (see *fopen*(3S)). A file can be changed from block buffered or line buffered to unbuffered by using *freopen* followed by *setbuf* with a buffer argument of NULL.

SEE ALSO

fopen(3S), *getc*(3S), *putc*(3S), *malloc*(3), *fclose*(3S), *puts*(3S), *printf*(3S), *fread*(3S)

BUGS

The standard error stream should be line buffered by default.

The *setbuffer* and *setlinebuf* functions are not portable to non-4.2BSD versions of UNIX. On 4.2BSD and 4.3BSD systems, *setbuf* always uses a suboptimal buffer size and should be avoided. *Setbuffer* is not usually needed as the default file I/O buffer sizes are optimal.

NAME

setjmp, longjmp – non-local goto

SYNOPSIS

```
#include <setjmp.h>
```

```
setjmp(env)
```

```
jmp_buf env;
```

```
longjmp(env, val)
```

```
jmp_buf env;
```

```
_setjmp(env)
```

```
jmp_buf env;
```

```
_longjmp(env, val)
```

```
jmp_buf env;
```

DESCRIPTION

These routines are useful for dealing with errors and interrupts encountered in a low-level subroutine of a program.

Setjmp saves its stack environment in *env* for later use by *longjmp*. It returns value 0.

Longjmp restores the environment saved by the last call of *setjmp*. It then returns in such a way that execution continues as if the call of *setjmp* had just returned the value *val* to the function that invoked *setjmp*, which must not itself have returned in the interim. All accessible data have values as of the time *longjmp* was called.

Setjmp and *longjmp* save and restore the signal mask *sigmask(2)*, while *_setjmp* and *_longjmp* manipulate only the C stack and registers.

ERRORS

If the contents of the *jmp_buf* are corrupted, or correspond to an environment that has already returned, *longjmp* calls the routine *longjmperror*. If *longjmperror* returns the program is aborted. The default version of *longjmperror* prints the message "longjmp botch" to standard error and returns. User programs wishing to exit more gracefully can write their own versions of *longjmperror*.

SEE ALSO

sigvec(2), *sigstack(2)*, *signal(3)*

NAME

setuid, seteuid, setruid, setgid, setegid, setrgid – set user and group ID

SYNOPSIS

```
#include <sys/types.h>
```

```
setuid(uid)
```

```
seteuid(euid)
```

```
setruid(ruid)
```

```
uid_t uid, euid, ruid;
```

```
setgid(gid)
```

```
setegid(egid)
```

```
setrgid(rgid)
```

```
gid_t gid, egid, rgid;
```

DESCRIPTION

Setuid (setgid) sets both the real and effective user ID (group ID) of the current process to as specified.

Seteuid (setegid) sets the effective user ID (group ID) of the current process.

Setruid (setrgid) sets the real user ID (group ID) of the current process.

These calls are only permitted to the super-user or if the argument is the real or effective ID.

SEE ALSO

setreuid(2), setregid(2), getuid(2), getgid(2)

DIAGNOSTICS

Zero is returned if the user (group) ID is set; -1 is returned otherwise.

NAME

siginterrupt – allow signals to interrupt system calls

SYNOPSIS

```
siginterrupt(sig, flag);  
int sig, flag;
```

DESCRIPTION

Siginterrupt is used to change the system call restart behavior when a system call is interrupted by the specified signal. If the flag is false (0), then system calls will be restarted if they are interrupted by the specified signal and no data has been transferred yet. System call restart is the default behavior on 4.2 BSD.

If the flag is true (1), then restarting of system calls is disabled. If a system call is interrupted by the specified signal and no data has been transferred, the system call will return -1 with *errno* set to *EINTR*. Interrupted system calls that have started transferring data will return the amount of data actually transferred. System call interrupt is the signal behavior found on 4.1 BSD and AT&T System V UNIX systems.

Note that the new 4.2 BSD signal handling semantics are not altered in any other way. Most notably, signal handlers always remain installed until explicitly changed by a subsequent *sigvec(2)* call, and the signal mask operates as documented in *sigvec(2)*. Programs may switch between restartable and interruptible system call operation as often as desired in the execution of a program.

Issuing a *siginterrupt(3)* call during the execution of a signal handler will cause the new action to take place on the next signal to be caught.

NOTES

This library routine uses an extension of the *sigvec(2)* system call that is not available in 4.2BSD, hence it should not be used if backward compatibility is needed.

RETURN VALUE

A 0 value indicates that the call succeeded. A -1 value indicates that an invalid signal number has been supplied.

SEE ALSO

sigvec(2), *sigblock(2)*, *sigpause(2)*, *sigsetmask(2)*.

NAME

signal – simplified software signal facilities

SYNOPSIS

```
#include <signal.h>
```

```
(*signal(sig, func))()
```

```
int (*func)();
```

DESCRIPTION

Signal is a simplified interface to the more general *sigvec(2)* facility.

A signal is generated by some abnormal event, initiated by a user at a terminal (quit, interrupt, stop), by a program error (bus error, etc.), by request of another program (kill), or when a process is stopped because it wishes to access its control terminal while in the background (see *tty(4)*). Signals are optionally generated when a process resumes after being stopped, when the status of child processes changes, or when input is ready at the control terminal. Most signals cause termination of the receiving process if no action is taken; some signals instead cause the process receiving them to be stopped, or are simply discarded if the process has not requested otherwise. Except for the SIGKILL and SIGSTOP signals, the *signal* call allows signals either to be ignored or to cause an interrupt to a specified location. The following is a list of all signals with names as in the include file *<signal.h>*:

SIGHUP	1	hangup
SIGINT	2	interrupt
SIGQUIT	3*	quit
SIGILL	4*	illegal instruction
SIGTRAP	5*	trace trap
SIGIOT	6*	IOT instruction
SIGEMT	7*	EMT instruction
SIGFPE	8*	floating point exception
SIGKILL	9	kill (cannot be caught or ignored)
SIGBUS	10*	bus error
SIGSEGV	11*	segmentation violation
SIGSYS	12*	bad argument to system call
SIGPIPE	13	write on a pipe with no one to read it
SIGALRM	14	alarm clock
SIGTERM	15	software termination signal
SIGURG	16●	urgent condition present on socket
SIGSTOP	17†	stop (cannot be caught or ignored)
SIGTSTP	18†	stop signal generated from keyboard
SIGCONT	19●	continue after stop
SIGCHLD	20●	child status has changed
SIGTTIN	21†	background read attempted from control terminal
SIGTTOU	22†	background write attempted to control terminal
SIGIO	23●	i/o is possible on a descriptor (see <i>fcntl(2)</i>)
SIGXCPU	24	cpu time limit exceeded (see <i>setrlimit(2)</i>)
SIGXFSZ	25	file size limit exceeded (see <i>setrlimit(2)</i>)
SIGVTALRM	26	virtual time alarm (see <i>setitimer(2)</i>)
SIGPROF	27	profiling timer alarm (see <i>setitimer(2)</i>)
SIGWINCH	28●	Window size change
SIGUSR1	30	User defined signal 1
SIGUSR2	31	User defined signal 2

The starred signals in the list above cause a core image if not caught or ignored.

If *func* is SIG_DFL, the default action for signal *sig* is reinstated; this default is termination (with a core image for starred signals) except for signals marked with ● or †. Signals marked with ● are discarded if the action is SIG_DFL; signals marked with † cause the process to stop. If *func* is SIG_IGN the signal is subsequently ignored and pending instances of the signal are discarded. Otherwise, when the signal occurs further occurrences of the signal are automatically blocked and *func* is called.

A return from the function unblocks the handled signal and continues the process at the point it was interrupted. Unlike previous signal facilities, the handler *func* remains installed after a signal has been delivered.

If a caught signal occurs during certain system calls, causing the call to terminate prematurely, the call is automatically restarted. In particular this can occur during a *read* or *write*(2) on a slow device (such as a terminal; but not a file) and during a *wait*(2).

The value of *signal* is the previous (or initial) value of *func* for the particular signal.

After a *fork*(2) or *vfork*(2) the child inherits all signals. *Execve*(2) resets all caught signals to the default action; ignored signals remain ignored.

RETURN VALUE

The previous action is returned on a successful call. Otherwise, -1 is returned and *errno* is set to indicate the error.

ERRORS

Signal will fail and no action will take place if one of the following occur:

- [EINVAL] *Sig* is not a valid signal number.
- [EINVAL] An attempt is made to ignore or supply a handler for SIGKILL or SIGSTOP.
- [EINVAL] An attempt is made to ignore SIGCONT (by default SIGCONT is ignored).

SEE ALSO

kill(1), *ptrace*(2), *kill*(2), *sigvec*(2), *sigblock*(2), *sigsetmask*(2), *sigpause*(2), *sigstack*(2), *setjmp*(3), *tty*(4)

NOTES (VAX-11)

The handler routine can be declared:

```
handler(sig, code, scp)
```

Here *sig* is the signal number, into which the hardware faults and traps are mapped as defined below. *Code* is a parameter which is either a constant as given below or, for compatibility mode faults, the code provided by the hardware. *Scp* is a pointer to the *struct sigcontext* used by the system to restore the process context from before the signal. Compatibility mode faults are distinguished from the other SIGILL traps by having PSL_CM set in the psl.

The following defines the mapping of hardware traps to signals and codes. All of these symbols are defined in *<signal.h>*:

Hardware condition	Signal	Code
Arithmetic traps:		
Integer overflow	SIGFPE	FPE_INTOVF_TRAP
Integer division by zero	SIGFPE	FPE_INTDIV_TRAP
Floating overflow trap	SIGFPE	FPE_FLOVF_TRAP
Floating/decimal division by zero	SIGFPE	FPE_FLTDIV_TRAP
Floating underflow trap	SIGFPE	FPE_FLTUND_TRAP
Decimal overflow trap	SIGFPE	FPE_DECOVF_TRAP
Subscript-range	SIGFPE	FPE_SUBRNG_TRAP
Floating overflow fault	SIGFPE	FPE_FLOVF_FAULT

Floating divide by zero fault	SIGFPE	FPE_FLTDIV_FAULT
Floating underflow fault	SIGFPE	FPE_FLTUND_FAULT
Length access control	SIGSEGV	
Protection violation	SIGBUS	
Reserved instruction	SIGILL	ILL_RESAD_FAULT
Customer-reserved instr.	SIGEMT	
Reserved operand	SIGILL	ILL_PRIVIN_FAULT
Reserved addressing	SIGILL	ILL_RESOP_FAULT
Trace pending	SIGTRAP	
Bpt instruction	SIGTRAP	
Compatibility-mode	SIGILL	hardware supplied code
Chme	SIGSEGV	
Chms	SIGSEGV	
Chmu	SIGSEGV	

NAME

sin, cos, tan, asin, acos, atan, atan2 – trigonometric functions and their inverses

SYNOPSIS

```
#include <math.h>
```

```
double sin(x)
```

```
double x;
```

```
double cos(x)
```

```
double x;
```

```
double tan(x)
```

```
double x;
```

```
double asin(x)
```

```
double x;
```

```
double acos(x)
```

```
double x;
```

```
double atan(x)
```

```
double x;
```

```
double atan2(y,x)
```

```
double y,x;
```

DESCRIPTION

Sin, cos and tan return trigonometric functions of radian arguments x .

Asin returns the arc sine in the range $-\pi/2$ to $\pi/2$.

Acos returns the arc cosine in the range 0 to π .

Atan returns the arc tangent in the range $-\pi/2$ to $\pi/2$.

On a VAX,

```
atan2(y,x) := atan(y/x)           if x > 0,
              sign(y)*( $\pi$  - atan(|y/x|)) if x < 0,
              0                       if x = y = 0, or
              sign(y)* $\pi/2$            if x = 0  $\neq$  y.
```

DIAGNOSTICS

On a VAX, if $|x| > 1$ then asin(x) and acos(x) will return reserved operands and *errno* will be set to EDOM.

NOTES

Atan2 defines atan2(0,0) = 0 on a VAX despite that previously atan2(0,0) may have generated an error message. The reasons for assigning a value to atan2(0,0) are these:

- (1) Programs that test arguments to avoid computing atan2(0,0) must be indifferent to its value. Programs that require it to be invalid are vulnerable to diverse reactions to that invalidity on diverse computer systems.
- (2) Atan2 is used mostly to convert from rectangular (x,y) to polar (r, θ) coordinates that must satisfy $x = r \cos \theta$ and $y = r \sin \theta$. These equations are satisfied when (x=0,y=0) is mapped to (r=0, θ =0) on a VAX. In general, conversions to polar coordinates should be computed thus:

$$\begin{aligned} r &:= \text{hypot}(x,y); & \dots &:= \sqrt{x^2+y^2} \\ \theta &:= \text{atan2}(y,x). \end{aligned}$$
- (3) The foregoing formulas need not be altered to cope in a reasonable way with signed zeros and infinities on a machine that conforms to IEEE 754; the versions of hypot and atan2 provided for such a machine are designed to handle all cases. That is why atan2(± 0 , -0)

= $\pm\pi$, for instance. In general the formulas above are equivalent to these:

$r := \sqrt{(x*x+y*y)}$; if $r = 0$ then $x := \text{copysign}(1,x)$;

if $x > 0$ then $\theta := 2*\text{atan}(y/(r+x))$

else $\theta := 2*\text{atan}((r-x)/y)$;

except if r is infinite then atan2 will yield an appropriate multiple of $\pi/4$ that would otherwise have to be obtained by taking limits.

ERROR (due to Roundoff etc.)

Let P stand for the number stored in the computer in place of $\pi = 3.14159\ 26535\ 89793\ 23846\ 26433\ \dots$. Let "trig" stand for one of "sin", "cos" or "tan". Then the expression "trig(x)" in a program actually produces an approximation to $\text{trig}(x*\pi/P)$, and "atrig(x)" approximates $(P/\pi)*\text{atrig}(x)$. The approximations are close, within 0.9 *ulps* for sin, cos and atan, within 2.2 *ulps* for tan, asin, acos and atan2 on a VAX. Moreover, $P = \pi$ in the codes that run on a VAX.

In the codes that run on other machines, P differs from π by a fraction of an *ulp*; the difference matters only if the argument x is huge, and even then the difference is likely to be swamped by the uncertainty in x . Besides, every trigonometric identity that does not involve π explicitly is satisfied equally well regardless of whether $P = \pi$. For instance, $\sin^2(x) + \cos^2(x) = 1$ and $\sin(2x) = 2\sin(x)\cos(x)$ to within a few *ulps* no matter how big x may be. Therefore the difference between P and π is most unlikely to affect scientific and engineering computations.

SEE ALSO

math(3M), hypot(3M), sqrt(3M), infnan(3M)

AUTHOR

Robert P. Corbett, W. Kahan, Stuart I. McDonald, Peter Tang and, for the codes for IEEE 754, Dr. Kwok-Choi Ng.

NAME

sinh, cosh, tanh – hyperbolic functions

SYNOPSIS

```
#include <math.h>
```

```
double sinh(x)
```

```
double x;
```

```
double cosh(x)
```

```
double x;
```

```
double tanh(x)
```

```
double x;
```

DESCRIPTION

These functions compute the designated hyperbolic functions for real arguments.

ERROR (due to Roundoff etc.)

Below 2.4 *ulps*; an *ulp* is one *Unit* in the *Last Place*.

DIAGNOSTICS

Sinh and cosh return the reserved operand on a VAX if the correct value would overflow.

SEE ALSO

math(3M), infnan(3M)

AUTHOR

W. Kahan, Kwok-Choi Ng

NAME

sleep – suspend execution for interval

SYNOPSIS

sleep(seconds)
unsigned seconds;

DESCRIPTION

The current process is suspended from execution for the number of seconds specified by the argument. The actual suspension time may be up to 1 second less than that requested, because scheduled wakeups occur at fixed 1-second intervals, and an arbitrary amount longer because of other activity in the system.

The routine is implemented by setting an interval timer and pausing until it occurs. The previous state of this timer is saved and restored. If the sleep time exceeds the time to the expiration of the previous timer, the process sleeps only until the signal would have occurred, and the signal is sent 1 second later.

SEE ALSO

setitimer(2), sigpause(2), usleep(3)

P
R
M
3

NAME

cbt, sqrt – cube root, square root

SYNOPSIS

```
#include <math.h>
```

```
double cbrt(x)
```

```
double x;
```

```
double sqrt(x)
```

```
double x;
```

DESCRIPTION

Cbrt(x) returns the cube root of x.

Sqrt(x) returns the square root of x.

DIAGNOSTICS

On a VAX, sqrt(negative) returns the reserved operand and sets *errno* to EDOM.

ERROR (due to Roundoff etc.)

Cbrt is accurate to within 0.7 *ulps*.

Sqrt on a VAX is accurate to within 0.501 *ulps*.

Sqrt on a machine that conforms to IEEE 754 is correctly rounded in accordance with the rounding mode in force; the error is less than half an *ulp* in the default mode (round-to-nearest). An *ulp* is one Unit in the Last Place carried.

SEE ALSO

math(3M), infnan(3M)

AUTHOR

W. Kahan

NAME

stdio – standard buffered input/output package

SYNOPSIS

```
#include <stdio.h>
```

```
FILE *stdin;
```

```
FILE *stdout;
```

```
FILE *stderr;
```

DESCRIPTION

The functions described in section 3S constitute a user-level buffering scheme. The in-line macros *getc* and *putc(3S)* handle characters quickly. The higher level routines *gets*, *fgets*, *scanf*, *fscanf*, *fread*, *puts*, *fputs*, *printf*, *sprintf*, *fwrite* all use *getc* and *putc*; they can be freely intermixed.

A file with associated buffering is called a *stream*, and is declared to be a pointer to a defined type *FILE*. *Fopen(3S)* creates certain descriptive data for a stream and returns a pointer to designate the stream in all further transactions. There are three normally open streams with constant pointers declared in the include file and associated with the standard open files:

```
stdin    standard input file
stdout   standard output file
stderr   standard error file
```

A constant 'pointer' NULL (0) designates no stream at all.

An integer constant EOF (-1) is returned upon end of file or error by integer functions that deal with streams.

Any routine that uses the standard input/output package must include the header file *<stdio.h>* of pertinent macro definitions. The functions and constants mentioned in sections labeled 3S are declared in the include file and need no further declaration. The constants, and the following 'functions' are implemented as macros; redeclaration of these names is perilous: *getc*, *getchar*, *putc*, *putchar*, *feof*, *ferror*, *fileno*.

SEE ALSO

open(2), *close(2)*, *read(2)*, *write(2)*, *fread(3S)*, *fseek(3S)*, *f*(3S)*

DIAGNOSTICS

The value EOF is returned uniformly to indicate that a *FILE* pointer has not been initialized with *fopen*, input (output) has been attempted on an output (input) stream, or a *FILE* pointer designates corrupt or otherwise unintelligible *FILE* data.

For purposes of efficiency, this implementation of the standard library has been changed to line buffer output to a terminal by default and attempts to do this transparently by flushing the output whenever a *read(2)* from the standard input is necessary. This is almost always transparent, but may cause confusion or malfunctioning of programs which use standard i/o routines but use *read(2)* themselves to read from the standard input.

In cases where a large amount of computation is done after printing part of a line on an output terminal, it is necessary to *fflush(3S)* the standard output before going off and computing so that the output will appear.

BUGS

The standard buffered functions do not interact well with certain other library and system functions, especially *vfork* and *abort*.

LIST OF FUNCTIONS

Name	Appears on Page	Description
clearerr	ferror.3s	stream status inquiries

<code>fclose</code>	<code>fclose.3s</code>	close or flush a stream
<code>fdopen</code>	<code>fopen.3s</code>	open a stream
<code>feof</code>	<code>ferror.3s</code>	stream status inquiries
<code>ferror</code>	<code>ferror.3s</code>	stream status inquiries
<code>fflush</code>	<code>fclose.3s</code>	close or flush a stream
<code>fgetc</code>	<code>getc.3s</code>	get character or word from stream
<code>fgets</code>	<code>gets.3s</code>	get a string from a stream
<code>fileno</code>	<code>ferror.3s</code>	stream status inquiries
<code>fopen</code>	<code>fopen.3s</code>	open a stream
<code>fprintf</code>	<code>printf.3s</code>	formatted output conversion
<code>fputc</code>	<code>putc.3s</code>	put character or word on a stream
<code>fputs</code>	<code>puts.3s</code>	put a string on a stream
<code>fread</code>	<code>fread.3s</code>	buffered binary input/output
<code>freopen</code>	<code>fopen.3s</code>	open a stream
<code>scanf</code>	<code>scanf.3s</code>	formatted input conversion
<code>fseek</code>	<code>fseek.3s</code>	reposition a stream
<code>ftell</code>	<code>fseek.3s</code>	reposition a stream
<code>fwrite</code>	<code>fread.3s</code>	buffered binary input/output
<code>getc</code>	<code>getc.3s</code>	get character or word from stream
<code>getchar</code>	<code>getc.3s</code>	get character or word from stream
<code>gets</code>	<code>gets.3s</code>	get a string from a stream
<code>getw</code>	<code>getc.3s</code>	get character or word from stream
<code>printf</code>	<code>printf.3s</code>	formatted output conversion
<code>putc</code>	<code>putc.3s</code>	put character or word on a stream
<code>putchar</code>	<code>putc.3s</code>	put character or word on a stream
<code>puts</code>	<code>puts.3s</code>	put a string on a stream
<code>putw</code>	<code>putc.3s</code>	put character or word on a stream
<code>rewind</code>	<code>fseek.3s</code>	reposition a stream
<code>scanf</code>	<code>scanf.3s</code>	formatted input conversion
<code>setbuf</code>	<code>setbuf.3s</code>	assign buffering to a stream
<code>setbuffer</code>	<code>setbuf.3s</code>	assign buffering to a stream
<code>setlinebuf</code>	<code>setbuf.3s</code>	assign buffering to a stream
<code>sprintf</code>	<code>printf.3s</code>	formatted output conversion
<code>sscanf</code>	<code>scanf.3s</code>	formatted input conversion
<code>ungetc</code>	<code>ungetc.3s</code>	push character back into input stream

NAME

strcat, strncat, strcmp, strncmp, strcpy, strncpy, strlen, index, rindex – string operations

SYNOPSIS

```
#include <strings.h>

char *strcat(s1, s2)
char *s1, *s2;

char *strncat(s1, s2, n)
char *s1, *s2;

strcmp(s1, s2)
char *s1, *s2;

strncmp(s1, s2, n)
char *s1, *s2;

strcpy(s1, s2)
char *s1, *s2;

strncpy(s1, s2, n)
char *s1, *s2;

strlen(s)
char *s;

char *index(s, c)
char *s, c;

char *rindex(s, c)
char *s, c;
```

DESCRIPTION

These functions operate on null-terminated strings. They do not check for overflow of any receiving string.

Strcat appends a copy of string *s2* to the end of string *s1*. *Strncat* copies at most *n* characters. Both return a pointer to the null-terminated result.

Strcmp compares its arguments and returns an integer greater than, equal to, or less than 0, according as *s1* is lexicographically greater than, equal to, or less than *s2*. *Strncmp* makes the same comparison but looks at at most *n* characters.

Strcpy copies string *s2* to *s1*, stopping after the null character has been moved. *Strncpy* copies exactly *n* characters, truncating or null-padding *s2*; the target may not be null-terminated if the length of *s2* is *n* or more. Both return *s1*.

Strlen returns the number of non-null characters in *s*.

Index (*rindex*) returns a pointer to the first (last) occurrence of character *c* in string *s*, or zero if *c* does not occur in the string.

NAME

stty, *gtty* – set and get terminal state (defunct)

SYNOPSIS

```
#include <sgtty.h>
```

```
stty(fd, buf)
int fd;
struct sgttyb *buf;
```

```
gtty(fd, buf)
int fd;
struct sgttyb *buf;
```

DESCRIPTION

This interface is obsoleted by *ioctl(2)*.

Stty sets the state of the terminal associated with *fd*. *Gtty* retrieves the state of the terminal associated with *fd*. To set the state of a terminal the call must have write permission.

The *stty* call is actually “*ioctl*(*fd*, *TIOCSETP*, *buf*)”, while the *gtty* call is “*ioctl*(*fd*, *TIOCGETP*, *buf*)”. See *ioctl(2)* and *tty(4)* for an explanation.

DIAGNOSTICS

If the call is successful 0 is returned, otherwise -1 is returned and the global variable *errno* contains the reason for the failure.

SEE ALSO

ioctl(2), *tty(4)*

NAME

swab – swap bytes

SYNOPSIS

swab(from, to, nbytes)
char *from, *to;

DESCRIPTION

Swab copies *nbytes* bytes pointed to by *from* to the position pointed to by *to*, exchanging adjacent even and odd bytes. It is useful for carrying binary data between PDP11's and other machines. *Nbytes* should be even.

P
R
M 3

NAME

syslog, openlog, closelog, setlogmask – control system log

SYNOPSIS

```
#include <syslog.h>

openlog(ident, logopt, facility)
char *ident;

syslog(priority, message, parameters ... )
char *message;

closelog()

setlogmask(maskpri)
```

DESCRIPTION

Syslog arranges to write *message* onto the system log maintained by *syslogd*(8). The message is tagged with *priority*. The message looks like a *printf*(3) string except that %m is replaced by the current error message (collected from *errno*). A trailing newline is added if needed. This message will be read by *syslogd*(8) and written to the system console, log files, or forwarded to *syslogd* on another host as appropriate.

Priorities are encoded as a *facility* and a *level*. The facility describes the part of the system generating the message. The level is selected from an ordered list:

LOG_EMERG	A panic condition. This is normally broadcast to all users.
LOG_ALERT	A condition that should be corrected immediately, such as a corrupted system database.
LOG_CRIT	Critical conditions, e.g., hard device errors.
LOG_ERR	Errors.
LOG_WARNING	Warning messages.
LOG_NOTICE	Conditions that are not error conditions, but should possibly be handled specially.
LOG_INFO	Informational messages.
LOG_DEBUG	Messages that contain information normally of use only when debugging a program.

If *syslog* cannot pass the message to *syslogd*, it will attempt to write the message on */dev/console* if the LOG_CONS option is set (see below).

If special processing is needed, *openlog* can be called to initialize the log file. The parameter *ident* is a string that is prepended to every message. *Logopt* is a bit field indicating logging options. Current values for *logopt* are:

LOG_PID	log the process id with each message: useful for identifying instantiations of daemons.
LOG_CONS	Force writing messages to the console if unable to send it to <i>syslogd</i> . This option is safe to use in daemon processes that have no controlling terminal since <i>syslog</i> will fork before opening the console.
LOG_NDELAY	Open the connection to <i>syslogd</i> immediately. Normally the open is delayed until the first message is logged. Useful for programs that need to manage the order in which file descriptors are allocated.
LOG_NOWAIT	Don't wait for children forked to log messages on the console. This option should be used by processes that enable notification of child termination via SIGCHLD, as <i>syslog</i> may otherwise block waiting for a

child whose exit status has already been collected.

The *facility* parameter encodes a default facility to be assigned to all messages that do not have an explicit facility encoded:

LOG_KERN	Messages generated by the kernel. These cannot be generated by any user processes.
LOG_USER	Messages generated by random user processes. This is the default facility identifier if none is specified.
LOG_MAIL	The mail system.
LOG_DAEMON	System daemons, such as <i>ftpd</i> (8), <i>routed</i> (8), etc.
LOG_AUTH	The authorization system: <i>login</i> (1), <i>su</i> (1), <i>getty</i> (8), etc.
LOG_LPR	The line printer spooling system: <i>lpr</i> (1), <i>lpc</i> (8), <i>lpd</i> (8), etc.
LOG_LOCAL0	Reserved for local use. Similarly for LOG_LOCAL1 through LOG_LOCAL7.

Closelog can be used to close the log file.

Setlogmask sets the log priority mask to *maskpri* and returns the previous mask. Calls to *syslog* with a priority not set in *maskpri* are rejected. The mask for an individual priority *pri* is calculated by the macro LOG_MASK(*pri*); the mask for all priorities up to and including *toppri* is given by the macro LOG_UPTO(*toppri*). The default allows all priorities to be logged.

EXAMPLES

```
syslog(LOG_ALERT, "who: internal error 23");

openlog("ftpd", LOG_PID, LOG_DAEMON);
setlogmask(LOG_UPTO(LOG_ERR));
syslog(LOG_INFO, "Connection from host %d", CallingHost);

syslog(LOG_INFO|LOG_LOCAL2, "foobar error: %m");
```

SEE ALSO

logger(1), syslogd(8)

NAME

system – issue a shell command

SYNOPSIS

system(string)
char *string;

DESCRIPTION

System causes the *string* to be given to *sh*(1) as input as if the string had been typed as a command at a terminal. The current process waits until the shell has completed, then returns the exit status of the shell.

SEE ALSO

popen(3S), *execve*(2), *wait*(2)

DIAGNOSTICS

Exit status 127 indicates the shell couldn't be executed.

P
R
M
3

NAME

tgetent, tgetnum, tgetflag, tgetstr, tgoto, tputs – terminal independent operation routines

SYNOPSIS

```
char PC;
char *BC;
char *UP;
short ospeed;

tgetent(bp, name)
char *bp, *name;

tgetnum(id)
char *id;

tgetflag(id)
char *id;

char *
tgetstr(id, area)
char *id, **area;

char *
tgoto(cm, destcol, destline)
char *cm;

tputs(cp, affcnt, outc)
register char *cp;
int affcnt;
int (*outc)();
```

DESCRIPTION

These functions extract and use capabilities from the terminal capability data base *termcap*(5). These are low level routines; see *curses*(3X) for a higher level package.

Tgetent extracts the entry for terminal *name* into the buffer at *bp*. *Bp* should be a character buffer of size 1024 and must be retained through all subsequent calls to *tgetnum*, *tgetflag*, and *tgetstr*. *Tgetent* returns -1 if it cannot open the *termcap* file, 0 if the terminal name given does not have an entry, and 1 if all goes well. It will look in the environment for a *TERMCAP* variable. If found, and the value does not begin with a slash, and the terminal type *name* is the same as the environment string *TERM*, the *TERMCAP* string is used instead of reading the *termcap* file. If it does begin with a slash, the string is used as a path name rather than */etc/termcap*. This can speed up entry into programs that call *tgetent*, as well as to help debug new terminal descriptions or to make one for your terminal if you can't write the file */etc/termcap*.

Tgetnum gets the numeric value of capability *id*, returning -1 if is not given for the terminal. *Tgetflag* returns 1 if the specified capability is present in the terminal's entry, 0 if it is not. *Tgetstr* returns the string value of the capability *id*, places it in the buffer at *area*, and advances the *area* pointer. It decodes the abbreviations for this field described in *termcap*(5), except for cursor addressing and padding information. *Tgetstr* returns NULL if the capability was not found.

Tgoto returns a cursor addressing string decoded from *cm* to go to column *destcol* in line *destline*. It uses the external variables *UP* (from the *up* capability) and *BC* (if *bc* is given rather than *bs*) if necessary to avoid placing *\n*, *^D* or *^@* in the returned string. (Programs which call *tgoto* should be sure to turn off the *XTABS* bit(s), since *tgoto* may now output a tab. Note that programs using *termcap* should in general turn off *XTABS* anyway since some terminals use control I for other functions, such as nondestructive space.) If a % sequence is given which is not understood, then *tgoto* returns "OOPS".

Tputs decodes the leading padding information of the string *cp*; *affcnt* gives the number of lines affected by the operation, or 1 if this is not applicable, *outc* is a routine which is called with each character in turn. The external variable *ospeed* should contain the output speed of the terminal as encoded by *stty(3)*. The external variable *PC* should contain a pad character to be used (from the *pc* capability) if a null (^@) is inappropriate.

FILES

/usr/lib/libtermcap.a -ltermcap library
/etc/termcap data base

SEE ALSO

ex(1), curses(3X), termcap(5)

AUTHOR

William Joy

P
R
M 3

NAME

time, ftime – get date and time

SYNOPSIS

```
long time(0)
```

```
long time(tloc)
```

```
long *tloc;
```

```
#include <sys/types.h>
```

```
#include <sys/timeb.h>
```

```
ftime(tp)
```

```
struct timeb *tp;
```

DESCRIPTION

These interfaces are obsoleted by `gettimeofday(2)`.

Time returns the time since 00:00:00 GMT, Jan. 1, 1970, measured in seconds.

If *tloc* is nonnull, the return value is also stored in the place to which *tloc* points.

The *ftime* entry fills in a structure pointed to by its argument, as defined by `<sys/timeb.h>`:

```
/*
 * Copyright (c) 1982 Regents of the University of California.
 * All rights reserved. The Berkeley software License Agreement
 * specifies the terms and conditions for redistribution.
 *
 *      @(#)timeb.h6.2 (Berkeley) 6/8/85
 */
```

```
/*
 * Structure returned by ftime system call
 */
```

```
struct timeb
{
    time_t    time;
    unsigned short millitm;
    short     timezone;
    short     dstflag;
};
```

The structure contains the time since the epoch in seconds, up to 1000 milliseconds of more-precise interval, the local time zone (measured in minutes of time westward from Greenwich), and a flag that, if nonzero, indicates that Daylight Saving time applies locally during the appropriate part of the year.

SEE ALSO

`date(1)`, `gettimeofday(2)`, `settimeofday(2)`, `ctime(3)`

NAME

times – get process times

SYNOPSIS

```
#include <sys/types.h>
```

```
#include <sys/times.h>
```

```
times(buffer)
```

```
struct tms *buffer;
```

DESCRIPTION

This interface is obsoleted by `getrusage(2)`.

Times returns time-accounting information for the current process and for the terminated child processes of the current process. All times are in 1/HZ seconds, where HZ is 60.

This is the structure returned by *times*:

```
/*
 * Copyright (c) 1982 Regents of the University of California.
 * All rights reserved. The Berkeley software License Agreement
 * specifies the terms and conditions for redistribution.
 *
 *      @(#)times.h    6.2 (Berkeley) 6/8/85
 */

/*
 * Structure returned by times()
 */
struct tms {
    time_t  tms_utime;      /* user time */
    time_t  tms_stime;      /* system time */
    time_t  tms_cutime;     /* user time, children */
    time_t  tms_cstime;     /* system time, children */
};
```

The children times are the sum of the children's process times and their children's times.

SEE ALSO

`time(1)`, `getrusage(2)`, `wait3(2)`, `time(3)`

NAME

ttyname, *isatty*, *ttyslot* – find name of a terminal

SYNOPSIS

char **ttyname*(*filedes*)

***isatty*(*filedes*)**

***ttyslot*()**

DESCRIPTION

Ttyname returns a pointer to the null-terminated path name of the terminal device associated with file descriptor *filedes* (this is a system file descriptor and has nothing to do with the standard I/O FILE typedef).

Isatty returns 1 if *filedes* is associated with a terminal device, 0 otherwise.

Ttyslot returns the number of the entry in the *ttys*(5) file for the control terminal of the current process.

FILES

/dev/*

/etc/ttys

SEE ALSO

ioctl(2), *ttys*(5)

DIAGNOSTICS

Ttyname returns a null pointer (0) if *filedes* does not describe a terminal device in directory '/dev'.

Ttyslot returns 0 if '/etc/ttys' is inaccessible or if it cannot determine the control terminal.

BUGS

The return value points to static data whose content is overwritten by each call.

NAME

`ualarm` – schedule signal after specified time

SYNOPSIS

```
unsigned ualarm(value, interval)
unsigned value;
unsigned interval;
```

DESCRIPTION

This is a simplified interface to `setitimer(2)`.

Ualarm causes signal `SIGALRM`, see *signal(3C)*, to be sent to the invoking process in a number of microseconds given by the *value* argument. Unless caught or ignored, the signal terminates the process.

If the *interval* argument is non-zero, the `SIGALRM` signal will be sent to the process every *interval* microseconds after the timer expires (e.g. after *value* microseconds have passed).

Because of scheduling delays, resumption of execution of when the signal is caught may be delayed an arbitrary amount. The longest specifiable delay time (on the vax) is 2147483647 microseconds.

The return value is the amount of time previously remaining in the alarm clock.

SEE ALSO

`getitimer(2)`, `setitimer(2)`, `sigpause(2)`, `sigvec(2)`, `signal(3C)`, `sleep(3)`, `alarm(3)`, `usleep(3)`

P
R
M
3

NAME

ungetc – push character back into input stream

SYNOPSIS

#include <stdio.h>

ungetc(c, stream)

FILE *stream;

DESCRIPTION

Ungetc pushes the character *c* back on an input stream. That character will be returned by the next *getc* call on that stream. *Ungetc* returns *c*.

One character of pushback is guaranteed provided something has been read from the stream and the stream is actually buffered. Attempts to push EOF are rejected.

Fseek(3S) erases all memory of pushed back characters.

SEE ALSO

getc(3S), *setbuf*(3S), *fseek*(3S)

DIAGNOSTICS

Ungetc returns EOF if it can't push a character back.

P
R
M
3

NAME

usleep – suspend execution for interval

SYNOPSIS

usleep(useconds)
unsigned useconds;

DESCRIPTION

The current process is suspended from execution for the number of microseconds specified by the argument. The actual suspension time may be an arbitrary amount longer because of other activity in the system or because of the time spent in processing the call.

The routine is implemented by setting an interval timer and pausing until it occurs. The previous state of this timer is saved and restored. If the sleep time exceeds the time to the expiration of the previous timer, the process sleeps only until the signal would have occurred, and the signal is sent a short time later.

This routine is implemented using *setitimer(2)*; it requires eight system calls each time it is invoked. A similar but less compatible function can be obtained with a single *select(2)*; it would not restart after signals, but would not interfere with other uses of *setitimer*.

SEE ALSO

setitimer(2), getitimer(2), sigpause(2), ualarm(3), sleep(3), alarm(3)

NAME

utime - set file times

SYNOPSIS

```
#include <sys/types.h>
```

```
utime(file, timep)
```

```
char *file;
```

```
time_t timep[2];
```

DESCRIPTION

This interface is obsoleted by `utimes(2)`.

The *utime* call uses the 'accessed' and 'updated' times in that order from the *timep* vector to set the corresponding recorded times for *file*.

The caller must be the owner of the file or the super-user. The 'inode-changed' time of the file is set to the current time.

SEE ALSO

`utimes(2)`, `stat(2)`

P
R
M
3

NAME

valloc – aligned memory allocator

SYNOPSIS

char *valloc(size)
unsigned size;

DESCRIPTION

Valloc is obsoleted by the current version of **malloc**, which aligns page-sized and larger allocations.

Valloc allocates *size* bytes aligned on a page boundary. It is implemented by calling *malloc(3)* with a slightly larger request, saving the true beginning of the block allocated, and returning a properly aligned pointer.

DIAGNOSTICS

Valloc returns a null pointer (0) if there is no available memory or if the arena has been detectably corrupted by storing outside the bounds of a block.

BUGS

Vfree isn't implemented.

NAME

varargs – variable argument list

SYNOPSIS

```
#include <varargs.h>

function(va_alist)
va_dcl
va_list pvar;
va_start(pvar);
f = va_arg(pvar, type);
va_end(pvar);
```

DESCRIPTION

This set of macros provides a means of writing portable procedures that accept variable argument lists. Routines having variable argument lists (such as *printf(3)*) that do not use *varargs* are inherently nonportable, since different machines use different argument passing conventions.

va_alist is used in a function header to declare a variable argument list.

va_dcl is a declaration for *va_alist*. Note that there is no semicolon after *va_dcl*.

va_list is a type which can be used for the variable *pvar*, which is used to traverse the list. One such variable must always be declared.

va_start(pvar) is called to initialize *pvar* to the beginning of the list.

va_arg(pvar, type) will return the next argument in the list pointed to by *pvar*. *Type* is the type to which the expected argument will be converted when passed as an argument. In standard C, arguments that are *char* or *short* should be accessed as *int*, *unsigned char* or *unsigned short* are converted to *unsigned int*, and *float* arguments are converted to *double*. Different types can be mixed, but it is up to the routine to know what type of argument is expected, since it cannot be determined at runtime.

va_end(pvar) is used to finish up.

Multiple traversals, each bracketed by *va_start* ... *va_end*, are possible.

EXAMPLE

```
#include <varargs.h>
execl(va_alist)
va_dcl
{
    va_list ap;
    char *file;
    char *args[100];
    int argno = 0;

    va_start(ap);
    file = va_arg(ap, char *);
    while (args[argno++] = va_arg(ap, char *))
        ;
    va_end(ap);
    return execl(file, args);
}
```

BUGS

It is up to the calling routine to determine how many arguments there are, since it is not possible to determine this from the stack frame. For example, *execl* passes a 0 to signal the end of the list. *Printf* can tell how many arguments are supposed to be there by the format.

The macros `va_start` and `va_end` may be arbitrarily complex; for example, `va_start` might contain an opening brace, which is closed by a matching brace in `va_end`. Thus, they should only be used where they could be placed within a single complex statement.

NAME

vlimit – control maximum system resource consumption

SYNOPSIS

```
#include <sys/vlimit.h>
```

```
vlimit(resource, value)
```

DESCRIPTION

This facility is superseded by `getrlimit(2)`.

Limits the consumption by the current process and each process it creates to not individually exceed *value* on the specified *resource*. If *value* is specified as `-1`, then the current limit is returned and the limit is unchanged. The resources which are currently controllable are:

LIM_NORAISE

A pseudo-limit; if set non-zero then the limits may not be raised. Only the super-user may remove the *noraise* restriction.

LIM_CPU the maximum number of cpu-seconds to be used by each process

LIM_FSIZE the largest single file which can be created

LIM_DATA the maximum growth of the data+stack region via *sbrk(2)* beyond the end of the program text

LIM_STACK the maximum size of the automatically-extended stack region

LIM_CORE the size of the largest core dump that will be created.

LIM_MAXRSS a soft limit for the amount of physical memory (in bytes) to be given to the program. If memory is tight, the system will prefer to take memory from processes which are exceeding their declared LIM_MAXRSS.

Because this information is stored in the per-process information this system call must be executed directly by the shell if it is to affect all future processes created by the shell; *limit* is thus a built-in command to *csh(1)*.

The system refuses to extend the data or stack space when the limits would be exceeded in the normal way; a *break* call fails if the data space limit is reached, or the process is killed when the stack limit is reached (since the stack cannot be extended, there is no way to send a signal!).

A file i/o operation which would create a file which is too large will cause a signal SIGXFSZ to be generated, this normally terminates the process, but may be caught. When the cpu time limit is exceeded, a signal SIGXCPU is sent to the offending process; to allow it time to process the signal it is given 5 seconds grace by raising the cpu time limit.

SEE ALSO

csh(1)

BUGS

LIM_NORAISE no longer exists.

NAME

`vtimes` – get information about resource utilization

SYNOPSIS

```
#include <sys/vtimes.h>

vtimes(par_vm, ch_vm)
struct vtimes *par_vm, *ch_vm;
```

DESCRIPTION

This facility is superseded by `getrusage(2)`.

`Vtimes` returns accounting information for the current process and for the terminated child processes of the current process. Either `par_vm` or `ch_vm` or both may be 0, in which case only the information for the pointers which are non-zero is returned.

After the call, each buffer contains information as defined by the contents of the include file `/usr/include/sys/vtimes.h`:

```
struct vtimes {
    int    vm_untime;          /* user time (*HZ) */
    int    vm_stime;           /* system time (*HZ) */
    /* divide next two by utime+stime to get averages */
    unsigned vm_idrssi;         /* integral of d+s rss */
    unsigned vm_ixrssi;         /* integral of text rss */
    int    vm_maxrss;          /* maximum rss */
    int    vm_majflt;          /* major page faults */
    int    vm_minflt;          /* minor page faults */
    int    vm_nswap;           /* number of swaps */
    int    vm_inblk;           /* block reads */
    int    vm_oublk;           /* block writes */
};
```

The `vm_untime` and `vm_stime` fields give the user and system time respectively in 60ths of a second (or 50ths if that is the frequency of wall current in your locality.) The `vm_idrssi` and `vm_ixrssi` measure memory usage. They are computed by integrating the number of memory pages in use each over cpu time. They are reported as though computed discretely, adding the current memory usage (in 512 byte pages) each time the clock ticks. If a process used 5 core pages over 1 cpu-second for its data and stack, then `vm_idrssi` would have the value `5*60`, where `vm_untime+vm_stime` would be the 60. `vm_idrssi` integrates data and stack segment usage, while `vm_ixrssi` integrates text segment usage. `vm_maxrss` reports the maximum instantaneous sum of the text+data+stack core-resident page count.

The `vm_majflt` field gives the number of page faults which resulted in disk activity; the `vm_minflt` field gives the number of page faults incurred in simulation of reference bits; `vm_nswap` is the number of swaps which occurred. The number of file system input/output events are reported in `vm_inblk` and `vm_oublk`. These numbers account only for real i/o; data supplied by the caching mechanism is charged only to the first process to read or write the data.

SEE ALSO

`time(2)`, `wait3(2)`, `getrusage(2)`

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

100-100000

PRM 3

NAME

intro – introduction to FORTRAN library functions

DESCRIPTION

This section describes those functions that are in the Fortran run time library. The functions listed here provide an interface from *f77* programs to the system in the same manner as the C library does for C programs. They are automatically loaded as needed by the Fortran compiler *f77(1)*, except for the graphics interface routines. Those must be explicitly requested, see *plot(3f)*.

The math intrinsics required by the 1977 Fortran standard are available, although not described here. In addition, the *abs*, *sqrt*, *exp*, *log*, *sin*, and *cos* intrinsics have been extended for double complex values. They may be referenced using the generic names listed above, or they may be referenced using their specific names that consist of the generic names preceded by either *cd* or *z*. For example, if *zz* is double complex, then *sqrt(zz)*, *zsqrt(zz)*, or *cdsqrt(zz)* compute the square root of *zz*. The *dcmplx* intrinsic forms a double complex value from two double precision variables or expressions, and the name of the specific function for the conjugate of a double complex value is *dconjg*.

Most of these functions are in *libU77.a*. Some are in *libF77.a* or *libI77.a*. A few intrinsic functions are described for the sake of completeness.

For efficiency, the SCCS ID strings are not normally included in the *a.out* file. To include them, simply declare

```
external f77lid
```

in any *f77* module.

LIST OF FUNCTIONS

Name	Appears on Page	Description
abort	abort.3f	abnormal termination
access	access.3f	determine accessibility of a file
alarm	alarm.3f	execute a subroutine after a specified time
and	bit.3f	bitwise and
arc	plot.3f	<i>f77</i> interface to <i>plot(3x)</i>
bessel	bessel.3f	bessel functions of two kinds for integer orders
box	plot.3f	<i>f77</i> interface to <i>plot(3x)</i>
chdir	chdir.3f	change default directory
chmod	chmod.3f	change mode of a file
circle	plot.3f	<i>f77</i> interface to <i>plot(3x)</i>
clospl	plot.3f	<i>f77</i> interface to <i>plot(3x)</i>
cont	plot.3f	<i>f77</i> interface to <i>plot(3x)</i>
ctime	time.3f	return system time
dfrac	flmin.3f	return extreme values
dflmax	flmin.3f	return extreme values
dflmin	flmin.3f	return extreme values
drand	rand.3f	return random values
drandm	random.3f	better random number generator
dtime	etime.3f	return elapsed execution time
erase	plot.3f	<i>f77</i> interface to <i>plot(3x)</i>
etime	etime.3f	return elapsed execution time
exit	exit.3f	terminate process with status
falloc	malloc.3f	memory allocator
fdate	fdate.3f	return date and time in an ASCII string
ffrac	flmin.3f	return extreme values

fgetc	getc.3f	get a character from a logical unit
flmax	flmin.3f	return extreme values
flmin	flmin.3f	return extreme values
flush	flush.3f	flush output to a logical unit
fork	fork.3f	create a copy of this process
fpecnt	trpfpe.3f	trap and repair floating point faults
fputc	putc.3f	write a character to a fortran logical unit
free	malloc.3f	memory allocator
fseek	fseek.3f	reposition a file on a logical unit
fstat	stat.3f	get file status
ftell	fseek.3f	reposition a file on a logical unit
gerror	perror.3f	get system error messages
getarg	getarg.3f	return command line arguments
getc	getc.3f	get a character from a logical unit
getcwd	getcwd.3f	get pathname of current working directory
getenv	getenv.3f	get value of environment variables
getgid	getuid.3f	get user or group ID of the caller
getlog	getlog.3f	get user's login name
getpid	getpid.3f	get process id
getuid	getuid.3f	get user or group ID of the caller
gmtime	time.3f	return system time
hostnm	hostnm.3f	get name of current host
iargc	getarg.3f	return command line arguments
idate	idate.3f	return date or time in numerical form
ierrno	perror.3f	get system error messages
index	index.3f	tell about character objects
inmax	flmin.3f	return extreme values
ioinit	ioinit.3f	change f77 I/O initialization
irand	rand.3f	return random values
irandm	random.3f	better random number generator
isatty	ttynam.3f	find name of a terminal port
itime	idate.3f	return date or time in numerical form
kill	kill.3f	send a signal to a process
label	plot.3f	f77 interface to plot(3x)
len	index.3f	tell about character objects
line	plot.3f	f77 interface to plot(3x)
linemd	plot.3f	f77 interface to plot(3x)
link	link.3f	make a link to an existing file
lnblk	index.3f	tell about character objects
loc	loc.3f	return the address of an object
long	long.3f	integer object conversion
lshift	bit.3f	left shift
lstat	stat.3f	get file status
ltime	time.3f	return system time
malloc	malloc.3f	memory allocator
move	plot.3f	f77 interface to plot(3x)
not	bit.3f	bitwise complement
openpl	plot.3f	f77 interface to plot(3x)
or	bit.3f	bitwise or
perror	perror.3f	get system error messages
point	plot.3f	f77 interface to plot(3x)
putc	putc.3f	write a character to a fortran logical unit
qsort	qsort.3f	quick sort

rand	rand.3f	return random values
random	random.3f	better random number generator
rename	rename.3f	rename a file
rindex	index.3f	tell about character objects
rshift	bit.3f	right shift
short	long.3f	integer object conversion
signal	signal.3f	change the action for a signal
sleep	sleep.3f	suspend execution for an interval
space	plot.3f	f77 interface to plot(3x)
stat	stat.3f	get file status
symlink	symlink.3f	make a symbolic link
system	system.3f	execute a UNIX command
tclose	topen.3f	f77 tape I/O
time	time.3f	return system time
topen	topen.3f	f77 tape I/O
traper	traper.3f	trap arithmetic errors
trapov	trapov.3f	trap and repair floating point overflow
tread	topen.3f	f77 tape I/O
trewin	topen.3f	f77 tape I/O
trpfpe	trpfpe.3f	trap and repair floating point faults
tskipf	topen.3f	f77 tape I/O
tstate	topen.3f	f77 tape I/O
ttynam	ttynam.3f	find name of a terminal port
twrite	topen.3f	f77 tape I/O
unlink	unlink.3f	remove a directory entry
wait	wait.3f	wait for a process to terminate
xor	bit.3f	bitwise exclusive or

P
R
M
3F

NAME

abort – abnormal termination

SYNOPSIS

subroutine abort (string)
character*(*) string

DESCRIPTION

Abort cleans up the I/O buffers and then terminates execution. If *string* is given, it is written to logical unit 0 preceded by "abort:".

If the *-g* flag was specified during loading, then execution is terminated by calling *abort* (3) which aborts producing a *core* file in the current directory. If *-g* was not specified while loading, then *** *Execution terminated* is written on logical unit 0 and execution is terminated.

If the *f77_dump_flag* environment variable has been set to a value which begins with *y*, *abort* (3) is called whether or not *-g* was specified during loading. Similarly, if the value of *f77_dump_flag* begins with *n*, *abort* is not called.

FILES

/usr/lib/libF77.a

SEE ALSO

abort(3)

BUGS

String is ignored on the PDP11.

P
R
M 3F

NAME

access – determine accessibility of a file

SYNOPSIS

integer function access (name, mode)
characters(*) name, mode

DESCRIPTION

Access checks the given file, *name*, for accessibility with respect to the caller according to *mode*. *Mode* may include in any order and in any combination one or more of:

r	test for read permission
w	test for write permission
x	test for execute permission
(blank)	test for existence

An error code is returned if either argument is illegal, or if the file cannot be accessed in all of the specified modes. 0 is returned if the specified access would be successful.

FILES

/usr/lib/libU77.a

SEE ALSO

access(2), perror(3F)

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in *<sys/param.h>*.

P
R
M
3F

NAME

alarm – execute a subroutine after a specified time

SYNOPSIS

integer function alarm (time, proc)
integer time
external proc

DESCRIPTION

This routine arranges for subroutine *proc* to be called after *time* seconds. If *time* is "0", the alarm is turned off and no routine will be called. The returned value will be the time remaining on the last alarm.

FILES

/usr/lib/libU77.a

SEE ALSO

alarm(3C), sleep(3F), signal(3F)

BUGS

Alarm and *sleep* interact. If *sleep* is called after *alarm*, the *alarm* process will never be called. SIGALRM will occur at the lesser of the remaining *alarm* time or the *sleep* time.

P
R
M 3F

NAME

bessel functions – of two kinds for integer orders

SYNOPSIS

function *besj0* (x)

function *besj1* (x)

function *besjn* (n, x)

function *besy0* (x)

function *besy1* (x)

function *besyn* (n, x)

double precision function *dbesj0* (x)

double precision x

double precision function *dbesj1* (x)

double precision x

double precision function *dbesjn* (n, x)

double precision x

double precision function *dbesy0* (x)

double precision x

double precision function *dbesy1* (x)

double precision x

double precision function *dbesyn* (n, x)

double precision x

DESCRIPTION

These functions calculate Bessel functions of the first and second kinds for real arguments and integer orders.

DIAGNOSTICS

Negative arguments cause *besy0*, *besy1*, and *besyn* to return a huge negative value. The system error code will be set to EDOM (33).

FILES

/usr/lib/libF77.a

SEE ALSO

j0(3M), *perror*(3F)

P
R
M
3F

NAME

bit – and, or, xor, not, rshift, lshift bitwise functions

SYNOPSIS

(intrinsic) function and (word1, word2)

(intrinsic) function or (word1, word2)

(intrinsic) function xor (word1, word2)

(intrinsic) function not (word)

(intrinsic) function rshift (word, nbits)

(intrinsic) function lshift (word, nbits)

DESCRIPTION

These bitwise functions are built into the compiler and return the data type of their argument(s). Their arguments must be integer or logical values.

The bitwise combinatorial functions return the bitwise “and” (and), “or” (or), or “exclusive or” (xor) of two operands. Not returns the bitwise complement of its operand.

Lshift, or *rshift* with a negative *nbits*, is a logical left shift with no end around carry. *Rshift*, or *lshift* with a negative *nbits*, is an arithmetic right shift with sign extension. No test is made for a reasonable value of *nbits*.

These functions may be used to create a variety of general routines, as in the following statement function definitions:

integer bitset, bitclr, getbit, word, bitnum

bitset(word, bitnum) = or(word,lshift(1,bitnum))

bitclr(word, bitnum) = and(word,not(lshift(1,bitnum)))

getbit(word, bitnum) = and(rshift(word,bitnum),1)

FILES

These functions are generated in-line by the f77 compiler.

P
R
M
3F

NAME

chdir – change default directory

SYNOPSIS

integer function **chdir** (*dirname*)
character*(*) *dirname*

DESCRIPTION

The default directory for creating and locating files will be changed to *dirname*. Zero is returned if successful; an error code otherwise.

FILES

/usr/lib/libU77.a

SEE ALSO

chdir(2), **cd(1)**, **perror(3F)**

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in *<sys/param.h>*.

Use of this function may cause **inquire** by unit to fail.

P
R
M
3F

NAME

chmod – change mode of a file

SYNOPSIS

integer function chmod (name, mode)
character*(*) name, mode

DESCRIPTION

This function changes the filesystem *mode* of file *name*. *Mode* can be any specification recognized by *chmod(1)*. *Name* must be a single pathname.

The normal returned value is 0. Any other value will be a system error number.

FILES

/usr/lib/libU77.a
/bin/chmod exec'ed to change the mode.

SEE ALSO

chmod(1)

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in <sys/param.h>.

P
R
M 3F

NAME

etime, dtime – return elapsed execution time

SYNOPSIS

function etime (tarray)
real tarray(2)

function dtime (tarray)
real tarray(2)

DESCRIPTION

These two routines return elapsed runtime in seconds for the calling process. *Dtime* returns the elapsed time since the last call to *dtime*, or the start of execution on the first call.

The argument array returns user time in the first element and system time in the second element. The function value is the sum of user and system time.

The resolution of all timing is 1/HZ sec. where HZ is currently 60.

FILES

/usr/lib/libU77.a

SEE ALSO

times(2)

P
R
M
3F

NAME

exit – terminate process with status

SYNOPSIS

subroutine exit (status)
integer status

DESCRIPTION

Exit flushes and closes all the process's files, and notifies the parent process if it is executing a *wait*. The low-order 8 bits of *status* are available to the parent process. (Therefore *status* should be in the range 0 – 255)

This call will never return.

The C function *exit* may cause cleanup actions before the final 'sys exit'.

FILES

/usr/lib/libF77.a

SEE ALSO

exit(2), fork(2), fork(3F), wait(2), wait(3F)

P
R
M
3F

NAME

fdate – return date and time in an ASCII string

SYNOPSIS

subroutine fdate (string)
character*(*) string

character*(*) function fdate()

DESCRIPTION

Fdate returns the current date and time as a 24 character string in the format described under *ctime(3)*. Neither 'newline' nor NULL will be included.

Fdate can be called either as a function or as a subroutine. If called as a function, the calling routine must define its type and length. For example:

```
character*24 fdate
external    fdate
```

```
write(*,*) fdate()
```

FILES

/usr/lib/libU77.a

SEE ALSO

ctime(3), *time(3F)*, *itime(3F)*, *idate(3F)*, *ltime(3F)*

P
R
M
3F

NAME

flmin, *flmax*, *ffrac*, *dflmin*, *dflmax*, *dffrac*, *inmax* – return extreme values

SYNOPSIS

function flmin()

function flmax()

function ffrac()

double precision function dflmin()

double precision function dflmax()

double precision function dffrac()

function inmax()

DESCRIPTION

Functions *flmin* and *flmax* return the minimum and maximum positive floating point values respectively. Functions *dflmin* and *dflmax* return the minimum and maximum positive double precision floating point values. Function *inmax* returns the maximum positive integer value.

The functions *ffrac* and *dffrac* return the fractional accuracy of single and double precision floating point numbers respectively. This is the difference between 1.0 and the smallest real number greater than 1.0.

These functions can be used by programs that must scale algorithms to the numerical range of the processor.

FILES

/usr/lib/libF77.a

P
R
M
3F

NAME

flush – flush output to a logical unit

SYNOPSIS

subroutine flush (lunit)

DESCRIPTION

Flush causes the contents of the buffer for logical unit *lunit* to be flushed to the associated file. This is most useful for logical units 0 and 6 when they are both associated with the control terminal.

FILES

/usr/lib/libl77.a

SEE ALSO

fclose(3S)

P
R
M
3F

NAME

fork – create a copy of this process

SYNOPSIS

integer function fork()

DESCRIPTION

Fork creates a copy of the calling process. The only distinction between the 2 processes is that the value returned to one of them (referred to as the 'parent' process) will be the process id of the copy. The copy is usually referred to as the 'child' process. The value returned to the 'child' process will be zero.

All logical units open for writing are flushed before the fork to avoid duplication of the contents of I/O buffers in the external file(s).

If the returned value is negative, it indicates an error and will be the negation of the system error code. See *perror*(3F).

A corresponding *exec* routine has not been provided because there is no satisfactory way to retain open logical units across the *exec*. However, the usual function of *fork/exec* can be performed using *system*(3F).

FILES

/usr/lib/libU77.a

SEE ALSO

fork(2), wait(3F), kill(3F), system(3F), perror(3F)

P
R
M
3F

NAME

fseek, *ftell* – reposition a file on a logical unit

SYNOPSIS

integer function *fseek* (*lunit*, *offset*, *from*)
integer *offset*, *from*

integer function *ftell* (*lunit*)

DESCRIPTION

lunit must refer to an open logical unit. *offset* is an offset in bytes relative to the position specified by *from*. Valid values for *from* are:

- 0 meaning 'beginning of the file'
- 1 meaning 'the current position'
- 2 meaning 'the end of the file'

The value returned by *fseek* will be 0 if successful, a system error code otherwise. (See *perror*(3F))

Ftell returns the current position of the file associated with the specified logical unit. The value is an offset, in bytes, from the beginning of the file. If the value returned is negative, it indicates an error and will be the negation of the system error code. (See *perror*(3F))

FILES

/usr/lib/libU77.a

SEE ALSO

fseek(3S), *perror*(3F)

P
R
M
3F

NAME

getarg, iargc – return command line arguments

SYNOPSIS

subroutine *getarg* (*k*, *arg*)
character*(*) *arg*

function *iargc* ()

DESCRIPTION

A call to *getarg* will return the *k**th* command line argument in character string *arg*. The 0*th* argument is the command name.

iargc returns the index of the last command line argument.

FILES

/usr/lib/libU77.a

SEE ALSO

getenv(3F), *execve*(2)

P
R
M
3F

NAME

getc, fgetc – get a character from a logical unit

SYNOPSIS

integer function **getc** (char)
character char

integer function **fgetc** (lunit, char)
character char

DESCRIPTION

These routines return the next character from a file associated with a fortran logical unit, bypassing normal fortran I/O. *Getc* reads from logical unit 5, normally connected to the control terminal input.

The value of each function is a system status code. Zero indicates no error occurred on the read; -1 indicates end of file was detected. A positive value will be either a UNIX system error code or an f77 I/O error code. See *perror*(3F).

FILES

/usr/lib/libU77.a

SEE ALSO

getc(3S), *intro*(2), *perror*(3F)

P
R
M
3F

NAME

getcwd – get pathname of current working directory

SYNOPSIS

integer function **getcwd** (*dirname*)
character*(*) *dirname*

DESCRIPTION

The pathname of the default directory for creating and locating files will be returned in *dirname*. The value of the function will be zero if successful; an error code otherwise.

FILES

/usr/lib/libU77.a

SEE ALSO

chdir(3F), perror(3F)

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in *<sys/param.h>*.

P
R
M 3F

NAME

getenv – get value of environment variables

SYNOPSIS

subroutine *getenv* (*ename*, *eval*)
character*(*) *ename*, *eval*

DESCRIPTION

Getenv searches the environment list (see *environ*(7)) for a string of the form *ename=value* and returns *value* in *eval* if such a string is present, otherwise fills *eval* with blanks.

FILES

/usr/lib/libU77.a

SEE ALSO

environ(7), *execve*(2)

P
R
M
3F

NAME

getlog – get user's login name

SYNOPSIS

subroutine getlog (name)
character*(*) name

character*(*) function getlog()

DESCRIPTION

Getlog will return the user's login name or all blanks if the process is running detached from a terminal.

FILES

/usr/lib/libU77.a

SEE ALSO

getlogin(3)

P
R
M
3F

NAME

`getpid` – get process id

SYNOPSIS

integer function `getpid()`

DESCRIPTION

Getpid returns the process ID number of the current process.

FILES

`/usr/lib/libU77.a`

SEE ALSO

`getpid(2)`

P
R
M
3F

NAME

getuid, getgid – get user or group ID of the caller

SYNOPSIS

integer function getuid()

integer function getgid()

DESCRIPTION

These functions return the real user or group ID of the user of the process.

FILES

/usr/lib/libU77.a

SEE ALSO

getuid(2)

P
R
M
3F

NAME

hostnm - get name of current host

SYNOPSIS

integer function hostnm (name)
character*(*) name

DESCRIPTION

This function puts the name of the current host into character string *name*. The return value should be 0; any other value indicates an error.

FILES

/usr/lib/libU77.a

SEE ALSO

gethostname(2)

P
R
M
3F

NAME

idate, itime – return date or time in numerical form

SYNOPSIS

subroutine idate (iarray)
integer iarray(3)

subroutine itime (iarray)
integer iarray(3)

DESCRIPTION

Idate returns the current date in *iarray*. The order is: day, mon, year. Month will be in the range 1-12. Year will be ≥ 1969 .

Itime returns the current time in *iarray*. The order is: hour, minute, second.

FILES

/usr/lib/libU77.a

SEE ALSO

ctime(3F), fdate(3F)

P
R
M
3F

NAME

index, rindex, lnblnk, len – tell about character objects

SYNOPSIS

(intrinsic) function index (string, substr)
character*(*) string, substr

integer function rindex (string, substr)
character*(*) string, substr

function lnblnk (string)
character*(*) string

(intrinsic) function len (string)
character*(*) string

DESCRIPTION

Index (*rindex*) returns the index of the first (last) occurrence of the substring *substr* in *string*, or zero if it does not occur. *Index* is an f77 intrinsic function; *rindex* is a library routine.

Lnblnk returns the index of the last non-blank character in *string*. This is useful since all f77 character objects are fixed length, blank padded. Intrinsic function *len* returns the size of the character object argument.

FILES

/usr/lib/libF77.a

P
R
M
3F

NAME

ioinit - change f77 I/O initialization

SYNOPSIS

logical function *ioinit* (*cctl*, *bzro*, *apnd*, *prefix*, *vrbose*)
 logical *cctl*, *bzro*, *apnd*, *vrbose*
 character*(*) *prefix*

DESCRIPTION

This routine will initialize several global parameters in the f77 I/O system, and attach externally defined files to logical units at run time. The effect of the flag arguments applies to logical units opened after *ioinit* is called. The exception is the preassigned units, 5 and 6, to which *cctl* and *bzro* will apply at any time. *ioinit* is written in Fortran-77.

By default, carriage control is not recognized on any logical unit. If *cctl* is *.true.* then carriage control will be recognized on formatted output to all logical units except unit 0, the diagnostic channel. Otherwise the default will be restored.

By default, trailing and embedded blanks in input data fields are ignored. If *bzro* is *.true.* then such blanks will be treated as zeros. Otherwise the default will be restored.

By default, all files opened for sequential access are positioned at their beginning. It is sometimes necessary or convenient to open at the END-OF-FILE so that a write will append to the existing data. If *apnd* is *.true.* then files opened subsequently on any logical unit will be positioned at their end upon opening. A value of *.false.* will restore the default behavior.

ioinit may be used to associate file names with Fortran logical unit numbers through environment variables (see "Introduction to the f77 I/O Library" for a more general way of doing this). If the argument *prefix* is a non-blank string, then names of the form *prefixNN* will be sought in the program environment. The value associated with each such name found will be used to open logical unit NN for formatted sequential access. For example, if f77 program *myprogram* included the call

```
call ioinit (.true., .false., .false., 'FORT', .false.)
```

then when the following sequence

```
% setenv FORT01 mydata
% setenv FORT12 myresults
% myprogram
```

would result in logical unit 1 opened to file *mydata* and logical unit 12 opened to file *myresults*. Both files would be positioned at their beginning. Any formatted output would have column 1 removed and interpreted as carriage control. Embedded and trailing blanks would be ignored on input.

If the argument *vrbose* is *.true.* then *ioinit* will report on its activity.

The effect of

```
call ioinit (.true., .true., .false., "", .false.)
```

can be achieved without the actual call by including "--ll66" on the f77 command line. This gives carriage control on all logical units except 0, causes files to be opened at their beginning, and causes blanks to be interpreted as zero's.

The internal flags are stored in a labeled common block with the following definition:

```
integer*2 ieof, ictl, ibzr
```

common /ioiflg/ ieof, ictl, ibzr

FILES

/usr/lib/libl77.a	f77 I/O library
/usr/lib/libl66.a	sets older fortran I/O modes

SEE ALSO

getarg(3F), getenv(3F), "Introduction to the f77 I/O Library"

BUGS

Prefix can be no longer than 30 characters. A pathname associated with an environment name can be no longer than 255 characters.

The "+" carriage control does not work.

P
R
M
3F

NAME

kill – send a signal to a process

SYNOPSIS

function kill (pid, signum)
integer pid, signum

DESCRIPTION

Pid must be the process id of one of the user's processes. *Signum* must be a valid signal number (see sigvec(2)). The returned value will be 0 if successful; an error code otherwise.

FILES

/usr/lib/libU77.a

SEE ALSO

kill(2), sigvec(2), signal(3F), fork(3F), perror(3F)

P
R
M 3F

NAME

link – make a link to an existing file

SYNOPSIS

function link (name1, name2)
character*(*) name1, name2

integer function symlink (name1, name2)
character*(*) name1, name2

DESCRIPTION

Name1 must be the pathname of an existing file. *Name2* is a pathname to be linked to file *name1*. *Name2* must not already exist. The returned value will be 0 if successful; a system error code otherwise.

Symlink creates a symbolic link to *name1*.

FILES

/usr/lib/libU77.a

SEE ALSO

link(2), symlink(2), perror(3F), unlink(3F)

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in <sys/param.h>.

P
R
M
3F

NAME

loc – return the address of an object

SYNOPSIS

function **loc** (**arg**)

DESCRIPTION

The returned value will be the address of *arg*.

FILES

/usr/lib/libU77.a

P
R
M
3F

NAME

long, short – integer object conversion

SYNOPSIS

integer•4 function long (int2)
integer•2 int2

integer•2 function short (int4)
integer•4 int4

DESCRIPTION

These functions provide conversion between short and long integer objects. *Long* is useful when constants are used in calls to library routines and the code is to be compiled with “-i2”. *Short* is useful in similar context when an otherwise long object must be passed as a short integer.

FILES

/usr/lib/libF77.a

P
R
M
3F

NAME

malloc, free, calloc – memory allocator

SYNOPSIS

subroutine malloc (size, addr)

integer size, addr

subroutine free (addr)

integer addr

subroutine calloc (nelem, elsize, clean, basevec, addr, offset)

integer nelem, elsize, clean, addr, offset

DESCRIPTION

Malloc, *calloc* and *free* provide a general-purpose memory allocation package. *Malloc* returns in *addr* the address of a block of at least *size* bytes beginning on an even-byte boundary.

Calloc allocates space for an array of *nelem* elements of size *elsize* and returns the address of the block in *addr*. It zeros the block if *clean* is 1. It returns in *offset* an index such that the storage may be addressed as *basevec(offset+1) ... basevec(offset+nelem)*. *Calloc* gets extra bytes so that after address arithmetic, all the objects so addressed are within the block.

The argument to *free* is the address of a block previously allocated by *malloc* or *calloc*; this space is made available for further allocation, but its contents are left undisturbed. To free blocks allocated by *calloc*, use *addr* in calls to *free*, do not use *basevec(offset+1)*.

Needless to say, grave disorder will result if the space assigned by *malloc* or *calloc* is overrun or if some random number is handed to *free*.

DIAGNOSTICS

Malloc and *calloc* set *addr* to 0 if there is no available memory or if the arena has been detectably corrupted by storing outside the bounds of a block.

The following example shows how to obtain memory and use it within a subprogram:

```
integer addr, work(1), offset
...
call calloc ( n, 4, 0, work, addr, offset )
do 10 i = 1, n
  work(offset+i) = ...
10 continue
```

The next example reads in dimension information, allocates space for two arrays and two vectors, and calls subroutine *doit* to do the computations:

```
integer addr, dummy(1), offs
read *, k, l, m
indm1 = 1
indm2 = indm1 + k*l
indm3 = indm2 + l*m
indsym = indm3 + k*m
lsym = n*(n+1)/2
indv = indsym + lsym
indtot = indv + m
call calloc ( indtot, 4, 0, dummy, addr, offs )
call doit( dummy(indm1+offs), dummy(indm2+offs),
.         dummy(indm3+offs), dummy(indsym+offs),
.         dummy(indv +offs), m, n, lsym )
end
```

```
subroutine doit( arr1, arr2, arr3, vsym, vec, m, n, lsym )
real arr1(k,l), arr2(l,m), arr3(k,m), vsym(lsym), v2(m)
...
```

FILES

/usr/lib/libU77.a

SEE ALSO

malloc(3)

P
R
M
3F

NAME

`perror`, `error`, `ierrno` – get system error messages

SYNOPSIS

subroutine `perror` (*string*)
character*(*) *string*

subroutine `error` (*string*)
character*(*) *string*

character*(*) **function** `error()`

function `ierrno()`

DESCRIPTION

Perror will write a message to fortran logical unit 0 appropriate to the last detected system error. *String* will be written preceding the standard error message.

Error returns the system error message in character variable *string*. *Error* may be called either as a subroutine or as a function.

Ierrno will return the error number of the last detected system error. This number is updated only when an error actually occurs. Most routines and I/O statements that might generate such errors return an error code after the call; that value is a more reliable indicator of what caused the error condition.

FILES

`/usr/lib/libU77.a`

SEE ALSO

`intro(2)`, `perror(3)`
 D. L. Wasley, *Introduction to the f77 I/O Library*

BUGS

String in the call to *perror* can be no longer than 127 characters.

The length of the string returned by *error* is determined by the calling program.

NOTES

UNIX system error codes are described in *intro(2)*. The f77 I/O error codes and their meanings are:

100	"error in format"
101	"illegal unit number"
102	"formatted i/o not allowed"
103	"unformatted i/o not allowed"
104	"direct i/o not allowed"
105	"sequential i/o not allowed"
106	"can't backspace file"
107	"off beginning of record"
108	"can't stat file"
109	"no * after repeat count"
110	"off end of record"
111	"truncation failed"
112	"incomprehensible list input"
113	"out of free space"
114	"unit not connected"
115	"invalid data for integer format term"
116	"invalid data for logical format term"

- 117 "new" file exists"
- 118 "can't find 'old' file"
- 119 "opening too many files or unknown system error"
- 120 "requires seek ability"
- 121 "illegal argument"
- 122 "negative repeat count"
- 123 "illegal operation for unit"
- 124 "invalid data for d, e, f, or g format term"

P
R
M
3F

NAME

plot: openpl et al. - f77 library interface to *plot* (3X) libraries.

SYNOPSIS

```

subroutine openpl()
subroutine erase()
subroutine label(str)
character str*(*)
subroutine line(ix1, iy1, ix2, iy2)
subroutine box(ix1, iy1, ix2, iy2)
Draw a rectangle and leave the cursor at ( ix2,iy2).
subroutine circle(ix, iy, ir)
subroutine arc(ix, iy, ix0, iy0, ix1, iy1)
subroutine move(ix, iy)
subroutine cont(ix, iy)
subroutine point(ix, iy)
subroutine linemd(str)
character str*(*)
subroutine space(ix0, iy0, ix1, iy1)
subroutine clospl()

```

DESCRIPTION

These are interface subroutines, in the library *-lf77plot*, allowing *f77* users to call the *plot*(3X) graphics routines which generate graphic output in a relatively device-independent manner. The *f77* subroutine names are the same as the *C* function names except that *linemod* and *closepl* have been shortened to *linemd* and *clospl*. See *plot*(5) and *plot*(3X) for a description of their effect.

Only the first 255 character in string arguments to *label* and *linemd* are used.

This library must be specified in the *f77*(1) command before the device specific graphics library; for example, to compile and load a FORTRAN program in *prog.f* to run on a Tektronix 4014 terminal:

```
f77 prog.f -lf77plot -l4014
```

See *plot*(3X) for a complete list of device specific plotting libraries.

SEE ALSO

plot(5), *plot*(1G), *plot*(3X), *graph*(1G)

NAME

putc, fputc – write a character to a fortran logical unit

SYNOPSIS

integer function putc (char)
character char

integer function fputc (lunit, char)
character char

DESCRIPTION

These functions write a character to the file associated with a fortran logical unit bypassing normal fortran I/O. *Putc* writes to logical unit 6, normally connected to the control terminal output.

The value of each function will be zero unless some error occurred; a system error code otherwise. See *perror(3F)*.

FILES

/usr/lib/libU77.a

SEE ALSO

putc(3S), intro(2), perror(3F)

P
R
M
3F

NAME

qsort – quick sort

SYNOPSIS

subroutine qsort (array, len, isize, compar)
external compar
integer*2 compar

DESCRIPTION

One dimensional *array* contains the elements to be sorted. *len* is the number of elements in the array. *isize* is the size of an element, typically -

4 for integer and real
8 for double precision or complex
16 for double complex
(length of character object) for character arrays

Compar is the name of a user supplied integer*2 function that will determine the sorting order. This function will be called with 2 arguments that will be elements of *array*. The function must return -

negative if arg 1 is considered to precede arg 2
zero if arg 1 is equivalent to arg 2
positive if arg 1 is considered to follow arg 2

On return, the elements of *array* will be sorted.

FILES

/usr/lib/libU77.a

SEE ALSO

qsort(3)

P
R
M 3F

NAME

rand, *drand*, *irand* – return random values

SYNOPSIS

function *irand* (*iflag*)

function *rand* (*iflag*)

double precision function *drand* (*iflag*)

DESCRIPTION

The newer *random(3f)* should be used in new applications; *rand* remains for compatibility.

These functions use *rand(3C)* to generate sequences of random numbers. If *iflag* is '1', the generator is restarted and the first random value is returned. If *iflag* is otherwise non-zero, it is used as a new seed for the random number generator, and the first new random value is returned.

Irand returns positive integers in the range 0 through 2147483647. *Rand* and *drand* return values in the range 0. through 1.0 .

FILES

/usr/lib/libF77.a

SEE ALSO

random(3F), *rand(3C)*

BUGS

The algorithm returns a 15 bit quantity on the PDP11; a 31 bit quantity on the VAX. *Irand* on the PDP11 calls *rand(3C)* twice to form a 31 bit quantity, but bit 15 will always be 0.

P
R
M
3F

NAME

random, drandm, irandm – better random number generator

SYNOPSIS

function irandm (iflag)

function random (iflag)

double precision function drandm (iflag)

DESCRIPTION

These functions use *random(3)* to generate sequences of random numbers, and should be used rather than the older functions described in *man 3f rand*. If *iflag* is non-zero, it is used as a new seed for the random number generator, and the first new random value is returned.

Irandm returns positive integers in the range 0 through 2147483647 ($2^{31}-1$). *Random* and *drandm* return values in the range 0. through 1.0 by dividing the integer random number from *random(3)* by 2147483647.

FILES

/usr/lib/libF77.a

SEE ALSO

random(3)

P
R
M
3F

NAME

rename – rename a file

SYNOPSIS

integer function **rename** (*from*, *to*)
character*(*) *from*, *to*

DESCRIPTION

From must be the pathname of an existing file. *To* will become the new pathname for the file. If *to* exists, then both *from* and *to* must be the same type of file, and must reside on the same filesystem. If *to* exists, it will be removed first.

The returned value will be 0 if successful; a system error code otherwise.

FILES

/usr/lib/libU77.a

SEE ALSO

rename(2), perror(3F)

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in <sys/param.h>.

P
R
M
3F

NAME

signal – change the action for a signal

SYNOPSIS

integer function **signal**(*signum*, *proc*, *flag*)
integer *signum*, *flag*
external *proc*

DESCRIPTION

When a process incurs a signal (see *signal*(3C)) the default action is usually to clean up and abort. The user may choose to write an alternative signal handling routine. A call to *signal* is the way this alternate action is specified to the system.

Signum is the signal number (see *signal*(3C)). If *flag* is negative, then *proc* must be the name of the user signal handling routine. If *flag* is zero or positive, then *proc* is ignored and the value of *flag* is passed to the system as the signal action definition. In particular, this is how previously saved signal actions can be restored. Two possible values for *flag* have specific meanings: 0 means "use the default action" (See NOTES below), 1 means "ignore this signal".

A positive returned value is the previous action definition. A value greater than 1 is the address of a routine that was to have been called on occurrence of the given signal. The returned value can be used in subsequent calls to *signal* in order to restore a previous action definition. A negative returned value is the negation of a system error code. (See *perror*(3F))

FILES

/usr/lib/libU77.a

SEE ALSO

signal(3C), *kill*(3F), *kill*(1)

NOTES

f77 arranges to trap certain signals when a process is started. The only way to restore the default *f77* action is to save the returned value from the first call to *signal*.

If the user signal handler is called, it will be passed the signal number as an integer argument.

P
R
M
3F

NAME

sleep – suspend execution for an interval

SYNOPSIS

subroutine sleep (*itime*)

DESCRIPTION

Sleep causes the calling process to be suspended for *itime* seconds. The actual time can be up to 1 second less than *itime* due to granularity in system timekeeping.

FILES

/usr/lib/libU77.a

SEE ALSO

sleep(3)

P
R
M
3F

NAME

stat, lstat, fstat – get file status

SYNOPSIS

integer function stat (name, statb)

character*(*) name

integer statb(12)

integer function lstat (name, statb)

character*(*) name

integer statb(12)

integer function fstat (lunit, statb)

integer statb(12)

DESCRIPTION

These routines return detailed information about a file. *Stat* and *lstat* return information about file *name*; *fstat* returns information about the file associated with fortran logical unit *lunit*. The order and meaning of the information returned in array *statb* is as described for the structure *stat* under *stat(2)*. The "spare" values are not included.

The value of either function will be zero if successful; an error code otherwise.

P
R
M
3F

FILES

/usr/lib/libU77.a

SEE ALSO

stat(2), access(3F), perror(3F), time(3F)

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in *<sys/param.h>*.

NAME

system – execute a UNIX command

SYNOPSIS

integer function system (string)
character*(*) string

DESCRIPTION

System causes *string* to be given to your shell as input as if the string had been typed as a command. If environment variable **SHELL** is found, its value will be used as the command interpreter (shell); otherwise *sh*(1) is used.

The current process waits until the command terminates. The returned value will be the exit status of the shell. See *wait*(2) for an explanation of this value.

FILES

/usr/lib/libU77.a

SEE ALSO

exec(2), wait(2), system(3)

BUGS

String can not be longer than NCARGS–50 characters, as defined in *<sys/param.h>*.

P
R
M
3F

NAME

time, *ctime*, *ltime*, *gmtime* – return system time

SYNOPSIS

integer function *time*()

character*(*) function *ctime* (*stime*)

integer *stime*

subroutine *ltime* (*stime*, *tarray*)

integer *stime*, *tarray*(9)

subroutine *gmtime* (*stime*, *tarray*)

integer *stime*, *tarray*(9)

DESCRIPTION

Time returns the time since 00:00:00 GMT, Jan. 1, 1970, measured in seconds. This is the value of the UNIX system clock.

Ctime converts a system time to a 24 character ASCII string. The format is described under *ctime*(3). No 'newline' or NULL will be included.

Ltime and *gmtime* dissect a UNIX time into month, day, etc., either for the local time zone or as GMT. The order and meaning of each element returned in *tarray* is described under *ctime*(3).

FILES

/usr/lib/libU77.a

SEE ALSO

ctime(3), *itime*(3F), *idate*(3F), *fdate*(3F)

P
R
M
3F

NAME

topen, *tclose*, *tread*, *twrite*, *trewin*, *tskipf*, *tstate* – f77 tape I/O

SYNOPSIS

integer function *topen* (*tlu*, *devnam*, *label*)

integer *tlu*

character*(*) *devnam*

logical *label*

integer function *tclose* (*tlu*)

integer *tlu*

integer function *tread* (*tlu*, *buffer*)

integer *tlu*

character*(*) *buffer*

integer function *twrite* (*tlu*, *buffer*)

integer *tlu*

character*(*) *buffer*

integer function *trewin* (*tlu*)

integer *tlu*

integer function *tskipf* (*tlu*, *nfiles*, *nrecs*)

integer *tlu*, *nfiles*, *nrecs*

integer function *tstate* (*tlu*, *fileno*, *recno*, *errf*, *coff*, *eotf*, *tcsr*)

integer *tlu*, *fileno*, *recno*, *tcsr*

logical *errf*, *coff*, *eotf*

DESCRIPTION

These functions provide a simple interface between f77 and magnetic tape devices. A “tape logical unit”, *tlu*, is “*topen*”ed in much the same way as a normal f77 logical unit is “*open*”ed. All other operations are performed via the *tlu*. The *tlu* has no relationship at all to any normal f77 logical unit.

Topen associates a device name with a *tlu*. *Tlu* must be in the range 0 to 3. The logical argument *label* should indicate whether the tape includes a tape label. This is used by *trewin* below. *Topen* does not move the tape. The normal returned value is 0. If the value of the function is negative, an error has occurred. See *perror*(3F) for details.

Tclose closes the tape device channel and removes its association with *tlu*. The normal returned value is 0. A negative value indicates an error.

Tread reads the next physical record from tape to *buffer*. *Buffer* must be of type **character**. The size of *buffer* should be large enough to hold the largest physical record to be read. The actual number of bytes read will be returned as the value of the function. If the value is 0, the end-of-file has been detected. A negative value indicates an error.

Twrite writes a physical record to tape from *buffer*. The physical record length will be the size of *buffer*. *Buffer* must be of type **character**. The number of bytes written will be returned. A value of 0 or negative indicates an error.

Trewin rewinds the tape associated with *tlu* to the beginning of the first data file. If the tape is a labelled tape (see *topen* above) then the label is skipped over after rewinding. The normal returned value is 0. A negative value indicates an error.

Tskipf allows the user to skip over files and/or records. First, *nfiles* end-of-file marks are skipped. If the current file is at EOF, this counts as 1 file to skip. (Note: This is the way to reset the EOF status for a *thu*.) Next, *nrecs* physical records are skipped over. The normal returned value is 0. A negative value indicates an error.

Finally, *tstate* allows the user to determine the logical state of the tape I/O channel and to see the tape drive control status register. The values of *fileno* and *recno* will be returned and indicate the current file and record number. The logical values *errf*, *eof*, and *eotf* indicate an error has occurred, the current file is at EOF, or the tape has reached logical end-of-tape. End-of-tape (EOT) is indicated by an empty file, often referred to as a double EOF mark. It is not allowed to read past EOT although it is allowed to write. The value of *tsr* will reflect the tape drive control status register. See *ht(4)* for details.

FILES

/usr/lib/libU77.a

SEE ALSO

ht(4), *perorr(3F)*, *rewind(1)*

P
R
M
3F

NAME

traper – trap arithmetic errors

SYNOPSIS

integer function traper (mask)

DESCRIPTION**NOTE:** This routine applies only to the VAX. It is ignored on the PDP11.

Integer overflow and floating point underflow are not normally trapped during execution. This routine enables these traps by setting status bits in the process status word. These bits are reset on entry to a subprogram, and the previous state is restored on return. Therefore, this routine must be called *inside* each subprogram in which these conditions should be trapped. If the condition occurs and trapping is enabled, signal SIGFPE is sent to the process. (See *signal(3C)*)

The argument has the following meaning:

value	meaning
0	do not trap either condition
1	trap integer overflow only
2	trap floating underflow only
3	trap both the above

The previous value of these bits is returned.

FILES

/usr/lib/libF77.a

SEE ALSO

signal(3C), signal(3F)

P
R
M
3F

NAME

trapov - trap and repair floating point overflow

SYNOPSIS

subroutine trapov (numesg, rtnval)
double precision rtnval

DESCRIPTION

NOTE: This routine applies only to the older VAX 11/780's. VAX computers made or upgraded since spring 1983 handle errors differently. See *trpfpe*(3F) for the newer error handler. This routine has always been ineffective on the VAX 11/750. It is a null routine on the PDP11.

This call sets up signal handlers to trap arithmetic exceptions and the use of illegal operands. Trapping arithmetic exceptions allows the user's program to proceed from instances of floating point overflow or divide by zero. The result of such operations will be an illegal floating point value. The subsequent use of the illegal operand will be trapped and the operand replaced by the specified value.

The first *numesg* occurrences of a floating point arithmetic error will cause a message to be written to the standard error file. If the resulting value is used, the value given for *rtnval* will replace the illegal operand generated by the arithmetic error. *Rtnval* must be a double precision value. For example, "0d0" or "dflmax()".

FILES

/usr/lib/libF77.a

SEE ALSO

trpfpe(3F), signal(3F), range(3F)

BUGS

Other arithmetic exceptions can be trapped but not repaired.

There is no way to distinguish between an integer value of 32768 and the illegal floating point form. Therefore such an integer value may get replaced while repairing the use of an illegal operand.

P
R
M
3F

NAME

trpfpe, specnt – trap and repair floating point faults

SYNOPSIS

subroutine trpfpe (numesg, rtnval)
double precision rtnval

integer function specnt ()

common /speflt/ fperr
logical fperr

DESCRIPTION

NOTE: This routine applies only to Vax computers. It is a null routine on the PDP11.

Trpfpe sets up a signal handler to trap arithmetic exceptions. If the exception is due to a floating point arithmetic fault, the result of the operation is replaced with the *rtnval* specified. *Rtnval* must be a double precision value. For example, "0d0" or "dflmax()".

The first *numesg* occurrences of a floating point arithmetic error will cause a message to be written to the standard error file. Any exception that can't be repaired will result in the default action, typically an abort with core image.

Fpecnt returns the number of faults since the last call to *trpfpe*.

The logical value in the common block labelled *speflt* will be set to .true. each time a fault occurs.

FILES

/usr/lib/libF77.a

SEE ALSO

signal(3F), range(3F)

BUGS

This routine works only for *faults*, not *traps*. This is primarily due to the Vax architecture.

If the operation involves changing the stack pointer, it can't be repaired. This seldom should be a problem with the f77 compiler, but such an operation might be produced by the optimizer.

The POLY and EMOD opcodes are not dealt with.

P
R
M
3F

NAME

`ttynam`, `isatty` – find name of a terminal port

SYNOPSIS

character(*) function `ttynam (lunit)`

logical function `isatty (lunit)`

DESCRIPTION

Ttynam returns a blank padded path name of the terminal device associated with logical unit *lunit*.

Isatty returns *.true.* if *lunit* is associated with a terminal device, *.false.* otherwise.

FILES

`/dev/*`

`/usr/lib/libU77.a`

DIAGNOSTICS

Ttynam returns an empty string (all blanks) if *lunit* is not associated with a terminal device in directory `'/dev'`.

P
R
M
3F

NAME

unlink - remove a directory entry

SYNOPSIS

integer function unlink (name)
character*(*) name

DESCRIPTION

Unlink causes the directory entry specified by pathname *name* to be removed. If this was the last link to the file, the contents of the file are lost. The returned value will be zero if successful; a system error code otherwise.

FILES

/usr/lib/libU77.a

SEE ALSO

unlink(2), link(3F), fsys(5), perror(3F)

BUGS

Pathnames can be no longer than MAXPATHLEN as defined in *<sys/param.h>*.

P
R
M
3F

NAME

wait – wait for a process to terminate

SYNOPSIS

integer function wait (status)
integer status

DESCRIPTION

Wait causes its caller to be suspended until a signal is received or one of its child processes terminates. If any child has terminated since the last *wait*, return is immediate; if there are no children, return is immediate with an error code.

If the returned value is positive, it is the process ID of the child and *status* is its termination status (see *wait(2)*). If the returned value is negative, it is the negation of a system error code.

FILES

/usr/lib/libU77.a

SEE ALSO

wait(2), signal(3F), kill(3F), perror(3F)

P
R
M
3F

NAME

intro – introduction to special files and hardware support

DESCRIPTION

This section describes the special files, related driver functions, and networking support available in the system. In this part of the manual, the SYNOPSIS section of each configurable device gives a sample specification for use in constructing a system description for the *config(8)* program. The DIAGNOSTICS section lists messages which may appear on the console and/or in the system error log */usr/adm/messages* due to errors in device operation; see *syslogd(8)* for more information.

This section contains both devices which may be configured into the system, “4” entries, and network related information, “4N”, “4P”, and “4F” entries; The networking support is introduced in *intro(4N)*.

VAX DEVICE SUPPORT

This section describes the hardware supported on the DEC VAX-11. Software support for these devices comes in two forms. A hardware device may be supported with a character or block *device driver*, or it may be used within the networking subsystem and have a *network interface driver*. Block and character devices are accessed through files in the file system of a special type; c.f. *mknod(8)*. Network interfaces are indirectly accessed through the interprocess communication facilities provided by the system; see *socket(2)*.

A hardware device is identified to the system at configuration time and the appropriate device or network interface driver is then compiled into the system. When the resultant system is booted, the autoconfiguration facilities in the system probe for the device on either the UNIBUS (or Q-bus) or MASSBUS and, if found, enable the software support for it. If a UNIBUS device does not respond at autoconfiguration time it is not accessible at any time afterwards. To enable a UNIBUS device which did not autoconfigure, the system will have to be rebooted. If a MASSBUS device comes “on-line” after the autoconfiguration sequence it will be dynamically autoconfigured into the running system.

The autoconfiguration system is described in *autoconf(4)*. A list of the supported devices is given below.

SEE ALSO

intro(4), intro(4N), autoconf(4), config(8).

Building 4.3BSD UNIX Systems with *Config* (SMM:2)

LIST OF DEVICES

The devices listed below are supported in this incarnation of the system. Pseudo-devices are not listed. Devices are indicated by their functional interface. If second vendor products provide functionally identical interfaces they should be usable with the supplied software. (Beware, however, that we promise the software works **ONLY** with the hardware indicated on the appropriate manual page.) Occasionally, new devices of a similar type may be added simply by creating appropriate table entries in the driver.

acc	ACC LH/DH IMP communications interface
ad	Data translation A/D interface
css	DEC IMP-11A communications interface
crl	VAX 8600, 8650 console RL02 disk
ct	C/A/T or APS phototypesetter
ddn	ACC ACP625 DDN Standard Mode X.25 IMP interface
de	DEC DEUNA 10Mb/s Ethernet controller
dh	DH-11 emulators, terminal multiplexor
dhu	DHU-11 terminal multiplexor
dmc	DEC DMC-11/DMR-11 point-to-point communications device

dmf	DEC DMF-32 terminal multiplexor and parallel printer interface
dmz	DEC DMZ-32 terminal multiplexor
dn	DEC DN-11 autodialer interface
dz	DZ-11 terminal multiplexor
ec	3Com 10Mb/s Ethernet controller
en	Xerox 3Mb/s Ethernet controller (obsolete)
ex	Excelan 10Mb/s Ethernet controller
fl	VAX-11/780 console floppy interface
hdh	ACC IF-11/HDH IMP interface
hk	RK6-11/RK06 and RK07 moving head disk
hp	MASSBUS disk interface (with RP06, RM03, RM05, etc.)
ht	TM03 MASSBUS tape drive interface (with TE-16, TU-45, TU-77)
hy	DR-11B or GI-13 interface to an NSC Hyperchannel
ik	Ikonas frame buffer graphics device interface
il	Interlan 1010, 1010A 10Mb/s Ethernet controller
ix	Interlan NP-100 10Mb/s Ethernet controller
kg	KL-11/DL-11W line clock
lp	LP-11 parallel line printer interface
mt	TM78 MASSBUS tape drive interface
np	Interlan NP-100 10Mb/s Ethernet controller (intelligent mode)
pcl	DEC PCL-11 communications interface
ps	Evans and Sutherland Picture System 2 graphics interface
qe	DEC DEQNA Q-bus 10 Mb/s Ethernet interface
rx	DEC RX02 floppy interface
tm	TM-11/TE-10 tape drive interface
tmscp	TMSCP-compatible tape controllers (e.g., TU81, TK50)
ts	TS-11 tape drive interface
tu	VAX-11/730 TU58 console cassette interface
uda	DEC UDA-50 disk controller
un	DR-11W interface to Ungermann-Bass
up	Emulex SC-21V, SC-31 UNIBUS disk controller
ut	UNIBUS TU-45 tape drive interface
uu	TU58 dual cassette drive interface (DL11)
va	Benson-Varian printer/plotter interface
vp	Versatec printer/plotter interface
vv	Proteon proNET 10Mb/s and 80Mb/s ring network interface

NAME

networking – introduction to networking facilities

SYNOPSIS

```
#include <sys/socket.h>
#include <net/route.h>
#include <net/if.h>
```

DESCRIPTION

This section briefly describes the networking facilities available in the system. Documentation in this part of section 4 is broken up into three areas: *protocol families* (domains), *protocols*, and *network interfaces*. Entries describing a protocol family are marked “4F,” while entries describing protocol use are marked “4P.” Hardware support for network interfaces are found among the standard “4” entries.

All network protocols are associated with a specific *protocol family*. A protocol family provides basic services to the protocol implementation to allow it to function within a specific network environment. These services may include packet fragmentation and reassembly, routing, addressing, and basic transport. A protocol family may support multiple methods of addressing, though the current protocol implementations do not. A protocol family is normally comprised of a number of protocols, one per *socket(2)* type. It is not required that a protocol family support all socket types. A protocol family may contain multiple protocols supporting the same socket abstraction.

A protocol supports one of the socket abstractions detailed in *socket(2)*. A specific protocol may be accessed either by creating a socket of the appropriate type and protocol family, or by requesting the protocol explicitly when creating a socket. Protocols normally accept only one type of address format, usually determined by the addressing structure inherent in the design of the protocol family/network architecture. Certain semantics of the basic socket abstractions are protocol specific. All protocols are expected to support the basic model for their particular socket type, but may, in addition, provide non-standard facilities or extensions to a mechanism. For example, a protocol supporting the `SOCK_STREAM` abstraction may allow more than one byte of out-of-band data to be transmitted per out-of-band message.

A network interface is similar to a device interface. Network interfaces comprise the lowest layer of the networking subsystem, interacting with the actual transport hardware. An interface may support one or more protocol families and/or address formats. The SYNOPSIS section of each network interface entry gives a sample specification of the related drivers for use in providing a system description to the *config(8)* program. The DIAGNOSTICS section lists messages which may appear on the console and/or in the system error log, */usr/adm/messages* (see *syslogd(8)*), due to errors in device operation.

PROTOCOLS

The system currently supports the DARPA Internet protocols and the Xerox Network Systems(tm) protocols. Raw socket interfaces are provided to the IP protocol layer of the DARPA Internet, to the IMP link layer (1822), and to the IDP protocol of Xerox NS. Consult the appropriate manual pages in this section for more information regarding the support for each protocol family.

ADDRESSING

Associated with each protocol family is an address format. The following address formats are used by the system (and additional formats are defined for possible future implementation):

```
#define AF_UNIX      1      /* local to host (pipes, portals) */
#define AF_INET      2      /* internetwork: UDP, TCP, etc. */
#define AF_IMPLINK   3      /* arpanet imp addresses */
#define AF_PUP        4      /* pup protocols: e.g. BSP */
#define AF_NS         6      /* Xerox NS protocols */
```



```
#define AF_HYLINK      15      /* NSC Hyperchannel */
```

ROUTING

The network facilities provided limited packet routing. A simple set of data structures comprise a "routing table" used in selecting the appropriate network interface when transmitting packets. This table contains a single entry for each route to a specific network or host. A user process, the routing daemon, maintains this data base with the aid of two socket-specific *ioctl(2)* commands, *SIOCADDRT* and *SIOCDELRT*. The commands allow the addition and deletion of a single routing table entry, respectively. Routing table manipulations may only be carried out by super-user.

A routing table entry has the following form, as defined in *<net/route.h>*;

```
struct rtentry {
    u_long      rt_hash;
    struct      sockaddr rt_dst;
    struct      sockaddr rt_gateway;
    short       rt_flags;
    short       rt_refcnt;
    u_long      rt_use;
    struct      ifnet *rt_ifp;
};
```

with *rt_flags* defined from,

```
#define RTF_UP          0x1      /* route usable */
#define RTF_GATEWAY     0x2      /* destination is a gateway */
#define RTF_HOST        0x4      /* host entry (net otherwise) */
#define RTF_DYNAMIC     0x10     /* created dynamically (by redirect) */
```

Routing table entries come in three flavors: for a specific host, for all hosts on a specific network, for any destination not matched by entries of the first two types (a wildcard route). When the system is booted and addresses are assigned to the network interfaces, each protocol family installs a routing table entry for each interface when it is ready for traffic. Normally the protocol specifies the route through each interface as a "direct" connection to the destination host or network. If the route is direct, the transport layer of a protocol family usually requests the packet be sent to the same host specified in the packet. Otherwise, the interface is requested to address the packet to the gateway listed in the routing entry (i.e. the packet is forwarded).

Routing table entries installed by a user process may not specify the hash, reference count, use, or interface fields; these are filled in by the routing routines. If a route is in use when it is deleted (*rt_refcnt* is non-zero), the routing entry will be marked down and removed from the routing table, but the resources associated with it will not be reclaimed until all references to it are released. The routing code returns *EEXIST* if requested to duplicate an existing entry, *ESRCH* if requested to delete a non-existent entry, or *ENOBUFS* if insufficient resources were available to install a new route. User processes read the routing tables through the */dev/kmem* device. The *rt_use* field contains the number of packets sent along the route.

When routing a packet, the kernel will first attempt to find a route to the destination host. Failing that, a search is made for a route to the network of the destination. Finally, any route to a default ("wildcard") gateway is chosen. If multiple routes are present in the table, the first route found will be used. If no entry is found, the destination is declared to be unreachable.

A wildcard routing entry is specified with a zero destination address value. Wildcard routes are used only when the system fails to find a route to the destination host and network. The combination of wildcard routes and routing redirects can provide an economical mechanism for routing traffic.

INTERFACES

Each network interface in a system corresponds to a path through which messages may be sent and received. A network interface usually has a hardware device associated with it, though certain interfaces such as the loopback interface, *lo(4)*, do not.

The following *ioctl* calls may be used to manipulate network interfaces. The *ioctl* is made on a socket (typically of type *SOCK_DGRAM*) in the desired domain. Unless specified otherwise, the request takes an *ifrequest* structure as its parameter. This structure has the form

```
struct ifreq {
    char    ifr_name[16];        /* name of interface (e.g. "ec0") */
    union {
        struct    sockaddr ifru_addr;
        struct    sockaddr ifru_dstaddr;
        struct    sockaddr ifru_broadaddr;
        short     ifru_flags;
        int        ifru_metric;
    } ifr_ifru;
#define ifr_addr    ifr_ifru.ifru_addr    /* address */
#define ifr_dstaddr ifr_ifru.ifru_dstaddr /* other end of p-to-p link */
#define ifr_broadaddr ifr_ifru.ifru_broadaddr /* broadcast address */
#define ifr_flags    ifr_ifru.ifru_flags /* flags */
#define ifr_metric    ifr_ifru.ifru_metric /* routing metric */
};
```

SIOCSIFADDR

Set interface address for protocol family. Following the address assignment, the "initialization" routine for the interface is called.

SIOCGIFADDR

Get interface address for protocol family.

SIOCSIFDSTADDR

Set point to point address for protocol family and interface.

SIOCGIFDSTADDR

Get point to point address for protocol family and interface.

SIOCSIFBRDADDR

Set broadcast address for protocol family and interface.

SIOCGIFBRDADDR

Get broadcast address for protocol family and interface.

SIOCSIFFLAGS

Set interface flags field. If the interface is marked down, any processes currently routing packets through the interface are notified; some interfaces may be reset so that incoming packets are no longer received. When marked up again, the interface is reinitialized.

SIOCGIFFLAGS

Get interface flags.

SIOCSIFMETRIC

Set interface routing metric. The metric is used only by user-level routers.

SIOCGIFMETRIC

Get interface metric.

SIOCGIFCONF

Get interface configuration list. This request takes an *ifconf* structure (see below) as a value-result parameter. The *ifc_len* field should be initially set to the size of the buffer pointed to by *ifc_buf*. On return it will contain the length, in bytes, of the configuration list.

```
/*
 * Structure used in SIOCGIFCONF request.
 * Used to retrieve interface configuration
 * for machine (useful for programs which
 * must know all networks accessible).
 */
struct ifconf {
    int    ifc_len;          /* size of associated buffer */
    union {
        caddr_t ifcu_buf;
        struct ifreq *ifcu_req;
    } ifc_ifcu;
#define ifc_buf ifc_ifcu.ifcu_buf    /* buffer address */
#define ifc_req ifc_ifcu.ifcu_req    /* array of structures returned */
};
```

SEE ALSO

socket(2), ioctl(2), intro(4), config(8), routed(8C)

NAME

acc – ACC LH/DH IMP interface

SYNOPSIS

pseudo-device imp
device acc0 at uba0 csr 167600 vector accrint accxint

DESCRIPTION

The *acc* device provides a Local Host/Distant Host interface to an IMP. It is normally used when participating in the DARPA Internet. The controller itself is not accessible to users, but instead provides the hardware support to the IMP interface described in *imp*(4). When configuring, the *imp* pseudo-device must also be included.

DIAGNOSTICS

acc%d: not alive. The initialization routine was entered even though the device did not autoconfigure. This indicates a system problem.

acc%d: can't initialize. Insufficient UNIBUS resources existed to initialize the device. This is likely to occur when the device is run on a buffered data path on an 11/750 and other network interfaces are also configured to use buffered data paths, or when it is configured to use buffered data paths on an 11/730 (which has none).

acc%d: imp doesn't respond, icsr=%b. The driver attempted to initialize the device, but the IMP failed to respond after 500 tries. Check the cabling.

acc%d: stray xmit interrupt, csr=%b. An interrupt occurred when no output had previously been started.

acc%d: output error, ocsr=%b, icsr=%b. The device indicated a problem sending data on output.

acc%d: input error, csr=%b. The device indicated a problem receiving data on input.

acc%d: bad length=%d. An input operation resulted in a data transfer of less than 0 or more than 1008 bytes of data into memory (according to the word count register). This should never happen as the maximum size of a host-IMP message is 1008 bytes.

NAME

ad – Data Translation A/D converter

SYNOPSIS

device **ad0** at uba0 csr 0170400 vector **adintr**

DESCRIPTION

Ad provides the interface to the Data Translation A/D converter. This is not a real-time driver, but merely allows the user process to sample the board's channels one at a time. Each minor device selects a different A/D board.

The driver communicates to a user process by means of **ioctl**s. The **AD_CHAN** **ioctl** selects which channel of the board to read. For example,

```
chan = 5; ioctl(fd, AD_CHAN, &chan);
```

selects channel 5. The **AD_READ** **ioctl** actually reads the data and returns it to the user process. An example is

```
ioctl(fd, AD_READ, &data);
```

FILES

/dev/ad

DIAGNOSTICS

None.

NAME

arp – Address Resolution Protocol

SYNOPSIS

pseudo-device ether

DESCRIPTION

ARP is a protocol used to dynamically map between DARPA Internet and 10Mb/s Ethernet addresses. It is used by all the 10Mb/s Ethernet interface drivers. It is not specific to Internet protocols or to 10Mb/s Ethernet, but this implementation currently supports only that combination.

ARP caches Internet-Ethernet address mappings. When an interface requests a mapping for an address not in the cache, ARP queues the message which requires the mapping and broadcasts a message on the associated network requesting the address mapping. If a response is provided, the new mapping is cached and any pending message is transmitted. ARP will queue at most one packet while waiting for a mapping request to be responded to; only the most recently “transmitted” packet is kept.

To facilitate communications with systems which do not use ARP, *ioctl*s are provided to enter and delete entries in the Internet-to-Ethernet tables. Usage:

```
#include <sys/ioctl.h>
#include <sys/socket.h>
#include <net/if.h>
struct arpreq arpreq;
```

```
ioctl(s, SIOCSARP, (caddr_t)&arpreq);
ioctl(s, SIOCGARP, (caddr_t)&arpreq);
ioctl(s, SIOCDAARP, (caddr_t)&arpreq);
```

Each *ioctl* takes the same structure as an argument. SIOCSARP sets an ARP entry, SIOCGARP gets an ARP entry, and SIOCDAARP deletes an ARP entry. These *ioctl*s may be applied to any socket descriptor *s*, but only by the super-user. The *arpreq* structure contains:

```
/*
 * ARP ioctl request
 */
struct arpreq {
    struct sockaddr    arp_pa; /* protocol address */
    struct sockaddr    arp_ha; /* hardware address */
    int                arp_flags; /* flags */
};
/* arp_flags field values */
#define ATF_COM        0x02 /* completed entry (arp_ha valid) */
#define ATF_PERM       0x04 /* permanent entry */
#define ATF_PUBL       0x08 /* publish (respond for other host) */
#define ATF_USETRAILERS 0x10 /* send trailer packets to host */
```

The address family for the *arp_pa* *sockaddr* must be AF_INET; for the *arp_ha* *sockaddr* it must be AF_UNSPEC. The only flag bits which may be written are ATF_PERM, ATF_PUBL and ATF_USETRAILERS. ATF_PERM causes the entry to be permanent if the *ioctl* call succeeds. The peculiar nature of the ARP tables may cause the *ioctl* to fail if more than 8 (permanent) Internet host addresses hash to the same slot. ATF_PUBL specifies that the ARP code should respond to ARP requests for the indicated host coming from other machines. This allows a host to act as an “ARP server,” which may be useful in convincing an ARP-only machine to talk to a non-ARP machine.

ARP is also used to negotiate the use of trailer IP encapsulations; trailers are an alternate encapsulation used to allow efficient packet alignment for large packets despite variable-sized headers. Hosts which wish to receive trailer encapsulations so indicate by sending gratuitous ARP translation replies along with replies to IP requests; they are also sent in reply to IP translation replies. The negotiation is thus fully symmetrical, in that either or both hosts may request trailers. The ATF_USETAILERS flag is used to record the receipt of such a reply, and enables the transmission of trailer packets to that host.

ARP watches passively for hosts impersonating the local host (i.e. a host which responds to an ARP mapping request for the local host's address).

DIAGNOSTICS

duplicate IP address!! sent from ethernet address: %x:%x:%x:%x:%x:%x. ARP has discovered another host on the local network which responds to mapping requests for its own Internet address.

SEE ALSO

ec(4), de(4), il(4), inet(4F), arp(8C), ifconfig(8C)

"An Ethernet Address Resolution Protocol," RFC826, Dave Plummer, Network Information Center, SRI.

"Trailer Encapsulations," RFC893, S.J. Leffler and M.J. Karels, Network Information Center, SRI.

BUGS

ARP packets on the Ethernet use only 42 bytes of data; however, the smallest legal Ethernet packet is 60 bytes (not including CRC). Some systems may not enforce the minimum packet size, others will.

NAME

autoconf – diagnostics from the autoconfiguration code

DESCRIPTION

When UNIX bootstraps it probes the innards of the machine on which it is running and locates controllers, drives, and other devices, printing out what it finds on the console. This procedure is driven by a system configuration table which is processed by *config(8)* and compiled into each kernel.

On the VAX, devices in NEXUS slots are normally noted, thus memory controllers, UNIBUS and MASSBUS adaptors. Devices which are not supported which are found in NEXUS slots are noted also. The Q-bus on the MICROVAX is configured in the same way as the UNIBUS.

MASSBUS devices are located by a very deterministic procedure since MASSBUS space is completely probe-able. If devices exist which are not configured they will be silently ignored; if devices exist of unsupported type they will be noted.

UNIBUS devices are located by probing to see if their control-status registers respond. If not, they are silently ignored. If the control status register responds but the device cannot be made to interrupt, a diagnostic warning will be printed on the console and the device will not be available to the system.

Normally, the system uses the disk from which it was loaded as the root filesystem. If that is not possible, a generic system will pick its root device as the "best" available device (MASSBUS disks are better than SMD UNIBUS disks are better than RK07's; the device must be drive 0 to be considered). If such a system is booted with the RB_ASKNAME option (see *reboot(2)*), then the name of the root device is read from the console terminal at boot time, and any available device may be used.

SEE ALSO

intro(4), boot(8), config(8)

DIAGNOSTICS

cpu type %d not configured. You tried to boot UNIX on a cpu type which it doesn't (or at least this compiled version of UNIX doesn't) understand.

mba%d at tr%d. A MASSBUS adapter was found in tr%d (the NEXUS slot number). UNIX will call it mba%d.

%d mba's not configured. More MASSBUS adapters were found on the machine than were declared in the machine configuration; the excess MASSBUS adapters will not be accessible.

uba%d at tr%d. A UNIBUS adapter was found in tr%d (the NEXUS slot number). UNIX will call it uba%d.

dr32 unsupported (at tr %d). A DR32 interface was found in a NEXUS, for which UNIX does not have a driver.

ci unsupported (at tr %d). A CI interface was found in a NEXUS, for which UNIX does not have a driver.

mcr%d at tr%d. A memory controller was found in tr%d (the NEXUS slot number). UNIX will call it mcr%d.

5 mcr's unsupported. UNIX supports only 4 memory controllers per cpu.

mpm unsupported (at tr%d). Multi-port memory is unsupported in the sense that UNIX does not know how to poll it for ECC errors.

%s%d at mba%d drive %d. A tape formatter or a disk was found on the MASSBUS; for disks %s%d will look like "hp0", for tape formatters like "ht1". The drive number comes from the unit plug on the drive or in the TM formatter (not on the tape drive; see below).

%s%d at %s%d slave %d. (For MASSBUS devices). Which would look like "tu0 at ht0 slave 0", where tu0 is the name for the tape device and ht0 is the name for the formatter. A tape slave was found on the tape formatter at the indicated drive number (on the front of the tape drive). UNIX will call the device, e.g., tu0.

%s%d at uba%d csr %o vec %o ipl %x. The device %s%d, e.g. dz0 was found on uba%d at control-status register address %o and with device vector %o. The device interrupted at priority level %x.

%s%d at uba%d csr %o zero vector. The device did not present a valid interrupt vector, rather presented 0 (a passive release condition) to the adapter.

%s%d at uba%d csr %o didn't interrupt. The device did not interrupt, likely because it is broken, hung, or not the kind of device it is advertised to be.

%s%d at %s%d slave %d. (For UNIBUS devices). Which would look like "up0 at sc0 slave 0", where up0 is the name of a disk drive and sc0 is the name of the controller. Analogous to MASSBUS case.

NAME

bk – line discipline for machine-machine communication (obsolete)

SYNOPSIS

pseudo-device bk

DESCRIPTION

This line discipline provides a replacement for the old and new tty drivers described in *tty(4)* when high speed output to and especially input from another machine is to be transmitted over an asynchronous communications line. The discipline was designed for use by the Berkeley network. It may be suitable for uploading of data from microprocessors into the system. If you are going to send data over asynchronous communications lines at high speed into the system, you must use this discipline, as the system otherwise may detect high input data rates on terminal lines and disable the lines; in any case the processing of such data when normal terminal mechanisms are involved saturates the system.

The line discipline is enabled by a sequence:

```
#include <sgtty.h>
int ldisc = NETLDDISC, fildes; ...
ioctl(fildes, TIOCSETD, &ldisc);
```

A typical application program then reads a sequence of lines from the terminal port, checking header and sequencing information on each line and acknowledging receipt of each line to the sender, who then transmits another line of data. Typically several hundred bytes of data and a smaller amount of control information will be received on each handshake.

The old standard teletype discipline can be restored by doing:

```
ldisc = OTTYDISC;
ioctl(fildes, TIOCSETD, &ldisc);
```

While in networked mode, normal teletype output functions take place. Thus, if an 8 bit output data path is desired, it is necessary to prepare the output line by putting it into RAW mode using *ioctl(2)*. This must be done **before** changing the discipline with *TIOCSETD*, as most *ioctl(2)* calls are disabled while in network line-discipline mode.

When in network mode, input processing is very limited to reduce overhead. Currently the input path is only 7 bits wide, with newline the only recognized character, terminating an input record. Each input record must be read and acknowledged before the next input is read as the system refuses to accept any new data when there is a record in the buffer. The buffer is limited in length, but the system guarantees to always be willing to accept input resulting in 512 data characters and then the terminating newline.

User level programs should provide sequencing and checksums on the information to guarantee accurate data transfer.

SEE ALSO

tty(4)

DIAGNOSTICS

None.

BUGS

The Purdue uploading line discipline, which provides 8 bits and uses timeout's to terminate uploading should be incorporated into the standard system, as it is much more suitable for microprocessor connections.

NAME

cons - VAX-11 console interface

DESCRIPTION

The console is available to the processor through the console registers. It acts like a normal terminal, except that when the local functions are not disabled, control-P puts the console in local console mode (where the prompt is ">>>"). The operation of the console in this mode varies slightly per-processor.

On an 11/780 or 785 the processor is not stopped by entering local console mode. The CPU may be halted with the "halt" command, which may be abbreviated to "h." Conversational mode is re-entered by using the command "set t p" (set terminal program) if the processor is still running, or "continue" if it is halted. The latter command may be abbreviated "c". If you hit the break key on the console, then the console LSI-11 will go into ODT (console debugger mode). Hit a "P" (upper-case letter p; "proceed") to get out of this mode.

On an 11/750 or an 11/730 the processor is halted whenever the console is not in conversational mode, and typing "C" returns to conversational mode. When in console mode on an 11/750 which has a remote diagnosis module, a ^D will put you in remote diagnosis mode, where the prompt will be "RDM>". The command "ret" will return from remote diagnosis mode to local console mode.

The VAX 8600 (8650) console normally works in the same way as the 11/750, except that there are many additional modes and commands. In the normal mode control-P halts the processor, and "c" or "continue" returns to conversational mode. If HEX debug is enabled, control-P does not halt the CPU; the "halt" command stops the CPU as on the 11/780.

With the above proviso's the console works like any other UNIX terminal.

FILES

/dev/console

SEE ALSO

tty(4), reboot(8)
VAX Hardware Handbook

P
R
M
4

NAME

crl - VAX 8600 console RL02 interface

DESCRIPTION

This is a simple interface to the DEC RL02 disk unit which is part of the console subsystem on the VAX 8600 and 8650. Access is given to the entire RL02 disk; the pack format is the same as that of RL02 disks on other controllers. As on other VAX console media, transfers are done a word at a time using privileged registers (i.e., slowly).

All I/O is raw; the seek addresses in raw transfers should be a multiple of 512 bytes and a multiple of 512 bytes should be transferred, as in other "raw" disk interfaces. (Although the sector size is actually 256 bytes, the driver allows operations only on 512-byte boundaries.)

FILES

/dev/crl

SEE ALSO

arff(8V)

NAME

css - DEC IMP-11A LH/DH IMP interface

SYNOPSIS

pseudo-device imp
device css0 at uba0 csr 167600 flags 10 vector cssrint cssxint

DESCRIPTION

The *css* device provides a Local Host/Distant Host interface to an IMP. It is normally used when participating in the DARPA Internet. The controller itself is not accessible to users, but instead provides the hardware support to the IMP interface described in *imp(4)*. When configuring, the *imp* pseudo-device is also included.

DIAGNOSTICS

css%d: not alive. The initialization routine was entered even though the device did not autoconfigure. This indicates a system problem.

css%d: can't initialize. Insufficient UNIBUS resources existed to initialize the device. This is likely to occur when the device is run on a buffered data path on an 11/750 and other network interfaces are also configured to use buffered data paths, or when it is configured to use buffered data paths on an 11/730 (which has none).

css%d: imp doesn't respond, icsr=%b. The driver attempted to initialize the device, but the IMP failed to respond after 500 tries. Check the cabling.

css%d: stray output interrupt csr=%b. An interrupt occurred when no output had previously been started.

css%d: output error, ocsr=%b icsr=%b. The device indicated a problem sending data on output.

css%d: recv error, csr=%b. The device indicated a problem receiving data on input.

css%d: bad length=%d. An input operation resulted in a data transfer of less than 0 or more than 1008 bytes of data into memory (according to the word count register). This should never happen as the maximum size of a host-IMP message is 1008 bytes.

NAME

ct – phototypesetter interface

SYNOPSIS

device ct0 at uba0 csr 0167760 vector ctintr

DESCRIPTION

This provides an interface to a Graphic Systems C/A/T phototypesetter or an Autologic APS-Micro5 using a DR11C interface. Bytes written on the file specify font, size, and other control information as well as the characters to be flashed. The coding is not described here.

Only one process may have this file open at a time. It is write-only.

FILES

/dev/cat

SEE ALSO

troff(1)

Phototypesetter interface specification

DIAGNOSTICS

None.

NAME

ddn – DDN Standard Mode X.25 IMP interface

SYNOPSIS

device ddn0 at uba0 csr 166740 vector ddnintr

DESCRIPTION

The *ddn* device provides a DDN Standard Mode X.25 interface to an IMP using the ACC ACP625 X.25 board. It is normally used for connecting to the Defense Data Network (DDN). The controller itself is not accessible to users, but instead provides a network interface for the Internet Protocol described in *ip*(4P).

SEE ALSO

intro(4N), *ip*(4P)

DIAGNOSTICS

ddn%d: not alive. The initialization routine was entered even though the device did not autoconfigure. This indicates a system problem.

ddn%d: failed getting UBA resources for lcn %d. Insufficient UNIBUS resources existed to initialize the device. This is likely to be a shortage of UNIBUS mapping registers.

ddn%d: couldn't get X25 init buffer. This indicates that an *mbuf* could not be allocated for sending the initialization message to the ACP625.

DDN: illegal X25 address length!

DDN: illegal X25 address format!

These errors indicate a problem with the called X.25 address received from the IMP on an incoming call.

X25 RESET on lcn = %d. This indicates that an unexpected X.25 RESET was received on the indicated LCN.

X25 INTERRUPT on lcn = %d, code = %d. This indicates that an unexpected X.25 INTERRUPT Packet was received on the indicated LCN.

ddn%d: failed to get supr msg bfr!. This indicates that an *mbuf* could not be allocated for sending a supervisor message to the ACP625.

Any other error message from *ddn%d*: indicates a serious error detected by either the driver or the ACP625 firmware.

NAME

de – DEC DEUNA 10 Mb/s Ethernet interface

SYNOPSIS

device de0 at uba0 csr 174510 vector deintr

DESCRIPTION

The *de* interface provides access to a 10 Mb/s Ethernet network through a Digital Equipment UNIBUS Network Adapter (DEUNA).

Each of the host's network addresses is specified at boot time with an SIOCSIFADDR ioctl. The *de* interface employs the address resolution protocol described in *arp*(4P) to dynamically map between Internet and Ethernet addresses on the local network.

The interface normally tries to use a "trailer" encapsulation to minimize copying data on input and output. The use of trailers is negotiated with ARP. This negotiation may be disabled, on a per-interface basis, by setting the IFF_NOTRAILERS flag with an SIOCSIF-FLAGS ioctl.

DIAGNOSTICS

de%d: hardware address %s. This is a normal autoconfiguration message noting the 6 byte physical ethernet address of the adapter.

de%d: oerror, flags=%b tdrerr=%b (len=%d). The hardware indicated an error in transmitting a packet to the cable. The status and error flags are reported.

de%d: ierror, flags=%b lenerr=%b (len=%d). The hardware indicated an error in reading a packet from the cable. The status and error flags are reported.

de%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

de%d: buffer unavailable. The interface received more packets than it had buffers allocated to receive them.

de%d: address change failed, csr0=%b csr1=%b. The interface was unable to reprogram its physical ethernet address. This may happen with very early models of the interface. This facility is used only when the controller is not the first network interface configured for XNS.

The following messages indicate a probable hardware error performing the indicated operation during autoconfiguration or initialization. The two control and status registers should indicate the nature of the failure. See the hardware manual for details.

de%d: reset failed, csr0=%b csr1=%b.

de%d: ppcb failed, csr0=%b csr1=%b.

de%d: read addr failed, csr0=%b csr1=%b.

de%d: wtring failed, csr0=%b csr1=%b.

de%d: wtmode failed, csr0=%b csr1=%b.

SEE ALSO

intro(4N), inet(4F), arp(4P)

NAME

dh - DH-11/DM-11 communications multiplexer

SYNOPSIS

device dh0 at uba0 csr 0160020 vector dhrint dhxint

device dm0 at uba0 csr 0170500 vector dmintr

DESCRIPTION

A dh-11 provides 16 communication lines; dm-11's may be optionally paired with dh-11's to provide modem control for the lines.

Each line attached to the DH-11 communications multiplexer behaves as described in *tty(4)*. Input and output for each line may independently be set to run at any of 16 speeds; see *tty(4)* for the encoding.

Bit *i* of flags may be specified for a dh to say that a line is not properly connected, and that the line should be treated as hard-wired with carrier always present. Thus specifying "flags 0x0004" in the specification of dh0 would cause line ttyh2 to be treated in this way.

The *dh* driver monitors the rate of input on each board, and switches between the use of character-at-a-time interrupts and input silos. While the silo is enabled during periods of high-speed input, the driver polls for input 30 times per second.

FILES

/dev/tty[h-o][0-9a-f]

/dev/ttyd[0-9a-f]

SEE ALSO

tty(4)

DIAGNOSTICS

dh%d: NXM. No response from UNIBUS on a dma transfer within a timeout period. This is often followed by a UNIBUS adapter error. This occurs most frequently when the UNIBUS is heavily loaded and when devices which hog the bus (such as rk07's) are present. It is not serious.

dh%d: silo overflow. The character input silo overflowed before it could be serviced. This can happen if a hard error occurs when the CPU is running with elevated priority, as the system will then print a message on the console with interrupts disabled. It is not serious.

NAME

dhc - DHU-11 communications multiplexer

SYNOPSIS

device dhu0 at uba0 csr 0160440 vector dhurint dhuxint

DESCRIPTION

A DHU-11 provides 16 communication lines.

Each line attached to the DHU-11 communications multiplexer behaves as described in *tty(4)*. Input and output for each line may independently be set to run at any of 13 speeds (50, 200 and 38400 baud are not available); see *tty(4)* for the encoding.

Bit *i* of flags may be specified for a DHU-11 to say that a line is not properly connected, and that the line should be treated as hard-wired with carrier always present. Thus specifying "flags 0x0004" in the specification of dhu0 would cause line ttyS2 to be treated in this way.

The DHU-11 driver normally uses input silos and delays receiver interrupts by 20 milliseconds rather than taking an interrupt on each input character.

FILES

/dev/tty[S-Z][0-9a-f]

SEE ALSO

tty(4)

DIAGNOSTICS

dhu(%d,%d): NXM fault. No response from UNIBUS on a DMA transfer within a timeout period. This is often followed by a UNIBUS adapter error. This occurs most frequently when the UNIBUS is heavily loaded and when devices which hog the bus (such as RK07s) are present. It is not serious.

dhu%d: silo overflow. The character input silo overflowed before it could be serviced. This can happen if a hard error occurs when the CPU is running with elevated priority, as the system may then print a message on the console with interrupts disabled.

NOTES

The driver currently does not make full use of the hardware capabilities of the DHU-11, for dealing with XON/XOFF flow-control or hard-wired lines for example.

Although the devices are not the same, a DHU-11 can convince the DH-11 autoconfiguration code that it is a DH-11.

The 4 40-way cables are a pain.

NAME

dmc – DEC DMC-11/DMR-11 point-to-point communications device

SYNOPSIS

device **dmc0** at **uba0** csr **167600** vector **dmcrint dmcxint**

DESCRIPTION

The *dmc* interface provides access to a point-to-point communications device which runs at either 1 Mb/s or 56 Kb/s. DMC-11's communicate using the DEC DDCMP link layer protocol.

The *dmc* interface driver also supports a DEC DMR-11 providing point-to-point communication running at data rates from 2.4 Kb/s to 1 Mb/s. DMR-11's are a more recent design and thus are preferred over DMC-11's. The *NXMT* and *NRCV* constants in the driver should be increased in this case, as the DMR can accept up to 64 transmit and receive buffers, as opposed to 7 for the DMC.

The configuration flags specify how to set up the device,

- 0 -- full duplex DDCMP (normal mode)
- 1 -- DDCMP Maintenance mode (generally useless)
- 2 -- DDCMP Half Duplex, primary station
- 3 -- DDCMP Half Duplex, secondary station

Several device error counters are available via "adb", for more information see the adb script /usr/lib/adb/dmcstats, or the DMC11 technical manual.

The host's address must be specified with an *SIOCSIFADDR* ioctl, and the destination address specified with a *SIOCSIFDSTADDR* ioctl, before the interface will transmit or receive any packets.

ROUTING

The driver places a *HOST* entry in the kernel routing tables for the address given in the *SIOCSIFDSTADDR* ioctl. To use the DMC as a link between local nets, the route to the remote net must be added manually with the *route(8)* command, or by the use of the routing process *routed(8)* on each end of the link.

DIAGNOSTICS

dmc%d: bad control %o. A bad parameter was passed to the *dmcload* routine.

dmc%d: unknown address type %d. An input packet was received which contained a type of address unknown to the driver.

DMC fatal error 0%o. A fatal error in DDMCP occurred, causing the device to be restarted.

DMC soft error 0%o. A non-fatal error in DDMCP has occurred.

dmc%d: af%d not supported. The interface was handed a message which has addresses formatted in an unsuitable address family.

SEE ALSO

intro(4N), *inet(4F)*

BUGS

The current version of the driver uses a link-level encapsulation so that multiple protocol types may be used. It is thus incompatible with earlier drivers, including the 4.2BSD version.

NAME

dmf - DMF-32, terminal multiplexor

SYNOPSIS

device *dmf0* at uba? csr 0160340

vector *dmfsrint dmfsxint dmfdaint dmfdaint dmfrint dmfxint dmflint*

DESCRIPTION

The *dmf* device provides 8 lines of asynchronous serial line support. The first two of these have full modem control. The device also provides a line printer port similar to the LP-11. Other features of the DMF-32 are not supported. During autoconfiguration, the driver examines the configuration of each DMF-32 and adjusts the interrupt vectors so that fewer vector locations are used if possible.

Each line attached to a DMF-32 serial line port behaves as described in *tty(4)*. Input and output for each line may independently be set to run at any of 16 speeds; see *tty(4)* for the encoding.

Bit *i* of flags may be specified for a *dmf* to say that a line is not properly connected, and that the line should be treated as hard-wired with carrier always present. Thus specifying "flags 0x04" in the specification of *dmf0* would cause line *ttyA2* to be treated in this way. Flags should be set for all lines without hardware support for modem control.

The serial line part of the *dmf* driver normally enables the input silos with a short timeout (30 milliseconds); this allows multiple characters to be received per interrupt during periods of high-speed input.

A line printer port on *dmfn* is designated by a minor device number of the form 128+n. Columns and lines per page may be changed from the default 132 columns and 66 lines by encoding the number of columns in bits 8-15 of flags and the number of lines in bits 16-23. This device does not provide the fancy output canonicalization features of the *lp(4)* driver.

FILES

/dev/tty[A-CE-I][0-7]
/dev/ttyd[0-7]
/dev/lp

SEE ALSO

tty(4)

DIAGNOSTICS

dmf%d: NXM line %d. No response from UNIBUS on a DMA transfer within a timeout period. This is often followed by a UNIBUS adapter error. This occurs most frequently when the UNIBUS is heavily loaded and when devices which hog the bus (such as RK07s) are present. It is not serious.

dmf%d: silo overflow. The character input silo overflowed before it could be serviced. This can happen if a hard error occurs when the CPU is running with elevated priority, as the system will then print a message on the console with interrupts disabled. It is not serious.

dmfsrint, dmfsxint, dmfdaint, dmfdaint. One of the unsupported parts of the *dmf* interrupted; something is amiss, check your interrupt vectors for a conflict with another device.

BUGS

It should be possible to set the silo timeout with a configuration file option, as the value is a trade-off between efficiency and response time for flow control and character echo.

NAME

dmz – DMZ-32 terminal multiplexor

SYNOPSIS

device dmz0 at uba? csr 0160540

vector dmzrinta dmzxinta dmzrintb dmzxintb dmzrintc dmzxintc

DESCRIPTION

The *dmz* device provides 24 lines of asynchronous serial line support. Modem control on all ports is available as an option for the H3014 distribution panel.

Each line attached to a DMZ-32 serial line port behaves as described in *tty(4)*. Input and output for each line may independently be set to run at any of 16 speeds; see *tty(4)* for the encoding.

Bit *i* of flags may be specified for a *dmz* to say that a line is not properly connected, and that the line should be treated as hard-wired with carrier always present. Thus specifying "flags 0x000004" in the specification of *dmz0* would cause line *ttya2* to be treated in this way.

The *dmz* driver normally enables the input silos with a short timeout (30 milliseconds); this allows multiple characters to be received per interrupt during periods of high-speed input.

FILES

/dev/tty[abcefg][0-9a-n]

SEE ALSO

tty(4)

DIAGNOSTICS

dmz%d: NXM line %d. No response from the UNIBUS on a DMA transfer within a timeout period. This is often followed by a UNIBUS adapter error. This occurs most frequently when the UNIBUS is heavily loaded and when devices which hog the bus (such as RK07s) are present. It is not serious.

dmz%d: silo overflow. The character input silo overflowed before it could be serviced. This can happen if a hard error occurs when the CPU is running with elevated priority, as the system will then print a message on the console with interrupts disabled. It is not serious.

BUGS

It should be possible to set the silo timeout with a configuration file option, as the value is a trade-off between efficiency and response time for flow control and character echo.

NAME

dn - DN-11 autocal unit interface

SYNOPSIS

device dn0 at uba? csr 0160020 vector dnintr

DESCRIPTION

The *dn* device provides an interface through a DEC DN-11 (or equivalent such as the Able Quadracall) to an auto-call unit (ACU). To place an outgoing call one forks a sub-process which opens the appropriate call unit file, */dev/cua?* and writes the phone number on it. The parent process then opens the corresponding modem line */dev/cul?*. When the connection has been established, the open on the modem line, */dev/cul?* will return and the process will be connected. A timer is normally used to timeout the opening of the modem line.

The codes for the phone numbers are:

0-9 dial 0-9
* dial * (': ' is a synonym)
dial # (': ' is a synonym)
- delay 20 milliseconds
< end-of-number ('e' is a synonym)
= delay for a second dial tone ('w' is a synonym)
f force a hangup of any existing connection

The entire telephone number must be presented in a single *write* system call.

By convention, even numbered call units are for 300 baud modem lines, while odd numbered units are for 1200 baud lines. For example, */dev/cua0* is associated with a 300 baud modem line, */dev/cul0*, while */dev/cua1* is associated with a 1200 baud modem line, */dev/cul1*. For devices such as the Quadracall which simulate multiple DN-11 units, the minor device indicates which outgoing modem to use.

FILES

/dev/cua? call units
/dev/cul? associated modem lines

SEE ALSO

tip(1C)

DIAGNOSTICS

Two error numbers are of interest at open time.

[EBUSY] The dialer is in use.

[ENXIO] The device doesn't exist, or there's no power to it.

NAME

drum – paging device

DESCRIPTION

This file refers to the paging device in use by the system. This may actually be a subdevice of one of the disk drivers, but in a system with paging interleaved across multiple disk drives it provides an indirect driver for the multiple drives.

FILES

/dev/drum

BUGS

Reads from the drum are not allowed across the interleaving boundaries. Since these only occur every .5Mbytes or so, and since the system never allocates blocks across the boundary, this is usually not a problem.

NAME

dz - DZ11 communications multiplexer

SYNOPSIS

device **dz0** at uba0 csr 0160100 vector **dzrint dzxint**

DESCRIPTION

A DZ11 provides 8 communication lines with partial modem control, adequate for UNIX dialup use. Each line attached to the DZ11 communications multiplexer behaves as described in *tty(4)* and may be set to run at any of 16 speeds; see *tty(4)* for the encoding.

Bit *i* of flags may be specified for a **dz** to say that a line is not properly connected, and that the line should be treated as hard-wired with carrier always present. Thus specifying "flags 0x04" in the specification of **dz0** would cause line **tty02** to be treated in this way.

The **dz** driver monitors the rate of input on each board, and switches between the use of character-at-a-time interrupts and input silos. While the silo is enabled during periods of high-speed input, the driver polls for input 30 times per second.

FILES

/dev/tty[0-9][0-9]

/dev/ttyd[0-9a-f]

dialups

SEE ALSO

tty(4)

DIAGNOSTICS

dz%d: silo overflow. The 64 character input silo overflowed before it could be serviced. This can happen if a hard error occurs when the CPU is running with elevated priority, as the system will then print a message on the console with interrupts disabled. It is not serious.

NAME

ec – 3Com 10 Mb/s Ethernet interface

SYNOPSIS

device ec0 at uba0 csr 161000 vector ecrint eccollide ecxint flags 0

DESCRIPTION

The *ec* interface provides access to a 10 Mb/s Ethernet network through a 3com controller.

The hardware has 32 kilobytes of dual-ported memory on the UNIBUS. This memory is used for internal buffering by the board, and the interface code reads the buffer contents directly through the UNIBUS. The address of this memory is given in the *flags* field in the configuration file. The first interface normally has its memory at Unibus address 0.

Each of the host's network addresses is specified at boot time with an SIOCSIFADDR ioctl. The *ec* interface employs the address resolution protocol described in *arp*(4P) to dynamically map between Internet and Ethernet addresses on the local network.

The interface normally tries to use a "trailer" encapsulation to minimize copying data on input and output. The use of trailers is negotiated with ARP. This negotiation may be disabled, on a per-interface basis, by setting the IFF_NOTRAILERS flag with an SIOCSIF_FLAGS ioctl.

The interface software implements an exponential backoff algorithm when notified of a collision on the cable. This algorithm utilizes a 16-bit mask and the VAX-11's interval timer in calculating a series of random backoff values. The algorithm is as follows:

1. Initialize the mask to be all 1's.
2. If the mask is zero, 16 retries have been made and we give up.
3. Shift the mask left one bit and formulate a backoff by masking the interval timer with the smaller of the complement of this mask and a 5-bit mask, resulting in a pseudo-random number between 0 and 31. This produces the number of slot times to delay, where a slot is 51 microseconds.
4. Use the value calculated in step 3 to delay before retransmitting the packet. The delay is done in a software busy loop.

DIAGNOSTICS

ec%d: send error. After 16 retransmissions using the exponential backoff algorithm described above, the packet was dropped.

ec%d: input error (offset=%d). The hardware indicated an error in reading a packet off the cable or an illegally sized packet. The buffer offset value is printed for debugging purposes.

ec%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

SEE ALSO

intro(4N), *inet*(4F), *arp*(4P)

BUGS

The hardware is not capable of talking to itself. The software implements local sending and broadcast by sending such packets to the loop interface. This is a kludge.

Backoff delays are done in a software busy loop. This can degrade the system if the network experiences frequent collisions.

NAME

en – Xerox 3 Mb/s Ethernet interface

SYNOPSIS

device **en0** at uba0 csr 161000 vector **enrint** **enxint** **encollide**

DESCRIPTION

The **en** interface provides access to a 3 Mb/s Ethernet network. Due to limitations in the hardware, DMA transfers to and from the network must take place in the lower 64K bytes of the UNIBUS address space, and thus this must be among the first UNIBUS devices enabled after boot.

Each of the host's network addresses is specified at boot time with an **SIOCSIFADDR** ioctl. The station address is discovered by probing the on-board Ethernet address register, and is used to verify the protocol addresses. No packets will be sent or accepted until a network address is supplied.

The interface software implements an exponential backoff algorithm when notified of a collision on the cable. This algorithm utilizes a 16-bit mask and the VAX-11's interval timer in calculating a series of random backoff values. The algorithm is as follows:

1. Initialize the mask to be all 1's.
2. If the mask is zero, 16 retries have been made and we give up.
3. Shift the mask left one bit and formulate a backoff by masking the interval timer with the mask (this is actually the two's complement of the value).
4. Use the value calculated in step 3 to delay before retransmitting the packet.

The interface handles both Internet and NS protocol families. It normally tries to use a "trailer" encapsulation to minimize copying data on input and output. The use of trailers is negotiated with ARP. This negotiation may be disabled, on a per-interface basis, by setting the **IFF_NOTRAILERS** flag with an **SIOCSIFFLAGS** ioctl.

DIAGNOSTICS

en%d: output error. The hardware indicated an error on the previous transmission.

en%d: send error. After 16 retransmissions using the exponential backoff algorithm described above, the packet was dropped.

en%d: input error. The hardware indicated an error in reading a packet off the cable.

en%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

SEE ALSO

intro(4N), **inet(4F)**

BUGS

The device has insufficient buffering to handle back to back packets. This makes use in a production environment painful.

The hardware does word at a time DMA without byte swapping. To compensate, byte swapping of user data must either be done by the user or by the system. A kludge to byte swap only IP packets is provided if the **ENF_SWABIPS** flag is defined in the driver and set at boot time with an **SIOCSIFFLAGS** ioctl.

NAME

ex – Excelan 10 Mb/s Ethernet interface

SYNOPSIS

device ex0 at uba0 csr 164000 vector excdint

DESCRIPTION

The *ex* interface provides access to a 10 Mb/s Ethernet network through an Excelan controller used as a link-layer interface.

Each of the host's network addresses is specified at boot time with an **SIOCSIFADDR** ioctl. The *ex* interface employs the address resolution protocol described in *arp*(4P) to dynamically map between Internet and Ethernet addresses on the local network.

The interface normally tries to use a "trailer" encapsulation to minimize copying data on input and output. The use of trailers is negotiated with ARP. This negotiation may be disabled, on a per-interface basis, by setting the **IFF_NOTRAILERS** flag with an **SIOCSIF_FLAGS** ioctl.

DIAGNOSTICS

ex%d: HW %c.%c, NX %c.%c, hardware address %s. This provides firmware revisions levels, and is expected during autoconfiguration.

ex%d: can't initialize. There was a failure in allocating unibus resources for the device.

ex%d: configuration failed; cc = %x. The hardware indicated an error when trying to initialize itself. The error code returned is described at length in the device Reference Manual.

ex%d: receive error %b. The hardware indicated an error in reading a packet from the cable. Specific Error bits are provided

ex%d: transmit error %b. The hardware indicated an error in transmitting a packet to the cable or an illegally sized packet. Specific Error bits are provided

ex%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

SEE ALSO

intro(4N), inet(4F), arp(4P)

NAME

fl – console floppy interface

DESCRIPTION

This is a simple interface to the DEC RX01 floppy disk unit, which is part of the console LSI-11 subsystem for VAX-11/780's. Access is given to the entire floppy consisting of 77 tracks of 26 sectors of 128 bytes.

All i/o is raw; the seek addresses in raw transfers should be a multiple of 128 bytes and a multiple of 128 bytes should be transferred, as in other "raw" disk interfaces.

FILES

/dev/floppy

SEE ALSO

arff(8V)

DIAGNOSTICS

None.

BUGS

Multiple console floppies are not supported.

If a write is given with a count not a multiple of 128 bytes then the trailing portion of the last sector will be zeroed.

NAME

hdh - ACC IF-11/HDH IMP interface

SYNOPSIS

pseudo-device imp
device hdh0 at uba0 csr 166740 vector hdhintr

DESCRIPTION

The *hdh* device provides an HDLC Host (HDH) interface to an IMP. It is normally used when participating in the DARPA Internet. The controller itself is not accessible to users, but instead provides the hardware support to the IMP interface described in *imp(4)*. When configuring, the *imp* pseudo-device must also be included.

DIAGNOSTICS

hdh%d: not alive. The initialization routine was entered even though the device did not autoconfigure. This indicates a system problem.

hdh%d: cannot get chan %d uba resources. Insufficient UNIBUS resources existed to initialize the device. This is likely to be a shortage of UNIBUS mapping registers.

hdh%d: LINE UP. This indicates that both the HDLC and HDH protocols have declared the link to the IMP alive.

hdh%d: LINE DOWN. This indicates that the link to the IMP has died.

hdh%d: HOST SEQUENCE ERROR

hdh%d: IMP SEQUENCE ERROR

hdh%d: HOST DATA ERROR

hdh%d: TIMEOUT

These errors indicate that an HDH protocol error has been detected.

hdh%d: cannot get supervisor cmd buffer. This error indicates that an *mbuf* could not be allocated to send a command to the IF-11/HDH.

Any other error message from hdh%d: indicates a serious error detected by either the driver or the IF-11/HDH firmware.

P
R
M
4

NAME

hk - RK6-11/RK06 and RK07 moving head disk

SYNOPSIS

controller hk0 at uba? csr 0177440 vector rkintr
disk rk0 at hk0 drive 0

DESCRIPTION

Files with minor device numbers 0 through 7 refer to various portions of drive 0; minor devices 8 through 15 refer to drive 1, etc. The standard device names begin with "hk" followed by the drive number and then a letter a-h for partitions 0-7 respectively. The character ? stands here for a drive number in the range 0-7.

The block files access the disk via the system's normal buffering mechanism and may be read and written without regard to physical disk records. There is also a 'raw' interface which provides for direct transmission between the disk and the user's read or write buffer. A single read or write call results in exactly one I/O operation and therefore raw I/O is considerably more efficient when many words are transmitted. The names of the raw files conventionally begin with an extra 'r.'

In raw I/O counts should be a multiple of 512 bytes (a disk sector). Likewise *seek* calls should specify a multiple of 512 bytes.

DISK SUPPORT

The origin and size (in sectors) of the pseudo-disks on each drive are as follows:

RK07 partitions:

disk	start	length	cyl
hk?a	0	15884	0-240
hk?b	15906	10032	241-392
hk?c	0	53790	0-814
hk?d	25938	15884	393-633
hk?f	41844	11792	634-814
hk?g	25938	27786	393-813

RK06 partitions

disk	start	length	cyl
hk?a	0	15884	0-240
hk?b	15906	11154	241-409
hk?c	0	27126	0-410

On a dual RK-07 system partition hk?a is used for the root for one drive and partition hk?g for the /usr file system. If large jobs are to be run using hk?b on both drives as swap area provides a 10Mbyte paging area. Otherwise partition hk?c on the other drive is used as a single large file system.

FILES

/dev/hk[0-7][a-h] block files
/dev/rhk[0-7][a-h] raw files

SEE ALSO

hp(4), uda(4), up(4), syslogd(8)

DIAGNOSTICS

rk%d%c: hard error sn%d cs2=%b ds=%b er=%b. An unrecoverable error occurred during transfer of the specified sector of the specified disk partition. The contents of the cs2, ds and er registers are printed in octal and symbolically with bits decoded. The error was either unrecoverable, or a large number of retry attempts (including offset positioning and drive recalibration) could not recover the error.

rk%d: write locked. The write protect switch was set on the drive when a write was attempted. The write operation is not recoverable.

rk%d: not ready. The drive was spun down or off line when it was accessed. The i/o operation is not recoverable.

rk%d: not ready (came back!). The drive was not ready, but after printing the message about being not ready (which takes a fraction of a second) was ready. The operation is recovered if no further errors occur.

rk%d%c: soft ecc sn%d. A recoverable ECC error occurred on the specified sector in the specified disk partition. This happens normally a few times a week. If it happens more frequently than this the sectors where the errors are occurring should be checked to see if certain cylinders on the pack, spots on the carriage of the drive or heads are indicated.

hk%d: lost interrupt. A timer watching the controller detected no interrupt for an extended period while an operation was outstanding. This indicates a hardware or software failure. There is currently a hardware/software problem with spinning down drives while they are being accessed which causes this error to occur. The error causes a UNIBUS reset, and retry of the pending operations. If the controller continues to lose interrupts, this error will recur a few seconds later.

BUGS

In raw I/O *read* and *write(2)* truncate file offsets to 512-byte block boundaries, and *write* scribbles on the tail of incomplete blocks. Thus, in programs that are likely to access raw devices, *read*, *write* and *lseek(2)* should always deal in 512-byte multiples.

DEC-standard error logging should be supported.

A program to analyze the logged error information (even in its present reduced form) is needed.

The partition tables for the file systems should be read off of each pack, as they are never quite what any single installation would prefer, and this would make packs more portable.

The rk07 g partition size in rk.c disagrees with that in /etc/disktab.

NAME

hp - MASSBUS disk interface

SYNOPSIS

disk hp0 at mba0 drive 0

DESCRIPTION

Files with minor device numbers 0 through 7 refer to various portions of drive 0; minor devices 8 through 15 refer to drive 1, etc. The standard device names begin with "hp" followed by the drive number and then a letter a-h for partitions 0-7 respectively. The character ? stands here for a drive number in the range 0-7.

The block file's access the disk via the system's normal buffering mechanism and may be read and written without regard to physical disk records. There is also a 'raw' interface which provides for direct transmission between the disk and the user's read or write buffer. A single read or write call results in exactly one I/O operation and therefore raw I/O is considerably more efficient when many words are transmitted. The names of the raw files conventionally begin with an extra 'r.'

In raw I/O counts should be a multiple of 512 bytes (a disk sector). Likewise *seek* calls should specify a multiple of 512 bytes.

DISK SUPPORT

This driver handles both standard DEC controllers and Emulex SC750 and SC780 controllers. Standard DEC drive types are recognized according to the MASSBUS drive type register. For the Emulex controller the drive type register should be configured to indicate the drive is an RM02. When this is encountered, the driver checks the holding register to find out the disk geometry and, based on this information, decides what the drive type is. The following disks are supported: RM03, RM05, RP06, RM80, RP05, RP07, ML11A, ML11B, CDC 9775, CDC 9730, AMPEX Capricorn (32 sectors/track), FUJITSU Eagle (48 sectors/track), Fujitsu 2361, and AMPEX 9300. The origin and size (in sectors) of the pseudo-disks on each drive are as follows:

RM03 partitions

disk	start	length	cyls
hp?a	0	15884	0-99
hp?b	16000	33440	100-309
hp?c	0	131680	0-822
hp?d	49600	15884	309-408
hp?e	65440	55936	409-758
hp?f	121440	10080	759-822
hp?g	49600	82080	309-822

RM05 partitions

disk	start	length	cyls
hp?a	0	15884	0-26
hp?b	16416	33440	27-81
hp?c	0	500384	0-822
hp?d	341696	15884	562-588
hp?e	358112	55936	589-680
hp?f	414048	86176	681-822
hp?g	341696	158528	562-822
hp?h	49856	291346	82-561

RP06 partitions

disk	start	length	cyls
hp?a	0	15884	0-37
hp?b	15884	33440	38-117

hp?c	0	340670	0-814
hp?d	49324	15884	118-155
hp?e	65208	55936	156-289
hp?f	121220	219296	290-814
hp?g	49324	291192	118-814

RM80 partitions

disk	start	length	cyls
hp?a	0	15884	0-36
hp?b	16058	33440	37-114
hp?c	0	242606	0-558
hp?d	49910	15884	115-151
hp?e	68096	55936	152-280
hp?f	125888	120466	281-558
hp?g	49910	192510	115-558

RP05 partitions

disk	start	length	cyls
hp?a	0	15884	0-37
hp?b	15884	33440	38-117
hp?c	0	171798	0-410
hp?d	2242	15884	118-155
hp?e	65208	55936	156-289
hp?f	121220	50424	290-410
hp?g	2242	122320	118-410

RP07 partitions

disk	start	length	cyls
hp?a	0	15884	0-9
hp?b	16000	66880	10-51
hp?c	0	1008000	0-629
hp?d	376000	15884	235-244
hp?e	392000	307200	245-436
hp?f	699200	308600	437-629
hp?g	376000	631800	235-629
hp?h	83200	291346	52-234

CDC 9775 partitions

disk	start	length	cyls
hp?a	0	15884	0-12
hp?b	16640	66880	13-65
hp?c	0	1077760	0-841
hp?d	376320	15884	294-306
hp?e	392960	307200	307-546
hp?f	700160	377440	547-841
hp?g	376320	701280	294-841
hp?h	84480	291346	66-293

CDC 9730 partitions

disk	start	length	cyls
hp?a	0	15884	0-49
hp?b	16000	33440	50-154
hp?c	0	263360	0-822
hp?d	49600	15884	155-204
hp?e	65600	55936	205-379
hp?f	121600	141600	380-822

hp?g	49600	213600	155-822
AMPEX Capricorn partitions			
disk	start	length	cyls
hp?a	0	15884	0-31
hp?b	16384	33440	32-97
hp?c	0	524288	0-1023
hp?d	342016	15884	668-699
hp?e	358400	55936	700-809
hp?f	414720	109408	810-1023
hp?g	342016	182112	668-1023
hp?h	50176	291346	98-667

FUJITSU Eagle partitions			
disk	start	length	cyls
hp?a	0	15884	0-16
hp?b	16320	66880	17-86
hp?c	0	808320	0-841
hp?d	375360	15884	391-407
hp?e	391680	55936	408-727
hp?f	698880	109248	728-841
hp?g	375360	432768	391-841
hp?h	83520	291346	87-390

FUJITSU 2361 partitions			
disk	start	length	cyls
hp?a	0	15884	0-12
hp?b	16640	66880	13-65
hp?c	0	1077760	0-841
hp?d	376320	15884	294-306
hp?e	392960	307200	307-546
hp?f	700160	377408	547-841
hp?g	363520	701248	294-841
hp?h	84480	291346	66-293

AMPEX 9300 partitions			
disk	start	length	cyl
hp?a	0	15884	0-26
hp?b	16416	33440	27-81
hp?c	0	495520	0-814
hp?d	341696	15884	562-588
hp?e	358112	55936	589-680
hp?f	414048	81312	681-814
hp?g	341696	153664	562-814
hp?h	49856	291346	82-561

It is unwise for all of these files to be present in one installation, since there is overlap in addresses and protection becomes a sticky matter. The hp?a partition is normally used for the root file system, the hp?b partition as a paging area, and the hp?c partition for pack-pack copying (it maps the entire disk). On disks larger than about 205 Megabytes, the hp?h partition is inserted prior to the hp?d or hp?g partition; the hp?g partition then maps the remainder of the pack. All disk partition tables are calculated using the *diskpart(8)* program.

FILES

/dev/hp[0-7][a-h]	block files
/dev/rhp[0-7][a-h]	raw files

SEE ALSO

hk(4), uda(4), up(4)

DIAGNOSTICS

hp%d%c: hard error sn%d mbsr=%b er1=%b er2=%b. An unrecoverable error occurred during transfer of the specified sector of the specified disk partition. The MASSBUS status register is printed in hexadecimal and with the error bits decoded if any error bits other than MBEXC and DTABT are set. In any case the contents of the two error registers are also printed in octal and symbolically with bits decoded. (Note that er2 is what old rp06 manuals would call er3; the terminology is that of the rm disks). The error was either unrecoverable, or a large number of retry attempts (including offset positioning and drive recalibration) could not recover the error.

hp%d: write locked. The write protect switch was set on the drive when a write was attempted. The write operation is not recoverable.

hp%d: not ready. The drive was spun down or off line when it was accessed. The I/O operation is not recoverable.

hp%d%c: soft ecc sn%d. A recoverable ECC error occurred on the specified sector of the specified disk partition. This happens normally a few times a week. If it happens more frequently than this the sectors where the errors are occurring should be checked to see if certain cylinders on the pack, spots on the carriage of the drive or heads are indicated.

During autoconfiguration one of the following messages may appear on the console indicating the appropriate drive type was recognized. The last message indicates the drive is of a unknown type.

hp%d: 9775 (direct).

hp%d: 9730 (direct).

hp%d: 9300.

hp%d: 9762.

hp%d: capricorn.

hp%d: eagle.

hp%d: 2361.

hp%d: ntracks %d, nsectors %d: unknown device.

BUGS

In raw I/O *read* and *write(2)* truncate file offsets to 512-byte block boundaries, and *write* scribbles on the tail of incomplete blocks. Thus, in programs that are likely to access raw devices, *read*, *write* and *lseek(2)* should always deal in 512-byte multiples.

DEC-standard error logging should be supported.

A program to analyze the logged error information (even in its present reduced form) is needed.

The partition tables for the file systems should be read off of each pack, as they are never quite what any single installation would prefer, and this would make packs more portable.

NAME

ht - TM-03/TE-16,TU-45,TU-77 MASSBUS magtape interface

SYNOPSIS

master ht0 at mba? drive ?
tape tu0 at ht0 slave 0

DESCRIPTION

The tm-03/transport combination provides a standard tape drive interface as described in *mtio(4)*. All drives provide both 800 and 1600 bpi; the TE-16 runs at 45 ips, the TU-45 at 75 ips, while the TU-77 runs at 125 ips and autoloads tapes.

SEE ALSO

mt(1), tar(1), tp(1), mtio(4), tm(4), ts(4), mnt(4), ut(4)

DIAGNOSTICS

tu%d: no write ring. An attempt was made to write on the tape drive when no write ring was present; this message is written on the terminal of the user who tried to access the tape.

tu%d: not online. An attempt was made to access the tape while it was offline; this message is written on the terminal of the user who tried to access the tape.

tu%d: can't change density in mid-tape. An attempt was made to write on a tape at a different density than is already recorded on the tape. This message is written on the terminal of the user who tried to switch the density.

tu%d: hard error bn%d mbsr=%b er=%b ds=%b. A tape error occurred at block *bn*; the ht error register and drive status register are printed in octal with the bits symbolically decoded. Any error is fatal on non-raw tape; when possible the driver will have retried the operation which failed several times before reporting the error.

BUGS

If any non-data error is encountered on non-raw tape, it refuses to do anything more until closed.

NAME

hy – Network Systems Hyperchannel interface

SYNOPSIS

device hy0 at uba0 csr 0172410 vector hyint

DESCRIPTION

The *hy* interface provides access to a Network Systems Corporation Hyperchannel Adapter.

The network to which the interface is attached is specified at boot time with an SIOCSI-FADDR ioctl. The host's address is discovered by reading the adapter status register. The interface will not transmit or receive packets until the network number is known.

DIAGNOSTICS

hy%d: unit number 0x%x port %d type %x microcode level 0x%x. Identifies the device during autoconfiguration.

hy%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

hy%d: can't initialize. The interface was unable to allocate UNIBUS resources. This is usually due to having too many network devices on an 11/750 where there are only 3 buffered data paths.

hy%d: NEX - Non Existent Memory. Non existent memory error returned from hardware.

hy%d: BAR overflow. Bus address register overflow error returned from hardware.

hy%d: Power Off bit set, trying to reset. Adapter has lost power, driver will reset the bit and see if power is still out in the adapter.

hy%d: Power Off Error, network shutdown. Power was really off in the adapter, network connections are dropped. Software does not shut down the network unless power has been off for a while.

hy%d: RECVD MP > MPSIZE (%d). A message proper was received that is too big. Probable a driver bug. Shouldn't happen.

hy%d: xmit error - len > hy_olen [%d > %d]. Probable driver error. Shouldn't happen.

hy%d: DRIVER BUG - INVALID STATE %d. The driver state machine reached a non-existent state. Definite driver bug.

hy%d: watchdog timer expired. A command in the adapter has taken too long to complete. Driver will abort and retry the command.

hy%d: adapter power restored. Software was able to reset the power off bit, indicating that the power has been restored.

SEE ALSO

intro(4N), inet(4F)

BUGS

If the adapter does not respond to the status command issued during autoconfigure, the adapter is assumed down. A reboot is required to recognize it.

The adapter power fail interrupt seems to occur sporadically when power has, in fact, not failed. The driver will believe that power has failed only if it can not reset the power fail latch after a "reasonable" time interval. These seem to appear about 2-4 times a day on some machines. There seems to be no correlation with adapter rev level, number of ports used etc. and whether a machine will get these "bogus powerfails". They don't seem to cause any real problems so they have been ignored.

NAME

icmp – Internet Control Message Protocol

SYNOPSIS

```
#include <sys/socket.h>
```

```
#include <netinet/in.h>
```

```
s = socket(AF_INET, SOCK_RAW, proto);
```

DESCRIPTION

ICMP is the error and control message protocol used by IP and the Internet protocol family. It may be accessed through a “raw socket” for network monitoring and diagnostic functions. The *proto* parameter to the socket call to create an ICMP socket is obtained from *getprotobyname*(3N). ICMP sockets are connectionless, and are normally used with the *sendto* and *recvfrom* calls, though the *connect*(2) call may also be used to fix the destination for future packets (in which case the *read*(2) or *recv*(2) and *write*(2) or *send*(2) system calls may be used).

Outgoing packets automatically have an IP header prepended to them (based on the destination address). Incoming packets are received with the IP header and options intact.

DIAGNOSTICS

A socket operation may fail with one of the following errors returned:

- [EISCONN] when trying to establish a connection on a socket which already has one, or when trying to send a datagram with the destination address specified and the socket is already connected;
- [ENOTCONN] when trying to send a datagram, but no destination address is specified, and the socket hasn't been connected;
- [ENOBUFS] when the system runs out of memory for an internal data structure;
- [EADDRNOTAVAIL] when an attempt is made to create a socket with a network address for which no network interface exists.

SEE ALSO

send(2), *recv*(2), *intro*(4N), *inet*(4F), *ip*(4P)

NAME

idp - Xerox Internet Datagram Protocol

SYNOPSIS

```
#include <sys/socket.h>
#include <netns/ns.h>
#include <netns/idp.h>

s = socket(AF_NS, SOCK_DGRAM, 0);
```

DESCRIPTION

IDP is a simple, unreliable datagram protocol which is used to support the SOCK_DGRAM abstraction for the Internet protocol family. IDP sockets are connectionless, and are normally used with the *sendto* and *recvfrom* calls, though the *connect(2)* call may also be used to fix the destination for future packets (in which case the *recv(2)* or *read(2)* and *send(2)* or *write(2)* system calls may be used).

Xerox protocols are built vertically on top of IDP. Thus, IDP address formats are identical to those used by SPP. Note that the IDP port space is the same as the SPP port space (i.e. a IDP port may be "connected" to a SPP port, with certain options enabled below). In addition broadcast packets may be sent (assuming the underlying network supports this) by using a reserved "broadcast address"; this address is network interface dependent.

DIAGNOSTICS

A socket operation may fail with one of the following errors returned:

- [EISCONN] when trying to establish a connection on a socket which already has one, or when trying to send a datagram with the destination address specified and the socket is already connected;
- [ENOTCONN] when trying to send a datagram, but no destination address is specified, and the socket hasn't been connected;
- [ENOBUFS] when the system runs out of memory for an internal data structure;
- [EADDRINUSE] when an attempt is made to create a socket with a port which has already been allocated;
- [EADDRNOTAVAIL] when an attempt is made to create a socket with a network address for which no network interface exists.

SOCKET OPTIONS

[SO_HEADERS_ON_INPUT]

When set, the first 30 bytes of any data returned from a read or *recv* from will be the initial 30 bytes of the IDP packet, as described by

```
struct idp {
    u_short    idp_sum;
    u_short    idp_len;
    u_char     idp_tc;
    u_char     idp_pt;
    struct ns_addr idp_dna;
    struct ns_addr idp_sna;
};
```

This allows the user to determine the packet type, and whether the packet was a multi-cast packet or directed specifically at the local host. When requested, gives the current state of the option, (NSP_RAWIN or 0).

[SO_HEADERS_ON_OUTPUT]

When set, the first 30 bytes of any data sent will be the initial 30 bytes of the

IDP packet. This allows the user to determine the packet type, and whether the packet should be multi-cast packet or directed specifically at the local host. You can also misrepresent the sender of the packet. When requested, gives the current state of the option. (NSP_RAWOUT or 0).

[SO_DEFAULT_HEADERS]

The user provides the kernel an IDP header, from which it gleans the Packet Type. When requested, the kernel will provide an IDP header, showing the default packet type, and local and foreign addresses, if connected.

[SO_ALL_PACKETS]

When set, this option defeats automatic processing of Error packets, and Sequence Protocol packets.

[SO_SEQNO]

When requested, this returns a sequence number which is not likely to be repeated until the machine crashes or a very long time has passed. It is useful in constructing Packet Exchange Protocol packets.

SEE ALSO

send(2), recv(2), intro(4N), ns(4F)

NAME

ik – Ikonas frame buffer, graphics device interface

SYNOPSIS

device ik0 at uba? csr 0172460 vector ikintr

DESCRIPTION

Ik provides an interface to an Ikonas frame buffer graphics device. Each minor device is a different frame buffer interface board. When the device is opened, its interface registers are mapped, via virtual memory, into the user processes address space. This allows the user process very high bandwidth to the frame buffer with no system call overhead.

Bytes written or read from the device are DMA'ed from or to the interface. The frame buffer XY address, its addressing mode, etc. must be set up by the user process before calling write or read.

Other communication with the driver is via ioctls. The IK_GETADDR ioctl returns the virtual address where the user process can find the interface registers. The IK_WAITINT ioctl suspends the user process until the ikonas device has interrupted (for whatever reason — the user process has to set the interrupt enables).

FILES

/dev/ik

DIAGNOSTICS

None.

BUGS

An invalid access (e.g., longword) to a mapped interface register can cause the system to crash with a machine check. A user process could possibly cause infinite interrupts hence bringing things to a crawl.

NAME

il – Interlan NI1010 10 Mb/s Ethernet interface

SYNOPSIS

device il0 at uba0 csr 164000 vector ilrint ilcint

DESCRIPTION

The *il* interface provides access to a 10 Mb/s Ethernet network through an Interlan 1010 or 1010A controller.

Each of the host's network addresses is specified at boot time with an **SIOCSIFADDR** ioctl. The *il* interface employs the address resolution protocol described in *arp*(4P) to dynamically map between Internet and Ethernet addresses on the local network.

The interface normally tries to use a “trailer” encapsulation to minimize copying data on input and output. The use of trailers is negotiated with ARP. This negotiation may be disabled, on a per-interface basis, by setting the **IFF_NOTRAILERS** flag with an **SIOCSIF_FLAGS** ioctl.

DIAGNOSTICS

il%d: input error. The hardware indicated an error in reading a packet off the cable or an illegally sized packet.

il%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

il%d: setaddr didn't work. The interface was unable to reprogram its physical ethernet address. This may happen with very early models of the interface. This facility is used only when the controller is not the first network interface configured for XNS. The oldest interface tested (2.7.1.0.1.45) has never failed in this way.

The following messages indicate a probable hardware error performing the indicated operation during autoconfiguration or initialization. The status field in the control and status register (the low-order four bits) should indicate the nature of the failure. See the hardware manual for details.

il%d: reset failed, csr=%b.

il%d: status failed, csr=%b.

il%d: hardware diag failed, csr=%b.

il%d: verifying setaddr, csr=%b.

il%d: stray xmit interrupt, csr=%b.

il%d: can't initialize.

SEE ALSO

intro(4N), inet(4F), arp(4P)

NAME

imp - 1822 network interface

SYNOPSIS

pseudo-device imp [count]

DESCRIPTION

The *imp* interface, as described in BBN Report 1822, provides access to an intelligent message processor normally used when participating in the Department of Defense ARPA network. The network interface communicates through a device controller, usually an ACC LH/DH or HDH or a DEC IMP-11A, with the IMP. The interface is "reliable" and "flow-controlled" by the host-IMP protocol.

To configure IMP support, at least one of *acc(4)*, *css(4)* or *hdh(4)* must be included. The optional *count* specifies the total number of IMP connections. The network number on which the interface resides is specified at boot time using the SIOCSIFADDR ioctl. The host number is discovered through receipt of NOOP messages from the IMP.

The network interface is always in one of four states: up, down, initializing, or going down. When the system is booted, the interface is marked down. If the hardware controller is successfully probed, the interface enters the initializing state and transmits three NOOP messages to the IMP. It then waits for the IMP to respond with two or more NOOP messages in reply. When it receives these messages it enters the up state. The "going down" state is entered only when notified by the IMP of an impending shutdown. Packets may be sent through the interface only while it is in the up state. Outgoing packets are dropped with the error ENET-DOWN returned to the caller if the interface is in any other state.

DIAGNOSTICS

imp%d: not configured. A hardware interface could not be attached during autoconfiguration because too few IMP pseudo-devices were configured.

imp%d: leader error. The IMP reported an error in a leader (1822 message header). This causes the interface to be reset and any packets queued up for transmission to be purged.

imp%d: going down in 30 seconds.

imp%d: going down for hardware PM.

imp%d: going down for reload software.

imp%d: going down for emergency reset. The Network Control Center (NCC) is manipulating the IMP. By convention these messages are reported to all hosts on an IMP.

imp?: host %x, lost %d rfnms. The IMP had messages outstanding to the host listed, but no RFNM (Request for Next Message) messages were received from the IMP in 127 seconds. The software state for that host is reinitialized.

imp%d: interface reset. The host has received an interface reset message from the IMP.

imp%d: address reset to x%x (%d/%d). The host has received a NOOP message which caused it to reset its notion of its current address. The Internet address is printed in hexadecimal, with the host and IMP numbers following. This indicates that the address originally set by *ifconfig(8)* was incorrect, that the IMP has undergone an identity crisis, or that communication between the IMP and the host is being garbled.

imp%d: data error. The IMP noted an error in data transmitted. The host-IMP interface is reset and the host enters the init state (awaiting NOOP messages).

imp%d: interface reset. The reset process has been completed.

imp%d: marked down. After receiving a "going down in 30 seconds" message, and waiting 30 seconds, the host has marked the IMP unavailable. Before packets may be sent to the IMP again, the IMP must notify the host, through a series of NOOP messages, that it is back up.

imp%d: can't handle af%d. The interface was handed a message with addresses formatting in an unsuitable address family; the packet was dropped.

SEE ALSO

intro(4N), inet(4F), acc(4), css(4), hdh(4), implog(8), implogd(8)

NAME

imp – IMP raw socket interface

SYNOPSIS

```
#include <sys/socket.h>
#include <netinet/in.h>
#include <netimp/if_imp.h>

s = socket(AF_IMPLINK, SOCK_RAW, proto);
```

DESCRIPTION

The raw imp socket provides direct access to the *imp*(4) network interface. Users send packets through the interface using the *send*(2) calls, and receive packets with the *recv*(2), calls. All outgoing packets must have an 1822 96-bit leader on the front. Likewise, packets received by the user will have this leader on the front. The 1822 leader and the legal values for the various fields are defined in the include file *<netimp/if_imp.h>*. The raw imp interface automatically installs the length and destination address in the 1822 leader of all outgoing packets; these need not be filled in by the user.

If the protocol selected, *proto*, is zero, the socket will receive all IMP messages except RFNM and incompletes which are not input data for a kernel protocol. If *proto* is non-zero, only messages for the specified link type will be received.

DIAGNOSTICS

An operation on a socket may fail with one of the following errors:

- [EISCONN] when trying to establish a connection on a socket which already has one, or when trying to send a datagram with the destination address specified and the socket is already connected;
- [ENOTCONN] when trying to send a datagram, but no destination address is specified, and the socket hasn't been connected;
- [ENOBUFS] when the system runs out of memory for an internal data structure;
- [ENOBUFS] eight messages to the destination host are outstanding, and another eight are already queued for output;
- [EADDRNOTAVAIL] when an attempt is made to create a socket with a network address for which no network interface exists.

SEE ALSO

intro(4N), inet(4F), imp(4)

NAME

inet – Internet protocol family

SYNOPSIS

```
#include <sys/types.h>
#include <netinet/in.h>
```

DESCRIPTION

The Internet protocol family is a collection of protocols layered atop the *Internet Protocol* (IP) transport layer, and utilizing the Internet address format. The Internet family provides protocol support for the SOCK_STREAM, SOCK_DGRAM, and SOCK_RAW socket types; the SOCK_RAW interface provides access to the IP protocol.

ADDRESSING

Internet addresses are four byte quantities, stored in network standard format (on the VAX these are word and byte reversed). The include file *<netinet/in.h>* defines this address as a discriminated union.

Sockets bound to the Internet protocol family utilize the following addressing structure,

```
struct sockaddr_in {
    short      sin_family;
    u_short    sin_port;
    struct      in_addr sin_addr;
    char       sin_zero[8];
};
```

Sockets may be created with the local address INADDR_ANY to effect “wildcard” matching on incoming messages. The address in a *connect(2)* or *sendto(2)* call may be given as INADDR_ANY to mean “this host.” The distinguished address INADDR_BROADCAST is allowed as a shorthand for the broadcast address on the primary network if the first network configured supports broadcast.

PROTOCOLS

The Internet protocol family is comprised of the IP transport protocol, Internet Control Message Protocol (ICMP), Transmission Control Protocol (TCP), and User Datagram Protocol (UDP). TCP is used to support the SOCK_STREAM abstraction while UDP is used to support the SOCK_DGRAM abstraction. A raw interface to IP is available by creating an Internet socket of type SOCK_RAW. The ICMP message protocol is accessible from a raw socket.

The 32-bit Internet address contains both network and host parts. It is frequency-encoded; the most-significant bit is clear in Class A addresses, in which the high-order 8 bits are the network number. Class B addresses use the high-order 16 bits as the network field, and Class C addresses have a 24-bit network part. Sites with a cluster of local networks and a connection to the DARPA Internet may choose to use a single network number for the cluster; this is done by using subnet addressing. The local (host) portion of the address is further subdivided into subnet and host parts. Within a subnet, each subnet appears to be an individual network; externally, the entire cluster appears to be a single, uniform network requiring only a single routing entry. Subnet addressing is enabled and examined by the following *ioctl(2)* commands on a datagram socket in the Internet domain; they have the same form as the SIOCIFADDR command (see *intro(4N)*).

SIOCSIFNETMASK Set interface network mask. The network mask defines the network part of the address; if it contains more of the address than the address type would indicate, then subnets are in use.

SIOCGIFNETMASK

Get interface network mask.

SEE ALSO

ioctl(2), socket(2), intro(4N), tcp(4P), udp(4P), ip(4P), icmp(4P)

An Introductory 4.3BSD Interprocess Communication Tutorial (PS1:7).

An Advanced 4.3BSD Interprocess Communication Tutorial (PS1:8).

CAVEAT

The Internet protocol support is subject to change as the Internet protocols develop. Users should not depend on details of the current implementation, but rather the services exported.

NAME

ip – Internet Protocol

SYNOPSIS

```
#include <sys/socket.h>
#include <netinet/in.h>
```

```
s = socket(AF_INET, SOCK_RAW, proto);
```

DESCRIPTION

IP is the transport layer protocol used by the Internet protocol family. Options may be set at the IP level when using higher-level protocols that are based on IP (such as TCP and UDP). It may also be accessed through a "raw socket" when developing new protocols, or special purpose applications.

A single generic option is supported at the IP level, `IP_OPTIONS`, that may be used to provide IP options to be transmitted in the IP header of each outgoing packet. Options are set with `setsockopt(2)` and examined with `getsockopt(2)`. The format of IP options to be sent is that specified by the IP protocol specification, with one exception: the list of addresses for Source Route options must include the first-hop gateway at the beginning of the list of gateways. The first-hop gateway address will be extracted from the option list and the size adjusted accordingly before use. IP options may be used with any socket type in the Internet family.

Raw IP sockets are connectionless, and are normally used with the `sendto` and `recvfrom` calls, though the `connect(2)` call may also be used to fix the destination for future packets (in which case the `read(2)` or `recv(2)` and `write(2)` or `send(2)` system calls may be used).

If `proto` is 0, the default protocol `IPPROTO_RAW` is used for outgoing packets, and only incoming packets destined for that protocol are received. If `proto` is non-zero, that protocol number will be used on outgoing packets and to filter incoming packets.

Outgoing packets automatically have an IP header prepended to them (based on the destination address and the protocol number the socket is created with). Incoming packets are received with IP header and options intact.

DIAGNOSTICS

A socket operation may fail with one of the following errors returned:

- [EISCONN] when trying to establish a connection on a socket which already has one, or when trying to send a datagram with the destination address specified and the socket is already connected;
- [ENOTCONN] when trying to send a datagram, but no destination address is specified, and the socket hasn't been connected;
- [ENOBUFS] when the system runs out of memory for an internal data structure;
- [EADDRNOTAVAIL] when an attempt is made to create a socket with a network address for which no network interface exists.

The following errors specific to IP may occur when setting or getting IP options:

- [EINVAL] An unknown socket option name was given.
- [EINVAL] The IP option field was improperly formed; an option field was shorter than the minimum value or longer than the option buffer provided.

SEE ALSO

`getsockopt(2)`, `send(2)`, `recv(2)`, `intro(4N)`, `icmp(4P)`, `inet(4F)`

NAME

ix – Interlan Np100 10 Mb/s Ethernet interface

SYNOPSIS

device np0 at uba0 csr 166000 vector npintr

DESCRIPTION

The *ix* interface provides access to a 10 Mb/s Ethernet network through an Interlan Np100 controller used as a link-layer interface.

This interface is unusual in that it requires loading firmware into the controller before it may be used as a network interface. This is accomplished by opening a character special device, and writing data to it. A program to load the image is provided in */usr/src/new/np100*. The sequence of commands would be:

```
# ./npload np.image [/dev/np<board #> if other than np00]
# sleep 10
# ifconfig ix0 ...
```

Each of the host's network addresses is specified at boot time with an *SIOCSIFADDR* ioctl. The *ix* interface employs the address resolution protocol described in *arp*(4P) to dynamically map between Internet and Ethernet addresses on the local network.

The interface normally tries to use a “trailer” encapsulation to minimize copying data on input and output. The use of trailers is negotiated with ARP. This negotiation may be disabled, on a per-interface basis, by setting the *IFF_NOTRAILERS* flag with an *SIOCSIF_FLAGS* ioctl.

DIAGNOSTICS

ix%d: Req failed, cmd %x, stat %x, ust error %x,%x. The firmware in the controller refused to honor a request from in initializing packet level communications. The board may need to be reset and reloaded. Or, you may not have allowed enough time between loading the board and issuing the request to begin unix network operation.

ix%d: can't initialize. The interface was unable to obtain unibus resources required for operation.

ix%d: failed to reinitialize DLA module. The interface got sick after attempting to reprogram its physical ethernet address. Try reloading the firmware. The attempt is made only when this interfaces is not the first one configured for XNS.

ix%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

ix%d: stray xmit interrupt, npreq=%x. This may happen if the board is reloaded while network processes are still running.

ixrint: cqe error %x, %x, %x. This will result if an *ifconfig*(8c) request is made at an inopportune time, such as not allowing enough time after loading the firmware. After 100 such errors are logged, the unix network driver will shut itself down, saying:

ixrint: shutting down unix dla. The recourse is to reload the firmware and allow more time.

SEE ALSO

intro(4N), *inet*(4F), *arp*(4P), *np*(4).

NAME

kg – KL-11/DL-11W line clock

SYNOPSIS

device kg0 at uba0 csr 0176500 vector kglock

DESCRIPTION

A kl-11 or dl-11w can be used as an alternate real time clock source. When configured, certain system statistics and, optionally, system profiling work will be collected each time the clock interrupts. For optimum accuracy in profiling, the dl-11w should be configured to interrupt at the highest possible priority level. The *kg* device driver automatically calibrates itself to the line clock frequency.

SEE ALSO

kgmon(8), config(8)

NAME

lo – software loopback network interface

SYNOPSIS

pseudo-device loop

DESCRIPTION

The *loop* interface is a software loopback mechanism which may be used for performance analysis, software testing, and/or local communication. As with other network interfaces, the loopback interface must have network addresses assigned for each address family with which it is to be used. These addresses may be set or changed with the `SIOCSIFADDR` ioctl. The loopback interface should be the last interface configured, as protocols may use the order of configuration as an indication of priority. The loopback should never be configured first unless no hardware interfaces exist.

DIAGNOSTICS

`lo%d: can't handle af%d`. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

SEE ALSO

intro(4N), inet(4F), ns(4F)

BUGS

Previous versions of the system enabled the loopback interface automatically, using a non-standard Internet address (127.1). Use of that address is now discouraged; a reserved host address for the local network should be used instead.

NAME

lp - line printer

SYNOPSIS

device lp0 at uba0 csr 0177514 vector lpintr

DESCRIPTION

Lp provides the interface to any of the standard DEC line printers on an LP-11 parallel interface. When it is opened or closed, a suitable number of page ejects is generated. Bytes written are printed.

The unit number of the printer is specified by the minor device after removing the low 3 bits, which act as per-device parameters. Currently only the lowest of the low three bits is interpreted: if it is set, the device is treated as having a 64-character set, rather than a full 96-character set. In the resulting half-ASCII mode, lower case letters are turned into upper case and certain characters are escaped according to the following table:

{	{
}	}
,	,

The driver correctly interprets carriage returns, backspaces, tabs, and form feeds. Lines longer than the maximum page width are truncated. The default page width is 132 columns. This may be overridden by specifying, for example, "flags 256".

FILES

/dev/lp

SEE ALSO

lpr(1)

DIAGNOSTICS

None.

P
R
M
4

NAME

mem, *kmem* – main memory

DESCRIPTION

Mem is a special file that is an image of the main memory of the computer. It may be used, for example, to examine (and even to patch) the system.

Byte addresses in *mem* are interpreted as physical memory addresses. References to non-existent locations cause errors to be returned.

The file *kmem* is the same as *mem* except that kernel virtual memory rather than physical memory is accessed. Only kernel virtual addresses that are mapped to memory are allowed. The file *kUmem* also refers to kernel virtual memory, but may be used to access areas mapped to UNIBUS address space and other I/O areas. It forces all accesses to use word (short integer) accesses. Examining and patching device registers is likely to lead to unexpected results when read-only or write-only bits are present.

On VAX 11/780 the I/O space begins at physical address 20000000(16); on an 11/750 I/O space addresses are of the form *fxxxxx*(16). On all VAX'en per-process data for the current process is UPAGES long, and ends at virtual address 80000000(16).

FILES

/dev/mem
/dev/kmem
/dev/kUmem

NAME

mt - TM78/TU-78 MASSBUS magtape interface

SYNOPSIS

master mt0 at mba? drive ?
tape mu0 at mt0 slave 0

DESCRIPTION

The tm78/tu-78 combination provides a standard tape drive interface as described in *mtio(4)*. Only 1600 and 6250 bpi are supported; the TU-78 runs at 125 ips and autoloads tapes.

SEE ALSO

mt(1), tar(1), tp(1), mtio(4), tm(4), ts(4), ut(4)

DIAGNOSTICS

mu%d: no write ring. An attempt was made to write on the tape drive when no write ring was present; this message is written on the terminal of the user who tried to access the tape.

mu%d: not online. An attempt was made to access the tape while it was offline; this message is written on the terminal of the user who tried to access the tape.

mu%d: can't change density in mid-tape. An attempt was made to write on a tape at a different density than is already recorded on the tape. This message is written on the terminal of the user who tried to switch the density.

mu%d: hard error bn%d mbsr=%b er=%x ds=%b. A tape error occurred at block *bn*; the mt error register and drive status register are printed in octal with the bits symbolically decoded. Any error is fatal on non-raw tape; when possible the driver will have retried the operation which failed several times before reporting the error.

mu%d: blank tape. An attempt was made to read a blank tape (a tape without even end-of-file marks).

mu%d: offline. During an i/o operation the device was set offline. If a non-raw tape was used in the access it is closed.

BUGS

If any non-data error is encountered on non-raw tape, it refuses to do anything more until closed.

Because 800 bpi tapes are not supported, the numbering of minor devices is inconsistent with triple-density tape units. Unit 0 is drive 0, 1600 bpi.

NAME

mtio – UNIX magtape interface

DESCRIPTION

The files *mt0*, ..., *mt15* refer to the UNIX magtape drives, which may be on the MASSBUS using the TM03 formatter *ht(4)*, or TM78 formatter, *mt(4)*, or on the UNIBUS using either the TM11 or TS11 formatters *tm(4)*, TU45 compatible formatters, *ut(4)*, or *ts(4)*. The following description applies to any of the transport/controller pairs. The files *mt0*, ..., *mt7* are 800bpi (or the transport's lowest density), *mt8*, ..., *mt15* are 1600bpi (or the transport's second density), and *mt16*, ..., *mt23* are 6250bpi (or the transport's third density). (But note that only 1600 bpi is available with the TS11.) The files *mt0*, ..., *mt3*, *mt8*, ..., *mt11*, and *mt16*, ..., *mt19* are rewound when closed; the others are not. When a file open for writing is closed, two end-of-files are written. If the tape is not to be rewound it is positioned with the head between the two tapemarks.

A standard tape consists of a series of 1024 byte records terminated by an end-of-file. To the extent possible, the system makes it possible, if inefficient, to treat the tape like any other file. Seeks have their usual meaning and it is possible to read or write a byte at a time. Writing in very small units is inadvisable, however, because it uses most of the tape in record gaps.

The *mt* files discussed above are useful when it is desired to access the tape in a way compatible with ordinary files. When foreign tapes are to be dealt with, and especially when long records are to be read or written, the 'raw' interface is appropriate. The associated files are named *rmt0*, ..., *rmt23*, but the same minor-device considerations as for the regular files still apply. A number of other ioctl operations are available on raw magnetic tape. The following definitions are from *<sys/mtio.h>*:

```
/*
 * Structures and definitions for mag tape io control commands
 */

/* structure for MTIOCTOP - mag tape op command */
struct mtop {
    short mt_op;          /* operations defined below */
    daddr_tmt_count;     /* how many of them */
};

/* operations */
#define MTWEOF 0          /* write an end-of-file record */
#define MTFSF 1          /* forward space file */
#define MTBSF 2          /* backward space file */
#define MTFSR 3          /* forward space record */
#define MTBSR 4          /* backward space record */
#define MTREW 5          /* rewind */
#define MTOFFL 6         /* rewind and put the drive offline */
#define MTNOP 7          /* no operation, sets status only */
#define MTCACHE 8        /* enable controller cache */
#define MTNOCACHE9      /* disable controller cache */

/* structure for MTIOCGET - mag tape get status command */

struct mtget {
    short mt_type;        /* type of magtape device */
    /* the following two registers are grossly device dependent */
    short mt_dsreg;       /* "drive status" register */
    short mt_erreg;       /* "error" register */
};
```

```

/* end device-dependent registers */
short  mt_resid;      /* residual count */
/* the following two are not yet implemented */
daddr_tmt_fileno;     /* file number of current position */
daddr_tmt_blkno;      /* block number of current position */
/* end not yet implemented */
};

/*
 * Constants for mt_type byte. These are the same
 * for other controllers compatible with the types listed.
 */
#define MT_ISTS          0x01      /* TS-11 */
#define MT_ISHT          0x02      /* TM03 Massbus: TE16, TU45, TU77 */
#define MT_ISTM          0x03      /* TM11/TE10 Unibus */
#define MT_ISMT          0x04      /* TM78/TU78 Massbus */
#define MT_ISUT          0x05      /* SI TU-45 emulation on Unibus */
#define MT_ISPCPC        0x06      /* SUN */
#define MT_ISAR          0x07      /* SUN */
#define MT_ISTMSCP        0x08      /* DEC TMSCP protocol (TU81, TK50) */

/* mag tape io control commands */
#define MTIOCTOP          _IOW(m, 1, struct mtop)      /* do a mag tape op */
#define MTIOCGET          _IOR(m, 2, struct mtget)     /* get tape status */
#define MTIOCIEOT         _IO(m, 3)                   /* ignore EOT error */
#define MTIOCEEOT         _IO(m, 4)                   /* enable EOT error */

#ifndef KERNEL
#define DEFTAPE            "/dev/rmt12"
#endif

```

Each *read* or *write* call reads or writes the next record on the tape. In the write case the record has the same length as the buffer given. During a read, the record size is passed back as the number of bytes read, provided it is no greater than the buffer size; if the record is long, an error is indicated. In raw tape I/O seeks are ignored. A zero byte count is returned when a tape mark is read, but another read will fetch the first record of the new tape file.

FILES

/dev/mt?
/dev/rmt?

SEE ALSO

mt(1), tar(1), tp(1), ht(4), tm(4), mft(4), ut(4)

BUGS

The status should be returned in a device independent format.

The special file naming should be redone in a more consistent and understandable manner.

NAME

np – Interlan Np100 10 Mb/s Ethernet interface

SYNOPSIS

device np0 at uba0 csr 166000 vector npintr

DESCRIPTION

The **NP** device provides access to an Interlan Np100 Ethernet interface for control functions.

This interface is unusual in that it requires loading firmware into the controller before it may be used as a network link-level interface. This is accomplished by opening a character special device, and writing data to it. It is also possible to do post-mortem debugging of firmware failures by reading the local memory of the device.

A program to load the image is provided in `/usr/src/new/np100`. The sequence of commands would be:

```
# ./npload np.image [/dev/np00]
# sleep 10
# ifconfig ix0 ...
```

Multiple control processes are allowed by opening separate minor devices; secondary interfaces are specified by shifting the interface number by 4 bits.

The device also responds to commands passed through the driver by the following ioctls:

NPRESET

kills off all active network processes.

NPSTART

begins execution of the board at the specified address (usually 0x400).

NPNETBOOT

downloads the image from a server on the network. [Contact MICOM-INTERLAN for details.]

DIAGNOSTICS

np%d: Bad Maintenance command: %x! An invalid ioctl was passed to the np driver.

np%d: Panic NP100 bad buffer chain. An error occurred in an read or write operation causing it to run out of buffers before it finished the operation. This indicates a kernel failure rather than a device failure.

NP100 unit %d not found! A failure occurred during initialization, such that the unibus address expected for the board was found to be bad. Probably indicates hardware problems with the board, as do the following:

NP100 Unit %d timed out!

NP100 Unit %d Failed diagnostics!
Status from CSR0: %x.

Panic from NP100 unit %d!\nPanic Message: %s. An occurrence on the board was deemed serious enough to have the vax print it out.

NP100 unit #%d available! The board was successfully loaded and started.

np%d: Bad Req: %x.. The board made a maintenance request to the vax that it did not understand.

np%d: No more room on Command Queue! The np driver allowed an internal resource to be exhausted. This should never happen.

There are 110 other diagnostic messages that can be enabled by setting bits in a debugging mask. Consult the driver for details.

SEE ALSO

intro(4N), inet(4F), arp(4P), ix(4)

NAME

ns – Xerox Network Systems(tm) protocol family

SYNOPSIS

options NS
options NSIP
pseudo-device ns

DESCRIPTION

The NS protocol family is a collection of protocols layered atop the *Internet Datagram Protocol* (IDP) transport layer, and using the Xerox NS address formats. The NS family provides protocol support for the SOCK_STREAM, SOCK_DGRAM, SOCK_SEQPACKET, and SOCK_RAW socket types; the SOCK_RAW interface is a debugging tool, allowing you to trace all packets entering, (or with toggling kernel variable, additionally leaving) the local host.

ADDRESSING

NS addresses are 12 byte quantities, consisting of a 4 byte Network number, a 6 byte Host number and a 2 byte port number, all stored in network standard format. (on the VAX these are word and byte reversed; on the Sun they are not reversed). The include file *<netns/ns.h>* defines the NS address as a structure containing unions (for quicker comparisons).

Sockets in the Internet protocol family use the following addressing structure:

```
struct sockaddr_ns {
    short      sns_family;
    struct ns_addr sns_addr;
    char       sns_zero[2];
};
```

where an ns_addr is composed as follows:

```
union ns_host {
    u_char      c_host[6];
    u_short     s_host[3];
};
```

```
union ns_net {
    u_char      c_net[4];
    u_short     s_net[2];
};
```

```
struct ns_addr {
    union ns_net  x_net;
    union ns_host x_host;
    u_short x_port;
};
```

Sockets may be created with an address of all zeroes to effect "wildcard" matching on incoming messages. The local port address specified in a *bind(2)* call is restricted to be greater than NSPORT_RESERVED (=3000, in *<netns/ns.h>*) unless the creating process is running as the super-user, providing a space of protected port numbers.

PROTOCOLS

The NS protocol family supported by the operating system is comprised of the Internet Datagram Protocol (IDP) *idp(4P)*, Error Protocol (available through IDP), and Sequenced Packet Protocol (SPP) *spp(4P)*.

SPP is used to support the SOCK_STREAM and SOCK_SEQPACKET abstraction, while IDP is used to support the SOCK_DGRAM abstraction. The Error protocol is responded to by the kernel to handle and report errors in protocol processing; it is, however, only accessible to user programs through heroic actions.

SEE ALSO

intro(3), byteorder(3N), gethostbyname(3N), getnetent(3N), getprotoent(3N), getservent(3N), ns(3N), intro(4N), spp(4P), idp(4P), nsip(4)

Internet Transport Protocols, Xerox Corporation document XSI-028112

An Advanced 4.3BSD Interprocess Communication Tutorial

NAME

nsip – software network interface encapsulating ns packets in ip packets.

SYNOPSIS

options NSIP

#include <netns/ns_if.h>

DESCRIPTION

The *nsip* interface is a software mechanism which may be used to transmit Xerox NS(tm) packets through otherwise uncooperative networks. It functions by prepending an IP header, and resubmitting the packet through the unix IP machinery.

The super-user can advise the operating system of a willing partner by naming an IP address to be associated with an NS address. Presently, only specific hosts pairs are allowed, and for each host pair, an artificial point-to-point interface is constructed. At some future date, IP broadcast addresses or hosts may be paired with NS networks or hosts.

Specifically, a socket option of SO_NSIP_ROUTE is set on a socket of family AF_NS, type SOCK_DGRAM, passing the following structure:

```
struct nsip_req {
    struct sockaddr rq_ns; /* must be ns format destination */
    struct sockaddr rq_ip; /* must be ip format gateway */
    short rq_flags;
};
```

DIAGNOSTICS

nsip%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

SEE ALSO

intro(4N), ns(4F)

BUGS

It is absurd to have a separate pseudo-device for each pt-to-pt link. There is no way to change the IP address for an NS host once the the encapsulation interface is set up. The request should honor flags of RTF_GATEWAY to indicate remote networks, and the absence of RTF_UP should be a clue to remove that partner. This was intended to postpone the necessity of rewriting reverse ARP for the en device, and to allow passing XNS packets through an Arpanet-Milnet gateway, to facilitate testing between some co-operating universities.

NAME

null – data sink

DESCRIPTION

Data written on a null special file is discarded.

Reads from a null special file always return 0 bytes.

FILES

/dev/null

NAME

pcl - DEC CSS PCL-11 B Network Interface

SYNOPSIS

device pcl0 at uba? csr 164200 vector pclxint pclrint

DESCRIPTION

The *pcl* device provides an IP-only interface to the DEC CSS PCL-11 time division multiplexed network bus. The controller itself is not accessible to users.

The hosts's address is specified with the SIOCSIFADDR ioctl. The interface will not transmit or receive any data before its address is defined.

As the PCL-11 hardware is only capable of having 15 interfaces per network, a single-byte host-on-network number is used, with range [1..15] to match the TDM bus addresses of the interfaces.

The interface currently only supports the Internet protocol family and only provides "natural" (header) encapsulation.

DIAGNOSTICS

pcl%d: can't init. Insufficient UNIBUS resources existed to initialize the device. This is likely to occur when the device is run on a buffered data path on an 11/750 and other network interfaces are also configured to use buffered data paths, or when it is configured to use buffered data paths on an 11/730 (which has none).

pcl%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

pcl%d: stray xmit interrupt. An interrupt occurred when no output had previously been started.

pcl%d: master. The TDM bus had no station providing "bus master" timing signals, so this interface has assumed the "master" role. This message should only appear at most once per UNIBUS INIT on a single system. Unless there is a hardware failure, only one station may be master at a time.

pcl%d: send error, tcr=%b, tsr=%b. The device indicated a problem sending data on output. If a "receiver offline" error is detected, it is not normally logged unless the option PCL_TESTING has been selected, as this causes a lot of console chatter when sending to a down machine. However, this option is quite useful when debugging problems with the PCL interfaces.

pcl%d: rcv error, rcr=%b rsr=%b. The device indicated a problem receiving data on input.

pcl%d: bad len=%d. An input operation resulted in a data transfer of less than 0 or more than 1008 bytes of data into memory (according to the word count register). This should never happen as the maximum size of a PCL message has been agreed upon to be 1008 bytes (same as ArpaNet message).

SEE ALSO

intro(4N), inet(4F)

NAME

ps – Evans and Sutherland Picture System 2 graphics device interface

SYNOPSIS

device ps0 at uba? csr 0172460 vector psclockintr pssystemintr

DESCRIPTION

The *ps* driver provides access to an Evans and Sutherland Picture System 2 graphics device. Each minor device is a new PS2. When the device is opened, its interface registers are mapped, via virtual memory, into a user process's address space. This allows the user process very high bandwidth to the device with no system call overhead.

DMA to and from the PS2 is not supported. All read and write system calls will fail. All data is moved to and from the PS2 via programmed I/O using the device's interface registers.

Commands are fed to and from the driver using the following ioctl's:

PSIOGETADDR

Returns the virtual address through which the user process can access the device's interface registers.

PSIOAUTOREFRESH

Start auto refreshing the screen. The argument is an address in user space where the following data resides. The first longword is a *count* of the number of static refresh buffers. The next *count* longwords are the addresses in refresh memory where the refresh buffers lie. The driver will cycle through these refresh buffers displaying them one by one on the screen.

PSIOAUTOMAP

Start automatically passing the display file through the matrix processor and into the refresh buffer. The argument is an address in user memory where the following data resides. The first longword is a *count* of the number of display files to operate on. The next *count* longwords are the address of these display files. The final longword is the address in refresh buffer memory where transformed coordinates are to be placed if the driver is not in double buffer mode (see below).

PSIODOUBLEBUFFER

Cause the driver to double buffer the output from the map that is going to the refresh buffer. The argument is again a user space address where the real arguments are stored. The first argument is the starting address of refresh memory where the two double buffers are located. The second argument is the length of each double buffer. The refresh mechanism displays the current double buffer, in addition to its static refresh lists, when in double buffer mode.

PSIOSINGLEREFRESH

Single step the refresh process. That is, the driver does not continually refresh the screen.

PSIOSINGLEMAP

Single step the matrix process. The driver does not automatically feed display files through the matrix unit.

PSIOSINGLEBUFFER

Turn off double buffering.

PSIOTIMEREFRESH

The argument is a count of the number of refresh interrupts to take before turning off the screen. This is used to do time exposures.

PSIOWAITREFRESH

Suspend the user process until a refresh interrupt has occurred. If in **TIMEREFRESH**

mode, suspend until count refreshes have occurred.

PSIOSTOPREFRESH

Wait for the next refresh, stop all refreshes, and then return to user process.

PSIOWAITMAP

Wait until a map done interrupt has occurred.

PSIOSTOPMAP

Wait for a map done interrupt, do not restart the map, and then return to the user.

FILES

/dev/ps

DIAGNOSTICS

ps device intr.

ps dma intr. An interrupt was received from the device. This shouldn't happen, check your device configuration for overlapping interrupt vectors.

BUGS

An invalid access (e.g., longword) to a mapped interface register can cause the system to crash with a machine check. A user process could possibly cause infinite interrupts hence bringing things to a crawl.

NAME

pty – pseudo terminal driver

SYNOPSIS

pseudo-device pty [count]

DESCRIPTION

The *pty* driver provides support for a device-pair termed a *pseudo terminal*. A pseudo terminal is a pair of character devices, a *master* device and a *slave* device. The slave device provides processes an interface identical to that described in *tty(4)*. However, whereas all other devices which provide the interface described in *tty(4)* have a hardware device of some sort behind them, the slave device has, instead, another process manipulating it through the master half of the pseudo terminal. That is, anything written on the master device is given to the slave device as input and anything written on the slave device is presented as input on the master device.

In configuring, if an optional “count” is given in the specification, that number of pseudo terminal pairs are configured; the default count is 32.

The following *ioctl* calls apply only to pseudo terminals:

TIOCSTOP

Stops output to a terminal (e.g. like typing ^S). Takes no parameter.

TIOCPKT

Restarts output (stopped by TIOCSTOP or by typing ^S). Takes no parameter.

TIOCPKT

Enable/disable *packet* mode. Packet mode is enabled by specifying (by reference) a nonzero parameter and disabled by specifying (by reference) a zero parameter. When applied to the master side of a pseudo terminal, each subsequent *read* from the terminal will return data written on the slave part of the pseudo terminal preceded by a zero byte (symbolically defined as TIOCPKT_DATA), or a single byte reflecting control status information. In the latter case, the byte is an inclusive-or of zero or more of the bits:

TIOCPKT_FLUSHREAD

whenever the read queue for the terminal is flushed.

TIOCPKT_FLUSHWRITE

whenever the write queue for the terminal is flushed.

TIOCPKT_STOP

whenever output to the terminal is stopped a la ^S.

TIOCPKT_START

whenever output to the terminal is restarted.

TIOCPKT_DOSTOP

whenever *t_stopc* is ^S and *t_startc* is ^Q.

TIOCPKT_NOSTOP

whenever the start and stop characters are not ^S/^Q.

While this mode is in use, the presence of control status information to be read from the master side may be detected by a *select* for exceptional conditions.

This mode is used by *rlogin(1C)* and *rlogind(8C)* to implement a remote-echoed, locally ^S/^Q flow-controlled remote login with proper back-flushing of output; it can be used by other similar programs.

TIOCUCNTL

Enable/disable a mode that allows a small number of simple user *ioctl* commands to

be passed through the pseudo-terminal, using a protocol similar to that of TIOCPKT. The TIOCUCNTL and TIOCPKT modes are mutually exclusive. This mode is enabled from the master side of a pseudo terminal by specifying (by reference) a nonzero parameter and disabled by specifying (by reference) a zero parameter. Each subsequent *read* from the master side will return data written on the slave part of the pseudo terminal preceded by a zero byte, or a single byte reflecting a user control operation on the slave side. A user control command consists of a special *ioctl* operation with no data; the command is given as UIOCCMD(*n*), where *n* is a number in the range 1-255. The operation value *n* will be received as a single byte on the next *read* from the master side. The *ioctl* UIOCCMD(0) is a no-op that may be used to probe for the existence of this facility. As with TIOCPKT mode, command operations may be detected with a *select* for exceptional conditions.

TIOCREMOTE

A mode for the master half of a pseudo terminal, independent of TIOCPKT. This mode causes input to the pseudo terminal to be flow controlled and not input edited (regardless of the terminal mode). Each write to the control terminal produces a record boundary for the process reading the terminal. In normal usage, a write of data is like the data typed as a line on the terminal; a write of 0 bytes is like typing an end-of-file character. TIOCREMOTE can be used when doing remote line editing in a window manager, or whenever flow controlled input is required.

FILES

/dev/pty[p-r][0-9a-f]	master pseudo terminals
/dev/tty[p-r][0-9a-f]	slave pseudo terminals

DIAGNOSTICS

None.

NAME

qe – DEC DEQNA Q-bus 10 Mb/s Ethernet interface

SYNOPSIS

device qe0 at uba? csr 174440 vector qeintr

DESCRIPTION

The qe interface provides access to a 10 Mb/s Ethernet network through the DEC DEQNA Q-bus controller.

Each of the host's network addresses is specified at boot time with an SIOCSIFADDR ioctl. The qe interface employs the address resolution protocol described in arp(4P) to map dynamically between Internet and Ethernet addresses on the local network.

The interface normally tries to use a "trailer" encapsulation to minimize copying data on input and output. The use of trailers is negotiated with ARP. This negotiation may be disabled, on a per-interface basis, by setting the IFF_NOTRAILERS flag with an SIOCSIFLAGS ioctl.

DIAGNOSTICS**SEE ALSO**

inet(4F), intro(4N), arp(4P)

NAME

rx - DEC RX02 floppy disk interface

SYNOPSIS

controller fx0 at uba0 csr 0177170 vector rxintr
 disk rx0 at fx0 drive 0
 disk rx1 at fx0 drive 1

DESCRIPTION

The rx device provides access to a DEC RX02 floppy disk unit with M8256 interface module (RX211 configuration). The RX02 uses 8-inch, single-sided, soft-sectored floppy disks (with pre-formatted industry-standard headers) in either single or double density.

Floppy disks handled by the RX02 contain 77 tracks, each with 26 sectors (for a total of 2,002 sectors). The sector size is 128 bytes for single density, 256 bytes for double density. Single density disks are compatible with the RX01 floppy disk unit and with IBM 3740 Series Diskette 1 systems.

In addition to normal ('block' and 'raw') i/o, the driver supports formatting of disks for either density and the ability to invoke a 2 for 1 interleaved sector mapping compatible with the DEC operating system RT-11.

The minor device number is interpreted as follows:

Bit	Description
0	Sector interleaving (1 disables interleaving)
1	Logical sector 1 is on track 1 (0 no, 1 yes)
2	Not used, reserved
Other	Drive number

The two drives in a single RX02 unit are treated as two disks attached to a single controller. Thus, if there are two RX02's on a system, the drives on the first RX02 are "rx0" and "rx1", while the drives on the second are "rx2" and "rx3".

When the device is opened, the density of the disk currently in the drive is automatically determined. If there is no floppy in the device, open will fail.

The interleaving parameters are represented in raw device names by the letters 'a' through 'd'. Thus, unit 0, drive 0 is called by one of the following names:

Mapping	Device name	Starting track
interleaved	/dev/rrx0a	0
direct	/dev/rrx0b	0
interleaved	/dev/rrx0c	1
direct	/dev/rrx0d	1

The mapping used on the 'c' device is compatible with the DEC operating system RT-11. The 'b' device accesses the sectors of the disk in strictly sequential order. The 'a' device is the most efficient for disk-to-disk copying. This mapping is always used by the block device.

I/O requests must start on a sector boundary, involve an integral number of complete sectors, and not go off the end of the disk.

NOTES

Even though the storage capacity on a floppy disk is quite small, it is possible to make filesystems on double density disks. For example, the command

```
% mkfs /dev/rx0 1001 13 1 4096 512 32 0 4
```

makes a file system on the double density disk in rx0 with 436 kbytes available for file storage. Using *tar*(1) gives a more efficient utilization of the available space for file storage. Single density diskettes do not provide sufficient storage capacity to hold file systems.

A number of *ioctl*(2) calls apply to the rx devices, and have the form

```
#include <vxuba/rxreg.h>
ioctl(fildes, code, arg)
int *arg;
```

The applicable codes are:

RXIOC_FORMAT

Format the diskette. The density to use is specified by the *arg* argument, zero gives single density while non-zero gives double density.

RXIOC_GETDENS

Return the density of the diskette (zero or non-zero as above).

RXIOC_WDDMK On the next write, include a *deleted data address mark* in the header of the first sector.

RXIOC_RDDMK Return non-zero if the last sector read contained a *deleted data address mark* in its header, otherwise return 0.

ERRORS

The following errors may be returned by the driver:

- [ENODEV] Drive not ready; usually because no disk is in the drive or the drive door is open.
- [ENXIO] Nonexistent drive (on open); offset is too large or not on a sector boundary or byte count is not a multiple of the sector size (on read or write); or bad (undefined) *ioctl* code.
- [EIO] A physical error other than "not ready", probably bad media or unknown format.
- [EBUSY] Drive has been opened for exclusive access.
- [EBADF] No write access (on format), or wrong density; the latter can only happen if the disk is changed without *closing* the device (i.e., calling *close*(2)).

FILES

/dev/rx?
/dev/rxx?[a-d]

SEE ALSO

rxformat(8V), newfs(8), mkfs(8), tar(1), arff(8V)

DIAGNOSTICS

rx%d: hard error, trk %d psec %d cs=%b, db=%b, err=%x, %x, %x, %x. An unrecoverable error was encountered. The track and physical sector numbers, the device registers and the extended error status are displayed.

rx%d: state %d (reset). The driver entered a bogus state. This should not happen.

BUGS

A floppy may not be formatted if the header info on sector 1, track 0 has been damaged. Hence, it is not possible to format completely degaussed disks or disks with other formats than the two known by the hardware.

If the drive subsystem is powered down when the machine is booted, the controller won't interrupt.

NAME

spp - Xerox Sequenced Packet Protocol

SYNOPSIS

```
#include <sys/socket.h>
#include <netns/ns.h>
s = socket(AF_NS, SOCK_STREAM, 0);

#include <netns/sp.h>
s = socket(AF_NS, SOCK_SEQPACKET, 0);
```

DESCRIPTION

The SPP protocol provides reliable, flow-controlled, two-way transmission of data. It is a byte-stream protocol used to support the SOCK_STREAM abstraction. SPP uses the standard NS(tm) address formats.

Sockets utilizing the SPP protocol are either "active" or "passive". Active sockets initiate connections to passive sockets. By default SPP sockets are created active; to create a passive socket the *listen(2)* system call must be used after binding the socket with the *bind(2)* system call. Only passive sockets may use the *accept(2)* call to accept incoming connections. Only active sockets may use the *connect(2)* call to initiate connections.

Passive sockets may "underspecify" their location to match incoming connection requests from multiple networks. This technique, termed "wildcard addressing", allows a single server to provide service to clients on multiple networks. To create a socket which listens on all networks, the NS address of all zeroes must be bound. The SPP port may still be specified at this time; if the port is not specified the system will assign one. Once a connection has been established the socket's address is fixed by the peer entity's location. The address assigned the socket is the address associated with the network interface through which packets are being transmitted and received. Normally this address corresponds to the peer entity's network.

If the SOCK_SEQPACKET socket type is specified, each packet received has the actual 12 byte sequenced packet header left for the user to inspect:

```
struct sphdr {
    u_char    sp_cc;          /* connection control */
#define SP_EM 0x10          /* end of message */
    u_char    sp_dt;          /* datastream type */
    u_short   sp_sid;
    u_short   sp_did;
    u_short   sp_seq;
    u_short   sp_ack;
    u_short   sp_alo;
};
```

This facilitates the implementation of higher level Xerox protocols which make use of the data stream type field and the end of message bit. Conversely, the user is required to supply a 12 byte header, the only part of which inspected is the data stream type and end of message fields.

For either socket type, packets received with the Attention bit set are interpreted as out of band data. Data sent with *send(..., ..., MSG_OOB)* cause the attention bit to be set.

DIAGNOSTICS

A socket operation may fail with one of the following errors returned:

[EISCONN] when trying to establish a connection on a socket which already has one;

[ENOBUFFS]	when the system runs out of memory for an internal data structure;
[ETIMEDOUT]	when a connection was dropped due to excessive retransmissions;
[ECONNRESET]	when the remote peer forces the connection to be closed;
[ECONNREFUSED]	when the remote peer actively refuses connection establishment (usually because no process is listening to the port);
[EADDRINUSE]	when an attempt is made to create a socket with a port which has already been allocated;
[EADDRNOTAVAIL]	when an attempt is made to create a socket with a network address for which no network interface exists.

SOCKET OPTIONS**SO_DEFAULT_HEADERS**

when set, this determines the data stream type and whether the end of message bit is to be set on every ensuing packet.

SO_MTU

This specifies the maximum ammount of user data in a single packet. The default is 576 bytes - sizeof(struct spidp). This quantity affects windowing -- increasing it without increasing the amount of buffering in the socket will lower the number of unread packets accepted. Anything larger than the default will not be forwarded by a bona fide XEROX product internetwork router. The data argument for the setsockopt call must be an unsigned short.

SEE ALSO

intro(4N), ns(4F)

BUGS

There should be some way to reflect record boundaries in a stream. For stream mode, there should be an option to get the data stream type of the record the user process is about to receive.

NAME

tb – line discipline for digitizing devices

SYNOPSIS

pseudo-device tb

DESCRIPTION

This line discipline provides a polled interface to many common digitizing devices which are connected to a host through a serial line. When these devices stream data at high speed, the use of the line discipline is critical in minimizing the number of samples that would otherwise be lost due to buffer exhaustion in the *tty(4)* handler.

The line discipline is enabled by a sequence:

```
#include <sys/tablet.h>
int ldisc = TBLDISC, fildes; ...
ioctl(fildes, TIOCSETD, &ldisc);
```

A typical application program then polls the digitizing device by reading a binary data structure which contains: the current X and Y positions (in the device coordinate space), up-down status of the buttons or pen stylus, proximity information (when available), and a count of the number of samples received from the input device since it was opened. In addition, devices such as the GTCO append tilt and pressure information to the end of the aforementioned structure. For the Polhemus 3-D digitizer the structure read is completely different. Refer to the include file for a complete description.

While in tablet mode, normal teletype input and output functions take place. Thus, if an 8 bit output data path is desired, it is necessary to prepare the output line by putting it into RAW mode using *ioctl(2)*. This must be done before changing the discipline with TIOCSETD, as most *ioctl(2)* calls are disabled while in tablet line-discipline mode.

The line discipline supports *ioctl(2)* requests to get/set the operating mode, and to get/set the tablet type and operating mode by *or-ing* the two values together.

The line discipline supports digitizing devices which are compatible with Hitachi, GTCO, or Polhemus protocol formats. For Hitachi there are several formats with that used in the newer model HDG-1111B the most common.

SEE ALSO

tty(4)

DIAGNOSTICS

None.

NAME

tcp – Internet Transmission Control Protocol

SYNOPSIS

```
#include <sys/socket.h>
#include <netinet/in.h>

s = socket(AF_INET, SOCK_STREAM, 0);
```

DESCRIPTION

The TCP protocol provides reliable, flow-controlled, two-way transmission of data. It is a byte-stream protocol used to support the SOCK_STREAM abstraction. TCP uses the standard Internet address format and, in addition, provides a per-host collection of “port addresses”. Thus, each address is composed of an Internet address specifying the host and network, with a specific TCP port on the host identifying the peer entity.

Sockets utilizing the tcp protocol are either “active” or “passive”. Active sockets initiate connections to passive sockets. By default TCP sockets are created active; to create a passive socket the *listen(2)* system call must be used after binding the socket with the *bind(2)* system call. Only passive sockets may use the *accept(2)* call to accept incoming connections. Only active sockets may use the *connect(2)* call to initiate connections.

Passive sockets may “underspecify” their location to match incoming connection requests from multiple networks. This technique, termed “wildcard addressing”, allows a single server to provide service to clients on multiple networks. To create a socket which listens on all networks, the Internet address INADDR_ANY must be bound. The TCP port may still be specified at this time; if the port is not specified the system will assign one. Once a connection has been established the socket's address is fixed by the peer entity's location. The address assigned the socket is the address associated with the network interface through which packets are being transmitted and received. Normally this address corresponds to the peer entity's network.

TCP supports one socket option which is set with *setsockopt(2)* and tested with *getsockopt(2)*. Under most circumstances, TCP sends data when it is presented; when outstanding data has not yet been acknowledged, it gathers small amounts of output to be sent in a single packet once an acknowledgement is received. For a small number of clients, such as window systems that send a stream of mouse events which receive no replies, this packetization may cause significant delays. Therefore, TCP provides a boolean option, TCP_NODELAY (from *<netinet/tcp.h>*), to defeat this algorithm. The option level for the *setsockopt* call is the protocol number for TCP, available from *getprotobyname(3N)*.

Options at the IP transport level may be used with TCP; see *ip(4P)*. Incoming connection requests that are source-routed are noted, and the reverse source route is used in responding.

DIAGNOSTICS

A socket operation may fail with one of the following errors returned:

[EISCONN]	when trying to establish a connection on a socket which already has one;
[ENOBUFS]	when the system runs out of memory for an internal data structure;
[ETIMEDOUT]	when a connection was dropped due to excessive retransmissions;
[ECONNRESET]	when the remote peer forces the connection to be closed;
[ECONNREFUSED]	when the remote peer actively refuses connection establishment (usually because no process is listening to the port);
[EADDRINUSE]	when an attempt is made to create a socket with a port which has already been allocated;

[EADDRNOTAVAIL]

when an attempt is made to create a socket with a network address for which no network interface exists.

SEE ALSO

getsockopt(2), socket(2), intro(4N), inet(4F), ip(4P)

NAME

tm – TM-11/TE-10 magtape interface

SYNOPSIS

controller tm0 at uba? csr 0172520 vector tmintr
tape te0 at tm0 drive 0

DESCRIPTION

The tm-11/te-10 combination provides a standard tape drive interface as described in *mtio(4)*. Hardware implementing this on the VAX is typified by the Emulex TC-11 controller operating with a Kennedy model 9300 tape transport, providing 800 and 1600 bpi operation at 125 ips.

SEE ALSO

mt(1), tar(1), tp(1), mtio(4), ht(4), ts(4), mt(4), ut(4)

DIAGNOSTICS

te%d: no write ring. An attempt was made to write on the tape drive when no write ring was present; this message is written on the terminal of the user who tried to access the tape.

te%d: not online. An attempt was made to access the tape while it was offline; this message is written on the terminal of the user who tried to access the tape.

te%d: can't switch density in mid-tape. An attempt was made to write on a tape at a different density than is already recorded on the tape. This message is written on the terminal of the user who tried to switch the density.

te%d: hard error bn%d er=%b. A tape error occurred at block *bn*; the tm error register is printed in octal with the bits symbolically decoded. Any error is fatal on non-raw tape; when possible the driver will have retried the operation which failed several times before reporting the error.

te%d: lost interrupt. A tape operation did not complete within a reasonable time, most likely because the tape was taken off-line during rewind or lost vacuum. The controller should, but does not, give an interrupt in these cases. The device will be made available again after this message, but any current open reference to the device will return an error as the operation in progress aborts.

BUGS

If any non-data error is encountered on non-raw tape, it refuses to do anything more until closed.

P
R
M
4

NAME

tmscp – DEC TMSCP magtape interface

SYNOPSIS

controller tmscp0 at uba? csr 0174500 vector tmscpintr
tape tms0 at tmscp0 drive 0

DESCRIPTION

Tape controllers compatible with the DEC Tape Mass Storage Control Protocol (TMSCP) architecture such as the TU81 and the TK50 provide a standard tape drive interface as described in *mtio*(4). The controller communicates with the host through a packet oriented protocol. Consult the file <vax/tmscp.h> for a detailed description of this protocol.

DIAGNOSTICS

tmscp controller failed to init. The controller initialization procedure failed. This probably indicates a hardware problem.

tmscp%d: sa 0%, state %d. (Additional status information given after a hard I/O error.) The values of the controller status register and the internal driver state are printed.

tmscp%d: random interrupt ignored. An unexpected interrupt was received (e.g. when no i/o was pending). The interrupt is ignored.

tmscp%d: interrupt in unknown state %d ignored. An interrupt was received when the driver was in an unknown internal state. Indicates a hardware problem or a driver bug.

tmscp%d: fatal error (0%). The controller detected a "fatal error" in the status returned to the host. The contents of the status register are displayed.

OFFLINE. (Additional status information given after a hard I/O error.) A hard I/O error occurred because the drive was not on-line.

The following errors are interpretations of TMSCP error messages returned by the controller to the host. Each is preceded by either **tmscp%d: hard error** or **tmscp%d: soft error**.

controller error, event 0%.

host memory access error, event 0%, addr 0%.

tape transfer error, unit %d, grp 0x%x, event 0%.

STI error, unit %d, event 0%.

STI Drive Error Log, unit %d, event 0%.

STI Formatter Error Log, unit %d, event 0%.

unknown error, unit %d, format 0%, event 0%.

SEE ALSO

mt(1), tar(1), tp(1), mtio(4), tm(4), ts(4), ut(4), dmesg(8)

NAME

ts - TS-11 magtape interface

SYNOPSIS

controller *zs0* at uba? csr 0172520 vector *tsintr*
tape *ts0* at *zs0* drive 0

DESCRIPTION

The ts-11 combination provides a standard tape drive interface as described in *mtio(4)*. The ts-11 operates only at 1600 bpi, and only one transport is possible per controller.

SEE ALSO

mt(1), *tar(1)*, *tp(1)*, *mtio(4)*, *ht(4)*, *tm(4)*, *mt(4)*, *ut(4)*

DIAGNOSTICS

ts%d: no write ring. An attempt was made to write on the tape drive when no write ring was present; this message is written on the terminal of the user who tried to access the tape.

ts%d: not online. An attempt was made to access the tape while it was offline; this message is written on the terminal of the user who tried to access the tape.

ts%d: hard error bn%d xs0=%b. A hard error occurred on the tape at block *bn*; status register 0 is printed in octal and symbolically decoded as bits.

BUGS

If any non-data error is encountered on non-raw tape, it refuses to do anything more until closed.

The device lives at the same address as a tm-11 *tm(4)*; as it is very difficult to get this device to interrupt, a generic system assumes that a ts is present whenever no tm-11 exists but the csr responds and a ts-11 is configured. This does no harm as long as a non-existent ts-11 is not accessed.

NAME

tty – general terminal interface

SYNOPSIS

```
#include <sgtty.h>
```

DESCRIPTION

This section describes both a particular special file `/dev/tty` and the terminal drivers used for conversational computing.

Line disciplines.

The system provides different *line disciplines* for controlling communications lines. In this version of the system there are two disciplines available for use with terminals:

- old The old (Version 7) terminal driver. This is sometimes used when using the standard shell `sh(1)`.
- new The standard Berkeley terminal driver, with features for job control; this must be used when using `csh(1)`.

Line discipline switching is accomplished with the `TIOCSETD` *ioctl*:

```
int ldisc = LDISC;
ioctl(f, TIOCSETD, &ldisc);
```

where `LDISC` is `OTTYDISC` for the standard tty driver and `NTTYDISC` for the “new” driver. The standard (currently old) tty driver is discipline 0 by convention. Other disciplines may exist for special purposes, such as use of communications lines for network connections. The current line discipline can be obtained with the `TIOCGETD` *ioctl*. Pending input is discarded when the line discipline is changed.

All of the low-speed asynchronous communications ports can use any of the available line disciplines, no matter what hardware is involved. The remainder of this section discusses the “old” and “new” disciplines.

The control terminal.

When a terminal file is opened, it causes the process to wait until a connection is established. In practice, user programs seldom open these files; they are opened by `getty(8)` or `rlogind(8C)` and become a user's standard input and output file.

If a process which has no control terminal opens a terminal file, then that terminal file becomes the control terminal for that process. The control terminal is thereafter inherited by a child process during a `fork(2)`, even if the control terminal is closed.

The file `/dev/tty` is, in each process, a synonym for a *control terminal* associated with that process. It is useful for programs that wish to be sure of writing messages on the terminal no matter how output has been redirected. It can also be used for programs that demand a file name for output, when typed output is desired and it is tiresome to find out which terminal is currently in use.

A process can remove the association it has with its controlling terminal by opening the file `/dev/tty` and issuing an

```
ioctl(f, TIOCNOTTY, 0);
```

This is often desirable in server processes.

Process groups.

Command processors such as `csh(1)` can arbitrate the terminal between different *jobs* by placing related jobs in a single process group and associating this process group with the terminal. A terminal's associated process group may be set using the `TIOCSPGRP` *ioctl(2)*:

`ioctl(fildes, TIOCSGRP, &pggrp);`

or examined using `TIOCGGRP`, which returns the current process group in `pggrp`. The new terminal driver aids in this arbitration by restricting access to the terminal by processes which are not in the current process group; see **Job access control** below.

Modes.

The terminal drivers have three major modes, characterized by the amount of processing on the input and output characters:

- cooked** The normal mode. In this mode lines of input are collected and input editing is done. The edited line is made available when it is completed by a newline, or when the `t_brkc` character (normally undefined) or `t_eofc` character (normally an EOT, control-D, hereafter `^D`) is entered. A carriage return is usually made synonymous with newline in this mode, and replaced with a newline whenever it is typed. All driver functions (input editing, interrupt generation, output processing such as delay generation and tab expansion, etc.) are available in this mode.
- CBREAK** This mode eliminates the character, word, and line editing input facilities, making the input character available to the user program as it is typed. Flow control, literal-next and interrupt processing are still done in this mode. Output processing is done.
- RAW** This mode eliminates all input processing and makes all input characters available as they are typed; no output processing is done either.

The style of input processing can also be very different when the terminal is put in non-blocking I/O mode; see the `FNDELAY` flag described in `fcntl(2)`. In this case a `read(2)` from the control terminal will never block, but rather return an error indication (`EWOULDBLOCK`) if there is no input available.

A process may also request that a `SIGIO` signal be sent it whenever input is present and also whenever output queues fall below the low-water mark. To enable this mode the `FASYNC` flag should be set using `fcntl(2)`.

Input editing.

A UNIX terminal ordinarily operates in full-duplex mode. Characters may be typed at any time, even while output is occurring, and are only lost when the system's character input buffers become completely choked, which is rare, or when the user has accumulated the maximum allowed number of input characters that have not yet been read by some program. Currently this limit is 256 characters. In RAW mode, the terminal driver throws away all input and output without notice when the limit is reached. In CBREAK or cooked mode it refuses to accept any further input and, if in the new line discipline, rings the terminal bell.

Input characters are normally accepted in either even or odd parity with the parity bit being stripped off before the character is given to the program. By clearing either the `EVEN` or `ODD` bit in the flags word it is possible to have input characters with that parity discarded (see the **Summary** below.)

In all of the line disciplines, it is possible to simulate terminal input using the `TIOCSTI` `ioctl`, which takes, as its third argument, the address of a character. The system pretends that this character was typed on the argument terminal, which must be the control terminal except for the super-user (this call is not in standard version 7 UNIX).

Input characters are normally echoed by putting them in an output queue as they arrive. This may be disabled by clearing the `ECHO` bit in the flags word using the `stty(3C)` call or the `TIOCSETN` or `TIOCSETP` `ioctls` (see the **Summary** below).

In cooked mode, terminal input is processed in units of lines. A program attempting to read will normally be suspended until an entire line has been received (but see the description of SIGTTIN in *Job access control* and of FIONREAD in *Summary*, both below.) No matter how many characters are requested in the read call, at most one line will be returned. It is not, however, necessary to read a whole line at once; any number of characters may be requested in a read, even one, without losing information.

During input, line editing is normally done, with the erase character *sg_erase* (by default, DELETE) logically erasing the last character typed and the *sg_kill* character (default, ^U: control-U) logically erasing the entire current input line. These characters never erase beyond the beginning of the current input line or an eof. These characters may be entered literally by preceding them with ^\; the ^\ will normally be erased when the character is typed.

The drivers normally treat either a carriage return or a newline character as terminating an input line, replacing the return with a newline and echoing a return and a line feed. If the CRMOD bit is cleared in the local mode word then the processing for carriage return is disabled, and it is simply echoed as a return, and does not terminate cooked mode input.

In the new driver there is a literal-next character (normally ^V) which can be typed in both cooked and CBREAK mode preceding *any* character to prevent its special meaning to the terminal handler. This is to be preferred to the use of ^\ escaping erase and kill characters, but ^\ is retained with its old function in the new line discipline.

The new terminal driver also provides two other editing characters in normal mode. The word-erase character, normally ^W, erases the preceding word, but not any spaces before it. For the purposes of ^W, a word is defined as a sequence of non-blank characters, with tabs counted as blanks. Finally, the reprint character, normally ^R, retypes the pending input beginning on a new line. Retyping occurs automatically in cooked mode if characters which would normally be erased from the screen are fouled by program output.

Input echoing and redisplay

The terminal driver has several modes (not present in standard UNIX Version 7 systems) for handling the echoing of terminal input, controlled by bits in a local mode word.

Hardcopy terminals. When a hardcopy terminal is in use, the LPRTERA bit is normally set in the local mode word. Characters which are logically erased are then printed out backwards preceded by ^\ and followed by ^/ in this mode.

CRT terminals. When a CRT terminal is in use, the LCRTBS bit is normally set in the local mode word. The terminal driver then echoes the proper number of erase characters when input is erased; in the normal case where the erase character is a ^H this causes the cursor of the terminal to back up to where it was before the logically erased character was typed. If the input has become fouled due to interspersed asynchronous output, the input is automatically retyped.

Erasing characters from a CRT. When a CRT terminal is in use, the LCRTERA bit may be set to cause input to be erased from the screen with a "backspace-space-backspace" sequence when character or word deleting sequences are used. A LCRTKIL bit may be set as well, causing the input to be erased in this manner on line kill sequences as well.

Echoing of control characters. If the LCTLECH bit is set in the local state word, then non-printing (control) characters are normally echoed as ^X (for some X) rather than being echoed unmodified; delete is echoed as ^?.

The normal modes for use on CRT terminals are speed dependent. At speeds less than 1200 baud, the LCRTERA and LCRTKILL processing is painfully slow, and *stty(1)* normally just sets LCRTBS and LCTLECH; at speeds of 1200 baud or greater all of these bits are normally set. *Stty(1)* summarizes these option settings and the use of the new terminal driver as "newcrt."

Output processing.

When one or more characters are written, they are actually transmitted to the terminal as soon as previously-written characters have finished typing. (As noted above, input characters are normally echoed by putting them in the output queue as they arrive.) When a process produces characters more rapidly than they can be typed, it will be suspended when its output queue exceeds some limit. When the queue has drained down to some threshold the program is resumed. Even parity is normally generated on output. The EOT character is not transmitted in cooked mode to prevent terminals that respond to it from hanging up; programs using RAW or CBREAK mode should be careful.

The terminal drivers provide necessary processing for cooked and CBREAK mode output including delay generation for certain special characters and parity generation. Delays are available after backspaces ^H, form feeds ^L, carriage returns ^M, tabs ^I and newlines ^J. The driver will also optionally expand tabs into spaces, where the tab stops are assumed to be set every eight columns, and optionally convert newlines to carriage returns followed by newline. These functions are controlled by bits in the tty flags word; see **Summary** below.

The terminal drivers provide for mapping between upper and lower case on terminals lacking lower case, and for other special processing on deficient terminals.

Finally, in the new terminal driver, there is a output flush character, normally ^O, which sets the LFLUSHO bit in the local mode word, causing subsequent output to be flushed until it is cleared by a program or more input is typed. This character has effect in both cooked and CBREAK modes and causes pending input to be retyped if there is any pending input. An *ioctl* to flush the characters in the input or output queues, TIOCFLUSH, is also available.

Upper case terminals and Hazeltines

If the LCASE bit is set in the tty flags, then all upper-case letters are mapped into the corresponding lower-case letter. The upper-case letter may be generated by preceding it by '^'. Upper case letters are preceded by a '^' when output. In addition, the following escape sequences can be generated on output and accepted on input:

for	^		~	{	}
use	^	^!	^	^(	^)

To deal with Hazeltine terminals, which do not understand that ~ has been made into an ASCII character, the LTILDE bit may be set in the local mode word; in this case the character ~ will be replaced with the character ^ on output.

Flow control.

There are two characters (the stop character, normally ^S, and the start character, normally ^Q) which cause output to be suspended and resumed respectively. Extra stop characters typed when output is already stopped have no effect, unless the start and stop characters are made the same, in which case output resumes.

A bit in the flags word may be set to put the terminal into TANDEM mode. In this mode the system produces a stop character (default ^S) when the input queue is in danger of overflowing, and a start character (default ^Q) when the input has drained sufficiently. This mode is useful when the terminal is actually another machine that obeys those conventions.

Line control and breaks.

There are several *ioctl* calls available to control the state of the terminal line. The TIOCSBRK *ioctl* will set the break bit in the hardware interface causing a break condition to exist; this can be cleared (usually after a delay with *sleep(3)*) by TIOCCBRK. Break conditions in the input are reflected as a null character in RAW mode or as the interrupt character in cooked or CBREAK mode. The TIOCCDTR *ioctl* will clear the data terminal ready condition; it can be set again by TIOCS DTR.

When the carrier signal from the dataset drops (usually because the user has hung up his terminal) a SIGHUP hangup signal is sent to the processes in the distinguished process group of the terminal; this usually causes them to terminate. The SIGHUP can be suppressed by setting the LNOHANG bit in the local state word of the driver. Access to the terminal by other processes is then normally revoked, so any further reads will fail, and programs that read a terminal and test for end-of-file on their input will terminate appropriately.

It is possible to ask that the phone line be hung up on the last close with the TIOCHPCL *ioctl*; this is normally done on the outgoing lines and dialups.

Interrupt characters.

There are several characters that generate interrupts in cooked and CBREAK mode; all are sent to the processes in the control group of the terminal, as if a TIOCGPRP *ioctl* were done to get the process group and then a *killpg(2)* system call were done, except that these characters also flush pending input and output when typed at a terminal (*à la* TIOCFLUSH). The characters shown here are the defaults; the field names in the structures (given below) are also shown. The characters may be changed.

- ^C *t_intrc* (ETX) generates a SIGINT signal. This is the normal way to stop a process which is no longer interesting, or to regain control in an interactive program.
- ^\\ *t_quite* (FS) generates a SIGQUIT signal. This is used to cause a program to terminate and produce a core image, if possible, in the file *core* in the current directory.
- ^Z *t_suspc* (EM) generates a SIGTSTP signal, which is used to suspend the current process group.
- ^Y *t_dsuspc* (SUB) generates a SIGTSTP signal as ^Z does, but the signal is sent when a program attempts to read the ^Y, rather than when it is typed.

Job access control.

When using the new terminal driver, if a process which is not in the distinguished process group of its control terminal attempts to read from that terminal its process group is sent a SIGTTIN signal. This signal normally causes the members of that process group to stop. If, however, the process is ignoring SIGTTIN, has SIGTTIN blocked, or is in the middle of process creation using *vfork(2)*, the read will return -1 and set *errno* to EIO.

When using the new terminal driver with the LTOSTOP bit set in the local modes, a process is prohibited from writing on its control terminal if it is not in the distinguished process group for that terminal. Processes which are holding or ignoring SIGTTOU signals or which are in the middle of a *vfork(2)* are excepted and allowed to produce output. Terminal/window sizes. In order to accommodate terminals and workstations with variable-sized windows, the terminal driver provides a mechanism for obtaining and setting the current terminal size. The driver does not use this information internally, but only stores it and provides a uniform access mechanism. When the size is changed, a SIGWINCH signal is sent to the terminal's process group so that knowledgeable programs may detect size changes. This facility was added in 4.3BSD and is not available in earlier versions of the system.

Summary of modes.

Unfortunately, due to the evolution of the terminal driver, there are 4 different structures which contain various portions of the driver data. The first of these (*sgttyb*) contains that part of the information largely common between version 6 and version 7 UNIX systems. The second contains additional control characters added in version 7. The third is a word of local state added in 4BSD, and the fourth is another structure of special characters added for the new driver. In the future a single structure may be made available to programs which need to access all this information; most programs need not concern themselves with all this state.

Basic modes: sgtty.

The basic *ioctl*s use the structure defined in *<sgtty.h>*:

```
struct sgtyb {
    char    sg_ispeed;
    char    sg_ospeed;
    char    sg_erase;
    char    sg_kill;
    short   sg_flags;
};
```

The *sg_ispeed* and *sg_ospeed* fields describe the input and output speeds of the device according to the following table, which corresponds to the DEC DH-11 interface. If other hardware is used, impossible speed changes are ignored. Symbolic values in the table are as defined in *<sgtty.h>*.

B0	0	(hang up dataphone)
B50	1	50 baud
B75	2	75 baud
B110	3	110 baud
B134	4	134.5 baud
B150	5	150 baud
B200	6	200 baud
B300	7	300 baud
B600	8	600 baud
B1200	9	1200 baud
B1800	10	1800 baud
B2400	11	2400 baud
B4800	12	4800 baud
B9600	13	9600 baud
EXTA	14	External A
EXTB	15	External B

Code conversion and line control required for IBM 2741's (134.5 baud) must be implemented by the user's program. The half-duplex line discipline required for the 202 dataset (1200 baud) is not supplied; full-duplex 212 datasets work fine.

The *sg_erase* and *sg_kill* fields of the argument structure specify the erase and kill characters respectively. (Defaults are DELETE and ^U.)

The *sg_flags* field of the argument structure contains several bits that determine the system's treatment of the terminal:

```
ALLDELAY 0177400 Delay algorithm selection
BSDELAY   0100000 Select backspace delays (not implemented):
BS0       0
BS1       0100000
VTDELAY   0040000 Select form-feed and vertical-tab delays:
FF0       0
FF1       0040000
CRDELAY   0030000 Select carriage-return delays:
CR0       0
CR1       0010000
CR2       0020000
CR3       0030000
TBDELAY   0006000 Select tab delays:
TAB0      0
```

TAB1	0002000
TAB2	0004000
XTABS	0006000
NLDELAY	0001400 Select new-line delays:
NL0	0
NL1	0000400
NL2	0001000
NL3	0001400
EVENP	0000200 Even parity allowed on input
ODDP	0000100 Odd parity allowed on input
RAW	0000040 Raw mode: wake up on all characters, 8-bit interface
CRMOD	0000020 Map CR into LF; output LF as CR-LF
ECHO	0000010 Echo (full duplex)
LCASE	0000004 Map upper case to lower on input and lower to upper on output
CBREAK	0000002 Return each character as soon as typed
TANDEM	0000001 Automatic flow control

The delay bits specify how long transmission stops to allow for mechanical or other movement when certain characters are sent to the terminal. In all cases a value of 0 indicates no delay.

Backspace delays are currently ignored but might be used for Terminet 300's.

If a form-feed/vertical tab delay is specified, it lasts for about 2 seconds.

Carriage-return delay type 1 lasts about .08 seconds and is suitable for the Terminet 300. Delay type 2 lasts about .16 seconds and is suitable for the VT05 and the TI 700. Delay type 3 is suitable for the concept-100 and pads lines to be at least 9 characters at 9600 baud.

New-line delay type 1 is dependent on the current column and is tuned for Teletype model 37's. Type 2 is useful for the VT05 and is about .10 seconds. Type 3 is unimplemented and is 0.

Tab delay type 1 is dependent on the amount of movement and is tuned to the Teletype model 37. Type 3, called XTABS, is not a delay at all but causes tabs to be replaced by the appropriate number of spaces on output.

The flags for even and odd parity control parity checking on input and generation on output in cooked and CBREAK mode (unless LPASS8 is enabled, see below). Even parity is generated on output unless ODDP is set and EVENP is clear, in which case odd parity is generated. Input characters with the wrong parity, as determined by EVENP and ODDP, are ignored in cooked and CBREAK mode.

RAW disables all processing save output flushing with LFLUSHO; full 8 bits of input are given as soon as it is available; all 8 bits are passed on output. A break condition in the input is reported as a null character. If the input queue overflows in raw mode all data in the input and output queues are discarded; this applies to both new and old drivers.

CRMOD causes input carriage returns to be turned into new-lines, and output and echoed new-lines to be output as a carriage return followed by a line feed.

CBREAK is a sort of half-cooked (rare?) mode. Programs can read each character as soon as typed, instead of waiting for a full line; all processing is done except the input editing: character and word erase and line kill, input reprint, and the special treatment of \ and EOT are disabled.

TANDEM mode causes the system to produce a stop character (default ^S) whenever the input queue is in danger of overflowing, and a start character (default ^Q) when the input queue has drained sufficiently. It is useful for flow control when the 'terminal' is really another computer which understands the conventions.

Note: The same “stop” and “start” characters are used for both directions of flow control; the *t_stopc* character is accepted on input as the character that stops output and is produced on output as the character to stop input, and the *t_startc* character is accepted on input as the character that restarts output and is produced on output as the character to restart input.

Basic ioctl

A large number of *ioctl*(2) calls apply to terminals. Some have the general form:

```
#include <sgtty.h>
```

```
ioctl(fildes, code, arg)
```

```
struct sgttyb *arg;
```

The applicable codes are:

- TIOCGETP** Fetch the basic parameters associated with the terminal, and store in the pointed-to *sgttyb* structure.
- TIOCSETP** Set the parameters according to the pointed-to *sgttyb* structure. The interface delays until output is quiescent, then throws away any unread characters, before changing the modes.
- TIOCSETN** Set the parameters like **TIOCSETP** but do not delay or flush input. Input is not preserved, however, when changing to or from RAW.

With the following codes *arg* is ignored.

- TIOCEXCL** Set “exclusive-use” mode: no further opens are permitted until the file has been closed.
- TIOCNXCL** Turn off “exclusive-use” mode.
- TIOCHPCL** When the file is closed for the last time, hang up the terminal. This is useful when the line is associated with an ACU used to place outgoing calls.

With the following codes *arg* is a pointer to an int.

- TIOCGETD** *arg* is a pointer to an int into which is placed the current line discipline number.
- TIOCSETD** *arg* is a pointer to an int whose value becomes the current line discipline number.
- TIOCFUSH** If the int pointed to by *arg* has a zero value, all characters waiting in input or output queues are flushed. Otherwise, the value of the int is for the FREAD and FWRITE bits defined in <sys/file.h>; if the FREAD bit is set, all characters waiting in input queues are flushed, and if the FWRITE bit is set, all characters waiting in output queues are flushed.

The remaining calls are not available in vanilla version 7 UNIX. In cases where arguments are required, they are described; *arg* should otherwise be given as 0.

- TIOCSTI** the argument points to a character which the system pretends had been typed on the terminal.
- TIOCSBRK** the break bit is set in the terminal.
- TIOCCBRK** the break bit is cleared.
- TIOCS DTR** data terminal ready is set.
- TIOCC DTR** data terminal ready is cleared.
- TIOCSTOP** output is stopped as if the “stop” character had been typed.
- TIOCSTART** output is restarted as if the “start” character had been typed.

- TIOCGPRG** *arg* is a pointer to an *int* into which is placed the process group ID of the process group for which this terminal is the control terminal.
- TIOCSPRG** *arg* is a pointer to an *int* which is the value to which the process group ID for this terminal will be set.
- TIOCOUTQ** returns in the *int* pointed to by *arg* the number of characters queued for output to the terminal.
- FIONREAD** returns in the *int* pointed to by *arg* the number of characters immediately readable from the argument descriptor. This works for files, pipes, and terminals.

Tchars

The second structure associated with each terminal specifies characters that are special in both the old and new terminal interfaces: The following structure is defined in `<sys/ioclt.h>`, which is automatically included in `<sgtty.h>`:

```
struct tchars {
    char  t_intrc;      /* interrupt */
    char  t_quitc;      /* quit */
    char  t_startc;     /* start output */
    char  t_stopc;      /* stop output */
    char  t_eofc;       /* end-of-file */
    char  t_brkc;       /* input delimiter (like nl) */
};
```

The default values for these characters are `^C`, `^Q`, `^S`, `^D`, and `-1`. A character value of `-1` eliminates the effect of that character. The `t_brkc` character, by default `-1`, acts like a new-line in that it terminates a 'line,' is echoed, and is passed to the program. The 'stop' and 'start' characters may be the same, to produce a toggle effect. It is probably counterproductive to make other special characters (including erase and kill) identical. The applicable *ioclt* calls are:

TIOCGETC Get the special characters and put them in the specified structure.

TIOCSETC Set the special characters to those given in the structure.

Local mode

The third structure associated with each terminal is a local mode word. The bits of the local mode word are:

LCRTBS	000001 Backspace on erase rather than echoing erase
LPRTERA	000002 Printing terminal erase mode
LCRTERA	000004 Erase character echoes as backspace-space-backspace
LTILDE	000010 Convert <code>~</code> to <code>`</code> on output (for Hazeltine terminals)
LMDMBUF	000020 Stop/start output when carrier drops
LLITOUT	000040 Suppress output translations
LTOSTOP	000100 Send SIGTTOU for background output
LFLUSHO	000200 Output is being flushed
LNOHANG	000400 Don't send hangup when carrier drops
LETXACK	001000 Diablo style buffer hacking (unimplemented)
LCRTKIL	002000 BS-space-BS erase entire line on line kill
LPASS8	004000 Pass all 8 bits through on input, in any mode
LCTLECH	010000 Echo input control chars as <code>^X</code> , delete as <code>^?</code>
LPENDIN	020000 Retype pending input at next read or input character
LDECCTQ	040000 Only <code>^Q</code> restarts output after <code>^S</code> , like DEC systems
LNOFLSH	100000 Inhibit flushing of pending I/O when an interrupt character is typed.

The applicable *ioctl* functions are:

- TIOCLBIS** *arg* is a pointer to an *int* whose value is a mask containing the bits to be set in the local mode word.
- TIOCLBIC** *arg* is a pointer to an *int* whose value is a mask containing the bits to be cleared in the local mode word.
- TIOCLSET** *arg* is a pointer to an *int* whose value is stored in the local mode word.
- TIOCLGET** *arg* is a pointer to an *int* into which the current local mode word is placed.

Local special chars

The final control structure associated with each terminal is the *lchars* structure which defines control characters for the new terminal driver. Its structure is:

```
struct lchars {
    char  t_suspc;      /* stop process signal */
    char  t_dsuspc;     /* delayed stop process signal */
    char  t_rprntc;     /* reprint line */
    char  t_flushc;     /* flush output (toggles) */
    char  t_werasc;     /* word erase */
    char  t_lnextc;     /* literal next character */
};
```

The default values for these characters are ^Z, ^Y, ^R, ^O, ^W, and ^V. A value of -1 disables the character.

The applicable *ioctl* functions are:

- TIOCSLTC** *arg* is a pointer to an *lchars* structure which defines the new local special characters.
- TIOCG LTC** *arg* is a pointer to an *lchars* structure into which is placed the current set of local special characters.

Window/terminal sizes

Each terminal has provision for storage of the current terminal or window size in a *winsize* structure, with format:

```
struct winsize {
    unsigned short ws_row;      /* rows, in characters */
    unsigned short ws_col;      /* columns, in characters */
    unsigned short ws_xpixel;   /* horizontal size, pixels */
    unsigned short ws_ypixel;   /* vertical size, pixels */
};
```

A value of 0 in any field is interpreted as "undefined;" the entire structure is zeroed on final close.

The applicable *ioctl* functions are:

- TIOCGWINSZ**
arg is a pointer to a *struct winsize* into which will be placed the current terminal or window size information.
- TIOCSWINSZ**
arg is a pointer to a *struct winsize* which will be used to set the current terminal or window size information. If the new information is different than the old information, a SIGWINCH signal will be sent to the terminal's process group.

FILES

/dev/tty
/dev/tty*
/dev/console

SEE ALSO

csh(1), stty(1), tset(1), ioctl(2), sigvec(2), stty(3C), getty(8)

NAME

tu - VAX-11/730 and VAX-11/750 TU58 console cassette interface

SYNOPSIS

options MRSP (for VAX-11/750's with an MRSP prom)

DESCRIPTION

The *tu* interface provides access to the VAX 11/730 and 11/750 TU58 console cassette drive(s).

The interface supports only block i/o to the TU58 cassettes. The devices are normally manipulated with the *arff*(8V) program using the "f" and "m" options.

The device driver is automatically included when a system is configured to run on an 11/730 or 11/750.

The TU58 on an 11/750 uses the Radial Serial Protocol (RSP) to communicate with the cpu over a serial line. This protocol is inherently unreliable as it has no flow control measures built in. On an 11/730 the Modified Radial Serial Protocol is used. This protocol incorporates flow control measures which insure reliable data transfer between the cpu and the device. Certain 11/750's have been modified to use the MRSP prom used in the 11/730. To reliably use the console TU58 on an 11/750 under UNIX, the MRSP prom is required. For those 11/750's without an MRSP prom, an unreliable but often useable interface has been developed. This interface uses an assembly language "pseudo-dma" routine to minimize the receiver interrupt service latency. To include this code in the system, the configuration must not specify the system will run on an 11/730 or use an MRSP prom. This unfortunately makes it impossible to configure a single system which will properly handle TU58's on both an 11/750 and an 11/730 (unless both machines have MRSP prompts).

FILES

/dev/tu0

/dev/tu1 (only on a VAX-11/730)

SEE ALSO

arff(8V)

DIAGNOSTICS

tu%d: no bp, active %d. A transmission complete interrupt was received with no outstanding i/o request. This indicates a hardware problem.

tu%d protocol error, state=%s, op=%x, cnt=%d, block=%d. The driver entered an illegal state. The information printed indicates the illegal state, operation currently being executed, the i/o count, and the block number on the cassette.

tu%d receive state error, state=%s, byte=%x. The driver entered an illegal state in the receiver finite state machine. The state is shown along with the control byte of the received packet.

tu%d: read stalled. A timer watching the controller detected no interrupt for an extended period while an operation was outstanding. This usually indicates that one or more receiver interrupts were lost and the transfer is restarted (11/750 only).

tu%d: hard error bn%d, pk_mod %o. The device returned a status code indicating a hard error. The actual error code is shown in octal. No retries are attempted by the driver.

BUGS

The VAX-11/750 console interface without MRSP prom is unuseable while the system is multi-user; it should be used only with the system running single-user and, even then, with caution.

NAME

uda - UDA-50 disk controller interface

SYNOPSIS

controller uda0 at uba0 csr 0172150 vector udintr
disk ra0 at uda0 drive 0

DESCRIPTION

This is a driver for the DEC UDA-50 disk controller and for other compatible controllers. The UDA-50 communicates with the host through a packet oriented protocol termed the Mass Storage Control Protocol (MSCP). Consult the file *<vax/mscp.h>* for a detailed description of this protocol.

Files with minor device numbers 0 through 7 refer to various portions of drive 0; minor devices 8 through 15 refer to drive 1, etc. The standard device names begin with "ra" followed by the drive number and then a letter a-h for partitions 0-7 respectively. The character ? stands here for a drive number in the range 0-7.

The block files access the disk via the system's normal buffering mechanism and may be read and written without regard to physical disk records. There is also a 'raw' interface which provides for direct transmission between the disk and the user's read or write buffer. A single read or write call results in exactly one I/O operation and therefore raw I/O is considerably more efficient when many words are transmitted. The names of the raw files conventionally begin with an extra 'r.'

In raw I/O counts should be a multiple of 512 bytes (a disk sector). Likewise *seek* calls should specify a multiple of 512 bytes.

DISK SUPPORT

This driver configures the drive type of each drive when it is first opened. A partition table in the driver is required for each type of disk. The origin and size (in sectors) of the pseudo-disks on each drive are shown below. Not all partitions begin on cylinder boundaries, as on other drives, because previous drivers used one partition table for all drive types. Variants of the partition tables are common; check the driver and the file */etc/disktab(disktab(5))* for other possibilities.

RC25 partitions

disk	start	length
ra?a	0	15884
ra?b	15884	10032
ra?c	0	50902
ra?g	25916	24986

RD52 partitions

disk	start	length
ra?a	0	15884
ra?b	15884	9766
ra?c	0	60480
ra?g	25650	34830

RD53 partitions

disk	start	length
ra?a	0	15884
ra?b	15884	33440
ra?c	0	138672
ra?g	49324	89348
ra?h	15884	122788

RA60 partitions

disk	start	length
ra?a	0	15884

ra?b	15884	33440	
ra?c	0	400176	
ra?d	49324	82080	same as 4.2BSD ra?g
ra?e	131404	268772	same as 4.2BSD ra?h
ra?f	49324	350852	
ra?g	242606	157570	
ra?h	49324	193282	

RA80 partitions

disk	start	length	
ra?a	0	15884	
ra?b	15884	33440	
ra?c	0	242606	
ra?e	49324	193282	same as old Berkeley ra?g
ra?f	49324	82080	same as 4.2BSD ra?g
ra?g	49910	192696	
ra?h	131404	111202	same as 4.2BSD

RA81 partitions

disk	start	length	
ra?a	0	15884	
ra?b	16422	66880	
ra?c	0	891072	
ra?d	375564	15884	
ra?e	391986	307200	
ra?f	699720	191352	
ra?g	375564	515508	
ra?h	83538	291346	

RA81 partitions with 4.2BSD-compatible partitions

disk	start	length	
ra?a	0	15884	
ra?b	16422	66880	
ra?c	0	891072	
ra?d	49324	82080	same as 4.2BSD ra?g
ra?e	131404	759668	same as 4.2BSD ra?h
ra?f	412490	478582	same as 4.2BSD ra?f
ra?g	375564	515508	
ra?h	83538	291346	

The ra?a partition is normally used for the root file system, the ra?b partition as a paging area, and the ra?c partition for pack-pack copying (it maps the entire disk).

FILES

/dev/ra[0-9][a-f]
/dev/rra[0-9][a-f]

DIAGNOSTICS

uda: ubinfo %x. (VAX 11/750 only.) When allocating UNIBUS resources, the driver found it already had resources previously allocated. This indicates a bug in the driver.

udasa %o, state %d. (Additional status information given after a hard i/o error.) The values of the UDA-50 status register and the internal driver state are printed.

uda%d: random interrupt ignored. An unexpected interrupt was received (e.g. when no i/o was pending). The interrupt is ignored.

uda%d: interrupt in unknown state %d ignored. An interrupt was received when the driver was in an unknown internal state. Indicates a hardware problem or a driver bug.

uda%d: fatal error (%o). The UDA-50 indicated a "fatal error" in the status returned to the host. The contents of the status register are displayed.

OFFLINE. (Additional status information given after a hard i/o error.) A hard i/o error occurred because the drive was not on-line.

status %o. (Additional status information given after a hard i/o error.) The status information returned from the UDA-50 is tacked onto the end of the hard error message printed on the console.

uda: unknown packet. An MSCP packet of unknown type was received from the UDA-50. Check the cabling to the controller.

The following errors are interpretations of MSCP error messages returned by the UDA-50 to the host.

uda%d: %s error, controller error, event 0%o.

uda%d: %s error, host memory access error, event 0%o, addr 0%o.

uda%d: %s error, disk transfer error, unit %d.

uda%d: %s error, SDI error, unit %d, event 0%o.

uda%d: %s error, small disk error, unit %d, event 0%o, cyl %d.

uda%d: %s error, unknown error, unit %d, format 0%o, event 0%o.

BUGS

The partition tables attempt to combine compatibility with previous drivers and functionality; this is impossible. The best solution would be to read the partition tables off the drive.

NAME

udp – Internet User Datagram Protocol

SYNOPSIS

```
#include <sys/socket.h>
#include <netinet/in.h>

s = socket(AF_INET, SOCK_DGRAM, 0);
```

DESCRIPTION

UDP is a simple, unreliable datagram protocol which is used to support the SOCK_DGRAM abstraction for the Internet protocol family. UDP sockets are connectionless, and are normally used with the *sendto* and *recvfrom* calls, though the *connect(2)* call may also be used to fix the destination for future packets (in which case the *recv(2)* or *read(2)* and *send(2)* or *write(2)* system calls may be used).

UDP address formats are identical to those used by TCP. In particular UDP provides a port identifier in addition to the normal Internet address format. Note that the UDP port space is separate from the TCP port space (i.e. a UDP port may not be “connected” to a TCP port). In addition broadcast packets may be sent (assuming the underlying network supports this) by using a reserved “broadcast address”; this address is network interface dependent.

Options at the IP transport level may be used with UDP; see *ip(4P)*.

DIAGNOSTICS

A socket operation may fail with one of the following errors returned:

- [EISCONN] when trying to establish a connection on a socket which already has one, or when trying to send a datagram with the destination address specified and the socket is already connected;
- [ENOTCONN] when trying to send a datagram, but no destination address is specified, and the socket hasn't been connected;
- [ENOBUFFS] when the system runs out of memory for an internal data structure;
- [EADDRINUSE] when an attempt is made to create a socket with a port which has already been allocated;
- [EADDRNOTAVAIL] when an attempt is made to create a socket with a network address for which no network interface exists.

SEE ALSO

getsockopt(2), recv(2), send(2), socket(2), intro(4N), inet(4F), ip(4P)

NAME

up – unibus storage module controller/drives

SYNOPSIS

controller sc0 at uba? csr 0176700 vector upintr
disk up0 at sc0 drive 0

DESCRIPTION

This is a generic UNIBUS storage module disk driver. It is specifically designed to work with the Emulex SC-21 and SC-31 controllers. It can be easily adapted to other controllers (although bootstrapping will not necessarily be directly possible.)

Files with minor device numbers 0 through 7 refer to various portions of drive 0; minor devices 8 through 15 refer to drive 1, etc. The standard device names begin with "up" followed by the drive number and then a letter a-h for partitions 0-7 respectively. The character ? stands here for a drive number in the range 0-7.

The block files access the disk via the system's normal buffering mechanism and may be read and written without regard to physical disk records. There is also a 'raw' interface which provides for direct transmission between the disk and the user's read or write buffer. A single read or write call results in exactly one I/O operation and therefore raw I/O is considerably more efficient when many words are transmitted. The names of the raw files conventionally begin with an extra 'r.'

In raw I/O counts should be a multiple of 512 bytes (a disk sector). Likewise *seek* calls should specify a multiple of 512 bytes.

DISK SUPPORT

The driver interrogates the controller's holding register to determine the type of drive attached. The driver recognizes seven different drives: CDC 9762, CDC 9766, AMPEX DM980, AMPEX 9300, AMPEX Capricorn, FUJITSU 160, and FUJITSU Eagle (the Eagle is not supported by the SC-21). The origin and size of the pseudo-disks on each drive are as follows:

CDC 9762 partitions

disk	start	length	cyls
hp?a	0	15884	0-99
hp?b	16000	33440	100-309
hp?c	0	131680	0-822
hp?d	49600	15884	309-408
hp?e	65440	55936	409-758
hp?f	121440	10080	759-822
hp?g	49600	82080	309-822

CDC 9766 300M drive partitions:

disk	start	length	cyl
up?a	0	15884	0-26
up?b	16416	33440	27-81
up?c	0	500384	0-822
up?d	341696	15884	562-588
up?e	358112	55936	589-680
up?f	414048	861760	681-822
up?g	341696	158528	562-822
up?h	49856	291346	82-561

AMPEX DM980 partitions

disk	start	length	cyls
hp?a	0	15884	0-99
hp?b	16000	33440	100-309

hp?c	0	131680	0-822
hp?d	49600	15884	309-408
hp?e	65440	55936	409-758
hp?f	121440	10080	759-822
hp?g	49600	82080	309-822

AMPEX 9300 300M drive partitions:

disk	start	length	cyl
up?a	0	15884	0-26
up?b	16416	33440	27-81
up?c	0	495520	0-814
up?d	341696	15884	562-588
up?e	358112	55936	589-680
up?f	414048	81312	681-814
up?g	341696	153664	562-814
up?h	49856	291346	82-561

AMPEX Capricorn 330M drive partitions:

disk	start	length	cyl
hp?a	0	15884	0-31
hp?b	16384	33440	32-97
hp?c	0	524288	0-1023
hp?d	342016	15884	668-699
hp?e	358400	55936	700-809
hp?f	414720	109408	810-1023
hp?g	342016	182112	668-1023
hp?h	50176	291346	98-667

FUJITSU 160M drive partitions:

disk	start	length	cyl
up?a	0	15884	0-49
up?b	16000	33440	50-154
up?c	0	263360	0-822
up?d	49600	15884	155-204
up?e	65600	55936	205-379
up?f	121600	141600	380-822
up?g	49600	213600	155-822

FUJITSU Eagle partitions

disk	start	length	cyls
hp?a	0	15884	0-16
hp?b	16320	66880	17-86
hp?c	0	808320	0-841
hp?d	375360	15884	391-407
hp?e	391680	55936	408-727
hp?f	698880	109248	728-841
hp?g	375360	432768	391-841
hp?h	83520	291346	87-390

It is unwise for all of these files to be present in one installation, since there is overlap in addresses and protection becomes a sticky matter. The up?a partition is normally used for the root file system, the up?b partition as a paging area, and the up?c partition for pack-pack copying (it maps the entire disk). On 160M drives the up?g partition maps the rest of the pack. On other drives both up?g and up?h are used to map the remaining cylinders.

FILES

/dev/up[0-7][a-h]	block files
/dev/rup[0-7][a-h]	raw files

SEE ALSO

hk(4), hp(4), uda(4)

DIAGNOSTICS

up%d%c: hard error sn%d cs2=%b er1=%b er2=%b. An unrecoverable error occurred during transfer of the specified sector in the specified disk partition. The contents of the cs2, er1 and er2 registers are printed in octal and symbolically with bits decoded. The error was either unrecoverable, or a large number of retry attempts (including offset positioning and drive recalibration) could not recover the error.

up%d: write locked. The write protect switch was set on the drive when a write was attempted. The write operation is not recoverable.

up%d: not ready. The drive was spun down or off line when it was accessed. The i/o operation is not recoverable.

up%d: not ready (flakey). The drive was not ready, but after printing the message about being not ready (which takes a fraction of a second) was ready. The operation is recovered if no further errors occur.

up%d%c: soft ecc sn%d. A recoverable ECC error occurred on the specified sector of the specified disk partition. This happens normally a few times a week. If it happens more frequently than this the sectors where the errors are occurring should be checked to see if certain cylinders on the pack, spots on the carriage of the drive or heads are indicated.

sc%d: lost interrupt. A timer watching the controller detecting no interrupt for an extended period while an operation was outstanding. This indicates a hardware or software failure. There is currently a hardware/software problem with spinning down drives while they are being accessed which causes this error to occur. The error causes a UNIBUS reset, and retry of the pending operations. If the controller continues to lose interrupts, this error will recur a few seconds later.

BUGS

In raw I/O *read* and *write(2)* truncate file offsets to 512-byte block boundaries, and *write* scribbles on the tail of incomplete blocks. Thus, in programs that are likely to access raw devices, *read*, *write* and *lseek(2)* should always deal in 512-byte multiples.

A program to analyze the logged error information (even in its present reduced form) is needed.

The partition tables for the file systems should be read off of each pack, as they are never quite what any single installation would prefer, and this would make packs more portable.

NAME

ut – UNIBUS TU45 tri-density tape drive interface

SYNOPSIS

controller *ut0* at uba0 csr 0172440 vector *utintr*
tape *tj0* at *ut0* drive 0

DESCRIPTION

The *ut* interface provides access to a standard tape drive interface as describe in *mtio(4)*. Hardware implementing this on the VAX is typified by the System Industries SI 9700 tape subsystem. Tapes may be read or written at 800, 1600, and 6250 bpi.

SEE ALSO

mt(1), *mtio(4)*

DIAGNOSTICS

tj%d: no write ring. An attempt was made to write on the tape drive when no write ring was present; this message is written on the terminal of the user who tried to access the tape.

tj%d: not online. An attempt was made to access the tape while it was offline; this message is written on the terminal of the user who tried to access the tape.

tj%d: can't change density in mid-tape. An attempt was made to write on a tape at a different density than is already recorded on the tape. This message is written on the terminal of the user who tried to switch the density.

ut%d: soft error bn%d cs1=%b er=%b cs2=%b ds=%b. The formatter indicated a corrected error at a density other than 800bpi. The data transferred is assumed to be correct.

ut%d: hard error bn%d cs1=%b er=%b cs2=%b ds=%b. A tape error occurred at block *bn*. Any error is fatal on non-raw tape; when possible the driver will have retried the operation which failed several times before reporting the error.

tj%d: lost interrupt. A tape operation did not complete within a reasonable time, most likely because the tape was taken off-line during rewind or lost vacuum. The controller should, but does not, give an interrupt in these cases. The device will be made available again after this message, but any current open reference to the device will return an error as the operation in progress aborts.

BUGS

If any non-data error is encountered on non-raw tape, it refuses to do anything more until closed.

NAME

uu – TU58/DECtape II UNIBUS cassette interface

SYNOPSIS

options UUDMA

device uu0 at uba0 csr 0176500 **vector** uurintr uuxintr

DESCRIPTION

The **uu** device provides access to dual DEC TU58 tape cartridge drives connected to the UNIBUS via a DL11-W interface module.

The interface supports only block i/o to the TU58 cassettes. The drives are normally manipulated with the *arff*(8V) program using the “m” and “f” options.

The driver provides for an optional write and verify (read after write) mode that is activated by specifying the “a” device.

The TU58 is treated as a single device by the system even though it has two separate drives, “uu0” and “uu1”. If there is more than one TU58 unit on a system, the extra drives are named “uu2”, “uu3” etc.

NOTES

Assembly language code to assist the driver in handling the receipt of data (using a pseudo-dma approach) should be included when using this driver; specify “options UUDMA” in the configuration file.

ERRORS

The following errors may be returned:

[ENXIO] Nonexistent drive (on open); offset is too large or bad (undefined) ioctl code.

[EIO] Open failed, the device could not be reset.

[EBUSY] Drive in use.

FILES

/dev/uu?

/dev/uu?a

SEE ALSO

tu(4), arff(8V)

DIAGNOSTICS

uu%d: no bp, active %d. A transmission complete interrupt was received with no outstanding i/o request. This indicates a hardware problem.

uu%d protocol error, state=%s, op=%x, cnt=%d, block=%d. The driver entered an illegal state. The information printed indicates the illegal state, the operation currently being executed, the i/o count, and the block number on the cassette.

uu%d: break received, transfer restarted. The TU58 was sending a continuous break signal and had to be reset. This may indicate a hardware problem, but the driver will attempt to recover from the error.

uu%d receive state error, state=%s, byte=%x. The driver entered an illegal state in the receiver finite state machine. The state is shown along with the control byte of the received packet.

uu%d: read stalled. A timer watching the controller detected no interrupt for an extended period while an operation was outstanding. This usually indicates that one or more receiver interrupts were lost and the transfer is restarted.

uu%d: hard error bn%d, pk_mod %o. The device returned a status code indicating a hard error. The actual error code is shown in octal. No retries are attempted by the driver.

NAME

va - Benson-Varian interface

SYNOPSIS

controller va0 at uba0 csr 0164000 vector vaintr
disk vz0 at va0 drive 0

DESCRIPTION

(NOTE: the configuration description, while counter-intuitive, is actually as shown above.)

The Benson-Varian printer/plotter is normally used with the line printer system. This description is designed for those who wish to drive the Benson-Varian directly.

In print mode, the Benson-Varian uses a modified ASCII character set. Most control characters print various non-ASCII graphics such as daggers, sigmas, copyright symbols, etc. Only LF and FF are used as format effectors. LF acts as a newline, advancing to the beginning of the next line, and FF advances to the top of the next page.

In plot mode, the Benson-Varian prints one raster line at a time. An entire raster line of bits (2112 bits = 264 bytes) is sent, and then the Benson-Varian advances to the next raster line.

Note: The Benson-Varian must be sent an even number of bytes. If an odd number is sent, the last byte will be lost. Nulls can be used in print mode to pad to an even number of bytes.

To use the Benson-Varian yourself, you must realize that you cannot open the device, */dev/va0* if there is a daemon active. You can see if there is an active daemon by doing a *lpq(1)* and seeing if there are any files being printed. Printing should be turned off using *lpc(8)*.

To set the Benson-Varian into plot mode include the file *<sys/vcmd.h>* and use the following *ioctl(2)* call

```
ioctl(fileno(va), VSETSTATE, plotmd);
```

where *plotmd* is defined to be

```
int plotmd[] = { VPLOT, 0, 0 };
```

and *va* is the result of a call to *fopen* on *stdio*. When you finish using the Benson-Varian in plot mode you should advance to a new page by sending it a FF after putting it back into print mode, i.e. by

```
int prtm[] = { VPRINT, 0, 0 };
...
fflush(va);
ioctl(fileno(va), VSETSTATE, prtm);
write(fileno(va), "\f\0", 2);
```

FILES

/dev/va0

SEE ALSO

vfont(5), *lpr(1)*, *lpd(8)*, *vp(4)*

DIAGNOSTICS

The following error numbers are significant at the time the device is opened.

[ENXIO] The device is already in use.

[EIO] The device is offline.

The following message may be printed on the console.

va%d: npr timeout. The device was not able to get data from the UNIBUS within the timeout period, most likely because some other device was hogging the bus. (But see **BUGS** below).

P
R
M 4

BUGS

The l's (one's) and l's (lower-case el's) in the Benson-Varian's standard character set look very similar; caution is advised.

The interface hardware is rumored to have problems which can play havoc with the UNIBUS. We have intermittent minor problems on the UNIBUS where our *va* lives, but haven't ever been able to pin them down completely.

NAME

vp - Versatec interface

SYNOPSIS

device vp0 at uba0 csr 0177510 vector vpintr vpintr

DESCRIPTION

The Versatec printer/plotter is normally used with the line printer system. This description is designed for those who wish to drive the Versatec directly.

To use the Versatec yourself, you must realize that you cannot open the device, */dev/vp0* if there is a daemon active. You can see if there is a daemon active by doing a *lpq(1)*, and seeing if there are any files being sent. Printing should be turned off using *lpc(8)*.

To set the Versatec into plot mode you should include *<sys/vcmd.h>* and use the *ioctl(2)* call

```
ioctl(fileno(vp), VSETSTATE, plotmd);
```

where *plotmd* is defined to be

```
int plotmd[] = { VPLOT, 0, 0 };
```

and *vp* is the result of a call to *fopen* on *stdio*. When you finish using the Versatec in plot mode you should eject paper by sending it a EOT after putting it back into print mode, i.e. by

```
int prtm[] = { VPRINT, 0, 0 };
```

```
...
```

```
fflush(vp);
```

```
ioctl(fileno(vp), VSETSTATE, prtm);
```

```
write(fileno(vp), "\04", 1);
```

FILES

/dev/vp0

SEE ALSO

vfont(5), *lpr(1)*, *lpd(8)*, *vtroff(1)*, *va(4)*

DIAGNOSTICS

The following error numbers are significant at the time the device is opened.

[ENXIO] The device is already in use.

[EIO] The device is offline.

BUGS

The configuration part of the driver assumes that the device is set up to vector print mode through 0174 and plot mode through 0200. As the configuration program can't be sure which vector interrupted at boot time, we specify that it has two interrupt vectors, and if an interrupt comes through 0200 it is reset to 0174. This is safe for devices with one or two vectors at these two addresses. Other configurations with 2 vectors may require changes in the driver.

NAME

vv – Proteon proNET 10 Megabit ring

SYNOPSIS

device vv0 at uba0 csr 0161000 vector vvrintr vxint

DESCRIPTION

The vv interface provides access to a 10 Mb/s Proteon proNET ring network.

The network address of the interface must be specified with an SIOCSIFADDR ioctl before data can be transmitted or received. It is only permissible to change the network address while the interface is marked "down".

The host's hardware address is discovered by putting the interface in digital loopback mode (not joining the ring) and sending a broadcast packet from which the hardware address is extracted.

Transmit timeouts are detected through use of a watchdog routine. Lost input interrupts are checked for when packets are sent out.

If the installation is running CTL boards which use the old broadcast address of 0 instead of the new address of 0xff, the define OLD_BROADCAST should be specified in the driver.

The driver can use "trailer" encapsulation to minimize copying data on input and output. This may be disabled, on a per-interface basis, by setting the IFF_NOTRAILERS flag with an SIOCSIFFLAGS ioctl.

DIAGNOSTICS

vv%d: host %d. The software announces the host address discovered during autoconfiguration.

vv%d: can't initialize. The software was unable to discover the address of this interface, so it deemed "dead" will not be enabled.

vv%d: error vvcsr=%b. The hardware indicated an error on the previous transmission.

vv%d: output timeout. The token timer has fired and the token will be recreated.

vv%d: error vvcsr=%b. The hardware indicated an error in reading a packet off the ring.

en%d: can't handle af%d. The interface was handed a message with addresses formatted in an unsuitable address family; the packet was dropped.

vv%d: vs_olen=%d. The ring output routine has been handed a message with a preposterous length. This results in an immediate *panic: vs_olen*.

SEE ALSO

intro(4N), inet(4F)

BUGS

The encapsulation of trailer packets in the 4.2BSD version of this driver was incorrect (the packet type was in VAX byte order). As a result, the trailer encapsulation in this version is not compatible with the 4.2BSD VAX version.

NAME

a.out – assembler and link editor output

SYNOPSIS

```
#include <a.out.h>
```

DESCRIPTION

A.out is the output file of the assembler *as*(1) and the link editor *ld*(1). Both programs make *a.out* executable if there were no errors and no unresolved external references. Layout information as given in the include file for the VAX-11 is:

```
/*
 * Header prepended to each a.out file.
 */
struct exec {
    long    a_magic; /* magic number */
    unsigned a_text; /* size of text segment */
    unsigned a_data; /* size of initialized data */
    unsigned a_bss; /* size of uninitialized data */
    unsigned a_syms; /* size of symbol table */
    unsigned a_entry; /* entry point */
    unsigned a_trsize; /* size of text relocation */
    unsigned a_drsize; /* size of data relocation */
};

#define OMAGIC 0407 /* old impure format */
#define NMAGIC 0410 /* read-only text */
#define ZMAGIC 0413 /* demand load format */

/*
 * Macros which take exec structures as arguments and tell whether
 * the file has a reasonable magic number or offsets to text | symbols | strings.
 */
#define N_BADMAG(x) \
    (((x).a_magic)!=OMAGIC && ((x).a_magic)!=NMAGIC && ((x).a_magic)!=ZMAGIC)

#define N_TXTOFF(x) \
    ((x).a_magic==ZMAGIC ? 1024 : sizeof(struct exec))
#define N_SYMOFF(x) \
    (N_TXTOFF(x) + (x).a_text + (x).a_data + (x).a_trsize + (x).a_drsize)
#define N_STROFF(x) \
    (N_SYMOFF(x) + (x).a_syms)
```

The file has five sections: a header, the program text and data, relocation information, a symbol table and a string table (in that order). The last three may be omitted if the program was loaded with the '-s' option of *ld* or if the symbols and relocation have been removed by *strip*(1).

In the header the sizes of each section are given in bytes. The size of the header is not included in any of the other sizes.

When an *a.out* file is executed, three logical segments are set up: the text segment, the data segment (with uninitialized data, which starts off as all 0, following initialized), and a stack. The text segment begins at 0 in the core image; the header is not loaded. If the magic number in the header is OMAGIC (0407), it indicates that the text segment is not to be write-protected and shared, so the data segment is immediately contiguous with the text segment. This is the oldest kind of executable program and is rarely used. If the magic number

is NMAGIC (0410) or ZMAGIC (0413), the data segment begins at the first 0 mod 1024 byte boundary following the text segment, and the text segment is not writable by the program; if other processes are executing the same file, they will share the text segment. For ZMAGIC format, the text segment begins at a 0 mod 1024 byte boundary in the *a.out* file, the remaining bytes after the header in the first block are reserved and should be zero. In this case the text and data sizes must both be multiples of 1024 bytes, and the pages of the file will be brought into the running image as needed, and not pre-loaded as with the other formats. This is especially suitable for very large programs and is the default format produced by *ld*(1).

The stack will occupy the highest possible locations in the core image, growing downwards from *USRSTACK* (from *<machine/vmparam.h>*). The stack is automatically extended as required. The data segment is only extended as requested by *brk*(2).

After the header in the file follow the text, data, text relocation data relocation, symbol table and string table in that order. The text begins at the byte 1024 in the file for ZMAGIC format or just after the header for the other formats. The *N_TXTOFF* macro returns this absolute file position when given the name of an exec structure as argument. The data segment is contiguous with the text and immediately followed by the text relocation and then the data relocation information. The symbol table follows all this; its position is computed by the *N_SYMOFF* macro. Finally, the string table immediately follows the symbol table at a position which can be gotten easily using *N_STROFF*. The first 4 bytes of the string table are not used for string storage, but rather contain the size of the string table; this size *INCLUDES* the 4 bytes, the minimum string table size is thus 4.

The layout of a symbol table entry and the principal flag values that distinguish symbol types are given in the include file as follows:

```
/*
 * Format of a symbol table entry.
 */
struct nlist {
    union {
        char    *n_name; /* for use when in-core */
        long    n_strx;  /* index into file string table */
    } n_un;
    unsigned char n_type; /* type flag, i.e. N_TEXT etc; see below */
    char          n_other;
    short         n_desc; /* see <stab.h> */
    unsigned      n_value; /* value of this symbol (or offset) */
};
#define n_hash    n_desc /* used internally by ld */

/*
 * Simple values for n_type.
 */
#define N_UNDF    0x0    /* undefined */
#define N_ABS     0x2    /* absolute */
#define N_TEXT    0x4    /* text */
#define N_DATA    0x6    /* data */
#define N_BSS     0x8    /* bss */
#define N_COMM    0x12   /* common (internal to ld) */
#define N_FN      0x1f   /* file name symbol */

#define N_EXT     01     /* external bit, or'ed in */
#define N_TYPE    0x1e   /* mask for all the type bits */
```

```

/*
 * Other permanent symbol table entries have some of the N_STAB bits set.
 * These are given in <stab.h>
 */
#define N_STAB      0xe0      /* if any of these bits set, don't discard */

```

```

/*
 * Format for namelist values.
 */
#define N_FORMAT "%08x"

```

In the *a.out* file a symbol's `n_un.n_strx` field gives an index into the string table. A `n_strx` value of 0 indicates that no name is associated with a particular symbol table entry. The field `n_un.n_name` can be used to refer to the symbol name only if the program sets this up using `n_strx` and appropriate data from the string table.

If a symbol's type is undefined external, and the value field is non-zero, the symbol is interpreted by the loader *ld* as the name of a common region whose size is indicated by the value of the symbol.

The value of a byte in the text or data which is not a portion of a reference to an undefined external symbol is exactly that value which will appear in memory when the file is executed. If a byte in the text or data involves a reference to an undefined external symbol, as indicated by the relocation information, then the value stored in the file is an offset from the associated external symbol. When the file is processed by the link editor and the external symbol becomes defined, the value of the symbol will be added to the bytes in the file.

If relocation information is present, it amounts to eight bytes per relocatable datum as in the following structure:

```

/*
 * Format of a relocation datum.
 */
struct relocation_info {
    int      r_address;      /* address which is relocated */
    unsigned r_symbolnum:24, /* local symbol ordinal */
    r_pcrel:1,               /* was relocated pc relative already */
    r_length:2,              /* 0=byte, 1=word, 2=long */
    r_extern:1,              /* does not include value of sym referenced */
    :4;                     /* nothing, yet */
};

```

There is no relocation information if `a_trsize+a_drsize==0`. If `r_extern` is 0, then `r_symbolnum` is actually a `n_type` for the relocation (i.e. `N_TEXT` meaning relative to segment text origin.)

SEE ALSO

`adb(1)`, `as(1)`, `ld(1)`, `nm(1)`, `dbx(1)`, `stab(5)`, `strip(1)`

BUGS

Not having the size of the string table in the header is a loss, but expanding the header size would have meant stripped executable file incompatibility, and we couldn't hack this just now.

NAME

acct - execution accounting file

SYNOPSIS

```
#include <sys/acct.h>
```

DESCRIPTION

The `acct(2)` system call arranges for entries to be made in an accounting file for each process that terminates. The accounting file is a sequence of entries whose layout, as defined by the include file is:

```
/*
 * Copyright (c) 1982 Regents of the University of California.
 * All rights reserved. The Berkeley software License Agreement
 * specifies the terms and conditions for redistribution.
 *
 *    @(#)acct.h    6.4 (Berkeley) 10/28/85
 */

/*
 * Accounting structures;
 * these use a comp_t type which is a 3 bits base 8
 * exponent, 13 bit fraction "floating point" number.
 * Units are 1/AHZ seconds.
 */
typedef u_short comp_t;

struct acct
{
    char      ac_comm[10]; /* Accounting command name */
    comp_t    ac_utime;    /* Accounting user time */
    comp_t    ac_stime;    /* Accounting system time */
    comp_t    ac_etime;    /* Accounting elapsed time */
    time_t    ac_btime;    /* Beginning time */
    uid_t     ac_uid;      /* Accounting user ID */
    gid_t     ac_gid;      /* Accounting group ID */
    short     ac_mem;      /* average memory usage */
    comp_t    ac_io;       /* number of disk IO blocks */
    dev_t     ac_tty;      /* control typewriter */
    char      ac_flag;     /* Accounting flag */
};

#define AFORK    0001 /* has executed fork, but no exec */
#define ASU      0002 /* used super-user privileges */
#define ACOMPAT  0004 /* used compatibility mode */
#define ACORE    0010 /* dumped core */
#define AXSIG    0020 /* killed by a signal */

/*
 * 1/AHZ is the granularity of the data encoded in the various
 * comp_t fields. This is not necessarily equal to hz.
 */
#define AHZ 64

#ifndef KERNEL
```

```
struct acct      acctbuf;  
struct inode     *acctp;  
#endif
```

If the process was created by an *execve(2)*, the first 10 characters of the filename appear in *ac_comm*. The accounting flag contains bits indicating whether *execve(2)* was ever accomplished, and whether the process ever had super-user privileges.

SEE ALSO

acct(2), *execve(2)*, *sa(8)*

NAME

aliases – aliases file for sendmail

SYNOPSIS

/usr/lib/aliases

DESCRIPTION

This file describes user id aliases used by */usr/lib/sendmail*. It is formatted as a series of lines of the form

name: name_1, name2, name_3, . . .

The *name* is the name to alias, and the *name_n* are the aliases for that name. Lines beginning with white space are continuation lines. Lines beginning with '#' are comments.

Aliasing occurs only on local names. Loops can not occur, since no message will be sent to any person more than once.

After aliasing has been done, local and valid recipients who have a ".forward" file in their home directory have messages forwarded to the list of users defined in that file.

This is only the raw data file; the actual aliasing information is placed into a binary format in the files */usr/lib/aliases.dir* and */usr/lib/aliases.pag* using the program *newaliases(1)*. A *newaliases* command should be executed each time the aliases file is changed for the change to take effect.

SEE ALSO

newaliases(1), *dbm(3X)*, *sendmail(8)*
SENDMAIL Installation and Operation Guide.
SENDMAIL An Internetwork Mail Router.

BUGS

Because of restrictions in *dbm(3X)* a single alias cannot contain more than about 1000 bytes of information. You can get longer aliases by "chaining"; that is, make the last name in the alias be a dummy name which is a continuation alias.

NAME

ar – archive (library) file format

SYNOPSIS

```
#include <ar.h>
```

DESCRIPTION

The archive command *ar* combines several files into one. Archives are used mainly as libraries to be searched by the link-editor *ld*.

A file produced by *ar* has a magic string at the start, followed by the constituent files, each preceded by a file header. The magic number and header layout as described in the include file are:

```
/*
 * Copyright (c) 1980 Regents of the University of California.
 * All rights reserved. The Berkeley software License Agreement
 * specifies the terms and conditions for redistribution.
 *
 *      @(#)ar.h    5.1 (Berkeley) 5/30/85
 */

#define ARMAG "!<arch>\n"
#define SARMAG 8

#define ARFMAG "\n"

struct ar_hdr {
    char    ar_name[16];
    char    ar_date[12];
    char    ar_uid[6];
    char    ar_gid[6];
    char    ar_mode[8];
    char    ar_size[10];
    char    ar_fmag[2];
};
```

The name is a blank-padded string. The *ar_fmag* field contains ARFMAG to help verify the presence of a header. The other fields are left-adjusted, blank-padded numbers. They are decimal except for *ar_mode*, which is octal. The date is the modification date of the file at the time of its insertion into the archive.

Each file begins on a even (0 mod 2) boundary; a new-line is inserted between files if necessary. Nevertheless the size given reflects the actual size of the file exclusive of padding.

There is no provision for empty areas in an archive file.

The encoding of the header is portable across machines. If an archive contains printable files, the archive itself is printable.

SEE ALSO

ar(1), *ld*(1), *nm*(1)

BUGS

File names lose trailing blanks. Most software dealing with archives takes even an included blank as a name terminator.

NAME

core – format of memory image file

SYNOPSIS

```
#include <sys/param.h>
```

DESCRIPTION

The UNIX System writes out a memory image of a terminated process when any of various errors occur. See *sigvec(2)* for the list of reasons; the most common are memory violations, illegal instructions, bus errors, and user-generated quit signals. The memory image is called 'core' and is written in the process's working directory (provided it can be; normal access controls apply).

The maximum size of a core file is limited by *setrlimit(2)*. Files which would be larger than the limit are not created.

The core file consists of the *u*. area, whose size (in pages) is defined by the UPAGES manifest in the *<sys/param.h>* file. The *u*. area starts with a *user* structure as given in *<sys/user.h>*. The remainder of the core file consists first of the data pages and then the stack pages of the process image. The amount of data space image in the core file is given (in pages) by the variable *u_dsize* in the *u*. area. The amount of stack image in the core file is given (in pages) by the variable *u_ssize* in the *u*. area. The size of a "page" is given by the constant NBPG (also from *<sys/param.h>*).

In general the debugger *adb(1)* is sufficient to deal with core images.

SEE ALSO

adb(1), *dbx(1)*, *sigvec(2)*, *setrlimit(2)*

NAME

dbx - dbx symbol table information

DESCRIPTION

The compiler symbol information generated for *dbx(1)* uses the same structure as described in *stab(5)*, with additional type and scope information appended to a symbol's name. The assembler directive used to describe symbol information has the following format:

```
stabs "string",kind,0,size,value
```

String contains the name, source language type, and scope of the symbol, *kind* specifies the memory class (e.g., external, static, parameter, local, register), and *size* specifies the byte size of the object, if relevant. The third field (0 above) is unused. For a global variable or a type, *value* is unused; for a local variable or parameter, it is the offset from the frame pointer, for a register variable, it is the associated register number.

The different kinds of stab entries are interpreted by dbx as follows:

N_GSYM The symbol is a global variable (e.g., .comm variable). The variable's address can be found from the corresponding *ld(1)* symbol entry, thus the value field for N_GSYM symbols is ignored. For example, a global variable "x" will have both an N_GSYM entry and an *ld(1)* entry (e.g., N_BSS + N_EXT). See *a.out(5)* for details about these other entries. of

N_FUN The symbol is a procedure or function. The size field contains the line number of the entry point. The value field contains the address of the entry point (in the text segment).

N_STSYM The symbol is a statically allocated variable for which an initial value has been specified. The value field contains the address of the variable (in the data segment).

N_LCSYM The symbol is statically allocated, but not initialized.

N_RSYM The symbol is a register variable whose value is kept in the register denoted by the value field.

N_PSYM The symbol is a parameter whose value is pushed on the stack before the call. The value field contains the offset from the argument base pointer (on the VAX, the ap register).

N_LSYM The symbol is a local variable whose value is stored in the most recently defined procedure's stack frame. The value is the (often negative) offset from the frame pointer (on the VAX, the fp register).

N_PC, N_MOD2 The symbol defines separate compilation information for pre-linking checking for Berkeley Pascal and DEC Modula-2 programs respectively. For Pascal, the value field contains the line number that the symbol is defined on. The value field is not used for Modula-2.

Most of the source level information about a symbol is stored in the string field of the stab entry. Since strings are kept in a separate string table in the *a.out* file, they can be arbitrarily long. Thus there are no restrictions on the kind or length of information in the string field, and it was not necessary to modify the assembler or loader when extending or modifying the format of this information.

Below is a grammar describing the syntax of the symbol string. Except in the case of a constant whose value is a string, there are no blanks in a symbol string.

```
NAME:      [a-zA-Z_][a-zA-Z_0-9]*
INTEGER:    [-][0-9][0-9]*
REAL:       [+ -][0-9]*([.][0-9][0-9]*|)([eE]([+ -])?[0-9][0-9]*|)
STRING:     ".*"
BSTRING:    .*
```

```
String:
  NAME ':' Class
  ':' Class
```

```
Class:
  'c' '=' Constant ':'
  Variable
  Procedure
  Parameter
  NamedType
  'X' ExportInfo          -- export or import information (for N_MOD2 only)
```

```
Constant:
  'i' INTEGER
  'r' REAL
  'c' OrdValue
  'b' OrdValue
  's' STRING
  'e' TypeId ':' OrdValue
  'S' TypeId ':' NumElements ':' NumBits ':' BSTRING
```

```
OrdValue:
  INTEGER
```

```
NumElements:
  INTEGER
```

```
NumBits:
  INTEGER
```

```
Variable:
  TypeId          -- local variable of type TypeId
  'r' TypeId      -- register variable of type TypeId
  'S' TypeId      -- module variable of type TypeId (static global in C)
  'V' TypeId      -- own variable of type TypeId (static local in C)
  'G' TypeId      -- global variable of type TypeId
```

```
Procedure:
  Proc          -- top level procedure
  Proc ':' NAME ':' NAME      -- local to first NAME,
                              -- second NAME is corresponding ld symbol
```

```
Proc:
  'P'          -- global procedure
```

```

'Q'      -- local procedure (static in C)
'I'      -- internal procedure (different calling sequence)
'F' TypId -- function returning type TypId
'f' TypId -- local function
'J' TypId -- internal function

Parameter:
'p' TypId -- value parameter of type TypId
'v' TypId -- reference parameter of type TypId

NamedType:
't' TypId -- type name for type TypId
'T' TypId -- C structure tag name for struct TypId

TypId:
INTEGER      -- Unique (per compilation) number of type
INTEGER '=' TypeDef -- Definition of type number
INTEGER '=' TypeAttr TypeDef

--
-- Type attributes are extra information associated with a type,
-- such as alignment constraints or pointer checking semantics.
-- Dbx interprets some of these, but will ignore rather than complain
-- about any it does not recognize. Therefore this is a way to add
-- extra information for pre-linking checking.
--
TypeAttr:
'@' TypeAttrList ';'

TypeAttrList:
TypeAttrList ';' TypeAttr
TypeAttr

TypeAttr:
'a' INTEGER      -- align boundary
's' INTEGER      -- size in bits
'p' INTEGER      -- pointer class (e.g., checking)
BSTRING          -- something else

TypeDef:
INTEGER
Subrange
Array
Record
'e' EnumList ';' -- enumeration
'*' TypId        -- pointer to TypId
'S' TypId        -- set of TypId
'd' TypId        -- file of TypId
ProcedureType
'i' NAME ':' NAME ';' -- imported type ModuleName:Name
'o' NAME ';'      -- opaque type
'i' NAME ':' NAME ';' TypId ';'
'o' NAME ';' TypId ';'

```

Subrange:

'r' TypeId ',' INTEGER ',' INTEGER

Array:

'a' TypeId ',' TypeId -- array [TypeId] of TypeId
 'A' TypeId -- open array of TypeId
 'D' INTEGER ',' TypeId -- N-dim. dynamic array
 'E' INTEGER ',' TypeId -- N-dim. subarray

ProcedureType:

'f' TypeId ',' -- C function type
 'f' TypeId ',' NumParams ',' TParamList ','
 'p' NumParams ',' TParamList ','

NumParams:

INTEGER

Record:

's' ByteSize FieldList ',' -- structure/record
 'u' ByteSize FieldList ',' -- C union

ByteSize:

INTEGER

FieldList :

Field
 FieldList Field

Field:

NAME ':' TypeId ',' BitOffset ',' BitSize ','

BitSize:

INTEGER

BitOffset:

INTEGER

EnumList:

Enum
 EnumList Enum

Enum:

NAME ':' OrdValue ','

ParamList:

Param
 ParamList Param

Param:

NAME ':' TypeId ',' PassBy ','

PassBy:

INTEGER

TParam:
TypeId ',' PassBy ','

TParamList :
TParam
TParamList TParam

Export:
INTEGER ExportInfo

ExportInfo:
't' TypeId
'f' TypeId ',' NumParams ',' ParamList ','
'p' NumParams ',' ParamList ','
'v' TypeId
'c' '=' Constant

A '?' indicates that the symbol information is continued in the next stab entry. This directive can only occur where a ',' would otherwise separate the fields of a record or constants in an enumeration. It is useful when the number of elements in one of these lists is large.

SEE ALSO

dbx(1), stab(5), a.out(5)

NAME

dir – format of directories

SYNOPSIS

```
#include <sys/types.h>
#include <sys/dir.h>
```

DESCRIPTION

A directory behaves exactly like an ordinary file, save that no user may write into a directory. The fact that a file is a directory is indicated by a bit in the flag word of its i-node entry; see *fs(5)*. The structure of a directory entry as given in the include file is:

```
/*
 * A directory consists of some number of blocks of DIRBLKSIZ
 * bytes, where DIRBLKSIZ is chosen such that it can be transferred
 * to disk in a single atomic operation (e.g. 512 bytes on most machines).
 *
 * Each DIRBLKSIZ byte block contains some number of directory entry
 * structures, which are of variable length. Each directory entry has
 * a struct direct at the front of it, containing its inode number,
 * the length of the entry, and the length of the name contained in
 * the entry. These are followed by the name padded to a 4 byte boundary
 * with null bytes. All names are guaranteed null terminated.
 * The maximum length of a name in a directory is MAXNAMLEN.
 *
 * The macro DIRSIZ(dp) gives the amount of space required to represent
 * a directory entry. Free space in a directory is represented by
 * entries which have dp->d_reclen > DIRSIZ(dp). All DIRBLKSIZ bytes
 * in a directory block are claimed by the directory entries. This
 * usually results in the last entry in a directory having a large
 * dp->d_reclen. When entries are deleted from a directory, the
 * space is returned to the previous entry in the same directory
 * block by increasing its dp->d_reclen. If the first entry of
 * a directory block is free, then its dp->d_ino is set to 0.
 * Entries other than the first in a directory do not normally have
 * dp->d_ino set to 0.
 */
#ifdef KERNEL
#define DIRBLKSIZ DEV_BSIZE
#else
#define DIRBLKSIZ 512
#endif

#define MAXNAMLEN 255

/*
 * The DIRSIZ macro gives the minimum record length which will hold
 * the directory entry. This requires the amount of space in struct direct
 * without the d_name field, plus enough space for the name with a terminating
 * null byte (dp->d_namlen+1), rounded up to a 4 byte boundary.
 */
#undef DIRSIZ
#define DIRSIZ(dp) \
    ((sizeof (struct direct) - (MAXNAMLEN+1)) + (((dp)->d_namlen+1 + 3) &~ 3))
```

```
struct direct {
    u_long    d_ino;
    short     d_reclen;
    short     d_namlen;
    char      d_name[MAXNAMLEN + 1];
    /* typically shorter */
};

struct _dirdesc {
    int        dd_fd;
    long       dd_loc;
    long       dd_size;
    char       dd_buf[DIRBLKSIZ];
};
```

By convention, the first two entries in each directory are for '.' and '..'. The first is an entry for the directory itself. The second is for the parent directory. The meaning of '..' is modified for the root directory of the master file system ("/"), where '..' has the same meaning as '.'.

SEE ALSO
fs(5)

NAME

disktab – disk description file

SYNOPSIS

```
#include <disktab.h>
```

DESCRIPTION

Disktab is a simple data base which describes disk geometries and disk partition characteristics. The format is patterned after the *termcap*(5) terminal data base. Entries in *disktab* consist of a number of ':' separated fields. The first entry for each disk gives the names which are known for the disk, separated by '|' characters. The last name given should be a long name fully identifying the disk.

The following list indicates the normal values stored for each disk entry.

Name	Type	Description
ns	num	Number of sectors per track
nt	num	Number of tracks per cylinder
nc	num	Total number of cylinders on the disk
ba	num	Block size for partition 'a' (bytes)
bd	num	Block size for partition 'd' (bytes)
be	num	Block size for partition 'e' (bytes)
bf	num	Block size for partition 'f' (bytes)
bg	num	Block size for partition 'g' (bytes)
bh	num	Block size for partition 'h' (bytes)
fa	num	Fragment size for partition 'a' (bytes)
fd	num	Fragment size for partition 'd' (bytes)
fe	num	Fragment size for partition 'e' (bytes)
ff	num	Fragment size for partition 'f' (bytes)
fg	num	Fragment size for partition 'g' (bytes)
fh	num	Fragment size for partition 'h' (bytes)
pa	num	Size of partition 'a' in sectors
pb	num	Size of partition 'b' in sectors
pc	num	Size of partition 'c' in sectors
pd	num	Size of partition 'd' in sectors
pe	num	Size of partition 'e' in sectors
pf	num	Size of partition 'f' in sectors
pg	num	Size of partition 'g' in sectors
ph	num	Size of partition 'h' in sectors
se	num	Sector size in bytes
sf	bool	supports bad144-style bad sector forwarding
so	bool	partition offsets in sectors
ty	str	Type of disk (e.g. removable, winchester)

Disktab entries may be automatically generated with the *diskpart* program.

FILES

/etc/disktab

SEE ALSO

newfs(8), diskpart(8), getdiskbyname(3)

BUGS

This file shouldn't exist, the information should be stored on each disk pack.

NAME

dump, dumpdates – incremental dump format

SYNOPSIS

```
#include <sys/types.h>
#include <sys/inode.h>
#include <protocols/dumpprestore.h>
```

DESCRIPTION

Tapes used by *dump* and *restore*(8) contain:

- a header record
- two groups of bit map records
- a group of records describing directories
- a group of records describing files

The format of the header record and of the first record of each description as given in the include file *<protocols/dumpprestore.h>* is:

```
#define NTREC      10
#define MLEN       16
#define MSIZ       4096

#define TS_TAPE    1
#define TS_INODE   2
#define TS_BITS    3
#define TS_ADDR    4
#define TS_END     5
#define TS_CLRI    6
#define MAGIC      (int) 60011
#define CHECKSUM   (int) 84446

struct spcl {
    int      c_type;
    time_t   c_date;
    time_t   c_ddate;
    int      c_volume;
    daddr_t  c_tapea;
    ino_t     c_inumber;
    int      c_magic;
    int      c_checksum;
    struct   dinode      c_dinode;
    int      c_count;
    char     c_addr[BSIZE];
} spcl;

struct idates {
    char      id_name[16];
    char      id_incno;
    time_t    id_ddate;
};

#define DUMPOUTFMT    "%-16s %c %s"      /* for printf */
#define DUMPINFMT    "%16s %c %[%n]\n"    /* name, incno, ctime(date) */
/* inverse for scanf */
```


NTREC is the number of 1024 byte records in a physical tape block. MLEN is the number of bits in a bit map word. MSIZ is the number of bit map words.

The TS_entries are used in the *c_type* field to indicate what sort of header this is. The types and their meanings are as follows:

TS_TAPE	Tape volume label
TS_INODE	A file or directory follows. The <i>c_dinode</i> field is a copy of the disk inode and contains bits telling what sort of file this is.
TS_BITS	A bit map follows. This bit map has a one bit for each inode that was dumped.
TS_ADDR	A subrecord of a file description. See <i>c_addr</i> below.
TS_END	End of tape record.
TS_CLRI	A bit map follows. This bit map contains a zero bit for all inodes that were empty on the file system when dumped.
MAGIC	All header records have this number in <i>c_magic</i> .
CHECKSUM	Header records checksum to this value.

The fields of the header structure are as follows:

<i>c_type</i>	The type of the header.
<i>c_date</i>	The date the dump was taken.
<i>c_ddate</i>	The date the file system was dumped from.
<i>c_volume</i>	The current volume number of the dump.
<i>c_tapea</i>	The current number of this (1024-byte) record.
<i>c_inumber</i>	The number of the inode being dumped if this is of type TS_INODE.
<i>c_magic</i>	This contains the value MAGIC above, truncated as needed.
<i>c_checksum</i>	This contains whatever value is needed to make the record sum to CHECKSUM.
<i>c_dinode</i>	This is a copy of the inode as it appears on the file system; see <i>fs(5)</i> .
<i>c_count</i>	The count of characters in <i>c_addr</i> .
<i>c_addr</i>	An array of characters describing the blocks of the dumped file. A character is zero if the block associated with that character was not present on the file system, otherwise the character is non-zero. If the block was not present on the file system, no block was dumped; the block will be restored as a hole in the file. If there is not sufficient space in this record to describe all of the blocks in a file, TS_ADDR records will be scattered through the file, each one picking up where the last left off.

Each volume except the last ends with a tapemark (read as an end of file). The last volume ends with a TS_END record and then the tapemark.

The structure *idates* describes an entry in the file */etc/dumpdates* where dump history is kept. The fields of the structure are:

<i>id_name</i>	The dumped filesystem is <i>'/dev/id_nam'</i> .
<i>id_incno</i>	The level number of the dump tape; see <i>dump(8)</i> .
<i>id_ddate</i>	The date of the incremental dump in system format see <i>types(5)</i> .

FILES

/etc/dumpdates

SEE ALSO

dump(8), *restore(8)*, *fs(5)*, *types(5)*

NAME

fs, inode – format of file system volume

SYNOPSIS

```
#include <sys/types.h>
#include <sys/fs.h>
#include <sys/inode.h>
```

DESCRIPTION

Every file system storage volume (disk, nine-track tape, for instance) has a common format for certain vital information. Every such volume is divided into a certain number of blocks. The block size is a parameter of the file system. Sectors beginning at BBLOCK and continuing for BBSIZE are used to contain primary and secondary bootstrapping programs.

The actual file system begins at sector SBLOCK with the *super block* that is of size SBSIZE. The layout of the super block as defined by the include file <sys/fs.h> is:

```
#define FS_MAGIC    0x011954
struct fs {
    struct fs *fs_link;          /* linked list of file systems */
    struct fs *fs_rlink;         /* used for incore super blocks */
    daddr_t fs_sbblkno;          /* addr of super-block in filesys */
    daddr_t fs_cblkno;           /* offset of cyl-block in filesys */
    daddr_t fs_iblkno;           /* offset of inode-blocks in filesys */
    daddr_t fs_dblkno;           /* offset of first data after cg */
    long fs_cgoffset;            /* cylinder group offset in cylinder */
    long fs_cgmask;              /* used to calc mod fs_ntrak */
    time_t fs_time;              /* last time written */
    long fs_size;                 /* number of blocks in fs */
    long fs_dsize;               /* number of data blocks in fs */
    long fs_ncg;                 /* number of cylinder groups */
    long fs_bsize;               /* size of basic blocks in fs */
    long fs_fsize;               /* size of frag blocks in fs */
    long fs_frag;                /* number of frags in a block in fs */

    /* these are configuration parameters */
    long fs_minfree;              /* minimum percentage of free blocks */
    long fs_rotdelay;            /* num of ms for optimal next block */
    long fs_rps;                  /* disk revolutions per second */

    /* these fields can be computed from the others */
    long fs_bmask;                /* "blkoff" calc of blk offsets */
    long fs_fmask;                /* "fragoff" calc of frag offsets */
    long fs_bshift;               /* "lblkno" calc of logical blkno */
    long fs_fshift;               /* "numfrags" calc number of frags */

    /* these are configuration parameters */
    long fs_maxcontig;            /* max number of contiguous blks */
    long fs_maxbpg;               /* max number of blks per cyl group */

    /* these fields can be computed from the others */
    long fs_fragshift;            /* block to frag shift */
    long fs_fsbtodb;              /* fsbtodb and dbtofsb shift constant */
    long fs_sbsize;               /* actual size of super block */
    long fs_csummask;             /* csum block offset */
    long fs_csshift;              /* csum block number */
    long fs_nindir;               /* value of NINDIR */
    long fs_inopb;                /* value of INOPB */
    long fs_nspf;                 /* value of NSPF */
    long fs_optim;                /* optimization preference, see below */
};
```

```

    long    fs_sparecon[5];        /* reserved for future constants */
/* sizes determined by number of cylinder groups and their sizes */
    daddr_t fs_csaddr;            /* blk addr of cyl grp summary area */
    long    fs_cssize;            /* size of cyl grp summary area */
    long    fs_cgsize;            /* cylinder group size */
/* these fields should be derived from the hardware */
    long    fs_ntrak;             /* tracks per cylinder */
    long    fs_nsect;            /* sectors per track */
    long    fs_spc;              /* sectors per cylinder */
/* this comes from the disk driver partitioning */
    long    fs_ncyl;             /* cylinders in file system */
/* these fields can be computed from the others */
    long    fs_cpg;              /* cylinders per group */
    long    fs_ipg;              /* inodes per group */
    long    fs_fpg;              /* blocks per group * fs_frag */
/* this data must be re-computed after crashes */
    struct  csum fs_cstotal;       /* cylinder summary information */
/* these fields are cleared at mount time */
    char    fs_fmod;             /* super block modified flag */
    char    fs_clean;            /* file system is clean flag */
    char    fs_roonly;           /* mounted read-only flag */
    char    fs_flags;            /* currently unused flag */
    char    fs_fsmnt[MAXMNTLEN]; /* name mounted on */
/* these fields retain the current block allocation info */
    long    fs_cgrotor;          /* last cg searched */
    struct  csum *fs_csp[MAXCSBUFS]; /* list of fs_cs info buffers */
    long    fs_cpc;              /* cyl per cycle in postbl */
    short   fs_postbl[MAXCPG][NRPOS]; /* head of blocks for each rotation */
    long    fs_magic;            /* magic number */
    u_char  fs_rotbl[1];         /* list of blocks for each rotation */
/* actually longer */
);

```

Each disk drive contains some number of file systems. A file system consists of a number of cylinder groups. Each cylinder group has inodes and data.

A file system is described by its super-block, which in turn describes the cylinder groups. The super-block is critical data and is replicated in each cylinder group to protect against catastrophic loss. This is done at file system creation time and the critical super-block data does not change, so the copies need not be referenced further unless disaster strikes.

Addresses stored in inodes are capable of addressing fragments of 'blocks'. File system blocks of at most size MAXBSIZE can be optionally broken into 2, 4, or 8 pieces, each of which is addressable; these pieces may be DEV_BSIZE, or some multiple of a DEV_BSIZE unit.

Large files consist of exclusively large data blocks. To avoid undue wasted disk space, the last data block of a small file is allocated as only as many fragments of a large block as are necessary. The file system format retains only a single pointer to such a fragment, which is a piece of a single large block that has been divided. The size of such a fragment is determinable from information in the inode, using the "blksiz(fs, ip, lbn)" macro.

The file system records space availability at the fragment level; to determine block availability, aligned fragments are examined.

The root inode is the root of the file system. Inode 0 can't be used for normal purposes and historically bad blocks were linked to inode 1, thus the root inode is 2 (inode 1 is no longer used for this purpose, however numerous dump tapes make this assumption, so we are stuck

with it). The *lost+found* directory is given the next available inode when it is initially created by *mkfs*.

fs_minfree gives the minimum acceptable percentage of file system blocks that may be free. If the freelist drops below this level only the super-user may continue to allocate blocks. This may be set to 0 if no reserve of free blocks is deemed necessary, however severe performance degradations will be observed if the file system is run at greater than 90% full; thus the default value of *fs_minfree* is 10%.

Empirically the best trade-off between block fragmentation and overall disk utilization at a loading of 90% comes with a fragmentation of 4, thus the default fragment size is a fourth of the block size.

fs_optim specifies whether the file system should try to minimize the time spent allocating blocks, or if it should attempt to minimize the space fragmentation on the disk. If the value of *fs_minfree* (see above) is less than 10%, then the file system defaults to optimizing for space to avoid running out of full sized blocks. If the value of *minfree* is greater than or equal to 10%, fragmentation is unlikely to be problematical, and the file system defaults to optimizing for time.

Cylinder group related limits: Each cylinder keeps track of the availability of blocks at different rotational positions, so that sequential blocks can be laid out with minimum rotational latency. NRPOS is the number of rotational positions which are distinguished. With NRPOS 8 the resolution of the summary information is 2ms for a typical 3600 rpm drive.

fs_rotdelay gives the minimum number of milliseconds to initiate another disk transfer on the same cylinder. It is used in determining the rotationally optimal layout for disk blocks within a file; the default value for *fs_rotdelay* is 2ms.

Each file system has a statically allocated number of inodes. An inode is allocated for each NBPI bytes of disk space. The inode allocation strategy is extremely conservative.

MAXIPG bounds the number of inodes per cylinder group, and is needed only to keep the structure simpler by having the only a single variable size element (the free bit map).

N.B.: MAXIPG must be a multiple of INOPB(fs).

MINBSIZE is the smallest allowable block size. With a MINBSIZE of 4096 it is possible to create files of size 2^{32} with only two levels of indirection. MINBSIZE must be big enough to hold a cylinder group block, thus changes to (struct cg) must keep its size within MINBSIZE. MAXCPG is limited only to dimension an array in (struct cg); it can be made larger as long as that structure's size remains within the bounds dictated by MINBSIZE. Note that super blocks are never more than size SBSIZE.

The path name on which the file system is mounted is maintained in *fs_fsmnt*. MAXMNTLEN defines the amount of space allocated in the super block for this name. The limit on the amount of summary information per file system is defined by MAXCSBUFS. It is currently parameterized for a maximum of two million cylinders.

Per cylinder group information is summarized in blocks allocated from the first cylinder group's data blocks. These blocks are read in from *fs_csaddr* (size *fs_cssize*) in addition to the super block.

N.B.: sizeof (struct csum) must be a power of two in order for the "fs_cs" macro to work.

Super block for a file system: MAXBPC bounds the size of the rotational layout tables and is limited by the fact that the super block is of size SBSIZE. The size of these tables is inversely proportional to the block size of the file system. The size of the tables is increased when sector sizes are not powers of two, as this increases the number of cylinders included before the rotational pattern repeats (*fs_cpc*). The size of the rotational layout tables is derived from the number of bytes remaining in (struct fs).

MAXBPG bounds the number of blocks of data per cylinder group, and is limited by the fact that cylinder groups are at most one block. The size of the free block table is derived from the size of blocks and the number of remaining bytes in the cylinder group structure (struct cg).

Inode: The inode is the focus of all file activity in the UNIX file system. There is a unique inode allocated for each active file, each current directory, each mounted-on file, text file, and the root. An inode is 'named' by its device/i-number pair. For further information, see the include file `<sys/inode.h>`.

NAME

fstab – static information about the filesystems

SYNOPSIS

```
#include <fstab.h>
```

DESCRIPTION

The file */etc/fstab* contains descriptive information about the various file systems. */etc/fstab* is only read by programs, and not written; it is the duty of the system administrator to properly create and maintain this file. The order of records in */etc/fstab* is important because *fsck*, *mount*, and *umount* sequentially iterate through */etc/fstab* doing their thing.

The special file name is the **block** special file name, and not the character special file name. If a program needs the character special file name, the program must create it by appending a "r" after the last "/" in the special file name.

If *fs_type* is "rw" or "ro" then the file system whose name is given in the *fs_file* field is normally mounted read-write or read-only on the specified special file. If *fs_type* is "rq", then the file system is normally mounted read-write with disk quotas enabled. The *fs_freq* field is used for these file systems by the *dump*(8) command to determine which file systems need to be dumped. The *fs_passno* field is used by the *fsck*(8) program to determine the order in which file system checks are done at reboot time. The root file system should be specified with a *fs_passno* of 1, and other file systems should have larger numbers. File systems within a drive should have distinct numbers, but file systems on different drives can be checked on the same pass to utilize parallelism available in the hardware.

If *fs_type* is "sw" then the special file is made available as a piece of swap space by the *swapon*(8) command at the end of the system reboot procedure. The fields other than *fs_spec* and *fs_type* are not used in this case.

If *fs_type* is "rq" then at boot time the file system is automatically processed by the *quota-check*(8) command and disk quotas are then enabled with *quotaon*(8). File system quotas are maintained in a file "quotas", which is located at the root of the associated file system.

If *fs_type* is specified as "xx" the entry is ignored. This is useful to show disk partitions which are currently not used.

```
#define FSTAB_RW    "rw"    /* read-write device */
#define FSTAB_RO    "ro"    /* read-only device */
#define FSTAB_RQ    "rq"    /* read-write with quotas */
#define FSTAB_SW    "sw"    /* swap device */
#define FSTAB_XX    "xx"    /* ignore totally */

struct fstab {
    char *fs_spec; /* block special device name */
    char *fs_file; /* file system path prefix */
    char *fs_type; /* rw,ro,sw or xx */
    int  fs_freq;  /* dump frequency, in days */
    int  fs_passno; /* pass number on parallel dump */
};
```

The proper way to read records from */etc/fstab* is to use the routines *getfsent*(), *getfsspec*(), *getfstype*(), and *getfsfile*().

FILES

/etc/fstab

SEE ALSO

getfsent(3X)

NAME

gettytab – terminal configuration data base

SYNOPSIS

/etc/gettytab

DESCRIPTION

Gettytab is a simplified version of the *termcap*(5) data base used to describe terminal lines. The initial terminal login process *getty*(8) accesses the *gettytab* file each time it starts, allowing simpler reconfiguration of terminal characteristics. Each entry in the data base is used to describe one class of terminals.

There is a default terminal class, *default*, that is used to set global defaults for all other classes. (That is, the *default* entry is read, then the entry for the class required is used to override particular settings.)

CAPABILITIES

Refer to *termcap*(5) for a description of the file layout. The *default* column below lists defaults obtained if there is no entry in the table obtained, nor one in the special *default* table.

Name	Type	Default	Description
ap	bool	false	terminal uses any parity
bd	num	0	backspace delay
bk	str	0377	alternate end of line character (input break)
cb	bool	false	use crt backspace mode
cd	num	0	carriage-return delay
ce	bool	false	use crt erase algorithm
ck	bool	false	use crt kill algorithm
cl	str	NULL	screen clear sequence
co	bool	false	console - add \n after login prompt
ds	str	^Y	delayed suspend character
dx	bool	false	set DECCTLQ
ec	bool	false	leave echo OFF
ep	bool	false	terminal uses even parity
er	str	^?	erase character
et	str	^D	end of text (EOF) character
ev	str	NULL	initial environment
f0	num	unused	tty mode flags to write messages
f1	num	unused	tty mode flags to read login name
f2	num	unused	tty mode flags to leave terminal as
fd	num	0	form-feed (vertical motion) delay
fl	str	^O	output flush character
hc	bool	false	do NOT hangup line on last close
he	str	NULL	hostname editing string
hn	str	hostname	hostname
ht	bool	false	terminal has real tabs
ig	bool	false	ignore garbage characters in login name
im	str	NULL	initial (banner) message
in	str	^C	interrupt character
is	num	unused	input speed
kl	str	^U	kill character
lc	bool	false	terminal has lower case
lm	str	login:	login prompt
ln	str	^V	"literal next" character
lo	str	/bin/login	program to exec when name obtained
nd	num	0	newline (line-feed) delay

nl	bool	false	terminal has (or might have) a newline character
nx	str	default	next table (for auto speed selection)
op	bool	false	terminal uses odd parity
os	num	unused	output speed
pc	str	\0	pad character
pe	bool	false	use printer (hard copy) erase algorithm
pf	num	0	delay between first prompt and following flush (seconds)
ps	bool	false	line connected to a MICOM port selector
qu	str	^\ ^R	quit character
rp	str	^R	line retype character
rw	bool	false	do NOT use raw for input, use cbreak
sp	num	unused	line speed (input and output)
su	str	^Z	suspend character
tc	str	none	table continuation
to	num	0	timeout (seconds)
tt	str	NULL	terminal type (for environment)
ub	bool	false	do unbuffered output (of prompts etc)
uc	bool	false	terminal is known upper case only
we	str	^W	word erase character
xc	bool	false	do NOT echo control chars as ^X
xf	str	^S	XOFF (stop output) character
xn	str	^Q	XON (start output) character

If no line speed is specified, speed will not be altered from that which prevails when `getty` is entered. Specifying an input or output speed will override line speed for stated direction only.

Terminal modes to be used for the output of the message, for input of the login name, and to leave the terminal set as upon completion, are derived from the boolean flags specified. If the derivation should prove inadequate, any (or all) of these three may be overridden with one of the `f0`, `f1`, or `f2` numeric specifications, which can be used to specify (usually in octal, with a leading '0') the exact values of the flags. Local (new tty) flags are set in the top 16 bits of this (32 bit) value.

Should `getty` receive a null character (presumed to indicate a line break) it will restart using the table indicated by the `nx` entry. If there is none, it will re-use its original table.

Delays are specified in milliseconds, the nearest possible delay available in the tty driver will be used. Should greater certainty be desired, delays with values 0, 1, 2, and 3 are interpreted as choosing that particular delay algorithm from the driver.

The `cl` screen clear string may be preceded by a (decimal) number of milliseconds of delay required (a la `termcap`). This delay is simulated by repeated use of the pad character `pc`.

The initial message, and login message, `im` and `lm` may include the character sequence `%h` or `%t` to obtain the hostname or tty name respectively. (`%%` obtains a single '%' character.) The hostname is normally obtained from the system, but may be set by the `hn` table entry. In either case it may be edited with `he`. The `he` string is a sequence of characters, each character that is neither '@' nor '#' is copied into the final hostname. A '@' in the `he` string, causes one character from the real hostname to be copied to the final hostname. A '#' in the `he` string, causes the next character of the real hostname to be skipped. Surplus '@' and '#' characters are ignored.

When `getty` execs the login process, given in the `lo` string (usually `/bin/login`), it will have set the environment to include the terminal type, as indicated by the `tt` string (if it exists). The `ev` string, can be used to enter additional data into the environment. It is a list of comma separated strings, each of which will presumably be of the form `name=value`.

If a non-zero timeout is specified, with *to*, then *getty* will exit within the indicated number of seconds, either having received a login name and passed control to *login*, or having received an alarm signal, and exited. This may be useful to hangup dial in lines.

Output from *getty* is even parity unless *op* is specified. *Op* may be specified with *ap* to allow any parity on input, but generate odd parity output. Note: this only applies while *getty* is being run, terminal driver limitations prevent a more complete implementation. *Getty* does not check parity of input characters in *RAW* mode.

SEE ALSO

login(1), *termcap*(5), *getty*(8).

BUGS

The special characters (erase, kill, etc.) are reset to system defaults by *login*(1). In all cases, '#' or '^H' typed in a login name will be treated as an erase character, and '@' will be treated as a kill character.

The delay stuff is a real crock. Apart from its general lack of flexibility, some of the delay algorithms are not implemented. The terminal driver should support sane delay settings.

The *he* capability is stupid.

Termcap format is horrid, something more rational should have been chosen.

NAME

group – group file

DESCRIPTION

Group contains for each group the following information:

- group name
- encrypted password
- numerical group ID
- a comma separated list of all users allowed in the group

This is an ASCII file. The fields are separated by colons; Each group is separated from the next by a new-line. If the password field is null, no password is demanded.

This file resides in directory */etc*. Because of the encrypted passwords, it can and does have general read permission and can be used, for example, to map numerical group ID's to names.

FILES

/etc/group

SEE ALSO

setgroups(2), *initgroups(3X)*, *crypt(3)*, *passwd(1)*, *passwd(5)*

BUGS

The *passwd(1)* command won't change the passwords.

NAME

hosts - host name data base

DESCRIPTION

The *hosts* file contains information regarding the known hosts on the network. For each host a single line should be present with the following information:

official host name
Internet address
aliases

Items are separated by any number of blanks and/or tab characters. A “#” indicates the beginning of a comment; characters up to the end of the line are not interpreted by routines which search the file.

When using the name server *named*(8), this file provides a backup when the name server is not running. For the name server, it is suggested that only a few addresses be included in this file. These include address for the local interfaces that *ifconfig*(8C) needs at boot time and a few machines on the local network.

This file may be created from the official host data base maintained at the Network Information Control Center (NIC), though local changes may be required to bring it up to date regarding unofficial aliases and/or unknown hosts. As the data base maintained at NIC is incomplete, use of the name server is recommend for sites on the DARPA Internet.

Network addresses are specified in the conventional “.” notation using the *inet_addr*() routine from the Internet address manipulation library, *inet*(3N). Host names may contain any printable character other than a field delimiter, newline, or comment character.

FILES

/etc/hosts

SEE ALSO

gethostbyname(3N), ifconfig(8C), named(8)
Name Server Operations Guide for BIND

NAME

L-devices – UUCP device description file

DESCRIPTION

The L-devices file is consulted by the UUCP daemon *uucico*(8C) under the direction of *L.sys*(5) for information on the devices that it may use. Each line describes exactly one device.

A line in *L-devices* has the form:

Caller Device Call_Unit Class Dialer [Expect Send]....

Each item can be separated by any number of blanks or tabs. Lines beginning with a '#' character are comments; long lines can be continued by appending a '\' character to the end of the line.

Caller denotes the type of connection, and must be one of the following:

ACU Automatic call unit, e.g., autodialing modems such as the Hayes Smartmodem 1200 or Novation "Smart Cat".

DIR Direct connect; hardwired line (usually RS-232) to a remote system.

DK AT&T Datakit.

MICOM

Micom Terminal switch.

PAD X.25 PAD connection.

PCP GTE Telenet PC Pursuit.

SYTEK Sytek high-speed dedicated modem port connection.

TCP Berkeley TCP/IP or 3Com UNET connection. These are mutually exclusive. Note that listing TCP connections in *L-devices* is superfluous; *uucico* does not even bother to look here since it has all the information it needs in *L.sys*(5).

Device is a device file in */dev/* that is opened to use the device. The device file must be owned by UUCP, with access modes of 0600 or better. (See *chmod*(2)).

Call_Unit is an optional second device file name. True automatic call units use a separate device file for data and for dialing; the *Device* field specifies the data port, while the *Call_unit* field specifies the dialing port. If the *Call_unit* field is unused, it must not be left empty. Insert a dummy entry as a placeholder, such as "0" or "unused."

Class is an integer number that specifies the line baud (for dialers and direct lines) or the port number (for network connections).

The *Class* may be preceded by a non-numeric prefix. This is to differentiate among devices that have identical *Caller* and baud, but are distinctly different. For example, "1200" could refer to all Bell 212-compatible modems, "V1200" to Racal-Vadic modems, and "C1200" to CCITT modems, all at 1200 baud. Similarly, "W1200" could denote long distance lines, while "L1200" could refer to local phone lines.

Dialer applies only to ACU devices. This is the "brand" or type of the ACU or modem.

DF02 DEC DF02 or DF03 modems.

DF112 Dec DF112 modems. Use a *Dialer* field of **DF112T** to use tone dialing, or **DF112P** for pulse dialing.

att AT&T 2224 2400 baud modem.

cds224 Concord Data Systems 224 2400 baud modem.

dn11 DEC DN11 Unibus dialer.

hayes Hayes Smartmodem 1200 and compatible autodialing modems. Use a *Dialer* field of *hayestone* to use tone dialing, or *hayespulse* for pulse dialing. It is also permissible to include the letters 'T' and 'P' in the phone number (in *L.sys*) to change to tone or pulse midway through dialing. (Note that a leading 'T' or 'P' will be interpreted as a dialcode!)

hayes2400

Hayes Smartmodem 2400 and compatible modems. Use a *Dialer* field of *hayes2400tone* to use tone dialing, or *hayes2400pulse* for pulse dialing.

novation

Novation "Smart Cat" autodialing modem.

penril Penril Corp "Hayes compatible" modems (they really aren't or they would use the *hayes* entry.)

rvmacs Racal-Vadic 820 dialer with 831 adapter in a MACS configuration.

va212 Racal-Vadic 212 autodialing modem.

va811s Racal-Vadic 811s dialer with 831 adapter.

va820 Racal-Vadic 820 dialer with 831 adapter.

vadic Racal-Vadic 3450 and 3451 series autodialing modems.

ventel Ventel 212+ autodialing modem.

vmacs Racal-Vadic 811 dialer with 831 adapter in a MACS configuration.

Expect/Send is an optional *Expect/Send* script for getting through a smart port selector, or for issuing special commands to the modem. The syntax is identical to that of the *Expect/Send* script of *L.sys*. The difference is that the *L-devices* script is used *before* the connection is made, while the *L.sys* script is used *after*.

FILES

/usr/lib/uucp/L-devices

/usr/lib/uucp/UUAIDS/L-devices L-devices example

SEE ALSO

uucp(1C), uux(1C), L.sys(5), uucico(8C)

NAME

L-dialcodes – UUCP phone number index file

DESCRIPTION

The *L-dialcodes* file defines the mapping of strings from the phone number field of *L.sys*(5) to actual phone numbers.

Each line in *L-dialcodes* has the form:

```
alpha_string phone_number
```

The two items can be separated by any number of blanks or tabs. Lines beginning with a '#' character are comments.

A phone number in *L.sys* can be preceded by an arbitrary alphabetic character string; the string is matched against the list of *alpha_strings* in *L-dialcodes*. If a match is found, *phone_number* is substituted for it. If no match is found, the string is discarded.

L-dialcodes is commonly used either of two ways:

- (1) The alphabetic strings are used as prefixes to denote area codes, zones, and other commonly used sequences. For example, if *L-dialcodes* included the following lines:

```
chi    1312
mv     1415
```

In *L.sys* you could enter:

```
chivax Any ACU 1200 chi5551234 ogin:--ogin: nuucp
mvpvr  Any ACU 1200 mv5556001 ogin:--ogin: Uuucp
```

instead of

```
chivax Any ACU 1200 13125551234 ogin:--ogin: nuucp
mvpvr  Any ACU 1200 14155556001 ogin:--ogin: Uuucp
```

- (2) All phone numbers are placed in *L-dialcodes*, one for each remote site. *L.sys* then refers to these by name. For example, if *L-dialcodes* contains the following lines:

```
chivax 13125551234
mvpvr  14155556601
```

then *L.sys* could have:

```
chivax Any ACU 1200 chivax ogin:--ogin: nuucp
mvpvr  Any ACU 1200 mvpvr  ogin:--ogin: Uuucp
```

This scheme allows a site administrator to give users read access to the table of phone numbers, while still protecting the login/password sequences in *L.sys*.

FILES

```
/usr/lib/uucp/L-dialcodes
/usr/lib/uucp/UUAIDS/L-dialcodes  L-dialcodes example
```

SEE ALSO

uucp(1C), uux(1C), L.sys(5), uucico(8C).

NAME

L.aliases – UUCP hostname alias file

DESCRIPTION

The *L.aliases* file defines mapping (aliasing) of system names for uucp. This is intended for compensating for systems that have changed names, or do not provide their entire machine name (like most USG systems). It is also useful when a machine's name is not obvious or commonly misspelled.

Each line in *L.aliases* is of the form:

real_name alias_name

Any amount of whitespace may separate the two items. Lines beginning with a '#' character are comments.

All occurrences of *alias_name* are mapped to *real_name* by *uucico*(8C), *uucp*(1), and *uux*(1). The mapping occurs regardless of whether the name was typed in by a user or provided by a remote site. An exception is the -s option of *uucico*; only the site's real hostname (the name in *L.sys*(5)) will be accepted there.

Aliased system names should not be placed in *L.sys*; they will not be used.

FILES

/usr/lib/uucp/L.aliases /usr/lib/uucp/UUAIDS/L.aliases *L.aliases* example

SEE ALSO

uucp(1C), *uux*(1C), *L.sys*(5), *uucico*(8C)

NAME

L.cmds - UUCP remote command permissions file

DESCRIPTION

The *L.cmds* file contains a list of commands, one per line, that are permitted for remote execution via *uux*(1C).

The default search path is */bin:/usr/bin:/usr/ucb*. To change the path, include anywhere in the file a line of the form:

PATH=/bin:/usr/bin:/usr/ucb

Normally, an acknowledgment is mailed back to the requesting site after the command completes. If a command name is suffixed with *,Error*, then an acknowledgment will be mailed only if the command fails. If the command is suffixed with *,No*, then no acknowledgment will ever be sent. (These correspond with the *-z* and *-n* options of *uux*, respectively.)

For most sites, *L.cmds* should only include the lines:

rmail
ruusend

News sites should add:

PATH=/bin:/usr/bin:/usr/ucb:/usr/new
rnews>Error

While file names supplied as arguments to *uux* commands will be checked against the list of accessible directory trees in *USERFILE*(5), this check can be easily circumvented and should not be depended upon. In other words, it is unwise to include any commands in *L.cmds* that accept local file names. In particular, *sh*(1) and *csh*(1) are extreme risks.

It is common (but hazardous) to include *uucp*(1C) in *L.cmds*; see the NOTES section of *USERFILE*.

FILES

/usr/lib/uucp/L.cmds
/usr/lib/uucp/UUAIDS/L.cmds *L.cmds* example.

SEE ALSO

uucp(1C), *uux*(1C), *USERFILE*(5), *uucico*(8C), *uuxqt*(8C)

NAME

L.sys – UUCP remote host description file

DESCRIPTION

The *L.sys* file is consulted by the UUCP daemon *uucico*(8C) for information on remote systems. *L.sys* includes the system name, appropriate times to call, phone numbers, and a login and password for the remote system. *L.sys* is thus a privileged file, owned by the UUCP Administrator; it is accessible only to the Administrator and to the superuser.

Each line in *L.sys* describes one connection to one remote host, and has the form:

System Times Caller Class Device/Phone_Number [Expect Send]...

Fields can be separated by any number of blanks or tabs. Lines beginning with a '#' character are comments; long lines can be continued by appending a '\' character to the end of the line.

The first five fields (*System* through *Device/Phone_Number*) specify the hardware mechanism that is necessary to make a connection to a remote host, such as a modem or network. *Uucico* searches from the top down through *L.sys* to find the desired *System*; it then opens the *L-devices*(5) file and searches for the first available device with the same *Caller*, *Class*, and (possibly) *Device*. ("Available" means that the device is ready and not being used for something else.) *Uucico* attempts a connection using that device; if the connection cannot be made (for example, a dialer gets a busy signal), *uucico* tries the next available device. If this also fails, it returns to *L.sys* to look for another line for the same *System*. If none is found, *uucico* gives up.

System is the hostname of the remote system. Every machine with which this system communicates via UUCP should be listed, regardless of who calls whom. Systems not listed in *L.sys* will not be permitted a connection. The local hostname should not appear here for security reasons.

Times is a comma-separated list of the times of the day and week that calls are permitted to this *System*. *Times* is most commonly used to restrict long distance telephone calls to those times when rates are lower. List items are constructed as:

*keyword*hhmm-hhmm/grade;retry_time

Keyword is required, and must be one of:

Any Any time, any day of the week.

Wk Any weekday. In addition, **Mo**, **Tu**, **We**, **Th**, **Fr**, **Sa**, and **Su** can be used for Monday through Sunday, respectively.

Evening When evening telephone rates are in effect, from 1700 to 0800 Monday through Friday, and all day Saturday and Sunday. **Evening** is the same as **Wk1700-0800,Sa,Su**.

Night When nighttime telephone rates are in effect, from 2300 to 0800 Monday through Friday, all day Saturday, and from 2300 to 1700 Sunday. **Night** is the same as **Any2300-0800,Sa,Su0800-1700**.

NonPeak

This is a slight modification of **Evening**. It matches when the USA X.25 carriers have their lower rate period. This is 1800 to 0700 Monday through Friday, and all day Saturday and Sunday. **NonPeak** is the same as **Any1800-0700,Sa,Su**.

Never Never call; calling into this *System* is forbidden or impossible. This is intended for polled connections, where the remote system calls into the local machine periodically. This is necessary when one of the machines is lacking either dial-in or dial-out modems.

The optional *hhmm-hhmm* subfield provides a time range that modifies the keyword. *hhmm* refers to *hours* and *minutes* in 24-hour time (from 0000 to 2359). The time range is permitted to "wrap" around midnight, and will behave in the obvious way. It is invalid to follow the *Evening*, *NonPeak*, and *Night* keywords with a time range.

The *grade* subfield is optional; if present, it is composed of a '/' (slash) and single character denoting the *grade* of the connection, from 0 to 9, A to Z, or a to z. This specifies that only requests of grade *grade* or better will be transferred during this time. (The grade of a request or job is specified when it is queued by *uucp* or *uux*.) By convention, mail is sent at grade C, news is sent at grade d, and uucp copies are sent at grade n. Unfortunately, some sites do not follow these conventions, so it is not 100% reliable.

The *retry_time* subfield is optional; it must be preceded by a ';' (semicolon) and specifies the time, in minutes, before a failed connection may be tried again. (This restriction is in addition to any constraints imposed by the rest of the *Time* field.) By default, the retry time starts at 10 minutes and gradually increases at each failure, until after 26 tries *uucico* gives up completely (MAX RETRIES). If the retry time is too small, *uucico* may run into MAX RETRIES too soon.

Caller is the type of device used:

ACU Automatic call unit or auto-dialing modem such as the Hayes Smartmodem 1200 or Novation "Smart Cat". See *L-devices* for a list of supported modems.

DIR Direct connect; hardwired line (usually RS-232) to a remote system.

MICOM

Micom Terminal Switch.

PAD X.25 PAD connection.

PCP GTE Telenet PC Pursuit. See *L-devices* for configuration details.

SYTEK Sytek high-speed dedicated modem port connection.

TCP Berkeley TCP/IP or 3Com UNET connection. These are mutually exclusive. TCP ports do not need entries in *L-devices* since all the necessary information is contained in *L.sys*. If several alternate ports or network connections should be tried, use multiple *L.sys* entries.

Class is usually the speed (baud) of the device, typically 300, 1200, or 2400 for ACU devices and 9600 for direct lines. Valid values are device dependent, and are specified in the *L-devices* file.

On some devices, the baud may be preceded by a non-numeric prefix. This is used in *L-devices* to distinguish among devices that have identical *Caller* and baud, but yet are distinctly different. For example, 1200 could refer to all Bell 212-compatible modems, V1200 to Racal-Vadic modems, and C1200 to CCITT modems, all at 1200 baud.

On TCP connections, *Class* is the port number (an integer number) or a port name from */etc/services* that is used to make the connection. For standard Berkeley TCP/IP, UUCP normally uses port number 540.

Device/Phone_Number varies based on the *Caller* field. For ACU devices, this is the phone number to dial. The number may include: digits 0 through 9; # and * for dialing those symbols on tone telephone lines; - (hyphen) to pause for a moment, typically two to four seconds; = (equal sign) to wait for a second dial tone (implemented as a pause on many modems). Other characters are modem dependent; generally standard telephone punctuation characters (such as the slash and parentheses) are ignored, although *uucico* does not guarantee this.

The phone number can be preceded by an alphabetic string; the string is indexed and converted through the *L-dialcodes(5)* file.

For DIR devices, the *Device/Phone_Number* field contains the name of the device in */dev* that is used to make the connection. There must be a corresponding line in *L-devices* with identical *Caller*, *Class*, and *Device* fields.

For TCP and other network devices, *Device/Phone_Number* holds the true network name of the remote system, which may be different from its UUCP name (although one would hope not).

Expect and *Send* refer to an arbitrarily long set of strings that alternately specify what to *expect* and what to *send* to login to the remote system once a physical connection has been established. A complete set of expect/send strings is referred to as an *expect/send script*. The same syntax is used in the *L-devices* file to interact with the dialer prior to making a connection; there it is referred to as a *chat script*. The complete format for one *expect/send* pair is:

```
expect-timeout-send-expect-timeout send
```

Expect and *Send* are character strings. *Expect* is compared against incoming text from the remote host; *send* is sent back when *expect* is matched. By default, the *send* is followed by a '\r' (carriage return). If the *expect* string is not matched within *timeout* seconds (default 45), then it is assumed that the match failed. The '*expect-send-expect*' notation provides a limited loop mechanism; if the first *expect* string fails to match, then the *send* string between the hyphens is transmitted, and *uucico* waits for the second *expect* string. This can be repeated indefinitely. When the last *expect* string fails, *uucico* hangs up and logs that the connection failed.

The timeout can (optionally) be specified by appending the parameter "*nn*" to the *expect* string, when *nn* is the timeout time in seconds.

Backslash escapes that may be imbedded in the *expect* or *send* strings include:

\b	Generate a 3/10 second BREAK.
\bn	Where <i>n</i> is a single-digit number; generate an <i>n</i> /10 second BREAK.
\c	Suppress the \r at the end of a <i>send</i> string.
\d	Delay; pause for 1 second. (<i>Send</i> only.)
\r	Carriage Return.
\s	Space.
\n	Newline.
\xxx	Where <i>xxx</i> is an octal constant; denotes the corresponding ASCII character.

As a special case, an empty pair of double-quotes "" in the *expect* string is interpreted as "expect nothing"; that is, transmit the *send* string regardless of what is received. Empty double-quotes in the *send* string cause a lone '\r' (carriage return) to be sent.

One of the following keywords may be substituted for the *send* string:

BREAK	Generate a 3/10 second BREAK
BREAK <i>n</i>	Generate an <i>n</i> /10 second BREAK
CR	Send a Carriage Return (same as "").
EOT	Send an End-Of-Transmission character, ASCII \004. Note that this will cause most hosts to hang up.
NL	Send a Newline.
PAUSE	Pause for 3 seconds.
PAUSE <i>n</i>	Pause for <i>n</i> seconds.
P_ODD	Use odd parity on future send strings.
P_ONE	Use parity one on future send strings.
P_EVEN	Use even parity on future send strings. (Default)
P_ZERO	Use parity zero on future send strings.

Finally, if the *expect* string consists of the keyword **ABORT**, then the string following is used to arm an abort trap. If that string is subsequently received any time prior to the completion of the entire *expect/send* script, then *uucico* will abort, just as if the script had timed out. This is useful for trapping error messages from port selectors or front-end processors such as "Host Unavailable" or "System is Down."

For example:

```
"" "" ogin:--ogin: nuucp ssword: ufeedme
```

This is executed as, "When the remote system answers, *expect* nothing. *Send* a carriage return. *Expect* the remote to transmit the string 'ogin:'. If it doesn't within 45 seconds, send another carriage return. When it finally does, *send* it the string 'nuucp'. Then *expect* the string 'ssword:'; when that is received, *send* 'ufeedme'."

FILES

/usr/lib/uucp/L.sys
/usr/lib/uucp/UUAIDS/L.sys L.sys example

SEE ALSO

uucp(1C), uux(1C), L-devices(5), services(5), uucico(8C)

BUGS

"ABORT" in the send/expect script is expressed "backwards," that is, it should be written "*expect ABORT*" but instead it is "**ABORT** *expect*".

Several of the backslash escapes in the send/expect strings are confusing and/or different from those used by AT&T and Honey-Danber UUCP. For example, '\b' requests a BREAK, while practically everywhere else '\b' means backspace. '\t' for tab and '\f' for formfeed are not implemented. '\s' is a kludge; it would be more sensible to be able to delimit strings with quotation marks.

NAME

map3270 – database for mapping ascii keystrokes into IBM 3270 keys

SYNOPSIS

/etc/map3270

DESCRIPTION

When emulating IBM-style 3270 terminals under UNIX (see *tn3270(1)*), a mapping must be performed between sequences of keys hit on a user's (ascii) keyboard, and the keys that are available on a 3270. For example, a 3270 has a key labeled **EEOF** which erases the contents of the current field from the location of the cursor to the end. In order to accomplish this function, the terminal user and a program emulating a 3270 must agree on what keys will be typed to invoke the EEOF function.

The requirements for these sequences are:

- 1.) that the first character of the sequence be outside of the standard ascii printable characters;
- 2.) that no one sequence be an initial part of another (although sequences may *share* initial parts).

FORMAT

The file consists of entries for various terminals. The first part of an entry lists the names of the terminals which use that entry. These names should be the same as in */etc/termcap* (see *termcap(5)*); note that often the terminals from various termcap entries will all use the same *map3270* entry; for example, both 925 and 925vb (for 925 with visual bells) would probably use the same *map3270* entry. After the names, separated by vertical bars ('|'), comes a left brace ('{'); the definitions; and, finally, a right brace ('}').

The definitions consist of a reserved keyword (see list below) which identifies the 3270 function (extended as defined below), followed by an equal sign ('='), followed by the various ways to generate this particular function, followed by a semi-colon(';'). Each way is a sequence of strings of *printable* ascii characters enclosed inside single quotes (''); various ways (options) are separated by vertical bars ('|').

Inside the single quotes, a few characters are special. A caret (^) specifies that the next character is the "control" character of whatever the character is. So, ^a represents control-a, ie: hexadecimal 1 (note that ^A would generate the same code). To generate *rubout*, one enters ^?. To represent a control character inside a file requires using the caret to represent a control sequence; simply typing control-A will not work. Note: the ctrl-caret sequence (to generate a hexadecimal 1E) is represented as ^^^ (not ^^).

In addition to the caret, a letter may be preceeded by a backslash ('\'). Since this has little effect for most characters, its use is usually not recommended. For the case of a single quote (''), the backslash prevents that single quote from terminating the string. To have the backslash be part of the string, it is necessary to place two backslashes ('\\') in the file.

In addition, the following characters are special:

- ^E' means an escape character;
- ^n' means newline;
- ^t' means tab;
- ^r' means carriage return.

It is not necessary for each character in a string to be enclosed within single quotes. '^E^E^E' means three escape characters.

Comments, which may appear anywhere on a line, begin with a hash mark ("#"), and terminate at the end of that line. However, comments cannot begin inside a quoted string; a hash mark inside a quoted string has no special meaning.

3270 KEYS SUPPORTED

The following is the list of 3270 key names that are supported in this file. Note that some of the keys don't really exist on a 3270. In particular, the developers of this file have relied extensively on the work at the Yale University Computer Center with their 3270 emulator which runs in an IBM Series/1 front end. The following list corresponds closely to the functions that the developers of the Yale code offer in their product.

In the following list, the starred (*) functions are not supported by *tn3270(1)*. An unsupported function will cause *tn3270(1)* to send a bell sequence to the user's terminal.

3270 Key Name Functional description

(*)LPRT	local print
DP	dup character
FM	field mark character
(*)CURSEL	cursor select
RESHOW	redisplay the screen
EINP	erase input
EEOF	erase end of field
DELETE	delete character
INSRT	toggle insert mode
TAB	field tab
BTAB	field back tab
COLTAB	column tab
COLBAK	column back tab
INDENT	indent one tab stop
UNDENT	undent one tab stop
NL	new line
HOME	home the cursor
UP	up cursor
DOWN	down cursor
RIGHT	right cursor
LEFT	left cursor
SETTAB	set a column tab
DELTAB	delete a columntab
SETMRG	set left margin
SETHOM	set home position
CLRTAB	clear all column tabs
(*)APLON	apl on
(*)APLOFF	apl off
(*)APLEND	treat input as ascii
(*)PCON	xon/xoff on
(*)PCOFF	xon/xoff off
DISC	disconnect (suspend)
(*)INIT	new terminal type
(*)ALTK	alternate keyboard dvorak
FLINP	flush input
ERASE	erase last character
WERASE	erase last word
FERASE	erase field

SYNCH we are in synch with the user
 RESET reset key-unlock keyboard
 MASTER_RESET reset, unlock and redisplay
 (*)XOFF please hold output
 (*)XON please give me output
 ESCAPE enter telnet command mode
 WORDTAB tab to beginning of next word
 WORDBACKTAB tab to beginning of current/last word
 WORDEND tab to end of current/next word
 FIELDEND tab to last non-blank of current/next
 unprotected (writable) field.

PA1 program attention 1
 PA2 program attention 2
 PA3 program attention 3

CLEAR local clear of the 3270 screen
 TREQ test request
 ENTER enter key

PFK1 program function key 1
 PFK2 program function key 2
 etc. etc.
 PFK36 program function key 36

A SAMPLE ENTRY

The following entry is used by tn3270(1) when unable to locate a reasonable version in the user's environment and in /etc/map3270:

```

name {          # actual name comes from TERM variable
clear = '^z';
flinp = '^x';
enter = '^m';
delete = '^d' | '^?'; # note that '^?' is delete (rubout)
synch = '^r';
reshow = '^v';
eof = '^e';
tab = '^i';
btabs = '^b';
nl = '^n';
left = '^h';
right = '^l';
up = '^k';
down = '^j';
einp = '^w';
reset = '^t';
xoff = '^s';
xon = '^q';
escape = '^c';
ferase = '^u';
insrt = '^_';
# program attention keys
pa1 = '^p1'; pa2 = '^p2'; pa3 = '^p3';
# program function keys

```

```

pfk1 = '1'; pfk2 = '2'; pfk3 = '3'; pfk4 = '4';
pfk5 = '5'; pfk6 = '6'; pfk7 = '7'; pfk8 = '8';
pfk9 = '9'; pfk10 = ' '; pfk11 = '-'; pfk12 = '=';
pfk13 = '~'; pfk14 = '@'; pfk15 = '0';
pfk17 = '~'; pfk18 = '~'; pfk19 = '~'; pfk20 = '~';
pfk21 = '~'; pfk22 = '~'; pfk23 = '~'; pfk24 = '~';
)

```

IBM 3270 KEY DEFINITIONS FOR AN ABOVE DEFINITION

The charts below show the proper keys to emulate each 3270 function when using the default key mapping supplied with *tn3270(1)* and *mset(1)*.

Command Keys	IBM 3270 Key	Default Key(s)
Enter	RETURN	
Clear	control-z	
Cursor Movement Keys		
New Line	control-n or Home	
Tab	control-i	
Back Tab	control-b	
Cursor Left	control-h	
Cursor Right	control-l	
Cursor Up	control-k	
Cursor Down	control-j or LINE FEED	
Edit Control Keys		
Delete Char	control-d or RUB	
Erase EOF	control-e	
Erase Input	control-w	
Insert Mode	ESC Space	
End Insert	ESC Space	
Program Function Keys		
PF1	ESC 1	
PF2	ESC 2	
...	...	
PF10	ESC 0	
PF11	ESC -	
PF12	ESC =	
PF13	ESC !	
PF14	ESC @	
...	...	
PF24	ESC +	
Program Attention Keys		
PA1	control-p 1	
PA2	control-p 2	
PA3	control-p 3	
Local Control Keys		
Reset After Error	control-r	
Purge Input Buffer	control-x	
Keyboard Unlock	control-t	
Redisplay Screen	control-v	
Other Keys		
Erase current field	control-u	

FILES

/etc/map3270

SEE ALSO

tn3270(1), mset(1), *Yale ASCII Terminal Communication System II Program Description/Operator's Manual* (IBM SB30-1911)

AUTHOR

Greg Minshall

BUGS

Tn3270 doesn't yet understand how to process all the functions available in *map3270*; when such a function is requested *tn3270* will beep at you.

The definition of "word" (for "word delete", "word tab") should be a run-time option. Currently it is defined as the kernel tty driver defines it (strings of non-blanks); more than one person would rather use the "vi" definition (strings of specials, strings of alphanumeric).

NAME

mtab – mounted file system table

SYNOPSIS

```
#include <fstab.h>
```

```
#include <mtab.h>
```

DESCRIPTION

Mtab resides in directory */etc* and contains a table of devices mounted by the *mount* command. *Umount* removes entries.

The table is a series of *mtab* structures, as defined in *<mtab.h>*. Each entry contains the null-padded name of the place where the special file is mounted, the null-padded name of the special file, and a type field, one of those defined in *<fstab.h>*. The special file has all its directories stripped away; that is, everything through the last '/' is thrown away. The type field indicates if the file system is mounted read-only, read-write, or read-write with disk quotas enabled.

This table is present only so people can look at it. It does not matter to *mount* if there are duplicated entries nor to *umount* if a name cannot be found.

FILES

/etc/mtab

SEE ALSO

mount(8)

NAME

networks – network name data base

DESCRIPTION

The *networks* file contains information regarding the known networks which comprise the DARPA Internet. For each network a single line should be present with the following information:

official network name

network number

aliases

Items are separated by any number of blanks and/or tab characters. A “#” indicates the beginning of a comment; characters up to the end of the line are not interpreted by routines which search the file. This file is normally created from the official network data base maintained at the Network Information Control Center (NIC), though local changes may be required to bring it up to date regarding unofficial aliases and/or unknown networks.

Network number may be specified in the conventional “.” notation using the *inet_network()* routine from the Internet address manipulation library, *inet(3N)*. Network names may contain any printable character other than a field delimiter, newline, or comment character.

FILES

/etc/networks

SEE ALSO

getnetent(3N)

BUGS

A name server should be used instead of a static file.

NAME

passwd – password file

DESCRIPTION

Passwd contains for each user the following information:

- name (login name, contains no upper case)
- encrypted password
- numerical user ID
- numerical group ID
- user's real name, office, extension, home phone.
- initial working directory
- program to use as Shell

The name may contain '&', meaning insert the login name. This information is set by the *chfn*(1) command and used by the *finger*(1) command.

This is an ASCII file. Each field within each user's entry is separated from the next by a colon. Each user is separated from the next by a new-line. If the password field is null, no password is demanded; if the Shell field is null, then */bin/sh* is used.

This file resides in directory */etc*. Because of the encrypted passwords, it can and does have general read permission and can be used, for example, to map numerical user ID's to names.

Appropriate precautions must be taken to lock the file against changes if it is to be edited with a text editor; *vipw*(8) does the necessary locking.

FILES

/etc/passwd

SEE ALSO

getpwent(3), *login*(1), *crypt*(3), *passwd*(1), *group*(5), *chfn*(1), *finger*(1), *vipw*(8), *adduser*(8)

BUGS

User information (name, office, etc.) should be stored elsewhere.

NAME

phones – remote host phone number data base

DESCRIPTION

The file `/etc/phones` contains the system-wide private phone numbers for the `tip(1C)` program. This file is normally unreadable, and so may contain privileged information. The format of the file is a series of lines of the form: `<system-name>[ \t]*<phone-number>`. The system name is one of those defined in the `remote(5)` file and the phone number is constructed from any sequence of characters terminated only by “,” or the end of the line. The “=” and “*” characters are indicators to the auto call units to pause and wait for a second dial tone (when going through an exchange). The “=” is required by the DF02-AC and the “*” is required by the BIZCOMP 1030.

Only one phone number per line is permitted. However, if more than one line in the file contains the same system name `tip(1C)` will attempt to dial each one in turn, until it establishes a connection.

FILES

`/etc/phones`

SEE ALSO

`tip(1C)`, `remote(5)`

NAME

plot – graphics interface

DESCRIPTION

Files of this format are produced by routines described in *plot(3X)* and *plot(3F)*, and are interpreted for various devices by commands described in *plot(1G)*. A graphics file is a stream of plotting instructions. Each instruction consists of an ASCII letter usually followed by bytes of binary information. The instructions are executed in order. A point is designated by four bytes representing the x and y values; each value is a signed integer. The last designated point in an l, m, n, a, or p instruction becomes the 'current point' for the next instruction. The a and c instructions change the current point in a manner dependent upon the specific device.

Each of the following descriptions begins with the name of the corresponding routine in *plot(3X)*.

- m** move: The next four bytes give a new current point.
- n** cont: Draw a line from the current point to the point given by the next four bytes.
- p** point: Plot the point given by the next four bytes.
- l** line: Draw a line from the point given by the next four bytes to the point given by the following four bytes.
- t** label: Place the following ASCII string so that its first character falls on the current point. The string is terminated by a newline.
- a** arc: The first four bytes give the center, the next four give the starting point, and the last four give the end point of a circular arc. The least significant coordinate of the end point is used only to determine the quadrant. The arc is drawn counter-clockwise.
- c** circle: The first four bytes give the center of the circle, the next two the radius.
- e** erase: Start another frame of output.
- f** linemod: Take the following string, up to a newline, as the style for drawing further lines. The styles are 'dotted,' 'solid,' 'longdashed,' 'shortdashed,' and 'dotdashed.' Effective only in *plot 4014* and *plot ver*.
- s** space: The next four bytes give the lower left corner of the plotting area; the following four give the upper right corner. The plot will be magnified or reduced to fit the device as closely as possible.

Space settings that exactly fill the plotting area with unity scaling appear below for devices supported by the filters of *plot(1G)*. The upper limit is just outside the plotting area. In every case the plotting area is taken to be square; points outside may be displayable on devices whose face isn't square.

```
4013      space(0, 0, 780, 780);
4014      space(0, 0, 3120, 3120);
ver       space(0, 0, 2048, 2048);
300, 300s space(0, 0, 4096, 4096);
450       space(0, 0, 4096, 4096);
```

SEE ALSO

plot(1G), plot(3X), plot(3F), graph(1G)

NAME

printcap – printer capability data base

SYNOPSIS

/etc/printcap

DESCRIPTION

Printcap is a simplified version of the *termcap*(5) data base used to describe line printers. The spooling system accesses the *printcap* file every time it is used, allowing dynamic addition and deletion of printers. Each entry in the data base is used to describe one printer. This data base may not be substituted for, as is possible for *termcap*, because it may allow accounting to be bypassed.

The default printer is normally *lp*, though the environment variable **PRINTER** may be used to override this. Each spooling utility supports an option, **-Pprinter**, to allow explicit naming of a destination printer.

Refer to the *4.3BSD Line Printer Spooler Manual* for a complete discussion on how setup the database for a given printer.

CAPABILITIES

Refer to *termcap*(5) for a description of the file layout.

Name	Type	Default	Description
af	str	NULL	name of accounting file
br	num	none	if lp is a tty, set the baud rate (ioctl call)
cf	str	NULL	cifplot data filter
df	str	NULL	tex data filter (DVI format)
fc	num	0	if lp is a tty, clear flag bits (sgtty.h)
ff	str	"\f"	string to send for a form feed
fo	bool	false	print a form feed when device is opened
fs	num	0	like 'fc' but set bits
gf	str	NULL	graph data filter (plot (3X) format)
hl	bool	false	print the burst header page last
ic	bool	false	driver supports (non standard) ioctl to indent printout
if	str	NULL	name of text filter which does accounting
lf	str	"/dev/console"	error logging file name
lo	str	"lock"	name of lock file
lp	str	"/dev/lp"	device name to open for output
mx	num	1000	maximum file size (in BUFSIZ blocks), zero = unlimited
nd	str	NULL	next directory for list of queues (unimplemented)
nf	str	NULL	ditroff data filter (device independent troff)
of	str	NULL	name of output filtering program
pc	num	200	price per foot or page in hundredths of cents
pl	num	66	page length (in lines)
pw	num	132	page width (in characters)
px	num	0	page width in pixels (horizontal)
py	num	0	page length in pixels (vertical)
rf	str	NULL	filter for printing FORTRAN style text files
rg	str	NULL	restricted group. Only members of group allowed access
rm	str	NULL	machine name for remote printer
rp	str	"lp"	remote printer name argument
rs	bool	false	restrict remote users to those with local accounts
rw	bool	false	open the printer device for reading and writing
sb	bool	false	short banner (one line only)
sc	bool	false	suppress multiple copies

sd	str	"/usr/spool/lpd"	spool directory
sf	bool	false	suppress form feeds
sh	bool	false	suppress printing of burst page header
st	str	"status"	status file name
tf	str	NULL	troff data filter (cat phototypesetter)
tr	str	NULL	trailer string to print when queue empties
vf	str	NULL	raster image filter
xc	num	0	if lp is a tty, clear local mode bits (tty (4))
xs	num	0	like 'xc' but set bits

If the local line printer driver supports indentation, the daemon must understand how to invoke it.

FILTERS

The *lpd(8)* daemon creates a pipeline of *filters* to process files for various printer types. The filters selected depend on the flags passed to *lpr(1)*. The pipeline set up is:

-p	pr		if	regular text + <i>pr(1)</i>
	none		if	regular text
-c	cf			cifplot
-d	df			DVI (tex)
-g	gf			<i>plot(3)</i>
-n	nf			ditroff
-f	rf			Fortran
-t	tf			troff
-v	vf			raster image

The *if* filter is invoked with arguments:

```
if[ -c ] -wwidth -llength -liindent -n login -h host acct-file
```

The *-c* flag is passed only if the *-l* flag (pass control characters literally) is specified to *lpr*. *Width* and *length* specify the page width and length (from *pw* and *pl* respectively) in characters. The *-n* and *-h* parameters specify the login name and host name of the owner of the job respectively. *Acct-file* is passed from the *af* *printcap* entry.

If no *if* is specified, *of* is used instead, with the distinction that *of* is opened only once, while *if* is opened for every individual job. Thus, *if* is better suited to performing accounting. The *of* is only given the *width* and *length* flags.

All other filters are called as:

```
filter -xwidth -ylength -n login -h host acct-file
```

where *width* and *length* are represented in pixels, specified by the *px* and *py* entries respectively.

All filters take *stdin* as the file, *stdout* as the printer, may log either to *stderr* or using *syslog(3)*, and must not ignore SIGINT.

LOGGING

Error messages generated by the line printer programs themselves (that is, the *lp** programs) are logged by *syslog(3)* using the *LPR* facility. Messages printed on *stderr* of one of the filters are sent to the corresponding *lf* file. The filters may, of course, use *syslog* themselves.

Error messages sent to the console have a carriage return and a line feed appended to them, rather than just a line feed.

SEE ALSO

termcap(5), lpc(8), lpd(8), pac(8), lpr(1), lpq(1), lprm(1)
4.3BSD Line Printer Spooler Manual

NAME

protocols – protocol name data base

DESCRIPTION

The *protocols* file contains information regarding the known protocols used in the DARPA Internet. For each protocol a single line should be present with the following information:

official protocol name
protocol number
aliases

Items are separated by any number of blanks and/or tab characters. A “#” indicates the beginning of a comment; characters up to the end of the line are not interpreted by routines which search the file.

Protocol names may contain any printable character other than a field delimiter, newline, or comment character.

FILES

/etc/protocols

SEE ALSO

getprotoent(3N)

BUGS

A name server should be used instead of a static file.

NAME

remote – remote host description file

DESCRIPTION

The systems known by *tip*(1C) and their attributes are stored in an ASCII file which is structured somewhat like the *termcap*(5) file. Each line in the file provides a description for a single system. Fields are separated by a colon (":"). Lines ending in a \ character with an immediately following newline are continued on the next line.

The first entry is the name(s) of the host system. If there is more than one name for a system, the names are separated by vertical bars. After the name of the system comes the fields of the description. A field name followed by an '=' sign indicates a string value follows. A field name followed by a '#' sign indicates a following numeric value.

Entries named "tip*" and "cu*" are used as default entries by *tip*, and the *cu* interface to *tip*, as follows. When *tip* is invoked with only a phone number, it looks for an entry of the form "tip300", where 300 is the baud rate with which the connection is to be made. When the *cu* interface is used, entries of the form "cu300" are used.

CAPABILITIES

Capabilities are either strings (str), numbers (num), or boolean flags (bool). A string capability is specified by *capability=value*; e.g. "dv=/dev/harris". A numeric capability is specified by *capability#value*; e.g. "xa#99". A boolean capability is specified by simply listing the capability.

- at** (str) Auto call unit type.
- br** (num) The baud rate used in establishing a connection to the remote host. This is a decimal number. The default baud rate is 300 baud.
- cm** (str) An initial connection message to be sent to the remote host. For example, if a host is reached through port selector, this might be set to the appropriate sequence required to switch to the host.
- cu** (str) Call unit if making a phone call. Default is the same as the 'dv' field.
- di** (str) Disconnect message sent to the host when a disconnect is requested by the user.
- du** (bool) This host is on a dial-up line.
- dv** (str) UNIX device(s) to open to establish a connection. If this file refers to a terminal line, *tip*(1C) attempts to perform an exclusive open on the device to insure only one user at a time has access to the port.
- el** (str) Characters marking an end-of-line. The default is NULL. "" escapes are only recognized by *tip* after one of the characters in 'el', or after a carriage-return.
- fs** (str) Frame size for transfers. The default frame size is equal to BUFSIZ.
- hd** (bool) The host uses half-duplex communication, local echo should be performed.
- ie** (str) Input end-of-file marks. The default is NULL.
- oe** (str) Output end-of-file string. The default is NULL. When *tip* is transferring a file, this string is sent at end-of-file.
- pa** (str) The type of parity to use when sending data to the host. This may be one of "even", "odd", "none", "zero" (always set bit 8 to zero), "one" (always set bit 8 to 1). The default is even parity.
- pn** (str) Telephone number(s) for this host. If the telephone number field contains an @ sign, *tip* searches the file */etc/phones* file for a list of telephone numbers; c.f. *phones*(5).

tc (str) Indicates that the list of capabilities is continued in the named description. This is used primarily to share common capability information.

Here is a short example showing the use of the capability continuation feature:

```
UNIX-1200:\
:dv=/dev/cau0:el=~D~U~C~S~Q~O@:du:at=ventel:ie=#$:oe=~D:br#1200:
arpavax|ax:\
:pn=7654321%:tc=UNIX-1200
```

FILES

/etc/remote

SEE ALSO

tip(1C), phones(5)

NAME

resolver configuration file

SYNOPSIS

/etc/resolv.conf

DESCRIPTION

The resolver configuration file contains information that is read by the resolver routines the first time they are invoked by a process. The file is designed to be human readable and contains a list of name-value pairs that provide various types of resolver information.

On a normally configured system this file should not be necessary. The only name server to be queried will be on the local machine and the domain name is retrieved from the system.

The different configuration options are:

nameserver

followed by the Internet address (in dot notation) of a name server that the resolver should query. At least one name server should be listed. Up to MAXNS (currently 3) name servers may be listed, in that case the resolver library queries tries them in the order listed. If no **nameserver** entries are present, the default is to use the name server on the local machine. (The algorithm used is to try a name server, and if the query times out, try the next, until out of name servers, then repeat trying all the name servers until a maximum number of retries are made).

domain followed by a domain name, that is the default domain to append to names that do not have a dot in them. If no **domain** entries are present, the domain returned by *gethostname(2)* is used (everything after the first '.'). Finally, if the host name does not contain a domain part, the root domain is assumed.

The name value pair must appear on a single line, and the keyword (e.g. **nameserver**) must start the line. The value follows the keyword, separated by white space.

FILES

/etc/resolv.conf

SEE ALSO

gethostbyname(3N), *resolver(3)*, *named(8)*
Name Server Operations Guide for BIND

NAME

services – service name data base

DESCRIPTION

The *services* file contains information regarding the known services available in the DARPA Internet. For each service a single line should be present with the following information:

official service name

port number

protocol name

aliases

Items are separated by any number of blanks and/or tab characters. The port number and protocol name are considered a single *item*; a “/” is used to separate the port and protocol (e.g. “512/tcp”). A “#” indicates the beginning of a comment; characters up to the end of the line are not interpreted by routines which search the file.

Service names may contain any printable character other than a field delimiter, newline, or comment character.

FILES

/etc/services

SEE ALSO

getservent(3N)

BUGS

A name server should be used instead of a static file.

NAME

stab – symbol table types

SYNOPSIS

#include <stab.h>

DESCRIPTION

Stab.h defines some values of the *n_type* field of the symbol table of *a.out* files. These are the types for permanent symbols (i.e. not local labels, etc.) used by the old debugger *sdb* and the Berkeley Pascal compiler *pc(1)*. Symbol table entries can be produced by the *.stabs* assembler directive. This allows one to specify a double-quote delimited name, a symbol type, one char and one short of information about the symbol, and an unsigned long (usually an address). To avoid having to produce an explicit label for the address field, the *.stabd* directive can be used to implicitly address the current location. If no name is needed, symbol table entries can be generated using the *.stabsn* directive. The loader promises to preserve the order of symbol table entries produced by *.stab* directives. As described in *a.out(5)*, an element of the symbol table consists of the following structure:

```
/*
 * Format of a symbol table entry.
 */
struct nlist {
    union {
        char *n_name; /* for use when in-core */
        long n_strx;  /* index into file string table */
    } n_un;
    unsigned char n_type; /* type flag */
    char n_other; /* unused */
    short n_desc; /* see struct desc, below */
    unsigned n_value; /* address or offset or line */
};
```

The low bits of the *n_type* field are used to place a symbol into at most one segment, according to the following masks, defined in <*a.out.h*>. A symbol can be in none of these segments by having none of these segment bits set.

```
/*
 * Simple values for n_type.
 */
#define N_UNDF 0x0 /* undefined */
#define N_ABS 0x2 /* absolute */
#define N_TEXT 0x4 /* text */
#define N_DATA 0x6 /* data */
#define N_BSS 0x8 /* bss */

#define N_EXT 01 /* external bit, or'ed in */
```

The *n_value* field of a symbol is relocated by the linker, *ld(1)* as an address within the appropriate segment. *N_value* fields of symbols not in any segment are unchanged by the linker. In addition, the linker will discard certain symbols, according to rules of its own, unless the *n_type* field has one of the following bits set:

```
/*
 * Other permanent symbol table entries have some of the N_STAB bits set.
 * These are given in <stab.h>
 */
#define N_STAB 0xe0 /* if any of these bits set, don't discard */
```

This allows up to 112 (7 * 16) symbol types, split between the various segments. Some of these have already been claimed. The old symbolic debugger, *sdb*, uses the following *n_type* values:

```
#define N_GSYM 0x20 /* global symbol: name,,0,type,0 */
#define N_FNAME 0x22 /* procedure name (f77 kludge): name,,0 */
#define N_FUN 0x24 /* procedure: name,,0,linenumber,address */
#define N_STSYM 0x26 /* static symbol: name,,0,type,address */
#define N_LCSYM 0x28 /* .lcomm symbol: name,,0,type,address */
#define N_RSYM 0x40 /* register sym: name,,0,type,register */
#define N_SLINE 0x44 /* src line: 0,,0,linenumber,address */
#define N_SSYM 0x60 /* structure elt: name,,0,type,struct_offset */
#define N_SO 0x64 /* source file name: name,,0,0,address */
#define N_LSYM 0x80 /* local sym: name,,0,type,offset */
#define N_SOL 0x84 /* #included file name: name,,0,0,address */
#define N_PSYM 0xa0 /* parameter: name,,0,type,offset */
#define N_ENTRY 0xa4 /* alternate entry: name,linenumber,address */
#define N_LBRAC 0xc0 /* left bracket: 0,,0,nesting level,address */
#define N_RBRAC 0xe0 /* right bracket: 0,,0,nesting level,address */
#define N_BCOMM 0xe2 /* begin common: name,, */
#define N_ECOMM 0xe4 /* end common: name,, */
#define N_ECOML 0xe8 /* end common (local name): ,,address */
#define N_LENG 0xfe /* second stab entry with length information */
```

where the comments give *sdb* conventional use for *.stabs* and the *n_name*, *n_other*, *n_desc*, and *n_value* fields of the given *n_type*. *Sdb* uses the *n_desc* field to hold a type specifier in the form used by the Portable C Compiler, *cc(1)*; see the header file *pcc.h* for details on the format of these type values.

The Berkeley Pascal compiler, *pc(1)*, uses the following *n_type* value:

```
#define N_PC 0x30 /* global pascal symbol: name,,0,subtype,line */
```

and uses the following subtypes to do type checking across separately compiled files:

- | | |
|----|--------------------|
| 1 | source file name |
| 2 | included file name |
| 3 | global label |
| 4 | global constant |
| 5 | global type |
| 6 | global variable |
| 7 | global function |
| 8 | global procedure |
| 9 | external function |
| 10 | external procedure |
| 11 | library variable |
| 12 | library routine |

SEE ALSO

as(1), *ld(1)*, *dbx(1)*, *a.out(5)*

BUGS

More basic types are needed.

NAME

tar - tape archive file format

DESCRIPTION

Tar, (the tape archive command) dumps several files into one, in a medium suitable for transportation.

A "tar tape" or file is a series of blocks. Each block is of size TBLOCK. A file on the tape is represented by a header block which describes the file, followed by zero or more blocks which give the contents of the file. At the end of the tape are two blocks filled with binary zeros, as an end-of-file indicator.

The blocks are grouped for physical I/O operations. Each group of *n* blocks (where *n* is set by the *b* keyletter on the *tar*(1) command line — default is 20 blocks) is written with a single system call; on nine-track tapes, the result of this write is a single tape record. The last group is always written at the full size, so blocks after the two zero blocks contain random data. On reading, the specified or default group size is used for the first read, but if that read returns less than a full tape block, the reduced block size is used for further reads.

The header block looks like:

```
#define TBLOCK      512
#define NAMSIZ      100

union hblock {
    char dummy[TBLOCK];
    struct header {
        char name[NAMSIZ];
        char mode[8];
        char uid[8];
        char gid[8];
        char size[12];
        char mtime[12];
        char chksum[8];
        char linkflag;
        char linkname[NAMSIZ];
    } dbuf;
};
```

Name is a null-terminated string. The other fields are zero-filled octal numbers in ASCII. Each field (of width *w*) contains *w*-2 digits, a space, and a null, except *size* and *mtime*, which do not contain the trailing null and *chksum* which has a null followed by a space. *Name* is the name of the file, as specified on the *tar* command line. Files dumped because they were in a directory which was named in the command line have the directory name as prefix and */filename* as suffix. *Mode* is the file mode, with the top bit masked off. *Uid* and *gid* are the user and group numbers which own the file. *Size* is the size of the file in bytes. Links and symbolic links are dumped with this field specified as zero. *Mtime* is the modification time of the file at the time it was dumped. *Chksum* is an octal ASCII value which represents the sum of all the bytes in the header block. When calculating the checksum, the *chksum* field is treated as if it were all blanks. *Linkflag* is NULL if the file is "normal" or a special file, ASCII '1' if it is an hard link, and ASCII '2' if it is a symbolic link. The name linked-to, if any, is in *linkname*, with a trailing null. Unused fields of the header are binary zeros (and are included in the checksum).

The first time a given i-node number is dumped, it is dumped as a regular file. The second and subsequent times, it is dumped as a link instead. Upon retrieval, if a link entry is retrieved, but not the file it was linked to, an error message is printed and the tape must be manually re-scanned to retrieve the linked-to file.

The encoding of the header is designed to be portable across machines.

SEE ALSO

`tar(1)`

BUGS

Names or linknames longer than NAMSIZ produce error reports and cannot be dumped.

NAME

termcap – terminal capability data base

SYNOPSIS

/etc/termcap

DESCRIPTION

Termcap is a data base describing terminals, used, *e.g.*, by *vi*(1) and *curses*(3X). Terminals are described in *termcap* by giving a set of capabilities that they have and by describing how operations are performed. Padding requirements and initialization sequences are included in *termcap*.

Entries in *termcap* consist of a number of ':'-separated fields. The first entry for each terminal gives the names that are known for the terminal, separated by '|' characters. The first name is always two characters long and is used by older systems which store the terminal type in a 16-bit word in a system-wide data base. The second name given is the most common abbreviation for the terminal, the last name given should be a long name fully identifying the terminal, and all others are understood as synonyms for the terminal name. All names but the first and last should be in lower case and contain no blanks; the last name may well contain upper case and blanks for readability.

Terminal names (except for the last, verbose entry) should be chosen using the following conventions. The particular piece of hardware making up the terminal should have a root name chosen, thus "hp2621". This name should not contain hyphens. Modes that the hardware can be in or user preferences should be indicated by appending a hyphen and an indicator of the mode. Therefore, a "vt100" in 132-column mode would be "vt100-w". The following suffixes should be used where possible:

Suffix	Meaning	Example
-w	Wide mode (more than 80 columns)	vt100-w
-am	With automatic margins (usually default)	vt100-am
-nam	Without automatic margins	vt100-nam
-n	Number of lines on the screen	aaa-60
-na	No arrow keys (leave them in local)	concept100-na
-np	Number of pages of memory	concept100-4p
-rv	Reverse video	concept100-rv

CAPABILITIES

The characters in the *Notes* field in the table have the following meanings (more than one may apply to a capability):

- N indicates numeric parameter(s)
- P indicates that padding may be specified
- * indicates that padding may be based on the number of lines affected
- o indicates capability is obsolete

"Obsolete" capabilities have no *terminfo* equivalents, since they were considered useless, or are subsumed by other capabilities. New software should not rely on them at all.

Name	Type	Notes	Description
ae	str	(P)	End alternate character set
AL	str	(NP*)	Add <i>n</i> new blank lines
al	str	(P*)	Add new blank line
am	bool		Terminal has automatic margins
as	str	(P)	Start alternate character set
bc	str	(o)	Backspace if not ^H
bl	str	(P)	Audible signal (bell)
bs	bool	(o)	Terminal can backspace with ^H

bt	str	(P)	Back tab
bw	bool		le (backspace) wraps from column 0 to last column
CC	str		Terminal settable command character in prototype
cd	str	(P*)	Clear to end of display
ce	str	(P)	Clear to end of line
ch	str	(NP)	Set cursor column (horizontal position)
cl	str	(P*)	Clear screen and home cursor
CM	str	(NP)	Memory-relative cursor addressing
cm	str	(NP)	Screen-relative cursor motion
co	num		Number of columns in a line (See BUGS section below)
cr	str	(P)	Carriage return
cs	str	(NP)	Change scrolling region (VT100)
ct	str	(P)	Clear all tab stops
cv	str	(NP)	Set cursor row (vertical position)
da	bool		Display may be retained above the screen
dB	num	(o)	Milliseconds of bs delay needed (default 0)
db	bool		Display may be retained below the screen
DC	str	(NP*)	Delete <i>n</i> characters
dC	num	(o)	Milliseconds of cr delay needed (default 0)
dc	str	(P*)	Delete character
dF	num	(o)	Milliseconds of ff delay needed (default 0)
DL	str	(NP*)	Delete <i>n</i> lines
dl	str	(P*)	Delete line
dm	str		Enter delete mode
dN	num	(o)	Milliseconds of nl delay needed (default 0)
DO	str	(NP*)	Move cursor down <i>n</i> lines
do	str		Down one line
ds	str		Disable status line
dT	num	(o)	Milliseconds of horizontal tab delay needed (default 0)
dV	num	(o)	Milliseconds of vertical tab delay needed (default 0)
ec	str	(NP)	Erase <i>n</i> characters
ed	str		End delete mode
ei	str		End insert mode
eo	bool		Can erase overstrikes with a blank
EP	bool	(o)	Even parity
es	bool		Escape can be used on the status line
ff	str	(P*)	Hardcopy terminal page eject
fs	str		Return from status line
gn	bool		Generic line type (e.g. dialup, switch)
hc	bool		Hardcopy terminal
HD	bool	(o)	Half-duplex
hd	str		Half-line down (forward 1/2 linefeed)
ho	str	(P)	Home cursor
hs	bool		Has extra "status line"
hu	str		Half-line up (reverse 1/2 linefeed)
hz	bool		Cannot print ~s (Hazeltime)
il-i3	str		Terminal initialization strings (<i>terminfo</i> only)
IC	str	(NP*)	Insert <i>n</i> blank characters
ic	str	(P*)	Insert character
if	str		Name of file containing initialization string
im	str		Enter insert mode
in	bool		Insert mode distinguishes nulls
iP	str		Pathname of program for initialization (<i>terminfo</i> only)

ip	str	(P*)	Insert pad after character inserted
is	str		Terminal initialization string (<i>termcap</i> only)
it	num		Tabs initially every <i>n</i> positions
K1	str		Sent by keypad upper left
K2	str		Sent by keypad upper right
K3	str		Sent by keypad center
K4	str		Sent by keypad lower left
K5	str		Sent by keypad lower right
k0-k9	str		Sent by function keys 0-9
kA	str		Sent by insert-line key
ka	str		Sent by clear-all-tabs key
kb	str		Sent by backspace key
kC	str		Sent by clear-screen or erase key
kD	str		Sent by delete-character key
kd	str		Sent by down-arrow key
kE	str		Sent by clear-to-end-of-line key
ke	str		Out of "keypad transmit" mode
kF	str		Sent by scroll-forward/down key
kH	str		Sent by home-down key
kh	str		Sent by home key
kI	str		Sent by insert-character or enter-insert-mode key
kL	str		Sent by delete-line key
kl	str		Sent by left-arrow key
kM	str		Sent by insert key while in insert mode
km	bool		Has a "meta" key (shift, sets parity bit)
kN	str		Sent by next-page key
kn	num	(o)	Number of function (k0-k9) keys (default 0)
ko	str	(o)	Termcap entries for other non-function keys
kP	str		Sent by previous-page key
kR	str		Sent by scroll-backward/up key
kr	str		Sent by right-arrow key
kS	str		Sent by clear-to-end-of-screen key
ks	str		Put terminal in "keypad transmit" mode
kT	str		Sent by set-tab key
kt	str		Sent by clear-tab key
ku	str		Sent by up-arrow key
l0-l9	str		Labels on function keys if not "fn"
LC	bool	(o)	Lower-case only
LE	str	(NP)	Move cursor left <i>n</i> positions
le	str	(P)	Move cursor left one position
li	num		Number of lines on screen or page (See BUGS section below)
ll	str		Last line, first column
lm	num		Lines of memory if > li (0 means varies)
ma	str	(o)	Arrow key map (used by <i>vi</i> version 2 only)
mb	str		Turn on blinking attribute
md	str		Turn on bold (extra bright) attribute
me	str		Turn off all attributes
mh	str		Turn on half-bright attribute
mi	bool		Safe to move while in insert mode
mk	str		Turn on blank attribute (characters invisible)
ml	str	(o)	Memory lock on above cursor
mm	str		Turn on "meta mode" (8th bit)
mo	str		Turn off "meta mode"

mp	str	Turn on protected attribute
mr	str	Turn on reverse-video attribute
ms	bool	Safe to move in standout modes
mu	str (o)	Memory unlock (turn off memory lock)
nc	bool (o)	No correctly-working cr (Datamedia 2500, Hazeltine 2000)
nd	str	Non-destructive space (cursor right)
NL	bool (o)	\n is newline, not line feed
nl	str (o)	Newline character if not \n
ns	bool (o)	Terminal is a CRT but doesn't scroll
nw	str (P)	Newline (behaves like cr followed by do)
OP	bool (o)	Odd parity
os	bool	Terminal overstrikes
pb	num	Lowest baud where delays are required
pc	str	Pad character (default NUL)
pf	str	Turn off the printer
pk	str	Program function key <i>n</i> to type string <i>s</i> (<i>terminfo</i> only)
pl	str	Program function key <i>n</i> to execute string <i>s</i> (<i>terminfo</i> only)
pO	str (N)	Turn on the printer for <i>n</i> bytes
po	str	Turn on the printer
ps	str	Print contents of the screen
pt	bool (o)	Has hardware tabs (may need to be set with is)
px	str	Program function key <i>n</i> to transmit string <i>s</i> (<i>terminfo</i> only)
r1-r3	str	Reset terminal completely to sane modes (<i>terminfo</i> only)
rc	str (P)	Restore cursor to position of last sc
rf	str	Name of file containing reset codes
RI	str (NP)	Move cursor right <i>n</i> positions
rp	str (NP*)	Repeat character <i>c</i> <i>n</i> times
rs	str	Reset terminal completely to sane modes (<i>termcap</i> only)
sa	str (NP)	Define the video attributes
sc	str (P)	Save cursor position
se	str	End standout mode
SF	str (NP*)	Scroll forward <i>n</i> lines
sf	str (P)	Scroll text up
sg	num	Number of garbage chars left by so or se (default 0)
so	str	Begin standout mode
SR	str (NP*)	Scroll backward <i>n</i> lines
sr	str (P)	Scroll text down
st	str	Set a tab in all rows, current column
ta	str (P)	Tab to next 8-position hardware tab stop
tc	str	Entry of similar terminal - must be last
te	str	String to end programs that use <i>termcap</i>
ti	str	String to begin programs that use <i>termcap</i>
ts	str (N)	Go to status line, column <i>n</i>
UC	bool (o)	Upper-case only
uc	str	Underscore one character and move past it
ue	str	End underscore mode
ug	num	Number of garbage chars left by us or ue (default 0)
ul	bool	Underline character overstrikes
UP	str (NP*)	Move cursor up <i>n</i> lines
up	str	Upline (cursor up)
us	str	Start underscore mode
vb	str	Visible bell (must not move cursor)
ve	str	Make cursor appear normal (undo vs/vi)