
# ETSITS 131 124 V8.2.0 (2009-07)

Technical Specification

Universal Mobile Telecommunications System (UMTS);

LTE;

Mobile Equipment (ME) conformance test specification; Universal Subscriber Interface Module Application Toolkit (USAT) conformance test specification (3GPP TS 31.124 version 8.2.0 Release 8)



Reference
RTS/TSGC-0631124v820

Keywords
LTE, UMTS

#### **ETSI**

650 Route des Lucioles F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C Association à but non lucratif enregistrée à la Sous-Préfecture de Grasse (06) N° 7803/88

#### Important notice

Individual copies of the present document can be downloaded from: <u>http://www.etsi.org</u>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<a href="http://portal.etsi.org/tb/status/status.asp">http://portal.etsi.org/tb/status/status.asp</a></a>

If you find errors in the present document, please send your comment to one of the following services: http://portal.etsi.org/chaircor/ETSI\_support.asp

#### **Copyright Notification**

No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2009. All rights reserved.

**DECT**<sup>TM</sup>, **PLUGTESTS**<sup>TM</sup>, **UMTS**<sup>TM</sup>, **TIPHON**<sup>TM</sup>, the TIPHON logo and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.

**3GPP**<sup>™</sup> is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **LTE**<sup>™</sup> is a Trade Mark of ETSI currently being registered

for the benefit of its Members and of the 3GPP Organizational Partners. **GSM**® and the GSM logo are Trade Marks registered and owned by the GSM Association.

## Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (http://webapp.etsi.org/IPR/home.asp).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

#### **Foreword**

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <a href="http://webapp.etsi.org/key/queryform.asp">http://webapp.etsi.org/key/queryform.asp</a>.

## Contents

Intelle	ectual Property Rights	2
Forew	ord	2
Forew	/ord	9
1	Scope	10
2	References	11
3	Definitions and abbreviations	
3.1	Mobile station definition and configurations	12
3.2	Applicability	12
3.2.1	Applicability of the present document	12
3.2.2	Applicability of the individual tests	12
3.2.3	Applicability to terminal equipment	
3.2.4	Definitions	
3.2.4.1	Format of the table of optional features	12
3.2.4.2		
3.2.4.3		
3.3	Table of optional features	
3.4	Applicability table	
3.5	Conventions for mathematical notations	
3.5.1	Mathematical signs	82
4	Test equipment	82
5	Testing methodology in general	87
5.1	Testing of optional functions and procedures	
5.2	Test interfaces and facilities	
5.3	Information to be provided by the apparatus supplier	
6	Implicit testing.	
7	Measurement uncertainty	
	Format of tests	
8		
9	Generic call set up procedures.	
10 - 2	6Not used	
27	Testing of the UICC/ME interface	
27.1 -	27.21Void	86
27.22	USIM Application Toolkit	
27.22.	1 1	
27.22.2		87
27.22.		
	ME (Profile Download)	
27.22.		
27.22.	1	
27.22.	1 1	
27.22.		
27.22.		
27.22.		
27.22.		
27.22.		
27.22.		
27.22.	4	
27.22.	· ·	
27.22.2 27.22.2		93
1.1.1.1.	4.7.1 IIIIUAI CONGIUOTIS	7 7

27.22.1.4.2	Procedure	
27.22.2.5	Test requirement	
27.22.3	Servicing of proactive UICC commands	93
27.22.3.1	Definition and applicability	93
27.22.3.2	Conformance requirement	93
27.22.3.3	Test purpose	
27.22.3.4	Method of test	
27.22.3.4.1	Initial conditions	
27.22.3.4.2	Procedure	
27.22.3.4.2		
	Test requirement	
27.22.4	Proactive UICC commands	
27.22.4.1	DISPLAY TEXT	
27.22.4.1.1	DISPLAY TEXT (Normal)	
27.22.4.1.2	DISPLAY TEXT (Support of "No response from user")	
27.22.4.1.3	DISPLAY TEXT (Display of extension text)	
27.22.4.1.4	DISPLAY TEXT (Sustained text)	
27.22.4.1.5	DISPLAY TEXT (Display of icons)	99
27.22.4.1.6	DISPLAY TEXT (UCS2 display in Cyrillic)	100
27.22.4.1.7	DISPLAY TEXT (Variable Time out)	100
27.22.4.1.8	DISPLAY TEXT (Support of Text Attribute)	
27.22.4.1.9	DISPLAY TEXT (UCS2 display in Chinese)	
27.22.4.1.10	DISPLAY TEXT (UCS2 display in Katakana)	
27.22.4.2	GET INKEY	
27.22.4.2.1	GET INKEY(normal)	
27.22.4.2.1	GET INKEY (No response from User)	
	GET INKEY (UCS2 display in Cyrillic)	
27.22.4.2.3		
27.22.4.2.4	GET INKEY (UCS2 entry in Cyrillic)	
27.22.4.2.5	GET INKEY ("Yes/No" Response)	
27.22.4.2.6	GET INKEY (display of Icon)	
27.22.4.2.7	GET INKEY (Help Information)	
27.22.4.2.8	GET INKEY (Variable Time out)	
27.22.4.2.9	GET INKEY (Support of Text Attribute)	
27.22.4.2.10	GET INKEY (UCS2 display in Chinese)	123
27.22.4.2.11	GET INKEY (UCS2 entry in Chinese)	123
27.22.4.2.12	GET INKEY (UCS2 display in Katakana)	124
27.22.4.2.13	GET INKEY (UCS2 entry in Katakana)	125
27.22.4.3	GET INPUT	126
27.22.4.3.1	GET INPUT (normal)	126
27.22.4.3.2	GET INPUT (No response from User)	
27.22.4.3.3	GET INPUT (UCS2 display in Cyrillic)	
27.22.4.3.4	GET INPUT (UCS2 entry in Cyrillic)	
27.22.4.3.5	GET INPUT (default text)	
27.22.4.3.6	GET INPUT (display of Icon)	
27.22.4.3.7	GET INPUT (Help Information)	
27.22.4.3.7	GET INPUT (Support of Text Attribute)	
27.22.4.3.9	GET INPUT (UCS2 display in Chinese)	
27.22.4.3.10	GET INPUT (UCS2 entry in Chinese)	
27.22.4.3.11	GET INPUT (UCS2 display in Katakana)	
27.22.4.3.12	GET INPUT (UCS2 entry in Katakana)	
27.22.4.4	MORE TIME	
27.22.4.4.2	Conformance requirement	
27.22.4.4.3	Test purpose	
27.22.4.4.4	Method of test	
27.22.4.4.5	Test requirement	142
27.22.4.5	PLAY TONE	142
27.22.4.5.1	PLAY TONE (Normal)	142
27.22.4.5.2	PLAY TONE (UCS2 display in Cyrillic)	
27.22.4.5.3	PLAY TONE (display of Icon)	
27.22.4.5.4	PLAY TONE (Support of Text Attribute)	
27.22.4.5.5	PLAY TONE (UCS2 display in Chinese)	
27.22.4.5.6	PLAY TONE (UCS2 display in Katakana)	
27.22.4.5.0	POLL INTERVAL	

27.22.4.6.1	Definition and applicability	
27.22.4.6.2	Conformance requirement	
27.22.4.6.3	Test purpose	
27.22.4.6.4	Method of test	
27.22.4.7	REFRESH	
27.22.4.7.1	REFRESH (normal)	
27.22.4.7.2	REFRESH (IMSI changing procedure)	
27.22.4.7.3	REFRESH (Steering of roaming)	
27.22.4.7.4	EF <sub>FPLMN</sub>	172
27.22.4.8	SET UP MENU and ENVELOPE MENU SELECTION	
27.22.4.8.1	SET UP MENU (normal) and ENVELOPE MENU SELECTION	
27.22.4.8.2	SET UP MENU (help request support) and ENVELOPE MENU SELECTION	
27.22.4.8.3	SET UP MENU (next action support) and ENVELOPE MENU SELECTION	
27.22.4.8.4	SET UP MENU (display of icons) and ENVELOPE MENU SELECTION	
27.22.4.8.5	SET UP MENU (soft keys support) and ENVELOPE MENU SELECTION	
27.22.4.8.6	SET UP MENU (support of Text Attribute) and ENVELOPE MENU SELECTION	
27.22.4.8.7 27.22.4.8.8	SET UP MENU (UCS2 display in Cyrillic) and ENVELOPE MENU SELECTION SET UP MENU (UCS2 display in Chinese) and ENVELOPE MENU SELECTION	
27.22.4.8.9	SET UP MENU (UCS2 display in Chinese) and ENVELOPE MENU SELECTION	
27.22.4.9	SELECT ITEMSELECT ITEM	
27.22.4.9	SELECT ITEM (mandatory features for ME supporting SELECT ITEM)	
27.22.4.9.1	SELECT ITEM (manuacity reactives for IME supporting SELECT ITEM)	
27.22.4.9.3	SELECT ITEM (default item support)	
27.22.4.9.4	SELECT ITEM (deltadit field support)	
27.22.4.9.5	SELECT ITEM (icons support)	
27.22.4.9.6	SELECT ITEM (presentation style)	
27.22.4.9.7	SELECT ITEM (soft keys support)	
27.22.4.9.8	SELECT ITEM (Support of "No response from user")	
27.22.4.9.9	SELECT ITEM (Support of Text Attribute)	
27.22.4.9.10	SELECT ITEM (UCS2 display in Cyrillic)	
27.22.4.9.11	SELECT ITEM (UCS2 display in Chinese)	205
27.22.4.9.12	SELECT ITEM (UCS2 display in Katakana)	206
27.22.4.10	SEND SHORT MESSAGE	
27.22.4.10.1	SEND SHORT MESSAGE (normal)	
27.22.4.10.2	SEND SHORT MESSAGE (UCS2 display in Cyrillic)	
27.22.4.10.3	SEND SHORT MESSAGE (icon support)	
27.22.4.10.4	SEND SHORT MESSAGE (Support of Text Attribute)	
27.22.4.10.5	SEND SHORT MESSAGE (UCS2 display in Chinese)	
27.22.4.10.6	SEND SHORT MESSAGE (UCS2 display in Katakana)	
27.22.4.11 27.22.4.11.1	SEND SS (normal)	
27.22.4.11.1	SEND SS (normal) SEND SS (Icon support).	
27.22.4.11.2	SEND SS (ICOI support)	
27.22.4.11.3	SEND SS (OCS2 display in Cyrinic)	
27.22.4.11.5	SEND SS (UCS2 display in Chinese)	
27.22.4.11.6	SEND SS (UCS2 display in Katakana)	
27.22.4.12	SEND USSD	
27.22.4.12.1	SEND USSD (normal)	
27.22.4.12.2	SEND USSD (Icon support)	
27.22.4.12.3	SEND USSD (UCS2 display in Cyrillic)	
27.22.4.12.4	SEND USSD (support of Text Attribute)	
27.22.4.12.5	SEND USSD (UCS2 display in Chinese)	
27.22.4.12.6	SEND USSD (UCS2 display in Katakana)	
27.22.4.13	SET UP CALL	
27.22.4.13.1	SET UP CALL (normal)	
27.22.4.13.2	SET UP CALL (second alpha identifier)	
27.22.4.13.3	SET UP CALL (display of icons)	
27.22.4.13.4	SET UP CALL (support of Text Attribute)	
27.22.4.13.5	SET UP CALL (UCS2 Display in <i>Cyrillic</i> )	
27.22.4.13.6	SET UP CALL (UCS2 Display in Chinese)	
27.22.4.13.7 27.22.4.14	SET UP CALL (UCS2 Display in Katakana) POLLING OFF	
41.44.14	I OLLINO OTT	403

27.22.4.14.1	Definition and applicability	463
27.22.4.14.2	Conformance requirement	463
27.22.4.14.3	Test purpose	463
27.22.4.14.4	Method of test	463
27.22.4.14.5	Test requirement	
27.22.4.15	PROVIDE LOCAL INFORMATION	466
27.22.4.15.1	Definition and applicability	466
27.22.4.15.2	Conformance requirement	466
27.22.4.15.3	Test purpose	466
27.22.4.15.4	Method of tests	467
27.22.4.15.5	Test requirement	476
27.22.4.16	SET UP EVENT LIST	
27.22.4.16.1	SET UP EVENT LIST (normal)	476
27.22.4.17	PERFORM CARD APDU	
27.22.4.17.1	PERFORM CARD APDU (normal)	
27.22.4.17.2	PERFORM CARD APDU (detachable card reader)	486
27.22.4.18	POWER OFF CARD	
27.22.4.18.1	POWER OFF CARD (normal)	
27.22.4.18.2	POWER OFF CARD (detachable card reader)	
27.22.4.19	POWER ON CARD	
27.22.4.19.1	POWER ON CARD (normal)	
27.22.4.19.2	POWER ON CARD (detachable card reader)	
27.22.4.20	GET READER STATUS	
27.22.4.20.1	GET READER STATUS (normal)	
27.22.4.20.2	GET CARD READER STATUS (detachable card reader)	
27.22.4.21	TIMER MANAGEMENT and ENVELOPE TIMER EXPIRATION	
27.22.4.21.1	TIMER MANAGEMENT (normal)	
27.22.4.21.2	ENVELOPE TIMER EXPIRATION (normal)	
27.22.4.22	SET UP IDLE MODE TEXT	
27.22.4.22.1	SET UP IDLE MODE TEXT (normal)	
27.22.4.22.2	SET UP IDLE MODE TEXT (Icon support)	
27.22.4.22.3	SET UP IDLE MODE TEXT (UCS2 support)	
27.22.4.22.4	SET UP IDLE MODE TEXT (support of Text Attribute)	
27.22.4.22.5	SET UP IDLE MODE TEXT (UCS2 display in Chinese)	
27.22.4.22.6	SET UP IDLE MODE TEXT (UCS2 display in Katakana)	
27.22.4.23	RUN AT COMMAND (named)	
27.22.4.23.1	RUN AT COMMAND (Joseph and St. 1984)	
27.22.4.23.2	RUN AT COMMAND (Icon support)	
27.22.4.23.3 27.22.4.23.4	RUN AT COMMAND (support of Text Attribute)	
27.22.4.23.4		
	RUN AT COMMAND (UCS2 display in Chinese)	
27.22.4.23.6 27.22.4.24	RUN AT COMMAND (UCS2 display in Katakana)	
27.22.4.24	SEND DTMF (Normal)	
27.22.4.24.1	SEND DTMF (Notifial)	
27.22.4.24.3	SEND DTMF (DCS2 display in Cyrillic)	
27.22.4.24.4	SEND DTMF (GCS2 display in Cylinic) SEND DTMF (support of Text Attribute)	
27.22.4.24.5	SEND DTMF (UCS2 Display in Chinese)	
27.22.4.24.6	SEND DTMF (UCS2 Display in Katakana)	
27.22.4.25	LANGUAGE NOTIFICATION	
27.22.4.25.1	Definition and applicability	
27.22.4.25.2	Conformance Requirement	
27.22.4.25.3	Test purpose	
27.22.4.25.4	Method of Test	
27.22.4.25.5	Test requirement	
27.22.4.26	LAUNCH BROWSER	
27.22.4.26.1	LAUNCH BROWSER (No session already launched)	
27.22.4.26.2	LAUNCH BROWSER (Interaction with current session)	
27.22.4.26.3	LAUNCH BROWSER (UCS2 display in Cyrillic)	
27.22.4.26.4	LAUNCH BROWSER (icons support)	
27.22.4.26.5	LAUNCH BROWSER (support of Text Attribute)	
27 22 4 26 6	I AUNCH BROWSER (UCS2 Display in Chinese)	66/

27.22.4.26.7	LAUNCH BROWSER (UCS2 Display in Katakana)	667
27.22.4.27	OPEN CHANNEL	669
27.22.4.27.2	Open Channel (related to GPRS)	669
27.22.4.27.3	Open Channel (default bearer)	681
27.22.4.27.4	Open Channel (Local Bearer)	
27.22.4.27.5	Open Channel (GPRS, support of Text Attribute)	
27.22.4.28	CLOSE CHANNEL	
27.22.4.28.1	CLOSE CHANNEL(normal)	
27.22.4.28.2	CLOSE CHANNEL (support of Text Attribute)	
27.22.4.29	RECEIVE DATA	
27.22.4.29.1	RECEIVE DATA (NORMAL)	
27.22.4.29.5	Test requirement	
27.22.4.29.2	RECEIVE DATA (support of Text Attribute)	
27.22.4.30	SEND DATA	
27.22.4.30.1	SEND DATA (normal)	
27.22.4.30.1	SEND DATA (support of Text Attribute)	
27.22.4.31	GET CHANNEL STATUS	
27.22.4.31.1	Definition and applicability	
27.22.4.31.1	Conformance requirements	
27.22.4.31.2	Test purpose	
27.22.4.31.3	Method of test	
27.22.4.31.4	Test requirement	
27.22.4.31.3	Data Download to UICC	
27.22.5.1	SMS-PP Data Download	
	Definition and applicability	
27.22.5.1.1	**	
27.22.5.1.2	Conformance requirement	
27.22.5.1.3 27.22.5.1.4	Test purpose	
	Method of Test	
27.22.5.1.5	Test requirement	
27.22.5.2 27.22.5.2.1	Cell Broadcast Data Download	
	Definition and applicability	
27.22.5.2.2	Conformance requirement	
27.22.5.2.3	Test purpose	
27.22.5.2.4	Method of Test	
27.22.5.2.5	Test requirement	
27.22.6	CALL CONTROL BY USIM	
27.22.6.1	Procedure for Mobile Originated calls	
27.22.6.1.1	Definition and applicability	
27.22.6.1.2	Conformance requirement	
27.22.6.1.3	Test purpose	
27.22.6.1.4	Method of tests	
27.22.6.1.5	Test requirement	
27.22.6.2	Procedure for Supplementary (SS) Services	
27.22.6.2.1	Definition and applicability	
27.22.6.2.2	Conformance requirement	
27.22.6.2.3	Test purpose	
27.22.6.2.4	Method of tests	
27.22.6.2.5	Test requirement	
27.22.6.3	Interaction with Fixed Dialling Number (FDN)	
27.22.6.3.1	Definition and applicability	
27.22.6.3.2	Conformance requirement	
27.22.6.3.3	Test purpose	
27.22.6.3.4	Method of tests	
27.22.6.3.5	Test requirement	
27.22.6.4	Support of Barred Dialling Number (BDN) service	
27.22.6.4.1	Definition and applicability	
27.22.6.4.2	Conformance requirement	
27.22.6.4.3	Test purpose	
27.22.6.4.4	Method of tests	
27.22.6.4.5	Test requirement	
27.22.6.5	Barred Dialling Number (BDN) service handling for terminals not supporting BDN	
27 22 6 5 1	Definition and applicability	9/15

Listory .	,	-	1000
Annex B (n Annex C (in	nformative):	Details of terminal profile support  Change history	
Annex A (n	•	Details of Test-SIM (TestSIM)	
27.22.9.5	Test requirer	nent	986
27.22.9.4.2		)	
27.22.9.4.1		nditions	
27.22.9.4		sts	
27.22.9.3			
27.22.9.2		e requirement	
27.22.9.1		d applicability	
27.22.9	Handling of con	mand number	985
27.22.8.5	Test requirer	nent	985
27.22.8.4.2		2	
27.22.8.4.1		nditions	
27.22.8.4		sts	
27.22.8.3		1	
27.22.8.2		e requirement	
27.22.8.1		d applicability	
27.22.8		ESSAGE CONTROL BY USIM	
27.22.7.15		tus event	
27.22.7.14		ch mode change event	
27.22.7.12		ction event	
27.22.7.11.4		nology Change event	
27.22.7.11.3		f test	
27.22.7.11.2		ose	
27.22.7.11.1		and applicatifity  ance requirements	
27.22.7.11		n and applicability	
27.22.7.10.4 27.22.7.11		it testus event	
27.22.7.10.3 27.22.7.10.4		ose	
27.22.7.10.2		ance requirementsose	
27.22.7.10.1		n and applicability	
27.22.7.10		e event	
27.22.7.9.1		rermination (normal)	
27.22.7.9		ination event	
27.22.7.8.1		selection event (normal)	
27.22.7.8		ection event	
27.22.7.7.2		der Status(detachable card reader)	
27.22.7.7.1		der Status (normal)	
27.22.7.7		tatus event	
27.22.7.6.1		en Available (normal)	
27.22.7.6		vailable event	
27.22.7.5.1	User Act	vity Event (normal)	961
27.22.7.5		Event	
27.22.7.4.1		Status Event (normal)	
27.22.7.4		tus Event	
27.22.7.3.1		onnected Event	
27.22.7.3		ected Event	
27.22.7.2.2		nected Event (ME supporting SET UP CALL)	
27.22.7.2.1		nected Event (MT and MO call)	
27.22.7.2		ed Event	
27.22.7.1		Event (normal)	
27.22.7		nt	
27.22.0.3.4		LOAD	
27.22.6.5.3 27.22.6.5.4		ose	
27.22.6.5.2		ance requirement	

## **Foreword**

This Technical Specification has been produced by the 3<sup>rd</sup> Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

#### where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

## 1 Scope

The present document describes the technical characteristics and methods of test for testing the USIM Application Toolkit implemented in 3<sup>rd</sup> Generation Mobile Equipments (ME) or Mobile Station (MS) for the 3G and 2G digital cellular communications systems within the 3GPP digital cellular telecommunications system, in compliance with the relevant requirements, and in accordance with the relevant guidance given in ISO/IEC 9646-7 [19] and ETSI ETS 300 406 [20].

The present document is valid for ME implemented according to 3GPP Release 99, or Release 4, or Release 5, or Release 6, or Release 7 or Release 8.

The present document covers the minimum characteristics considered necessary in order to provide sufficient performance for mobile equipment and to prevent interference to other services or to other users, and to the PLMNs.

It does not necessarily include all the characteristics which may be required by a user or subscriber, nor does it necessarily represent the optimum performance achievable.

The present document is part of the 3GPP-series of technical specifications. The present document neither replaces any of the other 3GPP technical specifications or 3GPP related ETSs or ENs, nor is it created to provide full understanding of (or parts of) the UMTS. The present document lists the requirements, and provides the methods of test for testing the USIM Application Toolkit implemented in a ME for conformance to the 3GPP standard.

For a full description of the system, reference should be made to all the 3GPP technical specifications or 3GPP related ETSIs, ETSs or ENs. Clause 2 provides a complete list of the 3GPP technical specifications, 3GPP related ETSI's ETSs, ENs, and ETRs, on which this conformance test specifications is based.

If there is a difference between this present conformance document, and any other 3GPP technical specification or 3GPP related ETSI, ETS, EN, or 3GPP TS, then the other 3GPP technical specification or 3GPP related ETSI ETS, EN or 3GPP TS shall prevail.

Within the context of this document, the term "terminal" used in ETSI TS 102 223 [16] refers to the Mobile Equipment (ME).

Within the context of this document, the term "UICC" used in ETSI TS 102 223 [16] refers to the USIM card.

Within the context of this document, the term "NAA" used in ETSI TS 102 223 [16] refers to the USIM application.

## 2 References

[20]

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the relevant Release*.
- References to 3GPP Technical Specifications and Technical Reports throughout the present document shall be
  interpreted according to the Release shown in the formal reference in this clause, based upon the Release of the
  implementation under test.
- 3GPP TR 21.905: "Vocabulary for 3GPP Specifications". [1] [2] 3GPP TS 22.001: "Principles of circuit telecommunication services supported by a Public Land Mobile Network (PLMN)". 3GPP TS 22.003: "Circuit Teleservices supported by a Public Land Mobile Network (PLMN)". [3] [4] 3GPP TS 22.004: "General on supplementary services". [5] ETSI TS 101 220: "ETSI numbering system for telecommunication application providers" 3GPP TS 21.904: "UE capability requirements" [6] [7] 3GPP TS 23.038: "Alphabets and language-specific information". [8] 3GPP TS 23.040: "Technical realization of the Short Message Service (SMS)". 3GPP TS 23.041: "Technical realization of Cell Broadcast Service (CBS)". [9] 3GPP TS 24.008: "Mobile radio interface layer 3 specification; Core network protocols; Stage 3". [10] 3GPP TS 24.011: "Point-to-Point (PP) Short Message Service (SMS) Support on mobile radio [11] interface". 3GPP TS 34.108: "Common test environments for User Equipment (UE) conformance testing". [12] ETSI TS 102 221: "UICC-Terminal interface; Physical and logical characteristics". [13] 3GPP TS 31.102: "Characteristics of the USIM application". [14] [15] 3GPP TS 31.111: "USIM Application Toolkit (USAT)" ETSI TS 102 223: "Smart cards; Card Application Toolkit (CAT)" [16] ISO/IEC 10646-1: "Information technology - Universal Multiple Octet Coded Character Set [17a] (UCS) - Part 1: Architecture and Basic Multilingual Plane". ISO/IEC 10646-2: "Information technology - Universal Multiple Octet Coded Character Set [17b] (UCS) - Part 2: Supplementary Planes". 3GPP TS 27.007: "AT command set for 3G User Equipment (UE)". [18] ISO/IEC 9646-7 (1995): "Information technology - Open Systems Interconnection - Conformance [19] testing methodology and framework - Part 7: Implementation Conformance Statements".

conformance testing specifications; Standardization methodology".

ETSI ETS 300 406 (1995): "Methods for Testing and Specification (MTS); Protocol and profile

[21]	3GPP TS 31.121: "UICC-terminal interface; USIM application test specification"
[22]	3GPP TS 22.101: "Service Aspects; Service principles"
[23]	3GPP TS 51.010-1: "Mobile Station (MS) conformance specification; Part 1: Conformance specification"
[24]	Void.
[25]	TIA/IS-820-A: "Removable User Identity Module (R-UIM) for TIA/EIA Spread Spectrum System".
[26]	ETSI TS 102 384: "Smart cards; UICC-Terminal interface; Card Application Toolkit (CAT) conformance specification".
[27]	3GPP TS 34.123-3: "User Equipment (UE) conformance specification; Part 3: Abstract test suites (ATSs)".
[28]	3GPP TS 31.115: "Secured packet structure for (U)SIM Toolkit applications".
[29]	3GPP TS 23.122: "Non-Access Stratum functions related to Mobile Station (MS) in idle mode".

### 3 Definitions and abbreviations

## 3.1 Mobile station definition and configurations

The mobile station definition and configurations specified in TS 34.108 [12] shall apply, unless otherwise specified in the present clause.

## 3.2 Applicability

### 3.2.1 Applicability of the present document

The present specification applies to a terminal equipment that supports the USIM Application Toolkit optional feature.

## 3.2.2 Applicability of the individual tests

Table A.1 lists the optional features for which the supplier of the implementation states the support.

## 3.2.3 Applicability to terminal equipment

The applicability to terminal equipment specified in TS 34.108 [12] shall apply, unless otherwise specified in the present clause.

Within the context of this document, the term "USS" refers to the 'UMTS System Simulator' when accessing a UTRAN and to the 'System Simulator' when accessing a GERAN.

See table B.1.

#### 3.2.4 Definitions

For the purposes of the present document, the terms and definitions given in TS 34.108 [12], , apply.

#### 3.2.4.1 Format of the table of optional features

Option: The optional feature supported or not by the implementation.

Support Answer notation: The support columns shall be filled in by the supplier of the implementation. The following common notations, defined in ISO/IEC 9646-7 [19], are used for the support column in the tables below.

Y or y supported by the implementation

N or n not supported by the implementation

N/A, n/a or - no answer required (allowed only if the status is N/A, directly or after evaluation of a conditional

status)

Mnemonic column: The Mnemonic column contains mnemonic identifiers for each item.

#### 3.2.4.2 Format of the applicability table

The applicability of every test in table B.1 is formally expressed by the use of Boolean expression defined in the following clause.

The columns in table B.1 have the following meaning:

- In the "Item" column a local entry number for the requirement in the table is given.
- In the "Description" column a short non-exhaustive description of the requirement is found.
- The "Release" column gives the Release applicable and onwards, for the item in the "Description" column
- The "Test Sequence(s)" column gives a reference to the test sequence number(s) detailed in the present document and required to validate the implementation of the corresponding item in the "Description" column.
- For a given Release, the corresponding "Rel X ME" column lists the tests required for a Mobile Station to be declared compliant to this Release.
- The "Support" column is blank in the proforma, and shall be completed by the manufacturer in respect of each particular requirement to indicate the choices, which have been made in the implementation.
- The "Network Dependency" column indicates if a test depends on specific network access technology or requires network connection, but the status may not have an impact on references to ETSI TS 102 384 [26].
- The "Terminal Profile" column gives a reference to the corresponding bit that needs to be present in the Terminal Profile.
- The "Additional test case execution parameter" column shall be used in conjunction with the entry in the "Rel-xx ME" column. The column indicates if the test is affected by additional test case execution parameters.

#### 3.2.4.3 Status and notations

"Release X ME" columns show the status of the entries as follows:

The following notations, defined in ISO/IEC 9646-7 [19], are used for the status column:

M mandatory - the capability is required to be supported.

O optional - the capability may be supported or not.

N/A not applicable - in the given context, it is impossible to use the capability.

X prohibited (excluded) - there is a requirement not to use this capability in the given context.

O.i qualified optional - for mutually exclusive or selectable options from a set. "i" is an integer which identifies an unique group of related optional items and the logic of their selection which is

defined immediately following the table.

Ci conditional - the requirement on the capability ("M", "O", "X" or "N/A") depends on the support of other optional or conditional items. "i" is an integer identifying an unique conditional status expression which is defined immediately following the table. For nested conditional expressions, the syntax "IF ... THEN (IF ... THEN ... ELSE...) ELSE ..." shall be used to avoid ambiguities.

The "Additional test case execution parameter" column shows the status of the entries as follows:

TCEPi Test Case Execution Parameter –defines additional parameters which have to be taken into

account when executing affected test case(s). "i" is an integer identifying an unique parameter

which is defined immediately following the table.

References to items: For each possible item answer (answer in the support column) there exists a unique reference, used, for example, in the conditional expressions. It is defined as the table identifier, followed by a solidus character "/", followed by the item number in the table. If there is more than one support column in a table, the columns shall be discriminated by letters (a, b, etc.), respectively.

EXAMPLE: A.1/4 is the reference to the answer of item 4 in table A.1.

### 3.3 Table of optional features

Support of USIM Application Toolkit is optional for Mobile Equipment. However, if an ME states conformance with a specific 3GPP release, it is mandatory for the ME to support all functions of that release, as stated in table B.1.

The support of letter classes, which specify mainly ME hardware dependent features, is optional for the ME and may supplement the USIM Application Toolkit functionality described in the present document. If an ME states conformance to a letter class, it is mandatory to support all functions within the respective letter class.

The supplier of the implementation shall state the support of possible options in table A.1.

Table A.1: Options

Item	Option	Status	Support	Mnemonic
1	Capability Configuration parameter	M	Support	O_Cap_Conf
2	Sustained text	M		O_sust_text
3	UCS2 coding scheme for Entry	0		O_Ucs2_Entry
4	Extended Text String	М		O_Ext_Str
5	Help information	0		O_Help
6	Icons	0		O_lcons
7	Class A: Dual Slot	0		O_Dual_Slot
8	Detachable reader	0		O_Detach_Rdr
9	Class B: RUN AT	0		O_Run_At
10	Class C: LAUNCH BROWSER	0		O_LB
11	Class D: Soft keys	0		O_Soft_key
12	Class E: B.I.P related to CSD	0		O_BIP_CSD
13	Screen sizing parameters	0		O_Scr_Siz
14	Screen Resizing	0		O_Scr_Resiz
15	UCS2 coding scheme for Display	0		O_Ucs2_Disp
16	Mobile supporting GPRS	0		O_GPRS
17	Mobile supporting UDP	0		O_UDP
18	Mobile supporting TCP	0		O_TCP
19	Redial in Set Up Call	0		O_Redial
20	Mobile decision to respond with "No response from user" in finite time	0		O_D_NoResp
21	Class E: B.I.P related to GPRS	0		O_BIP_GPRS
22	Mobile supporting Called Party Subaddress	0		O_CP_Subaddr
23	Immediate response	0		O_Imm_Resp
24	Variable Timeout	0		O_Duration
25	void			
26	Class F: B.I.P related to local bearer	0		O_BIP_Local
27	BlueTooth Support	0		O_BT
28	IrDA Support	0		O_IrDA
29	RS232 Support	0		O_RS232

31 V	WML Browser Support		
	Will Browser Support	0	O_WML
32 X	XHTML Browser Support	0	O_XHTML
33 H	HTML Browser Support	0	O_HTML
34	CHTML Browser Support	0	O_CHTML
35 C	Class G: Battery Data	0	O_Batt
36 C	Class H: Multimedia Call Support	0	O_Xmedia_Call
	Class I: Frame support	0	O_Frames
	Class J: Multimedia Messaging Support	0	O_MMS
c	ME requesting for user confirmation before sending the Envelope Call Control command	0	O_UC_Before_Env CC
С	ME requesting for user confirmation after sending the Envelope Call Control command	0	O_UC_After_EnvC C
	JCS2 in Cyrillic	0	O_UCS2_Cyrillic
	JCS2 in Chinese	0	O_UCS2_Chinese
	JCS2 in Katakana	0	O_UCS2_Katakan a
	Mobile supporting <b>B</b> arred <b>D</b> ialling Numbers	0	O_BDN
	Mobile supporting Fixed dialling numbers	0	O_FDN
c	Mobile supporting "+CIMI" in combination with Run AT Command	0	O_+CIMI
c	Mobile supporting "+CGMI" in combination with Run AT Command	0	O_+CGMI
() A d	Mobile supporting Open Channel GPRS) not containing a Network Access Name TLV when no default Access Point Name is set in the terminal configuration	0	O_Open_Channel_ GPRS_without_De faultAPN
th	Preferred buffer size supported by he terminal for Open Channel command is greater than 0 byte and less than 65535 bytes	0	O_BUFFER_SIZE
	Text attributes – Alignment left	0	O_TAT_AL
51 T	Text attributes – Alignment center	Ο	O_TAT_AC
52 T	Text attributes – Alignment right	0	O_TAT_AR
53 T	Text attributes – Font size normal	0	O_TAT_FSN
54 T	Text attributes – Font size large	Ο	O_TAT_FSL
55 T	Fext attributes – Font size small	0	O_TAT_FSS

56	Text attributes – Style normal	0	O_TAT_SN
57	Text attributes – Style bold	0	O_TAT_SB
58	Text attributes – Style italic	0	O_TAT_SI
59	Text attributes – Style underlined	0	O_TAT_SU
60	Text attributes – Style strikethrough	0	O_TAT_SS
61	Text attributes – Style text foreground colour	0	O_TAT_STFC
62	Text attributes – Style text background colour	0	O_TAT_STFB
63	Terminal supports Long ForwardToNumber	0	O_longFTN
64	Mobile supporting GERAN	0	O_GERAN
65	Support of global phonebook	C001	O_Global_PB
66	HSDPA Support	0	O_HSDPA
67	UTRAN PS with extended parameters Support	0	O_UTRAN_PS_Ext _Param
68	Terminal executes User	0	O_User_Confirm_
	confirmation phase before sending PDP context activation request		Before_PDP_Cont ext_Request
69	ME supports Call Hold Supplementary Service	0	O_Serv_SS_HOLD
70	Class E: B.I.P. related to I-WLAN	0	O_I-WLAN
71	Class K: Terminal Applications support	0	O_Terminal_Applic ations
72	Class E: Terminal supports TCP, UICC in Server Mode	0	O_TCP_UICC_Ser verMode
73	Class E: Terminal supports TCP, Terminal in Server Mode	0	O_TCP_Terminal_ ServerMode
74	Class E: Terminal supports UDP, UICC in Server Mode	0	O_UDP_Terminal_ ServerMode
75	ME supports icons as defined in record 1 of EF(IMG)	0	O_Icons_Rec1
76	ME supports icons as defined in record 2 of EF(IMG)	0	O_lcons_Rec2
77	ME supports icons as defined in record 5 of EF(IMG)	0	O_Icons_Rec5
78	Terminal supports at least one supplementary service.	0	O_AddInfo_SS
79	Terminal supports "Call Forwarding Unconditional"	0	O_ Serv_SS_CFU
80	Terminal supports "Calling Line Identification Restriction"	0	O_Serv_SS_CLIR
81	Class N:Terminal supports "Geographical location discovery"	0	O_Geo_Location_ Discovery
82	Terminal supports melody and theme tones	0	O_M_T_Tones
83	Terminal supports Toolkit-initiated GBA	0	O_Toolkit_GBA
84	Terminal supports display capability	C002	O_ No_Type_ND
85	Terminal supports keypad	C002	O_No_Type_NK
86	Terminal supports audio altering	C002	O_No_Type_NA
87	Terminal supports speech call	C002	O_No_Type_NS
88	Terminal supports multiple	C002	O_No_Type_NL
00		0002	O_INO_Type_INL
	languages		0.4000.0 ()
89	Class P:USSD Data Download and application mode	0	O_USSD_Data_DL
0004 1		Dal C -	loter than M. slas C
	f terminal is implemented according to f feature is implemented according to		

## 3.4 Applicability table

Table B.1: Applicability of tests

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
1	PROFILE DOWNLOAD27.22.1	R99	1	М	М	М	М	М	М	E.1/1	No		
2	Contents of the TERMINAL PROFILE command 27.22.2	R99		М	М	М	М	М	М	E.1/1	No		
3	Servicing of Proactive UICC Commands 27.22.3	R99		М	М	М	М	М	М		No		
4	DISPLAY TEXT 27.22.4.1												
	Unpacked	R99	1.1	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		
	Screen busy	R99	1.2	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		
	high priority	R99	1.3	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		
	Packed	R99	1.4	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		
	clear after delay	R99	1.5	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		
	long text up to 160 bytes	R99	1.6	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		
	Backwards move in USIM session	R99	1.7	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/17 AND E.1/110 AND E.1/111	No		
	Session terminated by user	R99	1.8	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/17 AND E.1/110 AND E.1/111	No		
	Command not understood by ME	R99	1.9	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		
	no response from user	R99	2.1	C120 AND C177 AND C178	C120 AND C177 AND C178	C120 AND C177 AND C178	C120 AND C177 AND C178	C120 AND C177 AND C178	C120 AND C177 AND C178	E.1/17 AND E.1/110 AND E.1/111	No		
	Extension Text	R99	3.1	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/16 AND E.1/110	No		
	sustained text	R99	4.1, 4.2, 4.3, 4.4	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/65 AND E.1/110	No		
	sustained text	R99	4.3	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/17 AND E.1/65 AND E.1/110 AND E.1/111	No		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	sustained text	R99	4.4	C177 AND C180	C177 AND	C177 AND C180	C177 AND	C177 AND	C177 AND	E.1/17 AND E.1/65	Yes	
	Icons – basic icon	R99	5.1, 5.3	C108 AND C177	C180 C108 AND C177	C180 C108 AND C177	C180 C108 AND C177	C180 C108 AND C177	C180 C108 AND C177	AND E.1/110 E.1/17 AND E.1/110	No	
	Icons – colour icon	R99	5.2	C171 AND C177	C171 AND C177	C171 AND C177	C171 AND C177	C171 AND C177	C171 AND C177	E.1/17 AND E.1/110	No	
	UCS2 display in Cyrillic	R99	6.1	C118 AND C177	C118 AND C177	C118 AND C177	C118 AND C177	C118 AND C177	C118 AND C177	E.1/17 AND E.1/15 AND E.1/110	No	
	Variable Timeout	Rel-4	7.1		C126 AND C177 AND C178	C126 AND C177 AND C178	C126 AND C177 AND C178	C126 AND C177 AND C178	C126 AND C177 AND C178	E.1/17 AND E.1/137 AND E.1/110 AND E.1/111	No	
	Text attribute – left alignment	Rel-5	8.1			C153 AND C177	C153 AND C177	C153 AND C177	C153 AND C177	E.1/17 AND E.1/124 AND E.1/217 AND E.1/110	No	
	Text attribute – center alignment	Rel-5	8.2			C154 AND C177	C154 AND C177	C154 AND C177	C154 AND C177	E.1/17 AND E.1/124 AND E.1/218 AND E.1/110	No	
	Text attribute – right alignment	Rel-5	8.3			C155 AND C177	C155 AND C177	C155 AND C177	C155 AND C177	E.1/17 AND E.1/124 AND E.1/219 AND E.1/110	No	
	Text attribute – large font size	Rel-5	8.4			C157 AND C156 AND C177	C157 AND C156 AND C177	C157 AND C156 AND C177	C157 AND C156 AND C177	E.1/17 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	No	
	Text attribute – small font size	Rel-5	8.5			C158 AND C156 AND C177	C158 AND C156 AND C177	C158 AND C156 AND C177	C158 AND C156 AND C177	E.1/17 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	No	
	Text attribute – bold on	Rel-5	8.6			C160 AND C159 AND C177	C160 AND C159 AND C177	C160 AND C159 AND C177	C160 AND C159 AND C177	E.1/17 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	No	

Item	Description	Re-	Test	Rel	Rel-4	Rel-5	Rel-6	Rel-7	Rel-8	Terminal	Network	Sup-
		lease	sequence (s)	99 ME	ME	ME	ME	ME	ME	Profile	Dependen cy	port
	Text attribute – italic on	Rel-5	8.7			C161	C161	C161	C161	E.1/17 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C159	C159	C159	C159	E.1/225 AND		
						AND	AND	AND	AND	E.1/227 AND		
						C177	C177	C177	C177	E.1/110		
	Text attribute – underlined on	Rel-5	8.8			C162	C162	C162	C162	E.1/17 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C159	C159	C159	C159	E.1/225 AND		
						AND	AND	AND	AND	E.1/228 AND		
						C177	C177	C177	C177	E.1/110		
	Text attribute – strikethrough on	Rel-5	8.9			C163	C163	C163	C163	E.1/17 AND	No	
	Text ditribute Striketinough on	T C C	0.0			AND	AND	AND	AND	E.1/124 AND	110	
						C159	C159	C159	C159	E.1/225 AND		
						AND	AND	AND	AND	E.1/229 AND		
						C177	C177	C177	C177	E.1/110		
	Text attribute – foreground and	Rel-5	8.10		-	C164	C164	C164	C164	E.1/17 AND	No	
	background colours	1161-5	0.10			AND	AND	AND	AND	E.1/17 AND E.1/124 AND	INO	
	background colours					C165	C165	C165	C165	E.1/230 AND		
						AND	AND	AND	AND	E.1/231 AND		
						C177	C177	C177	C177	E.1/110		
	UCS2 display in Chinese	R99	9.1			C143	C177	C143	C177	E.1/17 AND	No	
	UC32 display in Chinese	Kaa	9.1			AND	AND	AND	AND	E.1/17 AND E.1/15 AND	INO	
						C177	C177	C177	C177	E.1/15 AND E.1/110		
	LICCO display in Katalyana	DOO	10.1			C177	C177	C177	C177	E.1/17 AND	NIa	
	UCS2 display in Katakana	R99	10.1								No	
						AND	AND	AND	AND	E.1/15 AND		
		Dalo	TDD			C177	C177	C177	C177	E.1/110	TDD	
	Frames	Rel-6	TBD							E.1/17 AND	TBD	
										E.1/177 AND		
										E.1/178 AND		
_										E.1/110		
5	GET INKEY 27.22.4.2											
	prompt unpacked	R99	1.1	C177	C177	C177	C177	C177	C177	E.1/18 AND	No	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C178	C178	C178	C178	C178	C178	E.1/111		
	prompt packed	R99	1.2	C177	C177	C177	C177	C177	C177	E.1/18 AND	No	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C178	C178	C178	C178	C178	C178	E.1/111	1	ļ
	Backwards move in UICC session	R99	1.3	C177	C177	C177	C177	C177	C177	E.1/18 AND	No	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C178	C178	C178	C178	C178	C178	E.1/111		
	Session terminated by user	R99	1.4	C177	C177	C177	C177	C177	C177	E.1/18 AND	No	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
		1		C178	C178	C178	C178	C178	C178	E.1/111	1	
	SMS alphabet	R99	1.5	C177	C177	C177	C177	C177	C177	E.1/18 AND	No	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C178	C178	C178	C178	C178	C178	E.1/111		

1	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Long text up to 160 bytes	R99	1.6	C177	C177	C177	C177	C177	C177	E.1/18 AND	No	
	Long text up to 100 bytes	1133	1.0	AND	AND	AND	AND	AND	AND	E.1/10 AND	INO	
				C178	C178	C178	C178	C178	C178	E.1/111		
	no response from user	R99	2.1	C120	C120	C170	C170	C120	C170	E.1/18 AND	No	
	no response nom user	139	2.1	AND	AND	AND	AND	AND	AND	E.1/10 AND	INO	
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND	L.1/111		
				C178	C178	C178	C178	C178	C178			
	UCS2 display in Cyrillic	R99	3.1	C118	C118	C118	C118	C118	C118	E.1/18 AND	No	
	OCOZ display in Cyrillic	1133	5.1	AND	AND	AND	AND	AND	AND	E.1/15 AND	INO	
				C177	C177	C177	C177	C177	C177	E.1/110 AND		
				AND	AND	AND	AND	AND	AND	E.1/111		
				C178	C178	C178	C178	C178	C178	L. 1/ 1 1 1		
	UCS2 display, Long text up to 70	R99	3.2	C178	C178	C178	C178	C178	C178	E.1/18 AND	No	1
	chars in Cyrillic	1799	٥.۷	AND	AND	AND	AND	AND	AND	E.1/15 AND	INU	
	chars in Cyrillic			C177	C177	C177	C177	C177	C177	E.1/110 AND		
				AND	AND	AND	AND	AND	AND	E.1/111		
				C178	C178	C178	C178	C178	C178	L.1/111		
	UCS2 entry in Cyrillic	R99	4.1	C105	C105	C178	C176	C178	C178	E.1/18 AND	No	
	OC32 entry in Cyrillic	Kaa	4.1	AND	AND	AND	AND	AND	AND	E.1/14 AND	INO	
				C177	C177	C177	C177	C177	C177	E.1/110 AND		
				AND	AND	AND	AND	AND	AND	E.1/111		
				C178	C178	C178	C178	C178	C178	L. 1/ 1 1 1		
	"Yes/No" response	R99	5.1	C177	C177	C177	C177	C177	C177	E.1/18 AND	No	
	res/No response	139	5.1	AND	AND	AND	AND	AND	AND	E.1/60 AND	INO	
				C178	C178	C178	C178	C178	C178	E.1/110 AND		
				0170	0170	0170	0170	0170	0170	E.1/111		
	Icons – basic icon	R99	6.1, 6.2	C108	C108	C108	C108	C108	C108	E.1/18 AND	No	
	100110 00010 10011	1.00	0.1, 0.2	AND	AND	AND	AND	AND	AND	E.1/10 AND	140	
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND	L.1/111		
				C178	C178	C178	C178	C178	C178			
	Icons – colour icon	R99	6.3, 6.4	C171	C171	C171	C171	C171	C171	E.1/18 AND	No	
			0.0, 0.4	AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
	Help information	R99	7.1	C107	C107	C107	C107	C107	C107	E.1/18 AND	No	
	The monnation	1100	/	AND	AND	AND	AND	AND	AND	E.1/110 AND	140	
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND	L.1/111		
				C178	C178	C178	C178	C178	C178			
	Variable Timeout	Rel-4	8.1	0170	C126	C176	C176	C176	C176	E.1/18 AND	No	<del>                                     </del>
	variable fillicout	1101-4	0.1		AND	AND	AND	AND	AND	E.1/140 AND	INO	
					C177	C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178	C178	L.1/111		
					U1/8	U1/0	01/0	U1/0	01/0	1	1	

tem	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – left alignment	Rel-5	9.1			C153	C153	C153	C153	E.1/18 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/217 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
	Text attribute – center alignment	Rel-5	9.2			C154	C154	C154	C154	E.1/18 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/218 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
	Text attribute – right alignment	Rel-5	9.3			C155	C155	C155	C155	E.1/18 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/219 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
	Text attribute – large font size	Rel-5	9.4			C157	C157	C157	C157	E.1/18 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C156	C156	C156	C156	E.1/221 AND		
						AND	AND	AND	AND	E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
	Text attribute – small font size	Rel-5	9.5			C158	C158	C158	C158	E.1/18 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C156	C156	C156	C156	E.1/222 AND		
						AND	AND	AND	AND	E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
	Text attribute – bold on	Rel-5	9.6		1	C160	C160	C160	C160	E.1/18 AND	No	<u> </u>
	2014 011	1	0.0			AND	AND	AND	AND	E.1/124		
						C159	C159	C159	C159	E.1/221 AND		
						AND	AND	AND	AND	E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178	L.1/111		
	Text attribute – italic on	Rel-5	9.7		1	C161	C161	C161	C161	E.1/18 AND	No	<del>                                     </del>
	Tox attribute Italie on	11013	5.7			AND	AND	AND	AND	E.1/124	140	
						C159	C159	C159	C159	E.1/225 AND		
						AND	AND	AND	AND	E.1/227 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
		1		1		C178	C178	C178	C178	L. 1/ 1 1 1	İ	1

Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
Text attribute – underlined on	Rel-5	9.8			C162	C162	C162	C162	E.1/18 AND	No	
					AND	AND	AND	AND	E.1/124		
					C159	C159	C159	C159	E.1/225 AND		
					AND	AND	AND	AND	E.1/228 AND		
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178			
Text attribute – strikethough on	Rel-5	9.9			C163	C163	C163	C163	E.1/18 AND	No	
					AND	AND	AND	AND	E.1/124		
					C159	C159	C159	C159	E.1/225 AND		
					AND	AND	AND	AND	E.1/229 AND		
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178			
Text attribute – foreground and	Rel-5	9.10			C164	C164	C164	C164	E.1/18 AND	No	
background colours					AND	AND	AND	AND	E.1/124 AND	1	
					C165	C165	C165	C165	E.1/230 AND		
					AND	AND	AND	AND	E.1/231 AND		
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178			
UCS2 display in Chinese	R99	10.1			C143	C143	C143	C143	E.1/18 AND	No	
					AND	AND	AND	AND	E.1/15 AND		
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178			
UCS2 display in Chinese, Long	R99	10.2			C143	C143	C143	C143	E.1/18 AND	No	
text up to 70 chars					AND	AND	AND	AND	E.1/15 AND		
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178			
UCS2 entry in Chinese	R99	11.1		1	C142	C142	C142	C142	E.1/18 AND	No	
,					AND	AND	AND	AND	E.1/14 AND	1	
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178		1	
UCS2 display in Katakana	R99	12.1		1	C145	C145	C145	C145	E.1/18 AND	No	
1 1 1 1 1 1 1 1 1 1					AND	AND	AND	AND	E.1/15 AND		
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111	1	
					C178	C178	C178	C178	·		
UCS2 display in Katakana, Long	R99	12.2		1	C145	C145	C145	C145	E.1/18 AND	No	<b>†</b>
text up to 70 chars					AND	AND	AND	AND	E.1/15 AND	1	
					C177	C177	C177	C177	E.1/110 AND		
					AND	AND	AND	AND	E.1/111		
					C178	C178	C178	C178		1	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	UCS2 entry in Katakana	R99	13.1			C144 AND C177 AND C178	C144 AND C177 AND C178	C144 AND C177 AND C178	C144 AND C177 AND C178	E.1/18 AND E.1/14 AND E.1/110 AND E.1/111	No	
	Frames	Rel-6	TBD							E.1/18 AND E.1/177 AND E.1/178 AND E.1/110 AND E.1/111	TBD	
6	GET INPUT 27.22.4.3											
	input unpacked	R99	1.1	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	C177 AND C178
	input packed	R99	1.2	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	digits only	R99	1.1	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	SMS alphabet	R99	1.3	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	hidden input	R99	1.4	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	min / max acceptable length	R99	1.5, 1.9	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	Backwards move in UICC session	R99	1.6	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	Session terminated by user	R99	1.7	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	Prompt text up to 160 bytes	R99	1.8	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	SMS default alphabet, ME to echo text, packing not required	R99	1.9	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	
	Null length for the text string	R99	1.10	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/19 AND E.1/110 AND E.1/111	No	

m	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	no response from user	R99	2.1	C120	C120	C120	C120	C120	C120	E.1/19 AND	No	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
	UCS2 display in Cyrillic	R99	3.1, 3.2	C118	C118	C118	C118	C118	C118	E.1/19 AND	No	
	, , , ,		, -	AND	AND	AND	AND	AND	AND	E.1/15 AND		
				C177	C177	C177	C177	C177	C177	E.1/110 AND		
				AND	AND	AND	AND	AND	AND	E.1/111		
				C178	C178	C178	C178	C178	C178			
	UCS2 entry in Cyrillic	R99	4.1, 4.2	C105	C105	C105	C105	C105	C105	E.1/19 AND	No	
	, , , ,		,	AND	AND	AND	AND	AND	AND	E.1/14 AND		
				C177	C177	C177	C177	C177	C177	E.1/110 AND	1	
				AND	AND	AND	AND	AND	AND	E.1/111	1	
				C178	C178	C178	C178	C178	C178		1	
	default text for the input	R99	5.1, 5.2	C177	C177	C177	C177	C177	C177	E.1/19 AND	No	1
			5, 5	AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C178	C178	C178	C178	C178	C178	E.1/111		
	Icons – basic icon	R99	6.1, 6.2	C108	C108	C108	C108	C108	C108	E.1/19 AND	No	<u> </u>
		1100	0.1, 0.2	AND	AND	AND	AND	AND	AND	E.1/110 AND	110	
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND	2.17.111		
				C178	C178	C178	C178	C178	C178			
	Icons – colour icon	R99	6.3, 6.4	C171	C171	C171	C171	C171	C171	E.1/19 AND	No	
	100110 001041 10011	1.00	0.0, 0	AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
	help information	R99	7.1	C107	C107	C107	C107	C107	C107	E.1/19 AND	No	
	,	1		AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND		1	
				C178	C178	C178	C178	C178	C178		1	
	Text attribute- left alignment	Rel-5	8.1			C153	C153	C153	C153	E.1/19 AND	No	
	3 2 2					AND	AND	AND	AND	E.1/124 AND	1	
						C177	C177	C177	C177	E.1/217 AND	1	
						AND	AND	AND	AND	E.1/110 AND	1	
						C178	C178	C178	C178	E.1/111		
	Text attribute - center alignment	Rel-5	8.2	İ		C154	C154	C154	C154	E.1/19 AND	No	İ
	1 3 12 13 3 15 11					AND	AND	AND	AND	E.1/124 AND	1	
						C177	C177	C177	C177	E.1/218 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111	1	
	Text attribute – right alignment	Rel-5	8.3	1		C155	C155	C155	C155	E.1/19 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/219 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		1

Text attribute - large font size		Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
C156   C156   C156   C156   E1/221 AND   E1/1220 AND   E	Te	xt attribute – large font size	Rel-5				C157	C157	C157	C157	E.1/19 AND		
AND		ŭ					AND	AND	AND	AND	E.1/124 AND		
C177   C177   C177   C177   C177   C171							C156	C156	C156	C156	E.1/221 AND		
AND   AND   AND   C178   C177   C17							AND	AND	AND	AND	E.1/220 AND		
C178   C177							C177	C177	C177	C177	E.1/110 AND		
C178   C177   C178							AND	AND	AND	AND	E.1/111		
AND							C178	C178	C178	C178			
AND   AND   AND   AND   E.1/124 AND   E.1/122 AND   E.1/222 AND   AND   AND   AND   E.1/220 AND   E.1/220 AND   E.1/210 AND   E.1/111   E.1/110   E.1/110 AND   E.1/111	Te	xt attribute – small font size	Rel-5	8.5			C158	C158	C158	C158	E.1/19 AND	No	
C156													
AND   AND   AND   AND   E1/122 AND   E1/111							C156	C156	C156	C156			
C177   C177   C177   C177   C177   C177   C177   C177   C177   C178   C179   C159   C177													
AND   AND   AND   C178   C17													
C178								_					
Text attribute - bold on   Rel-5   8.6   C160											2.1,111		
AND   AND   AND   C159   C159   C159   C159   C17225 AND	Te	xt attribute – bold on	Rel-5	8.6							F 1/19 AND	No	
C159   C159   C159   C159   E.1/225 AND     AND   AND   AND   AND   AND     C177   C177   C177   C177   C177     C177   C177   C177   C177     C177   C177   C177   C177     C177   C177   C177   C177     C178   C178   C178   C178     C179   C159   C159   C159   C159     AND   AND   AND   AND   E.1/124 AND     C179   C177   C177   C177   C177     AND   AND   AND   AND   AND     C179   C179   C179   C179     C170   C170   C170     C171   C171   C171     71     C171   C171   C171   C171   C171     C171   C171   C171   C171   C171     C171   C171   C171   C171   C171     C171   C171   C171   C171   C171     C171   C171   C171   C1	1.0	At attribute bold on	11010	0.0								110	
AND   AND   AND   AND   E.1/226 AND   E.1/110 AND   AND   C177													
C177   C177   C177   C177   C177   C177   C178   C179   C159							1						
AND   AND   C178   C161   C161   C161   C161   E.1/19 AND   No   E.1/124 AND   C159   C159   C159   C159   C159   C159   C159   E.1/225 AND   AND   AND   AND   AND   AND   E.1/122 AND   C177   C177   C177   C177   C177   E.1/110 AND   E.1/111   C178													
C178   C178   C178   C178   C178   C178							1						
Text attribute - italic on   Rel-5   8.7   C161   C161   C161   C161   E.1/19 AND   No											L. 1/ 1 1 1		
AND   AND   AND   C159   C159   C159   E.1/124 AND   C159   C159   C159   C159   E.1/225 AND   E.1/227 AND   C177   C17	Ta	vt attribute – italic on	Ral-5	8.7							F 1/10 ΔΝΠ	No	
C159   C159   C159   C159   E.1/225 AND     AND   AND   AND   AND   E.1/227 AND     C177   C177   C177   C177   C177   E.1/110 AND     AND   AND   AND   AND   AND   E.1/111     C178   C178   C178   C178   C178     C178   C178   C178   C178     C179   C179   C179   C179     C170   C170   C170     C171   C171   C171     C171   C171   C171     C172   C173   C174     C173   C174   C175     C174   C175   C175     C175   C175   C177     C177   C177   C177     C177   C177   C177     C178   C178   C178     C163   C163   C163   C163     AND   AND   AND   AND   AND     AND   AND   AND   AND   AND     C159   C159   C159   C159   E.1/225 AND     AND   AND   AND   AND   AND     AND   AND   AND   AND   AND     AND   AND   AND   AND   E.1/124 AND     C159   C159   C159   C159   E.1/225 AND     AND   AND   AND   AND   AND   E.1/229 AND     C177   C177   C177   C177   E.1/110 AND     C177   C177   C177   C177   E.1/110 AND     C177   C177   C177   C177   E.1/110 AND     C177   C177   C177   C177   E.1/110 AND	10	At attribute Italie on	TKCI 5	0.7								140	
AND													
C177   C177   C177   C177   C177   E.1/110   AND   E.1/111													
AND   AND   C178   C178   C178   C178													
C178   C178   C178   C178   C178							1						
Text attribute – underlined on Rel-5 8.8 C162 C162 C162 E.1/19 AND No Rel-5 Re											L. 1/ 1 1 1		
AND	Te	xt attribute – underlined on	Rel-5	8.8	<b> </b>	1					F 1/10 ΔΝΠ	No	
C159   C159   C159   E.1/225   AND   AND   AND   AND   E.1/128   AND   C177   C171	1.6	At attribute andernined on	11013	0.0								140	
AND   AND   AND   E.1/228 AND   C177   C178   C163   C16													
C177   C177   C177   C177   E.1/110   AND   E.1/111													
AND   AND   AND   E.1/111   C178   C163													
C178   C178   C178   C178   C178							-	_					
Text attribute – strikethrough on Rel-5 8.9 C163 C163 C163 E.1/19 AND No AND AND AND AND E.1/124 AND C159 C159 C159 C159 E.1/225 AND AND AND AND AND E.1/229 AND C177 C177 C177 C177 E.1/110 AND											L. 1/ 1 1 1		
AND AND AND E.1/124 AND C159 C159 C159 E.1/225 AND AND AND AND E.1/225 AND AND AND AND E.1/229 AND C177 C177 C177 E.1/110 AND	Ta	vt attributa - etrikathraugh an	Pol F	9.0		1					E 1/10 AND	No	-
C159 C159 C159 C159 E.1/225 AND AND AND AND AND E.1/229 AND C177 C177 C177 C177 E.1/110 AND	l e	AL ALLIDULE – SHIKEHHOUGH OH	IV6I-0	0.9								INU	
AND AND AND E.1/229 AND C177 C177 C177 E.1/110 AND													
C177 C177 C177 E.1/110 AND							1						
							1						
C178 C178 C178 C178											E.7/171		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – foreground and	Rel-5	8.10			C164	C164	C164	C164	E.1/19 AND	No		T
	background colours					AND	AND	AND	AND	E.1/124 AND			
	ŭ					C165	C165	C165	C165	E.1/230 AND			
						AND	AND	AND	AND	E.1/231 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
	UCS2 display in Chinese	R99	9.1, 9.2			C143	C143	C143	C143	E.1/19 AND	No		T
						AND	AND	AND	AND	E.1/15 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
	UCS2 entry in Chinese	R99	10.1, 10.2			C142	C142	C142	C142	E.1/19 AND	No		T
	,					AND	AND	AND	AND	E.1/14 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
	UCS2 display in Katakana	R99	11.1, 11.2			C145	C145	C145	C145	E.1/19 AND	No		T
			,			AND	AND	AND	AND	E.1/15 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
	UCS2 entry in Katakana	R99	12.1, 12.2			C144	C144	C144	C144	E.1/19 AND	No		Ť
	,		,			AND	AND	AND	AND	E.1/14 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
	Frames	Rel-6	TBD							E.1/19 AND	TBD		Ť
										E.1/177 AND			
										E.1/178 AND			
										E.1/110 AND			
										E.1/111			
7	MORE TIME 27.22.4.4	R99	1.1	М	М	М	М	М	М	E.1/20	No		T
8	PLAY TONE 27.22.4.5												T
	play all tones, display alpha, user	R99	1.1	C177	C177	C177	C177	C177	C177	E.1/21 AND	Yes		Ī
	termination, superimpose			AND	AND	AND	AND	AND	AND	E.1/110 AND			
	, , , , , , , , , , , , , , , , , , , ,			C178	C178	C178	C178	C178	C178	E.1/111			
				AND	AND	AND	AND	AND	AND				
				C180	C180	C180	C180	C180	C180				
	UCS2 display in Cyrillic	R99	2.1	C118	C118	C118	C118	C118	C118	E.1/21 AND	No		
				AND	AND	AND	AND	AND	AND	E.1/15 AND	1.0		
				C180	C180	C180	C180	C180	C180	E.1/110	1		
							0.00		0.00		1		
											1		
													- 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Icons – basic icon	R99	3.1, 3.2	C108 AND C180	C108 AND C180	C108 AND C180	C108 AND C180	C108 AND C180	C108 AND C180	E.1/21 AND E.1/110	No	T C E F C C
	Icons – colour icon	R99	3.3, 3.4	C171 AND C180	C171 AND C180	C171 AND C180	C171 AND C180	C171 AND C180	C171 AND C180	E.1/21 AND E.1/110	No	T C E F C C
	Text attribute – left alignment	Rel-5	4.1			C153 AND C180	C153 AND C180	C153 AND C180	C153 AND C180	E.1/21 AND E.1/124 AND E.1/217 AND E.1/110	No	T C E F C C
	Text attribute – center alignment	Rel-5	4.2			C154 AND C180	C154 AND C180	C154 AND C180	C154 AND C180	E.1/21 AND E.1/124 AND E.1/218 AND E.1/110	No	T C E F C C
	Text attribute – right alignment	Rel-5	4.3			C155 AND C180	C155 AND C180	C155 AND C180	C155 AND C180	E.1/21 AND E.1/124 AND E.1/219 AND E.1/110	No	T C E F C C
	Text attribute – large font size	Rel-5	4.4			C157 AND C156 AND C180	C157 AND C156 AND C180	C157 AND C156 AND C180	C157 AND C156 AND C180	E.1/21 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	No	T C E F C C

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156 AND C180	C158 AND C156 AND C180	C158 AND C156 AND C180	C158 AND C156 AND C180	E.1/21 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	No		T C E C C C 1
	Text attribute – bold on	Rel-5	4.6			C160 AND C159 AND C180	C160 AND C159 AND C180	C160 AND C159 AND C180	C160 AND C159 AND C180	E.1/21 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	No		T C C C C C C
	Text attribute – italic on	Rel-5	4.7			C161 AND C159 AND C180	C161 AND C159 AND C180	C161 AND C159 AND C180	C161 AND C159 AND C180	E.1/21 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	No		T C E F 0 0 1
	Text attribute – underlined on	Rel-5	4.8			C162 AND C159 AND C180	C162 AND C159 AND C180	C162 AND C159 AND C180	C162 AND C159 AND C180	E.1/21 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	No		T C E F 0 0 1
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159 AND C180	C163 AND C159 AND C180	C163 AND C159 AND C180	C163 AND C159 AND C180	E.1/21 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	No		T C E P 0 0 1
	Text attribute– foreground and background colours	Rel-5	4.10			C164 AND C165 AND C180	C164 AND C165 AND C180	C164 AND C165 AND C180	C164 AND C165 AND C180	E.1/21 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	No		T C E F 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	UCS2 display in Chinese	R99	5.1			C143 AND C180	C143 AND C180	C143 AND C180	C143 AND C180	E.1/21 AND E.1/15 AND E.1/110	No		T C E F O O
	UCS2 display in Katakana	R99	6.1			C145 AND C180	C145 AND C180	C145 AND C180	C145 AND C180	E.1/21 AND E.1/15 AND E.1/110	No		1 C E F 0
	Frames	Rel-6	TBD							E.1/21 AND E.1/177 AND E.1/178 AND E.1/110	TBD		'
	Themed and Melody tones	Rel-6	TBD							E.1/21 AND E.1/171 AND E.1/110	C138		
9	POLL INTERVAL 27.22.4.6												t
	duration	R99	1.1	М	М	М	М	М	М	E.1/22	No		T
10	REFRESH 27.22.4.7												T
	USIM initialization, enabling FDN mode	R99	1.1	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	E.1/24 AND E.1/110 AND E.1/111	Yes		
	file change notification of FDN file	R99	1.2	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	C146 AND C177 AND C178 AND C180	E.1/24 AND E.1/110 AND E.1/111	Yes		
	USIM initialization and file change notification of ADN	R99	1.3	C168 AND C177 AND C178	C168 AND C177 AND C178	C168 AND C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/24 AND E.1/110 AND E.1/111	No		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	USIM initialization and full file change notification, enabling FDN	R99	1.4	C146 AND	C146 AND	C146 AND	C146 AND	C146 AND	C146 AND	E.1/24 AND E.1/110 AND	Yes	
	mode			C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	UICC reset	R99	1.5				М	М	M	E.1/24	No	
	USIM Initialization after SMS-PP	R99	1.6	C146	C146	C146	C146	C146	C146	E.1/24 AND	Yes	
	data download			AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	USIM Application Reset	R99	1.7				C146	C146	C146	E1/24 AND	Yes	
							AND	AND	AND	E.1/110 AND		
							C177	C177	C177	E.1/111		
							AND	AND	AND			
							C178	C178	C178			
							AND	AND	AND			
							C180	C180	C180			
	UICC Reset for IMSI Changing procedure	R99	2.1								TBD	
	USIM Application Reset for IMSI	R99	2.2				М	М	М	E.1/24	Yes	
	Changing procedure							""				
	3G Session Reset for IMSI	R99	2.3								TBD	
	Changing procedure											
	reject 3G Session Reset for IMSI	R99	2.4				C177	C177	C177	E 1/24 AND	Yes	
	Changing procedure during call						AND	AND	AND	E.1/110 AND	. 55	
	granging procedure daming can						C178	C178	C178	E.1/111		
							AND	AND	AND			
							C180	C180	C180			
	Steering of roaming, UTRAN	Rel-7	3.1					М	М	E.1/24 AND	UMTS	
										E.1/236	System	
											Simulator	
											only	
	Steering of roaming, InterRAT	Rel-7	3.2					C167	C167	E.1/24 AND	UMTS	
										E.1/236	System	
											Simulator	
											and System	
		<u> </u>	<u> </u>	<u> </u>	<u> </u>	<u> </u>					Simulator	
11	SET UP MENU 27.22.4.8											
	Set up, menu selection, replace	R99	1.1	C177	C177	C177	C177	C177	C177	E.1/30 AND	No	
	and remove menu			AND	AND	AND	AND	AND	AND	E.1/4 AND		
				C178	C178	C178	C178	C178	C178	E.1/110 AND		
		1		1	1	1	Ì			E.1/111		1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Large menu	R99	1.2	C177 AND	C177 AND	C177 AND	C177 AND	C177 AND	C177 AND	E.1/30 AND E.1/4 AND	No	
				C178	C178	C178	C178	C178	C178	E.1/110 AND		
	help information	R99	2.1	C107	C107	C107	C107	C107	C107	E.1/111 E.1/30 AND	No	
	morp information	1100		AND	AND	AND	AND	AND	AND	E.1/4 AND	110	
				C177 AND	C177 AND	C177 AND	C177 AND	C177 AND	C177 AND	E.1/110 AND E.1/111		
				C178	C178	C178	C178	C178	C178	E. 1/ 1 1 1		
	next action indicator	R99	3.1	C177	C177	C177	C177	C177	C177	E.1/30 AND	No	
				AND C178	AND C178	AND C178	AND C178	AND C178	AND C178	E.1/110 AND E.1/111		
	Icons	R99	4.1, 4.2	C173	C173	C172	C178	C178	C178	E.1/30 AND	No	
			,	AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177 AND	C177 AND	C177 AND	C177 AND	C177 AND	C177 AND	E.1/111		
				C178	C178	C178	C178	C178	C178			
	soft key access	R99	5.1	C112	C112	C112	C112	C112	C112	E.1/30 AND	No	
				AND C177	AND C177	AND C177	AND C177	AND C177	AND C177	E.1/74 AND E.1/110 AND		
				AND	AND	AND	AND	AND	AND	E.1/111		
	-			C178	C178	C178	C178	C178	C178	E //00 AND		
	Text attribute – left alignment	Rel-5	6.1			C153 AND	C153 AND	C153 AND	C153 AND	E.1/30 AND E.1/124 AND	No	
						C177	C177	C177	C177	E.1/217 AND		
						AND	AND	AND	AND	E.1/110 AND		
	Text attribute – center alignment	Rel-5	6.2	-		C178 C154	C178 C154	C178 C154	C178 C154	E.1/111 E.1/30 AND	No	
	Tox attribute contor angriment	11010	0.2			AND	AND	AND	AND	E.1/124 AND	110	
						C177	C177	C177	C177	E.1/218 AND		
						AND C178	AND C178	AND C178	AND C178	E.1/110 AND E.1/111		
	Text attribute – right alignment	Rel-5	6.3			C155	C155	C155	C155	E.1/30 AND	No	
						AND C177	AND C177	AND C177	AND C177	E.1/124 AND E.1/219 AND		
						AND	AND	AND	AND	E.1/219 AND E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
	Text attribute – large font size	Rel-5	6.4			C157	C157	C157	C157	E.1/30 AND	No	
						AND C156	AND C156	AND C156	AND C156	E.1/124 AND E.1/221 AND		
						AND	AND	AND	AND	E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND C178	AND C178	AND C178	AND C178	E.1/111		

m	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – small font size	Rel-5	6.5			C158	C158	C158	C158	E.1/30 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C156	C156	C156	C156	E.1/222 AND		
						AND	AND	AND	AND	E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
	Text attribute – bold on	Rel-5	6.6			C160	C160	C160	C160	E.1/30 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C159	C159	C159	C159	E.1/225 AND		
						AND	AND	AND	AND	E.1/226 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
	Text attribute – italic on	Rel-5	6.7			C161	C161	C161	C161	E.1/30 AND	No	
		1				AND	AND	AND	AND	E.1/124 AND	1	
						C159	C159	C159	C159	E.1/225 AND		
						AND	AND	AND	AND	E.1/227 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
	Text attribute – underlined on	Rel-5	6.8			C162	C162	C162	C162	E.1/30 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C159	C159	C159	C159	E.1/225 AND		
						AND	AND	AND	AND	E.1/228 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
	Text attribute – strikethrough on	Rel-5	6.9			C163	C163	C163	C163	E.1/30 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
		1				C159	C159	C159	C159	E.1/225 AND	1	
						AND	AND	AND	AND	E.1/229 AND		
						C177	C177	C177	C177	E.1/110 AND		
		1				AND	AND	AND	AND	E.1/111	1	
				<u> </u>		C178	C178	C178	C178		<u> </u>	
	Text attribute – foreground and	Rel-5	6.10			C164	C164	C164	C164	E.1/30 AND	No	
	background colours	1				AND	AND	AND	AND	E.1/124 AND	1	
						C165	C165	C165	C165	E.1/230 AND		
		1				AND	AND	AND	AND	E.1/231 AND	1	
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
				<u> </u>		C178	C178	C178	C178		<u> </u>	
	UCS2 display in Cyrillic	R99	7.1			C118	C118	C118	C118	E.1/39 AND	No	
						AND	AND	AND	AND	E.1/15 AND		
		1				C177	C177	C177	C177	E.1/110 AND	1	
		1				AND	AND	AND	AND	E.1/111	1	
						C178	C178	C178	C178			

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	UCS2 display in Chinese	R99	8.1	1		C143	C143	C143	C143	E.1/39 AND	No		T
						AND	AND	AND	AND	E.1/15 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
	UCS2 display in Katakana	R99	9.1			C145	C145	C145	C145	E.1/39 AND	No		T
	, , , , , , , , , , , , , , , , , , , ,					AND	AND	AND	AND	E.1/15 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
12	SELECT ITEM 27.22.4.9												T
	Mandatory features	R99	1.1	C177	C177	C177	C177	C177	C177	E.1/25 AND	No		T
	,			AND	AND	AND	AND	AND	AND	E.1/110 AND			
				C178	C178	C178	C178	C178	C178	E.1/111	1		
	Large menu	R99	1.2, 1.3,	C177	C177	C177	C177	C177	C177	E.1/25 AND	No		t
			1.5,1.6	AND	AND	AND	AND	AND	AND	E.1/110 AND			
				C178	C178	C178	C178	C178	C178	E.1/111			
	Backwards move	R99	1.4	C177	C177	C177	C177	C177	C177	E.1/25 AND	No		t
	Zaomarao mere	1.00		AND	AND	AND	AND	AND	AND	E.1/110 AND	1.0		
				C178	C178	C178	C178	C178	C178	E.1/111			
	user termination	R99	1.5	C177	C177	C177	C177	C177	C177	E.1/25 AND	No		t
		1100		AND	AND	AND	AND	AND	AND	E.1/110 AND			
				C178	C178	C178	C178	C178	C178	E.1/111			
	next action indicator	R99	2.1	C177	C177	C177	C177	C177	C177	E.1/25 AND	No		T
				AND	AND	AND	AND	AND	AND	E.1/110 AND			
				C178	C178	C178	C178	C178	C178	E.1/111			
	default selected item	R99	3.1	C177	C177	C177	C177	C177	C177	E.1/25 AND	No		T
				AND	AND	AND	AND	AND	AND	E.1/110 AND			
				C178	C178	C178	C178	C178	C178	E.1/111			
	help information	R99	4.1	C107	C107	C107	C107	C107	C107	E 1/25 AND	No		t
				AND	AND	AND	AND	AND	AND	E.1/110 AND			
				C177	C177	C177	C177	C177	C177	E.1/111	1		ĺ
				AND	AND	AND	AND	AND	AND		1		
				C178	C178	C178	C178	C178	C178				
	Icons	R99	5.1, 5.2	C172	C172	C172	C172	C172	C172	E.1/25 AND	No		T
	1.55.1.5	1.00	3, 3.2	AND	AND	AND	AND	AND	AND	E.1/110 AND			1
				C177	C177	C177	C177	C177	C177	E.1/111	1		
				AND	AND	AND	AND	AND	AND		1		
				C178	C178	C178	C178	C178	C178		1		
	Presentation style	R99	6.1, 6.2	C177	C177	C177	C177	C177	C177	E.1/25 AND	No		t
		1	, 5.2	AND	AND	AND	AND	AND	AND	E.1/110 AND	1.5		
				C178	C178	C178	C178	C178	C178	E.1/111	1		ĺ
	Soft keys	R99	7.1	C112	C112	C112	C112	C112	C112	E.1/25 AND	No		t
	25	1.00		AND	AND	AND	AND	AND	AND	E.1/73 AND			1
				C177	C177	C177	C177	C177	C177	E.1/110 AND			1
				AND	AND	AND	AND	AND	AND	E.1/111			1
				C178	C178	C178	C178	C178	C178	L.1/111			

em	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	No Response from user	R99	8.1	C120	C120	C120	C120	C120	C120	E.1/25 AND	No	
	·			AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
	Text attribute – left alignment	Rel-5	9.1			C153	C153	C153	C153	E.1/25 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/217 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
	Text attribute – center alignment	Rel-5	9.2			C154	C154	C154	C154	E.1/25 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/218 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111	ļ.,,	
	Text attribute – right alignment	Rel-5	9.3			C155	C155	C155	C155	E.1/25 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/219 AND		
						AND	AND	AND	AND	E.1/110 AND		
	Total attallanta Laura foot alex	D.I.E	0.4			C178	C178	C178	C178	E.1/111	NI-	
	Text attribute – large font size	Rel-5	9.4			C157	C157A	C157	C157	E.1/25 AND	No	
						AND	ND C156	AND C156	AND	E.1/124 AND E.1/221 AND		
						C156 AND	C156 AND	AND	C156 AND	E.1/221 AND E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178	□ □.1/111		
	Text attribute – small font size	Rel-5	9.5			C178	C158A	C178	C178	E.1/25 AND	No	
	Text attribute – Small forit Size	IVEI-2	9.5			AND	ND	AND	AND	E.1/124 AND	NO	
						C156	C156	C156	C156	E.1/222 AND		
						AND	AND	AND	AND	E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
		1				C178	C178	C178	C178			
	Text attribute – bold on	Rel-5	9.6	1	1	C160	C160	C160	C160	E.1/25 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
		1				C159	C159	C159	C159	E.1/225 AND		
		1				AND	AND	AND	AND	E.1/226 AND		
		1				C177	C177	C177	C177	E.1/110 AND		
		1				AND	AND	AND	AND	E.1/111		
		1				C178	C178	C178	C178		1	<u> </u>
	Text attribute – italic on	Rel-5	9.7			C161	C161	C161	C161	E.1/25 AND	No	
						AND	AND	AND	AND	E.1/124 AND		
						C159	C159	C159	C159	E.1/225 AND		
		1				AND	AND	AND	AND	E.1/227 AND		
		1				C177	C177	C177	C177	E.1/110 AND		
		1				AND	AND	AND	AND	E.1/111		
		1		1	1	C178	C178	C178	C178	Ì		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – underline on	Rel-5	9.8			C162 AND	C162 AND	C162 AND	C162 AND	E.1/25 AND E.1/124 AND	No		
						C159 AND	C159 AND	C159 AND	C159 AND	E.1/225 AND E.1/228 AND			
						C177	C177 AND	C177	C177	E.1/110 AND			
						AND C178	C178	AND C178	AND C178	E.1/111			
	Text attribute – strikethrough on	Rel-5	9.9			C163 AND	C163 AND	C163 AND	C163 AND	E.1/25 AND E.1/124 AND	No		
						C159 AND	C159 AND	C159 AND	C159 AND	E.1/225 AND E.1/229 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND C178	AND C178	AND C178	AND C178	E.1/111			
	Text attribute – foreground and background colours	Rel-5	9.10			C164 AND C165	C164 AND C165	C164 AND C165	C164 AND C165	E.1/25 AND E.1/124 AND E.1/230 AND	No		
						AND C177	AND C177	AND C177	AND C177	E.1/231 AND E.1/110 AND			
						AND C178	AND C178	AND C178	AND C178	E.1/111			
	UCS2 display in Cyrillic	R99	10.1, 10.2, 10.3			C118 AND C177 AND C178	C118 AND C177 AND C178	C118 AND C177 AND C178	C118 AND C177 AND C178	E.1/39 AND E.1/15 AND E.1/110 AND E.1/111	No		
	UCS2 display in Chinese	R99	11.1			C143 AND C177 AND C178	C143 AND C177 AND C178	C143 AND C177 AND C178	C143 AND C177 AND C178	E.1/25 AND E.1/15 AND E.1/110 AND E.1/111	No		
	UCS2 display in Katakana	R99	12.1, 12.2, 12.3			C145 AND C177 AND C178	C145 AND C177 AND C178	C145 AND C177 AND C178	C145 AND C177 AND C178	E.1/25 AND E.1/15 AND E.1/110 AND E.1/111	No		
	Frames	Rel-6	TBD							E.1/25 AND E.1/177 AND E.1/178 AND E.1/110 AND E.1/111	TBD		
13	SEND SMS 27.22.4.10												

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Packing not required, 8 bit data	R99	1.1	М	M	M	M	M	М	E.1/26 AND E.1/110	Yes		T C E P 0 0 1
	Packing required, 8 bit data	R99	1.2	M	M	M	M	M	M	E.1/26 AND E.1/110	Yes		T C E P 0 0 1
	Packing not required, SMS default alphabet	R99	1.3	M	M	M	M	M	M	E.1/26 AND E.1/110	Yes		T C E P 0 0 1
	Packing required, 8 bit data, 160 bytes length	R99	1.4	M	M	M	M	M	M	E.1/26 AND E.1/110	Yes		T C E P 0 0 1
	Packing not required, SMS default alphabet, 160 bytes length	R99	1.5	M	M	M	M	M	M	E.1/26 AND E.1/110	Yes		T C E P 0 0 1
	Alpha identifier	R99	1.6, 1.8	M	M	M	M	M	M	E.1/26 AND E.1/110	Yes		T C E P 0 0 1
	Alpha identifier length '00'	R99	1.7	М	М	М	М	М	М	E.1/26	Yes		Ė

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	UCS2 SMS in Cyrillic	R99	(s) 2.1	C118	C118	C118	C118	C118	C118	E.1/26 AND E.1/15 AND E.1/110	Yes	T   C   E   F   C   C
	Icons – basic icon	R99	3.1, 3.2	C108	C108	C108	C108	C108	C108	E.1/26 AND E.1/110	Yes	1 ( E F (
	Text attribute– left alignment	Rel-5	4.1			C153	C153	C153	C153	E.1/26 AND E.1/124 AND E.1/217 AND E.1/110	Yes	T   C   E   F   C   C
	Text attribute – center alignment	Rel-5	4.2			C154	C154	C154	C154	E.1/26 AND E.1/124 AND E.1/218 AND E.1/110	Yes	T   C   E   F   C   C
	Text attribute – right alignment	Rel-5	4.3			C155	C155	C155	C155	E.1/26 AND E.1/124 AND E.1/219 AND E.1/110	Yes	1   C   E   F   C   C
	Text attribute – large font size	Rel-5	4.4			C157 AND C156	C157A ND C156	C157 AND C156	C157A ND C156	E.1/26 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	Yes	T   C   E   F   C   C

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – small font size	Rel-5	(s) 4.5			C158 AND C156	C158A ND C156	C158 AND C156	C158A ND C156	E.1/26 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – bold on	Rel-5	4.6			C160 AND C159	C160 AND C159	C160 AND C159	C160 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – italic on	Rel-5	4.7			C161 AND C159	C161 AND C159	C161 AND C159	C161 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – underline on	Rel-5	4.8			C162 AND C159	C162 AND C159	C162 AND C159	C162 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute- strikethrough on	Rel-5	4.9			C163 AND C159	C163 AND C159	C163 AND C159	C163 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165	C164 AND C165	C164 AND C165	C164 AND C165	E.1/26 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	Yes		T C E P 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	UCS2 display in Chinese	R99	5.1			C143	C143	C143	C143	E.1/26 AND E.1/15 AND E.1/110	Yes		T C E P O O
	UCS2 display in Katakana	R99	6.1			C145	C145	C145	C145	E.1/26 AND E.1/15 AND E.1/110	Yes		1 T C E P 0
	Frames	Rel-6	TBD							E.1/26 AND E.1/177 AND E.1/178 AND E.1/110	TBD		1 T C E P 0 0 1
14	SEND SS 27.22.4.11 call forward unconditional, all bearers, successful	R99	1.1	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	E.1/27 AND E.1/110	Yes		T C E P 0 0 1
	call forward unconditional, all bearers, Return Error	R99	1.2	C174	C174	C174	C174	C174	C174	E.1/27 AND E.1/110	Yes		T C E P 0 1
	call forward unconditional, all bearers, Reject	R99	1.3	C174	C174	C174	C174	C174	C174	E.1/27 AND E.1/110	Yes		T C E P 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	call forward unconditional, all bearers, successful, SS request size limit	R99	1.4	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	E.1/27 AND E.1/110	Yes		T C E P O O
	interrogate CLIR status, successful, alpha identifier limits	R99	1.5	C175	C175	C175	C175	C175	C175	E.1/27 AND E.1/110	Yes		1 T C E P 0 0 1
	call forward unconditional, all bearers, successful, null data alpha identifier	R99	1.6	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	C166 AND C174	E.1/27 AND E.1/110	Yes		T C E P 0 0 1
	call forward unconditional, all bearers, successful, basic icon support	R99	2.1, 2.3, 2.4	C108 AND C174	C108 AND C174	C108 AND C174	C108 AND C174	C108 AND C174	C108 AND C174	E.1/27 AND E.1/110	Yes		T C E P 0 0 1
	call forward unconditional, all bearers, successful, colour icon support	R99	2.2	C171 AND C174	C171 AND C174	C171 AND C174	C171 AND C174	C171 AND C174	C171 AND C174	E.1/27 AND E.1/110	Yes		T C E P 0 0 1
	UCS2 display in Cyrillic	R99	3.1	C118 AND C174	C118 AND C174	C118 AND C174	C118 AND C174	C118 AND C174	C118 AND C174	E.1/27 AND E.1/15 AND E.1/110	Yes		T C E P 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – left alignment	Rel-5	4.1			C153 AND C166 AND C174	C153 AND C166 AND C174	C153 AND C166 AND C174	C153 AND C166 AND C174	E.1/27 AND E.1/124 AND E.1/217 AND E.1/110	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154 AND C166 AND C174	C154 AND C166 AND C174	C154 AND C166 AND C174	C154 AND C166 AND C174	E.1/27 AND E.1/124 AND E.1/218 AND E.1/110	Yes	E F
	Text attribute – right alignment	Rel-5	4.3			C155 AND C166 AND C174	C155 AND C166 AND C174	C155 AND C166 AND C174	C155 AND C166 AND C174	E.1/27 AND E.1/124 AND E.1/219 AND E.1/110	Yes	F ( )
	Text attribute – large font size	Rel-5	4.4			C157 AND C156 AND C166 AND C174	C157A ND C156A NDC1 66 AND C174	C157 AND C156 ANDC 166 AND C174	C157A ND C156A NDC1 66 AND C174	E.1/27 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	Yes	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156 AND C166 AND C174	C158A ND C156 AND C166 AND C174	C158 AND C156 AND C166 AND C174	C158A ND C156 AND C166 AND C174	E.1/27 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes	
	Text attribute – bold on	Rel-5	4.6			C160 AND C159 AND C166 AND C174	C160 AND C159 AND C166 AND C174	C160 AND C159 AND C166 AND C174	C160 AND C159 AND C166 AND C174	E.1/27 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – italic on	Rel-5	4.7			C161	C161	C161	C161	E.1/27 AND	Yes		T
						AND C159	AND C159	AND C159	AND C159	E.1/124 AND E.1/225 AND			C
						AND	AND	AND	AND	E.1/227 AND			F
						C166	C166	C166	C166	E.1/110			l'o
						AND	AND	AND	AND				
						C174	C174	C174	C174				1
	Text attribute – underline on	Rel-5	4.8			C162	C162	C162	C162	E.1/27 AND	Yes		T
						AND	AND	AND	AND	E.1/124 AND			(
						C159	C159	C159	C159	E.1/225 AND			E
						AND	AND	AND	AND	E.1/228 AND			F
						C166	C166	C166	C166	E.1/110			(
						AND	AND	AND	AND				(
	Tout attribute atributh accept as	Dalif	4.0			C174	C174	C174	C174	E 4/07 AND	Vaa		-
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND	C163 AND	C163 AND	C163 AND	E.1/27 AND E.1/124 AND	Yes		
						C159	C159	C159	C159	E.1/124 AND E.1/225 AND			
						AND	AND	AND	AND	E.1/229 AND			
						C166	C166	C166	C166	E.1/110			
						AND	AND	AND	AND	2.1/110			ľ
						C174	C174	C174	C174				ŀ
	Text attribute – foreground and	Rel-5	4.10			C164	C164	C164	C164	E.1/27 AND	Yes		T
	background colours					AND	AND	AND	AND	E.1/124 AND			-
						C165	C165	C165	C165	E.1/230 AND			
						AND	AND	AND	AND	E.1/231 AND			
						C166	C166	C166	C166	E.1/110			
						AND	AND	AND	AND				
						C174	C174	C174	C174				Į.
	UCS2 display in Chinese	R99	5.1			C143	C143	C143	C143	E.1/27 AND	Yes		
						AND	AND	AND	AND	E.1/15 AND			1
						C166	C166	C166	C166	E.1/110			
						AND C174	AND C174	AND C174	AND C174				
						C174	C174	C174	0174				
	UCS2 display in Katakana	R99	6.1			C145	C145	C145	C145	E.1/27 AND	Yes		
	0002 display iii Natakalia	1133	0.1			AND	AND	AND	AND	E.1/15 AND	162		
						C166	C166	C166	C166	E.1/110	1		
						AND	AND	AND	AND	2,110	1		
						C174	C174	C174	C174		1		
15	SEND USSD 27.22.4.12			1									+
	0000 EliEEITIE	1	1	1		1	1	i	İ	1	1	1	- 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	7-bit data, successful	R99	1.1	М	М	M	M	M	M	E.1/28 AND E.1/110	Yes		T C E P 0 0 1
	8-bit data, successful	R99	1.2	M	M	M	M	M	M	E.1/28 AND E.1/110	Yes		T C E P 0 0 1
	UCS2 data, successful	R99	1.3	М	M	М	M	М	M	E.1/28 AND E.1/110	Yes		T C E P 0 0 1
	7-bit data, unsuccessful	R99	1.4	M	M	M	M	M	M	E.1/28 AND E.1/110	Yes		T C E P 0 0 1
	7-bit data, unsuccessful	R99	1.5	M	М	M	M	M	M	E.1/28 AND E.1/110	Yes		T C E P 0 0 1
	256 octets, 7-bit data, successful, long alpha identifier	R99	1.6	М	М	M	М	М	M	E.1/28 AND E.1/110	Yes		T C E P 0 0 1
	7-bit data, successful, no alpha identifier	R99	1.7	М	М	М	М	M	М	E.1/28 AND E.1/110	Yes		
	7-bit data, successful, null length alpha identifier	R99	1.8	М	М	М	М	М	М	E.1/28 AND E.1/110	Yes		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Icons – basic icon	R99	2.1, 2.3, 2.4	C108	C108	C108	C108	C108	C108	E.1/28 AND E.1/110	Yes		T C E P 0 1
	Icons – colour icon	R99	2.2	C171	C171	C171	C171	C171	C171	E.1/28 AND E.1/110	Yes		T C E P 0
	UCS2 in Cyrillic	R99	3.1	C118	C118	C118	C118	C118	C118	E.1/28 AND E.1/15 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – left alignment	Rel-5	4.1			C153	C153	C153	C153	E.1/28 AND E.1/124 AND E.1/217 AND E.1/110	Yes		T C E P 0 1
	Text attribute – center alignment	Rel-5	4.2			C154	C154	C154	C154	E.1/28 AND E.1/124 AND E.1/218 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – right alignment	Rel-5	4.3			C155	C155	C155	C155	E.1/28 AND E.1/124 AND E.1/219 AND E.1/110	Yes		T C E P 0

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – large font size	Rel-5	4.4			C157 AND C156	C157A ND C156	C157 AND C156	C157 AND C156	E.1/28 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – small font size	Rel-5	4.5			C158 AND C156	C158A ND C156	C158 AND C156	C158 AND C156	E.1/28 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – bold on	Rel-5	4.6			C160 AND C159	C160 AND C159	C160 AND C159	C160 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – italic on	Rel-5	4.7			C161 AND C159	C161 AND C159	C161 AND C159	C161 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – underline on	Rel-5	4.8			C162 AND C159	C162 AND C159	C162 AND C159	C162 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159	C163 AND C159	C163 AND C159	C163 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	Yes		T C E P 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165	C164 AND C165	C164 AND C165	C164 AND C165	E.1/28 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	Yes		T C E P 0 0 1
	UCS2 in Chinese	R99	5.1			C143	C143	C143	C143	E.1/28 AND E.1/15 AND E.1/110	Yes		T C E P 0 0 1
	UCS2 in Katakana	R99	6.1			C145	C145	C145	C145	E.1/28 AND E.1/15 AND E.1/110	Yes		T C E F 0 0 1
16	SET UP CALL 27.22.4.13  Call confirmed by the user and connected	R99	1.1	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	E.1/29 AND E.1/110 AND E.1/111	Yes		
	call rejected by the user	R99	1.2	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	E.1/29 AND E.1/110 AND E.1/111	Yes		
	void putting all other calls on hold, ME busy	R99	1.4	C170 AND C177 AND C178 AND C180	C170 AND C177 AND C178 AND C180	C170 AND C177 AND C178 AND C180	C170 AND C177 AND C178 AND C180	C170 AND C177 AND C178 AND C180	C170 AND C177 AND C178 AND C180	E.1/29 E.1/29 AND E.1/110 AND E.1/111	Yes		
	disconnecting all other calls, ME busy	R99	1.5	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	E.1/29 AND E.1/110 AND E.1/111	Yes		

n	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	only if not currently busy on	R99	1.6	C177	C177	C177	C177	C177	C177	E.1/29 AND	Yes	
	another call, ME busy	1133	1.0	AND	AND	AND	AND	AND	AND	E.1/110 AND	103	
	another ban, WE baby			C178	C178	C178	C178	C178	C178	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	putting all other calls on hold, call	R99	1.7	C170	C170	C170	C170	C170	C170	E.1/29 AND	Yes	
	hold is not allowed	1100		AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	Capability configuration	R99	1.8	C101	C101	C101	C101	C101	C101	E.1/29 AND	Yes	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	long dialling number string	R99	1.9	C177	C177	C177	C177	C177	C177	E.1/29 AND	Yes	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C178	C178	C178	C178	C178	C178	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	long first alpha identifier	R99	1.10	C177	C177	C177	C177	C177	C177	E.1/29 AND	Yes	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C178	C178	C178	C178	C178	C178	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	Called party subaddress	R99	1.11	C124	C124	C124	C124	C124	C124	E.1/29 AND	Yes	
				AND	AND	AND	AND	AND	AND	E.1/110 AND		
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
	as a singular dispetion for the control	DOC	4.40	C180	C180	C180	C180	C180	C180	E 4/00 AND	Vaa	-
	maximum duration for the redial	R99	1.12	C119	C119	C119	C119	C119	C119	E.1/29 AND	Yes	
	mechanism			AND C177	AND C177	AND C177	AND C177	AND C177	AND C177	E.1/110 AND		
					AND	AND	AND	AND	AND	E.1/111		
				AND C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	second alpha identifier	R99	2.1	C177	C177	C177	C177	C177	C177	E.1/29 AND	Yes	
		1799	۷.۱	AND	AND	AND	AND	AND	AND	E.1/63 AND	162	
				C178	C178	C178	C178	C178	C178	E.1/110 AND		
				AND	AND	AND	AND	AND	AND	E.1/111		
				C180	C180	C180	C180	C180	C180	L. 1/ 1 1 1		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Icons – basic icon	R99	3.1,3.2, 3.4	C108 AND	C108 AND	C108 AND	C108 AND	C108 AND	C108 AND	E.1/29 AND E.1/110 AND	Yes	
				C177	C177	C177	C177	C177	C177	E.1/111		
				AND	AND	AND	AND	AND	AND			
				C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
	1	Doo	0.0	C180	C180	C180	C180	C180	C180	E 4/00 AND		
	Icons – colour icon	R99	3.3	C171 AND	C171 AND	C171 AND	C171 AND	C171 AND	C171 AND	E.1/29 AND E.1/110 AND	Yes	
				C177	C177	C177	C177	C177	C177	E.1/110 AND E.1/111		
				AND	AND	AND	AND	AND	AND	□.1/111		
				C178	C178	C178	C178	C178	C178			
				AND	AND	AND	AND	AND	AND			
				C180	C180	C180	C180	C180	C180			
	Text attribute – left alignment	Rel-5	4.1			C153	C153	C153	C153	E.1/29 AND	Yes	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/217 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
						AND	AND	AND	AND			
	Total attailments and an aliment and	Dale	4.2			C180	C180	C180	C180	E.1/29 AND	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154 AND	C154 AND	C154 AND	C154 AND	E.1/29 AND E.1/124 AND	res	
						C177	C177	C177	C177	E.1/218 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
						AND	AND	AND	AND			
						C180	C180	C180	C180			
	Text attribute – right alignment	Rel-5	4.3			C155	C155	C155	C155	E.1/29 AND	Yes	
						AND	AND	AND	AND	E.1/124 AND		
						C177	C177	C177	C177	E.1/219 AND		
						AND	AND	AND	AND	E.1/110 AND		
						C178	C178	C178	C178	E.1/111		
						AND	AND	AND	AND			
	Text attribute – large font size	Rel-5	4.4			C180 C157	C180 C157A	C180 C157	C180 C157A	E.1/29 AND	Yes	
	Toxt attribute - large forit size	1761-0	7.4			AND	ND	AND	ND	E.1/124 AND	169	
						C156	C156	C156	C156	E.1/221 AND		
						AND	AND	AND	AND	E.1/220 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
						AND	AND	AND	AND			
						C180	C180	C180	C180			

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cv	Sup- port	
	Text attribute – small font size	Rel-5	4.5			C158	C158A	C158	C158A	E.1/29 AND	<b>cy</b> Yes		1
						AND	ND	AND	ND	E.1/124 AND			
						C156	C156	C156	C156	E.1/222 AND			
						AND	AND	AND	AND	E.1/220 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
						AND	AND	AND	AND				
						C180	C180	C180	C180				
	Text attribute – bold on	Rel-5	4.6			C160	C160	C160	C160	E.1/29 AND	Yes		
						AND	AND	AND	AND	E.1/124 AND			
						C159	C159	C159	C159	E.1/225 AND			
						AND	AND	AND	AND	E.1/226 AND			
						C177	C177	C177	C177	E.1/110 AND	1		1
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
						AND	AND	AND	AND				
						C180	C180	C180	C180				
	Text attribute – italic on	Rel-5	4.7			C161	C161	C161	C161	E.1/29 AND	Yes		
						AND	AND	AND	AND	E.1/124 AND			
						C159	C159	C159	C159	E.1/225 AND			
						AND	AND	AND	AND	E.1/227 AND			
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
						AND	AND	AND	AND				
						C180	C180	C180	C180				
	Text attribute – underline on	Rel-5	4.8			C162	C162	C162	C162	E.1/29 AND	Yes		
						AND	AND	AND	AND	E.1/124 AND	1		1
						C159	C159	C159	C159	E.1/225 AND	1		1
						AND	AND	AND	AND	E.1/228 AND	1		1
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C178	C178	C178	C178				
						AND	AND	AND	AND		1		1
						C180	C180	C180	C180				L
	Text attribute – strikethrough on	Rel-5	4.9			C163	C163	C163	C163	E.1/29 AND	Yes		1
						AND	AND	AND	AND	E.1/124 AND			
						C159	C159	C159	C159	E.1/225 AND			
						AND	AND	AND	AND	E.1/229 AND	1		1
						C177	C177	C177	C177	E.1/110 AND			
						AND	AND	AND	AND	E.1/111	1		1
						C178	C178	C178	C178		1		1
						AND	AND	AND	AND		1		
						C180	C180	C180	C180				

ltem	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – foreground and	Rel-5	4.10			C164	C164	C164	C164	E.1/29 AND	Yes	
	background colours					AND	AND	AND	AND	E.1/124 AND		
	S .					C165	C165	C165	C165	E.1/230 AND		
						AND	AND	AND	AND	E.1/231 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
						AND	AND	AND	AND			
						C180	C180	C180	C180			
	UCS2 Display in Cyrillic	R99	5.1, 5.2.			C118	C118	C118	C118	E.1/29 AND	Yes	
						AND	AND	AND	AND	E.1/15 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
						AND	AND	AND	AND			
						C180	C180	C180	C180			
	UCS2 display in Chinese	R99	6.1, 6.2			C143	C143	C143	C143	E.1/29 AND	Yes	
						AND	AND	AND	AND	E.1/15 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
						AND	AND	AND	AND			
						C180	C180	C180	C180			
	UCS2 display in Katakana	R99	7.1, 7.2			C145	C145	C145	C145	E.1/29 AND	Yes	
						AND	AND	AND	AND	E.1/15 AND		
						C177	C177	C177	C177	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C178	C178	C178	C178			
						AND	AND	AND	AND			
						C180	C180	C180	C180			
	Frames	Rel-6	TBD							E.1/29 AND	TBD	
										E.1/177 AND		
										E.1/178 AND		
										E.1/110 AND		
										E.1/111		
17	POLLING OFF 27.22.4.14	R99	1.1	C180	C180	C180	C180	C180	C180	E.1/23	Yes	
18	PROVIDE LOCAL INFORMATION27.22.4.15											
	location information	R99	1.1	М	М	М	М	М	M	E.1/31	Yes	
	IMEI	R99	1.2	М	М	М	М	М	М	E.1/31	Yes	
	network measurement results and	R99	1.3	C167	C167	C167	C167	C167	C167	E.1/32 AND	System	
	BCCH channel list									E.1/67	Simulator only	
	Date, time and time zone	R99	1.4	М	M	M	М	М	М	E.1/59	No	-
		R99	1.4	M	M	M	M	M	M	E.1/68	No	-
	language setting		1.6	C167		C167						-
	Timing advance	R99	1.6	0167	C167	C16/	C167	C167	C167	E.1/69	System Simulator	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Access Technology	Rel-4	1.7				M	М	M	E.1/72	UMTS System Simulator only		
	Void												Г
	IMEISV	Rel-6	1.9				М	М	М	E.1/143	Yes		r
	Search Mode Change	Rel-6	1.10							E.1/144	TBD		r
	Charge State of the Battery	Rel-6	1.11				C139	C139	C139	E.1/170	No		ľ
	Intra-frequency UTRAN measurements	Rel-6	1.12				M	М	M	E.1/183	UMTS System Simulator only		
	Inter-frequency UTRAN measurements	Rel-6	1.13				М	М	М	E.1/183	UMTS System Simulator only		
19	SET UP EVENT LIST 27.22.4.16												Ī
	Set up call connected event	R99	1.1	C180	C180	C180	C180	C180	C180	E.1/33 AND E.1/35	Yes		ĺ
	Replace by new event list	R99	1.2	C180	C180	C180	C180	C180	C180	E.1/33 AND E.1/35 AND E.1/36	Yes		Ī
	Remove event	R99	1.3	C180	C180	C180	C180	C180	C180	E.1/33 AND E.1/35	Yes		ľ
	Remove Event on ME Power Cycle	R99	1.4	C180	C180	C180	C180	C180	C180	E.1/33 AND E.1/35	Yes		ĺ
20	PERFORM CARD APDU 27.22.4.17												ĺ
	Additional card inserted, Select MF and Get Response	R99	1.1	C109	C109	C109	C109	C109	C109	E.1/51	No		
	Additional card inserted, Select DF GSM, Select EF PLMN , Update Binary, Read Binary on EF PLMN	R99	1.2	C109	C109	C109	C109	C109	C109	E.1/51	No		
	Additional card inserted, card powered off	R99	1.3	C109	C109	C109	C109	C109	C109	E.1/51	No		Ī
	No card inserted, card powered off	R99	1.4	C109	C109	C109	C109	C109	C109	E.1/51	No		
	Invalid card reader identifier	R99	1.5	C109	C109	C109	C109	C109	C109	E.1/51	No		ĺ
	Detachable reader	R99	2.1	C116	C116	C116	C116	C116	C116	E.1/51	No		1
21	POWER OFF CARD 27.22.4.18												
	Additional card inserted	R99	1.1	C109	C109	C109	C109	C109	C109	E.1/50	No		ļ
	No card inserted	R99	1.2	C109	C109	C109	C109	C109	C109	E.1/50	No		ļ
	Detachable reader	R99	2.1	C116	C116	C116	C116	C116	C116	E.1/50	No		ļ
22	POWER ON CARD 27.22.4.19												

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Additional card inserted	R99	1.1	C109	C109	C109	C109	C109	C109	E.1/49	No	
	No ATR	R99	1.2	C109	C109	C109	C109	C109	C109	E.1/49	No	
	No card inserted	R99	1.3	C109	C109	C109	C109	C109	C109	E.1/49	No	
	Detachable reader	R99	2.1	C116	C116	C116	C116	C116	C116	E.1/49	No	
23	GET READER STATUS 27.22.4.20											
	Additional card inserted, card powered	R99	1.1	C109	C109	C109	C109	C109	C109	E.1/52	No	
	Additional card inserted, card not powered	R99	1.2	C109	C109	C109	C109	C109	C109	E.1/52	No	
	Additional card inserted, card not present	R99	1.3	C109	C109	C109	C109	C109	C109	E.1/52	No	
	Detachable reader	R99	2.1	C116	C116	C116	C116	C116	C116	E.1/52	No	
24	TIMER MANAGEMENT 27.22.4.21.1											
	Start timer 1 several times, get the current value of the timer and deactivate the timer successfully	R99	1.1	M	М	М	M	M	M	E.1/57 AND E.1/58	No	
	Start timer 2 several times, get the current value of the timer and deactivate the timer successfully	R99	1.2	M	М	М	M	M	M	E.1/57 AND E.1/58	No	
	Start timer 8 several times, get the current value of the timer and deactivate the timer successfully	R99	1.3	М	М	М	M	M	М	E.1/57 AND E.1/58	No	
	Try to get the current value of a timer which is not started: action in contradiction with the current timer state	R99	1.4	М	M	M	М	М	M	E.1/57 AND E.1/58	No	
	Try to deactivate a timer which is not started: action in contradiction with the current timer state	R99	1.5	М	М	М	M	M	М	E.1/57 AND E.1/58	No	
	Start 8 timers successfully	R99	1.6	M	М	М	M	М	М	E.1/57 AND E.1/58	No	
25	ENVELOPE TIMER EXPIRATION 27.22.4.21.2											
	Pending proactive UICC command	R99	2.1	М	М	М	М	М	М	E.1/6 AND E.1/57	No	
	USIM application toolkit busy	R99	2.2	М	М	М	M	M	M	E.1/6 AND E.1/57 AND E.1/20	No	
26	SET UP IDLE MODE TEXT 27.22.4.22											
	Display idle mode text	R99	1.1	C177	C177	C177	C177	C177	C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/110	Yes	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Replace idle mode text	R99	1.2	C177	C177	C177	C177	C177	C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/110	Yes	
	Remove idle mode test	R99	1.3	C177	C177	C177	C177	C177	C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/110	Yes	
	Competing information on ME display	R99	1.4	C177 AND C179 AND C180	C177 AND C179 AND C180	C177 AND C179 AND C180	C177 AND C179 AND C180	C177 AND C179 AND C180	C177 AND C179 AND C180	E.1/61 AND E.1/33 AND E.1/39 AND E.1/110	Yes	
	ME powered cycled	R99	1.5	C177	C177	C177	C177	C177	C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/110	Yes	
	Refresh with USIM initialization	R99	1.6	C177	C177	C177	C177	C177	C177	E.1/61 AND E.1/24 AND E.1/33 AND E.1/39 AND E.1/110	Yes	
	Large text string	R99	1.7	C177	C177	C177	C177	C177	C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/110	Yes	
	Icons – basic icon	R99	2.1, 2.2, 2.4	C108 AND C177	C108 AND C177	C108 AND C177	C108 AND C177	C108 AND C177	C108 AND C177	E.1/61 AND E.1/39 AND E.1/110	Yes	
	Icons – colour icon	R99	2.3	C171 AND C177	C171 AND C177	C171 AND C177	C171 AND C177	C171 AND C177	C171 AND C177	E.1/61 AND E.1/39 AND E.1/110	Yes	
	UCS2 display in Cyrillic	R99	3.1	C118 AND C177	C118 AND C177	C118 AND C177	C118 AND C177	C118 AND C177	C118 AND C177	E.1/61 AND E.1/15 AND E.1/39 AND E.1/110	Yes	
	Text attribute – left alignment	Rel-5	4.1			C153 AND C177	C153 AND C177	C153 AND C177	C153 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/217 AND E.1/110	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154 AND C177	C154 AND C177	C154 AND C177	C154 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/218 AND E.1/110	Yes	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – right alignment	Rel-5	4.3			C155 AND C177	C155 AND C177	C155 AND C177	C155 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/219 AND E.1/110	Yes	
	Text attribute – large font size	Rel-5	4.4			C157 AND C156 AND C177	C157A ND C156 AND C177	C157 AND C156 AND C177	C157 AND C156 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/10	Yes	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156 AND C177	C158A ND C156 AND C177	C158 AND C156 AND C177	C158 AND C156 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes	
	Text attribute – bold on	Rel-5	4.6			C160 AND C159 AND C177	C160 AND C159 AND C177	C160 AND C159 AND C177	C160 AND C159 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes	
	Text attribute – italic on	Rel-5	4.7			C161 AND C159 AND C177	C161 AND C159 AND C177	C161 AND C159 AND C177	C161 AND C159 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	Yes	
	Text attribute – underline on	Rel-5	4.8			C162 AND C159 AND C177	C162 AND C159 AND C177	C162 AND C159 AND C177	C162 AND C159 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	Yes	
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159 AND C177	C163 AND C159 AND C177	C163 AND C159 AND C177	C163 AND C159 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	Yes	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165 AND C177	C164 AND C165 AND C177	C164 AND C165 AND C177	C164 AND C165 AND C177	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/2110	Yes	
	UCS2 display in Chinese	R99	5.1			C143 AND C177	C143 AND C177	C143 AND C177	C143 AND C177	E.1/61 AND E.1/15 AND E.1/39 AND E.1/110	Yes	
	UCS2 display in Katakana	R99	6.1			C145 AND C177	C145 AND C177	C145 AND C177	C145 AND C177	E.1/61 AND E.1/15 AND E.1/39 AND E.1/110	Yes	
	Frames	Rel-6	TBD							E.1/61 AND E.1/177 AND E.1/178 AND E.1/110	TBD	
27	RUN AT COMMAND 27.22.4.23											
	No alpha Identifier	R99	1.1	C110	C110	C110	C110	C110	C110	E.1/62	No	
	null data alpha identifier presented	R99	1.2	C110	C110	C110	C110	C110	C110	E.1/62	No	
	alpha identifier presented	R99	1.3	C110 AND C177	C110 AND C177	C110 AND C177	C110 AND C177	C110 AND C177	C110 AND C177	E.1/62 AND E.1/110	No	
	Icons – basic icon	R99	2.1, 2.3, 2.5	C114 AND C177	C114 AND C177	C114 AND C177	C114 AND C177	C114 AND C177	C114 AND C177	E.1/62 AND E.1/110	No	
	Icons – colour icon	R99	2.2, 2.4,	C173 AND C177	C173 AND C177	C173 AND C177	C173 AND C177	C173 AND C177	C173 AND C177	E.1/62 AND E.1/110	No	
	Text attribute – left alignment	Rel-5	3.1			C110 AND C153 AND C177	C110 AND C153 AND C177	C110 AND C153 AND C177	C110 AND C153 AND C177	E.1/62 AND E.1/124 AND E.1/217 AND E.1/110	No	
	Text attribute – center alignment	Rel-5	3.2			C110 AND C154 AND C177	C110 ANDC 154 AND C177	C110 ANDC 154 AND C177	C110 AND C154 AND C177	E.1/62 AND E.1/124 AND E.1/218 AND E.1/110	No	
	Text attribute – right alignment	Rel-5	3.3			C110 AND C155 AND C177	C110 ANDC 155 AND C177	C110 ANDC 155 AND C177	C110 AND C155 AND C177	E.1/62 AND E.1/124 AND E.1/219 AND E.1/110	No	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – large font size	Rel-5	3.4			C110 AND	C110 ANDC	C110 ANDC	C110 AND	E.1/62 AND E.1/124 AND	No		
						C157	157AN	157A	C157	E.1/221 AND			
						AND	D	ND	AND	E.1/220 AND			
						C156	C156	C156	C156	E.1/110			
						AND	AND	AND	AND				
						C177	C177	C177	C177				
	Text attribute – small font size	Rel-5	3.5			C110	C110	C110	C110	E.1/62 AND	No		
						AND	ANDC	ANDC	AND	E.1/124 AND			
						C158	158AN	158A	C158	E.1/222 AND			
						AND	D	ND	AND	E.1/220 AND			
						C156	C156	C156	C156	E.1/110			
						AND	AND	AND	AND				
						C177	C177	C177	C177				L
	Text attribute – bold on	Rel-5	3.6			C110	C110	C110	C110	E.1/62 AND	No		
						AND	ANDC	ANDC	AND	E.1/124 AND			
						C160	160	160	C160	E.1/225 AND			
						AND	AND	AND	AND	E.1/226 AND			
						C159	C159	C159	C159	E.1/110			
						AND C177	AND C177	AND C177	AND C177				
	Text attribute – italic on	Rel-5	3.7			C1110	C177	C110	C177	E.1/62 AND	No		+
	Text attribute – Italic on	Kel-5	3.7			AND	ANDC	ANDC	AND	E.1/02 AND E.1/124 AND	INO		
						C161	161	161	C161	E.1/225 AND			
						AND	AND	AND	AND	E.1/227 AND			
						C159	C159	C159	C159	E.1/110			
						AND	AND	AND	AND	2.1/110			
						C177	C177	C177	C177				
	Text attribute – underline on	Rel-5	3.8		1	C110	C110	C110	C110	E.1/62 AND	No		T
						AND	ANDC	ANDC	AND	E.1/124 AND			
						C162	162	162	C162	E.1/225 AND			
						AND	AND	AND	AND	E.1/228 AND			
						C159	C159	C159	C159	E.1/110			
						AND	AND	AND	AND				
						C177	C177	C177	C177				
	Text attribute – strikethrough on	Rel-5	3.9			C110	C110	C110	C110	E.1/62 AND	No		
						AND	ANDC	ANDC	AND	E.1/124 AND			
						C163	163	163	C163	E.1/225 AND			
						AND	AND	AND	AND	E.1/229 AND			
						C159	C159	C159	C159	E.1/110			
						AND	AND	AND	AND				
						C177	C177	C177	C177				

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – foreground and background colours	Rel-5	3.10			C110 AND C164 AND C165 AND	C110 ANDC 164 AND C165 AND	C110 ANDC 164 AND C165 AND	C110 AND C164 AND C165 AND	E.1/62 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	No		
	UCS2 Display in Cyrillic	R99	4.1			C177 C149 AND C177	C177 C149 AND C177	C177 C149 AND C177	C177 C149 AND C177	E.1/62 AND E.1/15 AND E.1/110	No		
	UCS2 display in Chinese	R99	5.1			C150 AND C177	C150 AND C177	C150 AND C177	C150 AND C177	E.1/62 AND E.1/15 AND E.1/110	No		
	UCS2 display in Katakana	R99	6.1			C151 AND C177	C151 AND C177	C151 AND C177	C151 AND C177	E.1/62 AND E.1/15 AND E.1/110	No		
	Frames	Rel-6	TBD							E.1/62 AND E.1/177 AND E.1/178 AND E.1/110	TBD		
28	SEND DTMF 27.22.4.24												
	Normal	R99	1.1	C180	C180	C180	C180	C180	C180	E.1/66	Yes		L
	alpha identifier	R99	1.2, 1.3	C180	C180	C180	C180	C180	C180	E.1/66 AND E.1/110	Yes		TCEP001
	Mobile is not in a speech call	R99	1.4	C180	C180	C180	C180	C180	C180	E.1/66	Yes		
	Icons – basic icon	R99	2.1, 2.3	C108 AND C180	C108 AND C180	C108 AND C180	C108 AND C180	C108 AND C180	C108 AND C180	E.1/66 AND E.1/110	Yes		TCEP001
	Icons – colour icon	R99	2.2	C171 AND C180	C171 AND C180	C171 AND C180	C171 AND C180	C171 AND C180	C171 AND C180	E.1/66 AND E.1/110	Yes		T C E P 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	UCS2 display in Cyrillic	R99	3.1	C118 AND C180	C118 AND C180	C118 AND C180	C118 AND C180	C118 AND C180	C118 AND C180	E.1/66 AND E.1/15 AND E.1/110	Yes		T C E P 0 1
	Text attribute – left alignment	Rel-5	4.1			C153 AND C180	C153 AND C180	C153 AND C180	C153 AND C180	E.1/66 AND E.1/124 AND E.1/217 AND E.1/110	Yes		T C E P 0
	Text attribute – center alignment	Rel-5	4.2			C154 AND C180	C154 AND C180	C154 AND C180	C154 AND C180	E.1/66 AND E.1/124 AND E.1/218 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – right alignment	Rel-5	4.3			C155 AND C180	C155 AND C180	C155 AND C180	C155 AND C180	E.1/66 AND E.1/124 AND E.1/219 AND E.1/110	Yes		T C E P 0 1
	Text attribute – large font size	Rel-5	4.4			C157 AND C156 AND C180	C157A ND C156 AND C180	C157 AND C156 AND C180	C157 AND C156 AND C180	E.1/66 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – small font size	Rel-5	4.5			C158 AND C156 AND C180	C158A ND C156 AND C180	C158 AND C156 AND C180	C158 AND C156 AND C180	E.1/66 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes		T C E P 0 0

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – bold on	Rel-5	4.6			C160 AND C159 AND C180	C160 AND C159 AND C180	C160 AND C159 AND C180	C160 AND C159 AND C180	E.1/66 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes		T C E F 0 0 1
	Text attribute – italic on	Rel-5	4.7			C161 AND C159 AND C180	C161 AND C159 AND C180	C161 AND C159 AND C180	C161 AND C159 AND C180	E.1/66 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	Yes		T C E F 0 0 1
	Text attribute – underline on	Rel-5	4.8			C162 AND C159 AND C180	C162 AND C159 AND C180	C162 AND C159 AND C180	C162 AND C159 AND C180	E.1/66 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	Yes		T C E F 0 0 1
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159 AND C180	C163 AND C159 AND C180	C163 AND C159 AND C180	C163 AND C159 AND C180	E.1/66 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	Yes		T C E F 0 0
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165 AND C180	C164 AND C165 AND C180	C164 AND C165 AND C180	C164 AND C165 AND C180	E.1/66 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	Yes		T C E F 0 0
	UCS2 display in Chinese	R99	5.1			C143 AND C180	C143 AND C180	C143 AND C180	C143 AND C180	E.1/66 AND E.1/15 AND E.1/110	Yes		T C E F 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	UCS2 display in Katakana	R99	6.1			C145 AND C180	C145 AND C180	C145 AND C180	C145 AND C180	E.1/66 AND E.1/15 AND E.1/110	Yes		T C E P 0 0 1
	Frames	Rel-6	TBD							E.1/66 AND E.1/177 AND E.1/178 AND E.1/110	TBD		
29	LANGUAGE NOTIFICATION 27.22.4.25												
	Specific language notification	R99	1.1	C181	C181	C181	C181	C181	C181	E.1/70	No		╙
	Non specific language notification	R99	1.2	C181	C181	C181	C181	C181	C181	E.1/70	No		丄
30	LAUNCH BROWSER 27.22.4.26												
	No session already launched: Connect to the default URL	R99	1.1	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	E.1/71 AND E.1/110 AND E.1/111	Yes		
	connect to the specified URL, alpha identifier length=0	R99	1.2	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	E.1/71 AND E.1/110 AND E.1/111	Yes		
	Browser identity, no alpha identifier	R99	1.3	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	E.1/71 AND E.1/110 AND E.1/111	Yes		
	one bearer specified and gateway/proxy identity	R99	1.4	C122 AND C177 AND C178	C122 AND C177 AND C178	C122 AND C177 AND C178	C122 AND C177 AND C178	C122 AND C177 AND C178	C122 AND C177 AND C178	E.1/71 AND E.1/98 AND E.1/110 AND E.1/111	Yes		
	void	R99	1.5	Void			1						
	Interaction with current session	R99	2.1, 2.2, 2.3	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	E.1/71 AND E.1/110 AND E.1/111	Yes		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	UCS2 display in Cyrillic	R99	(s) 3.1	C111 AND	C111 AND	C111 AND	C111 AND	C111 AND	C111 AND	E.1/71 AND E.1/15 AND	Yes		
				C118	C118	C118	C118	C118	C118	E.1/110 AND			
				AND	AND	AND	AND	AND	AND	E.1/111			
				C177	C177	C177	C177	C177	C177				
				AND	AND	AND	AND	AND	AND				
				C178	C178	C178	C178	C178	C178				
	Icons – basic icon	R99	4.1, 4.2	C115	C115	C115	C115	C115	C115	E.1/71 AND	Yes		
				AND	AND	AND	AND	AND	AND	E.1/110 AND			
				C177	C177	C177	C177	C177	C177	E.1/111			
				AND	AND	AND	AND	AND	AND				
				C178	C178	C178	C178	C178	C178				
	Text attribute – left alignment	Rel-5	5.1			C111	C111	C111	C111	E.1/71 AND	Yes		
						AND	AND	AND	AND	E.1/124 AND			
						C153	C153 AND	C153 AND	C153 AND	E.1/217 AND E.1/110 AND			
						AND C177	C177	C177	C177	E.1/110 AND E.1/111			
						AND	AND	AND	AND	L.1/111			
						C178	C178	C178	C178				
	Text attribute – center alignment	Rel-5	5.2			C111	C111	C111	C111	E.1/71 AND	Yes		
	Text attribute Conten angriment	11010	0.2			AND	AND	AND	AND	E.1/124 AND	100		
						C154	C154	C154	C154	E.1/218 AND			
						AND	AND	AND	AND	E.1/110 AND			
						C177	C177	C177	C177	E.1/111			
						AND	AND	AND	AND				
						C178	C178	C178	C178				
	Text attribute – right alignment	Rel-5	5.3			C111	C111	C111	C111	E.1/71 AND	Yes		
						AND	AND	AND	AND	E.1/124 AND			
						C155	C155	C155	C155	E.1/219 AND			
						AND	AND	AND	AND	E.1/110 AND			
						C177	C177	C177	C177	E.1/111			
						AND C178	AND C178	AND C178	AND C178				
	Toyt attribute large font size	Rel-5	5.4			C178	C178	C178	C178	E.1/71 AND	Yes		
	Text attribute – large font size	Kei-5	5.4			AND	AND	AND	AND	E.1/124 AND	res		
						C157	C157A	C157	C157	E.1/124 AND E.1/221 AND			
						AND	ND	AND	AND	E.1/221 AND E.1/220 AND			
						C156	C156	C156	C156	E.1/110 AND			
						AND	AND	AND	AND	E.1/111			
						C177	C177	C177	C177				
						AND	AND	AND	AND				
						C178	C178	C178	C178				

ltem	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – small font size	Rel-5	5.5			C111	C111	C111	C111	E.1/71 AND	Yes	
						AND	AND	AND	AND	E.1/124 AND		
						C158	C158A	C158	C158	E.1/222 AND		
						AND	ND	AND	AND	E.1/220 AND		
						C156	C156	C156	C156	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C177	C177	C177	C177			
						AND	AND	AND	AND			
						C178	C178	C178	C178			
	Text attribute – bold on	Rel-5	5.6			C111	C111	C111	C111	E.1/71 AND	Yes	
						AND	AND	AND	AND	E.1/124 AND		
						C160	C160	C160	C160	E.1/225 AND		
						AND	AND	AND	AND	E.1/226 AND		
						C159	C159	C159	C159	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C177	C177	C177	C177			
						AND	AND	AND	AND			
	Tana and the same	D-L-E				C178	C178	C178	C178	E 4/74 AND	V	
	Text attribute – italic on	Rel-5	5.7			C111	C111	C111	C111	E.1/71 AND	Yes	
						AND	AND	AND	AND	E.1/124 AND		
						C161	C161	C161	C161	E.1/225 AND		
						AND	AND	AND	AND	E.1/227 AND		
						C159	C159	C159	C159	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C177 AND	C177 AND	C177 AND	C177 AND			
						C178	C178	C178	C178			
	Text attribute – underline on	Rel-5	5.8				C178	C178	C178	E.1/71 AND	Yes	
	Text attribute – underline on	Rei-5	5.6			C111					res	
						AND C162	AND C162	AND C162	AND C162	E.1/124 AND E.1/225 AND		
						AND	AND	AND	AND	E.1/228 AND		
						C159	C159	C159	C159	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C177	C177	C177	C177	L. 1/ 1 1 1		
						AND	AND	AND	AND			
						C178	C178	C178	C178			
	Text attribute – strikethrough on	Rel-5	5.9		+	C111	C111	C111	C111	E.1/71 AND	Yes	<b>-</b>
	Tox attribute Striketinough on	11013	0.5			AND	AND	AND	AND	E.1/124 AND	163	
						C163	C163	C163	C163	E.1/225 AND		
						AND	AND	AND	AND	E.1/229 AND		
						C159	C159	C159	C159	E.1/110 AND		
						AND	AND	AND	AND	E.1/111		
						C177	C177	C177	C177	L.1/111		
						AND	AND	AND	AND			
						C178	C178	C178	C178			

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – foreground and background colours	Rel-5	5.10			C111 AND C164	C111 AND C164	C111 AND C164	C111 AND C164	E.1/71 AND E.1/124 AND E.1/230 AND	Yes		
						AND C165 AND	AND C165 AND	AND C165 AND	AND C165 AND	E.1/231 AND E.1/110 AND E.1/111			
						C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178				
	UCS2 display in Chinese	R99	6.1			C111 AND C143 AND C177 AND C178	C111 AND C143 AND C177 AND C178	C111 AND C143 AND C177 AND C178	C111 AND C143 AND C177 AND C178	E.1/71 AND E.1/15 AND E.1/110 AND E.1/111	Yes		
	UCS2 display in Katakana	R99	7.1			C111 AND C145 AND C177 AND C178	C111 AND C145 AND C177 AND C178	C111 AND C145 AND C177 AND C178	C111 AND C145 AND C177 AND C178	E.1/71 AND E.1/15 AND E.1/110 AND E.1/111	Yes		
	Frames	Rel-6	TBD							E.1/71 AND E.1/177 AND E.1/178 AND E.1/110 AND E.1/111	TBD		
31	OPEN CHANNEL 27.22.4.27												
	void	R99	void	Void	void	void	void	void	void	void			Ш
	immediate link establishment, GPRS, no local address, no alpha identifier, no network access name	R99	2.1	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes		
	immediate link establishment GPRS, no alpha identifier, with network access name	R99	2.2	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	immediate link establishment, GPRS, with alpha identifier	R99	2.3	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/98 AND E.1/110 AND E.1/111	Yes		TCEP001,TCEP002
	immediate link establishment, GPRS, with null alpha identifier	R99	2.4	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes		
	immediate link establishment, GPRS, command performed with modifications (buffer size)	R99	2.5	C152	C152	C152	C152	C152	C152	E.1/89 AND E.1/98	Yes		
	void	void	2.6	Void	void	void	void	void	void	void			
	immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command	R99	2.7	C169	C169	C169	C169	C169	C169	E.1/89 AND E.1/98 AND E.1/110 AND E.1/111	Yes		TCEP001, TCEP002
	void	void	2.8	Void	void	void	void	void	void	void			<u> </u>
	Default bearer	R99	TBD							E.1/89 AND E.1/98 AND C132	TBD		
	Local Bearer	Rel-4	TBD							E.1/89 AND E.1/98 AND C132	TBD		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – left alignment	Rel-5	( <b>s</b> ) 5.1			C121 AND C153	C121 AND C153	C121 AND C153	C121 AND C153	E.1/89 AND E.1/98 AND E.1/124 AND E.1/217 AND E.1/110 AND E.1/111	Yes		TCEP001,TCEP00
	Text attribute – center alignment	Rel-5	5.2			C121 AND C154	C121 AND C154	C121 AND C154	C121 AND C154	E.1/89 AND E.1/98 AND E.1/124 AND E.1/218 AND E.1/110 AND E.1/111	Yes		02 TCEP001,TCEP002
	Text attribute – right alignment	Rel-5	5.3			C121 AND C155	C121 AND C155	C121 AND C155	C121 AND C155	E.1/89 AND E.1/98 AND E.1/124 AND E.1/219 AND E.1/110 AND E.1/111	Yes		TCEP001,TCEP002

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – large font size	Rel-5	5.4			C121 AND C157 AND C156	C121 AND C157A ND C156	C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/98 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110 AND E.1/111	Yes	T C E P 0 0 1 1 T C E
	Text attribute – small font size	Rel-5	5.5			C121 AND C158 AND C156	C121 AND C158A ND C156	C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/98 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110 AND E.1/111	Yes	2 T C E P 0 0 1 1 , T C E P 0 0 0 0 0 1 0 0 0 0 0 0 0 0 0 0 0 0 0
	Text attribute – bold on	Rel-5	5.6			C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110 AND E.1/111	Yes	T C E E P O O O O O O O O O O O O O O O O O

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Text attribute – italic on	Rel-5	5.7			C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110 AND E.1/111	Yes	T C E F O O O O O O O O O O O O O O O O O O
	Text attribute – underline on	Rel-5	5.8			C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110 AND E.1/111	Yes	2 T C E F 0 0 1 1 , T C E F 0 0 0 0 0 1 1 0 0 0 0 0 0 0 0 0 0 0 0
	Text attribute – strikethrough on	Rel-5	5.9			C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110 AND E.1/111	Yes	T C C E F C C C C C C C C C C C C C C C C

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – foreground and background colours	Rel-5	5.10			C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/98 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110 AND E.1/111	Yes		TCEP001, TCEP002
	Frames	Rel-6	TBD							E.1/89 AND E.1/98 AND E.1/177 AND E.1/178 AND E.1/110 AND E.1/111	TBD		
32	CLOSE CHANNEL 27.22.4.28												I
	successful	R99	1.1	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/90	Yes		
	with an invalid channel identifier	R99	1.2	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/90	Yes		
	on an already closed channel	R99	1.3	C121	C121	C121	C121	C121	C121	E.1/90	Yes		T
	Text attribute – left alignment	Rel-5	2.1			C121 AND C153	C121 AND C153	C121 AND C153	C121 AND C153	E.1/89 AND E.1/90 AND E.1/124 AND E.1/217 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – center alignment	Rel-5	2.2			C121 AND C154	C121 AND C154	C121 AND C154	C121 AND C154	E.1/89 AND E.1/90 AND E.1/124 AND E.1/218 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – right alignment	Rel-5	2.3			C121 AND C155	C121 AND C155	C121 AND C155	C121 AND C155	E.1/89 AND E.1/90 AND E.1/124 AND E.1/219 AND E.1/110	Yes		T C E P 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – large font size	Rel-5	2.4			C121 AND C157 AND C156	C121 AND C157A ND C156	C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/90 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	Yes		TCEP001
	Text attribute – small font size	Rel-5	2.5			C121 AND C158 AND C156	C121 AND C158A ND C156	C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/90 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes		TCEP001
	Text attribute – bold on	Rel-5	2.6			C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes		TCEP001
	Text attribute – italic on	Rel-5	2.7			C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	Yes		TCEP001
	Text attribute – underline on	Rel-5	2.8			C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	Yes		TCEP001
	Text attribute – strikethrough on	Rel-5	2.9			C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	Yes		TCEP001

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – foreground and background colours	Rel-5	2.10			C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/90 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	Yes		T C E P 0 1
	Frames	Rel-6	TBD							E.1/89 AND E.1/98 AND E.1/177 AND E.1/178 AND E.1/110	TBD		
33	already opened channel	R99	1.1	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/91 AND E.1/92	Yes		
	Text attribute – left alignment	Rel-5	2.1			C121 AND C153	C121 AND C153	C121 AND C153	C121 AND C153	E.1/89 AND E.1/91 AND E.1/92 AND E.1/124 AND E.1/1217 AND E.1/110	Yes		T C E P 0 0
	Text attribute – center alignment	Rel-5	2.2			C121 AND C154	C121 AND C154	C121 AND C154	C121 AND C154	E.1/89 AND E.1/91 AND E.1/124 AND E.1/218 AND E.1/110	Yes		T C E P 0 1
	Text attribute – right alignment	Rel-5	2.3			C121 AND C155	C121 AND C155	C121 AND C155	C121 AND C155	E.1/89 AND E.1/91 AND E.1/124 AND E.1/219 AND E.1/110	Yes		T C E P 0 1
	Text attribute – large font size	Rel-5	2.4			C121 AND C157 AND C156	C121 AND C157A ND C156	C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/91 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – small font size	Rel-5	2.5			C121 AND C158 AND C156	C121 AND C158A ND C156	C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/91 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – bold on	Rel-5	2.6			C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – italic on	Rel-5	2.7			C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – underline on	Rel-5	2.8			C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – strikethrough on	Rel-5	2.9			C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute— foreground and background colours	Rel-5	2.10			C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/91 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	Yes		T C E P 0 0 1
34	Frames  SEND DATA 27.22.4.30	Rel-6	TBD							E.1/89 AND E.1/91 AND E.1/177 AND E.1/178 AND E.1/110	TBD		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	immediate mode	R99	1.1	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes		
	Store mode	R99	1.2	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes		
	Store mode, Tx buffer fully used	R99	1.3	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes		T
	2 consecutive SEND DATA Store mode	R99	1.4	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes		Ī
	immediate mode with a bad channel identifier	R99	1.5	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes		
	void										Yes		
	Text attribute– left alignment	Rel-5	2.1			C121 AND C153	C121 AND C153	C121 AND C153	C121 AND C153	E.1/89 AND E.1/92 AND E.1/124 AND E.1/217 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – center alignment	Rel-5	2.2			C121 AND C154	C121 AND C154	C121 AND C154	C121 AND C154	E.1/89 AND E.1/92 AND E.1/124 AND E.1/218 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – right alignment	Rel-5	2.3			C121 AND C155	C121 AND C155	C121 AND C155	C121 AND C155	E.1/89 AND E.1/92 AND E.1/124 AND E.1/219 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – large font size	Rel-5	2.4			C121 AND C157 AND C156	C121 AND C157A ND C156	C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/92 AND E.1/124 AND E.1/221 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – small font size	Rel-5	2.5			C121 AND C158 AND C156	C121 AND C158A ND C156	C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/92 AND E.1/124 AND E.1/222 AND E.1/220 AND E.1/110	Yes		T C E P 0 0 1

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	Text attribute – bold on	Rel-5	2.6			C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/226 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – italic on	Rel-5	2.7			C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/227 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – underline on	Rel-5	2.8			C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/228 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute – strikethrough on	Rel-5	2.9			C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/229 AND E.1/110	Yes		T C E P 0 0 1
	Text attribute– foreground and background colours	Rel-5	2.10			C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/92 AND E.1/124 AND E.1/230 AND E.1/231 AND E.1/110	Yes		T C E P 0 0 1
	Frames	Rel-6	TBD							E.1/89 AND E.1/92 AND E.1/177 AND E.1/178 AND E.1/110	TBD		
35	GET CHANNEL STATUS 27.22.4.31												
	without any BIP channel opened	R99	1.1	C121	C121	C121	C121	C121	C121	E.1/93	Yes		П
	with a BIP channel currently opened	R99	1.2	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/93	Yes		
	after a link dropped	R99	1.3	C121	C121	C121	C121	C121	C121	E.1/89 AND E.1/93	Yes		

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
36	DATA DOWNLOAD TO UICC 27.22.5											
37	SMS-PP DATA DOWNLOAD 27.22.5.1											
	void		1.1									
	UICC responds with '61 XX'	R99	1.2	М	М	M	М	M	M	E.1/2	Yes	
	More time	R99	1.3	М	М	M	М	M	M	E.1/2	Yes	
	void		1.4									
	Data coding / message class	R99	1.6	М	М	M	М	M	M	E.1/2	Yes	
	RP-ERROR Handling	R99	1.7				М	М	М	E 1/2	Yes	
	General Data Coding UDH	R99	1.8	М	М	M	М	М	M	E 1/2	Yes	
38	CELL BROADCAST DATA DOWNLOAD 27.22.5.2											
	Cell Broadcast(GSM) - ME does not display message	R99	1.1	C167	C167	C167	C167	C167	C167	E.1/3	System Simulator only	
	void		1.2									
	Cell Broadcast(GSM) - ME displays message	R99	1.3	C167 AND C177	C167 AND C177	C167 AND C177	C167 AND C177	C167 AND C177	C167 AND C177	E.1/3 AND E.1/110	System Simulator only	
	Cell Broadcast (UTRAN) - ME does not display message	Rel-5	1.4					•		E.1/3	UMTS System Simulator only	
	Cell Broadcast (UTRAN) -More time	Rel-5	1.5							E.1/3 AND E.1/20	UMTS System Simulator only	
	Cell Broadcast(UTRAN) - ME displays message	Rel-5	1.6							E.1/3	UMTS System Simulator only	
	Cell Broadcast(GSM) - More time (UDH)	R99	1.7	C167	C167	C167	C167	C167	C167	E.1/3 AND E.1/20	System Simulator only	
39	CALL CONTROL BY USIM 27.22.6											
	Procedure for MO calls (Cell identity in envelope call control)	R99	1.1, 1.2, 1.4, 1.6, 1.8 to 1.14	C180	C180	C180	C180	C180	C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64	Yes	

tem	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	Procedure for MO calls (Cell identity in envelope call control)	R99	1.3 A, 1.5 A, 1.7 A	C140 AND C177 AND C178 AND C180	C140 AND C177 AND C178 AND C180	C140 AND C177 AND C178 AND C180	C140 AND C177 AND C178 AND C180	C140 AND C177 AND C178 AND C180	C140 AND C177 AND C178 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64 AND E.1/110 AND	Yes	
	Procedure for MO calls (Cell identity in envelope call control)	R99	1.3 B, 1.7 B	C141 AND C177 AND C178 AND C180	C141 AND C177 AND C178 AND C180	C141 AND C177 AND C178 AND C180	C141 AND C177 AND C178 AND C180	C141 AND C177 AND C178 AND C180	C141 AND C177 AND C178 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64 AND E.1/110 AND	Yes	
	Procedure for MO calls (Cell identity in envelope call control)	R99	1.5 B	C141 AND C180	C141 AND C180	C141 AND C180	C141 AND C180	C141 AND C180	C141 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64	Yes	
	Procedure for SS (Cell identity in envelope call control)	R99	2.1, 2.2, 2.3, 2.4	C174	C174	C174	C174	C174	C174	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
	Interaction with FDN (Cell identity in envelope call control)	R99	3.1, 3.2, 3.3, 3.4, 3.5	C146 AND C180	C146 AND C180	C146 AND C180	C146 AND C180	C146 AND C180	C146 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
	BDN service enabled	R99	4.1	C147 AND C177 AND C178 AND C180	C147 AND C177 AND C178 AND C180	C147 AND C177 AND C178 AND C180	C147 AND C177 AND C178 AND C180	C147 AND C177 AND C178 AND C180	C147 AND C177 AND C178 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64 AND E.1/110 AND	Yes	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	BDN service enabled, interaction with emergency call codes, R99 only	R99	4.2A	C147 AND C180						E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
	BDN service enabled, interaction with emergency call codes, Rel-4+	Rel-4	4.2B		C147 AND C180	C147 AND C180	C147 AND C180	C147 AND C180	C147 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 ND E.1/64	Yes	
	FDN and BDN enabled, set up a call in EFFDN, Allowed with modifications	R99	4.3	C146 AND C147 AND C177 AND C180	C146 AND C147 AND C177 AND C180	C146 AND C147 AND C177 AND C180	C146 AND C147 AND C177 AND C180	C146 AND C147 AND C177 AND C180	C146 AND C147 AND C177 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64 AND E.1/110	Yes	
	Call control on GPRS	Rel-5	TBD							E.1/98 AND E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13	TBD	
	BDN service enabled, ME not supporting BDN	R99	5.1			C176 AND C180	C176 AND C180	C176 AND C180	C176 AND C180	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
40	EVENT DOWNLOAD 27.22.7											
	27.22.7.1: MT call event	R99	1.1	C180	C180	C180	C180	C180	C180	E.1/34 AND E.1/33	Yes	
	27.22.7.2.1: call connected event	R99	1.1	C180	C180	C180	C180	C180	C180	E.1/35 AND E.1/33	Yes	
	27.22.7.2.2: ME supporting SET UP CALL	R99	2.1	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	C177 AND C178 AND C180	E.1/35 AND E.1/29 AND E.1/33 AND E.1/110 AND E.1/111	Yes	
	27.22.7.3: call disconnected event	R99	1.1	C180	C180	C180	C180	C180	C180	E.1/36 AND E.1/33	Yes	
	27.22.7.4: location status event	R99	1.1	М	М	М	М	М	М	E.1/37 AND E.1/33	Yes	
	27.22.7.5: user activity event	R99	1.1	C179	C179	C179	C179	C179	C179	E.1/38 AND E.1/33 AND E.1/111	No	

Item	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port
	27.22.7.6: idle screen available event	R99	1.1	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	C177 AND C178	E.1/39 AND E.1/33 AND E.1/110 AND E.1/111	Yes	
	27.22.7.7.1: Card reader status normal	R99	1.1	C109	C109	C109	C109	C109	C109	E.1/40 AND E.1/33	No	
	27.22.7.7.2: Detachable card reader	R99	2.1	C116	C116	C116	C116	C116	C116	E.1/40 AND E.1/33	No	
	27.22.7.8: language selection event	R99	1.1	C177 AND C178 AND C181	C177 AND C178 AND C181	C177 AND C178 AND C181	C177 AND C178 AND C181	C177 AND C178 AND C181	C177 AND C178 AND C181	E.1/41 AND E.1/33 AND E.1/110 AND E.1/111	No	
	27.22.7.9: Browser termination event	R99	1.1	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	C111 AND C177 AND C178	E.1/42 AND E.1/33 AND E.1/110 AND E.1/111	Yes	
	27.22.7.10: Data available event	R99	1.1	C121	C121	C121	C121	C121	C121	E.1/43 AND E.1/89 AND E.1/92 AND E.1/33	Yes	
	27.22.7.11: Channel status event	R99	1.1	C121	C121	C121	C121	C121	C121	E.1/44 AND E.1/89 AND E.1/33	Yes	
	27.22.7.12: Access Technology change event	Rel-4	TBD							E.1/45 AND E.1/33	TBD	
	27.22.7.13: Display parameter changed event	Rel-4	TBD							E.1/46 AND E.1/33	TBD	
	27.22.7.14: Local connection event	Rel-4	TBD							E.1/47 AND E.1/33	TBD	
	27.22.7.15: Network search mode change event	Rel-6	TBD							E.1/48 AND E.1/33	TBD	
	27.22.7.16: Browsing status event	Rel-6	TBD							E.1/193 AND E.1/33	TBD	
	Frame information changed event	Rel-6	TBD							E.1/195 AND E.1/177 AND E.1/178	TBD	
41	MO SMS Control by USIM 27.22.8											
	With proactive command, Allowed , no modification	R99	1.1	M	M	M	M	M	M	E1/12 AND E.1/26 AND E.1/110	Yes	

tem	Description	Re- lease	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Rel-7 ME	Rel-8 ME	Terminal Profile	Network Dependen cy	Sup- port	
	With user SMS, Allowed, no modification	R99	1.2	М	М	М	М	М	М	E1/12	Yes		
	With proactive command, Not allowed	R99	1.3	М	М	M	M	М	M	E1/12 AND E.1/26 AND E.1/110	Yes		
	With user SMS, Not allowed	R99	1.4	М	М	М	М	М	М	E1/12	Yes		+
	With proactive command,	R99	1.5	M	M	M	M	M	M	E1/12 AND	Yes		
	Allowed, with modifications									E.1/26 AND E.1/110			
	With user SMS, Allowed, with modifications	R99	1.6	М	М	М	М	М	М	E1/12	Yes		
	With Proactive command, the USIM responds with '90 00', Allowed, no modification	R99	1.7	М	М	M	M	M	M	E1/12 AND E.1/26 AND E.1/110	Yes		
	Send Short Message attempt by user, the USIM responds with '90 00', Allowed, no modification	R99	1.8	М	М	М	М	М	М	E1/12	Yes		_
	Void		1.9										_
<b>42</b>	SERVICE SEARCH	Rel-4	TBD							E.1/94	TBD		_
<b>43</b>	GET SERVICE INFORMATION	Rel-4	TBD							E.1/95	TBD		
14	DECLARE SERVICE	Rel-4	TBD							E.1/96	TBD		_
15	RETRIEVE MULTIMEDIA MESSAGE	Rel-6	TBD							E.1/173	TBD		
16	SUBMIT MULTIMEDIA MESSAGE	Rel-6	TBD							E.1/173	TBD		
17	DISPLAY MULTIMEDIA MESSAGE	Rel-6	TBD							E.1/173	TBD		
18	SET FRAMES	Rel-6	TBD							E.1/177 AND E.1/178	TBD		
49	GET FRAME STATUS	Rel-6	TBD							E.1/178 AND E.1/177	TBD		
50	Handling of command number 27.22.9												
	DISPLAY TEXT normal priority	R99	1.1	C177	C177	C177	C177	C177	C177	E.1/17 AND E.1/110	No		

10404	IE A 4/4 THEN MELOE N/A	0.0.0.1
C101	IF A.1/1 THEN M ELSE N/A	O_Cap_Conf
C102	IF A.1/16 THEN M ELSE N/A	O_GPRS
C103	void	
C104	IF A.1/2 THEN M ELSE N/A	O_Sust_text
C105	IF A.1/3 AND A.1/41 THEN M ELSE N/A	O_Ucs2_Entry AND O_UCS2_Cyrillic
C106	IF A.1/4 THEN M ELSE N/A	O Ext Str
C107	IF A.1/5 THEN M ELSE N/A	O_Help
C108	IF A.1/6 THEN O.1 ELSE N/A	O_lcons
C109	IF A.1/7 THEN M ELSE N/A	O_Dual_Slot
C110	IF A.1/9 AND A.1/46 THEN M ELSE N/A	O_Run_At AND O_+CIMI
C111	IF A.1/10 THEN M ELSE N/A	O LB
C112	IF A.1/11 THEN M ELSE N/A	O Soft key
C113	void	C_GOIL_KCY
		O DUE ALAND O COMILAND O LEGIS
C114	IF C110 AND C108 THEN O.1 ELSE N/A	O_Run_At AND O_+CIMI AND O_Icons
C115	IF C111 AND C108 THEN M ELSE N/A	O_LB AND O_lcons
C116	IF A.1/7 AND A.1/8 THEN M ELSE N/A	O_Dual_Slot AND O_Detach_Rdr
C117	void	
C118	IF A.1/15 AND A.1/41 THEN M ELSE N/A	O_Ucs2_Disp AND O_UCS2_Cyrillic
C119	IF A.1/19 THEN M ELSE N/A	O Redial
C120	IF A.1/20 THEN M ELSE N/A	O D NoResp
C121	IF A.1/21 AND A.1/17 THEN M ELSE N/A	O_BIP_GPRS AND O_UDP
C122	IF C111 AND A.1/16 THEN M ELSE N/A	O_LB AND O_GPRS
C123	void	
C124	IF A.1/22, test x.A M ELSE x.B M (where x is the expression of the	xpected sequence number value) O_CP_Subaddr
C125	IF A.1/23 THEN M ELSE N/A	O_lmm_Resp
C126	IF A.1/24 THEN M ELSE N/A	O Duration
C127	void	C_Balation
-		
C128	void	
C129	void	
C130	void	
C131	void	
C132	IF A.1/27 THEN M ELSE N/A	O BIP Local
C133	IF A.1/37 THEN M ELSE N/A	O Frames
C134	IF A.1/38 THEN M ELSE N/A	O MMS
C135	IF C110 AND C133 THEN M ELSE N/A	O_Run_At AND O_Frames
C136	IF C111 AND C133 THEN M ELSE N/A	O_LB AND O_Frames
C137	IF A.1/12 AND C133 THEN M ELSE N/A	O_BIP AND O_Frames
C138	IF A.1/82 THEN M ELSE N/A	O_M_T_Tones
C139	IF A.1/35 THEN M ELSE N/A	O_Batt
C140	IF A.1/39 THEN M ELSE N/A	O_UC_Before_EnvCC
C141	IF A.1/40 THEN M ELSE N/A	O_UC_After_EnvCC
C142		
	IF A.1/3 AND A.1/42 THEN M ELSE N/A	O_UCS2_Entry AND O_UCS2_Chinese
C143	IF A.1/15 AND A.1/42 THEN M ELSE N/A	O_UCS2_Disp AND O_UCS2_Chinese
C144	IF A.1/3 AND A.1/43 THEN M ELSE N/A	O_UCS2_Entry AND O_UCS2_Katakana
C145	IF A.1/15 AND A.1/43 THEN M ELSE N/A	O_UCS2_Disp AND O_UCS2_Katakana
C146	IF A. 1/45 THEN M ELSE N/A	O_FDN
C147	IF A. 1/44 THEN M ELSE N/A	O BDN
C148	IF (A.1/9 AND A.1/47) THEN M ELSE N/A	O Run At AND O +CGMI
C149	IF C148 AND C118 THEN M ELSE N/A	O_Run_At AND O_+CGMI AND O_ O_Ucs2_Disp AND
0149	II C140 AND C110 THEN WELSE N/A	
		O_Ucs2_ Cyrillic
C150	IF C148 AND C143 THEN M ELSE N/A	O_Run_At AND O_+CGMI AND O_ O_Ucs2_Disp AND
1		O_Ucs2_ Chinese
C151	IF C148 AND C145 THEN M ELSE N/A	O_Run_At AND O_+CGMI AND O_ O_Ucs2_Disp AND
1		O_Ucs2_ Katakana
C152	IF C121 AND A.1/49 THEN M ELSE N/A	O_BIP_GPRS AND O_UDP AND O_BUFFER_SIZE
C153	IF A.1/50 THEN M ELSE N/A	O_TAT_AL
	II /3.1/30 IIILIN IVI ELOL IN/A	O_IAI_AL

```
C154
            IF A.1/51 THEN M ELSE N/A
                                                                -- O TAT AC
C155
            IF A.1/52 THEN M ELSE N/A
                                                                -- O TAT AR
C156
            IF A.1/53 THEN M ELSE N/A
                                                                -- O_TAT_FSN
C157
            IF A.1/54 THEN M ELSE N/A
                                                                -- O TAT FSL
C158
            IF A.1/55 THEN M ELSE N/A
                                                                -- O TAT FSS
C159
            IF A.1/56 THEN M ELSE N/A
                                                                -- O TAT SN
C160
            IF A.1/57 THEN M ELSE N/A
                                                                -- O TAT SB
C161
            IF A.1/58 THEN M ELSE N/A
                                                                -- O TAT SI
C162
            IF A.1/59 THEN M ELSE N/A
                                                                -- O TAT SU
C163
            IF A.1/60 THEN M ELSE N/A
                                                                -- O TAT SS
C164
            IF A 1/61 THEN M FI SE N/A
                                                                -- O TAT STFC
C165
            IF A.1/62 THEN M ELSE N/A
                                                                -- O TAT STBC
C166
            IF A.1/63 THEN test step option n.A M ELSE test step option n.B M
                                                                          -- O longFTN
C167
            IF A.1/64 THEN M ELSE N/A
                                                                -- O GERAN
C168
            IF A.1/65 THEN M ELSE N/A
                                                                -- O Global PB
C169
            IF (C121 AND A.1/68 THEN test x.A M ELSE
                                                                -- (O BIP GPRS AND O UDP AND
            IF (C121 AND NOT A.1/68) test x.B M
                                                                   O_User_Confirm_Before_PDP_Context_Request) OR
                                                                   (O BIP GPRS AND O UDP AND NOT
                                                                O_User_Confirm_Before_PDP_Context_Request)
C170
            IF A.1/69 THEN M ELSE N/A
                                                                -- O Serv SS HOLD
C171
         IF A.1/6 THEN O.2 ELSE N/A
                                                                -- O Icons
                                                    -- O Icons
C172
           IF A.1/6 THEN O.4 ELSE N/A
C173
           IF C110 AND A.1/6 THEN O.2 ELSE N/A
                                                                -- O Run At AND O +CIMI AND O Icons
                                                    -- O AddInfo SS AND O Serv SS CFU
C174
         IF A.1/78 AND A.1/79 THEN M ELSE N/A
C175
         IF A.1/78 AND A.1/80 THEN M ELSE N/A
                                                    -- O AddInfo SS AND O Serv SS CLIR
                                                     -- O BDN
C176
         IF A. 1/44 THEN N/A ELSE M
C177
         IF A.1/84 THEN M ELSE N/A
                                                  -- O_No_Type_ND
C178
         IF A.1/85 THEN M ELSE N/A
                                                  -- O No Type NK
C179
         IF A.1/86 THEN M ELSE N/A
                                                  -- O_No_Type_NA
         IF A.1/87 THEN M ELSE N/A
                                                  -- O_No_Type_NS
C180
C181
         IF A.1/88 THEN M ELSE N/A
                                                  -- O_No_Type_NL
0.1
            IF A.1/75 tests x.yA M ELSE tests x.yB M (where x.y is the expected sequence number value)
0.2
            IF A.1/76 tests x.yA M ELSE tests x.yB M (where x.y is the expected sequence number value)
0.3
0.4
            IF A.1/75 AND A.1/77 tests x.yA M ELSE tests x.yB M (where x.y is the expected sequence number value)
TCEP001
            During the test execution, the display or the non-display of any alpha identifier, text string or icon shall be treated as successfully verified.
TCEP002
           The terminal may open the channel without explicit confirmation by the user.
```

# 3.5 Conventions for mathematical notations

The conventions for mathematical notations specified below shall apply.

# 3.5.1 Mathematical signs

The "plus or minus" sign is expressed by "±".

The sign "multiplied by" is expressed by "\*".

The sign "divided by" is expressed by "/", or the common division bar.

The sign "greater than or equal to" is expressed by "≥".

The sign "less than or equal to" is expressed by "≤".

# 4 Test equipment

The test equipment is specified in TS 34.108 [12] clause 4.

# 5 Testing methodology in general

When possible the present document refers to ETSITS 102 384 [26] to describe generic aspects of application toolkit tests

# 5.1 Testing of optional functions and procedures

Any function or procedure which is optional, as indicated in the present document, may be subject to a conformance test if it is implemented in the ME.

# 5.2 Test interfaces and facilities

The UICC, and (U)SS interfaces provides the main test interfaces for the purpose of performing conformance tests.

The tests which require a network simulator shall be carried out with using a Universal System Simulator when accessing a UTRAN, and if theses tests have to be performed additionally when accessing a GERAN a System Simulator shall be used instead.

# 5.3 Information to be provided by the apparatus supplier

The information to be provided by the apparatus supplier specified in both TS 34.108 [12] and TS 51.010-1 [23] shall apply, unless otherwise specified in the present clause.

In addition, the apparatus supplier shall provide the information with respect to the Supported Option table A.1 and to ME"s default configuration table A.2.

Table A.2: ME"s default configuration

Item	Description	Value	Status
1	DISPLAY TEXT: No Response from user timeout interval		С
2	GET INKEY: No response from user Timeout interval		С
3	GET INPUT: No response from user Timeout interval		С
4	SELECT ITEM: No response from user Timeout interval		С
5	DISPLAY TEXT Text Attributes Alignment [Left or Center or Right]		С
6	GET INKEY Text Attributes Alignment [Left or Center or Right]		С
7	GET IMPUT Text Attributes Alignment [Left or Center or Right]		С
8	PLAY TONE Text Attributes Alignment [Left or Center or Right]		С
9	SET UP MENU Text Attributes Alignment [Left or Center or Right]		С
10	SELECT ITEM Text Attributes Alignment [Left or Center or Right]		С
11	SEND SHORT MESSAGE Text Attributes Alignment [Left or Center or Right]		С
12	SEND SS Text Attributes Alignment [Left or Center or Right]		С
13	SEND USSD Text Attributes Alignment [Left or Center or Right]		С
14	SET UP CALL Text Attributes Alignment [Left or Center or Right]		С
15	SET UP IDLE MODE TEXT Text Attributes Alignment [Left or Center or Right]		С
16	RUN AT Text Attributes Alignment [Left or Center or Right]		С
17	SEND DTMF Text Attributes Alignment [Left or Center or Right]		С
18	LAUNCH BROWSER Text Attributes Alignment [Left or Center or Right]		С
19	OPEN CHANNEL Text Attributes Alignment [Left or Center or Right]		С
20	CLOSE CHANNEL Text Attributes Alignment [Left or Center or Right]		С
21	RECEIVE DATA Text Attributes Alignment [Left or Center or Right]		С
22	SEND DATA Text Attributes Alignment [Left or Center or Right]		С
23	IMEI		M
24	IMEISV		С
25	[Reserved]		
26	Additional Card Reader Id		С
27	Channel Id		С
28	Manufacturer identification as implemented according to TS 27.007, cl. 5.1		С
29	Preferred buffer size supported by the terminal for Open Channel command		С
Note:		in the tabl	e A.1

# 6 Implicit testing

For some 3GPP features conformance is not verified explicitly in the present document. This does not imply that correct functioning of these features is not essential, but that these are implicitly tested to a sufficient degree in other tests.

It should be noted that for these features some aspects have to be and are explicitly tested, e.g. the ability to switch between 1.8v and 3v operation.

Some UICC features will be explicitly tested as result of other tests. These should be identified for the following reason:

- To identify the areas of overlap and thus provide a more efficient testing.

# 7 Measurement uncertainty

The measured value relating to the corresponding limit shall be used to determine whether or not a terminal equipment meets the requirement. (ETR 028, annex B).

This process is often referred to as "shared risk".

# 8 Format of tests

In general the following basic format for tests is used:

27.22.X.X. Tested command

# 27.22.X.X.1 Command tested in «environment #1" (NORMAL, ICONS, UCS2 ...)

# 27.22.X.X.1.1 Definition and applicability

This clause refers back to clause 3.2.2.

# 27.22.X.X.1.2 Conformance requirement

Only if required, this clause details the necessary core specification references.

# 27.22.X.X.1.3 Test purpose

This clause details the purpose of the test.

#### 27.22.X.X.1.4 Method of test

#### 27.22.X.X.1.4.1 Initial conditions

If present this clause defines the initial conditions to be established before running each test sequence.

# 27.22.X.X.1.4.2 Procedure

This clause details the test procedure. Each test sequence shall be carried out independently unless otherwise stated.

- Sequence 1.1 (further initial conditions, added here)

Command 1.1.1
TERMINAL RESPONSE1.1.1A or 1.1.1B
Command 1.1.2
TERMINAL RESPONSE1.1.2

PROACTIVE COMMAND 1.1.1

**TERMINAL RESPONSE 1.1.1A** 

**TERMINAL RESPONSE 1.1.1B** 

PROACTIVE COMMAND 1.1.2

TERMINAL RESPONSE 1.1.2

- Sequence 1.2

Command 1.2.1
TERMINAL RESPONSE 1.2.1
Command 1.2.2
TERMINAL RESPONSE 1.2.2 (same as TERMINAL RESPONSE 1.2.1)
Command 1.2.3
TERMINAL RESPONSE 1.2.3

PROACTIVE COMMAND 1.2.1

PROACTIVE COMMAND 1.2.2

PROACTIVE COMMAND 1.2.3

**TERMINAL RESPONSE 1.2.1** 

TERMINAL RESPONSE 1.2.2

**TERMINAL RESPONSE 1.2.3** 

- Sequence 1.3

Command 1.3.1

TERMINAL RESPONSE1.3.1

#### PROACTIVE COMMAND 1.3.1

#### **TERMINAL RESPONSE 1.3.1**

#### 27.22.X.X.1.5 **Test requirement**

This clause details the conditions to be met for successful completion of the test.

#### 27.22.X.X.2 Command tested in "environment #2" (NORMAL, ICONS, UCS2 ...)

27.22.X.X. 2.1 **Definition and applicability** 

27.22.X.X. 2.2 **Conformance requirement** 

27.22.X.X. 2.3 Test purpose

27.22.X.X. 2.4 Method of test

27.22.X.X. 2.4.1.1 **Initial conditions** 

**Procedure** 27.22.X.X. 2.4.1.2

- Sequence 2.1

Command 2.1.1

TERMINAL RESPONSE2.1.1A or 2.1.1B

Command 2.1.2

TERMINAL RESPONSE2.1.2

PROACTIVE COMMAND 2.1.1

**TERMINAL RESPONSE 2.1.1A** 

**TERMINAL RESPONSE 2.1.1B** 

PROACTIVE COMMAND 2.1.2

**TERMINAL RESPONSE 2.1.2** 

Sequence 2.2

Command 2.2.1 TERMINAL RESPONSE 2.2.1

Command 2.2.2

TERMINAL RESPONSE 2.2.2 (same as TERMINAL RESPONSE 2.2.1)

Command 2.2.3

TERMINAL RESPONSE 2.2.3

PROACTIVE COMMAND 2.2.1

PROACTIVE COMMAND 2.2.2

PROACTIVE COMMAND 2.2.3

Coding TERMINAL RESPONSE 2.2.1

Coding TERMINAL RESPONSE 2.2.2

Coding TERMINAL RESPONSE 2.2.3

#### 27.22.X.X.2.5 **Test requirement**

# 9 Generic call set up procedures

The generic call set up procedure for PS and CS calls specified for GERAN and UTRAN shall apply.

For a ME accessing UTRAN the call set up procedures specified in TS 34.108 [12] subclause 7.2.3.1.3 and 7.2.3.2.3 shall apply, for session setup the ones defined in 7.2.4.1.3 and 7.2.4.2.3, unless otherwise specified in the present clause.

For a ME accessing GERAN the call set up procedures specified in TS 51.010-1 [23] subclause 26.9 shall apply, for session setup the ones defined in 45.2 and 45.4, unless otherwise specified in the present clause.

# 10 - 26Not used

# 27 Testing of the UICC/ME interface

This clause is an addition to TS 31.121 [21] to confirm the correct interpretation of the USIM Application Toolkit commands and the correct operation of the Toolkit facilities.

The definitions, declarations and default values specified in TS 31.121 [21] clause 4.1 shall apply, unless otherwise specified in the present clause.

A USIM Simulator with the appropriate USIM Application Toolkit functionality will be required. The USIM data defined below shall be used for all test cases unless otherwise specified within the test case.

The comprehension required flags in SIMPLE-TLV objects that are included in a TERMINAL RESPONSE or an ENVELOPE shall be set as described in TS 31.111 [15]. This means that in cases where it is up to the ME to decide if this flag is used or not, the corresponding Tag coding in the TERMINAL RESPONSEs and ENVELOPEs in this document represents only one of the two valid possibilities.

TS 31.111 [15] defines that in case of the general result "Command performed successfully" some proactive commands require additional information in the command result and in which cases this is mandatory or optional. Thus when additional information bytes are optional in the Result TLV, the additional information bytes of the Result TLV in the Terminal Responses shall be ignored.

# 27.1 - 27.21 Void

# 27.22 USIM Application Toolkit

# 27.22.1AGeneral Test purpose

Testing of functional conformance to USIM Application Toolkit commands, including proactive UICC commands.

All facilities given by the TERMINAL PROFILE as supported, for which tests exist in the present document, shall be tested.

Many of the proactive UICC commands include an alpha identifier data object. This is intended to be a short one or two word identifier for the ME to optionally display on the screen along with any other indications, at the same time as the ME performs the UICC command.

Note: The sequence of USIM Application Toolkit commands are specific to the Toolkit Application being executed within the UICC, hence sequential testing of commands is not possible. The testing will

therefore have to be performed on a command by command basis.

# 27.22.2ADefinition of default values for USIM Application Toolkit testing

A UICC containing the following default values is used for all tests of this clause unless otherwise stated.

For each item, the logical default values and the coding within the Elementary Files (EF) of the USIM follow, as defined in:

- TS 31.121 [21], clause 4.1.
- ETSI TS 102 384 [26], clause 27.22.1B.

Note 1: Bx represents byte x of the coding.

Note 2: Unless otherwise defined, the coding values in binary.

# EF<sub>UST</sub> (USIM Service Table)

# Logically:

(Service 01)	Local Phone	Book available					
(Service 02)	Fixed diallin	g numbers avail	lable				
(Service 06)	Barred dialli	ng numbers ava	ilable				
(Service 10)	Short Messa	ge Storage avail	able				
(Service 11)	Short Messa	ge Status Repor	ts available				
(Service 12)	Short Messa	ge Service Para	meters available				
(Service 15) Cell Broadcast Message Identifier available							
(Services 17, 18)	) The Group I	dentifier level 1	and level 2 not	available			
(Service 20)	User control	led PLMN selec	tor available				
(Service 22)	Image (IMG	) available					
(Service 27)	The GSM A	ccess available					
(Service 28)	Data downlo	ad via SMS-PP	available				
(Service 29)	Data downlo	oad via SMS-CB	available				
(Service 30)	Call Control	by USIM not a	vailable				
(Service 31)	MO-SMS C	ontrol by USIM	not available				
(Service 32)	RUN AT CO	OMMAND avail	lable				
(Service 33)	(Packed Swi	tched Domain)	shall be set to '1'				
(Service 34)	Enabled Ser	vices Table avai	lable				
Coding:	B1	B2	В3	B4	B5		
binary	xx1x xx11		xx1x 1x00	1001 11xx	xxx xx11		

The coding of EF<sub>UST</sub> shall conform with the capabilities of the USIM used.

# **EF**<sub>EST</sub> (Enabled Services Table)

# Logically:

(Service 1)	Fixed Dialling number deactivated
(Service 2)	Barred Dialling number deactivated
(Service 3)	APN Control List deactivated

Coding: B1 binary 00

# EF<sub>IMSI</sub> (International Mobile Subscriber Identity)

# Logically:

Length: 8 bytes

IMSI: 001 01 0123456789

Coding: '08 09 10 10 10 32 54 76 98'

# EF<sub>AD</sub> (Administrative Data)

Logically: Type approval operations

OFM to be deactivated by the Terminal

MNC: 2 digit

Coding: B1 B2 B3 B4 Hex 80 00 00 02

# **EF**<sub>LOCI</sub> (Location Information)

Logically:

LAI-MCC: 001 LAI-MNC: 01 LAI-LAC: 0001 TMSI: "FF .. FF"

B2 FF Coding: **B**5 **B7** B8 В9 B10 B11 B1 В3 B4 B6 FF FF FF 00 F1 10 00 01 FF Hex 00

# EF<sub>PSLOCI</sub> (Packet Switch Location Information)

Logically:

RAI-MCC: 001
RAI-MNC: 01
RAI-LAC: 0001
RAI-RAC: 05
P-TMSI: "FF...FF"

P-TMSI signature value: "FF...FF"

B4 Coding: В1 B2 B3 B5 B6 B7 FF FF FF Hex FF FF FF FF B13 Coding: B8 B9 B10 B11 **B12 B14** F1 00 00 01 05 00 Hex 10

# $EF_{CBMI}$ (Cell Broadcast Message Identifier)

Logically:

Cell Broadcast Message Identifier 1: '03 E7'

Coding: 03 E7 FF .. FF

# $EF_{CBMID}\left( Cell\ Broadcast\ Message\ Identifier\ for\ Data\ Download\right)$

Logically:

Cell Broadcast Message Identifier 1: '10 01'

Coding: 10 01 FF .. FF

# EF<sub>FDN</sub> (Fixed Dialling Numbers)

Logically:

Record 1: Length of alp ha identifier: 6 characters;

Alpha identifier: "FDN111";

Length of BCD number: "03";

TON and NPI: Telephony and unknown;

Dialled number: 123; CCI: None; Ext2: None.

Coding for record 1:

B1 B2 В3 В4 B5 B6 B7 B8 B9 B10 B11 B12 B13 Hex FF 44 4E 31 31 31 81 21 F3 FF FF 46 03

B14 B15 B16 B17 B18 B19 B20 FF FF FF FF FF FF FF

Record 2: Length of alpha identifier: 6 characters;

Alpha identifier: "FDN222";

Length of BCD number: "03";

TON and NPI: Telephony and Unknown;

Dialled number: 9876; CCI: None; Ext2: None.

Coding for record 2:

В1 B2 В3 В4 **B**5 B6 B7 B8 В9 B10 B11 B12 B13 Hex 46 44 4E 32 32 32 03 81 89 67 FF FF FF

B14 B15 B16 B17 B18 B19 B20 FF FF FF FF FF FF FF

Record 3: Length of alpha identifier: 6 characters;

Alpha identifier: "FDN333"; Length of BCD number: "0B";

TON and NPI: Telephony and International; bialled number: +12345678901234567890;

CCI: None; Ext2: None.

Coding for record 3:

В1 B2 В3 B4 **B**5 B6 B7 В8 В9 B10 B11 B12 B13 Hex 46 44 4E 33 33 33 0B 91 21 43 65 87 09

B14 B15 B16 B17 B18 B19 B20 21 43 65 87 09 FF FF

EF<sub>BDN</sub> (Barred Dialling Numbers)

Logically:

Record 1: Length of alpha identifier: 6 characters;

Alpha identifier: "BDN111"; Length of BCD number: "06";

TON and NPI: Telephony and International;

Dialled number: +1357924680;

CCI: None; Ext4: None Comprehension method pointer: None.

Coding for record 1:

Hex	B1 42	B2 44	B3 4E	B4 31	_	_		B8 91	-	B10 75		B13 08
	B14 FF	_	_	B17 FF	_	_	B20 FF					

Record 2: Length of alpha identifier: 6 characters;

Alpha identifier: "BDN222";

Length of BCD number: "03";

TON and NPI: Telephony and Unknown;

Dialled number: 122;
CCI: None;
Ext4: None
Comprehension method pointer: None.

Coding for record 2:

B2 B6 В7 В9 B10 B11 B12 B13 В1 В3 B4 B5 В8 Hex F2 FF 42 44 4E 32 32 32 04 81 21 FF FF B14 B15 B16 B17 B18 B19 B20 B21 FF FF FF FF FF FF FF FF

Record 3: Length of alpha identifier: 6 characters;

Alpha identifier: "BDN333";

Length of BCD number: "03";

TON and NPI: Telephony and Unknown;

Dialled number: 112;
CCI: None;
Ext4: None.
Comprehension method pointer: None

Coding for record 3:

B1 B2 ВЗ B4 В6 В7 В8 В9 B10 B13 **B**5 B11 B12 Hex 42 44 4E 33 33 33 03 81 11 F2 FF FF FF B14 B15 B16 B17 B18 B19 B20 B21 FF FF FF FF FF FF FF FF

 $EF_{ECC} \ (Emergency \ Call \ Codes)$ 

Logically: Emergency call code: "122";

Emergency call code alpha identifier: "TEST"; Emergency call Service Category: RFU

Coding: В1 B2 В3 В4 **B5** В6 B7 В8 F2 FF 54 Hex 21 45 53 54 00

EF<sub>SMSS</sub> (SMS Status)

Logically: Last used TP-MR set to "00".

Memory capacity available (flag unset b1="1").

Coding: B1 B2 Hex 00 FF

# EF<sub>SMSP</sub> (Short message service parameters)

Logically:

Record 1:

Record length: 28 bytes

Parameter Indicators:

TP-Destination Address: Parameter absent
TS-Service Centre Address: Parameter present
TP-Protocol Identifier: Parameter absent
TP-Data Coding Scheme: Parameter absent
TP-Validity Period: Parameter absent

TS-Service Centre Address:

TON: International Number

NPI: "ISDN / telephone numbering plan"

Dialled number string: "112233445566778"

Coding:	B1	B2	B3	 B13	B14	B15	B16	B17	B18	B19	B20	B21	B22	B23
Record 1:	FD	FF	FF	 FF	09	91	11	22	33	44	55	66	77	F8

B24	B25	B26	B27	B28
FF	FF	FF	FF	FF

For the display of icon: See ETSI TS 102 384 [26] subclause 27.22.1B.

# 27.22.1 Initialization of USIM Application Toolkit Enabled UICC by USIM Application Toolkit Enabled ME (Profile Download)

# 27.22.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.1.2 Conformance requirement

The ME shall support the PROFILE DOWNLOAD command as defined in:

- TS 31.111 [15] clause 5.2.

# 27.22.1.3 Test purpose

To verify that the ME sends a TERMINAL PROFILE command in accordance with the above requirements.

# 27.22.1.4 Method of test

# 27.22.1.4.1 Initial conditions

The ME is connected to the USIM Simulator. All elementary files are coded as the default Toolkit personalization..

# 27.22.1.4.2 Procedure

# **Expected Sequence 1 (PROFILE DOWNLOAD)**

Step	Direction	Message / Action	Comments
1	$USER \to ME$	Power on ME	[UICC Activation]
2	$ME \to UICC$	Select EF PL	
3	$UICC \to ME$	Read EF PL	
4	$ME \to UICC$	TERMINAL PROFILE 1.1	PROFILE DOWNLOAD
5	$UICC \to ME$	NORMAL ENDING OF	
		COMMAND 1.1	
6	$ME \to UICC$	Select USIM Application	

# **TERMINAL PROFILE: 1.1**

Logically:

Coding:

APDU:	CLA=80	INS=10	P1=00	P2=00	P3=XX	

DATA IN:	YY	ZZ	

With XX representing the length of the following DATA IN depending on the USIM Toolkit commands supported by the ME, and with YY, ZZ, ... representing here the bytes of the TERMINAL PROFILE data, as specified in TS 31.111 [15], clause 5.2.

# **NORMAL ENDING OF COMMAND: 1.1**

Logically:

Coding:

SW1=90	SW2=00
0001-30	0112-00

# 27.22.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.

# 27.22.2 Contents of the TERMINAL PROFILE command

# 27.22.2.1 Definition and applicability

See table E.1 in annex B.

# 27.22.2.2 Conformance requirement

The ME shall support the PROFILE DOWNLOAD command as defined in:

- TS 31.111 [15] clause 5.2.

# 27.22.2.3 Test purpose

- 1. Verify that the TERMINAL PROFILE indicates that Profile Download facility is supported.
- 2. Record which USIM Application Toolkit facilities are supported by the ME, to determine which subsequent tests are required.

# 27.22.2.4 Method of test

#### 27.22.2.4.1 Initial conditions

The ME is connected to the USIM Simulator. All elementary files are coded as the default USIM Application Toolkit personalization.

#### 27.22.1.4.2 Procedure

- a) The ME is powered on.
- b) After the ME sends the TERMINAL PROFILE command to the USIM Simulator, the USIM Simulator shall record the content of the TERMINAL PROFILE.
- c) The USIM Simulator shall return SW1 / SW2 of '90 00'.
- d) The contents of the TERMINAL PROFILE is recorded and compared to the corresponding table E.1 "status" column.

The test is terminated upon the ME sending the TERMINAL PROFILE command to the USIM Simulator.

# 27.22.2.5 Test requirement

- 1) After step a) the ME shall send the TERMINAL PROFILE command to the USIM Simulator with bit 1 of the first byte set to 1 (facility supported by ME).
- 2) In table E.1 for the corresponding ME USIM Toolkit Release and Options, The TERMINAL PROFILE information "support" recorded must be in accordance with the "Status" column. Support of features defined only in releases later than currently tested release shall be ignored.

# 27.22.3 Servicing of proactive UICC commands

# 27.22.3.1 Definition and applicability

See clause 3.2.2.

# 27.22.3.2 Conformance requirement

On detection of a pending USIM Application Toolkit command from the UICC the ME shall perform the FETCH command to retrieve the proactive UICC command. The result of the executed command shall be transmitted from the ME to the UICC within a TERMINAL RESPONSE command.

The MORE TIME proactive command is used in this test. The ME shall have knowledge of this command, but may not support this USIM Application Toolkit facility.

- TS 31.111 [15] clause 6.3.

# 27.22.3.3 Test purpose

To verify that the ME uses the FETCH command to obtain the proactive UICC command, after detection of a pending proactive UICC command. The pending proactive UICC command is indicated by the response parameters '91 xx' from the UICC.

To verify that the ME transmits the result of execution of the proactive UICC command to the UICC in the TERMINAL RESPONSE command.

# 27.22.3.4 Method of test

#### 27.22.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as the USIM Application Toolkit default.

The USIM Simulator is configured to indicate that a proactive UICC command is pending.

The USIM Simulator is configured to monitor the UICC - ME interface.

#### 27.22.3.4.2 Procedure

- a) The ME is powered on.
- b) After the ME has performed the PROFILE DOWNLOAD procedure, the USIM Simulator indicates that a Proactive UICC Command is pending with SW1 / SW2 of '91 0B'.
- c) After the ME sends the FETCH command to the USIM Simulator, the USIM Simulator returns Proactive UICC Command 2.1: MORE TIME.

# 27.22.3.5 Test requirement

- 1) After step b) the ME shall send the FETCH command to the UICC.
- 2) After step c) the ME shall send the TERMINAL REPONSE command with command number "01", type of command "02" and command qualifier "00".

# 27.22.4 Proactive UICC commands

#### 27.22.4.1 DISPLAY TEXT

# 27.22.4.1.1 DISPLAY TEXT (Normal)

#### 27.22.4.1.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.1.1.2 Conformance requirements

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

TS 31.111 [15], clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

#### 27.22.4.1.1.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.1.4 Method of test

# 27.22.4.1.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.1.4.2 Procedure

# Expected Sequence 1.1 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.1.

# Expected Sequence 1.2 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, screen busy)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.2.

# Expected Sequence 1.3 (DISPLAY TEXT, high priority, Unpacked 8 bit data for Text String, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.3.

# Expected Sequence 1.4 (DISPLAY TEXT, Packed, SMS default alphabet, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.4.

# Expected Sequence 1.5 (DISPLAY TEXT, Clear message after delay, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.5.

# Expected Sequence 1.6 (DISPLAY TEXT, Text string with 160 bytes, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.6.

# Expected Sequence 1.7 (DISPLAY TEXT, Backward move in UICC session, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.7.

# Expected Sequence 1.8 (DISPLAY TEXT, session terminated by user)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.8.

# Expected Sequence 1.9 (DISPLAY TEXT, icon and text to be displayed, no text string given, not understood by ME)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.9.

# 27.22.4.1.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.9.

# 27.22.4.1.2 DISPLAY TEXT (Support of "No response from user")

# 27.22.4.1.2.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.1.2.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

96

# 27.22.4.1.2.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.2.4 Method of test

27.22.4.1.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/1..

The USIM simulator shall be set to that period of time.

#### 27.22.4.1.2.4.2 Procedure

# Expected Sequence 2.1 (DISPLAY TEXT, no response from user)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.2.4.2, Expected Sequence.

#### 2.1.27.22.4.1.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

# 27.22.4.1.3 DISPLAY TEXT (Display of extension text)

# 27.22.4.1.3.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.1.3.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.15.

# 27.22.4.1.3.3 Test purpose

To verify that the ME displays the extension text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.3.4 Method of test

#### 27.22.4.1.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.1.3.4.2 Procedure

# **Expected Sequence 3.1 (DISPLAY TEXT, display of the extension text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.3.4.2, Expected Sequence 3.1.

# 27.22.4.1.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

# 27.22.4.1.4 DISPLAY TEXT (Sustained text)

#### 27.22.4.1.4.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.1.4.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.11, clause 8.6, clause 8.15, clause 8.15.

#### 27.22.4.1.4.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, returns a successful result in the TERMINAL RESPONSE command send to the UICC and sustain the display beyond sending the TERMINAL response.

#### 27.22.4.1.4.4 Method of test

# 27.22.4.1.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

# 27.22.4.1.4.4.2 Procedure

#### Expected Sequence 4.1 (DISPLAY TEXT, sustained text, unpacked data 8 bits, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.1.

# Expected Sequence 4.2 (DISPLAY TEXT, sustained text, clear message after delay, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.2.

# Expected Sequence 4.3 (DISPLAY TEXT, sustained text, wait for user MMI to clear, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.3.

# Expected Sequence 4.4 (DISPLAY TEXT, sustained text, wait for high priority event to clear, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: DISPLAY TEXT 4.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[wait for user to clear message]
		DISPLAY TEXT 4.4.1	
4	$ME \rightarrow USER$	Display "Toolkit Test 4"	
5	$ME \rightarrow UICC$	TERMINAL RESPONSE:	[Command performed successfully]
		DISPLAY TEXT 4.4.1	
6	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
7	$ME \rightarrow USER$	Display of "Toolkit Test 4"	Text shall sustain until - a higher priority event
			occurs.
8	$USS \to ME$	INCOMING MOBILE	
		TERMINATED CALL	

PROACTIVE COMMAND: DISPLAY TEXT 4.4.1

Logically:

Command details

Command number: 1

Command type: DISPLAY TEXT

Command qualifier: normal priority, wait for user to clear message

Device identities

Source device: UICC
Destination device: Display

**Text String** 

Data coding scheme: unpacked, 8 bit data Text: "Toolkit Test 4"

Immediate Response

Coding:

BER-TLV:	D0	1C	81	03	01	21	80	82	02	81	02	8D
	0F	04	54	6F	6F	6C	6B	69	74	20	54	65
	73	74	20	34	AB	00						

TERMINAL RESPONSE: DISPLAY TEXT 4.4.1

Logically:

Command details

Command number:

Command type: DISPLAY TEXT

Command qualifier: normal priority, wait for user to clear message

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	01	03	01	21	80	0.2	02	0.2	01	02	Λ1	00
DEK-ILV.	01	US	01	_ Z I	00	02	02	02	01	ೲ	UI	UU

# 27.22.4.1.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.4.

# 27.22.4.1.5 DISPLAY TEXT (Display of icons)

#### 27.22.4.1.5.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.1.5.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

# 27.22.4.1.5.3 Test purpose

To verify that the ME displays the icons which are referred to in the contents of the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.5.4 Method of test

#### 27.22.4.1.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

# 27.22.4.1.5.4.2 Procedure

# Expected Sequence 5.1A (DISPLAY TEXT, display of basic icon, self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.1A.

# Expected Sequence 5.1B (DISPLAY TEXT, display of basic icon, self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.1B.

# Expected Sequence 5.2A (DISPLAY TEXT, display of colour icon, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.2A.

# Expected Sequence 5.2B (DISPLAY TEXT, display of colour icon, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.2B.

# Expected Sequence 5.3A (DISPLAY TEXT, display of basic icon, not self explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.3A.

# Expected Sequence 5.3B (DISPLAY TEXT, display of basic icon, not self explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.3B.27.22.4.1.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1A to 5.3B.

# 27.22.4.1.6 DISPLAY TEXT (UCS2 display in Cyrillic)

# 27.22.4.1.6.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.1.6.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Cyrillic alphabet, as defined in the following technical specification: ISO/IEC 10646 [17].

# 27.22.4.1.6.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.6.4 Method of test

# 27.22.4.1.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.1.6.4.2 Procedure

# **Expected Sequence 6.1 (DISPLAY TEXT, UCS2 coded in Cyrillic)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.6.4.2, Expected Sequence 6.1.

# 27.22.4.1.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

# 27.22.4.1.7 DISPLAY TEXT (Variable Time out)

# 27.22.4.1.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.7.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31 and clause 8.43.

The ME shall support the variable time out for the display text.

# 27.22.4.1.7.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.7.4 Method of test

27.22.4.1.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.1.7.4.2 Procedure

# Expected Sequence 7.1 (DISPLAY TEXT, variable timeout of 10 seconds)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.7.4.2, Expected Sequence 7.1.

# 27.22.4.1.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

# 27.22.4.1.8 DISPLAY TEXT (Support of Text Attribute)

# 27.22.4.1.8.1 DISPLAY TEXT (Support of Text Attribute – Left Alignment)

# 27.22.4.1.8.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.1.8.1.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Left Alignment for the display text.

#### 27.22.4.1.8.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.1.4 Method of test

#### 27.22.4.1.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.1.8.1.4.2 Procedure

# **Expected Sequence 8.1 (DISPLAY TEXT, Text Attribute with Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.1.4.2, Expected Sequence 8.1.

27.22.4.1.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

27.22.4.1.8.2 DISPLAY TEXT (Support of Text Attribute – Center Alignment)

27.22.4.1.8.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.2.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Centre Alignment for the display text.

27.22.4.1.8.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.2.4 Method of test

27.22.4.1.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.2.4.2 Procedure

**Expected Sequence 8.2 (DISPLAY TEXT, Text Attribute with Center Alignment)** 

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.2.4.2, Expected Sequence 8.2.

27.22.4.1.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.2.

27.22.4.1.8.3 DISPLAY TEXT (Support of Text Attribute – Right Alignment)

27.22.4.1.8.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.3.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Right Alignment for the display text.

27.22.4.1.8.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.3.4 Method of test

27.22.4.1.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.3.4.2 Procedure

### **Expected Sequence 8.3 (DISPLAY TEXT, Text Attribute with Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.3.4.2, Expected Sequence 8.3.

27.22.4.1.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.3.

27.22.4.1.8.4 DISPLAY TEXT (Support of Text Attribute – Large Font Size)

27.22.4.1.8.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.4.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with large font size for the display text.

27.22.4.1.8.4.3 Test purpose

To verify that the ME displays the text formatted according to the large size font text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.4.4 Method of test

27.22.4.1.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.4.4.2 Procedure

# **Expected Sequence 8.4 (DISPLAY TEXT, Text Attribute with Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.4.4.2, Expected Sequence 8.4.

27.22.4.1.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.4.

27.22.4.1.8.5 DISPLAY TEXT (Support of Text Attribute – Small Font Size)

27.22.4.1.8.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.5.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with small font size for the display text.

27.22.4.1.8.5.3 Test purpose

To verify that the ME displays the text formatted according to the small size font text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.5.4 Method of test

27.22.4.1.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.5.4.2 Procedure

# **Expected Sequence 8.5 (DISPLAY TEXT, Text Attribute with Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.5.4.2, Expected Sequence 8.5.

27.22.4.1.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.5.

27.22.4.1.8.6 DISPLAY TEXT (Support of Text Attribute – Bold On)

27.22.4.1.8.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.6.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with bold on for the display text.

#### 27.22.4.1.8.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.6.4 Method of test

27.22.4.1.8.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.1.8.6.4.2 Procedure

# **Expected Sequence 8.6 (DISPLAY TEXT, Text Attribute with Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.6.4.2, Expected Sequence 8.6.

#### 27.22.4.1.8.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.6.

27.22.4.1.8.7 DISPLAY TEXT (Support of Text Attribute – Italic On)

27.22.4.1.8.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.7.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with italic on for the display text.

# 27.22.4.1.8.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.7.4 Method of test

27.22.4.1.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.7.4.2 Procedure

# **Expected Sequence 8.7 (DISPLAY TEXT, Text Attribute with Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.7.4.2, Expected Sequence 8.7.

27.22.4.1.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.7.

27.22.4.1.8.8 DISPLAY TEXT (Support of Text Attribute – Underline On)

27.22.4.1.8.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.8.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with underline on for the display text.

27.22.4.1.8.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.8.4 Method of test

27.22.4.1.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.8.4.2 Procedure

#### Expected Sequence 8.8 (DISPLAY TEXT, Text Attribute with Underline On)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.8.4.2, Expected Sequence 8.8.

27.22.4.1.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.8.

27.22.4.1.8.9 DISPLAY TEXT (Support of Text Attribute – Strikethrough On)

27.22.4.1.8.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.9.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with underline on for the display text.

27.22.4.1.8.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.9.4 Method of test

27.22.4.1.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.9.4.2 Procedure

# **Expected Sequence 8.9 (DISPLAY TEXT, Text Attribute with Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.9.4.2, Expected Sequence 8.9.

27.22.4.1.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.9.

27.22.4.1.8.10 DISPLAY TEXT (Support of Text Attribute – Foreground and Background Colours)

27.22.4.1.8.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.10.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with different foreground and background colours for the display text.

27.22.4.1.8.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.10.4 Method of test

27.22.4.1.8.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.10.4.2 Procedure

## **Expected Sequence 8.10 (DISPLAY TEXT, Text Attribute with Foreground and Background Colours)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.10.4.2, Expected Sequence 8.10.

27.22.4.1.8.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.10.

27.22.4.1.9 DISPLAY TEXT (UCS2 display in Chinese)

27.22.4.1.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.9.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Chinese characters, as defined in the following technical specification: ISO/IEC 10646 [17].

27.22.4.1.9.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.9.4 Method of test

27.22.4.1.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.9.4.2 Procedure

## Expected Sequence 9.1 (DISPLAY TEXT, UCS2 coded – Chinese characters)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.9.4.2, Expected Sequence 9.1.

27.22.4.1.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

27.22.4.1.10 DISPLAY TEXT (UCS2 display in Katakana)

27.22.4.1.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.10.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Katakana characters, as defined in the following technical specification: ISO/IEC 10646 [17].

27.22.4.1.10.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.10.4 Method of test

27.22.4.1.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.10.4.2 Procedure

### Expected Sequence 10.1 (DISPLAY TEXT, UCS2 coded – Katakana characters)

See ETSI TS 102 384 [26] in subclause 27.22.4.1.10.4.2, Expected Sequence 10.1.

27.22.4.1.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 10.1.

27.22.4.2 GET INKEY

27.22.4.2.1 GET INKEY(normal)

27.22.4.2.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.2.1.2 Conformance Requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.2.1.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the single character entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.1.4 Method of test

27.22.4.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be set to a display other than the idle display.

#### 27.22.4.2.1.4.2 Procedure

# Expected Sequence 1.1 (GET INKEY, digits only for character, Unpacked 8 bit data for Text String, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.1.

# Expected Sequence 1.2 (GET INKEY, digits only for character set, SMS default Alphabet for Text String, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.2.

#### Expected Sequence 1.3 (GET INKEY, backward move)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.3.

# **Expected Sequence 1.4 (GET INKEY, abort)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.4.

# Expected Sequence 1.5 (GET INKEY, SMS default alphabet for character set, Unpacked 8 bit data for Text String, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.5.

## Expected Sequence 1.6 (GET INKEY, Max length for the Text String, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.6.

27.22.4.2.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.6.

# 27.22.4.2.2 GET INKEY (No response from User)

# 27.22.4.2.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.2.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.2.2.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.2.2.4 Method of test

#### 27.22.4.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/2.

The USIM Simulator shall be set to that period of time.

#### 27.22.4.2.4.2 Procedure

#### **Expected Sequence 2.1 (GET INKEY, no response from the user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.2.4.2, Expected Sequence 2.1.

#### 27.22.4.2.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

# 27.22.4.2.3 GET INKEY (UCS2 display in Cyrillic)

# 27.22.4.2.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.2.3.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

## 27.22.4.2.3.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.3.4 Method of test

27.22.4.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.2.3.4.2 Procedure

### Expected Sequence 3.1 (GET INKEY, Text String coding in UCS2 Alphabet in Cyrillic, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.3.4.2, Expected Sequence 3.1.

# Expected Sequence 3.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet in Cyrillic, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.3.4.2, Expected Sequence 3.2.

#### 27.22.4.2.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1 to 3.2.

## 27.22.4.2.4 GET INKEY (UCS2 entry in Cyrillic)

### 27.22.4.2.4.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.2.4.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

## 27.22.4.2.4.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.4.4 Method of test

#### 27.22.4.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.2.4.4.2 Procedure

## Expected Sequence 4.1 (GET INKEY, characters from UCS2 alphabet in Cyrillic, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.4.2, Expected Sequence 4.1.

27.22.4.2.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.2.5 GET INKEY ("Yes/No" Response)

27.22.4.2.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.5.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

27.22.4.2.5.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.5.4 Method of test

27.22.4.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.2.5.4.2 Procedure

## Expected Sequence 5.1(GET INKEY, "Yes/No" Response for the input, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.5.4.2, Expected Sequence 5.1.

27.22.4.2.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

27.22.4.2.6 GET INKEY (display of Icon)

27.22.4.2.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.6.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

#### 27.22.4.2.6.3 Test purpose

To verify that the ME displays the Icon contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.6.4 Method of test

27.22.4.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

27.22.4.2.6.4.2 Procedure

## Expected Sequence 6.1A (GET INKEY, Basic icon, self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.1A.

# Expected Sequence 6.1B (GET INKEY, Basic icon, self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.1B.

## Expected Sequence 6.2A (GET INKEY, Basic icon, non self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.2A.

# Expected Sequence 6.2B (GET INKEY, Basic icon, non self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.2B.

#### Expected Sequence 6.3A (GET INKEY, Colour icon, self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.3A.

# Expected Sequence 6.3B (GET INKEY, Colour icon, self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.3B.

#### Expected Sequence 6.4A (GET INKEY, Colour icon, non self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.4A.

# Expected Sequence 6.4B (GET INKEY, Colour icon, non self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.4B.

## 27.22.4.2.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1A to 6.4B.

## 27.22.4.2.7 GET INKEY (Help Information)

## 27.22.4.2.7.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.2.7.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

#### 27.22.4.2.7.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.7.4 Method of test

#### 27.22.4.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.2.7.4.2 Procedure

## **Expected Sequence 7.1 (GET INKEY, help information available)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.7.4.2, Expected Sequence 7.1.

#### 27.22.4.2.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

## 27.22.4.2.8 GET INKEY (Variable Time out)

# 27.22.4.2.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.2.8.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

## 27.22.4.2.8.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.8.4 Method of test

27.22.4.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.8.4.2 Procedure

# Expected Sequence 8.1 (GET INKEY, variable time out of 10 seconds)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.8.4.2, Expected Sequence 8.1.

27.22.4.2.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

27.22.4.2.9 GET INKEY (Support of Text Attribute)

27.22.4.2.9.1 GET INKEY (Support of Text Attribute – Left Alignment)

27.22.4.2.9.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.1.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

# 27.22.4.2.9.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.1.4 Method of test

27.22.4.2.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.1.4.2 Procedure

# **Expected Sequence 9.1 (GET INKEY, Text attribute with Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.1.4.2, Expected Sequence 9.1.

27.22.4.2.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

27.22.4.2.9.2 GET INKEY (Support of Text Attribute – Center Alignment)

27.22.4.2.9.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.2.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

#### 27.22.4.2.9.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.2.4 Method of test

27.22.4.2.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.2.9.2.4.2 Procedure

#### Expected Sequence 9.2 (GET INKEY, Text attribute with Center Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.2.4.2, Expected Sequence 9.2.

27.22.4.2.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.2.

27.22.4.2.9.3 GET INKEY (Support of Text Attribute – Right Alignment)

27.22.4.2.9.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.3.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

## 27.22.4.2.9.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.3.4 Method of test

27.22.4.2.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.3.4.2 Procedure

# **Expected Sequence 9.3 (GET INKEY, Text attribute with Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.3.4.2, Expected Sequence 9.3.

27.22.4.2.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.3.

27.22.4.2.9.4 GET INKEY (Support of Text Attribute – Large Font Size)

27.22.4.2.9.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.4.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

### 27.22.4.2.9.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.4.4 Method of test

27.22.4.2.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.4.4.2 Procedure

# Expected Sequence 9.4 (GET INKEY, Text attribute with Large Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.4.4.2, Expected Sequence 9.4.

27.22.4.2.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.4.

27.22.4.2.9.5 GET INKEY (Support of Text Attribute – Small Font Size)

27.22.4.2.9.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.5.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

#### 27.22.4.2.9.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.5.4 Method of test

27.22.4.2.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.2.9.5.4.2 Procedure

#### Expected Sequence 9.5 (GET INKEY, Text attribute with Small Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.5.4.2, Expected Sequence 9.5.

27.22.4.2.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.5.

27.22.4.2.9.6 GET INKEY (Support of Text Attribute – Bold On)

27.22.4.2.9.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.6.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

## 27.22.4.2.9.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.6.4 Method of test

27.22.4.2.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.6.4.2 Procedure

# Expected Sequence 9.6 (GET INKEY, Text attribute with Bold On)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.6.4.2, Expected Sequence 9.6.

27.22.4.2.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.6.

27.22.4.2.9.7 GET INKEY (Support of Text Attribute – Italic On)

27.22.4.2.9.7.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.2.9.7.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

### 27.22.4.2.9.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.7.4 Method of test

27.22.4.2.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.7.4.2 Procedure

# Expected Sequence 9.7 (GET INKEY, Text attribute with Italic On)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.7.4.2, Expected Sequence 9.7.

27.22.4.2.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.7.

27.22.4.2.9.8 GET INKEY (Support of Text Attribute – Underline On)

27.22.4.2.9.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.8.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

#### 27.22.4.2.9.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.8.4 Method of test

27.22.4.2.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.2.9.8.4.2 Procedure

#### Expected Sequence 9.8 (GET INKEY, Text attribute with Underline On)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.8.4.2, Expected Sequence 9.8.

27.22.4.2.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.8.

27.22.4.2.9.9 GET INKEY (Support of Text Attribute – Strikethrough On)

27.22.4.2.9.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.9.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

## 27.22.4.2.9.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.9.4 Method of test

27.22.4.2.9.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.9.4.2 Procedure

# Expected Sequence 9.9 (GET INKEY, Text attribute with Strikethrough On)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.9.4.2, Expected Sequence 9.9.

27.22.4.2.9.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.9.

27.22.4.2.9.10 GET INKEY (Support of Text Attribute – Foreground and Background Colour)

27.22.4.2.9.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.10.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

27.22.4.2.9.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.10.4 Method of test

27.22.4.2.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.10.4.2 Procedure

## **Expected Sequence 9.10 (GET INKEY, Text attribute with Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.10.4.2, Expected Sequence 9.10.

27.22.4.2.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.10.

## 27.22.4.2.10 GET INKEY (UCS2 display in Chinese)

27.22.4.2.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.10.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

## 27.22.4.2.10.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.10.4 Method of test

27.22.4.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.2.10.4.2 Procedure

# Expected Sequence 10.1 (GET INKEY, Text String coding in UCS2 Alphabet - Chinese characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.10.4.2, Expected Sequence 10.1.

# Expected Sequence 10.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet - Chinese characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.10.4.2, Expected Sequence 10.2.

27.22.4.2.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 10.1 to 10.2.

27.22.4.2.11 GET INKEY (UCS2 entry in Chinese)

27.22.4.2.11.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.11.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.11.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.11.4 Method of test

27.22.4.2.11.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.2.11.4.2 Procedure

# Expected Sequence 11.1 (GET INKEY, characters from UCS2 alphabet - Chinese characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.11.4.2, Expected Sequence 11.1.

#### 27.22.4.2.11.5 Test requirement

The ME shall operate in the manner defined in expected sequence 11.1

### 27.22.4.2.12 GET INKEY (UCS2 display in Katakana)

# 27.22.4.2.12.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.2.12.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.12.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.12.4 Method of test

#### 27.22.4.2.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.2.12.4.2 Procedure

# Expected Sequence 12.1 (GET INKEY, Text String coding in UCS2 Alphabet - Katakana characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.12.4.2, Expected Sequence 12.1.

# Expected Sequence 12.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet - Katakana characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.12.4.2, Expected Sequence 12.2.

27.22.4.2.12.5 Test requirement

The ME shall operate in the manner defined in expected sequence 12.1 to 12.2.

27.22.4.2.13 GET INKEY (UCS2 entry in Katakana)

27.22.4.2.13.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.13.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

27.22.4.2.13.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.13.4 Method of test

27.22.4.2.13.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.2.13.4.2 Procedure

# Expected Sequence 13.1 (GET INKEY, characters from UCS2 alphabet - Katakana characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.2.13.4.2, Expected Sequence 13.1.

27.22.4.2.13.5 Test requirement

The ME shall operate in the manner defined in expected sequence 13.1

### 27.22.4.3 GET INPUT

### 27.22.4.3.1 GET INPUT (normal)

### 27.22.4.3.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.3.1.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

### 27.22.4.3.1.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.1.4 Method of test

#### 27.22.4.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.3.1.4.2 Procedure

# Expected Sequence 1.1 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.1.

# Expected Sequence 1.2 (GET INPUT, digits only, SMS default alphabet, ME to echo text, packing SMS Point-to-point required by ME)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.2.

# Expected Sequence 1.3 (GET INPUT, character set, SMS Default Alphabet, ME to echo text, ME supporting 8 bit data Message)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.3.

# Expected Sequence 1.4 (GET INPUT, digits only, SMS default alphabet, ME to hide text, ME supporting 8 bit data Message)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.4.

# Expected Sequence 1.5 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.5.

#### **Expected Sequence 1.6 (GET INPUT, backwards move)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.6.

## **Expected Sequence 1.7 (GET INPUT, abort)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.7.

# Expected Sequence 1.8 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.8.

# Expected Sequence 1.9 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.9.

#### Expected Sequence 1.10 (GET INPUT, null length for the text string, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.10.

## 27.22.4.3.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.10.

### 27.22.4.3.2 GET INPUT (No response from User)

#### 27.22.4.3.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.3.2.2 Conformance requirement

The ME shall support the GET INPUT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

## 27.22.4.3.2.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

### 27.22.4.3.2.4 Method of test

#### 27.22.4.3.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/3.

The USIM Simulator shall be set to that period of time.

#### 27.22.4.3.2.4.2 Procedure

### **Expected Sequence 2.1 (GET INPUT, no response from the user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.2.4.2, Expected Sequence 2.1.

27.22.4.3.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

27.22.4.3.3 GET INPUT (UCS2 display in Cyrillic)

27.22.4.3.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.3.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

27.22.4.3.3.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.3.4 Method of test

27.22.4.3.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.3.4.2 Procedure

Expected Sequence 3.1 (GET INPUT, text string coding in UCS2 in Cyrillic, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.3.4.2, Expected Sequence 3.1.

Expected Sequence 3.2 (GET INPUT, max length for the text string coding in UCS2 in Cyrillic, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.3.4.2, Expected Sequence 3.2.

27.22.4.3.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1 to 3.2.

27.22.4.3.4 GET INPUT (UCS2 entry in Cyrillic)

27.22.4.3.4.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.3.4.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

#### 27.22.4.3.4.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.4.4 Method of test

27.22.4.3.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.3.4.4.2 Procedure

## Expected Sequence 4.1 (GET INPUT, character set from UCS2 alphabet in Cyrillic, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.4.4.2, Expected Sequence 4.1.

# Expected Sequence 4.2 (GET INPUT, character set from UCS2 alphabet in Cyrillic, Max length for the input, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.4.4.2, Expected Sequence 4.2.

### 27.22.4.3.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.2.

# 27.22.4.3.5 GET INPUT (default text)

#### 27.22.4.3.5.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.3.5.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.23.

#### 27.22.4.3.5.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.5.4 Method of test

27.22.4.3.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.5.4.2 Procedure

## Expected Sequence 5.1(GET INPUT, default text for the input, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.5.4.2, Expected Sequence 5.1.

# Expected Sequence 5.2 (GET INPUT, default text for the input with max length, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.5.4.2, Expected Sequence 5.2.

27.22.4.3.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1 to 5.2.

27.22.4.3.6 GET INPUT (display of Icon)

27.22.4.3.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.6.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.5.4, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 12.31.

27.22.4.3.6.3 Test purpose

To verify that the ME displays the Icon contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.6.4 Method of test

27.22.4.3.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

27.22.4.3.6.4.2 Procedure

## Expected Sequence 6.1A (GET INPUT, Basic icon, self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.1A.

# Expected Sequence 6.1B (GET INPUT, Basic icon, self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.1B.

#### Expected Sequence 6.2A (GET INPUT, Basic icon, non self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.2A.

# Expected Sequence 6.2B (GET INPUT, Basic icon, non self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.2B.

## Expected Sequence 6.3A (GET INPUT, Colour icon, self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.3A.

# Expected Sequence 6.3B (GET INPUT, Colour icon, self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.3B.

### Expected Sequence 6.4A (GET INPUT, Colour icon, non self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.4A.

# Expected Sequence 6.4B (GET INPUT, Colour icon, non self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.4B.

# 27.22.4.3.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 6.1A to 6.4B.

### 27.22.4.3.7 GET INPUT (Help Information)

## 27.22.4.3.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.3.7.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.3.7.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns a 'help information required by the user' result value in the TERMINAL RESPONSE command sent to the UICC if the user has indicated the need to get help information.

#### 27.22.4.3.7.4 Method of test

### 27.22.4.3.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.7.4.2 Procedure

# Expected Sequence 7.1 (GET INPUT, digits only, ME to echo text, ME supporting 8 bit data Message, help information available)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.7.4.2, Expected Sequence 7.1.

27.22.4.3.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

27.22.4.3.8 GET INPUT (Support of Text Attribute)

27.22.4.3.8.1 GET INPUT (Support of Text Attribute – Left Alignment)

27.22.4.3.8.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.1.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

# 27.22.4.3.8.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.1.4 Method of test

27.22.4.3.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.1.4.2 Procedure

# Expected Sequence 8.1 (GET INPUT, Text attribute – Left Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.1.4.2, Expected Sequence 8.1.

27.22.4.3.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

27.22.4.3.8.2 GET INPUT (Support of Text Attribute – Center Alignment)

27.22.4.3.8.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.3.8.2.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.2.4 Method of test

27.22.4.3.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.3.8.2.4.2 Procedure

### Expected Sequence 8.2 (GET INPUT, Text attribute – Center Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.2.4.2, Expected Sequence 8.2.

### 27.22.4.3.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.2.

27.22.4.3.8.3 GET INPUT (Support of Text Attribute – Right Alignment)

27.22.4.3.8.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.3.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

## 27.22.4.3.8.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.3.4 Method of test

27.22.4.3.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.3.4.2 Procedure

## Expected Sequence 8.3 (GET INPUT, Text attribute – Right Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.3.4.2, Expected Sequence 8.3.

27.22.4.3.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.3.

27.22.4.3.8.4 GET INPUT (Support of Text Attribute – Large Font Size)

27.22.4.3.8.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.4.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

## 27.22.4.3.8.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.4.4 Method of test

27.22.4.3.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.4.4.2 Procedure

# Expected Sequence 8.4 (GET INPUT, Text attribute - Large Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.4.4.2, Expected Sequence 8.4.

27.22.4.3.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.4.

27.22.4.3.8.5 GET INPUT (Support of Text Attribute – Small Font Size)

27.22.4.3.8.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.5.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.5.4 Method of test

27.22.4.3.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.5.4.2 Procedure

### Expected Sequence 8.5 (GET INPUT, Text attribute – Small Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.5.4.2, Expected Sequence 8.5.

27.22.4.3.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.5.

27.22.4.3.8.6 GET INPUT (Support of Text Attribute – Bold On)

27.22.4.3.8.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.6.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.6.4 Method of test

27.22.4.3.8.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.6.4.2 Procedure

# Expected Sequence 8.6 (GET INPUT, Text attribute – Bold On)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.6.4.2, Expected Sequence 8.6.

27.22.4.3.8.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.6.

27.22.4.3.8.7 GET INPUT (Support of Text Attribute – Italic On)

27.22.4.3.8.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.7.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.7.4 Method of test

27.22.4.3.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.7.4.2 Procedure

Expected Sequence 8.7 (GET INPUT, Text attribute – Italic On)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.7.4.2, Expected Sequence 8.7.

27.22.4.3.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.7.

27.22.4.3.8.8 GET INPUT (Support of Text Attribute – Underline On)

27.22.4.3.8.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.8.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.8.4 Method of test

27.22.4.3.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.8.4.2 Procedure

# Expected Sequence 8.8 (GET INPUT, Text attribute – Underline On)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.8.4.2, Expected Sequence 8.8.

27.22.4.3.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.8.

27.22.4.3.8.9 GET INPUT (Support of Text Attribute – Strikethrough On)

27.22.4.3.8.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.9.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.9.4 Method of test

27.22.4.3.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.9.4.2 Procedure

# Expected Sequence 8.9 (GET INPUT, Text attribute – Strikethrough On)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.9.4.2, Expected Sequence 8.9.

27.22.4.3.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.9.

27.22.4.3.8.10 GET INPUT (Support of Text Attribute – Foreground and Background Colour)

27.22.4.3.8.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.10.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.10.3 Test purpose

To verify that the ME displays the text formatted according to the fore- and background colour text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.10.4 Method of test

27.22.4.3.8.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.10.4.2 Procedure

#### Expected Sequence 8.10 (GET INPUT, Text attribute – Foreground and Background Colour)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.10.4.2, Expected Sequence 8.10.

27.22.4.3.8.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.10.

27.22.4.3.9 GET INPUT (UCS2 display in Chinese)

27.22.4.3.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.9.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in the following technical specifications: ISO/IEC 10646 [17].

27.22.4.3.9.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.9.4 Method of test

27.22.4.3.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.9.4.2 Procedure

## Expected Sequence 9.1 (GET INPUT, text string coding in UCS2 - Chinese characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.9.4.2, Expected Sequence 9.1.

# Expected Sequence 9.2 (GET INPUT, max length for the text string coding in UCS2 - Chinese characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.9.4.2, Expected Sequence 9.2.

27.22.4.3.9.5 Test requirement

The ME shall operate in the manner defined in expected sequences 9.1 to 9.2

27.22.4.3.10 GET INPUT (UCS2 entry in Chinese)

27.22.4.3.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.10.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in ISO/IEC 10646 [17].

27.22.4.3.10.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.10.4 Method of test

27.22.4.3.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.10.4.2 Procedure

# Expected Sequence 10.1 (GET INPUT, character set from UCS2 alphabet - Chinese characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.10.4.2, Expected Sequence 10.1.

# Expected Sequence 10.2 (GET INPUT, character set from UCS2 alphabet - Chinese characters, Max length for the input, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.10.4.2, Expected Sequence 10.2.

27.22.4.3.10.5 Test requirement

The ME shall operate in the manner defined in expected sequences 10.1 to 10.2

27.22.4.3.11 GET INPUT (UCS2 display in Katakana)

27.22.4.3.11.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.11.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

27.22.4.3.11.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.11.4 Method of test

27.22.4.3.11.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.11.4.2 Procedure

# Expected Sequence 11.1 (GET INPUT, text string coding in UCS2 in Katakana, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.11.4.2, Expected Sequence 11.1.

# Expected Sequence 11.2 (GET INPUT, max length for the text string coding in UCS2 in Katakana, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.11.4.2, Expected Sequence 11.2.

27.22.4.3.11.5 Test requirement

The ME shall operate in the manner defined in expected sequences 11.1 to 11.2

27.22.4.3.12 GET INPUT (UCS2 entry in Katakana)

27.22.4.3.12.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.12.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in ISO/IEC 10646 [17].

27.22.4.3.12.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.12.4 Method of test

27.22.4.3.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.12.4.2 Procedure

Expected Sequence 12.1 (GET INPUT, character set from UCS2 alphabet in Katakana, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.12.4.2, Expected Sequence 12.1.

Expected Sequence 12.2 (GET INPUT, character set from UCS2 alphabet in Katakana, Max length for the input, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.3.12.4.2, Expected Sequence 12.2.

27.22.4.3.12.5 Test requirement

The ME shall operate in the manner defined in expected sequences 12.1 to 12.2.

27.22.4.4 MORE TIME

27.22.4.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.4.2 Conformance requirement

The ME shall support the MORE TIME command as defined in:

- TS 31.111 [15] clause 6.4.4, clause 6.6.4, clause 5.2, clause 8.6 and clause 8.7.

### 27.22.4.4.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the MORE TIME proactive UICC command.

#### 27.22.4.4.4 Method of test

#### 27.22.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.4.4.2 Procedure

# **Expected Sequence 1.1 (MORE TIME)**

See ETSI TS 102 384 [26] in subclause 27.22.4.4.4.2, Expected Sequence 1.1.

### 27.22.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

#### 27.22.4.5 PLAY TONE

## 27.22.4.5.1 PLAY TONE (Normal)

## 27.22.4.5.1.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.5.1.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.16 and clause 8.8.

### 27.22.4.5.1.3 Test purpose

To verify that the ME plays an audio tone of a type and duration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece whilst not in call and shall superimpose the tone on top of the downlink audio whilst in call.

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command.

#### 27.22.4.5.1.4 Method of test

## 27.22.4.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

# 27.22.4.5.1.4.2 Procedure

# Expected Sequence 1.1 (PLAY TONE)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
	ME . LUCC	PENDING: PLAY TONE 1.1.1	
2	ME → UICC	FETCH PROACTIVE COMMAND: PLAY	
٥	$UICC \to ME$	TONE 1.1.1	
4	$ME \rightarrow USER$	Display "Dial Tone"	
		Play a standard supervisory dial	
		tone through the external ringer for	
_		a duration of 5 s	
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY TONE 1.1.1	[Command performed successfully]
6	$UICC \to ME$	PROACTIVE UICC SESSION	
	OIOO / IVIL	ENDED	
7	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: PLAY TONE 1.1.2	
8	ME → UICC	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.1.2	
10	$ME \rightarrow USER$	Display "Sub. Busy"	
	WE 700ER	Play a standard supervisory called	
		subscriber busy tone for a duration	
		of 5 s	to
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
12	$UICC \to ME$	PROACTIVE UICC SESSION	
12	OIOO - IVIL	ENDED	
13	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: PLAY TONE 1.1.3	
14	ME → UICC	FETCH	
15	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.1.3	
16	$ME \to USER$	Display "Congestion"	
		Play a standard supervisory	
		congestion tone for a duration of 5	
17	ME LUCC	S TERMINAL RESPONSE: PLAY	[Command performed successfully]
''	$ME \rightarrow UICC$	TONE 1.1.3	[Confinant penomied successibility]
18	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
19	$UICC \to ME$	PROACTIVE COMMAND	
20	$MF \rightarrow UICC$	PENDING: PLAY TONE 1.1.4 FETCH	
21	$ME \to OICC$ $UICC \to ME$	PROACTIVE COMMAND: PLAY	
	JIJJ → IVIL	TONE 1.1.4	
22	$ME \to USER$	Display "RP Ack"	
		Play a standard supervisory radio	
22	ME LUCC	path acknowledgement tone TERMINAL RESPONSE: PLAY	[Command parformed augassafully]
23	$ME \rightarrow UICC$	TONE 1.1.4	[Command performed successfully]
24	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
25	$UICC \to ME$	PROACTIVE COMMAND	
26	ME LUCC	PENDING: PLAY TONE 1.1.5	
26 27	$ME \to UICC$ $UICC \to ME$	FETCH PROACTIVE COMMAND: PLAY	
<u> </u>	UICC → IVIE	TONE 1.1.5	
28	$ME \to USER$	Display "No RP"	
		Play a standard supervisory radio	
		path not available / call dropped	
29	$ME \to UICC$	tone for a duration of 5 s TERMINAL RESPONSE: PLAY	[Command performed successfully]
23	IVIE → UICC	TONE 1.1.5	[Command penomied successibily]
1		1	ı

Step	Direction	MESSAGE / Action	Comments
30	UICC → ME	PROACTIVE UICC SESSION	Comments
	OIOO / IVIL	ENDED	
31	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: PLAY TONE 1.1.6	
32	ME → UICC	FETCH	
33	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.1.6	
34	$ME \to USER$	Display "Spec Info"	
	WIL -> OOLK	Play a standard supervisory error /	
		special information tone for a	
		duration of 5 s	
35	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
36	$UICC \to ME$	TONE 1.1.6 PROACTIVE UICC SESSION	
30	OICC → IVIE	ENDED	
37	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: PLAY TONE 1.1.7	
38	$ME \rightarrow UICC$	FETCH	
39	$UICC \to ME$	PROACTIVE COMMAND: PLAY	
40	$ME \to USER$	TONE 1.1.7 Display "Call Wait"	
40	IVIE → USEK	Play a standard supervisory call	
		waiting tone for a duration of 5 s	
41	$ME \to UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
40		TONE 1.1.7	
42	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
43	$UICC \to ME$	PROACTIVE COMMAND	
10	0100 → IVIL	PENDING: PLAY TONE 1.1.8	
44	$ME \to UICC$	FETCH	
45	$UICC \to ME$	PROACTIVE COMMAND: PLAY	
40		TONE 1.1.8	
46	$ME \rightarrow USER$	Display "Ring Tone" Play a standard supervisory	
		ringing tone for duration of 5 s	
47	$ME \to UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
		TONE 1.1.8	
48	$UICC \to ME$	PROACTIVE UICC SESSION	
49	$USER \to ME$	ENDED Set up a voice call	User dials 123456789 to connect to the
43	USER → IVIE	Set up a voice can	network manually]
50	$ME \to USS$	Establish voice call	[Voice call is established]
51	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: PLAY TONE 1.1.1	
52	ME → UICC	FETCH	
53	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.1.1	
54	$ME \rightarrow USER$	Display "Dial Tone"	
0.	MIL 700ER	Superimpose the standard	
		supervisory dial tone on the audio	
		downlink for the duration of 5 s	
55	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
56	$UICC \to ME$	TONE 1.1.1 PROACTIVE UICC SESSION	
		ENDED	
57	$USER \to ME$	The user ends the call	
58	$UICC \to ME$	PROACTIVE COMMAND	
	ME !!!	PENDING: PLAY TONE 1.1.9	
59 60	ME → UICC	FETCH	
60	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.1.9	
İ	ı	1.5112 11.10	ı

Step	Direction	MESSAGE / Action	Comments
61	$ME \rightarrow USER$	Display "This command instructs	
		the ME to play an audio tone.	
		Upon receiving this command, the	
		ME shall check if it is currently in, or in the process of setting up	
		(SET-UP message sent to the	
		network, see GSM"04.08"(8)), a	
		speech call If the ME I"	
		Play a general beep	
62	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
		TONE 1.1.9a	Or [Command havend ME's canabilities]
		or TERMINAL RESPONSE: PLAY	[Command beyond ME's capabilities]
		TONE 1.1.9b	
63	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
64	$UICC \to ME$	PROACTIVE COMMAND	
0.5		PENDING: PLAY TONE 1.1.10	
65 66	ME → UICC	FETCH PROACTIVE COMMAND: PLAY	
00	$UICC \to ME$	TONE 1.1.10	
67	ME → USER	Display "Beep"	
		Play a ME proprietary general	
		beep	
68	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
		TONE 1.1.10a Or	or [Command beyond ME's capabilities]
		TERMINAL RESPONSE: PLAY	[Command beyond ME's capabilities]
		TONE 1.1.10b	
69	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
70	$UICC \to ME$	PROACTIVE COMMAND	
71	ME → UICC	PENDING: PLAY TONE 1.1.11 FETCH	
72	UICC → ME	PROACTIVE COMMAND: PLAY	
'-	OIOO / IVIL	TONE 1.1.11	
73	$ME \to USER$	Display "Positive"	
		Play a ME proprietary positive	
74	ME LUCC	acknowledgement tone TERMINAL RESPONSE: PLAY	[Command performed successfully]
'4	$ME \rightarrow UICC$	TONE 1.1.11a	or
		or	[Command beyond ME's capabilities]
		TERMINAL RESPONSE: PLAY	
		TONE 1.1.11b	
75	$UICC \to ME$	PROACTIVE UICC SESSION	
76	$UICC \to ME$	ENDED PROACTIVE COMMAND	
	O.OO 7 IVIL	PENDING: PLAY TONE 1.1.12	
77	$ME \to UICC$	FETCH	
78	$UICC \to ME$	PROACTIVE COMMAND: PLAY	
70	NE	TONE 1.1.12	
79	$ME \rightarrow USER$	Display "Negative" Play a ME proprietary negative	
1		acknowledgement tone	
80	$ME \to UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
		TONE 1.1.12a	or
1		or	[Command beyond ME's capabilities]
		TERMINAL RESPONSE: PLAY TONE 1.1.12b	
81	$UICC \to ME$	PROACTIVE UICC SESSION	
	JIOO → IVIL	ENDED	
82	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: PLAY TONE 1.1.13	
83	ME → UICC	FETCH	
84	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.1.13	
I	I	TIONE I.I.IS	ı

Step	Direction	MESSAGE / Action	Comments
85	$ME \to USER$	Display "Quick"	
		Play a ME proprietary general	
		beep	
86	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
		TONE 1.1.13a	or
		or	[Command beyond ME's capabilities]
		TERMINAL RESPONSE: PLAY	
07		TONE 1.1.13b	
87	$UICC \to ME$	PROACTIVE UICC SESSION	
0.0	LUCO ME	ENDED COMMAND	
88	$UICC \to ME$	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.14	
89	ME → UICC	FETCH	
90	$UICC \rightarrow ME$	PROACTIVE COMMAND: PLAY	
30		TONE 1.1.14	
91	ME → USER	Display " <abort>"</abort>	
0.	WE 7 OOLK	Play an ME Error / Special	
		information tone until user aborts	
		this command (the command shall	
		be aborted by the user within 1	
		minute)	
92	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Proactive UICC session terminated by the
		TONE 1.1.14	user]
93	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
94	$UICC \to ME$	PROACTIVE COMMAND	
0.5		PENDING: PLAY TONE 1.1.15	
95	ME → UICC	FETCH	
96	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.1.15	[No alpha identifier, no tone tag, no duration
97	ME → User	ME plays general beep, or if not	tag] [ME uses default duration defined by
97	IVIE → USEI	supported any (defined by ME-	ME-manufacturer]
		manufacturer) other supported	IVIE-IIIanulactuleij
		tone	
98	ME → UICC	TERMINAL RESPONSE: PLAY	[Command performed successfully], [ME uses
	WIE 70100	TONE 1.1.15	general beep, or if not supported any (defined
			by ME-manufacturer) other supported tone,
			uses default duration defined by
			ME-manufacturer]
99	$UICC \to ME$	PROACTIVE UICC SESSION	-
		ENDED	

For coding, see ETSI TS 102 384 [26] in subclause 27.22.4.5.1.4.2, Expected Sequence 1.1.

# 27.22.4.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

# 27.22.4.5.2 PLAY TONE (UCS2 display in Cyrillic)

# 27.22.4.5.2.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.5.2.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

27.22.4.5.2.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

27.22.4.5.2.4 Method of test

27.22.4.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.2.4.2 Procedure

#### Expected Sequence 2.1 (PLAY TONE, character set from UCS2 alphabet in Russian, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.2.4.2, Expected Sequence 2.1.

27.22.4.5.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

27.22.4.5.3 PLAY TONE (display of Icon)

27.22.4.5.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.3.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8 and clause 8.31.

27.22.4.5.3.3 Test purpose

To verify that the ME plays an audio tone of a type and duration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

To verify that the ME displays the icon contained in the PLAY TONE proactive UICC command.

27.22.4.5.3.4 Method of test

27.22.4.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.3.4.2 Procedure

# Expected Sequence 3.1A (PLAY TONE, Basic icon, self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.1A.

# Expected Sequence 3.1B (PLAY TONE, Basic icon, self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.1B.

#### Expected Sequence 3.2A (PLAY TONE, Basic icon, non self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.2A.

# Expected Sequence 3.2B (PLAY TONE, Basic icon, non self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.2B.

#### Expected Sequence 3.3A (PLAY TONE, Colour icon, self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.3A.

# Expected Sequence 3.3B (PLAY TONE, Colour icon, self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.3B.

#### Expected Sequence 3.4A (PLAY TONE, Colour icon, non self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.4A.

# Expected Sequence 3.4B (PLAY TONE, Colour icon, non self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.4B.

# 27.22.4.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.4B.

### 27.22.4.5.4 PLAY TONE (Support of Text Attribute)

#### 27.22.4.5.4.1 PLAY TONE (Support of Text Attribute – Left Alignment)

#### 27.22.4.5.4.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.5.4.1.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.1.4 Method of test

27.22.4.5.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.5.4.1.4.2 Procedure

#### Expected Sequence 4.1 (PLAY TONE, Text Attribute – Left Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.1.4.2, Expected Sequence 4.1.

#### 27.22.4.5.4.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.1.

27.22.4.5.4.2 PLAY TONE (Support of Text Attribute – Center Alignment)

#### 27.22.4.5.4.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.4.2.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

### 27.22.4.5.4.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.5.4.2.4 Method of test

#### 27.22.4.5.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

# 27.22.4.5.4.2.4.2 Procedure

#### Expected Sequence 4.2 (PLAY TONE, Text Attribute – Centre Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.2.4.2, Expected Sequence 4.2.

#### 27.22.4.5.4.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.2.

27.22.4.5.4.3 PLAY TONE (Support of Text Attribute – Right Alignment)

27.22.4.5.4.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.4.3.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.3.4 Method of test

27.22.4.5.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.5.4.3.4.2 Procedure

#### Expected Sequence 4.3 (PLAY TONE, Text Attribute – Right Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.3.4.2, Expected Sequence 4.3.

#### 27.22.4.5.4.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.3.

27.22.4.5.4.4 PLAY TONE (Support of Text Attribute – Large Font Size)

27.22.4.5.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.4.4.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.4.4 Method of test

27.22.4.5.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.5.4.4.4.2 Procedure

#### Expected Sequence 4.4 (PLAY TONE, Text Attribute – Large Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.4.2, Expected Sequence 4.4.

#### 27.22.4.5.4.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.4.

#### 27.22.4.5.4.5 PLAY TONE (Support of Text Attribute – Small Font Size)

#### 27.22.4.5.4.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.4.5.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

### 27.22.4.5.4.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

# 27.22.4.5.4.5.4 Method of test

#### 27.22.4.5.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

# 27.22.4.5.4.5.4.2 Procedure

#### Expected Sequence 4.5 (PLAY TONE, Text Attribute – Small Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.2, Expected Sequence 4.5.

#### 27.22.4.5.4.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.5.

27.22.4.5.4.6 PLAY TONE (Support of Text Attribute – Bold On)

27.22.4.5.4.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.6.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.6.4 Method of test

27.22.4.5.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.6.4.2 Procedure

#### Expected Sequence 4.6 (PLAY TONE, Text Attribute – Bold On)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.6.4.2, Expected Sequence 4.6.

27.22.4.5.4.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.6.

27.22.4.5.4.7 PLAY TONE (Support of Text Attribute – Italic On)

27.22.4.5.4.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.7.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.7.4 Method of test

27.22.4.5.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.7.4.2 Procedure

#### Expected Sequence 4.7 (PLAY TONE, Text Attribute – Italic On)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.7.4.2, Expected Sequence 4.7.

27.22.4.5.4.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.7.

27.22.4.5.4.8 PLAY TONE (Support of Text Attribute – Underline On)

27.22.4.5.4.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.8.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.8.4 Method of test

27.22.4.5.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.8.4.2 Procedure

#### Expected Sequence 4.8 (PLAY TONE, Text Attribute – Underline On)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.8.4.2, Expected Sequence 4.8.

27.22.4.5.4.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.8.

27.22.4.5.4.9 PLAY TONE (Support of Text Attribute – Strikethrough On)

27.22.4.5.4.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.9.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.9.4 Method of test

27.22.4.5.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.5.4.9.4.2 Procedure

#### Expected Sequence 4.9 (PLAY TONE, Text Attribute – Strikethrough On)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.9.4.2, Expected Sequence 4.9.

#### 27.22.4.5.4.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.9.

27.22.4.5.4.10 PLAY TONE (Support of Text Attribute – Foreground and Background Colour)

27.22.4.5.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.4.10.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.10.4 Method of test

27.22.4.5.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.10.4.2 Procedure

# Expected Sequence 4.10 (PLAY TONE, Text Attribute – Foreground and Background Colour)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.10.4.2, Expected Sequence 4.10.

27.22.4.5.4.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.10.

27.22.4.5.5 PLAY TONE (UCS2 display in Chinese)

27.22.4.5.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.5.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

27.22.4.5.5.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

27.22.4.5.5.4 Method of test

27.22.4.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.5.4.2 Procedure

### Expected Sequence 5.1 (PLAY TONE, character set from UCS2 alphabet in Chinese, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.5.4.2, Expected Sequence 5.1.

27.22.4.5.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

27.22.4.5.6 PLAY TONE (UCS2 display in Katakana)

27.22.4.5.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.6.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

27.22.4.5.6.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

27.22.4.5.6.4 Method of test

27.22.4.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.6.4.2 Procedure

#### Expected Sequence 6.1 (PLAY TONE, with UCS2 in Katakana, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.5.6.4.2, Expected Sequence 6.1.

27.22.4.5.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

27.22.4.6 POLL INTERVAL

27.22.4.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.6.2 Conformance requirement

The ME shall support the POLL INTERVAL command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.6, clause 6.6.6, clause 5.2, clause 8.6, clause 8.7 and clause 8.8.

# 27.22.4.6.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the POLL INTERVAL proactive UICC command.

To verify that the ME gives a valid response to the polling interval requested by the UICC.

To verify that the ME sends STATUS commands to the UICC at an interval no longer than the interval negotiated by the UICC.

#### 27.22.4.6.4 Method of test

#### 27.22.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.6.4.2 Procedure

See ETSI TS 102 384 [26] in subclause 27.22.4.6.4.2, Expected Sequence 1.1.

Note: If the requested poll interval is not supported by the ME, the ME is allowed to use a different one as stated in TS 31.111 [15], subclause 6.4.6.

#### 27.22.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

#### 27.22.4.7 REFRESH

# 27.22.4.7.1 REFRESH (normal)

# 27.22.4.7.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.7.1.2 Conformance requirement

The ME shall support the REFRESH command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.7, clause 6.6.13, clause 5.2, clause 8.6, clause 8.7 and clause 8.18.

Consequently the ME shall support the USIM Initialization procedure as defined in:

- TS 31.102 [14] clause 5.1.1.2 and ETSI TS 102 221[13] clause 11.1.2

#### 27.22.4.7.1.3 Test purpose

To verify that the ME performs the Proactive Command – REFRESH in accordance with the Command Qualifier. This shall require the ME to perform:

- the UICC and USIM initialization,
- a re-read of the contents and structure of the EFs on the UICC that have been notified as changed and are either part of initialization or used during the test,
- a restart of the card session,
- a successfull return of the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.7.1.4 Method of test

#### 27.22.4.7.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table..

The elementary files are coded as Toolkit default except for expected sequence 1.3.

For expected sequence 1.3 the global phonebook shall be present.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

These values might be overwritten with values defined in the expected sequences itself.

Prior to the execution of expected sequence 1.2 the FDN service shall be enabled.

#### 27.22.4.7.1.4.2 Procedure

#### **Expected Sequence 1.1 (REFRESH, USIM Initialization)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC\!\!\to\!ME$	PROACTIVE COMMAND	[To inform the ME that FDN becomes
		PENDING: REFRESH 1.1.1	enabled]
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		REFRESH 1.1.1	
4	UICC	EF EST contents states FDN	[New EF EST value: 01]
		enabled	
5	$ME \rightarrow UICC$	USIM Initialization including send	[ME performs USIM initialization in
		STATUS[P1='01']	accordance with TS 31.111 [15] clause 6.4.7]
6	ME → UICC	TERMINAL RESPONSE: REFRESH 1.1.1A	[normal ending]
		Or	
		TERMINAL RESPONSE:	[additional EFs read]
		REFRESH 1.1.1B	[additional El 3 lead]
7	$UICC \rightarrow MF$	PROACTIVE UICC SESSION	
	0.00 /	ENDED	
8	$USER \to ME$	Call setup to "321"	
9	$ME \rightarrow USER$	Call set up not allowed	
10	$USER \to ME$	Call setup to "123"	
11	$ME \to USS$	Setup	Called party BCD number shall be "123"

# PROACTIVE COMMAND: REFRESH 1.1.1

#### Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization

Device identities

Source device: UICC Destination device: ME

### Coding:

BER-TLV:	D0	09	81	03	01	01	03	82	02	81	82	

TERMINAL RESPONSE: REFRESH 1.1.1A

Logically:

Command details

Command number: 1

Command type: REFRESH
Command qualifier: USIM Initialization

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	00
D = 1 \ 1 = \ 1		00			00		~_				<b>.</b>	

TERMINAL RESPONSE: REFRESH 1.1.1B

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization

Device identities

Source device: ME
Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	03	

# **Expected Sequence 1.2 (REFRESH, File Change Notification)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	[To inform the ME that EF FDN will be in an
		PENDING: REFRESH 1.2.1	updated state, FDN service already enabled]
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: REFRESH 1.2.1	
4	UICC	Update EF FDN RECORD 1	[EF FDN record 1 updated to contain the dialling string "0123456789"]
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: REFRESH 1.2.1A Or	[normal ending]
		TERMINAL RESPONSE: REFRESH 1.2.1B	[additional EFs read]
6	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
7	$USER \to ME$	Call setup to "123"	
8	$ME \to USER$	Call set up not allowed	
9	$USER \to ME$	Call setup to "0123456789"	
10	$ME \to USS$	Setup	Called party BCD number shall be "0123456789"

PROACTIVE COMMAND: REFRESH 1.2.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: File Change Notification

Device identities

Source device: UICC
Destination device: ME
File List: EF FDN

Coding:

BER-TLV:	D0	12	81	03	01	01	01	82	02	81	82	92
	07	01	3F	00	7F	FF	6F	3B				

#### TERMINAL RESPONSE: REFRESH 1.2.1A

Logically:

Command details

Command number:

Command type: REFRESH

Command qualifier: File Change Notification

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	01	82	02	82	81	83	01	00

#### TERMINAL RESPONSE: REFRESH 1.2.1B

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: File Change Notification

Device identities

Source device: ME
Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

BER-TLV:	81	03	01	01	01	82	02	82	81	83	01	03

# **Expected Sequence 1.3 (REFRESH, USIM Initialization and File Change Notification)**

	Step	Direction	MESSAGE / Action	Comments
	1	$UICC \to$	PROACTIVE COMMAND	
		ME	PENDING: REFRESH 1.3.1	
	2	/	FETCH	
		UICC		
	3	$UICC \to$	PROACTIVE COMMAND:	
		ME	REFRESH 1.3.1	
	4	UICC	Update EF ADN in the global	[EF ADN entry 1 of the global phonebook to
			phonebook	contain the the new and previously unused
	_	NAT.	LICIM Initialization in alcoling	alpha identifier "Changed"
	5	$ME \to UICC$	USIM Initialization including sending STATUS [P1='01']	[ME performs USIM initialization in accordance with TS 31.111 [15] clause 6.4.7]
	6	ME →	TERMINAL RESPONSE:	[normal ending]
	0	UICC	REFRESH 1.3.1A	[Hornial ending]
		OICC	Or	
			TERMINAL RESPONSE:	[additional EFs read]
			REFRESH 1.3.1B	[
	7	$UICC \to$	PROACTIVE UICC SESSION	
		ME	ENDED	
	8	$USER \to$	Use an MMI dependent procedure	[To ensure that EF ADN in the global
		ME		
				Refresh command]
F	_	NAT.		
	9			
		USER		
		$\begin{array}{c} \text{ME} \\ \text{USER} \rightarrow \end{array}$	ENDED	[To ensure that EF ADN in the global phonebook has been read after issuing the Refresh command]

#### PROACTIVE COMMAND: REFRESH 1.3.1

# Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization and File Change Notification

Device identities

Source device: UICC Destination device: ME

File List: ADN in the global phonebook

# Coding:

BER-TLV:	D0	12	81	03	01	01	02	82	02	81	82	92
	Note 1											

Note 1: Length and data of the file list TLV depend on the card configuration used in this test. The global phonebook shall be used. The number of changed files shall be set to '01'.

#### TERMINAL RESPONSE: REFRESH 1.3.1A

#### Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization and File Change Notification

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	02	82	02	82	81	83	01	00
DLIX-ILV.	01	03	U I	Οī	02	02	02	02	01	೦೦	Οī	00

TERMINAL RESPONSE: REFRESH 1.3.1B

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization and File Change Notification

Device identities

Source device: ME
Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

ER-TLV	81	03	01	01	02	82	02	82	81	83	01	03	
--------	----	----	----	----	----	----	----	----	----	----	----	----	--

# **Expected Sequence 1.4 (REFRESH, USIM Initialization and Full File Change Notification)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: REFRESH 1.4.1	
2	11.12	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		REFRESH 1.4.1	
4	UICC	EF EST contents states FDN	[New EF EST value: 01]
_	11100	enabled	IEE EDN
5	UICC	Update EF FDN	[EF FDN record 1 updated to contain the
6	ME LUCC	LICIM Initialization including and	dialling string "0123456789"] [ME performs USIM initialization in
0	ME → UICC	USIM Initialization including send   STATUS[P1='01']	accordance with TS 31.111 [15] clause 6.4.7]
7	ME VIICC	TERMINAL RESPONSE:	[normal ending]
,	WL → OICC	REFRESH 1.4.1A	[Horrial Graing]
		Or	
		TERMINAL RESPONSE:	[additional EFs read]
		REFRESH 1.4.1B	-
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	Call setup to "321"	
10	$ME \to USER$	Call set up not allowed	
11	$USER \to ME$	Call setup to "0123456789"	
12	$ME \to USS$	Setup	Called party BCD number shall be
1			"0123456789"

PROACTIVE COMMAND: REFRESH 1.4.1

Logically:

Command details

Command number:

Command type: REFRESH

Command qualifier: USIM Initialization and Full File Change Notification

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	00	82	02	81	82

TERMINAL RESPONSE: REFRESH 1.4.1A

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization and Full file Change Notification

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	00	82	02	82	81	83	01	00
D	<b>.</b>	00			00						<b>.</b>	

TERMINAL RESPONSE: REFRESH 1.4.1B

Logically:

Command details

Command number:

Command type: REFRESH

Command qualifier: USIM Initialization and full File change Notification

Device identities

Source device: ME
Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

BER-TLV:	81	03	01	01	00	82	02	82	81	83	01	03
----------	----	----	----	----	----	----	----	----	----	----	----	----

# **Expected Sequence 1.5 (REFRESH, UICC Reset)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC { ightarrow} ME$	PROACTIVE COMMAND	
		PENDING: REFRESH 1.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		REFRESH 1.5.1	
4	$ME \rightarrow UICC$	STATUS[P1='02']	ME indicates to USIM that the termination
			procedure is starting
5	$ME \rightarrow UICC$	ME resets the UICC, performs	
		USIM initialisation, including send	
		STATUS[P1='01'] and	
		no TERMINAL RESPONSE shall	
		be sent	

PROACTIVE COMMAND: REFRESH 1.5.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: UICC Reset

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	04	82	02	81	82	

# Expected Sequence 1.6 (REFRESH, USIM Initialization after SMS-PP data download)

Step	Direction	MESSAGE / Action	Comments
1	ME	The ME shall be in its normal idle	[Start a sequence to verify that the ME returns
		mode	the RP-ACK message back to the USS, if the
2	LICC - ME	CMC DD Data Dawnland Massage	UICC responds with '90 00']
	$USS \to ME$	SMS-PP Data Download Message 1.6.1	
3	MF → LISER	The ME shall not display the	
	WIE 700ER	message or alert the user of a	
		short message waiting	
4	$ME \to UICC$	ENVELOPE: SMS-PP	
		DOWNLOAD 1.6.1	
5	$UICC \to ME$	SW1/SW2 of '90 00'	
6	$ME \to USS$	RP-ACK	
7	$UICC \to ME$	PROACTIVE COMMAND	
	ME IIIOO	PENDING: REFRESH 1.1.1 FETCH	
8 9	/ 0.00	PROACTIVE COMMAND:	
9	UICC → IVIE	REFRESH 1.1.1	
10	UICC	EF EST contents states FDN	[New EF EST value: 01]
	0.00	enabled	[From Er 201 randoron]
11	$ME \to UICC$	USIM Initialization including send	[ME performs USIM initialization in
		STATUS[P1='01']	accordance with TS 31.111 [15] clause 6.4.7]
12	$ME \rightarrow UICC$	TERMINAL RESPONSE:	[normal ending]
		REFRESH 1.1.1A	
		Or TERMINAL RESPONSE:	[additional FFa road]
		REFRESH 1.1.1B	[additional EFs read]
13	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
14	$USER \to ME$	Call setup to "321"	
15	$ME \to USER$	•	
16	$USER \to ME$	Call setup to "123"	
17	$ME \to USS$	Setup	Called party BCD number shall be "123"

# SMS-PP (Data Download) Message 1.6.1

Compression

# Logically:

SMS TPDU	
TP-MTI	SMS-DELIVER
TP-MMS	No more messages waiting for the MS in this SC
TP-RP	TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI	TP-UD field contains only the short message
TP-SRI	A status report will not be returned to the SME
TP-OA	•
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"1234"
TP-PID	(U)SIM Data download
TP-DCS	
Coding Group	General Data Coding

Text is uncompressed

Message Class Class 2 (U)SIM Specific Message

Alphabet 8 bit data

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 13

TP-UD "Short Message"

Coding:

Coding	04	04	91	21	43	7F	16	89	10	10	00	00
	00	00	0D	53	68	6F	72	74	20	4D	65	73
	73	61	67	65								

**ENVELOPE: SMS-PP DOWNLOAD 1.6.1** 

Logically:

SMS-PP Download

Device identities

Source device: Network
Destination device: UICC

Address

TON International number

NPI "ISDN / telephone numbering plan"
Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC

TP-RPTP-Reply-Path is not set in this SMS-DELIVER

TP-UDHI TP-UD field contains only the short message TP-SRI A status report will not be returned to the SME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "1234"

TP-PID (U)SIM Data download

TP-DCS

Coding Group General Data Coding Compression Text is uncompressed

Message Class Class 2 (U)SIM Specific Message

Alphabet 8 bit data

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 13

TP-UD "Short Message"

Coding:

BER-TLV:	D1	2D	82	02	83	81	06	09	91	11	22	33
	44	55	66	77	F8	8B	1C	04	04	91	21	43
	7F	16	89	10	10	00	00	00	00	0D	53	68
	6F	72	74	20	4D	65	73	73	61	67	65	

# **Expected Sequence 1.7 (REFRESH, USIM Application Reset)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC\!\!\to\!ME$	PROACTIVE COMMAND	[To inform the ME that FDN becomes
		PENDING: REFRESH 1.7.1	enabled]
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	No UICC reset shall be performed between
		REFRESH 1.7.1	steps 3 and 9.
4	$ME \rightarrow UICC$	STATUS[P1='02']	ME indicates to USIM that the termination
			procedure is starting
5	$ME \rightarrow UICC$	Select AID=USIM	Application termination
_		(P2='44') OR (P2='4C')	
6	UICC	EF EST contents states FDN	[New EF EST value: 01]
_		enabled	
7	$ME \rightarrow UICC$	USIM Initialization, including send	[ME performs USIM initialization]
	ME 11100	STATUS[P1='01']	for a more all a conditional
8	ME → UICC	TERMINAL RESPONSE:	[normal ending]
9	LUCC ME	REFRESH 1.7.1 PROACTIVE UICC SESSION	
9	OICC → IVIE	ENDED	
10	LICED VME	Call setup to "321"	
11		Call set up not allowed	
12		Call setup to "123"	
13		Setup	Called party BCD number shall be "123"
14		The ME receives the CONNECT	Called party BCD fluffiber shall be 123
14	$USS \to ME$	message from the USS.	
15	LICED VME	The user ends the call after a few	
13	USER → IVIE	seconds.	
		Jacobilua.	

# PROACTIVE COMMAND: REFRESH 1.7.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Application Reset

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	05	82	02	81	82	

# TERMINAL RESPONSE: REFRESH 1.7.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Application Reset

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

	1											
BER-TLV:	81	03	01	01	05	82	02	82	81	83	01	00

#### 27.22.4.7.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.7.

# 27.22.4.7.2 REFRESH (IMSI changing procedure)

#### 27.22.4.7.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.7.2.2 Conformance requirement

The ME shall support the REFRESH command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.7, clause 6.4.7.1, clause 6, clause 6.6.13, clause 5.2, clause 8.6, clause 8.7 and clause 8.18.

Additionally the ME shall support the USIM Initialization and USIM application closure procedure as defined in:

- TS 31.102 [14] clause 5.1.2 and Annex I.

### 27.22.4.7.2.3 Test purpose

To verify that the ME performs the Proactive Command – REFRESH in accordance with the Command Qualifier and the IMSI changing procedure. This may require the ME to perform:

- the USIM initialization
- a re-read of the contents and structure of the IMSI on the USIM
- a restart of the card session
- a successful return of the result of the execution of the command in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.7.2.4 Method of test

#### 27.22.4.7.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table..

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ATT flag broadcast in the SYSTEM INFORMATION BLOCK TYPE 1 on the BCCH is set to "UEs shall apply IMSI attach and detach procedure" for Expected Sequences 2.2.

#### 27.22.4.7.2.4.2 Procedure

#### Expected Sequence 2.1 (REFRESH, UICC Reset for IMSI Changing procedure)

**TBD** 

# Expected Sequence 2.2 (REFRESH, USIM Application Reset for IMSI Changing procedure)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \rightarrow ME$	PROACTIVE COMMAND	[To inform the ME that IMSI has changed]
_		PENDING: REFRESH 2.2.1	
2	, 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
4	ME	REFRESH 2.2.1	NAT in diseases to LICINA the at the atomic ation
4	$ME \rightarrow UICC$	STATUS[P1='02']	ME indicates to USIM that the termination procedure is starting
5	ME → UICC		Application termination
6	ME→USS	IMSI DETACH INDICATION	Indicates IMSI detach and/or GPRS detach,
	III_ 7 000	and/or DETACH REQUEST	depending on if the ME is CS and/or PS
			registered according to its capabilities
7	UICC	Update EF IMSI and EF LOCI	[Update the content of EF IMSI to
			"001010123456786", Temporary Mobile
			Subscriber Identity (TMSI) in EF LOCI be set
			to "FF FF FF FF"]
8	$ME \rightarrow UICC$	SELECT AID=USIM	Application selection
9	ME VIICC	(P2='0x') USIM Initialization, including send	[ME performs USIM initialization]
3	INIE → OICC	STATUS[P1='01']	[INE Periorins OSIW Initialization]
10	ME → UICC	TERMINAL RESPONSE:	[normal ending]
	, 0.00	REFRESH 2.2.1	31
11	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
12	$ME \rightarrow USS$	LOCATION UPDATING	The ME will again register in CS and/or PS
		REQUEST and/or ATTACH	depending on its capabilities
13	LIGO ME	REQUEST LOCATION UPDATING ACCEPT	
13	$USS \to ME$	and/or ATTACH ACCEPT	
14	ME → USS	TMSI REALLOCATION	
'-	IVIL -> USS	COMPLETE and/or ATTACH	
		COMPLETE	

#### PROACTIVE COMMAND: REFRESH 2.2.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Application Reset

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	05	82	02	81	82

# TERMINAL RESPONSE: REFRESH 2.2.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Application Reset

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

ER-TLV: 81 03 01	01 05 82	02 82	81 83 01	00
------------------	----------	-------	----------	----

# Expected Sequence 2.3 (REFRESH, 3G Session Reset for IMSI Changing procedure)

**TBD** 

# Expected Sequence 2.4 (REFRESH, reject 3G Session Reset for IMSI Changing procedure during call)

Step	Direction	MESSAGE / Action	Comments
1	$USER \to ME$	MO Call setup	
2	$ME \to USS$	Call established and maintained	
3	$UICC \to ME$	PROACTIVE COMMAND PENDING: REFRESH 2.4.1	
4	$ME \rightarrow UICC$	FETCH	
5	$UICC \to ME$	PROACTIVE COMMAND:	
		REFRESH 2.4.1	
6	$ME \rightarrow UICC$		ME rejects REFRESH proactive command
		REFRESH 2.4.1A	
		Or	
		TERMINAL RESPONSE:	
		REFRESH 2.4.1B	
7	$UICC \to ME$	PROACTIVE UICC SESSION	Note: EF IMSI and EF LOCI are not updated
		ENDED	by the UICC, see TS 31.111[15], cl. 6.4.7.1
8	$USER \to ME$	The MO call is terminated	

# PROACTIVE COMMAND: REFRESH 2.4.1

# Logically:

Command details

Command number: 1

Command type: REFRESH
Command qualifier: 3G Session Reset

Device identities

Source device: UICC Destination device: ME

File list

Number of files: 2
File: EF IMSI
File: EF LOCI

Coding:

BER-I	LV:	D0	18	81	03	01	01	06	82	02	81	82	92
		0D	02	3F	00	7F	FF	6F	07	3F	00	7F	FF
		6F	7E										

TERMINAL RESPONSE: REFRESH 2.4.1A

Logically:

Command details

Command number: 1

Command type: REFRESH
Command qualifier: 3G Session Reset

Device identities

Source device: ME

Destination device: UICC

Result

General Result: ME currently unable to process command Additional information on result: ME currently busy on call

Coding:

BER-TLV:	81	03	01	01	06	82	02	82	81	83	02	20
	02											

TERMINAL RESPONSE: REFRESH 2.4.1B

Logically:

Command details

Command number: 1

Command type: REFRESH
Command qualifier: 3G Session Reset

Device identities

Source device: ME
Destination device: UICC

Result

General Result: ME currently unable to process command

Additional information on result: Screen is busy

Coding:

BER-TLV:	81	03	01	01	06	82	02	82	81	83	02	20
	01											

27.22.4.7.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

27.22.4.7.3 REFRESH (Steering of roaming)

27.22.4.7.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.7.3.2 Conformance requirement

The ME shall support the REFRESH command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.47, clause 6.6.13, clause 5.2, clause 8.2, 8.6, clause 8.7 and clause 8.90.

Consequently the Rel-7 or later ME shall support the steering of roaming procedure as defined in:

- TS 23.122 [29] clause 4.4.6.

27.22.4.7.3.3 Test purpose

To verify that the ME performs the Proactive Command – REFRESH in accordance with the Command Qualifier. This shall require the ME to perform:

- the steering of roaming procedure,

a successfull return of the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

27.22.4.7.3.4 Method of test

27.22.4.7.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and connected to the USS/SS.

The elementary files are coded as Toolkit default with the following exception:

# 27.22.4.7.4 EF<sub>FPLMN</sub>

Logica	lly:	PLMN2 PLMN2 PLMN2 PLMN2 PLMN3	2: 25 3: 25 4: 23 5: 23	64 002 (M 64 003 64 004 64 004 64 005 64 006	ICC MN	C)						
Coding: Hex	B1 52	B2 24	B3 00	B4 52	B5 34	B6 00	B7 52	B8 44	B9 00	B10 32	B11 44	B12 00
	B13 32	B14 54	B15 00	B16 32	B17 64	B18 00						
EF <sub>OPLMNwA</sub>	СТ											

Logica	ally:	1st PLMN 1st ACT: 2nd PLMN 2nd ACT: 3rd PLMN 3rd ACT: 4th PLMN 4th ACT: 5th PLMN 6th ACT: 6th PLMN 6th ACT: 7th PLMN 7th ACT: 8th PLMN 8th ACT:	UTRA GSM : 274 00 UTRA : 274 00 UTRA : 274 00 UTRA : 274 00 UTRA : 274 00 UTRA	01 02 AN 03 AN 04 AN 05 AN 06 AN	ANC)					
Coding:	B01	B02	B03	B04	B05	B06	B07	B08	B09	B10
Hex	52	14	00	80	00	52	14	00	00	80
	B11	B12	B13	B14	B15	B16	B17	B18	B19	B20
	72	24	00	80	00	72	34	00	80	00
	B21	B22	B23	B24	B25	B26	B27	B28	B29	B30
	72	44	00	80	00	72	54	00	80	00
	B31	B32	B33	B34	B35	B36	B37	B38	B39	B40
	72	64	00	80	00	72	74	00	80	00

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

# 27.22.4.7.3.4.2 Procedure

# **Expected Sequence 3.1 (REFRESH, Steering of roaming, UTRAN)**

Step	Direction	MESSAGE / Action	Comments
1	USS	The first UMTS USS transmits on BCCH, with	
		the following network parameters:	
		- Attach/detach: disabled.	
		- LAI (MCC/MNC/LAC): 254/001/0001. - Access control: unrestricted.	
		- Access control: unrestricted. The second UMTS USS transmits on BCCH,	
		with the following network parameters:	
		- Attach/detach: disabled.	
		- LAI (MCC/MNC/LAC): 254/002/0001.	
		- Access control: unrestricted.	
2	$ME \rightarrow USS$	The ME registers to the first USS.	
3	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		REFRESH 3.1.1	
4	$ME \rightarrow UICC$	FETCH	
5	$UICC \to ME$	PROACTIVE COMMAND: REFRESH 3.1.1	
6a	UICC	Update of EF OPLMNwACT	[First entry: PLMN= 254/003, ACT=UTRAN, second entry: PLMN 254/004, ACT=GERAN]
6b	$ME \rightarrow UICC$	Update of EF FPLMN	[Deletion of the entries with PLMN 254/003 and PLMN 254/004]
6c	ME	Update of ME's internal memory	[Not explicitly verified: Deletion of the FPLMN entries with PLMN 254/003 and PLMN 254/004]
7	$ME \rightarrow USS$	The ME does not register to another USS than the currently selected.	20 1/000 0110 1 211111 20 1/00 1
8	ME → UICC	TERMINAL RESPONSE: REFRESH 3.1.1	[Unable to process command]
9	$UICC \rightarrow ME$	PROACTIVE UICC SESSION ENDED	
10		Wait approx. 60 seconds	[The ME does not register to another USS than the currently selected.]
11	$UICC \to ME$	PROACTIVE COMMAND PENDING: REFRESH 3.1.2	
12	$ME \rightarrow UICC$	FETCH	
13	$UICC \to ME$	PROACTIVE COMMAND: REFRESH 3.1.2	
14a	UICC	Update of EF OPLMNwACT	[First entry: PLMN= 254/002, ACT=UTRAN,GERAN, second entry: PLMN 254/001, ACT=UTRAN,GERAN]
14b	$ME \rightarrow UICC$	Update of EF FPLMN	[Deletion of the entry with PLMN 254/002]
14c	ME	Update of ME's internal memory	[Not explicitly verified: Deletion of the FPLMN entry with PLMN 254/002]
15	$ME \rightarrow USS$	The ME registers to the second USS.	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: REFRESH 3.1.2	[normal ending]
17	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
18	$UICC \to ME$	PROACTIVE COMMAND PENDING: REFRESH 3.1.3	
19	$ME \rightarrow UICC$	FETCH	
20	$UICC \rightarrow ME$	PROACTIVE COMMAND: REFRESH 3.1.3	
21a	UICC	Update of EF OPLMNwACT	[First entry: PLMN= 254/003, ACT=UTRAN,GERAN, second entry: PLMN 254/001, ACT=UTRAN,GERAN]
21b	UICC	EF FPLMN	[PLMN entries 254/003 and PLMN 254/001 not existent in EF FPLMN]
21c	ME	ME's internal memory	[Not explicitly verified: PLMN entries 254/003 and PLMN 254/001 not existent in FPLMN list]
22	$ME \rightarrow USS$	The ME registers to the first USS.	
23	$ME \rightarrow UICC$	TERMINAL RESPONSE: REFRESH 3.1.2	[normal ending]

24 UICC → ME PROACTIVE UICC SESSION ENDED
---

#### PROACTIVE COMMAND: REFRESH 3.1.1

Logically:

Command details

Command number: 1

Command type: REFRESH
Command qualifier: Steering of roaming

Device identities

Source device: UICC Destination device: ME

PLMNwACT List

 1stPLMN:
 254/003

 1stACT:
 UTRAN

 2stPLMN:
 254/004

 2stACT:
 GERAN

Coding:

BER-TLV:	D0	15	81	03	01	01	07	82	02	81	82	72
	0A	52	34	00	80	00	52	44	00	00	80	

#### TERMINAL RESPONSE: REFRESH 3.1.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: Steering of roaming

Device identities

Source device: ME
Destination device: UICC

Result

General Result: ME unable to process command

Coding:

IBER-TLV	1 0 1	03	01	01	07	82	02	82	81	83	01	20

# PROACTIVE COMMAND: REFRESH 3.1.2

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: Steering of roaming

Device identities

Source device: UICC Destination device: ME

PLMNwACT List

1stPLMN: 254/002

1stACT: UTRAN/GERAN

2stPLMN: 254/001

2stACT: UTRAN/GERAN

Coding:

BER-TLV:	D0	15	81	03	01	01	07	82	02	81	82	72
	0A	52	24	00	80	80	52	14	00	80	80	

TERMINAL RESPONSE: REFRESH 3.1.2

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: Steering of roaming

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	07	82	02	82	81	83	01	00
D	<b>.</b>	00			, o.		~_				<b>.</b>	00

PROACTIVE COMMAND: REFRESH 3.1.3

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: Steering of roaming

Device identities

Source device: UICC Destination device: ME

PLMNwACT List

1stPLMN: 254/003

1stACT: UTRAN/GERAN

2stPLMN: 254/001

2stACT: UTRAN/GERAN

Coding:

BER-TLV:	D0	15	81	03	01	01	07	82	02	81	82	72	
·	0A	52	34	00	80	80	52	14	00	80	80		

# Expected Sequence 3.2 (REFRESH, Steering of roaming, InterRAT)

Step	Direction	MESSAGE / Action	Comments
1	USS	The UMTS USS transmits on BCCH, with the	
		following network parameters:	
		- Attach/detach: disabled.	
		- LAI (MCC/MNC/LAC): 254/001/0001.	
		- Access control: unrestricted.	
		The GSM SS transmits on BCCH, with the	
		following network parameters:	
		- Attach/detach: disabled. - LAI (MCC/MNC/LAC): 254/002/0001.	
		- LAI (MCC/MNC/LAC): 254/002/0001. - Access control: unrestricted.	
2	$ME \rightarrow USS$	The ME registers to the UMTS USS and	
	IVIE → USS	achieves updated idle mode.	
3	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
	OICC → IVIE	REFRESH 3.2.1	
4	$ME \rightarrow UICC$	FETCH	
5	UICC → ME	PROACTIVE COMMAND: REFRESH 3.2.1	
6a	UICC	Update of EF OPLMNwACT	[First entry: PLMN= 254/002,
ou	0.00	opadio of El Of Elimination	ACT= GERAN, second entry:
			PLMN 254/001, ACT=UTRAN]
6b	$ME \rightarrow UICC$	Update of EF FPLMN	[Deletion of the entry with PLMN
	, 0.00		254/002]
6c	ME	Update of ME's internal memory	[Not explicitly verified: Deletion of
			the FPLMN entry with PLMN
			254/002]
7	$ME \to USS$	The ME registers to the GSM SS and is in	
		updated idle mode.	
8	$ME \to UICC$	TERMINAL RESPONSE: REFRESH 3.1.2	[normal ending]
9	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		REFRESH 3.2.2	
11	$ME \rightarrow UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: REFRESH 3.2.2	
13a	UICC	Update of EF OPLMNwACT	[First entry: PLMN= 254/001,
			ACT= UTRAN, second entry:
401	11100	LL L (FF FD) MAN	PLMN 254/002, ACT=GERAN]
13b	UICC	Update of EF FPLMN	[Entries with PLMN 254/002 and
			PLMN 254/001 not existen in EF
13b	ME	Update of ME's internal memory	FPLMNt] [Not explicitly verified: FPLMN
	IVIL	Opuate of ME's internal memory	entries with PLMN 254/002 and
		1	JULIULUS WILL LIVIN 204/002 AILU
			PLMN 254/001 not existent in
100			PLMN 254/001 not existent in FPLMN list!
14	MF → USS	The ME registers to the UMTS USS and is in	PLMN 254/001 not existent in FPLMN list]
	$ME \to USS$	The ME registers to the UMTS USS and is in updated idle mode.	
	$ME \to USS$ $ME \to UICC$	The ME registers to the UMTS USS and is in updated idle mode.  TERMINAL RESPONSE: REFRESH 3.1.2	
14		updated idle mode.	FPLMN list]

# PROACTIVE COMMAND: REFRESH 3.2.1

# Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: Steering of roaming

Device identities

Source device: UICC Destination device: ME

PLMNwACT List

 1stPLMN:
 254/002

 1stACT:
 GERAN

 2stPLMN:
 254/001

2stACT: UTRAN

#### Coding:

BER-TLV:	D0	15	81	03	01	01	07	82	02	81	82	72
	0A	00	11	00	00	80	00	11	00	80	00	

#### PROACTIVE COMMAND: REFRESH 3.2.2

#### Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: Steering of roaming

Device identities

Source device: UICC Destination device: ME

PLMNwACT List

 1stPLMN:
 254/003

 1stACT:
 GERAN

 2stPLMN:
 254/001

 2stACT:
 UTRAN

#### Coding:

BER-TLV:	D0	15	81	03	01	01	07	82	02	81	82	72
	0A	00	31	00	00	80	00	11	00	80	00	

#### 27.22.4.7.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1 to 3.2.

#### 27.22.4.8 SET UP MENU and ENVELOPE MENU SELECTION

# 27.22.4.8.1 SET UP MENU (normal) and ENVELOPE MENU SELECTION

#### 27.22.4.8.1.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.8.1.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.

#### 27.22.4.8.1.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

27.22.4.8.1.4 Method of test

27.22.4.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.1.4.2 Procedure

# Expected Sequence 1.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.1.4.2, Expected Sequence 1.1.

# Expected Sequence 1.2 (SET UP MENU, Large Menu with many items or with large items or with Large Alpha Identifier)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.1.4.2, Expected Sequence 1.2.

The following table details the test requirements with relation to the tested features:

	Proactive UICC Command Facilities		
Proactive UICC Command Number	Alpha Identifier Length	Number of items	Maximum length of item
1.1.1	12	4	6
1.1.2	12	2	3
1.1.3	10	0	-
1.2.1	10	30	8
1.2.2	10	7	37
1.2.3	235	1	1

#### 27.22.4.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1 and in expected sequence 1.2.

# 27.22.4.8.2 SET UP MENU (help request support) and ENVELOPE MENU SELECTION

27.22.4.8.2.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.8.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- TS 31.111 [15] clause 8.21.

#### 27.22.4.8.2.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that when the help is available for the command and the user has indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.2.4 Method of test

27.22.4.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.2.4.2 Procedure

# Expected Sequence 2.1 (SET UP MENU and MENU SELECTION, with Help Request, Replace and Remove a Toolkit Menu)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.2.4.2, Expected Sequence 2.1.

#### 27.22.4.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

# 27.22.4.8.3 SET UP MENU (next action support) and ENVELOPE MENU SELECTION

#### 27.22.4.8.3.1 Definition and applicability

See clause 3.2.2.

If the UICC provides an Items Next Action Indicator data object, the comprehension required flag shall be set to '0'.

#### 27.22.4.8.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- TS 31.111 [15] clause 8.24.

#### 27.22.4.8.3.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the next action indicator is supported.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.3.4 Method of test

27.22.4.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.3.4.2 Procedure

## Expected Sequence 3.1 (SET UP MENU, next action indicator "Send SM", "Set Up Call", "Launch Browser", "Provide Local Information", successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.3.4.2, Expected Sequence 3.1.

27.22.4.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

## 27.22.4.8.4 SET UP MENU (display of icons) and ENVELOPE MENU SELECTION

27.22.4.8.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clause 6.5.4, 8.31 and 8.32.

### 27.22.4.8.4.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that icons are displayed with the command Set Up Menu in the Alpha Identifier and Items Data Objects. To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.4.4 Method of test

27.22.4.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.4.4.2 Procedure

## Expected Sequence 4.1A (SET UP MENU, BASIC ICON NOT SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.1A.

## Expected Sequence 4.1B (SET UP MENU, BASIC ICON NOT SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.1B.

## Expected Sequence 4.2A (SET UP MENU, BASIC ICON SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.2A.

## Expected Sequence 4.2B (SET UP MENU, BASIC ICON SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.2B.

27.22.4.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1A to 4.2B.

27.22.4.8.5 SET UP MENU (soft keys support) and ENVELOPE MENU SELECTION

27.22.4.8.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1.

27.22.4.8.5.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that if soft key preferred is indicated in the command details and soft key for SET UP MENU is supported by the ME and the number of icon items does not exceed the number of soft keys available, then the ME displays those icons as soft key.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.5.4 Method of test

27.22.4.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.5.4.2 Procedure

### Expected Sequence 5.1 (SET UP MENU, SOFT KEY PREFERRED, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.5.4.2, Expected Sequence 5.1.

27.22.4.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

#### 27.22.4.8.6 SET UP MENU (support of Text Attribute) and ENVELOPE MENU SELECTION

27.22.4.8.6.1 SET UP MENU (support of Text Attribute - Left Alignment) and ENVELOPE MENU **SELECTION** 

27.22.4.8.6.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.1.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.1.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the left alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.1.4 Method of test

27.22.4.8.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.6.1.4.2 Procedure

## Expected Sequence 6.1 (SET UP MENU, Text Attribute – Left Alignment, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.1.4.2, Expected Sequence 6.1.

27.22.4.8.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

27.22.4.8.6.2 SET UP MENU (support of Text Attribute - Center Alignment) and ENVELOPE MENU

**SELECTION** 

27.22.4.8.6.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.2.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the center alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.2.4 Method of test

27.22.4.8.6.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.2.4.2 Procedure

## Expected Sequence 6.2 (SET UP MENU, Text Attribute - Center Alignment, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.2.4.2, Expected Sequence 6.2.

27.22.4.8.6.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.2.

27.22.4.8.6.3 SET UP MENU (support of Text Attribute – Right Alignment) and ENVELOPE MENU SELECTION

27.22.4.8.6.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.3.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the right alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.3.4 Method of test

27.22.4.8.6.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.3.4.2 Procedure

## Expected Sequence 6.3 (SET UP MENU, Text Attribute - Right Alignment, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.3.4.2, Expected Sequence 6.3.

27.22.4.8.6.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.3.

27.22.4.8.6.4 SET UP MENU (support of Text Attribute – Large Font Size) and ENVELOPE MENU

**SELECTION** 

27.22.4.8.6.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.4.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the large font size text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.4.4 Method of test

27.22.4.8.6.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.4.4.2 Procedure

## Expected Sequence 6.4 (SET UP MENU, Text Attribute – Large Font Size, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.4.4.2, Expected Sequence 6.4.

27.22.4.8.6.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.4.

27.22.4.8.6.5 SET UP MENU (support of Text Attribute – Small Font Size) and ENVELOPE MENU

**SELECTION** 

27.22.4.8.6.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.5.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the with small font size text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.5.4 Method of test

27.22.4.8.6.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.5.4.2 Procedure

## Expected Sequence 6.5 (SET UP MENU, Text Attribute - Small Font Size, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.5.4.2, Expected Sequence 6.5.

27.22.4.8.6.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.5.

27.22.4.8.6.6 SET UP MENU (support of Text Attribute – Bold On) and ENVELOPE MENU

**SELECTION** 

27.22.4.8.6.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.6.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.6.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.6.4 Method of test

27.22.4.8.6.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.6.4.2 Procedure

## Expected Sequence 6.6 (SET UP MENU, Text Attribute – Bold On, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.6.4.2, Expected Sequence 6.6.

27.22.4.8.6.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.6.

27.22.4.8.6.7 SET UP MENU (support of Text Attribute – Italic On) and ENVELOPE MENU

**SELECTION** 

27.22.4.8.6.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.7.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.7.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.7.4 Method of test

27.22.4.8.6.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.7.4.2 Procedure

## Expected Sequence 6.7 (SET UP MENU, Text Attribute – Italic On, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.7.4.2, Expected Sequence 6.7.

27.22.4.8.6.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.7.

27.22.4.8.6.8 SET UP MENU (support of Text Attribute – Underline On) and ENVELOPE MENU

**SELECTION** 

27.22.4.8.6.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.8.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.8.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.8.4 Method of test

27.22.4.8.6.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.8.4.2 Procedure

## Expected Sequence 6.8 (SET UP MENU, Text Attribute – Underline On, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.8.4.2, Expected Sequence 6.8.

27.22.4.8.6.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.8.

27.22.4.8.6.9 SET UP MENU (support of Text Attribute – Strikethrough On) and ENVELOPE MENU

SELECTION

27.22.4.8.6.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.9.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

## 27.22.4.8.6.9.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.9.4 Method of test

27.22.4.8.6.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.6.9.4.2 Procedure

## Expected Sequence 6.9 (SET UP MENU, Text Attribute - Strikethrough On, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.9.4.2, Expected Sequence 6.9.

#### 27.22.4.8.6.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.9.

27.22.4.8.6.10 SET UP MENU (support of Text Attribute – Foreground and Background Colour) and ENVELOPE MENU SELECTION

27.22.4.8.6.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.10.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

## 27.22.4.8.6.10.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.10.4 Method of test

27.22.4.8.6.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.6.10.4.2 Procedure

## Expected Sequence 6.10 (SET UP MENU, Text Attribute – Foreground and Background Colour, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.10.4.2, Expected Sequence 6.10.

### 27.22.4.8.6.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.10.

## 27.22.4.8.7 SET UP MENU (UCS2 display in Cyrillic) and ENVELOPE MENU SELECTION

## 27.22.4.8.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.8.7.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

#### 27.22.4.8.7.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

27.22.4.8.7.4 Method of test

27.22.4.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.7.4.2 Procedure

# Expected Sequence 7.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 in Cyrillic Characters)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.7.4.2, Expected Sequence 7.1.

### 27.22.4.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

## 27.22.4.8.8 SET UP MENU (UCS2 display in Chinese) and ENVELOPE MENU SELECTION

## 27.22.4.8.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.8.8.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.8.8.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

27.22.4.8.8.4 Method of test

27.22.4.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.8.4.2 Procedure

# Expected Sequence 8.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 – Chinese characters)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.8.4.2, Expected Sequence 8.1.

27.22.4.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

## 27.22.4.8.9 SET UP MENU (UCS2 display in Katakana) and ENVELOPE MENU SELECTION

27.22.4.8.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.9.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

## 27.22.4.8.9.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

27.22.4.8.9.4 Method of test

27.22.4.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.9.4.2 Procedure

# Expected Sequence 9.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 in Katakana Characters)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.9.4.2, Expected Sequence 9.1.

### 27.22.4.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

## 27.22.4.9 SELECT ITEM

## 27.22.4.9.1 SELECT ITEM (mandatory features for ME supporting SELECT ITEM)

### 27.22.4.9.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.9.1.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.

## 27.22.4.9.1.3 Test purpose

To verify that the ME correctly presents the set of items contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

#### 27.22.4.9.1.4 Method of test

## 27.22.4.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.1.4.2 Procedure

## Expected Sequence 1.1 (SELECT ITEM, mandatory features, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.1.

## Expected Sequence 1.2 (SELECT ITEM, large menu, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.2.

## Expected Sequence 1.3 (SELECT ITEM, call options, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.3.

## Expected Sequence 1.4 (SELECT ITEM, backward move by user, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.4.

## Expected Sequence 1.5 (SELECT ITEM, "Y", successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.5.

## Expected Sequence 1.6 (SELECT ITEM, Large menu, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.6.

The following table details the test commands with relation to the tested features:

	Proactive UIC	CC Command	I Facilities
Proactive UICC Command SELECT ITEM Number	Alpha Identifier Length	Number of items	Maximum length of item
1.1	14	4	6
1.2	10	30	8
1.3	10	7	43
1.4	11	2	3
1.5	236	1	1
1.6	10	7	37

## 27.22.4.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1, 1.2, 1.3, 1.4, 1.5 and 1.6 (SELECT ITEM, mandatory features).

## 27.22.4.9.2 SELECT ITEM (next action support)

27.22.4.9.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.2.2 Conformance Requirement

Same as clause 27.22.4.9.1.2.

## 27.22.4.9.2.3 Test purpose

To verify that the mobile supports next action indicator mode.

27.22.4.9.2.4 Method of test

27.22.4.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.2.4.2 Procedure

## Expected Sequence 2.1 (SELECT ITEM, next action indicator, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.2.4.2, Expected Sequence 2.1.

27.22.4.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1

27.22.4.9.3 SELECT ITEM (default item support)

27.22.4.9.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.3.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

27.22.4.9.3.3 Test purpose

To verify that the mobile supports "default item" mode.

27.22.4.9.3.4 Method of test

27.22.4.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.3.4.2 Procedure

## Expected Sequence 3.1 (SELECT ITEM, default item, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.3.4.2, Expected Sequence 3.1.

27.22.4.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1

27.22.4.9.4 SELECT ITEM (help request support)

27.22.4.9.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.4.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

27.22.4.9.4.3 Test purpose

To verify that the mobile supports "help request" for the command Select Item.

27.22.4.9.4.4 Method of test

27.22.4.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.4.4.2 Procedure

## Expected Sequence 4.1 (SELECT ITEM, help request, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.4.4.2, Expected Sequence 4.1.

27.22.4.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1

27.22.4.9.5 SELECT ITEM (icons support)

27.22.4.9.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.5.2 Conformance requirement

Same as clause 27.22.4.9.1.2 and TS 31.111 [15] clause 8.31 and clause 8.32.

27.22.4.9.5.3 Test purpose

To verify that the mobile displays icons with the command Select Item.

27.22.4.9.5.4 Method of test

27.22.4.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.5.4.2 Procedure

## Expected Sequence 5.1A (SELECT ITEM, BASIC ICON NOT SELF EXPLANATORY, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.1A.

## Expected Sequence 5.1B (SELECT ITEM, BASIC ICON NOT SELF EXPLANATORY, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.1B.

## Expected Sequence 5.2A (SELECT ITEM, BASIC ICON SELF EXPLANATORY, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.2A.

## Expected Sequence 5.2B (SELECT ITEM, BASIC ICON SELF EXPLANATORY, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.2B.

27.22.4.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1A to 5.2B.

27.22.4.9.6 SELECT ITEM (presentation style)

27.22.4.9.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.6.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

27.22.4.9.6.3 Test purpose

To verify that the mobile supports the "presentation style" with the command Select Item.

27.22.4.9.6.4 Method of test

27.22.4.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.6.4.2 Procedure

## Expected Sequence 6.1 (SELECT ITEM, PRESENTATION AS A CHOICE OF NAVIGATION OPTIONS, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.6.4.2, Expected Sequence 6.1.

# Expected Sequence 6.2 (SELECT ITEM, PRESENTATION AS A CHOICE OF DATA VALUES, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.6.4.2, Expected Sequence 6.2.

27.22.4.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequences 6.1 and 6.2.

27.22.4.9.7 SELECT ITEM (soft keys support)

27.22.4.9.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.7.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

27.22.4.9.7.3 Test purpose

To verify that the mobile supports the "soft keys" with the command Select Item.

27.22.4.9.7.4 Method of test

27.22.4.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.7.4.2 Procedure

## Expected Sequence 7.1 (SELECT ITEM, SELECTING USING SOFT KEYS PREFERRED, successful, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.7.4.2, Expected Sequence 7.1.

27.22.4.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

27.22.4.9.8 SELECT ITEM (Support of "No response from user")

27.22.4.9.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.8.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

27.22.4.9.8.3 Test purpose

To verify that after a period of user inactivity the ME returns a "No response from user" result value in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.9.8.4 Method of test

27.22.4.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME Manufacturer shall have defined the "no response from user" period of time as declared in table A.2/4.

The USIM Simulator shall be set to that period of time.

27.22.4.9.8.4.2 Procedure

## Expected Sequence 8.1 (SELECT ITEM, no response from user)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.8.4.2, Expected Sequence 8.1.

27.22.4.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

27.22.4.9.9 SELECT ITEM (Support of Text Attribute)

27.22.4.9.9.1 SELECT ITEM (Support of Text Attribute – Left Alignment)

27.22.4.9.9.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.1.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.1.3 Test purpose

To verify that the ME displays text formatted according to the left alignment text attribute configuration within the command Select Item.

27.22.4.9.9.1.4 Method of test

27.22.4.9.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.1.4.2 Procedure

#### Expected Sequence 9.1 (SELECT ITEM, Text Attribute – Left Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.1.4.2, Expected Sequence 9.1.

27.22.4.9.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

27.22.4.9.9.2 SELECT ITEM (Support of Text Attribute – Center Alignment)

27.22.4.9.9.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.2.3 Test purpose

To verify that the ME displays text formatted according to the center alignment text attribute configuration within the command Select Item.

27.22.4.9.9.2.4 Method of test

27.22.4.9.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.2.4.2 Procedure

## Expected Sequence 9.2 (SELECT ITEM, Text Attribute – Center Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.2.4.2, Expected Sequence 9.2.

27.22.4.9.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.2.

27.22.4.9.9.3 SELECT ITEM (Support of Text Attribute – Right Alignment)

27.22.4.9.9.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.3.3 Test purpose

To verify that the ME displays text formatted according to the right alignment text attribute configuration within the command Select Item.

27.22.4.9.9.3.4 Method of test

27.22.4.9.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.3.4.2 Procedure

## Expected Sequence 9.3 (SELECT ITEM, Text Attribute – Right Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.3.4.2, Expected Sequence 9.3.

27.22.4.9.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.3.

27.22.4.9.9.4 SELECT ITEM (Support of Text Attribute – Large Font Size)

27.22.4.9.9.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.4.3 Test purpose

To verify that the ME displays text formatted according to the large font size text attribute configuration within the command Select Item.

27.22.4.9.9.4.4 Method of test

27.22.4.9.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.4.4.2 Procedure

#### Expected Sequence 9.4 (SELECT ITEM, Text Attribute – Large Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.4.4.2, Expected Sequence 9.4.

27.22.4.9.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.4.

27.22.4.9.9.5 SELECT ITEM (Support of Text Attribute – Small Font Size)

27.22.4.9.9.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.5.3 Test purpose

To verify that the ME displays text formatted according to the small font size text attribute configuration within the command Select Item.

27.22.4.9.9.5.4 Method of test

27.22.4.9.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.5.4.2 Procedure

## Expected Sequence 9.5 (SELECT ITEM, Text Attribute – Small Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.5.4.2, Expected Sequence 9.5.

27.22.4.9.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.5.

27.22.4.9.9.6 SELECT ITEM (Support of Text Attribute – Bold On)

27.22.4.9.9.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.6.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.6.3 Test purpose

To verify that the ME displays text formatted according to the bold text attribute configuration within the command Select Item.

27.22.4.9.9.6.4 Method of test

27.22.4.9.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.6.4.2 Procedure

## Expected Sequence 9.6 (SELECT ITEM, Text Attribute – Bold On)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.6.4.2, Expected Sequence 9.6.

27.22.4.9.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.6.

27.22.4.9.9.7 SELECT ITEM (Support of Text Attribute – Italic On)

27.22.4.9.9.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.7.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.7.3 Test purpose

To verify that the ME displays text formatted according to the italic text attribute configuration within the command Select Item.

27.22.4.9.9.7.4 Method of test

27.22.4.9.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.7.4.2 Procedure

## Expected Sequence 9.7 (SELECT ITEM, Text Attribute – Italic On)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.7.4.2, Expected Sequence 9.7.

27.22.4.9.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.7.

27.22.4.9.9.8 SELECT ITEM (Support of Text Attribute – Underline On)

27.22.4.9.9.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.8.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.8.3 Test purpose

To verify that the ME displays text formatted according to the underline text attribute configuration within the command Select Item.

27.22.4.9.9.8.4 Method of test

27.22.4.9.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.8.4.2 Procedure

## Expected Sequence 9.8 (SELECT ITEM, Text Attribute - Underline On)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.8.4.2, Expected Sequence 9.8.

27.22.4.9.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.8.

27.22.4.9.9.9 SELECT ITEM (Support of Text Attribute – Strikethrough On)

27.22.4.9.9.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.9.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.9.3 Test purpose

To verify that the ME displays text formatted according to the strikethrough text attribute configuration within the command Select Item.

27.22.4.9.9.9.4 Method of test

27.22.4.9.9.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.9.4.2 Procedure

## Expected Sequence 9.9 (SELECT ITEM, Text Attribute – Strikethrough On)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.9.4.2, Expected Sequence 9.9.

27.22.4.9.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.9.

27.22.4.9.9.10 SELECT ITEM (Support of Text Attribute – Foreground and Background Colour)

27.22.4.9.9.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.10.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.10.3 Test purpose

To verify that the ME displays text formatted according to the foreground and background colour text attribute configuration within the command Select Item.

27.22.4.9.9.10.4 Method of test

27.22.4.9.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.10.4.2 Procedure

### Expected Sequence 9.10 (SELECT ITEM, Text Attribute – Foreground and Background Colour)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.10.4.2, Expected Sequence 9.10.

27.22.4.9.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.10.

27.22.4.9.10 SELECT ITEM (UCS2 display in Cyrillic)

27.22.4.9.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.10.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.9.10.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

27.22.4.9.10.4 Method of test

27.22.4.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.10.4.2 Procedure

## Expected Sequence 10.1 (SELECT ITEM with UCS2 in Cyrillic characters, 0x80 UCS2 coding, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.1.

## Expected Sequence 10.2 (SELECT ITEM with UCS2 in Cyrillic characters, 0x81 UCS2 coding, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.2.

## Expected Sequence 10.3 (SELECT ITEM with UCS2 in Cyrillic characters, 0x82 UCS2 coding, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.3.

#### 27.22.4.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequences 10.1 to 10.3.

## 27.22.4.9.11 SELECT ITEM (UCS2 display in Chinese)

## 27.22.4.9.11.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.11.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.9.11.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

## 27.22.4.9.11.4 Method of test

#### 27.22.4.9.11.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.11.4.2 Procedure

## Expected Sequence 11.1 (SELECT ITEM with UCS2 in Chinese characters, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.11.4.2, Expected Sequence 11.1.

#### 27.22.4.9.11.5 Test requirement

The ME shall operate in the manner defined in expected sequence 11.1.

## 27.22.4.9.12 SELECT ITEM (UCS2 display in Katakana)

27.22.4.9.12.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.12.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

## 27.22.4.9.12.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

27.22.4.9.12.4 Method of test

27.22.4.9.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.12.4.2 Procedure

## Expected Sequence 12.1 (SELECT ITEM with UCS2 in Katakana characters, 0x80 UCS2 coding, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.1.

## Expected Sequence 12.2 (SELECT ITEM with UCS2 - Katakana characters, 0x81 UCS2 coding, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.2.

## Expected Sequence 12.3 (SELECT ITEM with UCS2 - Katakana characters, 0x82 UCS2 coding, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.3.

#### 27.22.4.9.12.5 Test requirement

The ME shall operate in the manner defined in expected sequences 12.1 to 12.3.

## 27.22.4.10 SEND SHORT MESSAGE

## 27.22.4.10.1 SEND SHORT MESSAGE (normal)

## 27.22.4.10.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.1.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

## 27.22.4.10.1.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

### 27.22.4.10.1.4 Method of test

#### 27.22.4.10.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

### 27.22.4.10.1.4.2 Procedure

## Expected Sequence 1.1(SEND SHORT MESSAGE, packing not required, 8-bit data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, 8-bit data]
		SHORT MESSAGE 1.1.1	
4	$ME \rightarrow USER$	Display "Send SM"	[Alpha Identifier]
5	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 1.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 1.1.1	

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send SM"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data Message class class 0 TP-UDL 12

TP-UD "Test Message"

#### Coding:

BER-TLV:	D0	37	81	03	01	13	00	82	02	81	83	85
-	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65			

## SMS-PP (SEND SHORT MESSAGE) Message 1.1

#### Logically:

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data Message class class 0 TP-UDL 12 TP-UD "Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00

## Expected Sequence 1.2 (SEND SHORT MESSAGE, packing required, 8-bit data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 1.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing required, 8-bit data]
		SHORT MESSAGE 1.2.1	
4	$ME \rightarrow USER$	Display "Send SM"	[Alpha Identifier]
5	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 1.2	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 1.2.1	

### PROACTIVE COMMAND: SEND SHORT MESSAGE 1.2.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send SM"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding8-bit dataMessage classclass 0TP-UDL7

TP-UD "Send SM"

#### Coding:

BER-TLV:	D0	32	81	03	01	13	01	82	02	81	83	85
	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	13	01	00	09
	91	10	32	54	76	F8	40	F4	07	53	65	6E
	64	20	53	4D								

## SMS-PP (SEND SHORT MESSAGE) Message 1.2

#### Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 7

TP-UD "Send SM"

## Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F0	07
	D3	B2	9B	0C	9A	36	01					

## TERMINAL RESPONSE: SEND SHORT MESSAGE 1.2.1

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing required

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	01	82	02	82	81	83	01	00
D		00							<b>.</b>		<b>.</b>	00

## Expected Sequence 1.3 (SEND SHORT MESSAGE, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 1.3.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
		SHORT MESSAGE 1.3.1	
4	$ME \to USER$	Display "Short Message"	[Alpha Identifier]
5	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 1.3	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 1.3.1	

## PROACTIVE COMMAND: SEND SHORT MESSAGE 1.3.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Short Message"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 13

TP-UD "Short Message"

Coding:

BER-TLV:	D0	3D	81	03	01	13	00	82	02	81	83	85
	0D	53	68	6F	72	74	20	4D	65	73	73	61
	67	65	86	09	91	11	22	33	44	55	66	77
	F8	8B	18	01	00	09	91	10	32	54	76	F8
	40	F0	0D	53	F4	5B	4E	07	35	CB	F3	79
	F8	5C	06									

## SMS-PP (SEND SHORT MESSAGE) Message 1.3

#### Logically:

**SMS TPDU** 

**SMS-SUBMIT** TP-MTI

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-Reply-Path is not set in this SMS-SUBMIT TP-RP TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

"012345678" Address value

Short message type 0 TP-PID

TP-DCS

Message coding SMS default alphabet

class 0 Message class TP-UDL 13

"Short Message" TP-UD

## Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F0	0D
	53	F4	5B	4E	07	35	CB	F3	79	F8	5C	06

## TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1

## Logically:

Command details

Command number:

Command type: SEND SHORT MESSAGE Command qualifier: packing not required

Device identities

Source device: ME Destination device: **UICC** 

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00	
----------	----	----	----	----	----	----	----	----	----	----	----	----	--

## Expected Sequence 1.4 (SEND SHORT MESSAGE, packing required, 8 bit data, message of 160 characters user data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 1.4. 1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing required, 8 bit data]
		SHORT MESSAGE 1.4.1	
4	$ME \to USER$	Display "The address data object	[Alpha Identifier]
		holds the RP_Destination_Address	
		"	
5		Send SMS-PP(SEND SHORT	[message of 140 bytes user data]
		MESSAGE) Message 1.4	
6		SMS RP-ACK	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 1.4.1	

### PROACTIVE COMMAND: SEND SHORT MESSAGE 1.4.1

### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "The address data object holds the RP\_Destination\_Address"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8 bit data Message class class 0 TP-UDL 160

TP-UD "Two types are defined: - A short message to be sent to the network in an

SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can

be passed transp"

## Coding:

BER-TLV:	D0	81	FD	81	03	01	13	01	82	02	81	83
	85	38	54	68	65	20	61	64	64	72	65	73
	73	20	64	61	74	61	20	6F	62	6A	65	63
	74	20	68	6F	6C	64	73	20	74	68	65	20
	52	50	11	44	65	73	74	69	6E	61	74	69
	6F	6E	11	41	64	64	72	65	73	73	86	09
	91	11	22	33	44	55	66	77	F8	8B	81	AC
	01	00	09	91	10	32	54	76	F8	40	F4	A0
	54	77	6F	20	74	79	70	65	73	20	61	72
	65	20	64	65	66	69	6E	65	64	3A	20	2D
	20	41	20	73	68	6F	72	74	20	6D	65	73
	73	61	67	65	20	74	6F	20	62	65	20	73
	65	6E	74	20	74	6F	20	74	68	65	20	6E
	65	74	77	6F	72	6B	20	69	6E	20	61	6E
	20	53	4D	53	2D	53	55	42	4D	49	54	20
	6D	65	73	73	61	67	65	2C	20	6F	72	20
	61	6E	20	53	4D	53	2D	43	4F	4D	4D	41
	4 <sup>E</sup>	44	20	6D	65	73	73	61	67	65	2C	20
	77	68	65	72	65	20	74	68	65	20	75	73
	65	72	20	64	61	74	61	20	63	61	6 <sup>E</sup>	20
	62	65	20	70	61	73	73	65	64	20	74	72
	61	6E	73	70								

## SMS-PP (SEND SHORT MESSAGE) Message 1.4

## Logically:

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 160

TP-UD "Two types are defined: - A short message to be sent to the network in an

 $SMS\mbox{-}SUBMIT$  message, or an  $SMS\mbox{-}COMMAND$  message, where the user data can

be passed transp"

## Coding:

Coding		01	01	09	91	10	32	54	76	F8	40	F0
	A0	D4	FB	1B	44	CF	C3	CB	73	50	58	5E
	06	91	СВ	E6	B4	BB	4C	D6	81	5A	A0	20
	68	8E	7E	CB	E9	A0	76	79	3E	0F	9F	CB
	20	FA	1B	24	2 <sup>E</sup>	83	E6	65	37	1D	44	7F
	83	E8	E8	32	C8	5D	A6	DF	DF	F2	35	28
	ED	06	85	DD	A0	69	73	DA	9A	56	85	CD
	24	15	D4	2E	CF	E7	E1	73	99	05	7A	CB
	41	61	37	68	DA	9C	B6	86	CF	66	33	E8
	24	82	DA	E5	F9	3C	7C	2E	В3	40	77	74
	59	5E	06	D1	D1	65	50	7D	5E	96	83	C8
	61	7A	18	34	0E	BB	41	E2	32	08	1E	9E
	CF	СВ	64	10	5D	1E	76	CF	E1			

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.4.1

Logically:

Command details

Command number:

Command type: SEND SHORT MESSAGE

Command qualifier: packing required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	01	82	02	82	81	83	01	00

## Expected Sequence 1.5 (SEND SHORT MESSAGE, packing not required, SMS default alphabet, message of 160 characters user data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 1.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
		SHORT MESSAGE 1.5.1	
4	$ME \to USER$	Display "The address data object	[Alpha Identifier]
		holds the RP Destination Address "	
5	$ME \to USS$	Send SMS-PP (SEND SHORT	[message of 140 bytes user data]
		MESSAGE) Message 1.5	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 1.5.1	

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.5.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "The address data object holds the RP Destination Address"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 160

TP-UD "Two types are defined: - A short message to be sent to the network in an

SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can

be passed transp"

## Coding:

BER-TLV:	D0	81	E9	81	03	01	13	00	82	02	81	83
_	85	38	54	68	65	20	61	64	64	72	65	73
	73	20	64	61	74	61	20	6F	62	6A	65	63
	74	20	68	6F	6C	64	73	20	74	68	65	20
	52	50	20	44	65	73	74	69	6E	61	74	69
	6F	6E	20	41	64	64	72	65	73	73	86	09
	91	11	22	33	44	55	66	77	F8	8B	81	98
	01	00	09	91	10	32	54	76	F8	40	F0	A0
	D4	FB	1B	44	CF	C3	CB	73	50	58	5E	06
	91	СВ	E6	B4	BB	4C	D6	81	5A	A0	20	68
	8E	7E	CB	E9	A0	76	79	3E	0F	9F	СВ	20
	FA	1B	24	2 <sup>E</sup>	83	E6	65	37	1D	44	7F	83
	E8	E8	32	C8	5D	A6	DF	DF	F2	35	28	ED
	06	85	DD	A0	69	73	DA	9A	56	85	CD	24
	15	D4	2E	CF	E7	E1	73	99	05	7A	СВ	41
	61	37	68	DA	9C	B6	86	CF	66	33	E8	24
	82	DA	E5	F9	3C	7C	2E	В3	40	77	74	59
	5E	06	D1	D1	65	50	7D	5E	96	83	C8	61
	7A	18	34	0E	BB	41	E2	32	80	1E	9E	CF
	CB	64	10	5D	1E	76	CF	E1				

#### SMS-PP (SEND SHORT MESSAGE) Message 1.5

## Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 160

TP-UD "Two types are defined: - A short message to be sent to the network in an SMS-

SUBMIT message, or an SMS-COMMAND message, where the user data can be

passed transp"

# Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F0	A0
	D4	FB	1B	44	CF	C3	CB	73	50	58	5E	06
	91	CB	E6	B4	BB	4C	D6	81	5A	A0	20	68
	8E	7E	CB	E9	A0	76	79	3E	0F	9F	CB	20
	FA	1B	24	2 <sup>E</sup>	83	E6	65	37	1D	44	7F	83
	E8	E8	32	C8	5D	A6	DF	DF	F2	35	28	ED
	06	85	DD	A0	69	73	DA	9A	56	85	CD	24
	15	D4	2E	CF	E7	E1	73	99	05	7A	CB	41
	61	37	68	DA	9C	B6	86	CF	66	33	E8	24
	82	DA	E5	F9	3C	7C	2E	В3	40	77	74	59
	5E	06	D1	D1	65	50	7D	5E	96	83	C8	61
	7A	18	34	0E	BB	41	E2	32	08	1E	9E	CF
	СВ	64	10	5D	1E	76	CF	E1				

# TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81	03	01	13	00	82	02	82	81	83	01	00
-------------	----	----	----	----	----	----	----	----	----	----	----

# Expected Sequence 1.6 (SEND SHORT MESSAGE, alpha identifier 160 bytes long, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 1.6.1	
2	$ME \rightarrow UICC$	FEICH	
3	$UICC \to ME$		[packing not required, SMS default alphabet]
		SHORT MESSAGE 1.6.1	
4	$ME \rightarrow USER$	Display "Two types are defined: - A	[Alpha Identifier of 160 bytes]
		short message to be sent to the	
		network in an SMS-SUBMIT	
		message, or an SMS-COMMAND	
		message, where the user data can	
		be passed transparently; - A short	
		message to be sent to the network	
		in an SMS-SUBMIT "	
5	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 1.6	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 1.6.1	

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 1.6.1

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Two types are defined: - A short message to be sent to the network in an

SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can

be passed transparently; - A short message to be sent to the network in an

SMS-SUBMIT"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

# Coding:

BER-TLV:	D0	81	FD	81	03	01	13	00	82	02	81	83
	85	81	E6	54	77	6F	20	74	79	70	65	73
	20	61	72	65	20	64	65	66	69	6E	65	64
	3A	20	2D	20	41	20	73	68	6F	72	74	20
	6D	65	73	73	61	67	65	20	74	6F	20	62
	65	20	73	65	6E	74	20	74	6F	20	74	68
	65	20	6E	65	74	77	6F	72	6B	20	69	6 <sup>E</sup>
	20	61	6 <sup>E</sup>	20	53	4D	53	2D	53	55	42	4D
	49	54	20	6D	65	73	73	61	67	65	2C	20
	6F	72	20	61	6E	20	53	4D	53	2D	43	4F
	4D	4D	41	4 <sup>E</sup>	44	20	6D	65	73	73	61	67
	65	2C	20	77	68	65	72	65	20	74	68	65
	20	75	73	65	72	20	64	61	74	61	20	63
	61	6 <sup>E</sup>	20	62	65	20	70	61	73	73	65	64
	20	74	72	61	6 <sup>E</sup>	73	70	61	72	65	6 <sup>E</sup>	74
	6C	79	3B	20	2D	20	41	20	73	68	6F	72
	74	20	6D	65	73	73	61	67	65	20	74	6F
	20	62	65	20	73	65	6E	74	20	74	6F	20
	74	68	65	20	6E	65	74	77	6F	72	6B	20
	69	6E	20	61	6E	20	53	4D	53	2D	53	55
	42	4D	49	54	20	8B	09	01	00	02	91	10
	40	F0	01	20								

## SMS-PP (SEND SHORT MESSAGE) Message 1.6

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Coding:

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.6.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
D = 1 \ 1 = \ 1		00			00		~_				<b>.</b>	00

# Expected Sequence 1.7(SEND SHORT MESSAGE, alpha identifier length '00', packing not required, 8-bit data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to$	PROACTIVE COMMAND	
	ME	PENDING: SEND SHORT	
		MESSAGE 1.7.1	
2	ME  o	FETCH	
	UICC		
3	$UICC \to$	PROACTIVE COMMAND: SEND	[packing not required, 8-bit data]
	ME	SHORT MESSAGE 1.7.1	
4	ME	No information to user	[Alpha identifier length '00']
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 1.7	
6	$USS \to ME$	SMS RP-ACK	
7	ME  o	TERMINAL RESPONSE: SEND	[Command performed successfully]
	UICC	SHORT MESSAGE 1.7.1	

## PROACTIVE COMMAND: SEND SHORT MESSAGE 1.7.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier:

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data
Message class class 0
TP-UDL 12

TP-UD "Test Message"

Coding:

BER-TLV:	D0	30	81	03	01	13	00	82	02	81	83	85
	00	86	09	91	11	22	33	44	55	66	77	F8
	8B	18	01	00	09	91	10	32	54	76	F8	40
	F4	0C	54	65	73	74	20	4D	65	73	73	61
	67	65										

## SMS-PP (SEND SHORT MESSAGE) Message 1.7

Logically:

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data Message class class 0 TP-UDL 12

TP-UD "Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
'	54	65	73	74	20	4D	65	73	73	61	67	65

# TERMINAL RESPONSE: SEND SHORT MESSAGE 1.7.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

# Expected Sequence 1.8 (SEND SHORT MESSAGE, packing not required, 8-bit data, no alpha identifier, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 1.8.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, 8-bit data]
		SHORT MESSAGE 1.8.1	
4	$ME \rightarrow USER$	May give information to user	[No Alpha Identifier]
		concerning what is happening	
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 1.8	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 1.8.1	

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 1.8.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data Message class class 0 TP-UDL 12

TP-UD "Test Message"

# Coding:

BER-TLV:	D0	2E	81	03	01	13	00	82	02	81	83	86
	09	91	11	22	33	44	55	66	77	F8	8B	18
	01	00	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

SMS-PP (SEND SHORT MESSAGE) Message 1.8

## Logically:

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data
Message class class 0
TP-UDL 12

TP-UD "Test Message"

## Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 1.8.1

### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully

# Coding:

RER-TI V	81	03	01	13	00	82	02	82	81	83	01	00
DLIX-ILV.	01	03	UI	13	00	02	02	02	01	03	UI	00

# 27.22.4.10.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.8.

# 27.22.4.10.2 SEND SHORT MESSAGE (UCS2 display in Cyrillic)

27.22.4.10.2.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.10.2.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

# 27.22.4.10.2.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.2.4 Method of test

27.22.4.10.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.2.4.2 Procedure

# Expected Sequence 2.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data in Cyrillic))

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
2	$ME \rightarrow UICC$	MESSAGE 2.1.1 FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, 16-bit data]
		SHORT MESSAGE 2.1.1	[paoking not required, no-bit data]
4	$ME \rightarrow USER$		[Alpha Identifier]
			"Hello" in Russian, 0x80 coding of UCS2
_			format
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	Cyrillic
6	$USS \to ME$	MESSAGE) Message 2.1 SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
1	IVIL -> 0100	SHORT MESSAGE 2.1.1	[Command performed adocederally]
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
10	ME → UICC	MESSAGE 2.1.2 FETCH	
11	$VICC \rightarrow ME$	PROACTIVE COMMAND SEND	
	OIGG / WIE	SHORT MESSAGE 2.1.2	
12	$ME \rightarrow USER$	Display "ЗДРАВСТВУЙТЕ"	[Alpha Identifier]
			"Hello" in Russian, 0x81 coding of UCS2
40	NAT LIGO	O - T - I OMO DD (OFNID OLIODT	format
13	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 2.1	
14	$USS \to ME$	ISMS RP-ACK	
15	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
	, , , ,	SHORT MESSAGE 2.1.1	, , , , , , , , , , , , , , , , , , , ,
16	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
17	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT MESSAGE 2.1.3	
18	ME → UICC	FETCH	
19	UICC → ME	PROACTIVE COMMAND: SEND	[UCS2 alphabet]
1		SHORT MESSAGE 2.1.3	· · ·
20	$ME \rightarrow USER$	Display "ЗДРАВСТВУЙТЕ"	[Alpha Identifier]
1			"Hello" in Russian, 0x82 coding of UCS2
21	ME LICO	Sand SMS DD (SEND SHORT	format
41	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 2.1	
22	$USS \to ME$	SMS RP-ACK	
23	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
1		SHORT MESSAGE 2.1.1	·
24	$UICC \to ME$	PROACTIVE UICC SESSION	
1		ENDED	1

PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.1

# Logically:

Command details

Command number:

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 16-bit data Message class class 0 TP-UDL 24

ТР-UD "ЗДРАВСТВУЙТЕ"

#### Coding:

BER-TLV:	D0	55	81	03	01	13	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	86	09	91	11	22	33	44	55	66	77
	F8	8B	24	01	00	09	91	10	32	54	76	F8
	40	80	18	04	17	04	14	04	20	04	10	04
	12	04	21	04	22	04	12	04	23	04	19	04
	22	04	15									

## SMS-PP (SEND SHORT MESSAGE) Message 2.1

## Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding UCS2 (16-bit data)

Message class 0 TP-UDL 24

ТР-UD "ЗДРАВСТВУЙТЕ"

## Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	80	18
	04	17	04	14	04	20	04	10	04	12	04	21
	04	22	04	12	04	23	04	19	04	22	04	15

#### PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.2

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 16-bit data Message class class 0 TP-UDL 24

ТР-UD "ЗДРАВСТВУЙТЕ"

Coding:

BER-TLV:	D0	4B	81	03	01	13	00	82	02	81	83	85
'	0F	81	0C	08	97	94	A0	90	92	A1	A2	92
	A3	99	A2	95	86	09	91	11	22	33	44	55
	66	77	F8	8B	24	01	00	09	91	10	32	54
	76	F8	40	08	18	04	17	04	14	04	20	04
	10	04	12	04	21	04	22	04	12	04	23	04
	19	04	22	04	15							

## PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.3

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

228

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

**TP-DCS** 

Message coding 16-bit data Message class class 0 TP-UDL 24

TP-UD "ЗДРАВСТВУЙТЕ"

#### Coding:

BER-TLV:	D0	4C	81	03	01	13	00	82	02	81	83	85
	10	82	0C	04	10	87	84	90	80	82	91	92
	82	93	89	92	85	86	09	91	11	22	33	44
	55	66	77	F8	8B	24	01	00	09	91	10	32
	54	76	F8	40	08	18	04	17	04	14	04	20
	04	10	04	12	04	21	04	22	04	12	04	23
	04	19	04	22	04	15						

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1

Logically:

Command details

Command number:

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

	0.1	00	0.4	40		00	02	0.0	0.4	0.2		
BER-TLV:	l 81	03	l 01	13	00	82	1 02	82	81	83	01	00

27.22.4.10.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

27.22.4.10.3 SEND SHORT MESSAGE (icon support)

27.22.4.10.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.10.3.2 Conformance requirement

27.22.4.10.3.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.3.4 Method of test

27.22.4.10.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.10.3.4.2 Procedure

# Expected Sequence 3.1A (SEND SHORT MESSAGE, basic icon self-explanatory, packing not required, 8-bit data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 3.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, 8-bit data]
		SHORT MESSAGE 3.1.1	
4	$ME \rightarrow USER$	Displays the icon and not the alpha	[basic icon self-explanatory]
		identifier	
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 3.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 3.1.1A	

# PROACTIVE COMMAND: SEND SHORT MESSAGE 3.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "NO ICON"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8bit-data Message class class 0 TP-UDL 12

TP-UD "Test Message"

Icon Identifier

Icon Qualifier self-explanatory

Icon Identifier 1 (number of record in EF IMG)

Coding:

BER-TLV:	D0	3B	81	03	01	13	00	82	02	81	83	85
	07	4E	4F	20	49	43	4F	4E	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65	9E	02	00
	01											_

# SMS-PP (SEND SHORT MESSAGE) Message 3.1

#### Logically:

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding8-bit dataMessage classclass 0TP-UDL12

TP-UD "Test Message"

## Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

## TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1A

### Logically:

Command details

Command number:

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
	•			. •			~-		<b>.</b>		• .	

# Expected Sequence 3.1B (SEND SHORT MESSAGE, basic icon self-explanatory, packing not required, 8-bit data, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 3.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, 8-bit data, basic icon
		SHORT MESSAGE 3.1.1	self-explanatory]]
4	$ME \rightarrow USER$	Displays the alpha identifier	·
		without the icon	
5	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 3.1	
6	000 /	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully, but
		SHORT MESSAGE 3.1.1B	requested icon could not be displayed]

## TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1B

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	04
DLIX-ILV.	01	03	ΟĪ	13	00	02	02	02	01	00	Οī	04

# Expected Sequence 3.2A (SEND SHORT MESSAGE, basic icon non-self-explanatory, packing not required, 8-bit data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 3.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, 8-bit data]
		SHORT MESSAGE 3.2.1	
4	$ME \rightarrow USER$	display the icon and "Send SM"	[basic icon non-self-explanatory]
5	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 3.2	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 3.2.1A	

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 3.2.1

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha Identifier "Send SM"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8bit-data Message class class 0 TP-UDL 12

TP-UD "Test Message"

Icon Identifier

Icon Qualifier non-self-explanatory

Icon Identifier 1 (number of record in EF IMG)

#### Coding:

BER-TLV:	D0	3B	81	03	01	13	00	82	02	81	83	85
	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65	1E	02	01
	01											

# SMS-PP (SEND SHORT MESSAGE) Message 3.2

### Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

**TP-DCS** 

Message coding8-bit dataMessage classclass 0TP-UDL12

TP-UD "Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1A

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00

# Expected Sequence 3.2B (SEND SHORT MESSAGE, basic icon non-self-explanatory, packing not required, 8-bit data, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 3.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, 8-bit data, basic icon
		SHORT MESSAGE 3.2.1	non-self-explanatory ]
4	$ME \to USER$	display "Send SM" without the icon	
5	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 3.2	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully, but
		SHORT MESSAGE 3.2.1B	requested icon could not be displayed]

## TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1B

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed;

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	04

# 27.22.4.10.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.2B.

## 27.22.4.10.4 SEND SHORT MESSAGE (Support of Text Attribute)

27.22.4.10.4.1 SEND SHORT MESSAGE (Support of Text Attribute – Left Alignment)

27.22.4.10.4.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.10.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

## 27.22.4.10.4.1.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the left alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.4.1.4 Method of test

#### 27.22.4.10.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.1.4.2 Procedure

# Expected Sequence 4.1 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Left Alignment, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.1	[packing not required, SMS default alphabet]
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with left alignment]
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1	[Command performed successfully]
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.1.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.2	[packing not required, SMS default alphabet]
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place]
12	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	$USS \to ME$	SMS RP-ACK	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1	[Command performed successfully]

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.1

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1 TP-UD " "
Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.2

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
·	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

# SMS-PP (SEND SHORT MESSAGE) Message 4.1

Logically:

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0
TP-UDL 1
TP-UD " "

#### Coding:

Coding	01	01	02	91	10	40	F0	01	20
--------	----	----	----	----	----	----	----	----	----

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

### Coding:

BER-TI V	Ω1	ივ	01	12	00	82	02	82	Ω1	83	Ω1	00

# 27.22.4.10.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.10.4.2 SEND SHORT MESSAGE (Support of Text Attribute – Center Alignment)

27.22.4.10.4.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.10.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

## 27.22.4.10.4.2.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the center alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.2.4 Method of test

27.22.4.10.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.10.4.2.4.2 Procedure

# Expected Sequence 4.2 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Center Alignment, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.2.1	
2	$ME \rightarrow UICC$		
3			[packing not required, SMS default alphabet]
	0100 → IVIL	SHORT MESSAGE 4.2.1	[packing not required, Owle deliadit alphabet]
4	$ME \to USER$	Display "Text Attribute 1"	[Message shall be formatted with center alignment]
5	$ME \to USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	, , , ,	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1	[Command performed successfully]
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.2.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.2	[packing not required, SMS default alphabet]
11	$ME \to USER$	Display "Text Attribute 2"	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place]
12	$ME \to USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	$USS \to ME$	SMS RP-ACK	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1	[Command performed successfully]

# PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1

TP-UD " "
Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough

Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	01	B4		

### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.2

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0
TP-UDL 1
TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

#### Coding:

	~ 4	00	•	40	9	00		00	- 4		•	
BER-TLV:	l 21		I 01	I 1′≺	00		02	1 27	l 21	ม	∩1	00
	1 01	00		10	00	02	02	02	01	ೲ		1 00

## 27.22.4.10.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

27.22.4.10.4.3 SEND SHORT MESSAGE (Support of Text Attribute – Right Alignment)

27.22.4.10.4.3.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.10.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

# 27.22.4.10.4.3.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the right alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.3.4 Method of test

# 27.22.4.10.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.10.4.3.4.2 Procedure

# Expected Sequence 4.3 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Right Alignment, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 4.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
		SHORT MESSAGE 4.3.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with right alignment]
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.3.1	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
9	ME → UICC	MESSAGE 4.3.2 FETCH	
	/ 0.00	. = . *	[nasking pat required CMC default alphabat]
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.2	[packing not required, SMS default alphabet]
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted without right
			alignment. Remark: If right alignment is the
			ME"s default alignment as declared in table
			A.2/11, no alignment change will take place]
12	$ME \to USS$	Send SMS-PP (SEND SHORT	
40	1100 145	MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1	[Command performed successfully]

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.1

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1 TP-UD " "
Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough

Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
_	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	02	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.2

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00

# 27.22.4.10.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

27.22.4.10.4.4 SEND SHORT MESSAGE (Support of Text Attribute – Large Font Size)

27.22.4.10.4.4.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.10.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

# 27.22.4.10.4.4.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the large font size text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.4.4 Method of test

#### 27.22.4.10.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

# 27.22.4.10.4.4.4.2 Procedure

# Expected Sequence 4.4 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Large Font Size, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT MESSAGE 4.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1	[packing not required, SMS default alphabet]
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with large font size]
5	$ME \to USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	5.251
6	$USS \to ME$	SMS RP-ACK	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.2	[packing not required, SMS default alphabet]
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	$ME \to USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	S.E.G.
13	$USS \to ME$	SMS RP-ACK	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1	[packing not required, SMS default alphabet]
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with large font size]
19	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
20	$USS \to ME$	SMS RP-ACK	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.3	[packing not required, SMS default alphabet]
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
27	$USS \to ME$	SMS RP-ACK	
28	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1

TP-UD " "
Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	04	B4		

### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.2

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.3

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

# TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00	1
----------	----	----	----	----	----	----	----	----	----	----	----	----	---

## 27.22.4.10.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.10.4.5 SEND SHORT MESSAGE (Support of Text Attribute – Small Font Size)

27.22.4.10.4.5.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.10.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

# 27.22.4.10.4.5.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the small font size text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.5.4 Method of test

#### 27.22.4.10.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

# 27.22.4.10.4.5.4.2 Procedure

# Expected Sequence 4.5 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Small Font Size, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
2	ME → UICC	MESSAGE 4.5.1 FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
	OIGG / WIE	SHORT MESSAGE 4.5.1	[[pasiming not required, eme delacin alphaeet]
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with small font
_	ME LIGO	Card CMC DD (CEND CLIODT	size]
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.5.1	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT MESSAGE 4.5.2	
9	ME → UICC	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
		SHORT MESSAGE 4.5.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	Sizej
		MESSAGE) Message 4.1	
13	$USS \to ME$	SMS RP-ACK	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
15	$UICC \to ME$	SHORT MESSAGE 4.5.1 PROACTIVE COMMAND	
	0100 → IVIL	PENDING: SEND SHORT	
		MESSAGE 4.5.1	
16	ME → UICC	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with small font
			size]
19	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	
20	$USS \to ME$	MESSAGE) Message 4.1 SMS RP-ACK	
21	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
	, , G.GG	SHORT MESSAGE 4.5.1	[[
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
23	ME → UICC	MESSAGE 4.5.3 FETCH	
24	$VICC \rightarrow ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
	3.00 /	SHORT MESSAGE 4.5.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with normal font
26	ME LISS	Send SMS-PP (SEND SHORT	size]
26	$ME \rightarrow USS$	MESSAGE) Message 4.1	
27	$USS \to ME$	SMS RP-ACK	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.5.1	

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1

TP-UD " "
Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	08	B4		

### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.2

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1

TP-UD " "
Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.3

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

# 27.22.4.10.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.10.4.6 SEND SHORT MESSAGE (Support of Text Attribute – Bold On)

27.22.4.10.4.6.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.10.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

## 27.22.4.10.4.6.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the bold text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.6.4 Method of test

#### 27.22.4.10.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

# 27.22.4.10.4.6.4.2 Procedure

# Expected Sequence 4.6 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Bold On, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 4.6.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
4	ME → USER	SHORT MESSAGE 4.6.1 Display "Text Attribute 1"	[Message shall be formatted with bold on]
5	ME → USS	Send SMS-PP (SEND SHORT	[Message shall be formatted with bold on]
3	IVIE → USS	MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
	, 5.55	SHORT MESSAGE 4.6.1	[
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
_		MESSAGE 4.6.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
11	ME LICED	SHORT MESSAGE 4.6.2	[Mossage shall be formatted with held off]
12	$\begin{array}{c} ME \to USER \\ ME \to USS \end{array}$	Display "Text Attribute 2" Send SMS-PP (SEND SHORT	[Message shall be formatted with bold off]
12	IVIE → USS	MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
	, 5.55	SHORT MESSAGE 4.6.1	,,
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 4.6.1	
16	ME → UICC	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with bold on]
19	ME → USS	Send SMS-PP (SEND SHORT	[message shall be formatted with bold on]
	WL 7000	MESSAGE) Message 4.1	
20	$USS \to ME$	SMS RP-ACK	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.6.1	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
22	ME	MESSAGE 4.6.3	
23 24	ME → UICC	FETCH PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
24	$UICC \to ME$	SHORT MESSAGE 4.6.3	[packing not required, SiviS default alphabet]
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with bold off]
26	ME → USS	Send SMS-PP (SEND SHORT	[sssage ones se formation with bold on]
	/ 000	MESSAGE) Message 4.1	
27	$USS \to ME$	SMS RP-ACK	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.6.1	

# PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 1"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	10	B4		

# PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.2

### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1 TP-UD " '

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.3

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1 TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00

### 27.22.4.10.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.10.4.7 SEND SHORT MESSAGE (Support of Text Attribute – Italic On)

27.22.4.10.4.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.10.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

# 27.22.4.10.4.7.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the italic text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.7.4 Method of test

27.22.4.10.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

# 27.22.4.10.4.7.4.2 Procedure

# Expected Sequence 4.7 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Italic On, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 4.7.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
4	ME → USER	SHORT MESSAGE 4.7.1 Display "Text Attribute 1"	[Message shall be formatted with italic on]
5	ME → USS	Send SMS-PP (SEND SHORT	[Message shall be formatted with italic on]
3	IVIE → USS	MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.7.1	, , , , , , , , , , , , , , , , , , , ,
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 4.7.2	
9	ME → UICC	FETCH	[
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with italic off]
12	ME → USS	Send SMS-PP (SEND SHORT	[INCSSage shall be formatted with Italie on]
'-	WE 7 000	MESSAGE) Message 4.1	
13	$USS \to ME$	SMS RP-ACK	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.7.1	
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
16	ME LUCC	MESSAGE 4.7.1 FETCH	
17	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
17		SHORT MESSAGE 4.7.1	[packing not required, Sivio default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with italic on]
19	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 4.1	
20	$USS \to ME$	SMS RP-ACK	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
00		SHORT MESSAGE 4.7.1	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT	
		MESSAGE 4.7.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
	· ···-	SHORT MESSAGE 4.7.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with italic off]
26	$ME \to USS$	Send SMS-PP (SEND SHORT	
		MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.7.1	

# PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	20	B4		

# PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.2

### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1 TP-UD ""

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.3

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0
TP-UDL 1
TP-UD ""

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
·	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1

Logically:

Command details

Command number:

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
DEIX IEV.	01	00	01	13	00	02	02	02	01	00	01	00

#### 27.22.4.10.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

27.22.4.10.4.8 SEND SHORT MESSAGE (Support of Text Attribute – Underline On)

27.22.4.10.4.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.10.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

# 27.22.4.10.4.8.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the underline text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.8.4 Method of test

27.22.4.10.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

# 27.22.4.10.4.8.4.2 Procedure

# Expected Sequence 4.8 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Underline On, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
2	ME → UICC	MESSAGE 4.8.1 FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
	Oldo / WIE	SHORT MESSAGE 4.8.1	[[pasiming not required, eme derican dipriored]
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with underline
_		0 10140 55 (05115 011057	on]
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.8.1	, , , , , , , , , , , , , , , , , , , ,
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT MESSAGE 4.8.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
		SHORT MESSAGE 4.8.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with underline
12	$ME \to USS$	Send SMS-PP (SEND SHORT	off]
12	IVIE → USS	MESSAGE) Message 4.1	
13	$USS \to ME$	SMS RP-ACK	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
4-		SHORT MESSAGE 4.8.1	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT	
		MESSAGE 4.8.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
40		SHORT MESSAGE 4.8.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with underline on]
19	$ME \to USS$	Send SMS-PP (SEND SHORT	
	/ 555	MESSAGE) Message 4.1	
20	$USS \to ME$	SMS RP-ACK	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
22	$UICC \to ME$	SHORT MESSAGE 4.8.1 PROACTIVE COMMAND	
22		PENDING: SEND SHORT	
		MESSAGE 4.8.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
25	$ME \rightarrow USER$	SHORT MESSAGE 4.8.3 Display "Text Attribute 3"	Message shall be formatted with underline
23	IVIE → USER	Display Text Attribute 3	off]
26	$ME \to USS$	Send SMS-PP (SEND SHORT	1
		MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	[Common dispersion of 11.3]
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1	[Command performed successfully]
	L	OFFICIAL MILOUAGE 4.0.1	

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	40	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.2

### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.3

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1

Logically:

Command details

Command number: 1

SEND SHORT MESSAGE Command type: Command qualifier:

packing not required

Device identities

ME Source device: Destination device: **UICC** 

Result

General Result: Command performed successfully

Coding:

#### 27.22.4.10.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

27.22.4.10.4.9 SEND SHORT MESSAGE (Support of Text Attribute – Strikethrough On)

27.22.4.10.4.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.9.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the strikethrough text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.9.4 Method of test

#### 27.22.4.10.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.9.4.2 Procedure

# Expected Sequence 4.9 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Strikethrough On, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
2	ME → UICC	MESSAGE 4.9.1 FETCH	
3	$   ME \rightarrow 0   CC $ $   U CC \rightarrow ME $	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
3		SHORT MESSAGE 4.9.1	[packing not required, Sivio default alphabet]
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with
			strikethrough on]
5	$ME \to USS$	Send SMS-PP (SEND SHORT	3 1
		MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.9.1	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT	
		MESSAGE 4.9.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
		SHORT MESSAGE 4.9.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with
			strikethrough off]
12	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	
12	$USS \to ME$	MESSAGE) Message 4.1 SMS RP-ACK	
13 14	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
'-	INIE → OICC	SHORT MESSAGE 4.9.1	[Command performed successfully]
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 4.9.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
18	ME LICED	SHORT MESSAGE 4.9.1	[Massage shall be formatted with
10	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with strikethrough on]
19	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	Striket ilough on
		MESSAGE) Message 4.1	
20	$USS \to ME$	SMS RP-ACK	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SHORT MESSAGE 4.9.1	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
23	ME → UICC	MESSAGE 4.9.3 FETCH	
23	$UICC \to ME$	PROACTIVE COMMAND: SEND	[packing not required, SMS default alphabet]
~.	JIJJ → IVIL	SHORT MESSAGE 4.9.3	[Fasting flot required, Sine doladit dipridibit]
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with
1			strikethrough off]
26	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT	
0.7	1100 145	MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	[Command parformed consected to 1
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	80	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.2

### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.3

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0
TP-UDL 1
TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

### TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01	13 00 8		81 83	01 00
-------------------	---------	--	-------	-------

# 27.22.4.10.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.10.4.10 SEND SHORT MESSAGE (Support of Text Attribute – Foreground and Background Colour)

27.22.4.10.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.10.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the foreground and background colour text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.10.4 Method of test

# 27.22.4.10.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

# 27.22.4.10.4.10.4.2 Procedure

# Expected Sequence 4.10 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Foreground and Background Colour, packing not required, SMS default alphabet, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 4.10.1	
2	1112 / 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.1	[packing not required, SMS default alphabet]
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with foreground and background colour according to text attribute configuration]
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1	[Command performed successfully]
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.10.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.2	[packing not required, SMS default alphabet]
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with ME"s default foreground and background colour]
12	$ME \to USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	$USS \to ME$	SMS RP-ACK	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1	[Command performed successfully]

# PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1 TP-UD " " Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.2

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class 0 TP-UDL 1

TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
-	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME Destination device: UICC Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
	•			. •			~-		<b>.</b>		• .	

#### 27.22.4.10.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

#### 27.22.4.10.5 SEND SHORT MESSAGE (UCS2 display in Chinese)

27.22.4.10.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.10.5.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.5.4 Method of test

#### 27.22.4.10.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.5.4.2 Procedure

# Expected Sequence 5.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data in Chinese))

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
	ME	MESSAGE 5.1.1	
2 3	ME → UICC	FETCH PROACTIVE COMMAND: SEND	[packing not required, 16-bit data]
3	$UICC \to ME$	SHORT MESSAGE 5.1.1	[packing not required, 16-bit data]
4	ME → USER	Display "中一"	[Alpha Identifier]
			"Middle 1" in Chinese, 0x80 coding of UCS2 format
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 5.1	
6	$USS \to ME$	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1	[Command performed successfully]
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.2	
10	$ME \rightarrow UICC$	FETCH	
11	$UICC \to ME$	PROACTIVE COMMAND SEND SHORT MESSAGE 5.1.2	
12	$ME \rightarrow USER$	Display "中一"	[Alpha Identifier] "Middle 1" in Chinese, 0x81 coding of UCS2 format
13	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 5.1	
14	$USS \to ME$	SMS RP-ACK	
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1	[Command performed successfully]
16	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
17	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.3	
18	$ME \rightarrow UICC$	FETCH	
19	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 5.1.3	[UCS2 alphabet]
20	$ME \rightarrow USER$	Display "中一"	[Alpha Identifier] "Middle 1" in Chinese, 0x82 coding of UCS2 format
21	$ME \to USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 5.1	
22	$USS \to ME$	SMS RP-ACK	
23	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
24	$UICC \to ME$	SHORT MESSAGE 5.1.1 PROACTIVE UICC SESSION ENDED	

PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "中一"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

**TP-DCS** 

Message coding 16-bit data Message class class 0 TP-UDL 24 TP-UD "中一"

#### Coding:

BER-TLV:	D0	2D	81	03	01	13	00	82	02	81	83	85
	05	80	4E	2D	4E	00	86	09	91	11	22	33
	44	55	66	77	F8	8B	10	01	00	09	91	10
	32	54	76	F8	40	08	04	4E	2D	4E	00	

## SMS-PP (SEND SHORT MESSAGE) Message 5.1

# Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding UCS2 (16-bit data)

 $\begin{array}{ll} \text{Message class} & \text{class 0} \\ \text{TP-UDL} & 24 \\ \text{TP-UD} & " \not \!\!\! + - " \end{array}$ 

#### Coding:

BER-TLV:	01	01	09	91	10	32	54	76	F8	40	08	04
	4E	2D	4E	00								

#### PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.2

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "中一"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 16-bit data
Message class class 0
TP-UDL 24
TP-UD "中一"

#### Coding:

BER-TLV:	D0	2D	81	03	01	13	00	82	02	81	83	85
	05	81	02	9C	AD	80	86	09	91	11	22	33
	44	55	66	77	F8	8B	10	01	00	09	91	10
	32	54	76	F8	40	80	04	4E	2D	4E	00	

#### PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.3

### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "中一"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 16-bit data
Message class class 0
TP-UDL 24
TP-UD "中一"

#### Coding:

BER-TLV:	D0	2E	81	03	01	13	00	82	02	81	83	85
	06	82	02	4E	00	AD	80	86	09	91	11	22
	33	44	55	66	77	F8	8B	10	01	00	09	91
	10	32	54	76	F8	40	08	04	4E	2D	4E	00

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

# Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00

## 27.22.4.10.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

#### 27.22.4.10.6 SEND SHORT MESSAGE (UCS2 display in Katakana)

# 27.22.4.10.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

# 27.22.4.10.6.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.6.4 Method of test

27.22.4.10.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.6.4.2 Procedure

# Expected Sequence 6.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data, in Katakana))

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SHORT	
		MESSAGE 6.1.1	
2	ME → UICC	FETCH	[and in a part of social AC bit data]
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.1	[packing not required, 16-bit data]
4	$ME \rightarrow USER$		[Characters in katakana]
5	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 6.1	
6	$USS \to ME$	SMS RP-ACK	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1	[Command performed successfully]
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.2	
10	$ME \rightarrow UICC$	FETCH	
11	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.2	[packing not required, 16-bit data]
12	$ME \rightarrow USER$	Display "81./レ1"	[Characters in katakana]
13	$ME \to USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 6.2	
14	$USS \to ME$	SMS RP-ACK	
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1	[Command performed successfully]
16	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
17	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.3	
18	$ME \rightarrow UICC$	FETCH	
19	$UICC \to ME$	PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.3	[packing not required, 16-bit data]
20	$ME \rightarrow USER$	Display "82ル2"	[Characters in katakana]
21	$ME \rightarrow USS$	Send SMS-PP (SEND SHORT MESSAGE) Message 6.3	
22	$USS \to ME$	SMS RP-ACK	
23	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1	[Command performed successfully]
24	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	

# PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.1

# Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "80/\(\nu\)0"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept a SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 16-bit data Message class class 0 TP-UDL 10 TP-UD "80/ $\nu$ 1"

#### Coding:

BER-TLV:	D0	35	81	03	01	13	00	82	02	81	83	85
	09	80	00	38	00	30	30	EB	00	30	86	09
	91	11	22	33	44	55	66	77	F8	8B	14	01
	00	09	91	10	32	54	76	F8	40	08	08	00
	38	00	30	30	EB	00	31					

#### SMS-PP (SEND SHORT MESSAGE) Message 6.1

#### Logically:

**SMS TPDU** 

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding UCS2 (16-bit data)

Message class 0 TP-UDL 10 TP-UD "80/\(\nu\)1"

## Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	08	80
	00	38	00	30	30	EB	00	31				

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 13	00 82 02	82 81	83 01 00
----------------------	----------	-------	----------

# PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.2

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "81/\(\bu\)1"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept a SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

**TP-DCS** 

Message coding 16-bit data
Message class class 0
TP-UDL 10
TP-UD "80/\(\nu\)2"

Coding:

BER-TLV:	D0	33	81	03	01	13	00	82	02	81	83	85
	07	81	04	61	38	31	EB	31	86	09	91	11
	22	33	44	55	66	77	F8	8B	14	01	00	09
	91	10	32	54	76	F8	40	08	08	00	38	00
	30	30	FR	00	32							

### SMS-PP (SEND SHORT MESSAGE) Message 6.2

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

Instruct the SC to accept an SMS-SUBMIT for a SM TP-RD

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

A status report is not requested **TP-SRR** 

"01" TP-MR

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding UCS2 (16-bit data)

Message class class 0 TP-UDL 10 "80ル2" TP-UD

#### Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	80	08
	00	38	00	30	30	EB	00	32				

#### PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.3

### Logically:

Command details

Command number:

SEND SHORT MESSAGE Command type: packing not required

Command qualifier:

Device identities

Source device: **UICC** Destination device: Network Alpha identifier: "82ル2"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

"112233445566778" Dialling number string

**SMS TPDU** 

TP-MTI **SMS-SUBMIT** 

TP-RD Instruct the SC to accept a SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

"012345678" Address value

TP-PID Short message type 0

**TP-DCS** 

Message coding 16-bit data class 0 Message class TP-UDL 10 "80ル3" TP-UD

#### Coding:

BER-TLV:	D0	34	81	03	01	13	00	82	02	81	83	85
	08	82	04	30	A0	38	32	CB	32	86	09	91
	11	22	33	44	55	66	77	F8	8B	14	01	00
	09	91	10	32	54	76	F8	40	08	08	00	38
	00	30	30	EB	00	33						

#### SMS-PP (SEND SHORT MESSAGE) Message 6.3

### Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding UCS2 (16-bit data)

Message class 0
TP-UDL 10
TP-UD "80/\(\partial 3\)"

#### Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	80	80
	00	38	00	30	30	EB	00	33				

# 27.22.4.10.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

#### 27.22.4.11 SEND SS

# 27.22.4.11.1 SEND SS (normal)

#### 27.22.4.11.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.11.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.1.3 Test purpose

To verify that the ME correctly translates and sends the supplementary service request indicated in the SEND SS proactive UICC command to the USS.

To verify that the ME returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the SS and any contents of the SS result as additional data.

#### 27.22.4.11.1.4 Method of test

#### 27.22.4.11.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.1.4.2 Procedure

# Expected Sequence 1.1A (SEND SS, call forward unconditional, all bearers, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 1.1.1	
4	$ME \rightarrow USER$	Display "Call Forward"	
5	$ME \to USS$	REGISTER 1.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 1.1A	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND	
		SS 1.1.1A	

#### Expected Sequence 1.1B (SEND SS, call forward unconditional, all bearers, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 1.1.1	
4	$ME \rightarrow USER$	Display "Call Forward"	
5	$ME \rightarrow USS$	REGISTER 1.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 1.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 1.1.1B	

#### PROACTIVE COMMAND: SEND SS 1.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Call Forward"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

# Coding:

BER-TLV:	D0	29	81	03	01	11	00	82	02	81	83	85
	0C	43	61	6C	6C	20	46	6F	72	77	61	72
	64	89	10	91	AA	12	0A	21	43	65	87	09
	21	43	65	87	A9	01	FB					

#### **REGISTER 1.1A**

Logically (only SS argument):

#### REGISTER SS ARGUMENT

SS-Code:

- Call Forwarding Unconditional

TeleserviceCode

- All Tele Services

ForwardedToNumber

- nature of address ind.: international

numbering plan ind.: ISDN/Telephony (E.164)
 TBCD String: 01234567890123456789

- longFTN-Supported

#### Coding:

BER-TLV	30	15	04	01	21	83	01	00	84	0B	91	10
_	32	54	76	98	10	32	54	76	98	89	00	

#### **REGISTER 1.1B**

Logically (only SS argument):

#### REGISTER SS ARGUMENT

SS-Code:

- Call Forwarding Unconditional

TeleserviceCode

- All Tele Services

Forwarded To Number

- nature of address ind.: international

numbering plan ind.: ISDN/Telephony (E.164)
 TBCD String: 01234567890123456789

Coding:

BER-TLV	30	13	04	01	21	83	01	00	84	0B	91	10
	32	54	76	98	10	32	54	76	98			

# RELEASE COMPLETE (SS RETURN RESULT) 1.1A

Logically (only from operation code):

#### REGISTER SS RETURN RESULT

Forwarding Info

SS-Code

- Call Forwarding Unconditional

ForwardFeatureList

ForwardingFeature

TeleserviceCode

- All Tele Services

SS-Status

- state ind.: operative

provision ind.: provisionedregistration ind.: registered

- activation ind .: active

long Forward ed To Number

- nature of address ind.: international

numbering plan ind.: ISDN/Telephony (E.164)TBCD String: 01234567890123456789

Coding:

Coding	0A	A0	1A	04	01	21	30	15	30	13	83	01
_	00	84	01	07	89	0B	91	10	32	54	76	98
	10	32	54	76	98							

#### RELEASE COMPLETE (SS RETURN RESULT) 1.1B

Logically (only from operation code):

# REGISTER SS RETURN RESULT

ForwardingInfo

SS-Code

- Call Forwarding Unconditional

Forward Feature List

ForwardingFeature

TeleserviceCode

- All Tele Services

SS-Status

- state ind.: operative

- provision ind.: provisioned

- registration ind.: registered

- activation ind .: active

Coding:

Coding	0A	A0	0D	04	01	21	30	80	30	06	83	01
	00	84	01	07								

#### TERMINAL RESPONSE: SEND SS 1.1.1A

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	1E
_	00	0A	A0	1A	04	01	21	30	15	30	13
	83	01	00	84	01	07	89	0B	91	10	32
	54	76	98	10	32	54	76	98			

TERMINAL RESPONSE: SEND SS 1.1.1B

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	11
	00	0A	A0	0D	04	01	21	30	80	30	06
	83	01	00	84	01	07					

# Expected Sequence 1.2 (SEND SS, call forward unconditional, all bearers, Return Error)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 1.1.1	
4	$ME \rightarrow USER$	Display "Call Forward"	
5	$ME \to USS$	REGISTER 1.1A	
		Or	
		REGISTER 1.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN ERROR) 1.1	[Return Error]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 1.2.1	

# RELEASE COMPLETE (SS RETURN ERROR) 1.1

Logically (only from error code):

Error Code: Facility not supported

Coding:

Coding 02 01 15

TERMINAL RESPONSE: SEND SS 1.2.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: SS Return Error Additional information: Error Code

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	02
_	34	15									

# Expected Sequence 1.3 (SEND SS, call forward unconditional, all bearers, Reject)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 1.1.1	
4	$ME \rightarrow USER$	Display "Call Forward"	
5	$ME \rightarrow USS$	REGISTER 1.1A	
		Or	
		REGISTER 1.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS REJECT) 1.1.	[Reject]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 1.3.1	

#### RELEASE COMPLETE (SS REJECT) 1.1

Logically (only from problem code):

Problem Code:

- General problem
- Unrecognized component

Coding:

Coding	80	01	00
--------	----	----	----

TERMINAL RESPONSE: SEND SS 1.3.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: SS Return Error

Additional information: No specific cause can be given

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	02
	34	00									

# Expected Sequence 1.4A (SEND SS, call forward unconditional, all bearers, successful, SS request size limit)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 1.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 1.4.1	
4	$ME \rightarrow USER$	Display "Call Forward"	
5	$ME \rightarrow USS$	REGISTER 1.2A	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 1.2A	[Successful]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 1.4.1A	

# Expected Sequence 1.4B (SEND SS, call forward unconditional, all bearers, successful, SS request size limit)

	Step	Direction	MESSAGE / Action	Comments
Ī	1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 1.4.1	
	2	$ME \rightarrow UICC$	FETCH	
	3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 1.4.1	
	4	$ME \rightarrow USER$	Display "Call Forward"	
	5	$ME \to USS$	REGISTER 1.2B	
	6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 1.2B	[Successful]
	7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 1.4.1B	

#### PROACTIVE COMMAND: SEND SS 1.4.1

Logically:

Command details

Command number:

Command type: SEND SS Command qualifier: "00"

Command quantier.

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Call Forward"

SS String

TON: International

NPI: "ISDN / telephone numbering plan"

SS string: "\*\*21\*0123456789012345678901234567\*11#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	0C	43	61	6C	6C	20	46	6F	72	77	61	72
	64	89	14	91	AA	12	0A	21	43	65	87	09
	21	43	65	87	09	21	43	65	A7	11	FB	

#### **REGISTER 1.2A**

Logically (only SS argument):

# REGISTER SS ARGUMENT

RegisterSSArg

SS-Code

Call Forwarding Unconditional

TeleserviceCode

See Note 1

Forwarded To Number

nature of address ind.: international

numbering plan ind.: ISDN/Telephony (E.164)

TBCD String: 0123456789012345678901234567

longFTN-Supported

# Coding:

BER-TLV	30	19	04	01	21	83	01	Note 1	84	0F	91	10
	32	54	76	98	10	32	54	76	98	10	32	54
	76	89	00									

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

**REGISTER 1.2B** 

Logically (only SS argument):

#### **REGISTER SS ARGUMENT**

Register SSArg

SS-Code

Call Forwarding Unconditional

TeleserviceCode

See Note 1

Forwarded To Number

nature of address ind.: international

numbering plan ind.: ISDN/Telephony (E.164)

TBCD String: 0123456789012345678901234567

# Coding:

BER-TLV	30	17	04	01	21	83	01	Note 1	84	0F	91	10
	32	54	76	98	10	32	54	76	98	10	32	54
	76											

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

Logically (only from operation code):

#### REGISTER SS RETURN RESULT

ForwardingInfo

SS-Code

- Call Forwarding Unconditional

Forward Feature List

ForwardingFeature

TeleserviceCode

- See Note 1

SS-Status

- state ind.: operative

- provision ind.: provisioned

- registration ind.: registered

- activation ind.: active

long Forwarded To Number

- nature of address ind .: international

- numbering plan ind.: ISDN/Telephony (E.164)

- TBCD String: 0123456789012345678901234567

#### Coding:

Coding	0A	A0	1E	04	01	21	30	19	30	17	83	01
	Note 1	84	01	07	89	0F	91	10	32	54	76	98
	10	32	54	76	98	10	32	54	76			

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

#### RELEASE COMPLETE (SS RETURN RESULT) 1.2B

Logically (only from operation code):

# REGISTER SS RETURN RESULT

ForwardingInfo

SS-Code

- Call Forwarding Unconditional

ForwardFeatureList

ForwardingFeature

TeleserviceCode

- See Note 1

SS-Status

- state ind.: operative

provision ind.: provisionedregistration ind.: registeredactive

#### Coding:

Coding	0A	A0	0D	04	01	21	30	80	30	06	83	01
	Note 1	84	01	07								

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

TERMINAL RESPONSE: SEND SS 1.4.1A

### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Additional information: Operation Code and SS Parameters

#### Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	22
	00	0A	A0	1E	04	01	21	30	19	30	17
	83	01	Note 1	84	01	07	89	0F	91	10	32
	54	76	98	10	32	54	76	98	10	32	54
	76										

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

TERMINAL RESPONSE: SEND SS 1.4.1B

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Additional information: Operation Code and SS Parameters

BER-TLV:	81	03	01	11	00	82	02	82	81	03	11
	00	0A	A0	0D	04	01	21	30	08	30	06
	83	01	Note 1	84	01	07					

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

#### Expected Sequence 1.5 (SEND SS, interrogate CLIR status, successful, alpha identifier limits)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 1.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 1.5.1	
4	$ME \rightarrow USER$	Display "Even if the Fixed Dialling Number service is	
		enabled, the supplementary service control string	
		included in the SEND SS proactive command shall not	
		be checked against those of the FDN list. Upon	
		receiving this command, the ME shall deci"	
5	$ME \to USS$	REGISTER 1.3	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 1.3	[Successful]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 1.5.1	

#### PROACTIVE COMMAND: SEND SS 1.5.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Even if the Fixed Dialling Number service is enabled, the supplementary service

control string included in the SEND SS proactive command shall not be checked against those of the FDN list. Upon receiving this command, the ME shall deci"

SS String

TON: Undefined NPI: Undefined SS string: "\*#31#"

#### Coding:

BER-TLV:	D0	81	FD	81	03	01	11	00	82	02	81	83
	85	81	EB	45	76	65	6 <sup>E</sup>	20	69	66	20	74
	68	65	20	46	69	78	65	64	20	44	69	61
	6C	6C	69	6 <sup>E</sup>	67	20	4 <sup>E</sup>	75	6D	62	65	72
	20	73	65	72	76	69	63	65	20	69	73	20
	65	6 <sup>E</sup>	61	62	6C	65	64	2C	20	74	68	65
	20	73	75	70	70	6C	65	6D	65	6E	74	61
	72	79	20	73	65	72	76	69	63	65	20	63
	6F	6E	74	72	6F	6C	20	73	74	72	69	6 <sup>E</sup>
	67	20	69	6 <sup>E</sup>	63	6C	75	64	65	64	20	69
	6E	20	74	68	65	20	53	45	4E	44	20	53
	53	20	70	72	6F	61	63	74	69	76	65	20
	63	6F	6D	6D	61	6E	64	20	73	68	61	6C
	6C	20	6E	6F	74	20	62	65	20	63	68	65
	63	6B	65	64	20	61	67	61	69	6E	73	74
	20	74	68	6F	73	65	20	6F	66	20	74	68
	65	20	46	44	4 <sup>E</sup>	20	6C	69	73	74	2 <sup>E</sup>	20
	55	70	6F	6E	20	72	65	63	65	69	76	69
	6E	67	20	74	68	69	73	20	63	6F	6D	6D
	61	6E	64	2C	20	74	68	65	20	4D	45	20
	73	68	61	6C	6C	20	64	65	63	69	89	04
	FF	BA	13	FB								

#### **REGISTER 1.3**

Logically (only SS argument):

#### INTERROGATE SS ARGUMENT

SS-Code

- Calling Line Id Restriction

Coding:

BER-TLV 30 03 04 01 12

#### RELEASE COMPLETE (SS RETURN RESULT) 1.3

Logically (only from operation code):

#### INTERROGATE SS RESULT

CliRestrictionInfo

SS-Status

- state ind.: operative

- provision ind.: provisioned

- registration ind.: registered

- activation ind.: not active

CliRestrictionOption

- Temporary Def Allowed

Coding:

Coding	0E	A4	06	04	01	06	0A	01	02
--------	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: SEND SS 1.5.1

Logically:

Command details

Command number: 1

Command type: SEND SS

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Additional information

Operation Code: SS Code

Parameters: SS Return Result

BER-TLV:	81	03	01	11	00	82	02	82	81	03	0A	
·	00	0E	A4	06	04	01	06	0A	01	02		ĺ

### Expected Sequence 1.6A (SEND SS, call forward unconditional, all bearers, successful, null data alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to$	PROACTIVE COMMAND PENDING: SEND SS 1.6.1	
	ME		
2	ME  o	FETCH	
	UICC		
3	$UICC \to$	PROACTIVE COMMAND: SEND SS 1.6.1	
	ME		
4	ME	Should not give any information to the user on the fact that	
		the ME is sending an SS request	
5	$ME \rightarrow USS$	REGISTER 1.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 1.1A	[Successful]
7	ME  o	TERMINAL RESPONSE: SEND SS 1.1.1A	
	UICC		

### Expected Sequence 1.6B (SEND SS, call forward unconditional, all bearers, successful, null data alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to$	PROACTIVE COMMAND PENDING: SEND SS 1.6.1	
	ME		
2	ME  o	FETCH	
	UICC		
3	$UICC \rightarrow$	PROACTIVE COMMAND: SEND SS 1.6.1	
	ME		
4	ME	Should not give any information to the user on the fact that	
		the ME is sending an SS request	
5		REGISTER 1.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful]
7	ME  o	TERMINAL RESPONSE: SEND SS 1.1.1B	
	UICC		

#### PROACTIVE COMMAND: SEND SS 1.6.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: null data object

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	1D	81	03	01	11	00	82	02	81	83	85
	00	89	10	91	AA	12	0A	21	43	65	87	09
	21	43	65	87	Α9	01	FB					

#### 27.22.4.11.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1 to 1.6.

27.22.4.11.2 SEND SS (Icon support)

27.22.4.11.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.11.2.2 Conformance requirement

27.22.4.11.2.3 Test purpose

To verify that the ME displays the text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

27.22.4.11.2.4 Method of test

27.22.4.11.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and to the USS. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

The elementary files are coded as Toolkit default.

#### 27.22.4.11.2.4.2 Procedure

### Expected Sequence 2.1A (SEND SS, call forward unconditional, all bearers, successful, basic icon self explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		SS 2.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 2.1.1	[BASIC-ICON, self-explanatory]
4	$ME \rightarrow USER$	Display the basic icon without the alpha identifier	
5	$ME \rightarrow USS$	REGISTER 1.1A	Option A applies if A.1/63 is
		Or	supported,
		REGISTER 1.1B	Option B applies if A.1/63 is not
_			supported
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN	[Successful]
		RESULT) 1.1A or	Option A applies if A.1/63 is
		RELEASE COMPLETE (SS RETURN	supported,
		RESULT) 1.1B	Option B applies if A.1/63 is not
			supported
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 2.1.1AA	[Command performed successfully]
		or	Option AA applies if A.1/63 is
		TERMINAL RESPONSE: SEND SS 2.1.1AB	supported,
			Option AB applies if A.1/63 is not
			supported

#### PROACTIVE COMMAND: SEND SS 2.1.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC

Destination device: Network
Alpha identifier: "Basic Icon"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Icon Identifier:

Icon qualifier: icon is self-explanatory Icon Identifier: record 1 in  $EF_{(IMG)}$ 

#### Coding:

BER-TLV:	D0	2B	81	03	01	11	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	89
	10	91	AA	12	0A	21	43	65	87	09	21	43
	65	87	A9	01	FB	9E	02	00	01			

TERMINAL RESPONSE: SEND SS 2.1.1AA

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Additional information: Operation Code and SS Parameters

#### Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	1E
	00	0A	A0	1A	04	01	21	30	15	30	13
	83	01	00	84	01	07	89	0B	91	10	32
	54	76	98	10	32	54	76	98			

TERMINAL RESPONSE: SEND SS 2.1.1AB

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Additional information: Operation Code and SS Parameters

BER-TLV:	81	03	01	11	00	82	02	82	81	03	11
	00	0A	A0	0D	04	01	21	30	80	30	06
	83	01	00	84	01	07					

### Expected Sequence 2.1B (SEND SS, call forward unconditional, all bearers, successful, basic icon self explanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 2.1.1	
2	$ME \rightarrow UICC$	_	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[BASIC-ICON, self-explanatory]
		SS 2.1.1	
4	$ME \rightarrow USER$	Display "Basic Icon" without the	
		icon	
5	$ME \rightarrow USS$	REGISTER 1.1A	Option A applies if A.1/63 is supported,
		Or	Option B applies if A.1/63 is not supported
		REGISTER 1.1B	
6	$USS \to ME$	`	[Successful]
		RETURN RESULT) 1.1A or	Option A applies if A.1/63 is supported,
		RELEASE COMPLETE (SS	Option B applies if A.1/63 is not supported
_		RETURN RESULT) 1.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully, but
		SS 2.1.1BA or	requested icon could not be displayed]
		TERMINAL RESPONSE: SEND	Option BA applies if A.1/63 is supported,
		SS 2.1.1BB	Option BB applies if A.1/63 is not supported

TERMINAL RESPONSE: SEND SS 2.1.1BA

Logically:

Command details

Command number:

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:

81	03	01	11	00	82	02	82	81	03	1E
04	0A	A0	1A	04	01	21	30	15	30	13
83	01	00	84	01	07	89	0B	91	10	32
54	76	98	10	32	54	76	98			

TERMINAL RESPONSE: SEND SS 2.1.1BB

Logically:

Command details

Command number: 1 Command type: SEND SS

Command type: SEND S
Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Additional information: Operation Code and SS Parameters

BER-TLV:

81	03	01	11	00	82	02	82	81	03	11
04	0A	A0	0D	04	01	21	30	80	30	06
83	01	00	84	01	07					

### Expected Sequence 2.2A (SEND SS, call forward unconditional, all bearers, successful, colour icon self explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 2.2.1	
2	/ 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[COLOUR-ICON, self-explanatory]
		SS 2.2.1	
4		Display the colour icon without	
		thealpha identifier	
5	$ME \rightarrow USS$	REGISTER 1.1A	Option A applies if A.1/63 is supported,
		Or	Option B applies if A.1/63 is not supported
		REGISTER 1.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 1.1A or	Option A applies if A.1/63 is supported,
		RELEASE COMPLETE (SS	Option B applies if A.1/63 is not supported
		RETURN RESULT) 1.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SS 2.1.1AA or	Option AA applies if A.1/63 is supported,
		TERMINAL RESPONSE: SEND	Option AB applies if A.1/63 is not supported
		SS 2.1.1AB	

PROACTIVE COMMAND: SEND SS 2.2.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Colour Icon"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Icon Identifier:

 $\begin{array}{ll} \text{Icon qualifier:} & \text{icon is self-explanatory} \\ \text{Icon Identifier:} & \text{record 2 in } EF_{\text{(IMG)}} \\ \end{array}$ 

BER-TLV:	D0	2C	81	03	01	11	00	82	02	81	83	85
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	89	10	91	AA	12	0A	21	43	65	87	09	21
	43	65	87	Α9	01	FB	9F	02	00	02		

### Expected Sequence 2.2B (SEND SS, call forward unconditional, all bearers, successful, colour icon self explanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 2.2.1	
2	$ME \rightarrow UICC$	_	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[COLOUR-ICON, self-explanatory]
		SS 2.2.1	
4	$ME \rightarrow USER$	Display "Colour Icon" without the	
		icon	
5	$ME \rightarrow USS$	REGISTER 1.1A	Option A applies if A.1/63 is supported,
		Or	Option B applies if A.1/63 is not supported
_		REGISTER 1.1B	
6	$USS \to ME$	,	[Successful]
		RETURN RESULT) 1.1A or	Option A applies if A.1/63 is supported,
		RELEASE COMPLETE (SS	Option B applies if A.1/63 is not supported
		RETURN RESULT) 1.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed but requested icon
		SS 2.1.1BA or	could not be displayed]
		TERMINAL RESPONSE: SEND	Option BA applies if A.1/63 is supported,
		SS 2.1.1BB	Option BB applies if A.1/63 is not supported

### Expected Sequence 2.3A (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 2.3.1	
2	WIL / 0100	FETCH	
3	$UICC \to ME$		[BASIC-ICON, non self-explanatory]
		SS 2.3.1	
4	$ME \rightarrow USER$	Display "Basic Icon" and the basic	
_		icon	
5	$ME \rightarrow USS$	REGISTER 1.1A	Option A applies if A.1/63 is supported,
		Or	Option B applies if A.1/63 is not supported
		REGISTER 1.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 1.1A or	Option A applies if A.1/63 is supported,
		RELEASE COMPLETE (SS	Option B applies if A.1/63 is not supported
		RETURN RESULT) 1.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SS 2.1.1AA or	Option AA applies if A.1/63 is supported,
		TERMINAL RESPONSE: SEND	Option AB applies if A.1/63 is not supported
		SS 2.1.1AB	

#### PROACTIVE COMMAND: SEND SS 2.3.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Text: "Basic Icon"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Icon Identifier

Icon qualifier: icon is non self-explanatory

Icon Identifier: record 1 in  $EF_{(IMG)}$ 

Coding:

BER-TLV:	D0	2B	81	03	01	11	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	89
	10	91	AA	12	0A	21	43	65	87	09	21	43
	65	87	A9	01	FB	9E	02	01	01			

### Expected Sequence 2.3B (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 2.3.1	
2	$ME \rightarrow UICC$		
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[BASIC-ICON, non self-explanatory]
		SS 2.3.1	
4	$ME \rightarrow USER$	Display "Basic Icon" without the	
		icon	
5	$ME \rightarrow USS$	REGISTER 1.1A	Option A applies if A.1/63 is supported,
		Or	Option B applies if A.1/63 is not supported
		REGISTER 1.1B	[Cuasastul]
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 1.1A or	Option A applies if A.1/63 is supported,
		RELEASE COMPLETE (SS	Option B applies if A.1/63 is not supported
_		RETURN RESULT) 1.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed but requested icon
		SS 2.1.1BA or	could not be displayed]
		TERMINAL RESPONSE: SEND	Option BA applies if A.1/63 is supported,
		SS 2.1.1BB	Option BB applies if A.1/63 is not supported

### Expected Sequence 2.4 (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory, no alpha identifier presented)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to$	PROACTIVE COMMAND PENDING:	
	ME	SEND SS 2.4.1	
2	ME  o	FETCH	
	UICC		
3	$UICC \to$	PROACTIVE COMMAND: SEND SS 2.4.1	[BASIC-ICON, non self-explanatory]
	ME		
4	ME  o	TERMINAL RESPONSE: SEND SS 2.4.1	[Command data not understood by ME]
	UICC		

PROACTIVE COMMAND: SEND SS 2.4.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789#"

Icon Identifier

Icon qualifier: icon is non self-explanatory

Icon Identifier: record 1 in  $EF_{(IMG)}$ 

Coding:

BER-TLV:	D0	1D	81	03	01	11	00	82	02	81	83	89
	0E	91	AA	12	0A	21	43	65	87	09	21	43
	65	87	B9	9E	02	01	01					

TERMINAL RESPONSE: SEND SS 2.4.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command data not understood by ME

Coding:

	BER-TLV:	81	03	01	11	00	82	02	82	81	83	01	32
--	----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.11.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1A to 2.4.

#### 27.22.4.11.3 SEND SS (UCS2 display in Cyrillic)

#### 27.22.4.11.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.3.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionnally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.11.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.3.4 Method of test

#### 27.22.4.11.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.3.4.2 Procedure

#### Expected Sequence 3.1 (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Cyrillic)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 3.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 3.1.1	
4	$ME \rightarrow USER$	Display "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
5	$ME \rightarrow USS$	REGISTER 1.1A	Option A applies if A.1/63 is supported,
		Or	Option B applies if A.1/63 is not supported
		REGISTER 1.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 1.1A or	Option A applies if A.1/63 is supported,
		RELEASE COMPLETE (SS	Option B applies if A.1/63 is not supported
		RETURN RESULT) 1.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SS 1.1.1A or	Option A applies if A.1/63 is supported,
		TERMINAL RESPONSE: SEND	Option B applies if A.1/63 is not supported
		SS 1.1.1B	

#### PROACTIVE COMMAND: SEND SS 3.1.1

#### Logically:

Command details

Command number:

SEND SS Command type:

Command qualifier:

"00"

Device identities

**UICC** Source device: Network

Destination device:

Alpha Identifier

Data coding scheme: UCS2 (16bit)

Text: "ЗДРАВСТВУЙТЕ"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" "\*\*21\*01234567890123456789\*10#" SS string:

#### Coding:

BER-TLV:	D0	36	81	03	01	11	00	82	02	81	83	85
_	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	89	10	91	AA	12	0A	21	43	65	87
	09	21	43	65	87	A9	01	FB				

#### 27.22.4.11.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

#### 27.22.4.11.4 SEND SS (support of Text Attribute)

27.22.4.11.4.1 SEND SS (support of Text Attribute – Left Alignment)

#### 27.22.4.11.4.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.1.3 Test purpose

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.1.4 Method of test

#### 27.22.4.11.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.4.1.4.2 Procedure

## Expected Sequence 4.1A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.1.1	
4		Display "Text Attribute 1"	[Message shall be formatted with left alignment]
5	$ME \to USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND	
9	ME  o UICC	PENDING: SEND SS 4.1.2	
_			
10	UICC → ME	PROACTIVE COMMAND: SEND ISS 4.1.2	
11	ME → USER		[Message shall be formatted with left
'''	IVIE → USEK	Display Text Attribute 2	alignment. Remark: If left alignment is the
			ME"s default alignment as declared in table
			A.2/12, no alignment change will take place]
12	$ME \to USS$	REGISTER 4.1A	, 23 2 2 2 3 3 2 2 3 3 3 3 3 3 3 3 3 3 3
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	-
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	

### Expected Sequence 4.1B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.1.1	
2	$ME \rightarrow UICC$	FETCH	
3		PROACTIVE COMMAND: SEND SS 4.1.1	
4		Display "Text Attribute 1"	[Message shall be formatted with left alignment]
5	$ME \to USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.1.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.1.2	
11	$ME \to USER$	Display "Text Attribute 2"	[Message shall be formatted with left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place]
12	$ME \to USS$	REGISTER 4.1B	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

#### PROACTIVE COMMAND: SEND SS 4.1.2

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

#### Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	Α9	01	FB	

#### **REGISTER 4.1A**

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

**REGISTER 4.1B** 

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1B

RELEASE COMPLETE (SS RETURN RESULT) 4.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

RELEASE COMPLETE (SS RETURN RESULT) 4.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

TERMINAL RESPONSE: SEND SS 4.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

TERMINAL RESPONSE: SEND SS 4.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

27.22.4.11.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.11.4.2 SEND SS (support of Text Attribute – Center Alignment)

27.22.4.11.4.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.11.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.2.3 Test purpose

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.11.4.2.4 Method of test

27.22.4.11.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.4.2.4.2 Procedure

## Expected Sequence 4.2A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.2.1	
2	$ME \rightarrow UICC$		
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.2.1	
4		Display "Text Attribute 1"	[Message shall be formatted with center alignment]
5	$ME \rightarrow USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND	
9	ME LUCC	PENDING: SEND SS 4.2.2	
_	ME → UICC		
10	OICC → ME	PROACTIVE COMMAND: SEND ISS 4.2.2	
11	ME → USER		[Message shall be formatted with center
''	IVIE → USER	Display Text Attribute 2	alignment. Remark: If center alignment is the
			ME"s default alignment as declared in table
			A.2/12, no alignment change will take place]
12	$ME \rightarrow USS$	REGISTER 4.1A	
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	,
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	

### Expected Sequence 4.2B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.2.1	
4	$ME \to USER$	Display "Text Attribute 1"	[Message shall be formatted with center alignment]
5	$ME \to USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.2.2	
9	$ME \rightarrow UICC$		
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.2.2	
11	$ME \to USER$	Display "Text Attribute 2"	[Message shall be formatted with center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place]
12	$ME \to USS$	REGISTER 4.1B	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.2.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough

Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	01	B4							

#### PROACTIVE COMMAND: SEND SS 4.2.2

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

#### Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

27.22.4.11.4.3 SEND SS (support of Text Attribute – Right Alignment)

27.22.4.11.4.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.3.3 Test purpose

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.3.4 Method of test

#### 27.22.4.11.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.4.3.4.2 Procedure

### Expected Sequence 4.3A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.3.1	
2	11.12	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.3.1	
4		Display "Text Attribute 1"	[Message shall be formatted with right alignment]
5	$ME \to USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND	
,	IVIE → UICC	ISS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.3.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.3.2	
11	$ME \to USER$	Display "Text Attribute 2"	[Message shall be formatted with right
			alignment. Remark: If right alignment is the
			ME"s default alignment as declared in table
12	ME LISS	REGISTER 4.1A	A.2/12, no alignment change will take place]
13	USS → ME	RELEASE COMPLETE (SS	[Successful]
13	USS → IVIE	RETURN RESULT) 4.1A	[Ouccessial]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
	WE / 0100	SS 4.1.1A	

### Expected Sequence 4.3B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.3.1	
2	, 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.3.1	
4		Display "Text Attribute 1"	[Message shall be formatted with right alignment]
5	$ME \rightarrow USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	MF → UICC	TERMINAL RESPONSE: SEND	
	, 5.55	SS 4.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.3.2	
9	$ME \rightarrow UICC$		
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.3.2	
11	ME → USER		Message shall be formatted with right
''	IVIL -> USLIX	Display Text Attribute 2	alignment. Remark: If right alignment is the
			ME"s default alignment as declared in table
			A.2/12, no alignment change will take place]
12	$ME \rightarrow USS$	REGISTER 4.1B	
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1B	

#### PROACTIVE COMMAND: SEND SS 4.3.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough

Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	02	B4							

PROACTIVE COMMAND: SEND SS 4.3.2

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

#### Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

27.22.4.11.4.4 SEND SS (support of Text Attribute – Large Font Size)

27.22.4.11.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.4.3 Test purpose

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.4.4 Method of test

#### 27.22.4.11.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.4.4.4.2 Procedure

# Expected Sequence 4.4A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.4.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with large font size]
5	$ME \rightarrow USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.4.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.4.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	$ME \rightarrow USS$	REGISTER 4.1A	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND SS 4.1.1A	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.4.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.4.1	
18	$ME \rightarrow USER$		[Message shall be formatted with large font size]
19	$ME \rightarrow USS$	REGISTER 4.1A	_
20	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND SS 4.1.1A	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.4.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.4.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	$ME \rightarrow USS$	REGISTER 4.1A	-
27	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1A	

### Expected Sequence 4.4B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Large Font Size)

	$UICC \to ME$	PROACTIVE COMMAND	
1 2 11		PENDING: SEND SS 4.4.1	
1	/ 0.00	FETCH	
3   1	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.4.1	
4   1	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with large font size]
5	$ME \to USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7   1	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	
8 (	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.4.2	
9 1	$ME \rightarrow UICC$	FETCH	
	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.4.2	
11 N	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	$ME \to USS$	REGISTER 4.1B	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND ISS 4.1.1B	
15 l	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.4.1	
16	$ME \to UICC$	FETCH	
17 ι	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.4.1	
18 N	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with large font size]
19	$ME \to USS$	REGISTER 4.1B	
20	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	
22 (	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.4.3	
23	$ME \to UICC$	FETCH	
	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.4.3	
25 N	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	$ME \to USS$	REGISTER 4.1B	_
27	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	

### PROACTIVE COMMAND: SEND SS 4.4.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	04	B4							

PROACTIVE COMMAND: SEND SS 4.4.2

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

PROACTIVE COMMAND: SEND SS 4.4.3

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.11.4.5 SEND SS (support of Text Attribute – Small Font Size)

27.22.4.11.4.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.5.3 Test purpose

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.11.4.5.4 Method of test

#### 27.22.4.11.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.4.5.4.2 Procedure

# Expected Sequence 4.5A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.5.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.5.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with small font size]
5	$ME \rightarrow USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.5.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.5.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	$ME \rightarrow USS$	REGISTER 4.1A	
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
14	ME → UICC	RETURN RESULT) 4.1A TERMINAL RESPONSE: SEND	
15	$UICC \to ME$	SS 4.1.1A PROACTIVE COMMAND	
16	ME → UICC	PENDING: SEND SS 4.5.1 FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with small font size]
19	$ME \rightarrow USS$	REGISTER 4.1A	
20	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1A	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.5.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.5.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	$ME \rightarrow USS$	REGISTER 4.1A	
27	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1A	

### Expected Sequence 4.5B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.5.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with small font size]
5	$ME \to USS$	REGISTER 4.1B	_
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
_		RETURN RESULT) 4.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
8	LUCC ME	SS 4.1.1B PROACTIVE COMMAND	
0	$UICC \to ME$	PENDING: SEND SS 4.5.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
		SS 4.5.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with normal font
40		DECICIED 44D	size]
12	ME → USS	REGISTER 4.1B	[Cupacatul]
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND	
	WIE 7 0100	SS 4.1.1B	
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.5.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	
18	$ME \rightarrow USER$	SS 4.5.1 Display "Text Attribute 1"	Message shall be formatted with small font
10	IVIE → USER	Display Text Attribute 1	size
19	$ME \rightarrow USS$	REGISTER 4.1B	0120]
20	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
20		SS 4.1.1B	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.5.3	
23	ME → UICC	FETCH	
24	$VICC \rightarrow ME$	PROACTIVE COMMAND: SEND	
	3.00 / WIL	SS 4.5.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with normal font
			size]
26	ME → USS	REGISTER 4.1B	
27	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
28	ME → UICC	RETURN RESULT) 4.1B TERMINAL RESPONSE: SEND	
20	INIE -> DICC	SS 4.1.1B	
	l	1	

#### PROACTIVE COMMAND: SEND SS 4.5.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	08	B4							

#### PROACTIVE COMMAND: SEND SS 4.5.2

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

#### PROACTIVE COMMAND: SEND SS 4.5.3

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.11.4.6 SEND SS (support of Text Attribute – Bold On)

27.22.4.11.4.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.11.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.6.3 Test purpose

To verify that the ME displays the alpha identifier according to the bold text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.11.4.6.4 Method of test

27.22.4.11.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.4.6.4.2 Procedure

### Expected Sequence 4.6A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.6.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.6.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with bold on]
5	$ME \to USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND	
0	ME	PENDING: SEND SS 4.6.2	
9	ME → UICC	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.6.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with bold off]
12	ME → USS	REGISTER 4.1A	[message shall be formatted with bold on]
13	$USS \rightarrow ME$	RELEASE COMPLETE (SS	[Successful]
13	USS → IVIE	RETURN RESULT) 4.1A	[Ouccessiui]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
	WE 7 0100	SS 4.1.1A	
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.6.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.6.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with bold on]
19	$ME \rightarrow USS$	REGISTER 4.1A	
20	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
0.4		RETURN RESULT) 4.1A	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
22	LUCO ME	SS 4.1.1A	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.6.3	
23	ME → UICC	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.6.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with bold off]
26	ME → USS	REGISTER 4.1A	[
27	USS → ME	RELEASE COMPLETE (SS	[Successful]
	OGG / WIL	RETURN RESULT) 4.1A	1
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	

### Expected Sequence 4.6B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.6.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.6.1	
4		Display "Text Attribute 1"	[Message shall be formatted with bold on]
5	$ME \rightarrow USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
0	ME	PENDING: SEND SS 4.6.2	
9	ME → UICC	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.6.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with bold off]
12	$ME \rightarrow USS$	REGISTER 4.1B	[wessage shall be formatted with bold on]
13	USS → ME	RELEASE COMPLETE (SS	[Successful]
13		RETURN RESULT) 4.1B	[Ouccessiui]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
	IIIL	SS 4.1.1B	
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.6.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.6.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with bold on]
19	$ME \rightarrow USS$	REGISTER 4.1B	
20	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
00	11100 145	SS 4.1.1B	
22	$UICC \to ME$	PROACTIVE COMMAND	
23	ME LUCC	PENDING: SEND SS 4.6.3 FETCH	
23	ME → UICC	PROACTIVE COMMAND: SEND	
24	$UICC \to ME$	ISS 4.6.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with bold off]
26	$ME \rightarrow USS$	REGISTER 4.1B	[moscage shall be formatted with bold on]
27	USS → ME	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	[Cuccocciai]
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.6.1

#### Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	10	B4							

#### PROACTIVE COMMAND: SEND SS 4.6.2

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

#### PROACTIVE COMMAND: SEND SS 4.6.3

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	Α9	01	FB	

#### 27.22.4.11.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.11.4.7 SEND SS (support of Text Attribute – Italic On)

27.22.4.11.4.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.7.3 Test purpose

To verify that the ME displays the alpha identifier according to the italic text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.7.4 Method of test

#### 27.22.4.11.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.4.7.4.2 Procedure

# Expected Sequence 4.7A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.7.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.7.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with italic on]
5	$ME \rightarrow USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
7	11100	RETURN RESULT) 4.1A	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND ISS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.7.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
	OIGG / WIE	SS 4.7.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with italic off]
12	$ME \to USS$	REGISTER 4.1A	
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
!		SS 4.1.1A	
15	$UICC \to ME$		
16	ME LUCC		
17	OICC → ME		
18	ME - LISER		[Message shall be formatted with italic on]
			[message shall be formation with traile ship
			[Successful]
	7 1112		[Cuccoccian]
21	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND	
		SS 4.1.1A	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.7.3	
		_	
24	$UICC \to ME$		
25	NE		[Manager ahall ha famager at a district to the
			[[iviessage snail be formatted with Italic off]
			[Cusassaful]
21	USS → ME		[Successful]
28	ME VIICO	1	
20	INIE → UICC		
14 15 16 17 18 19 20 21	$\begin{split} ME &\to UICC \\ UICC &\to ME \\ ME &\to UICC \\ UICC &\to ME \\ ME &\to USER \\ ME &\to USS \\ USS &\to ME \\ ME &\to UICC \\ UICC &\to ME \\ ME &\to UICC \\ UICC &\to ME \\ ME &\to UICC \\ \end{split}$	RETURN RESULT) 4.1A TERMINAL RESPONSE: SEND SS 4.1.1A PROACTIVE COMMAND PENDING: SEND SS 4.7.1 FETCH PROACTIVE COMMAND: SEND SS 4.7.1 Display "Text Attribute 1" REGISTER 4.1A RELEASE COMPLETE (SS RETURN RESULT) 4.1A TERMINAL RESPONSE: SEND SS 4.1.1A PROACTIVE COMMAND	[Message shall be formatted with italic or [Successful]  [Message shall be formatted with italic of [Successful]

### Expected Sequence 4.7B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.7.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.7.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with italic on]
5	$ME \rightarrow USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
	11100	PENDING: SEND SS 4.7.2	
9	ME → UICC	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.7.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with italic off]
12	$ME \rightarrow USS$	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS	[Successful]
	7	RETURN RESULT) 4.1B	[[
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1B	
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.7.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.7.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with italic on]
19	$ME \rightarrow USS$	REGISTER 4.1B	
20	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
00	11100 145	SS 4.1.1B	
22	$UICC \to ME$	PROACTIVE COMMAND	
23	ME THOC	PENDING: SEND SS 4.7.3 FETCH	
23	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND: SEND	
Z4	UICC → IVIE	ISS 4.7.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with italic off]
26	ME → USS	REGISTER 4.1B	[moseage shall be formatted with Italie on]
27	USS → ME	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	[Caccoodiai]
28	ME → UICC	TERMINAL RESPONSE: SEND	
	7 0.00	SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.7.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	20	B4							

#### PROACTIVE COMMAND: SEND SS 4.7.2

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
·	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

#### PROACTIVE COMMAND: SEND SS 4.7.3

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	Α9	01	FB	

## 27.22.4.11.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

27.22.4.11.4.8 SEND SS (support of Text Attribute – Underline On)

27.22.4.11.4.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

## 27.22.4.11.4.8.3 Test purpose

To verify that the ME displays the alpha identifier according to the underline text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.8.4 Method of test

#### 27.22.4.11.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

# 27.22.4.11.4.8.4.2 Procedure

# Expected Sequence 4.8A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.8.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.8.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with underline
_		DECICTED 4.44	on]
5	ME → USS	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
7	ME LUCC	RETURN RESULT) 4.1A	
/	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND ISS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND	
0		PENDING: SEND SS 4.8.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
10	OIGG / WIL	SS 4.8.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with underline
			off]
12	$ME \rightarrow USS$	REGISTER 4.1A	
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
4-		SS 4.1.1A	
15	$UICC \to ME$	PROACTIVE COMMAND	
16	ME	PENDING: SEND SS 4.8.1	
17	ME → UICC	PROACTIVE COMMAND: SEND	
17	$UICC \to ME$	ISS 4.8.1	
18	ME → USER		Message shall be formatted with underline
10	IVIL -> OOLK	Display Text Attribute 1	on]
19	$ME \rightarrow USS$	REGISTER 4.1A	
20	$USS \rightarrow ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.8.3	
23	ME → UICC	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND	
25	ME LIGED	SS 4.8.3	[Massage shall be formatted with underline
20	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with underline off]
26	$ME \rightarrow USS$	REGISTER 4.1A	01
27	USS → ME	RELEASE COMPLETE (SS	[Successful]
	COO / IVIL	RETURN RESULT) 4.1A	[
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	

# Expected Sequence 4.8B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
_		PENDING: SEND SS 4.8.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.8.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with underline on]
5	$ME \to USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
_		RETURN RESULT) 4.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
8	LUCC ME	SS 4.1.1B PROACTIVE COMMAND	
0	$UICC \to ME$	PENDING: SEND SS 4.8.2	
9	$ME \rightarrow UICC$	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
		SS 4.8.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with underline
4.0		DE0107ED 4.4D	off]
12	ME → USS	REGISTER 4.1B	[O
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND	
	IVIL -> 0100	SS 4.1.1B	
15	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.8.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	
18	ME LICED	SS 4.8.1 Display "Text Attribute 1"	[Message shall be formatted with underline
10	$ME \rightarrow USER$	Display Text Attribute 1	on]
19	$ME \rightarrow USS$	REGISTER 4.1B	011
20	USS → ME	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
00		SS 4.1.1B	
22	$UICC \to ME$	PROACTIVE COMMAND	
23	ME → UICC	PENDING: SEND SS 4.8.3 FETCH	
24	$VICC \rightarrow ME$	PROACTIVE COMMAND: SEND	
	JIGO / IVIL	SS 4.8.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Message shall be formatted with underline
			off]
26	$ME \rightarrow USS$	REGISTER 4.1B	
27	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
20	ME LUCC	RETURN RESULT) 4.1B TERMINAL RESPONSE: SEND	
28	$ME \rightarrow UICC$	SS 4.1.1B	
L	l .	00 1.1.10	

# PROACTIVE COMMAND: SEND SS 4.8.1

# Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	40	B4							

PROACTIVE COMMAND: SEND SS 4.8.2

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

PROACTIVE COMMAND: SEND SS 4.8.3

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

27.22.4.11.4.9 SEND SS (support of Text Attribute – Strikethrough On)

27.22.4.11.4.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

## 27.22.4.11.4.9.3 Test purpose

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.11.4.9.4 Method of test

#### 27.22.4.11.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

# 27.22.4.11.4.9.4.2 Procedure

# Expected Sequence 4.9A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.9.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.9.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with
			strikethrough on]
5	$ME \rightarrow USS$	REGISTER 4.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
_		RETURN RESULT) 4.1A	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
	11100 145	SS 4.1.1A	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.9.2	
9	ME VIICC	FETCH	
10	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND: SEND	
10		SS 4.9.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with
	, 001.1		strikethrough off]
12	$ME \to USS$	REGISTER 4.1A	ŭ .
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
4.5		SS 4.1.1A	
15	$UICC \to ME$	PROACTIVE COMMAND	
16	ME → UICC	PENDING: SEND SS 4.9.1 FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND	
17		ISS 4.9.1	
18	ME → USER	Display "Text Attribute 1"	Message shall be formatted with
	ML 700LK		strikethrough on]
19	$ME \to USS$	REGISTER 4.1A	ŭ .
20	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1A	
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	
22	$UICC \to ME$	PROACTIVE COMMAND	
22	ME LUCC	PENDING: SEND SS 4.9.3 FETCH	
23 24	ME → UICC	PROACTIVE COMMAND: SEND	
24	$UICC \to ME$	ISS 4.9.3	
25	ME → USER	Display "Text Attribute 3"	Message shall be formatted with
-	WIL / OOLIK		strikethrough off]
26	$ME \rightarrow USS$	REGISTER 4.1A	3 - 1
27	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
1		RETURN RESULT) 4.1A	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1A	

# Expected Sequence 4.9B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.9.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND SS 4.9.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with strikethrough on]
5	$ME \to USS$	REGISTER 4.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
	LUCO ME	SS 4.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.9.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
	OIOO / WIL	SS 4.9.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with
			strikethrough off]
12	$ME \rightarrow USS$	REGISTER 4.1B	
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
4.4	NAT 11100	RETURN RESULT) 4.1B	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND SS 4.1.1B	
15	$UICC \to ME$	PROACTIVE COMMAND	
	OIGG / WIE	PENDING: SEND SS 4.9.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.9.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with
19	$ME \rightarrow USS$	REGISTER 4.1B	strikethrough on]
20	$USS \rightarrow ME$	RELEASE COMPLETE (SS	[Successful]
20		RETURN RESULT) 4.1B	[Ouccessiui]
21	ME → UICC	TERMINAL RESPONSE: SEND	
		SS 4.1.1B	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.9.3	
23	ME → UICC	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND	
25	ME LIGED	SS 4.9.3 Display "Text Attribute 3"	[Message shall be formatted with
2.5	$ME \rightarrow USER$	Display Text Attribute 5	strikethrough off]
26	$ME \to USS$	REGISTER 4.1B	- Cameanough on
27	USS → ME	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	j - 1
28	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND	
		SS 4.1.1B	

# PROACTIVE COMMAND: SEND SS 4.9.1

# Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	80	B4							

PROACTIVE COMMAND: SEND SS 4.9.2

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

PROACTIVE COMMAND: SEND SS 4.9.3

Logically:

Command details

Command number:

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

## 27.22.4.11.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.11.4.10 SEND SS (support of Text Attribute – Foreground and Background Colour)

27.22.4.11.4.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

## 27.22.4.11.4.10.3 Test purpose

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.11.4.10.4 Method of test

#### 27.22.4.11.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.10.4.2 Procedure

# Expected Sequence 4.10A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.10.1	
2	$ME \rightarrow UICC$		
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.10.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with foreground
			and background colour according to text
_	ME 1100	REGISTER 4.1A	attribute configuration]
5	WIL 7 000		
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
_		RETURN RESULT) 4.1A	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
0	LUCO ME		
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND SS 4.10.2	
9	ME → UICC		
10		PROACTIVE COMMAND: SEND	
10	OICC → IVIE	ISS 4.10.2	
11	ME VIISED	Display "Text Attribute 2"	[Message shall be formatted with ME"s
	IVIL -> USLIX	Display Text Attribute 2	default foreground and background colour
12	$ME \rightarrow USS$	REGISTER 4.1A	delacit foregreating and buokground colour
13	USS → ME	RELEASE COMPLETE (SS	[Successful]
	COO / IVIL	RETURN RESULT) 4.1A	[
14	MF → UICC	TERMINAL RESPONSE: SEND	
''	2 / 0.00	SS 4.1.1A	

# Expected Sequence 4.10B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 4.10.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.10.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with foreground
			and background colour according to text
5	ME LISS	REGISTER 4.1B	attribute configuration]
6			[Cupagasful]
0	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME VIICC	TERMINAL RESPONSE: SEND	
,	IVIL -> OICC	ISS 4.1.1B	
8	$UICC \rightarrow ME$	PROACTIVE COMMAND	
	0.00 /	PENDING: SEND SS 4.10.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 4.10.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with ME"s
			default foreground and background colour]
12	$ME \rightarrow USS$	REGISTER 4.1B	
13	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 4.1B	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.10.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

#### PROACTIVE COMMAND: SEND SS 4.10.2

## Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

## Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

## 27.22.4.11.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

# 27.22.4.11.5 SEND SS (UCS2 display in Chinese)

## 27.22.4.11.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionnally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in: ISO/IEC 10646 [17].

## 27.22.4.11.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.11.5.4 Method of test

#### 27.22.4.11.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.5.4.2 Procedure

# Expected Sequence 5.1A (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Chinese)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 5.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 5.1.1	
4	$ME \rightarrow USER$	Display "你好"	["Hello" in Chinese]
5	$ME \to USS$	REGISTER 5.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 5.1A	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SS 5.1.1A	

# Expected Sequence 5.1B (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Chinese)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 5.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 5.1.1	
4	$ME \rightarrow USER$	Display "你好"	["Hello" in Chinese]
5	$ME \to USS$	REGISTER 5.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 5.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SS 5.1.1B	

PROACTIVE COMMAND: SEND SS 5.1.1

Logically:

Command details

Command number: 1

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Data coding scheme: UCS2 (16bit)

Text: "你好"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	22	81	03	01	11	00	82	02	81	83	85
	05	80	4F	60	59	7D	89	10	91	AA	12	0A
	21	43	65	87	09	21	43	65	87	A9	01	FB

#### **REGISTER 5.1A**

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

**REGISTER 5.1B** 

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1B

## RELEASE COMPLETE (SS RETURN RESULT) 5.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

RELEASE COMPLETE (SS RETURN RESULT) 5.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

TERMINAL RESPONSE: SEND SS 5.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

TERMINAL RESPONSE: SEND SS 5.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

# 27.22.4.11.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

## 27.22.4.11.6 SEND SS (UCS2 display in Katakana)

#### 27.22.4.11.6.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.11.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionnally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in: ISO/IEC 10646 [17].

## 27.22.4.11.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.6.4 Method of test

#### 27.22.4.11.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.6.4.2 Procedure

# Expected Sequence 6.1A (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Katakana)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 6.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 6.1.1	
4	$ME \rightarrow USER$	Display "ル"	[Character in Katakana]
5	$ME \to USS$	REGISTER 6.1A	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 6.1A	-
7	$ME \to UICC$	TERMINAL RESPÓNSE: SEND	[Command performed successfully]
		SS 6.1.1A	

# Expected Sequence 6.1B (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Katakana)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND SS 6.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		SS 6.1.1	
4	$ME \rightarrow USER$	Display "ル"	[Character in Katakana]
5	$ME \to USS$	REGISTER 6.1B	
6	$USS \to ME$	RELEASE COMPLETE (SS	[Successful]
		RETURN RESULT) 6.1B	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		SS 6.1.1B	

#### PROACTIVE COMMAND: SEND SS 6.1.1

# Logically:

Command details

Command number:

Command type: SEND SS Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Data coding scheme: UCS2 (16bit)

Text: "ル"

SS String

TON: International

NPI: "ISDN / telephone numbering plan" SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	20	81	03	01	11	00	82	02	81	83	85
	03	80	30	EB	89	10	91	AA	12	0A	21	43
	65	87	09	21	43	65	87	A9	01	FB		_

**REGISTER 6.1A** 

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

**REGISTER 6.1B** 

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1B

RELEASE COMPLETE (SS RETURN RESULT) 6.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

RELEASE COMPLETE (SS RETURN RESULT) 6.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

TERMINAL RESPONSE: SEND SS 6.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

TERMINAL RESPONSE: SEND SS 6.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

27.22.4.11.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

27.22.4.12 SEND USSD

27.22.4.12.1 SEND USSD (normal)

27.22.4.12.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

## 27.22.4.12.1.3 Test purpose

To verify that the ME correctly translates and sends the unstructured supplementary service request indicated in the SEND USSD proactive UICC command to the USS.

To verify that the ME returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the USSD request and including a USSD result as a text string in the TERMINAL RESPONSE.

#### 27.22.4.12.1.4 Method of test

#### 27.22.4.12.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.12.1.4.2 Procedure

# Expected Sequence 1.1 (SEND USSD, 7-bit data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 1.1.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 1.1.1	
4	$ME \to USER$	Display "7-bit USSD"	
5	$ME \to USS$	REGISTER 1.1	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 1.1	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND	
		USSD 1.1.1	

## PROACTIVE COMMAND: SEND USSD 1.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "7-bit USSD"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

# Coding:

BER-TLV:	D0	50	81	03	01	12	00	82	02	81	83	85
	0A	37	2D	62	69	74	20	55	53	53	44	8A
	39	F0	41	E1	90	58	34	1 <sup>⊨</sup>	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	B3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60		

#### **REGISTER 1.1**

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

# Coding:

BER-TLV	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## RELEASE COMPLETE (SS RETURN RESULT) 1.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "USSD string received from SS"

# Coding:

BER-TLV	30	1 <sup>-</sup>	04	01	F0	04	19	D5	E9	94	80	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

#### TERMINAL RESPONSE: SEND USSD 1.1.1

Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

# Expected Sequence 1.2 (SEND USSD, 8-bit data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 1.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 1.2.1	
4	$ME \rightarrow USER$	Display "8-bit USSD"	
5	$ME \to USS$	REGISTER 1.2	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 1.2	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 1.2.1	

PROACTIVE COMMAND: SEND USSD 1.2.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "8-bit USSD"

**USSD String** 

Data coding scheme: Uncompressed, no message class meaning, 8-bit data

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Coding:

BER-TLV:	D0	58	81	03	01	12	00	82	02	81	83	85
	0A	38	2D	62	69	74	20	55	53	53	44	8A
	41	44	41	42	43	44	45	46	47	48	49	4A
	4B	4C	4D	4E	4F	50	51	52	53	54	55	56
	57	58	59	5A	2D	61	62	63	64	65	66	67
	68	69	6A	6B	6C	6D	6E	6F	70	71	72	73
	74	75	76	77	78	79	7A	2D	31	32	33	34
	35	36	37	38	39	30						

#### **REGISTER 1.2**

Logically (only USSD argument):

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- Uncompressed, no message class meaning, 8-bit data

USSD string:

- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

BER-TLV	30	45	04	01	44	04	40	41	42	43	44	45
	46	47	48	49	4A	4B	4C	4D	4E	4F	50	51
	52	53	54	55	56	57	58	59	5A	2D	61	62
	63	64	65	66	67	68	69	6A	6B	6C	6D	6E
	6F	70	71	72	73	74	75	76	77	78	79	7A
	2D	31	32	33	34	35	36	37	38	39	30	

# RELEASE COMPLETE (SS RETURN RESULT) 1.2

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- Uncompressed, no message class meaning, 8-bit data

USSD string:

- "USSD string received from SS"

#### Coding:

BER-TLV	30	21	04	01	44	04	1C	55	53	53	44	20
_	73	74	72	69	6E	67	20	72	65	63	65	69
	76	65	64	20	66	72	6F	6D	20	53	53	

TERMINAL RESPONSE: SEND USSD 1.2.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**Text String** 

Data coding scheme: Uncompressed, no message class meaning, 8-bit data

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1D	04	55	53	53	44	20	73	74
	72	69	6E	67	20	72	65	63	65	69	76
	65	64	20	66	72	6F	6D	20	53	53	

## Expected Sequence 1.3 (SEND USSD, UCS2 data, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 1.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 1.3.1	
4	$ME \rightarrow USER$	Display "UCS2 USSD"	
5	$ME \to USS$	REGISTER 1.3	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT)	["USSD string received from SS"]
		1.3	-
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 1.3.1	

PROACTIVE COMMAND: SEND USSD 1.3.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "UCS2 USSD"

**USSD String** 

Data coding scheme: Uncompressed, no message class meaning, UCS2 (16 bit)

USSD string: "ЗДРАВСТВУЙТЕ" ("Hello" in Russian)

# Coding:

BER-TLV:	D0	2F	81	03	01	12	00	82	02	81	83	85
	09	55	43	53	32	20	55	53	53	44	8A	19
	48	04	17	04	14	04	20	04	10	04	12	04
	21	04	22	04	12	04	23	04	19	04	22	04
	15											

#### **REGISTER 1.3**

Logically (only USSD argument):

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- Uncompressed, no message class meaning, UCS2 (16 bit)

**USSD** string:

- "ЗДРАВСТВУЙТЕ" ("Hello" in Russian)

## Coding:

BER-TLV	30	1D	04	01	48	04	18	04	17	04	14	04
	20	04	10	04	12	04	21	04	22	04	12	04
	23	04	19	04	22	04	15					

# RELEASE COMPLETE (SS RETURN RESULT) 1.3

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- Uncompressed, no message class meaning, UCS2 (16 bit) USSD string:

- "USSD string received from SS"

## Coding:

BER-TLV	30	3D	04	01	48	04	38	00	55	00	53	00
	53	00	44	00	20	00	73	00	74	00	72	00
	69	00	6E	00	67	00	20	00	72	00	65	00
	63	00	65	00	69	00	76	00	65	00	64	00
	20	00	66	00	72	00	6F	00	6D	00	20	00
	53	00	53									

TERMINAL RESPONSE: SEND USSD 1.3.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

**Text String** 

Data coding scheme: Uncompressed, no message class meaning, UCS2 (16 bit)

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
-	00	8D	39	80	00	55	00	53	00	53	00
	44	00	20	00	73	00	74	00	72	00	69
	00	6E	00	67	00	20	00	72	00	65	00
	63	00	65	00	69	00	76	00	65	00	64
	00	20	00	66	00	72	00	6F	00	6D	00
	20	00	53	00	53						

# Expected Sequence 1.4 (SEND USSD, 7-bit data, unsuccessful (Return Error))

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 1.1.1	
4	$ME \to USER$	Display "7-bit USSD"	
5	$ME \to USS$	REGISTER 1.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN ERROR) 1.1	Return Error
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 1.4.1	

# RELEASE COMPLETE (SS RETURN ERROR) 1.1

Logically (only from Return Error code):

ProcessUnstructuredSS-Request RETURN ERROR

Return Error code:

- Unknown alphabet

Coding:

TERMINAL RESPONSE: SEND USSD 1.4.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: USSD Return Error Additional information: "Unknown alphabet"

BER-TLV:	81	03	01	12	00	82	02	82	81	83	02
	37	47									

# Expected Sequence 1.5 (SEND USSD, 7-bit data, unsuccessful (Reject))

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 1.1.1	
4	$ME \rightarrow USER$	Display "7-bit USSD"	
5	$ME \to USS$	REGISTER 1.1	
6	$USS \to ME$	RELEASE COMPLETE (SS REJECT) 1.1	Reject
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 1.5.1	

# RELEASE COMPLETE (SS REJECT) 1.1

Logically (only from Problem code):

ProcessUnstructuredSS-Request REJECT

Invoke Problem code:

- Mistyped parameter

Coding:

Codina	81	01	02

TERMINAL RESPONSE: SEND <u>U</u>SSD 1.5.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: USSD Return Error

Additional information: "No specific cause can be given"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	02
	37	00									

# Expected Sequence 1.6 (SEND USSD, 256 octets, 7-bit data, successful, long alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 1.6.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 1.6.1	
4		Display "once a RELEASE COMPLETE	
		message containing the USSD Return Result	
		message not containing an error has been	
		received from the network, the ME shall	
		inform the SIM that the command has"	
5	$ME \to USS$	REGISTER 1.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN	["USSD string received from SS"]
		RESULT) 1.1	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND USSD 1.1.1	

PROACTIVE COMMAND: SEND USSD 1.6.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "once a RELEASE COMPLETE message containing the USSD Return Result

message not containing an error has been received from the network, the ME shall

inform the SIM that the command has"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

## Coding:

BER-TLV:	D0	81	FD	81	03	01	12	00	82	02	81	83
	85	81	В6	6F	6E	63	65	20	61	20	52	45
	4C	45	41	53	45	20	43	4F	4D	50	4C	45
	54	45	20	6D	65	73	73	61	67	65	20	63
	6F	6E	74	61	69	6 <sup>E</sup>	69	6 <sup>E</sup>	67	20	74	68
	65	20	55	53	53	44	20	52	65	74	75	72
	6 <sup>E</sup>	20	52	65	73	75	6C	74	20	6D	65	73
	73	61	67	65	20	6E	6F	74	20	63	6F	6E
	74	61	69	6E	69	6E	67	20	61	6E	20	65
	72	72	6F	72	20	68	61	73	20	62	65	65
	6E	20	72	65	63	65	69	76	65	64	20	66
	72	6F	6D	20	74	68	65	20	6E	65	74	77
	6F	72	6B	2C	20	74	68	65	20	4D	45	20
	73	68	61	6C	6C	20	69	6E	66	6F	72	6D
	20	74	68	65	20	53	49	4D	20	74	68	61
	74	20	74	68	65	20	63	6F	6D	6D	61	6E
	64	20	68	61	73	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

# Expected Sequence 1.7 (SEND USSD, 7-bit data, successful, no alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 1.7.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 1.7.1	
4	$ME \rightarrow USER$	Optionally display an informative message	
5	$ME \to USS$	REGISTER 1.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT)	["USSD string received from SS"]
		1.1	_
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 1.1.1	

# PROACTIVE COMMAND: SEND USSD 1.7.1

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

UICC

Destination device:

Network

**USSD String** 

Data coding scheme:

7-bit default, no message class

USSD string:

Source device:

"ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

## Coding:

BER-TLV:	D0	44	81	03	01	12	00	82	02	81	83	8A
-	39	F0	41	E1	90	58	34	1 <sup>E</sup>	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	В3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60		

# Expected Sequence 1.8 (SEND USSD, 7-bit data, successful, null length alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 1.8.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 1.8.1	
4	$ME \rightarrow USER$	the ME should not give any information to the	
		user on the fact that the ME is sending a USSD	
		request	
5	$ME \to USS$	REGISTER 1.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT)	["USSD string received from SS"]
		1.1	-
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 1.1.1	

## PROACTIVE COMMAND: SEND USSD 1.8.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: ""

Aipiia id

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

BER-TLV:	D0	46	81	03	01	12	00	82	02	81	83	85
	00	8A	39	F0	41	E1	90	58	34	1 <sup>E</sup>	91	49
	E5	92	D9	74	3E	A1	51	E9	94	5A	B5	5E
	B1	59	6D	2B	2C	1E	93	CB	E6	33	3A	AD
	5E	В3	DB	EE	37	3C	2E	9F	D3	EB	F6	3B
	3E	AF	6F	C5	64	33	5A	CD	76	C3	E5	60

## 27.22.4.12.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 - 1.8.

# 27.22.4.12.2 SEND USSD (Icon support)

27.22.4.12.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.2.2 Conformance requirement

27.22.4.12.2.3 Test purpose

To verify that the ME displays the text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

27.22.4.12.2.4 Method of test

27.22.4.12.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and to the USS. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS

The elementary files are coded as Toolkit default.

#### 27.22.4.12.2.4.2 Procedure

# Expected Sequence 2.1A (SEND USSD, 7-bit data, successful, basic icon self explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 2.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 2.1.1	[BASIC-ICON, self-explanatory]
4	$ME \rightarrow USER$	Display BASIC ICON	
5	$ME \rightarrow USS$	REGISTER 2.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN	["USSD string received from SS"]
		RESULT) 2.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 2.1.1A	[Command performed successfully]

#### PROACTIVE COMMAND: SEND USSD 2.1.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Basic Icon"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Icon Identifier:

Icon qualifier: icon is self-explanatory Icon Identifier: record 1 in  $EF_{(IMG)}$ 

Coding:

BER-TLV:	D0	54	81	03	01	12	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	8A
	39	F0	41	E1	90	58	34	1 <sup>Ŀ</sup>	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	В3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9⁵	02
	00	01										

#### **REGISTER 2.1**

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Coding:

BER-TLV	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## RELEASE COMPLETE (SS RETURN RESULT) 2.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "USSD string received from SS"

## Coding:

BER-TLV	30	1E	04	01	F0	04	19	D5	E9	94	80	9A
	D3	E5	69	F7	19	24	2F	8F	СВ	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

TERMINAL RESPONSE: SEND USSD 2.1.1A

Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**Text String** 

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

# Expected Sequence 2.1B (SEND USSD, 7-bit data, successful, basic icon self explanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 2.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[BASIC-ICON, self-explanatory]
		USSD 2.1.1	
4	$ME \rightarrow USER$	Display "Basic Icon" without the	
		icon	
5	$ME \rightarrow USS$	REGISTER 2.1	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 2.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed but requested icon
		USSD 2.1.1B	could not be displayed]

TERMINAL RESPONSE: SEND USSD 2.1.1B

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

**Text String** 

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	04	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

# Expected Sequence 2.2 (SEND USSD, 7-bit data, successful, colour icon self explanatory)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 2.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[COLOUR-ICON, self-explanatory]
		USSD 2.2.1	
4	$ME \rightarrow USER$	Display COLOUR-ICON	
		or	
		May give information to user	
		concerning what is happening	
5	IIIL / 000	REGISTER 2.1	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 2.1	
7	$ME \rightarrow UICC$		[Command performed successfully]
		USSD 2.1.1A	or
		or	[Command performed but requested icon
		TERMINAL RESPONSE: SEND	could not be displayed]
		USSD 2.1.1B	

PROACTIVE COMMAND: SEND USSD 2.2.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Color Icon"

USSD String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Icon Identifier:

Icon qualifier: icon is self-explanatory Icon Identifier: record 2 in  $EF_{(IMG)}$ 

BER-TLV:	D0	54	81	03	01	12	00	82	02	81	83	85
	0A	43	6F	6C	6F	72	20	49	63	6F	6E	8A
	39	F0	41	E1	90	58	34	1 <sup>E</sup>	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	В3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9 <sup>E</sup>	02
	00	02			,					,		

# Expected Sequence 2.3A (SEND USSD, 7-bit data, successful, basic icon non self-explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 2.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	[BASIC-ICON, non self-explanatory]
		USSD 2.3.1	
4	$ME \rightarrow USER$	Display "Basic Icon" and BASIC-	
		ICON	
5	ME LIGO	REGISTER 2.1	
_	/ 000		
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 2.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		USSD 2.1.1A	

PROACTIVE COMMAND: SEND USSD 2.3.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Basic Icon"

USSD String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Icon Identifier

Icon qualifier: icon is non self-explanatory

Icon Identifier: record 1 in  $EF_{(IMG)}$ 

BER-TLV:	D0	54	81	03	01	12	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	СВ	E6	33	3A	AD	5E	В3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9 <sup>E</sup>	02
	01	Ω1										

# Expected Sequence 2.3B (SEND USSD, 7-bit data, successful, basic icon non self-explanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to$	PROACTIVE COMMAND	
	ME	PENDING: SEND USSD 2.3.1	
2	ME  o	FETCH	
	UICC		
3	$UICC \rightarrow$	PROACTIVE COMMAND: SEND	[BASIC-ICON, non self-explanatory]
	ME	USSD 2.3.1	
4	ME  o	Display "Basic Icon" without the	
	USER	icon	
5	$ME \rightarrow USS$	REGISTER 2.1	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 2.1	
7	ME  o	TERMINAL RESPONSE: SEND	[Command performed but requested icon
	UICC	USSD 2.1.1B	could not be displayed]

# Expected Sequence 2.4 (SEND USSD, 7-bit data, basic icon non self-explanatory, no alpha identifier presented)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to$	PROACTIVE COMMAND	
	ME	PENDING: SEND USSD 2.4.1	
2	ME  o	FETCH	
	UICC		
3	$UICC \to$	PROACTIVE COMMAND: SEND	[BASIC-ICON, non self-explanatory]
	ME	USSD 2.4.1	
4	ME  o	TERMINAL RESPONSE: SEND	[Command data not understood by ME]
	UICC	USSD 2.4.1	

# PROACTIVE COMMAND: SEND USSD 2.4.1

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

Icon Identifier

Icon qualifier: icon is non self-explanatory

Icon Identifier: record 1 in  $EF_{(IMG)}$ 

Coding:

BER-TLV:	D0	48	81	03	01	12	00	82	02	81	83	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	В3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9 <sup>೬</sup>	02
	01	01										

TERMINAL RESPONSE: SEND USSD 2.4.1

## Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command data not understood by ME

#### Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01	32

#### 27.22.4.12.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 - 2.4.

## 27.22.4.12.3 SEND USSD (UCS2 display in Cyrillic)

27.22.4.12.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.12.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.12.3.4 Method of test

# 27.22.4.12.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.3.4.2 Procedure

# Expected Sequence 3.1 (SEND USSD, 7-bit data, successful, UCS2 text in Cyrillic)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 3.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 3.1.1	
4	$ME \rightarrow USER$	Display "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
5	$ME \to USS$	REGISTER 3.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN	[Successful]
		RESULT) 3.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 3.1.1	[Command performed successfully]

#### PROACTIVE COMMAND: SEND USSD 3.1.1

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Data coding scheme: UCS2 (16bit)
Text: "ЗДРАВСТВУЙТЕ"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD String: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

# Coding:

BER-TLV:	D0	5F	81	03	01	12	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	8A	39	F0	41	E1	90	58	34	1E	91
	49	E5	92	D9	74	3E	A1	51	E9	94	5A	B5
	5E	B1	59	6D	2B	2C	1E	93	CB	E6	33	3A
	AD	5E	В3	DB	EE	37	3C	2E	9F	D3	EB	F6
	3B	3E	AF	6F	C5	64	33	5A	CD	76	C3	E5
	60											

#### **REGISTER 3.1**

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD String:

- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Coding:

BER-TLV	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

#### RELEASE COMPLETE (SS RETURN RESULT) 3.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

**USSD String:** 

- "USSD string received from SS"

## Coding:

BER-TLV	30	1 <sup>E</sup>	04	01	F0	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

#### TERMINAL RESPONSE: SEND USSD 3.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

# Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

# 27.22.4.12.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

# 27.22.4.12.4 SEND USSD (support of Text Attribute)

27.22.4.12.4.1 SEND USSD (support of Text Attribute – Left Alignment)

27.22.4.12.4.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.4.1.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.1.3 Test purpose

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.1.4 Method of test

#### 27.22.4.12.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.12.4.1.4.2 Procedure

# Expected Sequence 4.1 (SEND USSD, 7-bit data, successful, with Text Attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.1.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with left alignment]
5	$ME \rightarrow USS$	REGISTER 4.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.1.1	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.1.2	
9	$ME \rightarrow UICC$		
10		PROACTIVE COMMAND: SEND USSD 4.1.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/13, no alignment change will take place]
12	$ME \rightarrow USS$	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND USSD 4.1.1	

#### PROACTIVE COMMAND: SEND USSD 4.1.1

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
_	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

#### PROACTIVE COMMAND: SEND USSD 4.1.2

## Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

## Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1 <sup>Ŀ</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

#### **REGISTER 4.1**

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Coding:

Coding	30	3D	04	01	F0	04	40	41	E1	90	58	34
	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	СВ	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## RELEASE COMPLETE (SS RETURN RESULT) 4.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "USSD string received from SS"

## Coding:

BER-TLV	30	1E	04	01	F0	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

#### TERMINAL RESPONSE: SEND USSD 4.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

# Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

# 27.22.4.12.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.12.4.2 SEND USSD (support of Text Attribute – Center Alignment)

27.22.4.12.4.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.4.2.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.2.3 Test purpose

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.2.4 Method of test

#### 27.22.4.12.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.12.4.2.4.2 Procedure

# Expected Sequence 4.2 (SEND USSD, 7-bit data, successful, with Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$		
		PENDING: SEND USSD 4.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.2.1	
4		Display "Text Attribute 1"	[Alpha identifier is displayed with center alignment]
5	$ME \rightarrow USS$	REGISTER 4.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.2.1	
8	$UICC \to ME$	PROACTIVE COMMAND	
_		PENDING: SEND USSD 4.2.2	
9	$ME \rightarrow UICC$		
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.2.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/13, no alignment change will take place]
12	$ME \to USS$	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
14	$ME \rightarrow UICC$		
		USSD 4.2.1	

#### PROACTIVE COMMAND: SEND USSD 4.2.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	01	B4		

#### PROACTIVE COMMAND: SEND USSD 4.2.2

# Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

#### Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1 <sup>Ŀ</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

#### TERMINAL RESPONSE: SEND USSD 4.2.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	СВ	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

# 27.22.4.12.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

27.22.4.12.4.3 SEND USSD (support of Text Attribute – Right Alignment)

27.22.4.12.4.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.4.3.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

# 27.22.4.12.4.3.3 Test purpose

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.3.4 Method of test

## 27.22.4.12.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.3.4.2 Procedure

# Expected Sequence 4.3 (SEND USSD, 7-bit data, successful, with Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.3.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with right alignment]
5	$ME \rightarrow USS$	REGISTER 4.1	
6		RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.3.1	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.3.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.3.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/13, no alignment change will take place]
12	$ME \to USS$	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.3.1	

## PROACTIVE COMMAND: SEND USSD 4.3.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	02	B4		

# PROACTIVE COMMAND: SEND USSD 4.3.2

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

# Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1 <sup>Ŀ</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

## TERMINAL RESPONSE: SEND USSD 4.3.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**Text String** 

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

## 27.22.4.12.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

## 27.22.4.12.4.4 SEND USSD (support of Text Attribute – Large Font Size)

## 27.22.4.12.4.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.4.4.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

## 27.22.4.12.4.4.3 Test purpose

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.4.4 Method of test

#### 27.22.4.12.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

# 27.22.4.12.4.4.4.2 Procedure

# Expected Sequence 4.4 (SEND USSD, 7-bit data, successful, with Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.4.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.4.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with large font size]
5	$ME \to USS$	REGISTER 4.1	3120]
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
0	LUCC ME	USSD 4.4.1	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.4.2	
9	$ME \rightarrow UICC$	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
		USSD 4.4.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Alpha identifier is displayed with normal font size]
12	$ME \to USS$	REGISTER 4.1	_
13	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.4.1	
15	$UICC \to ME$	PROACTIVE COMMAND	
	Oldo / WIE	PENDING: SEND USSD 4.4.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND	
40		USSD 4.4.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with large font size]
19	$ME \to USS$	REGISTER 4.1	Sizej
20	USS → ME	RELEASE COMPLETE (SS	["USSD string received from SS"]
	7	RETURN RESULT) 4.1	l cool amigration and i
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.4.1	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.4.3	
23	ME → UICC	FETCH	
24	$VICC \rightarrow ME$	PROACTIVE COMMAND: SEND	
	3.00 / WL	USSD 4.4.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Alpha identifier is displayed with normal font size]
26	$ME \to USS$	REGISTER 4.1	•
27	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.4.1	

# PROACTIVE COMMAND: SEND USSD 4.4.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
-	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	04	B4		

## PROACTIVE COMMAND: SEND USSD 4.4.2

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD** String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	F5	60	D0	04	00	10	00	B4		

#### PROACTIVE COMMAND: SEND USSD 4.4.3

Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	СВ
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.4.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

27.22.4.12.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.12.4.5 SEND USSD (support of Text Attribute – Small Font Size)

27.22.4.12.4.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.5.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

# 27.22.4.12.4.5.3 Test purpose

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.5.4 Method of test

#### 27.22.4.12.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

# 27.22.4.12.4.5.4.2 Procedure

# Expected Sequence 4.5 (SEND USSD, 7-bit data, successful, with Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.5.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with small font size]
5	$ME \to USS$	REGISTER 4.1	_
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.5.1	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.5.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.5.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Alpha identifier is displayed with normal font size]
12	$ME \to USS$	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.5.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.5.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with small font size]
19	$ME \to USS$	REGISTER 4.1	
20	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.5.1	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.5.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.5.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Alpha identifier is displayed with normal font size]
26	$ME \to USS$	REGISTER 4.1	_
27	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
28	ME → UICC	RETURN RESULT) 4.1 TERMINAL RESPONSE: SEND USSD 4.5.1	
	l .	1	1

# PROACTIVE COMMAND: SEND USSD 4.5.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	08	B4		

## PROACTIVE COMMAND: SEND USSD 4.5.2

## Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD** String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	F5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.5.3

Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

## Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

## TERMINAL RESPONSE: SEND USSD 4.5.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

# Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	СВ	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				_

## 27.22.4.12.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.12.4.6 SEND USSD (support of Text Attribute – Bold On)

27.22.4.12.4.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.6.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

# 27.22.4.12.4.6.3 Test purpose

To verify that the ME displays the alpha identifier according to the bold text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.6.4 Method of test

#### 27.22.4.12.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

# 27.22.4.12.4.6.4.2 Procedure

# Expected Sequence 4.6 (SEND USSD, 7-bit data, successful, with Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.6.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.6.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with bold on]
5	$ME \rightarrow USS$	REGISTER 4.1	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
_		RETURN RESULT) 4.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
8	LUCC ME	USSD 4.6.1 PROACTIVE COMMAND	
0	$UICC \to ME$	PENDING: SEND USSD 4.6.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
	OIGG / WIL	USSD 4.6.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed with bold off]
12	$ME \rightarrow USS$	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.6.1	
15	$UICC \to ME$	PROACTIVE COMMAND	
40	11100	PENDING: SEND USSD 4.6.1	
16	ME → UICC	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.6.1	
18	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with bold on]
19	ME → USS	REGISTER 4.1	[Alpha identifier is displayed with bold on]
20	USS → ME	RELEASE COMPLETE (SS	["USSD string received from SS"]
20	033 → IVIL	RETURN RESULT) 4.1	[ OOOD String received from OO ]
21	ME → UICC	TERMINAL RESPONSE: SEND	
		USSD 4.6.1	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.6.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND	
0.5		USSD 4.6.3	
25	ME → USER	Display "Text Attribute 3"	[Alpha identifier is displayed with bold off]
26	ME → USS	REGISTER 4.1	[
27	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
20	ME LUCC	RETURN RESULT) 4.1	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.6.1	
		1.0.0 4.0.1	

# PROACTIVE COMMAND: SEND USSD 4.6.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD** String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

375

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	10	B4		

## PROACTIVE COMMAND: SEND USSD 4.6.2

#### Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	F5	60	D0	04	00	10	00	B4		

# PROACTIVE COMMAND: SEND USSD 4.6.3

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1 <sup>Ŀ</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.6.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	СВ	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

27.22.4.12.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.12.4.7 SEND USSD (support of Text Attribute – Italic On)

27.22.4.12.4.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.7.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

# 27.22.4.12.4.7.3 Test purpose

To verify that the ME displays the alpha identifier according to the italic text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.7.4 Method of test

## 27.22.4.12.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.12.4.7.4.2 Procedure

# Expected Sequence 4.7 (SEND USSD, 7-bit data, successful, with Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.7.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.7.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with italic on]
5	$ME \rightarrow USS$	REGISTER 4.1	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
7	ME 11100	RETURN RESULT) 4.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.7.1	
8	UICC → ME	PROACTIVE COMMAND	
0		PENDING: SEND USSD 4.7.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	
	OIOO / WIL	USSD 4.7.2	
11	$ME \rightarrow USER$		[Alpha identifier is displayed with italic off]
12	$ME \rightarrow USS$	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.7.1	
15	$UICC \rightarrow ME$	PROACTIVE COMMAND	
4.0		PENDING: SEND USSD 4.7.1	
16	ME → UICC	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.7.1	
18	ME → USER		[Alpha identifier is displayed with italic on]
19	ME → USS	REGISTER 4.1	[Alpha identifier is displayed with Italic on]
20	$USS \rightarrow ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
20	USS → IVIE	RETURN RESULT) 4.1	[ 000D string received from 00 ]
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.7.1	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.7.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.7.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Alpha identifier is displayed with italic off]
26	$ME \rightarrow USS$	REGISTER 4.1	
27	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
00	ME IIICO	RETURN RESULT) 4.1	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.7.1	

#### PROACTIVE COMMAND: SEND USSD 4.7.1

#### Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	20	B4		

# PROACTIVE COMMAND: SEND USSD 4.7.2

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.7.3

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

# Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

## TERMINAL RESPONSE: SEND USSD 4.7.1

Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**Text String** 

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

## 27.22.4.12.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

## 27.22.4.12.4.8 SEND USSD (support of Text Attribute – Underline On)

# 27.22.4.12.4.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.4.8.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

## 27.22.4.12.4.8.3 Test purpose

To verify that the ME displays the alpha identifier according to the underline text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.8.4 Method of test

#### 27.22.4.12.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

# 27.22.4.12.4.8.4.2 Procedure

# Expected Sequence 4.8 (SEND USSD, 7-bit data, successful, with Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.8.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.8.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with underline on]
5	$ME \to USS$	REGISTER 4.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND USSD 4.8.1	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.8.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.8.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Alpha identifier is displayed with underline off]
12	$ME \to USS$	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND USSD 4.8.1	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.8.1	
16	$ME \rightarrow UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.8.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with underline on]
19	$ME \to USS$	REGISTER 4.1	
20	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.8.1	
22	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.8.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.8.3	
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Alpha identifier is displayed with underline off]
26	$ME \to USS$	REGISTER 4.1	
27	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 4.8.1	

# PROACTIVE COMMAND: SEND USSD 4.8.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
-	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	40	B4		

## PROACTIVE COMMAND: SEND USSD 4.8.2

## Logically:

Command details

Command number:

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD** String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	F5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.8.3

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

## Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.8.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

27.22.4.12.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

27.22.4.12.4.9 SEND USSD (support of Text Attribute – Strikethrough On)

27.22.4.12.4.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.9.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

# 27.22.4.12.4.9.3 Test purpose

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.9.4 Method of test

#### 27.22.4.12.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

# 27.22.4.12.4.9.4.2 Procedure

# Expected Sequence 4.9 (SEND USSD, 7-bit data, successful, with Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
_		PENDING: SEND USSD 4.9.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 4.9.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with strikethrough on]
5	$ME \rightarrow USS$	REGISTER 4.1	
6	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
_		RETURN RESULT) 4.1	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND IUSSD 4.9.1	
8	UICC → ME	PROACTIVE COMMAND	
	OICC → IVIL	PENDING: SEND USSD 4.9.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.9.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Alpha identifier is displayed with strikethrough off]
12	$ME \rightarrow USS$	REGISTER 4.1	J ,
13	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
4.5		USSD 4.9.1	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND USSD 4.9.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND	
	0.00 /2	USSD 4.9.1	
18	$ME \rightarrow USER$	Display "Text Attribute 1"	[Alpha identifier is displayed with strikethrough
			on]
19	$ME \rightarrow USS$	REGISTER 4.1	FIII 100D
20	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	ME → UICC	TERMINAL RESPONSE: SEND	
21	IVIL -> OICC	USSD 4.9.1	
22	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.9.3	
23	$ME \rightarrow UICC$	FETCH	
24	$UICC \to ME$	PROACTIVE COMMAND: SEND	
0.5		USSD 4.9.3	[Alaba identification lands admits at the state of the st
25	$ME \rightarrow USER$	Display "Text Attribute 3"	[Alpha identifier is displayed with strikethrough
26	$ME \to USS$	REGISTER 4.1	off]
27	USS → ME	RELEASE COMPLETE (SS	["USSD string received from SS"]
	COO / IVIL	RETURN RESULT) 4.1	[
28	$ME \rightarrow UICC$	TERMINAL RESPÓNSE: SEND	
		USSD 4.9.1	

# PROACTIVE COMMAND: SEND USSD 4.9.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
\ <u>-</u>	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	80	B4		

## PROACTIVE COMMAND: SEND USSD 4.9.2

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD** String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	F5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.9.3

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 3"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

## Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.9.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	СВ	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

27.22.4.12.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.12.4.10 SEND USSD (support of Text Attribute – Foreground and Background Colour)

27.22.4.12.4.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.10.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.10.3 Test purpose

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.10.4 Method of test

#### 27.22.4.12.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.10.4.2 Procedure

# Expected Sequence 4.10 (SEND USSD, 7-bit data, successful, with Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.10.1	
2	$ME \rightarrow UICC$		
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.10.1	
4	$ME \rightarrow USER$	Display "Text Attribute 1"	[Message shall be formatted with foreground
			and background colour according to text
5	ME → USS	REGISTER 4.1	attribute configuration]
6	WIL 7 000		["LICCD string resolved from CC"]
0	$USS \to ME$	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME -> LIICC	TERMINAL RESPONSE: SEND	
'	IVIL 70100	USSD 4.10.1	
8	UICC → ME	PROACTIVE COMMAND	
		PENDING: SEND USSD 4.10.2	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		USSD 4.10.2	
11	$ME \rightarrow USER$	Display "Text Attribute 2"	[Message shall be formatted with ME"s
			default foreground and background colour]
12	WIL 7000	REGISTER 4.1	
13	$USS \to ME$	RELEASE COMPLETE (SS	["USSD string received from SS"]
		RETURN RESULT) 4.1	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	
		USSD 4.10.1	

## PROACTIVE COMMAND: SEND USSD 4.10.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 1"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

Text Attribute

Formatting position: 0
Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.10.2

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Text Attribute 2"

**USSD** String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

# Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
•	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1 <sup>E</sup>	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.10.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	СВ	DF	6D	D0	74	0A				

# 27.22.4.12.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

# 27.22.4.12.5 SEND USSD (UCS2 display in Chinese)

27.22.4.12.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in: ISO/IEC 10646 [17].

# 27.22.4.12.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.5.4 Method of test

#### 27.22.4.12.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.5.4.2 Procedure

# Expected Sequence 5.1 (SEND USSD, 7-bit data, successful, UCS2 text in Chinese)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 5.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 5.1.1	
4	$ME \rightarrow USER$	Display "你好"	["Hello" in Chinese]
5	$ME \to USS$	REGISTER 5.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN	[Successful]
		RESULT) 5.1	-
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND USSD 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND USSD 5.1.1

## Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Data coding scheme: UCS2 (16bit)
Text: "你好"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD String: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

# Coding:

BER-TLV:	D0	4B	81	03	01	12	00	82	02	81	83	85
	05	80	4F	60	59	7D	8A	39	F0	41	E1	90
	58	34	1E	91	49	E5	92	D9	74	3E	A1	51
	E9	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93
	CB	E6	33	3A	AD	5E	В3	DB	EE	37	3C	2E
	9F	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A
	CD	76	C3	E5	60							

## **REGISTER 5.1**

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-Data Coding Scheme:

- 7-bit default, no message class

USSD String:

- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

# Coding:

Coding	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## RELEASE COMPLETE (SS RETURN RESULT) 5.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

**USSD String:** 

- "USSD string received from SS"

## Coding:

Coding	30	1E	04	01	00	04	19	D5	E9	94	80	9A
	D3	E5	69	F7	19	24	2F	8F	СВ	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

#### TERMINAL RESPONSE: SEND USSD 5.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

# 27.22.4.12.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

# 27.22.4.12.6 SEND USSD (UCS2 display in Katakana)

27.22.4.12.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.12.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.6.4 Method of test

#### 27.22.4.12.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.12.6.4.2 Procedure

#### Expected Sequence 6.1 (SEND USSD, 7-bit data, successful, UCS2 text in Katakana)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		USSD 6.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND USSD 6.1.1	
4	$ME \to USER$	Display "ル"	[Character " in Katakana]
5	$ME \to USS$	REGISTER 6.1	
6	$USS \to ME$	RELEASE COMPLETE (SS RETURN	[Successful]
		RESULT) 6.1	
7	$ME \to UICC$	TERMINAL RESPONSE: SEND USSD 6.1.1	[Command performed successfully]

#### PROACTIVE COMMAND: SEND USSD 6.1.1

# Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Data coding scheme: UCS2 (16bit)

Text: "ル"

**USSD String** 

Data coding scheme: 7-bit default, no message class

USSD String: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

1234567890"

# Coding:

BER-TLV:	D0	49	81	03	01	12	00	82	02	81	83	85
	03	80	30	EB	8A	39	F0	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	В3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

#### **REGISTER 6.1**

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD String:

- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Coding:

Coding	30	3D	04	01	F0	04	38	41	E1	90	58	34
_	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## RELEASE COMPLETE (SS RETURN RESULT) 6.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD String:

- "USSD string received from SS"

# Coding:

Coding	30	1E	04	01	00	04	19	D5	E9	94	80	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

TERMINAL RESPONSE: SEND USSD 6.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**Text String** 

Data coding scheme: 7-bit default, no message class String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	80	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

## 27.22.4.12.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

# 27.22.4.13 SET UP CALL

# 27.22.4.13.1 SET UP CALL (normal)

## 27.22.4.13.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.13.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

# 27.22.4.13.1.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

# 27.22.4.13.1.4 Method of test

# 27.22.4.13.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

### 27.22.4.13.1.4.2 Procedure

# Expected Sequence 1.1 (SET UP CALL, call confirmed by the user and connected)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET	
		UP CALL 1.1.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL	
		1.1.1	
4	$ME \rightarrow USER$	ME displays "Not busy" during user	
		confirmation phase.	
5	$USER \to ME$	The user confirms the call set up	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to	
		"+012340123456"	
7	$USS \to ME$	9	[The USS also has to handle the
		from the USS.	START DTMF and STOP DTMF
			messages sent by the ME in an
			appropriate way]
8	$ME \rightarrow UICC$		[Command performed successfully]
		The ME shall not update EF LND with the	
		called party address.	
9	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns to idle mode.	

### PROACTIVE COMMAND: SET UP CALL 1.1.1

### Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Not busy"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

## Coding:

BER-TLV:	D0	1 <sup>E</sup>	81	03	01	10	00	82	02	81	83	85
	80	4 <sup>E</sup>	6F	74	20	62	75	73	79	86	09	91
	10	32	04	21	43	65	1C	2C				

## TERMINAL RESPONSE: SET UP CALL 1.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

# Expected Sequence 1.2 (SET UP CALL, call rejected by the user)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 1.1.1	
4	$ME \rightarrow USER$	ME displays "Not busy" during the	
		user confirmation phase	
5	$USER \to ME$	The user rejects the set up call	[user rejects the call]
6	$ME \to UICC$	TERMINAL RESPONSE 1.2.1	[User did not accept call set-up request]
7	$ME \rightarrow USER$	The ME returns in idle mode.	

TERMINAL RESPONSE: SET UP CALL 1.2.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: User did not accept the proactive command

Coding:

Expected Sequence 1.3void

Expected Sequence 1.4 (SET UP CALL, putting all other calls on hold, ME busy)

ME is busy on a call

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET	
		UP CALL 1.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 1.4.1	[putting all other calls on hold]
4	$ME \to USER$	ME displays "On hold" during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirms the call]
6	$ME \to USS$	The active call is put on hold	
7	ME→USS	The ME attempts to set up a call to "+012340123456"	
8	$USS \to ME$	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
9	$ME \to UICC$	TERMINAL RESPONSE 1.4.1	[Command performed successfully]
10	$USER \to ME$	The user ends the call after 10 s. The ME retrieves the previous call automatically or on request of the user.	

### PROACTIVE COMMAND: SET UP CALL 1.4.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: putting all other calls on hold

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "On hold"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

## Coding:

BER-TLV:	D0	1D	81	03	01	10	02	82	02	81	83	85
	07	4F	6E	20	68	6F	6C	64	86	09	91	10
	32	04	21	43	65	1C	2C					

### TERMINAL RESPONSE: SET UP CALL 1.4.1

# Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: putting all other calls on hold

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	02	82	02	82	81	83	01	00
DEIX IEV.	0.	00	0.		02	02	02	02		00	0.	00

## Expected Sequence 1.5 (SET UP CALL, disconnecting all other calls, ME busy)

ME is busy on a call

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET	
		UP CALL 1.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL	[disconnecting all other calls]
		1.5.1	
4	$ME \rightarrow USER$	ME displays "Disconnect" during the user	
		confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirms the call]
6	$ME \to USS$	The ME disconnects the active call	
7	$ME { ightarrow} USS$	The ME attempts to set up a call to	
		"+012340123456"	
8	$USS \to ME$	The ME receives the CONNECT message	[The USS also has to handle the
		from the USS.	START DTMF and STOP DTMF
			messages sent by the ME in an
_			appropriate way]
9	$ME \rightarrow UICC$	TERMINAL RESPONSE 1.5.1	[Command performed successfully]
10	$USER \to ME$	The user ends the call after 10 s.	

## PROACTIVE COMMAND: SET UP CALL 1.5.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: disconnecting all other calls

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Disconnect"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Coding:

BER-TLV:	D0	20	81	03	01	10	04	82	02	81	83	85
	0A	44	69	73	63	6F	6 <sup>E</sup>	6 <sup>E</sup>	65	63	74	86
	09	91	10	32	04	21	43	65	1C	2C		

TERMINAL RESPONSE: SET UP CALL 1.5.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: putting all other calls on hold

Device identities

Source device: ME Destination device: UICC Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	04	82	02	82	81	83	01	00
DEIX IEV.	0.	00	0.		0 1	02	02	02	0.	03	0.	00

# Expected Sequence 1.6 (SET UP CALL, only if not currently busy on another call, ME busy)

ME is busy on a call

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[only if not currently busy on another call]
		CALL 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE 1.6.1	[ME currently unable to process command]

TERMINAL RESPONSE: SET UP CALL 1.6.1

Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME Destination device: UICC

Result

General Result: ME currently unable to process command

Additional Information: ME currently busy on call

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	02	20
	02											

## Expected Sequence 1.7 (SET UP CALL, putting all other calls on hold, call hold is not allowed)

ME is busy on a call. The USS shall be configured to not allow Call Hold.

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[putting all other calls on hold]
		CALL 1.4.1	
4	$ME \rightarrow USER$	ME displays "On hold" during the	
		user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirms the call]
6	$ME \to USS$	The ME attempts to put the active	
		call on hold.	
7	USS->ME	The ME receives the HOLD	[USS sends 'Facility Rejected' as cause value]
		REJECT message from the USS.	
8	$ME \rightarrow UICC$		[Network currently unable to process command]
		OR	
		TERMINAL RESPONSE 1.7.1B	[Option A shall apply only from R99 to Rel-6,
			whereas option B is applicable in all releases]

TERMINAL RESPONSE: SET UP CALL 1.7.1A

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: putting all other calls on hold

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Network currently unable to process command

Additional Information: No specific cause can be given

Coding:

BER-TLV:	81	03	01	10	02	82	02	82	81	83	02	21
' <u>-</u>	00											

TERMINAL RESPONSE: SET UP CALL 1.7.1B

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: putting all other calls on hold

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Network currently unable to process command

Additional Information: Facility Rejected

Coding:

BER-TLV:	81	03	01	10	02	82	02	82	81	83	02	21
	9D											

# **Expected Sequence 1.8 (SET UP CALL, Capability configuration)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.8.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[Capability configuration parameters: full rate
		CALL 1.8.1	support]
4	$ME \rightarrow USER$	ME displays "Capability config"	
		during the user confirmation phase	
5		The user confirms the set up call	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to	
		"+012340123456" using the	
7	$USS \to ME$		<u>-</u>
		message from the USS.	9
0	ME IIIOO	TERMINAL RESPONSE 4 9 4	
0	IVIE → UICC	TERIVIINAL RESPONSE 1.6.1	[Command performed successfully]
۵	LICED ME	The user ends the call after 10 s	
9	USEN → IVIE		
7 8 9	ME → UICC	capability configuration parameters supplied by UICC The ME receives the CONNECT message from the USS.  TERMINAL RESPONSE 1.8.1  The user ends the call after 10 s The ME returns in idle mode.	[The USS also has to handle the S DTMF and STOP DTMF messages the ME in an appropriate way] [Command performed successfully

### PROACTIVE COMMAND: SET UP CALL 1.8.1

### Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: if not busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Capability config"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Capability configuration parameters

Information transfer cap: full rate support only MS

## Coding:

BER-TLV:	D0	2B	81	03	01	10	00	82	02	81	83	85
	11	43	61	70	61	62	69	6C	69	74	79	20
	63	6F	6E	66	69	67	86	09	91	10	32	04
	21	43	65	1C	2C	87	02	01	A0			

## TERMINAL RESPONSE: SET UP CALL 1.8.1

### Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: if not busy on another call

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully

### Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## Expected Sequence 1.9 (SET UP CALL, max dialling number string, no alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.9.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND SET UP	[dialling number string, no alpha identifier]
		CALL 1.9.1	
4	$USER \to ME$	The user confirms the set up call	[user confirmation]
5	$ME { ightarrow} USS$	The ME attempts to set up a call to	
		"+01234567890123456789012345	
		678901"	
6	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE 1.9.1	[Command performed successfully]
8	$USER \to ME$	The user ends the call	
		The ME returns in idle mode.	

### PROACTIVE COMMAND: SET UP CALL 1.9.1

### Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call with redial

Device identities

Source device: UICC
Destination device: Network

Address

TON: International

NPI: ISDN / telephone numbering plan
Dialling number string: "01234567890123456789012345678901"

## Coding:

BER-TLV:	D0	1C	81	03	01	10	01	82	02	81	83	86
	11	91	10	32	54	76	98	10	32	54	76	98
	10	32	54	76	98	10						

### TERMINAL RESPONSE: SET UP CALL 1.9.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call with redial

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	01	02	01	10	01	82	02	92	01	92	01	00
DEN-ILV.	01	03	UI	10	UI	02	02	02	01	03	UI	00

## Expected Sequence 1.10 (SET UP CALL,256 octets length, long first alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP	
		CALL 1.10.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL	[ alpha identifier]
		1.10.1	
4	$ME \rightarrow USER$	ME displays "Three types are defined: - set up	
		a call, but only if not currently busy on another	
		call; - set up a call, putting all other calls (if any)	
		on hold; - set up a call, disconnecting all other	
		calls (if any) first. For each of these types, "	
_		during the user confirmation phase.	
5		The user confirms the set up call	[user confirmation]
6	ME→USS	The ME attempts to set up a call to "+01"	
7	$USS \to ME$	The ME receives the CONNECT message from	
		the USS.	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 1.10.1	[Command performed successfully]
9	$USER \to ME$	The user ends the call	
		The ME returns in idle mode.	

### PROACTIVE COMMAND: SET UP CALL 1.10.1

### Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call with redial

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Three types are defined: - set up a call, but only if not currently busy on another

call; - set up a call, putting all other calls (if any) on hold; - set up a call, disconnecting all other calls (if any) first. For each of these types, "

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string: "01"

### Coding:

BER-TLV:	D0	81	FD	81	03	01	10	01	82	02	81	83
•	85	81	ED	54	68	72	65	65	20	74	79	70
	65	73	20	61	72	65	20	64	65	66	69	6E
	65	64	3A	20	2D	20	73	65	74	20	75	70
	20	61	20	63	61	6C	6C	2C	20	62	75	74
	20	6F	6E	6C	79	20	69	66	20	6E	6F	74
	20	63	75	72	72	65	6E	74	6C	79	20	62
	75	73	79	20	6F	6E	20	61	6E	6F	74	68
	65	72	20	63	61	6C	6C	3B	20	2D	20	73
	65	74	20	75	70	20	61	20	63	61	6C	6C
	2C	20	70	75	74	74	69	6E	67	20	61	6C
	6C	20	6F	74	68	65	72	20	63	61	6C	6C
	73	20	28	69	66	20	61	6E	79	29	20	6F
	6E	20	68	6F	6C	64	3B	20	2D	20	73	65
	74	20	75	70	20	61	20	63	61	6C	6C	2C
	20	64	69	73	63	6F	6 <sup>E</sup>	6 <sup>E</sup>	65	63	74	69
	6 <sup>E</sup>	67	20	61	6C	6C	20	6F	74	68	65	72
	20	63	61	6C	6C	73	20	28	69	66	20	61
	6 <sup>E</sup>	79	29	20	66	69	72	73	74	2 <sup>E</sup>	20	46
	6F	72	20	65	61	63	68	20	6F	66	20	74
	68	65	73	65	20	74	79	70	65	73	2C	20
	86	02	91	10								

TERMINAL RESPONSE: SET UP CALL 1.10.1

# Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call with redial

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	Λ1	10	Λ1	82	02	82	81	83	Λ1	00
DENTILV.	01	US	01	10	01	02	UZ	02	01	ೲ	01	UU

# Expected Sequence 1.11A (SET UP CALL, Called party subaddress, command performed successfully)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.11.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[set up a call with called party subaddress]
		CALL 1.11.1	
4	$ME \rightarrow USER$	ME displays "Called party" during	
		the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME { ightarrow} USS$	The ME attempts to set up a call to	
		"+012340123456" with the called	
		party subaddress information	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by
			the ME in an appropriate way]
8	L / 0.00		[Command performed successfully]
9	$USER \to ME$	The user ends the call after 10 s	
		The ME returns in idle mode.	

# Expected Sequence 1.11B (SET UP CALL, Called party subaddress, ME not supporting the called party subaddress)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.11.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[set up a call with called party subaddress]
		CALL 1.11.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE 1.11.1B	[beyond ME's capabilities]

PROACTIVE COMMAND: SET UP CALL 1.11.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: if not busy on another call

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Called party"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string: "012340123456p1p2"

Called party subaddress

Type of subaddress: NSAP (X.213 / ISO 8348 AD2) Odd / even indicator: even number of address signals Subaddress information: AFI, 95, 95, 95, 95

Coding:

BER-TLV:	D0	2B	81	03	01	10	00	82	02	81	83	85
	0C	43	61	6C	6C	65	64	20	70	61	72	74
	79	86	09	91	10	32	04	21	43	65	1C	2C
	88	07	80	50	95	95	95	95	95			

TERMINAL RESPONSE: SET UP CALL 1.11.1A

### Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: if not busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

### TERMINAL RESPONSE: SET UP CALL 1.11.1B

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: if not busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Beyond ME's capabilities

### Coding:

BER-TLV:   81   03   01   10   00   82   02   82   81   83   01   30
--

## Expected Sequence 1.12 (SET UP CALL, maximum duration for the redial mechanism)

The USS shall be configured such that call set up requests will be rejected with cause "User Busy".

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 1.12.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[only if not currently busy on another call with
		CALL 1.12.1	redial]
4	$ME \rightarrow USER$	ME displays "Duration" during the	
		user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirms the call]
6	$ME \to USS$	ME attempts to set up a call to	[redial mechanism with maximum duration of
		"+012340123456" . It stops its	10 seconds]]
		attempts after 10 seconds.	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE 1.12.1	[network currently unable to process
			command]
8	$ME \rightarrow USER$	The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 1.12.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call with redial

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Duration"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string: "012340123456p1p2"

Duration

Unit: Seconds Interval: 10

Coding:

BER-TLV:	D0	22	81	03	01	10	01	82	02	81	83	85
	08	44	75	72	61	74	69	6F	6E	86	09	91
	10	32	04	21	43	65	1C	2C	84	02	01	0A

TERMINAL RESPONSE: SET UP CALL 1.12.1

Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call with redial

Device identities

Source device: ME
Destination device: UICC

Result

General Result: network currently unable to process command

Additional Information: User Busy

Coding:

BER-TLV:	81	03	01	10	01	82	02	82	81	83	02	21
	91											

27.22.4.13.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.12.

27.22.4.13.2 SET UP CALL (second alpha identifier)

27.22.4.13.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.13.2.2 Conformance requirement

Same as clause 27.22.4.13.2.1.

27.22.4.13.2.3 Test purpose

To verify that the ME accepts a Proactive Command - Set Up Call, displays the alpha identifiers to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.2.4 Method of test

27.22.4.13.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and is in updated idle mode on the USS.

### 27.22.4.13.2.4.2 Procedure

## **Expected Sequence 2.1 (SET UP CALL, two alpha identifiers)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 2.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 2.1.1	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION" during	
		the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME \rightarrow USS$	The ME attempts to set up a call to	[second alpha identifier]
		"+012340123456".	
		The ME displays "CALL"	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
			by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 2.1.1	[Command performed successfully]
		The ME shall not update EF LND with	
		the called party address.	
9	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

### PROACTIVE COMMAND: SET UP CALL 2.1.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL"

# Coding:

BER-TLV:	D0	28	81	03	01	10	00	82	02	81	83	85
	0C	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	86	09	91	10	32	04	21	43	65	1C	2C
	85	04	43	41	4C	4C						

TERMINAL RESPONSE: SET UP CALL 2.1.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

27.22.4.13.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

27.22.4.13.3 SET UP CALL (display of icons)

27.22.4.13.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.13.3.2 Conformance requirement

27.22.4.13.3.3 Test purpose

To verify that the ME accepts a Proactive Set Up Call , displays the message or icon to the user ,attempts to set up a call to the address, returns the result in the TERMINAL response.

27.22.4.13.3.4 Method of test

27.22.4.13.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and is in updated idle mode on the USS.

### 27.22.4.13.3.4.2 Procedure

# Expected Sequence 3.1A (SET UP CALL, display of basic icon during confirmation phase, not selfexplanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 3.1.1	Including icon identifier, icon shall be displayed in addition of the first alpha identifier
4	$ME \rightarrow USER$	ME displays "Set up call Icon 3.1.1" and the basic icon during a user confirmation phase.	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	ME→USS	The ME attempts to set up a call to "+012340123456"	
7	$USS \to ME$	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	$ME \to UICC$	TERMINAL RESPONSE 3.1.1A	[Command performed successfully]
9	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	

### PROACTIVE COMMAND: SET UP CALL 3.1.1

### Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Set up call Icon 3.1.1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Icon identifier

Icon qualifier: icon is not self-explanatory
Icon identifier: <record 1 in EF IMG>

### Coding:

BER-TLV:	D0	30	81	03	01	10	00	82	02	81	83	85
	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6E	20	33	2E	31	2E	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	01	01										

### TERMINAL RESPONSE: SET UP CALL 3.1.1A

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03	01 10	00 82	02 82	81	83	01	00
----------------	-------	-------	-------	----	----	----	----

# Expected Sequence 3.1B (SET UP CALL, display of basic icon during confirmation phase, not selfexplanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	Including icon identifier, icon shall be
			displayed in addition of the first alpha identifier
4	$ME \rightarrow USER$	ME displays "Set up call Icon 3.1.1" without the basic icon during a user confirmation phase.	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	ME→USS	The ME attempts to set up a call to "+012340123456"	
7	$USS \to ME$	message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	$ME \to UICC$	TERMINAL RESPONSE 3.1.1B	[Command performed successfully, but requested icon could not be displayed].
9	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	

TERMINAL RESPONSE: SET UP CALL 3.1.1B

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TI V	01	0.3	Λ1	10	00	92	02	92	01	02	Λ1	04
IDEK-ILV.	1 0 1	เบอ		1 10	I UU	02	1 02	1 02	101	റാ	1 01	I U4

# Expected Sequence 3.2A (SET UP CALL, display of basic icon during confirmation phase, self-explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.2.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	Including icon identifier, icon shall be
		CALL 3.2.1	displayed instead of the first alpha identifier
4	$ME \to USER$	ME displays the basic icon during	
		a user confirmation phase.	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to	
		"+012340123456"	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		, ,	DTMF and STOP DTMF messages sent by
			the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 3.2.1A	[Command performed successfully]
9	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 3.2.1

# Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Set up call Icon 3.2.1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Icon identifier

Icon qualifier: icon is self-explanatory
Icon identifier: <record 1 in EF IMG>

# Coding:

BER-TLV:	D0	30	81	03	01	10	00	82	02	81	83	85
	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6 <sup>E</sup>	20	33	2 <sup>E</sup>	32	2 <sup>E</sup>	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	00	01										

### TERMINAL RESPONSE: SET UP CALL 3.2.1A

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## Expected Sequence 3.2B (SET UP CALL, display of basic icon during confirmation phase, selfexplanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.2.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	Including icon identifier, icon shall be
		CALL 3.2.1	displayed instead of the first alpha identifier
4	$ME \to USER$	ME display "Set up call Icon 3.2.1"	
		without the icon	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME \rightarrow USS$	The ME attempts to set up a call to	
		"+012340123456"	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by
_			the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 3.2.1B	[Command performed successfully, but
			requested icon could not be displayed].
9	$USER \rightarrow ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

TERMINAL RESPONSE: SET UP CALL 3.2.1B

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	04

# Expected Sequence 3.3A (SET UP CALL, display of colour icon during confirmation phase, not self-explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	Including icon identifier, icon shall be displayed in
		CALL 3.3.1	addition of the first alpha identifier
4	$ME \rightarrow USER$	ME displays "Set up call Icon	
		3.3.1" and the colour icon during a	
		user confirmation phase.	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME { ightarrow} USS$	The ME attempts to set up a call to	
		"+012340123456"	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START DTMF
		message from the USS.	and STOP DTMF messages sent by the ME in an
			appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 3.3.1A	[Command performed successfully]
9	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

### PROACTIVE COMMAND: SET UP CALL 3.3.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Set up call Icon 3.3.1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Icon identifier

Icon qualifier: icon is not self-explanatory
Icon identifier: <record 2 in EF IMG>

## Coding:

BER-TLV:	D0	30	81	03	01	10	00	82	02	81	83	85
	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6E	20	33	2E	33	2E	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	01	02										

### TERMINAL RESPONSE: SET UP CALL 3.3.1A

# Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

# Expected Sequence 3.3B (SET UP CALL, display of colour icon during confirmation phase, not self-explanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.3.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	Including icon identifier, icon shall be
		CALL 3.3.1	displayed in addition of the first alpha identifier
4	$ME \rightarrow USER$	ME only display alpha string: " Set up call Icon 3.3.1"	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to "+012340123456"	
7	$USS \to ME$	message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	$ME \to UICC$	TERMINAL RESPONSE 3.3.1B	[Command performed successfully, but requested icon could not be displayed].
9	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	

TERMINAL RESPONSE: SET UP CALL 3.3.1B

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	04

# Expected Sequence 3.4A (SET UP CALL, display of self explanatory basic icon during set up call, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	Including a second alpha identifier and two
		CALL 3.4.1	icons
4	$ME \to USER$	ME displays the basic icon during	
		a user confirmation phase.	
5	$USER \to ME$	•	[user confirmation]
6	ME→USS	The ME attempts to set up a call to	
		"+012340123456". The ME	
		displays the basic icon without the	
		text during the set up call.	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by
_			the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 3.4.1A	[Command performed successfully]
9	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 3.4.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Set up call Icon 3.4.1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Icon identifier

Icon qualifier: icon is self-explanatory
Icon identifier: <record 1 in EF IMG>
Alpha identifier: "Set up call Icon 3.4.2"

Icon identifier

Icon qualifier: icon is self-explanatory
Icon identifier: <record 1 in EF IMG>

# Coding:

BER-TLV:	D0	4C	81	03	01	10	00	82	02	81	83	85
•	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6E	20	33	2E	34	2E	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	00	01	85	16	53	65	74	20	75	70	20	63
	61	6C	6C	20	49	63	6F	6E	20	33	2E	34
	2E	32	9E	02	00	01						

TERMINAL RESPONSE: SET UP CALL 3.4.1A

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

# Expected Sequence 3.4B (SET UP CALL, display of self explanatory basic icon during set up call, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP CALL 3.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	Including a second alpha identifier and two
		CALL 3.4.1	icons
4	$ME \rightarrow USER$	ME displays "Set up call Icon	
		3.4.1" without the icon	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to	
		"+012340123456". The ME	
		displays "Set up call Icon 3.4.2"	
		without the icon during the set up	
_		call.	
7	$USS \to ME$		[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by
8	ME 11100	TEDMINAL DECDONCE 2 4 4D	the ME in an appropriate way]
٥	$ME \rightarrow UICC$	TERMINAL RESPONSE 3.4.1B	[Command performed successfully, but
9	LICED ME	The user ends the call after 10 s.	requested icon could not be displayed].
9	$USER \to ME$	The ME returns in idle mode.	
		THE ME TELUINS III IUIE MOUE.	

TERMINAL RESPONSE: SET UP CALL 3.4.1B

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:   81   03   01   10   00   82   02   82   81   83   01   0
---

## 27.22.4.13.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.4B.

## 27.22.4.13.4 SET UP CALL (support of Text Attribute)

27.22.4.13.4.1 SET UP CALL (support of Text Attribute – Left Alignment)

27.22.4.13.4.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.13.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

### 27.22.4.13.4.1.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the left alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.1.4 Method of test

### 27.22.4.13.4.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

### 27.22.4.13.4.1.4.2 Procedure

# Expected Sequence 4.1 (SET UP CALL, Text Attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
_		CALL 4.1.1	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with left
	OSER - WIE	The user committee set up can	alignment]
6	$ME \to USS$	The ME attempts to set up a call to	[second alpha identifier is displayed with
		"+012340123456".	left alignment]
		The ME displays "CALL 1"	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
		TERMINIAL DECRONOE 4.4.4	by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.1.1 The ME shall not update EF LND with	[Command performed successfully]
		the called party address.	
9	USER → ME	The user ends the call after 10 s.	
	OOLIK 7 WIL	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.1.2	
11	$ME \rightarrow UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
40		CALL 4.1.2	
13	$ME \rightarrow USER$	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[User confirmation shall be formatted
14	USER → IVIE	The user committis the set up can	without left alignment. Remark: If left
			alignment is the ME"s default alignment
			as declared in table A.2/14, no alignment
			change will take place]
15	ME  o USS	The ME attempts to set up a call to	[Second alpha identifier shall be
		"+012340123456".	formatted without left alignment.
		The ME displays "CALL 2"	Remark: If left alignment is the ME"s
1			default alignment as declared in table
1			A.2/14, no alignment change will take place]
16	$USS \to ME$	The ME receives the CONNECT	The USS also has to handle the START
.0		message from the USS.	DTMF and STOP DTMF messages sent
			by the ME in an appropriate way]
17	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.1.1	[Command performed successfully]
		The ME shall not update EF LND with	
1		the called party address.	
18	$USER \to ME$	The user ends the call after 18 s.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 4.1.1

# Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	B4		

#### PROACTIVE COMMAND: SET UP CALL 4.1.2

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

1

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2" Alpha Identifier (call set up phase): "CALL 2"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		

### TERMINAL RESPONSE: SET UP CALL 4.1.1

### Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

### 27.22.4.13.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.13.4.2 SET UP CALL (support of Text Attribute – Center Alignment)

27.22.4.13.4.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.13.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

### 27.22.4.13.4.2.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the center alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.2.4 Method of test

### 27.22.4.13.4.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.2.4.2 Procedure

# Expected Sequence 4.2 (SET UP CALL, Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
_		CALL 4.2.1	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with
	OSER - WIE	The user committee set up can	center alignment]
6	$ME \to USS$	The ME attempts to set up a call to	[second alpha identifier is displayed with
		"+012340123456".	center alignment]
		The ME displays "CALL 1"	
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
		TERMINAL RESPONSE 4.0.4	by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.2.1	[Command performed successfully]
		The ME shall not update EF LND with the called party address.	
9	USER → ME	The user ends the call after 10 s.	
3	USER → IVIE	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
	0.00 /	SET UP CALL 4.2.2	
11	$ME \rightarrow UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 4.2.2	
13	$ME \rightarrow USER$	ME displays "CONFIRMATION 2"	
4.4		during the user confirmation phase	
14	$USER \to ME$	The user confirms the set up call	[User confirmation shall be formatted
			without center alignment. Remark: If center alignment is the ME"s default
			alignment as declared in table A.2/14, no
			alignment change will take place]
15	ME  o USS	The ME attempts to set up a call to	[Second alpha identifier shall be
	, , , , , ,	"+012340123456".	formatted without centert alignment.
		The ME displays "CALL 2"	Remark: If center alignment is the ME"s
			default alignment as declared in table
			A.2/14, no alignment change will take
4.0		TI ME : (1 00) 1150 T	place]
16	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.2.1	Command performed successfully
''	IVIE → UICC	The ME shall not update EF LND with	
		the called party address.	
18	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 4.2.1

# Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

### Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	01	B4	D0	04	00	06	01	B4		

## PROACTIVE COMMAND: SET UP CALL 4.2.2

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2" Alpha Identifier (call set up phase):"CALL 2"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		Į.

### TERMINAL RESPONSE: SET UP CALL 4.2.1

### Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	01	03	01	10	00	92	02	02	01	02	01	00
DEK-ILV.	01	US	UI	10	00	02	02	02	01	ಂ	UI	00

### 27.22.4.13.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

27.22.4.13.4.3 SET UP CALL (support of Text Attribute – Right Alignment)

27.22.4.13.4.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.13.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

### 27.22.4.13.4.3.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the right alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.3.4 Method of test

# 27.22.4.13.4.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.3.4.2 Procedure

# Expected Sequence 4.3 (SET UP CALL, Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.3.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION 1"	
	IVIL -> OOLIK	during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with right
		T. M	alignment]
6	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with right alignment]
		The ME displays "CALL 1"	ingrit angrimentj
7	$USS \to ME$	The ME receives the CONNECT	The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
			by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.3.1	[Command performed successfully]
		The ME shall not update EF LND with the called party address.	
9	USER → ME	The user ends the call after 10 s.	
	OOLIN -> IVIL	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.3.2	
11	$ME \rightarrow UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
13	ME → USER	CALL 4.3.2 ME displays "CONFIRMATION 2"	
13	IVIE → USEK	during the user confirmation phase	
14	$USER \to ME$	The user confirms the set up call	[User confirmation shall be formatted
		·	without right alignment. Remark: If right
			alignment is the ME"s default alignment
			as declared in table A.2/14, no alignment
15	ME  o USS	The ME attempts to set up a call to	change will take place] [Second alpha identifier shall be
13		"+012340123456".	formatted without right alignment.
		The ME displays "CALL 2"	Remark: If right alignment is the ME"s
		. ,	default alignment as declared in table
			A.2/14, no alignment change will take
40		The ME we said to the COMMISSE	place]
16	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START DTMF and STOP DTMF messages sent
		message from the USS.	by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.3.1	[Command performed successfully]
		The ME shall not update EF LND with	
		the called party address.	
18	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 4.3.1

# Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	02	B4	D0	04	00	06	02	B4		

#### PROACTIVE COMMAND: SET UP CALL 4.3.2

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2" Alpha Identifier (call set up phase):"CALL 2"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		

### TERMINAL RESPONSE: SET UP CALL 4.3.1

### Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

427

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

### 27.22.4.13.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

27.22.4.13.4.4 SET UP CALL (support of Text Attribute – Large Font Size)

27.22.4.13.4.4.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.13.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

### 27.22.4.13.4.4.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the large font size text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.4.4 Method of test

### 27.22.4.13.4.4.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

# 27.22.4.13.4.4.4.2 Procedure

# Expected Sequence 4.4 (SET UP CALL, Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION 1"	
	IVIE → USEK	during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with large
		·	font size]
6	$ME \to USS$	The ME attempts to set up a call to	[second alpha identifier is displayed with
		"+012340123456".	large font size]
7	$USS \to ME$	The ME displays "CALL 1" The ME receives the CONNECT	[The USS also has to handle the START
,	USS → IVIE	message from the USS.	DTMF and STOP DTMF messages sent
		mossage nom the ede.	by the ME in an appropriate way]
8	$ME \to UICC$	TERMINAL RESPONSE 4.4.1	[Command performed successfully]
		The ME shall not update EF LND with	
		the called party address.	
9	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
	OIOO IVIL	SET UP CALL 4.4.2	
11	$ME \to UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 4.4.2	
13	$ME \rightarrow USER$	ME displays "CONFIRMATION 2"	
14	$USER \to ME$	during the user confirmation phase The user confirms the set up call	[user confirmation is displayed with
14	USER → IVIE	The user committis the set up can	normal font size
15	ME  o USS	The ME attempts to set up a call to	[second alpha identifier is displayed with
	,	"+012340123456".	normal font size]
		The ME displays "CALL 2"	
16	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.4.1	[Command performed successfully]
	WE 7 0100	The ME shall not update EF LND with	[
		the called party address.	
18	$USER \to ME$	The user ends the call after 10 s.	
10	LUCC ME	The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.4.1	
20	$ME \rightarrow UICC$	FETCH	
21	$UICC \rightarrow ME$	PROACTIVE COMMAND: SET UP	
		CALL 4.4.1	
22	$ME \to USER$	ME displays "CONFIRMATION 1"	
22	LICED ME	during the user confirmation phase The user confirms the set up call	Lucar confirmation is displayed with large
23	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with large font size]
24	ME □USS	The ME attempts to set up a call to	[second alpha identifier is displayed with
	L	"+012340123456".	large font size]
		The ME displays "CALL 1"	
25	$USS \to ME$	The ME receives the CONNECT	The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
26	$ME \to UICC$	TERMINAL RESPONSE 4.4.1	by the ME in an appropriate way] [Command performed successfully]
20	IVIE → UICC	The ME shall not update EF LND with	
		the called party address.	
27	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
29	ME VIICO	SET UP CALL 4.4.3 FETCH	
29	$ME \rightarrow UICC$	ILE I OU	l .

30	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
31	$ME \rightarrow USER$	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with normal font size]
33	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with normal font size]
34	$USS \to ME$	The ME displays "CALL 3" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with	[Command performed successfully]
36	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	

### PROACTIVE COMMAND: SET UP CALL 4.4.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sub>F</sub>	04	B4	D0	04	00	06	04	B4		

### PROACTIVE COMMAND: SET UP CALL 4.4.2

# Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

### Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	B4		

### PROACTIVE COMMAND: SET UP CALL 4.4.3

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 3"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 3"

### Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.4.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

# 27.22.4.13.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.13.4.5 SET UP CALL (support of Text Attribute – Small Font Size)

27.22.4.13.4.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.13.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

### 27.22.4.13.4.5.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the small font size text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.4.5 Method of test

### 27.22.4.13.4.4.5.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.4.5.2 Procedure

## Expected Sequence 4.5 (SET UP CALL, Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
2	$ME \rightarrow UICC$	SET UP CALL 4.5.1 FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP	
		CALL 4.5.1	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with small
			font size]
6	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with small font size]
		The ME displays "CALL 1"	ornan fork oizoj
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.5.1	[Command performed successfully]
		The ME shall not update EF LND with	
9	$USER \to ME$	the called party address. The user ends the call after 10 s.	
	00211	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
11	ME → UICC	SET UP CALL 4.5.2 FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
13	ME → USER	CALL 4.5.2 ME displays "CONFIRMATION 2"	
13	IVIE → USER	during the user confirmation phase	
14	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with
15	ME  o USS	The ME attempts to set up a call to	normal font size] [second alpha identifier is displayed with
	WIE -7 000	"+012340123456".	normal font size]
40	1100 145	The ME displays "CALL 2"	The 1100 stee has to be still the OTABT
16	$USS \to ME$	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent
			by the ME in an appropriate way]
17	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with	[Command performed successfully]
		the called party address.	
18	$USER \to ME$	The user ends the call after 10 s.	
19	$UICC \to ME$	The ME returns in idle mode. PROACTIVE COMMAND PENDING:	
	OIGG / WIL	SET UP CALL 4.5.1	
20	ME → UICC	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 4.5.1	
22	$ME \rightarrow USER$	ME displays "CONFIRMATION 1"	
23	LIGED ME	during the user confirmation phase The user confirms the set up call	[user confirmation is displayed with small
23	USER → ME	The user committee the set up can	font size]
24	ME □USS	The ME attempts to set up a call to	[second alpha identifier is displayed with
		"+012340123456". The ME displays "CALL 1"	small font size]
25	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
26	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.5.1	by the ME in an appropriate way] [Command performed successfully]
-3	, 3,33	The ME shall not update EF LND with	
27	LICED . MF	the called party address. The user ends the call after 10 s.	
21	USER → ME	The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
29	$ME \rightarrow UICC$	SET UP CALL 4.5.3 FETCH	
23	I IVIL — UICC	1 - 1 - 1 - 1	l l

30	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
31	$ME \rightarrow USER$	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with normal font size]
33	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with normal font size]
34	$USS \to ME$	The ME displays "CALL 3" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with	[Command performed successfully]
36	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 4.5.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	08	B4	D0	04	00	06	08	B4		

## PROACTIVE COMMAND: SET UP CALL 4.5.2

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	B4		

#### PROACTIVE COMMAND: SET UP CALL 4.5.3

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 3"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 3"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.5.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## 27.22.4.13.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.13.4.6 SET UP CALL (support of Text Attribute – Bold On)

27.22.4.13.4.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

## 27.22.4.13.4.6.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the bold text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.6.4 Method of test

#### 27.22.4.13.4.6.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.6.4.2 Procedure

# Expected Sequence 4.6 (SET UP CALL, Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
2	ME  o UICC	SET UP CALL 4.6.1 FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP	
		CALL 4.6.1	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with bold
6	ME LISS	The ME attempts to set up a call to	on]
0	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with bold on]
_		The ME displays "CALL 1"	TT. 1100 1 1 1 1 1 1 0TABT
7	$USS \to ME$	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent
		linessage nem ale see.	by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.6.1	[Command performed successfully]
		The ME shall not update EF LND with the called party address.	
9	$USER \to ME$	The user ends the call after 10 s.	
10	LUCC ME	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.6.2	
11	$ME \to UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 4.6.2	
13	$ME \rightarrow USER$	ME displays "CONFIRMATION 2"	
		during the user confirmation phase	
14	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with bold off]
15	ME  o USS	The ME attempts to set up a call to	[second alpha identifier is displayed with
		"+012340123456". The ME displays "CALL 2"	bold off]
16	$USS \to ME$	The ME displays CALL 2  The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
17	ME → UICC	TERMINAL RESPONSE 4.6.1	by the ME in an appropriate way] [Command performed successfully]
	WIE 70100	The ME shall not update EF LND with	[command performed edecectally]
10	LICED ME	the called party address.	
18	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
20	$ME \rightarrow UICC$	SET UP CALL 4.6.1 FETCH	
21	$VICC \rightarrow ME$	PROACTIVE COMMAND: SET UP	
		CALL 4.6.1	
22	$ME \rightarrow USER$	ME displays "CONFIRMATION 1" during the user confirmation phase	
23	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with bold
24	ME □USS	The ME attempts to get up a cell to	on]
Z4	IVI⊏ □USS	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with bold on]
2-		The ME displays "CALL 1"	-
25	$USS \to ME$	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent
			by the ME in an appropriate way]
26	$ME \to UICC$	TERMINAL RESPONSE 4.6.1	[Command performed successfully]
		The ME shall not update EF LND with the called party address.	
27	$USER \to ME$	The user ends the call after 10 s.	
20	LUCC ME	The ME returns in idle mode. PROACTIVE COMMAND PENDING:	
28	$UICC \to ME$	SET UP CALL 4.6.3	
29	$ME \to UICC$	FETCH	

30	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
31	$ME \rightarrow USER$	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with bold off]
33	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with bold off]
34	$USS \to ME$	The ME displays "CALL 3" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with	[Command performed successfully]
36	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 4.6.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sub>F</sub>	10	B4	D0	04	00	06	10	B4		

## PROACTIVE COMMAND: SET UP CALL 4.6.2

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	B4		

#### PROACTIVE COMMAND: SET UP CALL 4.6.3

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 3"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 3"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.6.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## 27.22.4.13.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.13.4.7 SET UP CALL (support of Text Attribute – Italic On)

27.22.4.13.4.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

## 27.22.4.13.4.7.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the italic text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.7.4 Method of test

#### 27.22.4.13.4.7.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.7.4.2 Procedure

## Expected Sequence 4.7 (SET UP CALL, Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
2	$ME \rightarrow UICC$	SET UP CALL 4.7.1 FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP	
4	ME LIGED	CALL 4.7.1 ME displays "CONFIRMATION 1"	
4	$ME \rightarrow USER$	during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with italic on]
6	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with italic on]
7	$USS \to ME$	The ME displays "CALL 1" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with	[Command performed successfully]
9	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.7.2	
11	$ME \rightarrow UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 4.7.2	
13	$ME \rightarrow USER$	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with italic off]
15	ME  o USS	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with italic off]
16	$USS \to ME$	The ME displays "CALL 2" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.7.1	
20 21	$\begin{array}{c} ME \to UICC \\ UICC \to ME \end{array}$	FETCH PROACTIVE COMMAND: SET UP	
22	$ME \rightarrow USER$	CALL 4.7.1 ME displays "CONFIRMATION 1"	
23	USER → ME	during the user confirmation phase The user confirms the set up call	[user confirmation is displayed with italic
24	ME DUSS	The ME attempts to set up a call to	on] [second alpha identifier is displayed with
	,	"+012340123456". The ME displays "CALL 1"	italic on]
25	$USS \to ME$	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
27	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.7.3	
29	$ME \rightarrow UICC$	FETCH	

30	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
31	$ME \rightarrow USER$	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with italic off]
33	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with italic off]
34	$USS \to ME$	The ME displays "CALL 3" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with	[Command performed successfully]
36	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 4.7.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	20	B4	D0	04	00	06	20	B4		

## PROACTIVE COMMAND: SET UP CALL 4.7.2

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	B4		

## PROACTIVE COMMAND: SET UP CALL 4.7.3

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 3"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 3"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.7.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## 27.22.4.13.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

27.22.4.13.4.8 SET UP CALL (support of Text Attribute – Underline On)

27.22.4.13.4.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.13.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

## 27.22.4.13.4.8.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the underline text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.8.4 Method of test

#### 27.22.4.13.4.8.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.8.4.2 Procedure

# Expected Sequence 4.8 (SET UP CALL, Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.8.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
4	$ME \rightarrow USER$	CALL 4.8.1 ME displays "CONFIRMATION 1"	
-	IVIE → USER	during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with
		·	underline on]
6	$ME \to USS$	The ME attempts to set up a call to	[second alpha identifier is displayed with
		"+012340123456".	underline on]
7	$USS \to ME$	The ME displays "CALL 1" The ME receives the CONNECT	[The USS also has to handle the START
,	USS → IVIE	message from the USS.	DTMF and STOP DTMF messages sent
		moodage from the CCC.	by the ME in an appropriate way]
8	$ME \to UICC$	TERMINAL RESPONSE 4.8.1	[Command performed successfully]
		The ME shall not update EF LND with	
		the called party address.	
9	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
'0	OICC IVIL	SET UP CALL 4.8.2	
11	$ME \to UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 4.8.2	
13	$ME \rightarrow USER$	ME displays "CONFIRMATION 2"	
1.1	LICED . ME	during the user confirmation phase	Lugar confirmation is displayed with
14	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with underline off]
15	ME  o USS	The ME attempts to set up a call to	[second alpha identifier is displayed with
	, 000	"+012340123456".	underline off]
		The ME displays "CALL 2"	
16	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.8.1	[Command performed successfully]
	WE 70100	The ME shall not update EF LND with	[command personned edecederany]
		the called party address.	
18	$USER \to ME$	The user ends the call after 10 s.	
40		The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.8.1	
20	$ME \rightarrow UICC$	FETCH	
21	UICC → ME	PROACTIVE COMMAND: SET UP	
	0.00 /	CALL 4.8.1	
22	$ME \to USER$	ME displays "CONFIRMATION 1"	
		during the user confirmation phase	
23	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with
24	ME □USS	The ME attempts to set up a call to	underline on] [second alpha identifier is displayed with
24	IVIL 1000	"+012340123456".	[second alpha identifier is displayed with underline on]
		The ME displays "CALL 1"	
25	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
26	ME	TERMINAL RESPONSE 4.0.4	by the ME in an appropriate way]
26	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.8.1	[Command performed successfully]
		The ME shall not update EF LND with the called party address.	
27	$USER \to ME$	The user ends the call after 10 s.	
	- · · · · · · · · · · · · · · · · · · ·	The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
00	ME :::00	SET UP CALL 4.8.3	
29	$ME \rightarrow UICC$	FETCH	l l

30	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 4.8.3	
31	$ME \rightarrow USER$	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with underline off]
33	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3"	[second alpha identifier is displayed with Undeline off]
34	$USS \to ME$	The ME displays CALE 3 The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with	[Command performed successfully]
36	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 4.8.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	40	B4	D0	04	00	06	40	B4		

## PROACTIVE COMMAND: SET UP CALL 4.8.2

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	B4		

#### PROACTIVE COMMAND: SET UP CALL 4.8.3

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 3"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 3"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.8.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## 27.22.4.13.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

27.22.4.13.4.9 SET UP CALL (support of Text Attribute – Strikethrough On)

27.22.4.13.4.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

## 27.22.4.13.4.9.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the strikethrough text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.9.4 Method of test

#### 27.22.4.13.4.9.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.9.4.2 Procedure

## Expected Sequence 4.9 (SET UP CALL, Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.9.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
4	$ME \rightarrow USER$	CALL 4.9.1 ME displays "CONFIRMATION 1"	
	IVIL -> USER	during the user confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with strikethrough on]
6	$ME \to USS$	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with strikethrough on]
7	$USS \to ME$	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the MF in an appropriate way!
8	$ME \to UICC$	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with	by the ME in an appropriate way] [Command performed successfully]
9	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	
10	$UICC \to ME$	The ME returns in idle mode. PROACTIVE COMMAND PENDING: SET UP CALL 4.9.2	
11	$ME \to UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 4.9.2	
13	$ME \to USER$	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with strikethrough off]
15	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with strikethrough off]
16	$USS \to ME$	The ME displays "CALL 2" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	$ME \to UICC$	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	$USER \to ME$	The user ends the call after 10 s. The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.9.1	
20 21	$\begin{array}{c} ME \to UICC \\ UICC \to ME \end{array}$	FETCH PROACTIVE COMMAND: SET UP	
22	$ME \to USER$	CALL 4.9.1 ME displays "CONFIRMATION 1"	
23	$USER \to ME$	during the user confirmation phase The user confirms the set up call	[user confirmation is displayed with strikethrough on]
24	ME □USS	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with strikethrough on]
25	$USS \to ME$	The ME displays "CALL 1" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	$ME \to UICC$	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with	[Command performed successfully]
27	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP CALL 4.9.3	
29	$ME \to UICC$	FETCH	

30	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 4.9.3	
31	$ME \rightarrow USER$	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with strikethrough off]
33	$ME \rightarrow USS$	The ME attempts to set up a call to "+012340123456".	[second alpha identifier is displayed with strikethrough off]
34	$USS \to ME$	The ME displays "CALL 3" The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with	[Command performed successfully]
36	$USER \to ME$	the called party address. The user ends the call after 10 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 4.9.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	80	B4	D0	04	00	06	80	B4		

## PROACTIVE COMMAND: SET UP CALL 4.9.2

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

#### Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	B4		

#### PROACTIVE COMMAND: SET UP CALL 4.9.3

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 3"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 3"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.9.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## 27.22.4.13.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.13.4.10 SET UP CALL (support of Text Attribute – Foreground and Background Colour)

27.22.4.13.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

## 27.22.4.13.4.10.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the foreground and background colour text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.4.10.4 Method of test

#### 27.22.4.13.4.10.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.10.4.2 Procedure

## Expected Sequence 4.10 (SET UP CALL, Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 4.10.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 4.10.1	
4	$ME \rightarrow USER$	ME displays "CONFIRMATION 1"	
5	LICED . ME	during the user confirmation phase The user confirms the set up call	Lugar confirmation is displayed with
3	$USER \to ME$	The user committis the set up can	[user confirmation is displayed with foreground and background colour
			according to Text Attribute configuration]
6	$ME \to USS$	The ME attempts to set up a call to	[second alpha identifier is displayed with
	ME 7000	"+012340123456".	foreground and background colour
		The ME displays "CALL 1"	according to Text Attribute configuration]
7	$USS \to ME$	The ME receives the CONNECT	[The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
			by the ME in an appropriate way]
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.10.1	[Command performed successfully]
		The ME shall not update EF LND with	
9	LICED . ME	the called party address. The user ends the call after 10 s.	
9	$USER \to ME$	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
	OIOO / IVIL	SET UP CALL 4.10.2	
11	$ME \rightarrow UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 4.10.2	
13	$ME \rightarrow USER$	ME displays "CONFIRMATION 2"	
		during the user confirmation phase	
14	$USER \to ME$	The user confirms the set up call	[user confirmation is displayed with ME"s
			default foreground and background colourl
15	ME  o USS	The ME attempts to set up a call to	[second alpha identifier is displayed with
13	IVIE - USS	"+012340123456".	ME"s default foreground and
		The ME displays "CALL 2"	background colour]
16	$USS \to ME$	The ME receives the CONNECT	The USS also has to handle the START
		message from the USS.	DTMF and STOP DTMF messages sent
			by the ME in an appropriate way]
17	$ME \rightarrow UICC$	TERMINAL RESPONSE 4.10.1	[Command performed successfully]
		The ME shall not update EF LND with	
40		the called party address.	
18	$USER \to ME$	The user ends the call after 10 s.	
		The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 4.10.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0 Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Bright Yellow Foreground, Dark Green Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
-	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4 <sup>E</sup>	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0 <sup>E</sup>	00	B4	D0	04	00	06	00	4B		

#### PROACTIVE COMMAND: SET UP CALL 4.10.2

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
•	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		

#### TERMINAL RESPONSE: SET UP CALL 4.10.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

#### Coding:

BER-TL\	: 81	03	01	10	00	82	02	82	81	83	01	00	
---------	------	----	----	----	----	----	----	----	----	----	----	----	--

## 27.22.4.13.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

## 27.22.4.13.5 SET UP CALL (UCS2 Display in *Cyrillic*)

27.22.4.13.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.13.5.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

## 27.22.4.13.5.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.5.4 Method of test

#### 27.22.4.13.5.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.13.5.4.2 Procedure

# Expected Sequence 5.1 (SET UP CALL with UCS2 – Cyrillic Characters, call confirmed by the user and connected)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET	
		UP CALL 5.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 5.1.1	
4	$ME \rightarrow USER$	ME displays "ЗДРАВСТВУЙТЕ" during user confirmation phase.	["ЗДРАВСТВУЙТЕ": 'Hello' in Russian]
5	$USER \to ME$	The user confirms the call set up	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to "+012340123456"	
7	$USS \to ME$	The ME receives the CONNECT message from the USS.	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 5.1.1 The ME shall not update EF LND with the	[Command performed successfully]
9	$USER \to ME$	called party address. The user ends the call after 5 s. The ME returns to idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 5.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456"

## Coding:

BER-TLV:	D0	2D	81	03	01	10	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	86	07	91	10	32	04	21	43	65	

## TERMINAL RESPONSE: SET UP CALL 5.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## Expected Sequence 5.2 (SET UP CALL, two alpha identifiers coded in UCS2 - Cyrillic Characters)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 5.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 5.2.1	
4	$ME \rightarrow USER$	ME displays "ЗДРАВСТВУЙТЕ1" during	['ЗДРАВСТВУЙТЕ1' : 'Hello1' in
			Russian]
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to	[second alpha identifier]
		"+012340123456".	['ЗДРАВСТВУЙТЕ2' : 'Hello2' in
		, , , , , , , , , , , , , , , , , , , ,	Russian]
7	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 5.2.1	[Command performed successfully]
		The ME shall not update EF LND with	
		the called party address.	
9	USER $\rightarrow$ ME	The user ends the call after 5 s.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 5.2.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456" Alpha Identifier (call set up phase): "ЗДРАВСТВУЙТЕ2"

Coding:

BER-TLV:	D0	4C	81	03	01	10	00	82	02	81	83	85
	1B	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	00	31	86	07	91	10	32	04	21	43
	65	85	1B	80	04	17	04	14	04	20	04	10
	04	12	04	21	04	22	04	12	04	23	04	19
	04	22	04	15	00	32						

TERMINAL RESPONSE: SET UP CALL 5.2.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## 27.22.4.13.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1 to 5.2.

## 27.22.4.13.6 SET UP CALL (UCS2 Display in Chinese)

27.22.4.13.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.13.6.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in:

- ISO/IEC 10646 [17].

## 27.22.4.13.6.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.6.4 Method of test

## 27.22.4.13.6.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.13.6.4.2 Procedure

# Expected Sequence 6.1 (SET UP CALL with UCS2 – Chinese characters, call confirmed by the user and connected)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET	
		UP CALL 6.1.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL	
		6.1.1	
4	$ME \rightarrow USER$	ME displays "不忙" during user confirmation	['不忙' : 'Not Busy' in Chinese]
		phase.	
5	$USER \to ME$	1	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to	
		"+012340123456"	
7	$USS \to ME$	The ME receives the CONNECT message	
		from the USS.	
8	$ME \to UICC$	TERMINAL RESPONSE 6.1.1	[Command performed successfully]
		The ME shall not update EF LND with the	
		called party address.	
9	$USER \to ME$	The user ends the call after 5 s.	
		The ME returns to idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 6.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "不忙"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456"

## Coding:

BER-TLV:	D0	19	81	03	01	10	00	82	02	81	83	85
	05	80	4E	0D	5F	D9	86	07	91	10	32	04
	21	43	65									

## TERMINAL RESPONSE: SET UP CALL 6.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## Expected Sequence 6.2 (SET UP CALL, two alpha identifiers coded in UCS2 - Chinese characters)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
2	ME IIIOO	SET UP CALL 6.2.1 FETCH	
_	11.12	1. –	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 6.2.1	
4	$ME \rightarrow USER$	ME displays "确定" during the user	['确定': 'Confirmation' in Chinese]
5 6		confirmation phase The user confirms the set up call The ME attempts to set up a call to "+012340123456".	[user confirmation] [second alpha identifier] ['打电话' : 'CALL' in Chinese]
		The ME displays "打电话"	
7	$USS \to ME$	The ME receives the CONNECT message from the USS.	
8	$ME \to UICC$	TERMINAL RESPONSE 6.2.1 The ME shall not update EF LND with	[Command performed successfully]
9	$USER \to ME$	the called party address. The user ends the call after 5 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 6.2.1

Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC Destination device: Network Alpha identifier: "确定"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456"

Alpha Identifier (call set up phase): "打电话"

Coding:

BER-TLV:	D0	22	81	03	01	10	00	82	02	81	83	85
	05	80	78	6E	5B	9A	86	07	91	10	32	04
	21	43	65	85	07	80	62	53	75	35	8B	DD

## TERMINAL RESPONSE: SET UP CALL 6.2.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

DED TIVE	0.4	00	0.4	10	00	0.2	00	0.0	0.4	0.2	01	00
BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

#### 27.22.4.13.6.5 Test requirement

The ME shall operate in the manner defined in expected sequences 6.1 to 6.2.

## 27.22.4.13.7 SET UP CALL (UCS2 Display in Katakana)

27.22.4.13.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.13.7.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in:

- ISO/IEC 10646 [17].

## 27.22.4.13.7.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.7.4 Method of test

## 27.22.4.13.7.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.13.7.4.2 Procedure

# Expected Sequence 7.1 (SET UP CALL with UCS2 – Katakana characters, call confirmed by the user and connected)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET	
		UP CALL 7.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 7.1.1	
4	$ME \to USER$	ME displays "ル" during user confirmation phase.	[Character in Katakana]
5	$USER \to ME$	The user confirms the call set up	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to "+012340123456"	
7	$USS \to ME$	The ME receives the CONNECT message from the USS.	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE 7.1.1 The ME shall not update EF LND with the	[Command performed successfully]
9	$USER \to ME$	called party address. The user ends the call after 5 s. The ME returns to idle mode.	

## PROACTIVE COMMAND: SET UP CALL 7.1.1

#### Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "/\mathcal{V}"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456"

#### Coding:

BER-TLV:	D0	17	81	03	01	10	00	82	02	81	83	85
	03	80	30	EB	86	07	91	10	32	04	21	43
	65											

## TERMINAL RESPONSE: SET UP CALL 7.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## Expected Sequence 7.2 (SET UP CALL, two alpha identifiers coded in UCS2 - Katakana characters)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		SET UP CALL 7.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		CALL 7.2.1	
4	$ME \rightarrow USER$	ME displays "ル1" during the user	[Character in Katakana]
		confirmation phase	
5	$USER \to ME$	The user confirms the set up call	[user confirmation]
6	$ME \to USS$	The ME attempts to set up a call to	[second alpha identifier]
		"+012340123456".	[Character in Katakana]
		The ME displays "/V2".	
7	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
8	$ME \to UICC$		[Command performed successfully]
		The ME shall not update EF LND with	
		the called party address.	
9	USER $\rightarrow$ ME	The user ends the call after 5 s.	
		The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 7.2.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "//1"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string "012340123456"

Alpha Identifier (call set up phase): "/\(\mathcal{D}\)2"

Coding:

BER-TLV:	D0	20	81	03	01	10	00	82	02	81	83	85
	05	80	30	EB	00	31	86	07	91	10	32	04
	21	43	65	85	05	80	30	EB	00	32		

## TERMINAL RESPONSE: SET UP CALL 7.2.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00

## 27.22.4.13.7.5 Test requirement

The ME shall operate in the manner defined in expected sequences 7.1 to 7.2.

## 27.22.4.14 POLLING OFF

## 27.22.4.14.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.14.2 Conformance requirement

The ME shall support the POLLING OFF as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.14, clause 6.6.14, clause 6.8, clause 6.11, clause 8.6 and clause 8.7.

## 27.22.4.14.3 Test purpose

To verify that the ME cancels the effect of any previous POLL INTERVAL commands and does not effect UICC presence detection.

## 27.22.4.14.4 Method of test

## 27.22.4.14.4.1 Initial conditions

The ME is connected to the USIM Simulator and to the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.14.4.2 Procedure

## **Expected Sequence 1.1 (POLLING OFF)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: POLL INTERVAL	
		1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	Interval = 1 min
		POLL INTERVAL 1.1.1	
4	$ME \to UICC$	TERMINAL RESPONSE: POLL	[command performed successfully, duration
		INTERVAL 1.1.1 A or	depends on the ME"s capabilities]
		TERMINAL RESPONSE: POLL	
		INTERVAL 1.1.1B	
5	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: POLLING OFF	
_		1.1.2	
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND:	
		POLLING OFF 1.1.2	
8	$ME \rightarrow UICC$		[command performed successfully]
_		POLLING OFF 1.1.2	
9	$USER \to ME$	Call to be set up	
10	$ME \rightarrow UICC$	Periods of inactivity on the	
		UICC-ME interfaceshall not	
		exceed 30 seconds	
11	$USER \to ME$	Call to be terminated 3 minutes	
		after call setup	

#### PROACTIVE COMMAND: POLL INTERVAL 1.1.1

## Logically:

Command details

Command number:

Command type: POLL INTERVAL

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Duration

Time unit: Minutes
Time interval: 1

## Coding:

BER-TLV:	D0	0D	81	03	01	03	00	82	02	81	82	84
	02	00	01									

## TERMINAL RESPONSE: POLL INTERVAL 1.1.1A

## Logically:

Command details

Command number: 1

Command type: POLL INTERVAL

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Duration

Time unit: Minutes
Time interval: 1

Coding:

BER-TLV:	81	03	01	03	00	82	02	82	81	83	01	00
	84	02	00	01								

#### TERMINAL RESPONSE: POLL INTERVAL 1.1.1B

Logically:

Command details

Command number: 1

Command type: POLL INTERVAL

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Duration

Time unit: Seconds
Time interval: 60

Coding:

BER-TLV:	81	03	01	03	00	82	02	82	81	83	01	00
	84	02	01	3C								

Note: If the requested poll interval is not supported by the ME, the ME is allowed to use a different one as

stated in TS 31.111 [15], subclause 6.4.6.

PROACTIVE COMMAND: POLLING OFF 1.1.2

Logically:

Command details

Command number: 1

Command type: POLLING OFF

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV: D0 09 81 03 01 04 00	82	02	81	82
-------------------------------	----	----	----	----

## TERMINAL RESPONSE: POLLING OFF 1.1.2

Logically:

Command details

Command number: 1

Command type: POLLING OFF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	04	00	82	02	82	81	83	01	00
DEIX IEV.	01	03	01	0-	00	02	02	02	01	03	01	00

## 27.22.4.14.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.4.15 PROVIDE LOCAL INFORMATION

## 27.22.4.15.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.15.2 Conformance requirement

The ME shall support the PROVIDE LOCAL INFORMATION facility as defined in:

- TS 31.111 [15] clause 6.4.15.

## 27.22.4.15.3 Test purpose

To verify that the ME returns the following requested local information within a TERMINAL RESPONSE:

- location information:
  - Mobile Country Code (MCC);
  - Mobile Network Code (MNC);
  - Location Area Code (LAC); and
  - cell ID of the current serving cell;
- the IMEI of the ME;
- the Network Measurement Results and the BCCH channel list;
- the current date, time and time zone;
- the current ME language setting;
- the Timing Advance;
- the Access Technology;
- the IMEISV
- the Search Mode change
- the Battery charge State
- the UTRAN measurements.

if the local information is stored in the ME; otherwise, sends the correct error code to the UICC in the TERMINAL RESPONSE.

#### 27.22.4.15.4 Method of tests

#### 27.22.4.15.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME is connected to the USS and has performed the location update procedure.

The UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The GERAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;
- Timing advance = 0;
- Neighbour allocations = 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;
- Timing advance = 0;
- Neighbour allocations = 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585.

The elementary files are coded as the USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Expected sequence 1.3 and 1.6 shall be used on a USS setting up only a GERAN or PCS 1900 cell and expected sequences 1.7 and 1.12 shall be used on a USS setting up only a UTRAN cell.

Expected sequence 1.12 requires 2 UTRA cells on the same frequency and 1.13 requires 2 UTRA cells on different frequencies.

#### 27.22.4.15.4.2 Procedure

# Expected Sequence 1.1 (PROVIDE LOCAL INFORMATION, Local Info (MCC, MNC, LAC & Cell ID))

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING PROVIDE LOCAL	
		INFORMATION 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		PROVIDE LOCAL INFORMATION	
		1.1.1	
4	$ME \rightarrow UICC$		[Command performed successfully, MCC MNC LAC
		PROVIDE LOCAL INFORMATION	and Cell Identity as USS, option A shall apply for
		1.1.1A	3GPP parameters]
			[Command performed successfully, MCC MNC LAC
			and Cell Identity as USS, option B shall apply for
		PROVIDE LOCAL INFORMATION	PCS1900 parameters]
		1.1.1B	

#### PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.1.1

#### Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	26	00	82	02	81	82
DLIX-ILV.		0.0	01	00	O I	20	00	02	02	01	02

## TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1A

### Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**Location Information** 

MCC & MNC: MCC = 001, MNC = 01

Location Area Code: 0001 Cell Identity Value: 0001

Extended Cell Identity Value: RNC-id value (for Rel-4 onwards), see also Note 2

### Coding:

BER-TLV:	81	03	01	26	00	82	02	82	81	83	01	00
	93	Note 1	00	F1	10	00	01	00	01	Note 2		

Note 1: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 2: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

## TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1B

#### Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**Location Information** 

MCC & MNC: MCC = 001, MNC = 011

Location Area Code: 0001 Cell Identity Value: 0001

#### Coding:

BER-TLV:	81	03	01	26	00	82	02	82	81	83	01	00
	93	07	00	11	10	00	01	00	01			

### **Expected Sequence 1.2 (PROVIDE LOCAL INFORMATION, IMEI of the ME)**

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	Identity request	[Identity type = IMEI]
2	$ME \rightarrow USS$	Identity response	[Mobile identity = IMEI]
3	$UICC \to ME$	PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.2.1	
4	$ME \rightarrow UICC$	FETCH	
5	$UICC \to ME$	PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.2.1	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.2.1	[Command performed successfully, IMEI as USS, but spare digit shall be zero when transmitted by the ME]

#### PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.2.1

# Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "01" IMEI of the ME

Device identities

Source device: UICC
Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	26	01	82	02	81	82

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.2.1

Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "01" IMEI of the ME

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**IMEI** 

IMEI of the ME: The IMEI of the ME

The result coding depends on the Mobile IMEI value as declared in table A.2/23.

#### Coding:

BER-TLV:	81	03	01	26	01	82	02	82	81	83	01	00
·	94	80	XX	XX	XX	XX	XX	XX	XX	XX		

# Expected Sequence 1.3 (PROVIDE LOCAL INFORMATION, Network Measurement Results (NMR))

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING PROVIDE LOCAL	
		INFORMATION 1.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		PROVIDE LOCAL INFORMATION	
		1.3.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE:	[Command performed successfully,
		PROVIDE LOCAL INFORMATION	NMR as USS ]
		1.3.1	-

### PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.3.1

#### Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION
Qualifier: "02" Network Measurement Results

Device identities

Source device: UICC Destination device: ME

# Coding:

BER-TLV:	D0	09	81	03	01	26	02	82	02	81	82

## TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.3.1

The actual values of the measurements are not tested.

#### Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION
Qualifier: "02" Network Measurement Results

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Network Measurement Results RXLEV-FULL-SERVING-CELL=52, BA not used, DTX not used, as

an example in the BER-TLV)

BCCH channel list 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585

Coding:

BER-TLV:	81	03	01	26	02	82	02	82	81	83	01	00
_	96	10	34	34	00	00	00	00	00	00	00	00
	00	00	00	00	00	00	9D	0D	8C	63	58	E2
	39	8F	63	F9	06	45	91	A4	90			

## Expected Sequence 1.4 (PROVIDE LOCAL INFORMATION, Date, Time, Time Zone)

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.4.

## **Expected Sequence 1.5 (PROVIDE LOCAL INFORMATION, Language setting)**

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.5.

# **Expected Sequence 1.6 (PROVIDE LOCAL INFORMATION, Timing advance)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING	
		PROVIDE LOCAL INFORMATION 1.6.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: PROVIDE	
		LOCAL INFORMATION 1.6.1	
4	$ME \to UICC$	TERMINAL RESPONSE: PROVIDE	[Command performed successfully]
		LOCAL INFORMATION 1.6.1	

### PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.6.1

# Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "05" Timing Advance

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV: D0 09 81 03 01 26 05 82 02 81 82
---

### TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.6.1

## Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "05" Timing Advance

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Timing Advance 2 bytes

ME status: "00" ME is in idle state

Timing Advance: 0

Coding:

BER-TLV:	81	03	01	26	05	82	02	82	81	83	01	00
	ΑE	02	00	00								

# **Expected Sequence 1.7 (PROVIDE LOCAL INFORMATION, Access Technology**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING PROVIDE LOCAL	
		INFORMATION 1.7.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		PROVIDE LOCAL INFORMATION	
		1.7.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE:	[Command performed successfully]
		PROVIDE LOCAL INFORMATION	
		1.7.1	

### PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.7.1

Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "06" Access Technology

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV: D0 09 81 03 01 26 06 82 02 81 82	03 01 26 06 82 02 81 82
---	-------------------------

#### TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.7.1

Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "06" Access Technology

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Access Technology

Technology: UTRAN

Coding:

BER-TLV:	81	03	01	26	06	82	02	82	81	83	01	00
	3F	01	03									

# **Expected Sequence 1.8 (Void)**

# **Expected Sequence 1.9 (PROVIDE LOCAL INFORMATION, IMEISV of the terminal)**

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	Identity request	[Identity type = IMEISV]
2	$ME \rightarrow USS$	Identity response	[Mobile identity = IMEISV]
3	$UICC \to ME$	PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.9.1	
4	$ME \rightarrow UICC$	FETCH	
5	$UICC \to ME$	PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.9.1	
6	ME → UICC	TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.9.1	[Command performed successfully, IMEISV] as USS

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.9.1

Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "08" IMEISV of the ME

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV: D0 09 81	03 01	26 08	82	02	81	82
-------------------	-------	-------	----	----	----	----

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.9.1

Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION

Qualifier: "08" IMEISV of the ME

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

**IMEISV** 

IMEISV of the ME: The IMEISV of the ME

The result coding depends on the ME IMEISV value as declared in table A.2/24.

Coding:

BER-TLV:	81	03	01	26	80	82	02	82	81	83	01	00
	F2	09	XX	XX	XX	XX	XX	XX	XX	XX	XX	

### Expected Sequence 1.10 (PROVIDE LOCAL INFORMATION, Search Mode Change)

**TBD** 

### Expected Sequence 1.11 (PROVIDE LOCAL INFORMATION, charge state of the battery)

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.11.

#### Expected Sequence 1.12 (PROVIDE LOCAL INFORMATION, Intra-Frequency UTRAN Measurements)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING PROVIDE LOCAL	
		INFORMATION 1.12.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		PROVIDE LOCAL INFORMATION	
		1.12.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE:	[Command performed successfully]
		PROVIDE LOCAL INFORMATION	
		1.12.1	

### PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.12.1

Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION
Qualifier: "02" Network Measurement Results

Device identities

Source device: UICC
Destination device: ME
UTRAN Measurement Qualifier

UTRAN Measurement Qualifier: "01" Intra-frequency measurements

#### Coding:

BER-TLV:	D0	0C	81	03	01	26	02	82	02	81	82	69
	01	01										

## TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.12.1

The actual values of the measurements are not tested.

Logically:

Command details

Command number:

Command type: PROVIDE LOCAL INFORMATION
Qualifier: "02" Network Measurement Results

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully
Network Measurement Results MEASUREMENT REPORT message

intra Freq Measured Results List

Coding:

BER-TLV:	81	03	01	26	02	82	02	82	81	83	01	00
	96	Note	80	00	Note							
		1			2							

Note 1: This is the length indicator for the following bytes which represent the Measurement report coded in ASN.1 and therefore the length cannot be foreseen.

Note2: The remaining bytes shall not be verified.

# **Expected Sequence 1.13 (PROVIDE LOCAL INFORMATION, Inter-frequency UTRAN Measurements)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING PROVIDE LOCAL	
		INFORMATION 1.13.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		PROVIDE LOCAL INFORMATION	
		1.13.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE:	[Command performed successfully]
		PROVIDE LOCAL INFORMATION	
		1.13.1	

#### PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.13.1

## Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION
Qualifier: "02" Network Measurement Results

Device identities

Source device: UICC
Destination device: ME
UTRAN Measurement Qualifier

UTRAN Measurement Qualifier: "02" Inter-frequency measurements

## Coding:

BER-TLV:	D0	0C	81	03	01	26	02	82	02	81	82	69
	01	02										

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.13.1

The actual values of the measurements are not tested.

### Logically:

Command details

Command number: 1

Command type: PROVIDE LOCAL INFORMATION
Qualifier: "02" Network Measurement Results

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully
Network Measurement Results MEASUREMENT REPORT message
interFreqMeasuredResultsList

Coding:

BER-TLV:	81	03	01	26	02	82	02	82	81	83	01	00
	96	Note	80	11	Note							
		1			2							

Note 1: This is the length indicator for the following bytes which represent the Measurement report coded in ASN.1 and therefore the length cannot be foreseen.

Note2: The remaining bytes shall not be verified.

## 27.22.4.15.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.13.

### 27.22.4.16 SET UP EVENT LIST

# 27.22.4.16.1 SET UP EVENT LIST (normal)

27.22.4.16.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.16.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Event List facility as defined in:

- TS 31.111 [15] clause 6.4.16 and clause 6.6.16.

Additionally the ME shall support the Event Download: Call Connect and the Event Download: Call Disconnected mechanism as defined in:

- TS 31.111 [15] clause 11.2, clause 11.2.1, clause 11.2.2, clause 11.3, clause 11.3.1 and clause 11.3.2.

### 27.22.4.16.1.3 Test purpose

To verify that the ME accepts a list of events that it shall monitor the current list of events supplied by the UICC, is able to have this current list of events replaced and is able to have the list of events removed.

To verify that when the ME has successfully accepted or removed the list of events, it shall send TERMINAL RESPONSE (OK) to the UICC and when the ME is not able to successfully accept or remove the list of events, it shall send TERMINAL RESPONSE (Command beyond ME's capabilities).

27.22.4.16.1.4 Method of test

27.22.4.16.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.16.1.4.2 Procedure

# Expected Sequence 1.1 (SET UP EVENT LIST, Set Up Call Connect Event)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP	
		EVENT LIST 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT	
		LIST 1.1.1	
4	$ME \to UICC$	TERMINAL RESPONSE: SET UP EVENT	
		LIST 1.1.1	
5	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
6	$USS \to ME$	SETUP 1.1.1	[Incoming call alert]
7	$USER \to ME$	User shall accept the incoming call	
8	$ME \to USS$	CONNECT 1.1.1	
9	$ME \to UICC$	ENVELOPE: EVENT DOWNLOAD CALL	[Call Connected Event]
		CONNECTED 1.1.1	-
10	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	

# PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

# Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Connected

### Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99	
_	01	01											

### TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

#### Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01	05 00 82	02 82 81 83	01 00
-------------------	----------	-------------	-------

# **SET UP 1.1.1**

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)

Address

TON: "Unknown"

NPI: "ISDN/ telephone numbering plan"

Dialling number string: "9876"

CONNECT 1.1.1

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

ENVELOPE: EVENT DOWNLOAD CALL CONNECTED 1.1.1

Logically

Event list

Event 1: Call Connected

Device identities

Source device: ME
Destination device: UICC

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

Coding:

BER-TLV:	D6	0A	99	01	01	82	02	82	81	9C	01	80
----------	----	----	----	----	----	----	----	----	----	----	----	----

# **Expected Sequence 1.2 (SET UP EVENT LIST, Replace Event)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
		1.2.1	
2	ME → UICC		[C    C
3	$UICC \to ME$	EVENT LIST 1.2.1	[Call Connected and Call Disconnected
4	ME LUCC	TERMINAL RESPONSE: SET UP	Events]
4	ME → OICC	EVENT LIST 1.2.1	
5	$UICC \to ME$	PROACTIVE COMMAND	
	0.00 / III.E	PENDING: SET UP EVENT LIST	
		1.2.2	
6	$ME \to UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[Call Disconnected Event]
		EVENT LIST 1.2.2	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
9	11100 ME	EVENT LIST 1.2.2	
9	UICC → ME	PROACTIVE UICC SESSION ENDED	
10	$USS \to ME$	SETUP 1.2.2	[Incoming call alert]
11		User shall accept the incoming call	[oong can along
12		CONNECT 1.2.2	
13		DISCONNECT 1.2.2	
14	$ME \to UICC$	ENVELOPE: EVENT DOWNLOAD	[Call Disconnect Event]
		CALL DISCONNECT 1.2.2A	
		or	
		ENVELOPE: EVENT DOWNLOAD	
4.5		CALL DISCONNECT 1.2.2B	
15	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	

# PROACTIVE COMMAND: SET UP EVENT LIST 1.2.1

# Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Connected Event 2: Call Disconnected

# Coding:

BER-TLV:	D0	0D	81	03	01	05	00	82	02	81	82	99
	02	01	02									

# TERMINAL RESPONSE: SET UP EVENT LIST 1.2.1

# Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 05 00 82 02 82 81 83 01 00

480

#### PROACTIVE COMMAND: SET UP EVENT LIST 1.2.2

Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Disconnected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	02										

#### TERMINAL RESPONSE: SET UP EVENT LIST 1.2.2

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

# **SET UP 1.2.2**

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)

Address

TON: "Unknown"

NPI: "ISDN/ telephone numbering plan"

Dialling number string: "9876"

CONNECT 1.2.2

Logically:

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

# **DISCONNECT 1.2.2**

Logically:

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Cause

Value: Normal call clearing

### ENVELOPE: EVENT DOWNLOAD CALL DISCONNECTED 1.2.2A

Logically:

Event list

Event 1: Call Disconnected

Device identities

Source device: Network
Destination device: UICC

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Cause

Value: Normal call clearing

Coding:

BER-TLV:	D6	0E	99	01	02	82	02	83	81	9C	01	00
	9A	02	60	90								

#### ENVELOPE: EVENT DOWNLOAD CALL DISCONNECTED 1.2.2B

Logically:

Event list

Event 1: Call Disconnected

Device identities

Source device: Network
Destination device: UICC

Transaction identifier

Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)

Cause

Value: Normal call clearing

Coding:

BER-TLV:	D6	0E	99	01	02	82	02	83	81	9C	01	00
·	QΔ	02	FΩ	90								

# **Expected Sequence 1.3 (SET UP EVENT LIST, Remove Event)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
		1.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[Call Connected Event]
		EVENT LIST 1.3.1	
	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
		EVENT LIST 1.3.1	
4	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
_		1.3.2	
5	$ME \rightarrow UICC$		
6	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[Remove Event]
_		EVENT LIST 1.3.2	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
8	LUCO	EVENT LIST 1.3.2	
0	UICC → ME	PROACTIVE UICC SESSION ENDED	
10	LICC VME	SETUP 1.3.2	[Incoming call alert]
11		User shall accept the incoming call	[Incoming can alert]
12		CONNECT 1.3.2	
13		No ENVELOPE: EVENT	
13	INIE → UICC	DOWNLOAD (call connected) sent	
14	$USS \to ME$	DISCONNECT 1.3.2	
14		DIOCONNECT 1.3.2	

### PROACTIVE COMMAND: SET UP EVENT LIST 1.3.1

Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

TERMINAL RESPONSE: SET UP EVENT LIST 1.3.1

Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

#### PROACTIVE COMMAND: SET UP EVENT LIST 1.3.2

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00

Device identities

Source device: UICC
Destination device: ME
Event list: Empty

Coding:

BER-TLV:	D0	0B	81	03	01	05	00	82	02	81	82	99
	00											

### TERMINAL RESPONSE: SET UP EVENT LIST 1.3.2

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

### **SET UP 1.3.2**

Logically:

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Address

TON: "Unknown"

NPI: "ISDN/ telephone numbering plan"

Dialling number string: "9876"

CONNECT 1.3.2

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

**DISCONNECT 1.3.2** 

Logically:

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Cause

Value: Normal call clearing

# Expected Sequence 1.4 (SET UP EVENT LIST, Remove Event on ME Power Cycle)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
		1.4.1	
2	$ME \to UICC$		
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[Call Connected Event]
		EVENT LIST 1.4.1	
	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
		EVENT LIST 1.4.1	
4	$UICC \to ME$	PROACTIVE UICC SESSION	
_		ENDED	
5		Power off ME	
6		Power on ME	
7	$USS \to ME$	SETUP 1.4.1	[Incoming call alert]
8	$USER \to ME$	User shall accept the incoming call	
9	$ME \to USS$	CONNECT 1.4.1	
10	$ME \to UICC$	No ENVELOPE: EVENT	
		DOWNLOAD (call connected) sent	
11	$USS \to ME$	DISCONNECT 1.4.1	

# PROACTIVE COMMAND: SET UP EVENT LIST 1.4.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

TERMINAL RESPONSE: SET UP EVENT LIST 1.4.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

#### **SET UP 1.4.1**

#### Logically:

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Address

TON: "Unknown"

NPI: "ISDN/ telephone numbering plan"

Dialling number string: "9876"

#### CONNECT 1.4.1

#### Logically:

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

### DISCONNECT 1.4.1

#### Logically:

Transaction identifier

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Cause

Value: Normal call clearing

#### 27.22.4.16.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4.

# 27.22.4.17 PERFORM CARD APDU

# 27.22.4.17.1 PERFORM CARD APDU (normal)

# 27.22.4.17.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.17.1.2 Conformance requirement

The ME shall support the Proactive UICC: Perform Card APDU facility as defined in:

- TS 31.111 [15] clause 6.1, clause 5.2, clause 6.4.17, clause 6.6.17, clause 6.8, clause 8.6, clause 8.7, clause 8.35, clause 8.36 and clause 8.12.9.

Additionally the ME shall support multiple card operation as defined in:

- TS 31.111 [15] clause 6.4.19, clause 6.6.19, clause 6.4.18 and clause 6.6.18.

# 27.22.4.17.1.3 Test purpose

To verify that the ME sends an APDU command to the additional card identified in the PERFORM CARD APDU proactive UICC command, and successfully returns the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

In this particular case a special Test-SIM (TestSIM) with T=0 protocol is chosen as additional card for the additional ME card reader (for coding of the TestSIM see annex A).

27.22.4.17.1.4 Method of test

27.22.4.17.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The TestSIM is inserted in the additional ME card reader.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

The elementary files of the TestSIM are coded as defined in annex A. Another card with different parameters may be used as TestSIM to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

27.22.4.17.1.4.2 Procedure

# Expected Sequence 1.1 (PERFORM CARD APDU, card reader 1, additional card inserted, Select MF and Get Response)

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.1.

# Expected Sequence 1.2 (PERFORM CARD APDU, card reader 1, additional card inserted, Select DF GSM, Select EF PLMN, Update Binary, Read Binary on EF PLMN)

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.2.

### Expected Sequence 1.3 (PERFORM CARD APDU, card reader 1, card inserted, card powered off)

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.3.

#### Expected Sequence 1.4 (PERFORM CARD APDU, card reader 1, no card inserted)

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.4.

# Expected Sequence 1.5 (PERFORM CARD APDU, card reader 7 (which is not the valid card reader identifier of the additional ME card reader))

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.5.

27.22.4.17.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.5.

# 27.22.4.17.2 PERFORM CARD APDU (detachable card reader)

27.22.4.17.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.17.2.2 Conformance requirement

27.22.4.17.2.3 Test purpose

To verify that the ME sends an APDU command to the additional card identified in the PERFORM CARD APDU proactive UICC command, and successfully returns the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

27.22.4.17.2.4 Method of test

27.22.4.17.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The card reader shall be detached from the ME.

#### 27.22.4.17.2.4.2 Procedure

### Expected Sequence 2.1 (PERFORM CARD APDU, card reader 1, card reader detached)

See ETSI TS 102 384 [26] in subclause 27.22.4.17.2.4.2, Expected Sequence 2.1.

### 27.22.4.17.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.18 POWER OFF CARD

### 27.22.4.18.1 POWER OFF CARD (normal)

### 27.22.4.18.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.18.1.2 Conformance requirement

The ME shall support the Proactive UICC: Power Off Card facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.18, clause 6.6.18, clause 8.6, clause 8.7, clause 8.12, clause 8.12.9, clause 5.2 and annex H.

# 27.22.4.18.1.3 Test purpose

To verify that the ME closes a session with the additional card identified in the POWER OFF CARD proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

#### 27.22.4.18.1.4 Method of test

#### 27.22.4.18.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to aSIM Simulator (SIM2). Instead of a SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

27.22.4.18.1.4.2 Procedure

### Expected Sequence 1.1 (POWER OFF CARD, card reader 1)

See ETSI TS 102 384 [26] in subclause 27.22.4.18.1.4.2, Expected Sequence 1.1.

### Expected Sequence 1.2 (POWER OFF CARD, card reader 1, no card inserted)

See ETSI TS 102 384 [26] in subclause 27.22.4.18.1.4.2, Expected Sequence 1.2.

27.22.4.18.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.2.

27.22.4.18.2 POWER OFF CARD (detachable card reader)

27.22.4.18.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.18.2.2 Conformance requirement

Void.

27.22.4.18.2.3 Test purpose

To verify that the ME closes a session with the additional card identified in the POWER OFF CARD proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.18.2.4 Method of test

27.22.4.18.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2).

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

The card reader shall be detached from the ME.

27.22.4.18.2.4.2 Procedure

# Expected Sequence 2.1 (POWER OFF CARD, card reader 1, no card reader attached)

See ETSI TS 102 384 [26] in subclause 27.22.4.18.2.4.2, Expected Sequence 2.1.

27.22.4.18.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.19 POWER ON CARD

### 27.22.4.19.1 POWER ON CARD (normal)

### 27.22.4.19.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.19.1.2 Conformance requirement

The ME shall support the Proactive UICC: Power On Card facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.19, clause 6.6.19, clause 8.6, clause 8.7, clause 8.12, clause 8.12.9, clause 8.34, clause 5.2 and annex H.

### 27.22.4.19.1.3 Test purpose

To verify that the ME starts a session with the additional card identified in the POWER ON CARD proactive UICC command, and successfully returns the Answer To Reset within the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

#### 27.22.4.19.1.4 Method of test

### 27.22.4.19.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2). Instead of the SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

## 27.22.4.19.1.4.2 Procedure

#### Expected Sequence 1.1 (POWER ON CARD, card reader 1)

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.1.

### Expected Sequence 1.2 (POWER ON CARD, card reader 1, no ATR)

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.2.

## Expected Sequence 1.3 (POWER ON CARD, card reader 1, no card inserted)

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.3.

### 27.22.4.19.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

# 27.22.4.19.2 POWER ON CARD (detachable card reader)

27.22.4.19.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.19.2.2 Conformance requirement

27.22.4.19.2.3 Test purpose

To verify that the ME starts a session with the additional card identified in the POWER ON CARD proactive UICC command, and successfully returns the Answer To Reset within the TERMINAL RESPONSE command send to the UICC.

27.22.4.19.2.4 Method of test

27.22.4.19.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The card reader shall be detached from the ME.

27.22.4.19.2.4.2 Procedure

#### Expected Sequence 2.1 (POWER ON CARD, card reader 1, no card reader attached)

See ETSI TS 102 384 [26] in subclause 27.22.4.19.2.4.2, Expected Sequence 2.1.

27.22.4.19.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.20 GET READER STATUS

# 27.22.4.20.1 GET READER STATUS (normal)

27.22.4.20.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.20.1.2 Conformance requirement

The ME shall support the Proactive UICC: Get Card Reader Status facility as defined in:

- TS 31.111 [15] clause 6.1, clause 5.2, clause 6.4.20, clause 6.6.20, clause 6.8, clause 8.6, clause 8.7, clause 8.33, clause 8.57 and annex H.

Additionally the ME shall support multiple card operation as defined in:

- TS 31.111 [15] clause 6.4.19, clause 6.6.19, clause 6.4.18 and clause 6.6.18.

#### 27.22.4.20.1.3 Test purpose

To verify that the ME sends starts a session with the additional card identified in the GET CARD READER STATUS proactive UICC command, and successfully returns information about all interfaces to additional card reader(s) in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

In this test case the SIM-Simulator (SIM2) shall response with the ATR "3B 00".

27.22.4.20.1.4 Method of test

27.22.4.20.1.4.1 Initial conditions

The ME shall support the Proactive UICC: Get Card Reader Status (Card Reader Status) facility. The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2). Instead of the SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

27.22.4.20.1.4.2 Procedure

### Expected Sequence 1.1 (GET CARD READER STATUS, card reader 1, card inserted, card powered)

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.1.

# Expected Sequence 1.2 (GET CARD READER STATUS, card reader 1, card inserted, card not powered)

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.2.

### Expected Sequence 1.3 (GET CARD READER STATUS, card reader 1, card not present)

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.3.

27.22.4.20.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

27.22.4.20.2 GET CARD READER STATUS (detachable card reader)

27.22.4.20.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.20.2.2 Conformance requirement

Void.

27.22.4.20.2.3 Test purpose

To verify that the ME closes a session with the additional card identified in the GET CARD READER STATUS proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.20.2.4 Method of test

27.22.4.20.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

The card reader shall be detached from the ME.

27.22.4.20.2.4.2 Procedure

## Expected Sequence 2.1 (GET CARD READER STATUS, no card reader attached)

See ETSI TS 102 384 [26] in subclause 27.22.4.20.2.4.2, Expected Sequence 2.1.

27.22.4.20.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

# 27.22.4.21 TIMER MANAGEMENT and ENVELOPE TIMER EXPIRATION

### 27.22.4.21.1 TIMER MANAGEMENT (normal)

27.22.4.21.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.21.1.2 Conformance Requirement

The ME shall support the TIMER MANAGEMENT as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.21, clause 6.8, clause 8.6, clause 8.7, clause 8.37 and clause 8.38.

### 27.22.4.21.1.3 Test purpose

To verify that the ME manages correctly its internal timers, start a timer, deactivate a timer or return the current value of a timer according to the Timer Identifier defined in the TIMER MANAGEMENT proactive UICC command.

27.22.4.21.1.4 Method of Test

27.22.4.21.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.21.1.4.2 Procedure

# Expected Sequence 1.1 (TIMER MANAGEMENT, start timer 1 several times, get the current value of the timer and deactivate the timer successfully)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.1.

# Expected Sequence 1.2 (TIMER MANAGEMENT, start timer 2 several times, get the current value of the timer and deactivate the timer successfully)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.2.

# Expected Sequence 1.3 (TIMER MANAGEMENT, start timer 8 several times, get the current value of the timer and deactivate the timer successfully)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.3.

# Expected Sequence1.4 (TIMER MANAGEMENT, try to get the current value of a timer which is not started: action in contradiction with the current timer state)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.4.

# Expected Sequence1.5 (TIMER MANAGEMENT, try to deactivate a timer which is not started: action in contradiction with the current timer state)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.5.

#### Expected Sequence 1.6 (TIMER MANAGEMENT, start 8 timers successfully)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.6.

#### 27.22.4.21.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.6.

## 27.22.4.21.2 ENVELOPE TIMER EXPIRATION (normal)

## 27.22.4.21.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.21.2.2 Conformance requirement

The ME shall support the ENVELOPE (TIMER EXPIRATION) command as defined in the following technical specifications:

- TS 31.111 [15] clause 4.10, clause 7.4.1 and clause 7.4.2.

The ME shall support the TIMER MANAGEMENT as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.21, clause 6.8, clause 8.6, clause 8.7, clause 8.37 and clause 8.38.

# 27.22.4.21.2.3 Test purpose

To verify that the ME shall pass the identifier of the timer that has expired and its value using the ENVELOPE (TIMER EXPIRATION) command, when a timer previously started in a TIMER MANAGEMENT proactive command expires.

#### 27.22.4.21.2.4 Method of test

#### 27.22.4.21.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The timer 1 is not started.

When the UICC is busy when the envelope TIMER EXPIRATION is sent, either the ME retries periodically to send the envelope or it waits for a status not indicating busy.

#### 27.22.4.21.2.4.2 Procedure

### Expected Sequence 2.1 (TIMER EXPIRATION, pending proactive UICC command)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.2.4.2, Expected Sequence 2.1.

### Expected Sequence 2.2 (TIMER EXPIRATION, UICC application toolkit busy)

See ETSI TS 102 384 [26] in subclause 27.22.4.21.2.4.2, Expected Sequence 2.2.

#### 27.22.4.21.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.2.

#### 27.22.4.22 SET UP IDLE MODE TEXT

## 27.22.4.22.1 SET UP IDLE MODE TEXT (normal)

### 27.22.4.22.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.22.1.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 6.4.7 and clause 6.6.13.

Additionally the ME shall support the REFRESH proactive UICC facility as defined in:

- TS 31.111 [15] clause 5.2, clause 6.1, clause 6.4.7, clause 6.6.13, clause 6.11, clause 8.6, clause 8.7, clause 8.12, clause 9.4 and clause 10.

#### 27.22.4.22.1.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text.

# 27.22.4.22.1.4 Method of test

#### 27.22.4.22.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.22.1.4.2 Procedure

## Expected Sequence 1.1 (SET UP IDLE MODE TEXT, display idle mode text)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.1.

### Expected Sequence 1.2 (SET UP IDLE MODE TEXT, replace idle mode text)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.2.

# Expected Sequence 1.3 (SET UP IDLE MODE TEXT, remove idle mode text)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.3.

# **Expected Sequence 1.4 (SET UP IDLE MODE TEXT, competing information on ME display)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP IDLE MODE	
		TEXT 1.1.1	
2		FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	["Idle Mode Text"]
		IDLE MODE TEXT 1.1.1	
4	$ME \rightarrow UICC$		[Command performed successfully]
_		IDLE MODE TEXT 1.1.1	
5	USER → ME	Select idle screen	Only if idle screen not already available
6	ME → USER	Display "Idle Mode Text"	[D: 1 : 1: 4 OMO]
7	USS → ME	SMS PP 1.4.1	[Display immediate SMS]
8	ME → USER		
9	$USER \to ME$	Clear display and select idle screen	
10	$ME \rightarrow USER$	Display "Idle Mode Text"	
11	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: DISPLAY TEXT 1.4.1	
12	$ME \rightarrow UICC$	FETCH	
13	$UICC \to ME$	PROACTIVE COMMAND:	[Normal priority, wait for user to clear
		DISPLAY TEXT 1.4.1	message, unpacked, 8 bit data]
14	$ME \rightarrow USER$	Display "Toolkit Test 1"	
15	$USER \to ME$	Clear Message	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE:	[Command performed successfully]
		DISPLAY TEXT 1.4.1	
17	$ME \rightarrow USER$	I	
18	$UICC \to ME$	PROACTIVE COMMAND	
40		PENDING: PLAY TONE 1.4.1	
19	/ 0.00	FETCH	
20	$UICC \to ME$	PROACTIVE COMMAND: PLAY TONE 1.4.1	
21	ME → USER	Display "Dial Tone"	
21	IVIE -> USER	Play a standard supervisory dial	
		tone through the external ringer for	
		a duration of 5 s	
22	$ME \rightarrow UICC$	TERMINAL RESPONSE: PLAY	[Command performed successfully]
	/ 0.00	TONE 1.4.1	
23	$UICC \to ME$	PROACTIVE UICC SESSION	
	_	ENDED	
24	$ME \rightarrow USER$	Display "Idle Mode Text"	

# SMS-PP 1.4.1

Logically:

SMS TPDU

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC
TP-RP TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI TP-UD field contains only the short message
TP-SRI A status report will not be returned to the ME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "1234" TP-PID "00"

TP-DCS

Coding Group General Data Coding Compression Text is uncompressed Message Class Class 0

Alphabet GSM 7 bit default alphabet TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 12

TP-UD "Test Message"

Coding:

Coding	04	04	91	21	43	00	10	89	10	10	00	00
	00	00	0C	D4	F2	9C	0E	6A	96	E7	F3	F0
	B9	0C										

# PROACTIVE COMMAND: DISPLAY TEXT 1.4.1

Logically:

Command details

Command number: 1

Command type: DISPLAY TEXT

Command qualifier: normal priority, wait for user to clear message

Device identities

Source device: UICC
Destination device: Display

**Text String** 

Data coding scheme: unpacked, 8 bit data
Text: "Toolkit Test 1"

Coding:

BER-TLV:	D0	1A	81	03	01	21	80	82	02	81	02	8D
	0F	04	54	6F	6F	6C	6B	69	74	20	54	65
	73	74	20	31								

#### TERMINAL RESPONSE: DISPLAY TEXT 1.4.1

Logically:

Command details

Command number: 1

Command type: DISPLAY TEXT

Command qualifier: normal priority, wait for user to clear message

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

## PROACTIVE COMMAND: PLAY TONE 1.4.1

Logically:

Command details

Command number:

Command type: PLAY TONE

Command qualifier: "00"

Device identities

Source device: UICC

Destination device: Earpiece Alpha identifier: "Dial Tone"

TONe: Standard supervisory tones: dial tone

Duration

Time unit: Seconds Time interval:

Coding:

BER-TLV:	D0	1B	81	03	01	20	00	82	02	81	03	85
	09	44	69	61	6C	20	54	6F	6E	65	8E	01
	01	84	02	01	05							

TERMINAL RESPONSE: PLAY TONE 1.4.1

Logically:

Command details

Command number:

PLAY TONE Command type:

Command qualifier:

"00"

Device identities

Source device: ME Destination device: **UICC** 

Result

General Result: Command performed successfully

Coding:

	BER-TLV:	81	03	01	20	00	82	02	82	81	83	01	00
--	----------	----	----	----	----	----	----	----	----	----	----	----	----

# Expected Sequence 1.5 (SET UP IDLE MODE TEXT, ME power cycled)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP IDLE MODE	
		TEXT 1.1.1	
2	$ME \rightarrow UICC$		
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	["Idle Mode Text"]
		IDLE MODE TEXT 1.1.1	
4	$ME \rightarrow UICC$		[command performed successfully]
		IDLE MODE TEXT 1.1.1	
5		Select idle screen	Only if idle screen not already available
6		Display "Idle Mode Text"	
7		Power off ME	
8	ME ⇔ UICC	3G Session TERMINATION	
		PROCEDURE	
9		Power on ME	
10	ME ⇔ UICC	3G Session ACTIVATION	
		PROCEDURE	
11		USIM INITIALIZATION	
12	$USER \to ME$	Select idle screen	Only if idle screen not already available
13	$ME \rightarrow USER$	Display idle screen / "Idle Mode	
		Text" not to be displayed	

# **Expected Sequence 1.6 (SET UP IDLE MODE TEXT, REFRESH with USIM Initialization)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	[Idle Mode Text]
		PENDING: SET UP IDLE MODE	
		TEXT 1.1.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		IDLE MODE TEXT 1.1.1	
4	$ME \to UICC$	TERMINAL RESPONSE: SET UP	
		IDLE MODE TEXT 1.1.1	
5	$USER \to ME$	Select idle screen	Only if idle screen not already available
6	$ME \to USER$	Display "Idle Mode Text"	
7	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: REFRESH 1.6.1	
8	$ME \to UICC$	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND:	[USIM Initialization]
		REFRESH 1.6.1	
10	$ME \Leftrightarrow UICC$	USIM INITIALIZATION	
11	$USER \to ME$	Select idle screen	Only if idle screen not already available
12	$ME \to USER$	Display idle screen / "Idle Mode	
		Text" not to be displayed	
13	$ME \to UICC$	TERMINAL RESPONSE:	[Command performed successfully]
		REFRESH 1.6.1A	[Command performed successfully with
		or	additional files read]
		TERMINAL RESPONSE:	
		REFRESH 1.6.1B	
14	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	

# PROACTIVE COMMAND: REFRESH 1.6.1

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	03	82	02	81	82

TERMINAL RESPONSE: REFRESH 1.6.1A

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	00
	• .		• .	• .		~-	~-	~-	• .		• .	

TERMINAL RESPONSE: REFRESH 1.6.1B

Logically:

Command details

Command number: 1

Command type: REFRESH

Command qualifier: USIM Initialization

Device identities

Source device: ME
Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	03

# **Expected Sequence 1.7 (SET UP IDLE MODE TEXT, large text string)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.7.

27.22.4.22.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.7.

27.22.4.22.2 SET UP IDLE MODE TEXT (Icon support)

27.22.4.22.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.2.2 Conformance requirement

27.22.4.22.2.3 Test purpose

To verify that the ME text and / or icon passed to the ME is displayed by the ME as an idle mode text.

To verify that the icon identifier provided with the text string can replace the text string or accompany it.

To verify that if both an alpha identifier or text string, and an icon are provided with a proactive command, and both are requested to be displayed, but the ME is not able to display both together on the screen, then the alpha identifier or text string takes precedence over the icon.

To verify that if the UICC provides an icon identifier with a proactive command, then the ME shall inform the UICC if the icon could not be displayed by sending the general result "Command performed successfully, but requested icon could not be displayed".

To verify that if the ME receives an icon identifier with a proactive command, and either an empty, or no alpha identifier / text string is given by the UICC, than the ME shall reject the command with general result "Command data not understood by ME".

27.22.4.22.2.4 Method of test

27.22.4.22.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in update idle mode on the System Simulator.

27.22.4.22.2.4.2 Procedure

# Expected Sequence 2.1A (SET UP IDLE MODE TEXT, Icon is self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.1A.

# Expected Sequence 2.1B (SET UP IDLE MODE TEXT, Icon is self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.1B.

# Expected Sequence 2.2A (SET UP IDLE MODE TEXT, Icon is not self-explanatory, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.2A.

# Expected Sequence 2.2B (SET UP IDLE MODE TEXT, Icon is not self-explanatory, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.2B.

# Expected Sequence 2.3A (SET UP IDLE MODE TEXT, Icon is self-explanatory, colour icon, successful)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.3A.

# Expected Sequence 2.3B (SET UP IDLE MODE TEXT, Icon is self-explanatory, colour icon, requested icon could not be displayed)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.3B.

### Expected Sequence 2.4 (SET UP IDLE MODE TEXT, Icon is not self-explanatory, empty text string)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.4.

27.22.4.22.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1A to 2.4.

# 27.22.4.22.3 SET UP IDLE MODE TEXT (UCS2 support)

27.22.4.22.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.22.3.2 Conformance requirement

The ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

27.22.4.22.3.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

27.22.4.22.3.4 Method of test

27.22.4.22.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in update idle mode on the System Simulator..

27.22.4.22.3.4.2 Procedure

### Expected Sequence 3.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.3.4.2, Expected Sequence 3.1.

27.22.4.22.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

27.22.4.22.4 SET UP IDLE MODE TEXT (support of Text Attribute)

27.22.4.22.4.1 SET UP IDLE MODE TEXT (support of Text Attribute – Left Alignment)

27.22.4.22.4.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.22.4.1.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.1.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the left alignment text attribute configuration.

27.22.4.22.4.1.4 Method of test

27.22.4.22.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.1.4.2 Procedure

# Expected Sequence 4.1 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Left Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.1.4.2, Expected Sequence 4.1.

### 27.22.4.22.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

#### 27.22.4.22.4.2 SET UP IDLE MODE TEXT (support of Text Attribute – Center Alignment)

### 27.22.4.22.4.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.22.4 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.2.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the center alignment text attribute configuration.

#### 27.22.4.22.4 Method of test

#### 27.22.4.22.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.22.4.2 Procedure

Expected Sequence 4.2 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Center Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.2, Expected Sequence 4.2.

#### 27.22.4.22.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

### 27.22.4.22.4.3 SET UP IDLE MODE TEXT (support of Text Attribute – Right Alignment)

#### 27.22.4.22.4.3.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.22.4.3.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.3.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the right alignment text attribute configuration.

27.22.4.22.4.3.4 Method of test

27.22.4.22.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.22.4.3.4.2 Procedure

# Expected Sequence 4.3 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Right Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.3.4.2, Expected Sequence 4.3.

27.22.4.22.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

27.22.4.22.4.4 SET UP IDLE MODE TEXT (support of Text Attribute – Large Font Size)

27.22.4.22.4.4.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.22.4.4.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

### 27.22.4.22.4.4.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the large font size text attribute configuration.

27.22.4.22.4.4.4 Method of test

27.22.4.22.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.22.4.4.4.2 Procedure

# Expected Sequence 4.4 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Large Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.4.2, Expected Sequence 4.4.

27.22.4.22.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.22.4.5 SET UP IDLE MODE TEXT (support of Text Attribute – Small Font Size)

27.22.4.22.4.5.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.22.4.5.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

### 27.22.4.22.4.5.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the small font size text attribute configuration.

27.22.4.22.4.5.4 Method of test

27.22.4.22.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.22.4.5.4.2 Procedure

# Expected Sequence 4.5 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Small Font Size)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.5.4.2, Expected Sequence 4.5.

### 27.22.4.22.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.22.4.6 SET UP IDLE MODE TEXT (support of Text Attribute – Bold On)

27.22.4.22.4.6.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.22.4.6.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.6.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the bold text attribute configuration.

27.22.4.22.4.6.4 Method of test

27.22.4.22.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.6.4.2 Procedure

### Expected Sequence 4.6 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Bold On)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.6.4.2, Expected Sequence 4.6.

27.22.4.22.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.22.4.7 SET UP IDLE MODE TEXT (support of Text Attribute – Italic On)

27.22.4.22.4.7.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.22.4.7.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

### 27.22.4.22.4.7.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the italic text attribute configuration.

27.22.4.22.4.7.4 Method of test

#### 27.22.4.22.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.7.4.2 Procedure

#### Expected Sequence 4.7 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Italic On)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.7.4.2, Expected Sequence 4.7.

27.22.4.22.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

27.22.4.22.4.8 SET UP IDLE MODE TEXT (support of Text Attribute – Underline On)

27.22.4.22.4.8.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.22.4.8.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.8.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the underline text attribute configuration.

27.22.4.22.4.8.4 Method of test

27.22.4.22.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.8.4.2 Procedure

# Expected Sequence 4.8 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Underline On)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.8.4.2, Expected Sequence 4.8.

27.22.4.22.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

27.22.4.22.4.9 SET UP IDLE MODE TEXT (support of Text Attribute – Strikethrough On)

27.22.4.22.4.9.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.22.4.9.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

### 27.22.4.22.4.9.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the strikethrough text attribute configuration.

27.22.4.22.4.9.4 Method of test

27.22.4.22.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.9.4.2 Procedure

# Expected Sequence 4.9 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Strikethrough On)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.9.4.2, Expected Sequence 4.9.

27.22.4.22.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.22.4.10 SET UP IDLE MODE TEXT (support of Text Attribute – Foreground and Background Colour)

27.22.4.22.4.10.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.22.4.10.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

### 27.22.4.22.4.10.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the foreground and background colour text attribute configuration.

27.22.4.22.4.10.4 Method of test

27.22.4.22.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.22.4.10.4.2 Procedure

# Expected Sequence 4.10 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Foreground and Background Colour)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.10.4.2, Expected Sequence 4.10.

27.22.4.22.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

# 27.22.4.22.5 SET UP IDLE MODE TEXT (UCS2 display in Chinese)

27.22.4.22.5.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.22.5.2 Conformance requirement

TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

The Terminal shall additionally support the UCS2 facility for the coding of the Chinese character, as defined in: ISO/IEC 10646 [17a/17b].

# 27.22.4.22.5.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

508

27.22.4.22.5.4 Method of test

27.22.4.22.5.4.1 Initial conditions

The Terminal is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the Terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.22.5.4.2 Procedure

# **Expected Sequence 5.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text in Chinese)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.5.4.2, Expected Sequence 5.1.

27.22.4.22.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.22.6 SET UP IDLE MODE TEXT (UCS2 display in Katakana)

27.22.4.22.6.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.22.6.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

The ME shall additionally support the UCS2 facility for the coding of the Katakana character, as defined in:

ISO/IEC 10646 [17a/17b].

#### 27.22.4.22.6.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

27.22.4.22.6.4 Method of test

27.22.4.22.6.4.1 Initial conditions

The ME is connected to both the UICC Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.22.6.4.2 Procedure

### Expected Sequence 6.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text in Katakana)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.6.4.2, Expected Sequence 6.1.

27.22.4.22.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

### 27.22.4.23 RUN AT COMMAND

#### 27.22.4.23.1 RUN AT COMMAND (normal)

#### 27.22.4.23.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.1.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31 and clause 8.41.
- TS 27.007 [18].

#### 27.22.4.23.1.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.1.4 Method of test

#### Initial conditions 27.22.4.23.1.4.1

The ME is connected to the USIM Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.1.4.2 Procedure

### Expected Sequence 1.1(RUN AT COMMAND, no alpha identifier presented, request IMSI)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[no alpha identifier, request IMSI]
		AT COMMAND 1.1.1	
4	ME ( $\rightarrow$ User)	The ME may give information to	
		the user concerning what is	
		happening	
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
		COMMAND 1.1.1	Response containing IMSI]

# PROACTIVE UICC COMMAND: RUN AT COMMAND 1.1.1

#### Logically:

Command details

Command number:

**RUN AT COMMAND** Command type:

Command qualifier:

"00"

Device identities

Source device: **UICC** Destination device: ME

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	12	81	03	01	34	00	82	02	81	82	A8
	07	41	54	2B	43	49	4D	49				

TERMINAL RESPONSE: RUN AT COMMAND 1.1.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

# Expected Sequence 1.2 (RUN AT COMMAND, null data alpha identifier presented, request IMSI)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		1.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[null data alpha identifier, request IMSI]
		AT COMMAND 1.2.1	
4	ME	The ME should not give any	
		information to user on the fact	
		that the ME is performing an AT	
		command	
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN	[Command performed successfully, AT
1		AT COMMAND 1.1.1	Response containing IMSI]

PROACTIVE UICC COMMAND: RUN AT COMMAND 1.2.1

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier null data object

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	14	81	03	01	34	00	82	02	81	82	85
	00	A8	07	41	54	2B	43	49	4D	49		

# Expected Sequence 1.3 (RUN AT COMMAND, alpha identifier presented, request IMSI)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		1.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[alpha identifier, request IMSI]
		AT COMMAND 1.3.1	
4	$ME \to USER$	Display "Run AT Command"	
5	$ME \to UICC$	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
		COMMAND 1.1.1	Response containing IMSI]

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 1.3.1

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	22	81	03	01	34	00	82	02	81	82	85
	0 <sup>E</sup>	52	75	6 <sup>E</sup>	20	41	54	20	43	6F	6D	6D
	61	6E	64	A8	07	41	54	2B	43	49	4D	49

### 27.22.4.23.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

# 27.22.4.23.2 RUN AT COMMAND (Icon support)

# 27.22.4.23.2.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.23.2.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31 and clause 8.41.
- TS 27.007 [18].

### 27.22.4.23.2.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

27.22.4.23.2.4 Method of test

27.22.4.23.2.4.1 Initial conditions

The ME is connected to the USIM Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.23.2.4.2 Procedure

# Expected Sequence 2.1A (RUN AT COMMAND, basic icon self explanatory, request IMSI, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[BASIC-ICON, self-explanatory, request IMSI]
		AT COMMAND 2.1.1	
4	$ME \rightarrow USER$	Display BASIC ICON without the	
		alpha identifier	
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
		COMMAND 2.1.1A	response containing IMSI]

#### PROACTIVE COMMAND: RUN AT COMMAND 2.1.1

### Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha identifier: "Basic Icon"

AT Command

AT Command string: "AT+CIMI"

Icon identifier:

Icon qualifier: icon is self-explanatory Icon identifier: record 1 in  $EF_{(IMG)}$ 

#### Coding:

BER-TLV:	D0	22	81	03	01	34	00	82	02	81	82	85
_	0A	42	61	73	69	63	20	49	63	6F	6E	A8
	07	41	54	2B	43	49	4D	49	9E	02	00	01

TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

# Expected Sequence 2.1B (RUN AT COMMAND, basic icon self explanatory, request IMSI, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[BASIC-ICON, self-explanatory, request IMSI]
		AT COMMAND 2.1.1	
4	$ME \rightarrow USER$	Display 'Basic Icon' without the	
		BASIC-ICON	
5	$ME \rightarrow UICC$		[Command performed but requested icon
		COMMAND 2.1.1B	could not be displayed, AT response
			containing IMSI]

TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	04
	A9	08	09	10	10	10	32	54	76	98		

# Expected Sequence 2.2A (RUN AT COMMAND, colour icon self explanatory, request IMSI, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[COLOUR-ICON, self-explanatory, request
		AT COMMAND 2.2.1	IMSI]
4		Display COLOUR-ICON without	
		the alpha identifier	
5	$ME \rightarrow UICC$		[Command performed successfully, AT
		COMMAND 2.1.1A	response containing IMSI]

PROACTIVE COMMAND: RUN AT COMMAND 2.2.1

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: ME

Alpha Identifier

Alpha identifier: "Colour Icon"

AT Command

AT Command string: "AT+CIMI"

Icon identifier:

 $\begin{array}{ll} \hbox{Icon qualifier:} & \hbox{icon is self-explanatory} \\ \hbox{Icon identifier:} & \hbox{record 2 in } EF_{(IMG)} \\ \end{array}$ 

Coding:

BER-TLV:	D0	23	81	03	01	34	00	82	02	81	82	A8
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	A8	07	41	54	2B	43	49	4D	49	9E	02	00
	02											

# Expected Sequence 2.2B (RUN AT COMMAND, colour icon self explanatory, request IMSI, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[COLOUR-ICON, self-explanatory, request
		AT COMMAND 2.2.1	IMSI]
4	$ME \rightarrow USER$	Display 'Colour Icon' without the	
		COLOUR-ICON	
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed but requested icon
		COMMAND 2.1.1B	could not be displayed, AT response
			containing IMSI1

# Expected Sequence 2.3A (RUN AT COMMAND, basic icon non self-explanatory, request IMSI, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[BASIC-ICON, non self-explanatory, request
		AT COMMAND 2.3.1	IMSI]
4	$ME \rightarrow USER$	Display "Basic Icon" and BASIC-	
		ICON	
5	$ME \rightarrow UICC$		[Command performed successfully, AT
		COMMAND 2.1.1A	response containing IMSI]

PROACTIVE COMMAND: RUN AT COMMAND 2.3.1

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha identifier: "Basic Icon"

AT Command

AT Command string: "AT+CIMI"

Icon identifier

Icon qualifier: icon is non self-explanatory

Icon identifier: record 1 in  $EF_{(IMG)}$ 

Coding:

BER-TLV:	D0	22	81	03	01	34	00	82	02	81	82	85
·	0A	42	61	73	69	63	20	49	63	6F	6E	A8
	07	41	54	2B	43	49	4D	49	9E	02	01	01

# Expected Sequence 2.3B (RUN AT COMMAND, basic icon non self-explanatory, request IMSI, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.3.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[BASIC-ICON, non self-explanatory, request
		AT COMMAND 2.3.1	IMSI]
4	$ME \to USER$	Display "Basic Icon" without	
		BASIC-ICON	
5	$ME \to UICC$	TERMINAL RESPONSE: RUN AT	[Command performed but requested icon
		COMMAND 2.1.1B	could not be displayed, AT response
			containing IMSI]

# Expected Sequence 2.4A (RUN AT COMMAND, colour icon non self-explanatory, request IMSI, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[COLOUR-ICON, non self-explanatory,
		AT COMMAND 2.4.1	request IMSI]
4	$ME \rightarrow USER$	Display "Colour Icon" and	
		COLOUR-ICON	
5	$ME \rightarrow UICC$		[Command performed successfully, AT
		COMMAND 2.1.1A	response containing IMSI]

PROACTIVE COMMAND: RUN AT COMMAND 2.4.1

# Logically:

Command details

Command number:

Command type: **RUN AT COMMAND** 

Command qualifier: "00"

Device identities

Source device: **UICC** Destination device: ME

Alpha Identifier

Alpha identifier: "Colour Icon"

AT Command

Icon qualifier:

Icon identifier:

AT Command string: "AT+CIMI"

Icon identifier:

icon is self-explanatory record 2 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	23	81	03	01	34	00	82	02	81	82	85
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	A8	07	41	54	2B	43	49	4D	49	9E	02	01
	02											

# Expected Sequence 2.4B (RUN AT COMMAND, colour icon non self-explanatory, request IMSI, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[COLOUR-ICON, non self-explanatory,
		AT COMMAND 2.4.1	request IMSI]
4	$ME \rightarrow USER$	Display "Colour Icon" without	
		COLOUR-ICON	
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed but requested icon
		COMMAND 2.1.1B	could not be displayed, AT response
			containing IMSI]

# Expected Sequence 2.5 (RUN AT COMMAND, basic icon non self-explanatory, no alpha identifier presented)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		2.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	[BASIC-ICON, non self-explanatory]
		AT COMMAND 2.5.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN	[Command data not understood by ME]
		AT COMMAND 2.5.1	

PROACTIVE COMMAND: RUN AT COMMAND 2.5.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: ME

AT Command

AT Command string: "AT+CIMI"

Icon identifier

Icon qualifier: icon is non self-explanatory

Icon identifier: record 1 in  $EF_{(IMG)}$ 

Coding:

BER-TLV:	D0	16	81	03	01	34	00	82	02	81	82	A8	l
	07	41	54	2B	43	49	4D	49	9E	02	01	01	l

TERMINAL RESPONSE: RUN AT COMMAND 2.5.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Result

General Result: Command data not understood by ME

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	32

27.22.4.23.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.5.

# 27.22.4.23.3 RUN AT COMMAND (support of Text Attribute)

27.22.4.23.3.1 RUN AT COMMAND (support of Text Attribute – Left Alignment)

27.22.4.23.3.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.23.3.1.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

### 27.22.4.23.3.1.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with left alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.1.4 Method of test

27.22.4.23.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

### 27.22.4.23.3.1.4.2 Procedure

# Expected Sequence 3.1(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		3.1.1	
2	11.12 / 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.1.1	
4	ME ( $ ightarrow$ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with left alignment, request IMSI]
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.1.1	[Command performed successfully, AT Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
7	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.1.2	
8	$ME \rightarrow UICC$	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.1.2	
10	ME (→ USER)	Display "Run AT Command 2"	[Message shall be formatted without left alignment, request IMSI. Remark: If left alignment is the ME"s default alignment as declared in table A.2/16, no alignment change will take place]
11	$ME \to UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.1.1	[Command performed successfully, AT Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	

### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.1.1

# Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

### Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.1.2

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

### Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

#### TERMINAL RESPONSE: RUN AT COMMAND 3.1.1

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

### Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

# 27.22.4.23.3.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

27.22.4.23.3.2 RUN AT COMMAND (support of Text Attribute – Center Alignment)

27.22.4.23.3.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.23.3.2.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.2.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with center alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.2.4 Method of test

27.22.4.23.3.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

### 27.22.4.23.3.2.4.2 Procedure

# Expected Sequence 3.2(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
	ME	3.2.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.2.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with center alignment, request IMSI]
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.2.1	[Command performed successfully, AT Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
7	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.2.2	
8	$ME \rightarrow UICC$	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.2.2	
10	ME (→ USER)	Display "Run AT Command 2"	[Message shall be formatted without center alignment, request IMSI. Remark: If center alignment is the ME"s default alignment as declared in table A.2/16, no alignment change will take place]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.2.1	[Command performed successfully, AT Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.2.1

1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	01	B4				

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.2.2

### Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
·	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

# TERMINAL RESPONSE: RUN AT COMMAND 3.2.1

#### Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

# 27.22.4.23.3.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.2.

27.22.4.23.3.3 RUN AT COMMAND (support of Text Attribute – Right Alignment)

27.22.4.23.3.3.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.23.3.3.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

# 27.22.4.23.3.3.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with right alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.3.4 Method of test

27.22.4.23.3.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

### 27.22.4.23.3.3.4.2 Procedure

# Expected Sequence 3.3(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		3.3.1	
2	1112 / 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.3.1	
4	$ME \; (\to USER)$	Display "Run AT Command 1"	[alpha identifier is displayed with right
_			alignment, request IMSI]
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN	[Command performed successfully, AT
		AT COMMAND 3.3.1	Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION	
7	UICC → ME	ENDED PROACTIVE COMMAND	
'	UICC → ME	PENDING: RUN AT COMMAND	
		3.3.2	
8	ME → UICC	FETCH	
9	WE / 0100	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.3.2	
10	ME ( LISER)	Display "Run AT Command 2"	[Message shall be formatted without right
'0	INL ( > OOLIK)	Biopiay Ran Al Commana 2	alignment, request IMSI. Remark: If right
			alignment is the ME"s default alignment as
			declared in table A.2/16, no alignment change
			will take place]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN	[Command performed successfully, AT
		AT COMMAND 3.3.1	Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.3.1

# Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

### Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	02	B4				

525

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.3.2

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier

"Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

#### TERMINAL RESPONSE: RUN AT COMMAND 3.3.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

27.22.4.23.3.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.3.

27.22.4.23.3.4 RUN AT COMMAND (support of Text Attribute – Large Font Size)

27.22.4.23.3.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.4.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

# 27.22.4.23.3.4.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with large font size as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.4.4 Method of test

27.22.4.23.3.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

# 27.22.4.23.3.4.4.2 Procedure

# Expected Sequence 3.4(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		3.4.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.4.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with large font size, request IMSI]
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
7	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.2	
8	$ME \rightarrow UICC$	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.4.2	
10	$ME \left(  ightarrow  ight.$	Display "Run AT Command 2"	[alpha identifier is displayed with normal font
	USER)		size, request IMSI]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
13	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN	
16	ME (→	AT COMMAND 3.4.1 Display "Run AT Command 1"	[alpha identifier is displayed with large font
	USER)	Ziopiay itamirti denimana i	size, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
18	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	3 0,
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.3	
20	ME → UICC	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.4.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with normal font size, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
24	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	responde containing more

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.1

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	04	B4				

### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.2

### Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.3

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 3"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.4.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

27.22.4.23.3.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.4.

27.22.4.23.3.5 RUN AT COMMAND (support of Text Attribute – Small Font Size)

27.22.4.23.3.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.5.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.5.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with small font size as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.5.4 Method of test

27.22.4.23.3.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.5.4.2 Procedure

# Expected Sequence 3.5(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		3.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.5.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with small font size, request IMSI]
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
7	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.2	
8	$ME \to UICC$	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.5.2	
10	$ME \left(  ightarrow  ight.$	Display "Run AT Command 2"	[alpha identifier is displayed with normal font
	USER)		size, request IMSI]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
13	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.1	
14	$ME \rightarrow UICC$	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN	
16	ME (→	AT COMMAND 3.5.1 Display "Run AT Command 1"	[alpha identifier is displayed with small font
	USER)	Bioplay Ruit/Ri Gommana I	size, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
18	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	Trooperior contaming mo.
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.3	
20	$ME \rightarrow UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.5.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with normal font size, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
24	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	recoporac containing intol

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.1

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	08	B4				

### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.2

### Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.3

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 3"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.5.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

27.22.4.23.3.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.5.

27.22.4.23.3.6 RUN AT COMMAND (support of Text Attribute – Bold On)

27.22.4.23.3.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.6.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.6.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with bold text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.6.4 Method of test

27.22.4.23.3.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

# 27.22.4.23.3.6.4.2 Procedure

# Expected Sequence 3.6(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
2	$ME \to UICC$	3.6.1 FETCH	
3	$UICC \rightarrow ME$	PROACTIVE COMMAND: RUN	
	OICC → IVIL	AT COMMAND 3.6.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with bold on, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION	Response containing livion
7	$UICC \to ME$	ENDED PROACTIVE COMMAND PENDING: RUN AT COMMAND	
		3.6.2	
8	ME → UICC	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.6.2	
10	ME ( $ ightarrow$ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with bold off, request IMSI]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.6.1	[Command performed successfully, AT Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	3
13	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.1	
14	$ME \rightarrow UICC$	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.6.1	
16	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with bold on, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.6.1	[Command performed successfully, AT Response containing IMSI]
18	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	Trosponse containing intol
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.3	
20	$ME \rightarrow UICC$	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.6.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with bold off, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.6.1	[Command performed successfully, AT Response containing IMSI]
24	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	response containing into[]

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.1

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	10	B4				

### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.2

### Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.3

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 3"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.6.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

27.22.4.23.3.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.6.

27.22.4.23.3.7 RUN AT COMMAND (support of Text Attribute – Italic On)

27.22.4.23.3.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.7.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.7.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with italic text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.7.4 Method of test

27.22.4.23.3.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

# 27.22.4.23.3.7.4.2 Procedure

# Expected Sequence 3.7(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments					
1	$UICC \to ME$	PROACTIVE COMMAND						
		PENDING: RUN AT COMMAND						
	NAT 11100	3.7.1						
2	ME → UICC	FETCH						
3	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.7.1						
4	ME (→	Display "Run AT Command 1"	[alpha identifier is displayed with italic on,					
	USER)	Biopiay Train At Communic 1	request IMSI]					
5	ME → UICC	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT					
		COMMAND 3.7.1	Response containing IMSI]					
6	$UICC \to ME$	PROACTIVE UICC SESSION						
_		ENDED						
7	$UICC \to ME$	PROACTIVE COMMAND						
		PENDING: RUN AT COMMAND 3.7.2						
8	ME → UICC	FETCH						
9	UICC → ME	PROACTIVE COMMAND: RUN						
		AT COMMAND 3.7.2						
10	$ME \left(  ightarrow  ight.$	Display "Run AT Command 2"	[alpha identifier is displayed with italic off,					
	USER)		request IMSI]					
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT Response containing IMSI]					
12	$UICC \to ME$	COMMAND 3.7.1 PROACTIVE UICC SESSION	Response containing livi5ij					
12	OICC → IVIL	ENDED						
13	$UICC \to ME$	PROACTIVE COMMAND						
		PENDING: RUN AT COMMAND						
		3.7.1						
14	ME → UICC	FETCH						
15	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.7.1						
16	ME (→	Display "Run AT Command 1"	[alpha identifier is displayed with italic on,					
	USER)	Bioplay Ruit/Ri Gommana I	request IMSI]					
17	ME → UICC	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT					
		COMMAND 3.7.1	Response containing IMSI]					
18	$UICC \to ME$	PROACTIVE UICC SESSION						
19	LUCC ME	PROACTIVE COMMAND						
19	$UICC \to ME$	PENDING: RUN AT COMMAND						
		3.7.3						
20	$ME \rightarrow UICC$	FETCH						
21	$UICC \to ME$	PROACTIVE COMMAND: RUN						
		AT COMMAND 3.7.3						
22	ME (→	Display "Run AT Command 3"	[alpha identifier is displayed with italic off,					
22	USER)	TEDMINIAL DESCONSE, DUN AT	request IMSI] [Command performed successfully, AT					
23	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.7.1	Response containing IMSI]					
24	$UICC \to ME$	PROACTIVE UICC SESSION	Tresponse containing inion					
	3.00 / WL	ENDED						

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.1

# Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	20	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.2

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.3

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 3"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.7.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

27.22.4.23.3.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.7.

27.22.4.23.3.8 RUN AT COMMAND (support of Text Attribute – Underline On)

27.22.4.23.3.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.8.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.8.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with underline text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.8.4 Method of test

27.22.4.23.3.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

# 27.22.4.23.3.8.4.2 Procedure

# Expected Sequence 3.8(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		3.8.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.8.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with underline on, request IMSI]
5	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT COMMAND 3.8.1	[Command performed successfully, AT Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	3
7	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.2	
8	$ME \rightarrow UICC$	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: RUN AT COMMAND 3.8.2	
10	$ME \left(  ightarrow  ight.$	Display "Run AT Command 2"	[alpha identifier is displayed with underline off,
	USER)		request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.8.1	[Command performed successfully, AT Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
13	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.1	
14	$ME \rightarrow UICC$	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN	
	OIOO / IVIL	AT COMMAND 3.8.1	
16	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with underline on, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.8.1	[Command performed successfully, AT Response containing IMSI]
18	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	respense containing inter,
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.3	
20	$ME \rightarrow UICC$	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.8.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with underline off, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
24	$UICC \to ME$	COMMAND 3.8.1 PROACTIVE UICC SESSION ENDED	Response containing IMSI]

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.1

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	40	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.2

## Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.3

# Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 3"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.8.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	80	09	10	10	10	32	54	76	98		

27.22.4.23.3.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.8.

27.22.4.23.3.9 RUN AT COMMAND (support of Text Attribute – Strikethrough On)

27.22.4.23.3.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.9.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.9.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with strikethrough text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.9.4 Method of test

27.22.4.23.3.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.9.4.2 Procedure

# Expected Sequence 3.9(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		3.9.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.9.1	
4	ME ( $ ightarrow$ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with strikethrough on, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
	WE 70100	COMMAND 3.9.1	Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
7	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
0	ME . IIICC	3.9.2  FETCH	
8 9	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND: RUN	
9	OICC → IVIE	AT COMMAND 3.9.2	
10	$ME \left( \to \right.$	Display "Run AT Command 2"	[alpha identifier is displayed with strikethrough
	USER)		off, request IMSI]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
		COMMAND 3.9.1	Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION	
13	LUCC ME	PROACTIVE COMMAND	
13	$UICC \to ME$	PENDING: RUN AT COMMAND	
		3.9.1	
14	$ME \to UICC$	FETCH	
15	$UICC \to ME$	PROACTIVE COMMAND: RUN	
		AT COMMAND 3.9.1	
16	ME (→	Display " Run AT Command 1"	[alpha identifier is displayed with strikethrough
17	USER)	TERMINAL RESPONSE: RUN AT	on, request IMSI] [Command performed successfully, AT
17	$ME \rightarrow UICC$	COMMAND 3.9.1	Response containing IMSI]
18	$UICC \to ME$	PROACTIVE UICC SESSION	response containing interj
	0.00 /	ENDED	
19	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
20	ME . LUCC	3.9.3	
20 21	ME → UICC	FETCH PROACTIVE COMMAND: RUN	
Z1	$UICC \to ME$	AT COMMAND 3.9.3	
22	$ME \left( \to \right.$	Display "Run AT Command 3"	[alpha identifier is displayed with strikethrough
	USER)		off, request IMSI]
23	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
		COMMAND 3.9.1	Response containing IMSI]
24	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.1

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	80	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.2

## Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0 Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.3

# Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 3"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.9.1

Logically:

Command details

Command number:

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result:

Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

27.22.4.23.3.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.9.

27.22.4.23.3.10 RUN AT COMMAND (support of Text Attribute – Foreground and Background Colour)

27.22.4.23.3.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.10.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.10.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with foreground and background colour text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.10.4 Method of test

27.22.4.23.3.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.3.10.4.2 Procedure

# Expected Sequence 3.10(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
		3.10.1	
2	11.12 / 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: RUN	
4	NAT (	AT COMMAND 3.10.1	Calaba identifier is displayed with foreground
4	ME (→	Display "Run AT Command 1"	[alpha identifier is displayed with foreground and background colour according to the text
	USER)		attribute configuration, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
	, olog	COMMAND 3.10.1	Response containing IMSI]
6	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
7	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: RUN AT COMMAND	
0		3.10.2	
8	L / 0.00	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: RUN	
40	NAT (	AT COMMAND 3.10.2	Falmba identifiar is displayed with NATI a default
10	ME (→	Display "Run AT Command 2"	[alpha identifier is displayed with ME"s default
	USER)		foreground and background colour, request IMSI]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: RUN AT	[Command performed successfully, AT
		COMMAND 3.10.1	Response containing IMSI]
12	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	

# PROACTIVE UICC COMMAND: RUN AT COMMAND 3.10.1

## Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.10.2

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
-	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

# TERMINAL RESPONSE: RUN AT COMMAND 3.10.1

Logically:

Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
<u></u>	Α9	08	09	10	10	10	32	54	76	98		

## 27.22.4.23.3.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.10.

# 27.22.4.23.4 RUN AT COMMAND (UCS2 display in Cyrillic)

27.22.4.23.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.23.4.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.4.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.4.4 Method of test

27.22.4.23.4.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.4.4.2 Procedure

# Expected Sequence 4.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Cyrillic, request ME Manufacturer ID)

See ETSI TS 102 384 [26] in subclause 27.22.4.23.4.4.2, Expected Sequence 4.1.

27.22.4.23.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

# 27.22.4.23.5 RUN AT COMMAND (UCS2 display in Chinese)

27.22.4.23.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.23.5.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.5.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.5.4 Method of test

27.22.4.23.5.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.5.4.2 Procedure

# Expected Sequence 5.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Chinese, request ME Manufacturer ID)

See ETSI TS 102 384 [26] in subclause 27.22.4.23.5.4.2, Expected Sequence 5.1.

27.22.4.23.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

# 27.22.4.23.6 RUN AT COMMAND (UCS2 display in Katakana)

27.22.4.23.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.6.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.6.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.6.4 Method of test

27.22.4.23.6.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.6.4.2 Procedure

# Expected Sequence 6.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Katakana, request ME Manufacturer ID)

See ETSI TS 102 384 [26] in subclause 27.22.4.23.6.4.2, Expected Sequence 6.1.

#### 27.22.4.23.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

#### 27.22.4.24 SEND DTMF

## 27.22.4.24.1 SEND DTMF (Normal)

#### 27.22.4.24.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

# 27.22.4.24.1.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that if an alpha identifier is provided by the UICC and is a null data object the ME does not give any information to the user on the fact that the ME is performing a SEND DTMF command.

#### 27.22.4.24.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.24.1.4. 2 Procedure

# **Expected Sequence 1.1 (SEND DTMF, normal)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \rightarrow ME$	Set up a call to "+0123456789"	
2	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 1.1.1	
5	$ME \rightarrow UICC$		
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 1.1.1	
7	ME → USER	May give information to the user concerning what is happening. Do not locally generate audible DTMF tones and play them to the user.	
8	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 1.1.1	[Command performed successfully]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
13	$User \to ME$	End the call	

# PROACTIVE COMMAND: SEND DTMF 1.1.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	0D	81	03	01	14	00	82	02	81	83	AC
_	02	C1	F2									

Start DTMF 1.1

Logically:

DTMF String: "1"

Start DTMF 1.2

Logically:

DTMF String: "2"

TERMINAL RESPONSE: SEND DTMF 1.1.1

Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	Ω1	14	00	82	02	82	81	83	01	00
DER-ILV.	01	03	Οī	14	00	02	02	02	01	ಂ	UI	00

# **Expected Sequence 1.2 (SEND DTMF, containing alpha identifier)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND	
_	ME 11100	PENDING: SEND DTMF 1.2.1	
5	ME → UICC		
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 1.2.1	
7	ME → USER		Alpha identifier
<b>'</b>	IVIE → USER	Do not locally generate audible	Alpria identiliei
		DTMF tones and play them to the	
		user.	
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	$ME \to USS$	Start DTMF 1.2	["2"]
10	$ME \to USS$	Start DTMF 1.3	["3"]
11	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
12	$ME \to USS$	Start DTMF 1.5	["5"]
13	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
14	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
15	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
16	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
17	$ME \rightarrow USS$	Start DTMF 1.10	["0"]
18	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DTMF 1.1.1	
19	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
20	User $\rightarrow$ ME	End the call	

# PROACTIVE COMMAND: SEND DTMF 1.2.1

# Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF"
DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1B	81	03	01	14	00	82	02	81	83	85
	09	53	65	6E	64	20	44	54	4D	46	AC	05
	21	43	65	87	09							

Start DTMF 1.3

Logically:

DTMF String: "3"

Start DTMF 1.4

Logically:

DTMF String: "4"

Start DTMF 1.5

Logically:

DTMF String: "5"

Start DTMF 1.6

Logically:

DTMF String: "6"

Start DTMF 1.7

Logically:

DTMF String: "7"

Start DTMF 1.8

Logically:

DTMF String: "8"

Start DTMF 1.9

Logically:

DTMF String: "9"

Start DTMF 1.10

Logically:

DTMF String: "0"

Expected Sequence 1.3 (SEND DTMF, containing alpha identifier with null data object)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND	
_	ME IIIOO	PENDING: SEND DTMF 1.3.1	
5	$ME \rightarrow UICC$		
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 1.3.1	Alpha identifier with null data object
7	$ME \rightarrow USER$	Do not give any information to the	
		user on the fact that the ME is	
		performing a SEND DTMF	
		command.	
		Do not locally generate audible	
		DTMF tones and play them to the	
0	ME	USEr.	["4"]
8	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
9	ME	Ctout DTME 4.0	No DTMF sending for 30 seconds ±20%
10		Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
40		DTMF 1.1.1	
12	$UICC \to ME$	PROACTIVE UICC SESSION	
40		ENDED	
13	User $\rightarrow$ ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 1.3.1

# Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "" (null data object)

DTMF String: "1" pause pause pause pause pause pause pause pause pause pause "2"

# Coding:

BER-TLV:	D0	13	81	03	01	14	00	82	02	81	83	85
	00	AC	06	C1	CC	CC	CC	CC	2C			

# Expected Sequence 1.4 (SEND DTMF, mobile is not in a speech call)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	[Mobile is not in a speech call]
		PENDING: SEND DTMF 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		DTMF 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[ME currently unable to process command,
			not in speech call]
5	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	

TERMINAL RESPONSE: SEND DTMF 1.4.1

Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: ME currently unable to process command

Additional information: Not in speech call

#### Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	02	20
	07											

## 27.22.4.24.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4.

# 27.22.4.24.2 SEND DTMF (Display of icons)

## 27.22.4.24.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44, clause 8.31 and clause 6.5.4.

# 27.22.4.24.2.3 Test purpose

To verify that after a call has been successfully established the ME send the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME do not locally generate audible DTMF tones and play them to the user.

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the icons which are referred to in the contents of the SEND DTMF proactive UICC command.

## 27.22.4.24.2.4 Method of test

#### 27.22.4.24.2.4.1 Initial conditions

The ME is connected to the SIM Simulator and only connected to the System Simulator if the System Simulator is mentioned in the sequence table. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

The elementary files are coded as Toolkit default.

#### 27.22.4.24.2.4.2 Procedure

# Expected Sequence 2.1A (SEND DTMF, BASIC ICON self explanatory, successful)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
3	$USS \to ME$	"+0123456789" The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	I <u>9</u>	
5	$ME \to UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 2.1.1	[BASIC-ICON, self-explanatory]
7	$ME \to USER$	Display the BASIC-ICON	
		Do not locally generate audible DTMF tones and play them to the	
8	$ME \rightarrow USS$	luser. Start DTMF 1.1	["1"]
9	ME → 000	Otal Divil	No DTMF sending for 3 seconds ±20%
10	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
11	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DTMF 2.1.1A	
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
13	$User \to ME$	End the call	

## PROACTIVE COMMAND: SEND DTMF 2.1.1

# Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Basic Icon"
DTMF String: "1" pause "2"

Icon identifier

Icon qualifier: icon is self-explanatory Icon identifier: record 1 in  $EF_{(IMG)}$ 

## Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	AC
	02	C1	F2	9E	02	00	01					

# DTMF Request 2.1.1

Logically:

DTMF String: \$DTMF\_2.1\$ = "C1 F2" (given as example)

TERMINAL RESPONSE: SEND DTMF 2.1.1A

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00

# Expected Sequence 2.1B (SEND DTMF, BASIC ICON self explanatory, requested icon could not be displayed)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
_		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 2.1.1	
5	ME → UICC		
6		PROACTIVE COMMAND: SEND	[BASIC-ICON, self-explanatory]
0		DTMF 2.1.1	[BASIC-ICON, Self-explanatory]
7	ME - LISER	Display "Basic Icon" without the	
_	ML 700LK	icon	
		Do not locally generate audible	
		DTMF tones and play them to the	
		user.	
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20 %
10	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully, but
		DTMF 2.1.1B	requested icon could not be displayed]
12	$UICC \to ME$	PROACTIVE UICC SESSION	
40		ENDED	
13	User $\rightarrow$ ME	End the call	

TERMINAL RESPONSE: SEND DTMF 2.1.1B

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

# Expected Sequence 2.2A (SEND DTMF, COLOUR-ICON self explanatory, successful)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \rightarrow USS$	The ME attempts to set up a call to	
3	$USS \to ME$	"+0123456789" The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 2.2.1	
5	$ME \rightarrow UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 2.2.1	[COLOUR-ICON]
7	$ME \rightarrow USER$	' '	
		Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME / CCC	July 2 min 111	No DTMF sending for 3 seconds ±20%
10	$ME \to USS$	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 2.1.1A	[Command performed successfully]
12	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
13	$User \to ME$	End the call	

## PROACTIVE COMMAND: SEND DTMF 2.2.1

# Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Colour Icon"
DTMF String: "1" pause "2"

Icon identifier:

Icon qualifier: icon is self-explanatory Icon identifier: record 2 in  $EF_{(IMG)}$ 

## Coding:

BER-TLV:	D0	1E	81	03	01	14	00	82	02	81	83	85
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	AC	02	C1	F2	9E	02	00	02				

# Expected Sequence 2.2B (SEND DTMF, COLOUR-ICON self explanatory, requested icon could not be displayed)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
4	UICC → ME	message from the USS. PROACTIVE COMMAND	
7	OICC → IVIE	PENDING: SEND DTMF 2.2.1	
5	$ME \rightarrow UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND	[COLOUR-ICON]
		DTMF 2.2.1	-
7	$ME \rightarrow USER$	1. ' '	
		icon	
		Do not locally generate audible	
		DTMF tones and play them to the user.	
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	$ME \to USS$	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully, but
		DTMF 2.1.1B	requested icon could not be displayed]
12	$UICC \to ME$	PROACTIVE UICC SESSION	
10	Llaam . ME	ENDED	
13	User $\rightarrow$ ME	End the call	

# Expected Sequence 2.3A (SEND DTMF, Alpha identifier & BASIC-ICON, not self-explanatory, successful)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
_		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
4	LUCO ME	message from the USS. PROACTIVE COMMAND	
4	$UICC \to ME$	PENDING: SEND DTMF 2.3.1	
5	$ME \rightarrow UICC$		
6		PROACTIVE COMMAND: SEND	[Alpha identifier & BASIC-ICON, not self-
		DTMF 2.3.1	explanatory]
7	$ME \rightarrow USER$	Display 'Send DTMF' and the	71
		BASIC-ICON	
		Do not locally generate audible	
		DTMF tones and play them to the	
_		user.	
8	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20 %
10	/ 000	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DTMF 2.1.1A	
12	$UICC \to ME$	PROACTIVE UICC SESSION	
	CIOO / IVIL	ENDED	
13	$User \to ME$	End the call	

# PROACTIVE COMMAND: SEND DTMF 2.3.1

# Logically:

## Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF"
DTMF String: "1" pause "2"

Icon identifier:

Icon qualifier: icon is not self-explanatory

Icon identifier: record 1 in  $EF_{(IMG)}$ 

Coding:

BER-TLV:	D0	1C	81	03	01	14	00	82	02	81	83	85
	09	53	65	6E	64	20	44	54	4D	46	AC	02
	C1	F2	9E	02	01	01						

# Expected Sequence 2.3B (SEND DTMF, Alpha identifier & BASIC-ICON, not self-explanatory, requested icon could not be displayed)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND	
_		PENDING: SEND DTMF 2.3.1	
5	$ME \rightarrow UICC$		
6	$UICC \to ME$	PROACTIVE COMMAND: SEND	[Alpha identifier & BASIC-ICON, not self-
_		DTMF 2.3.1	explanatory]
7	$ME \rightarrow USER$	Display "Send DTMF" without the	
		icon	
		Do not locally generate audible	
		DTMF tones and play them to the	
8	ME LICC	user. Start DTMF 1.1	["4"]
9	$ME \rightarrow USS$ $ME$	Start DTIVIE 1.1	["1"]
10		Start DTMF 1.2	No DTMF sending for 3 seconds ±20%
_	,		["2"]
11	INIE → UICC	TERMINAL RESPONSE: SEND DTMF 2.1.1B	[Command performed successfully, but
12	UICC → ME	PROACTIVE UICC SESSION	requested icon could not be displayed]
12		ENDED	
13	User → ME	End the call	

## 27.22.4.24.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

# 27.22.4.24.3 SEND DTMF (UCS2 display in Cyrillic)

27.22.4.24.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646. [17].

#### 27.22.4.24.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.24.3.4 Method of test

#### 27.22.4.24.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.24.3.4.2 Procedure

# Expected Sequence 3.1 (SEND DTMF, successful, UCS2 text in Cyrillic)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
4	LUCC - ME	message from the USS. PROACTIVE COMMAND	
4	OICC → ME	PENDING: SEND DTMF 3.1.1	
5	$ME \rightarrow UICC$		
_			
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 3.1.1	
_		_	FILLI-U-II in December 1
7		Display "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	$ME \to USS$	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DTMF 3.1.1	
12	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
13	$User \to ME$	End the call	

#### PROACTIVE COMMAND: SEND DTMF 3.1.1

# Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Text: "ЗДРАВСТВУЙТЕ" DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	28	81	03	01	14	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	AC	02	C1	F2						

TERMINAL RESPONSE: SEND DTMF 3.1.1

Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successful

Coding:

BER-TLV: 81 03 01		82 02 82	81 83 01 0	00
-------------------	--	----------	------------	----

#### 27.22.4.12.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

# 27.22.4.24.4 SEND DTMF (support of Text Attribute)

27.22.4.24.4.1 SEND DTMF (support of Text Attribute – Left Alignment)

#### 27.22.4.24.4.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.1.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.1.4 Method of test

27.22.4.24.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.1.4.2 Procedure

# **Expected Sequence 4.1 (SEND DTMF, with text attribute – Left Alignment)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \rightarrow ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
4	$UICC \to ME$	message from the USS. PROACTIVE COMMAND PENDING: SEND DTMF 4.1.1	
5	$ME \to UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.1.1	
7	$ME \to USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with left alignment]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	$ME \to USS$	Start DTMF 1.2	["2"]
10	$ME \to USS$	Start DTMF 1.3	["3"]
11	$ME \to USS$	Start DTMF 1.4	["4"]
12	$ME \to USS$	Start DTMF 1.5	["5"]
13	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
14	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
15	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
16	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
17	$ME \rightarrow USS$	Start DTMF 1.10	["0"]
18	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
19	$UICC \to ME$	DTMF 4.1.1 PROACTIVE UICC SESSION	
20	$User \to ME$	ENDED End the call	
21	$User \to ME$	Set up a call to "+0123456789"	
22	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT message from the USS.	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.1.2	
25	$ME \to UICC$	FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.1.2	
27	$ME \to USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/17, no alignment change will take place]
28	$ME \to USS$	Start DTMF 1.1	["1"]
29	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
30	$ME \to USS$	Start DTMF 1.3	["3"]
31	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
32	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
33	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
34	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
35	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
36	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
37		Start DTMF 1.9	["0"]
	$ME \rightarrow USS$		
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.1.1	[Command performed successfully]
39	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
40	$User \to ME$	End the call	

PROACTIVE COMMAND: SEND DTMF 4.1.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.1.2

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85	
	0B	53	65	6E	64	20	44	54	4D	46	20	32	
	AC	05	21	43	65	87	09						

# TERMINAL RESPONSE: SEND DTMF 4.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV	: 81	03	01	14	00	82	02	82	81	83	01	00	
---------	------	----	----	----	----	----	----	----	----	----	----	----	--

## 27.22.4.24.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.24.4.2 SEND DTMF (support of Text Attribute – Center Alignment)

27.22.4.24.4.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.2.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.2.4 Method of test

#### 27.22.4.24.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.24.4.2.4.2 Procedure

# Expected Sequence 4.2 (SEND DTMF, with text attribute – Center Alignment)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \rightarrow ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
3	$USS \to ME$	"+0123456789" The ME receives the CONNECT	
4	$UICC \to ME$	message from the USS. PROACTIVE COMMAND PENDING: SEND DTMF 4.2.1	
5	$ME \rightarrow UICC$	FETCH	
6		PROACTIVE COMMAND: SEND	
	OICC → IVIL	DTMF 4.2.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with center alignment]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	$ME \to USS$	Start DTMF 1.2	["2"]
10	$ME \to USS$	Start DTMF 1.3	["3"]
11	$ME \to USS$	Start DTMF 1.4	["4"]
12	$ME \to USS$	Start DTMF 1.5	["5"]
13	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
14	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
15	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
16	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18		TERMINAL RESPONSE: SEND	[Command performed successfully]
19	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
20	User $\rightarrow$ ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22		The ME attempts to set up a call to	
	ME → USS	"+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT message from the USS.	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.2.2	
25	$ME \rightarrow UICC$	FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.2.2	
27		Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/17, no alignment change will take place]
28	$ME \to USS$	Start DTMF 1.1	["1"]
29	$ME \to USS$	Start DTMF 1.2	["2"]
30	$ME \to USS$	Start DTMF 1.3	["3"]
31	$ME \to USS$	Start DTMF 1.4	["4"]
32	$ME \to USS$	Start DTMF 1.5	["5"]
33	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
34	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
35	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
36	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
37		Start DTMF 1.9	["0"]
	ME → USS		
38	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.2.1	[Command performed successfully]
39	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
40	$User \to ME$	End the call	

PROACTIVE COMMAND: SEND DTMF 4.2.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
_	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	01
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.2.2

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

# Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
•	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09					

## TERMINAL RESPONSE: SEND DTMF 4.2.1

#### Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00	1
----------	----	----	----	----	----	----	----	----	----	----	----	----	---

27.22.4.24.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

27.22.4.24.4.3 SEND DTMF (support of Text Attribute – Right Alignment)

27.22.4.24.4.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.24.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.3.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.3.4 Method of test

27.22.4.24.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.3.4.2 Procedure

# Expected Sequence 4.3 (SEND DTMF, with text attribute – Right Alignment)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	$User \rightarrow ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to	
		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
4	11100 145	message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.3.1	
5	$ME \rightarrow UICC$	FETCH	
6		PROACTIVE COMMAND: SEND	
		DTMF 4.3.1	
7	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with right
		Do not locally generate audible	alignment]
		DTMF tones and play them to the	
		user.	FII 4 II 3
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5 Start DTMF 1.6	["5"]
13 14	ME → USS	Start DTMF 1.6	["6"] ["7"]
15	$ME \rightarrow USS$	Start DTMF 1.7	[ "8"]
16	$\begin{array}{c} ME \to USS \\ ME \to USS \end{array}$	Start DTMF 1.9	["9"]
17	$ME \rightarrow USS$	Start DTMF 1.10	[["0"]
18		TERMINAL RESPONSE: SEND	[Command performed successfully]
10	WE 70100	DTMF 4.3.1	[Command ponomica decederany]
19	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
20	$User \to ME$	End the call	
21	$User \to ME$	Set up a call to "+0123456789"	
22	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT	
	OGO / IVIE	message from the USS.	
24	$UICC \to ME$	PROAČTIVE COMMAND	
		PENDING: SEND DTMF 4.3.2	
25		FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND	
27	ME LIGED	DTMF 4.3.2	[Magazaga aball be formatted without right
27		Display "Send DTMF" Do not locally generate audible	[Message shall be formatted without right alignment. Remark: If right alignment is the
		DTMF tones and play them to the	ME"s default alignment as declared in table
		user.	A.2/17, no alignment change will take place]
28	$ME \to USS$	Start DTMF 1.1	["1"]
29	$ME \to USS$	Start DTMF 1.2	["2"]
30	$ME \to USS$	Start DTMF 1.3	["3"]
31	$ME \to USS$	Start DTMF 1.4	["4"]
32	$ME \to USS$	Start DTMF 1.5	["5"]
33	$ME \to USS$	Start DTMF 1.6	["6"]
34	$ME \to USS$	Start DTMF 1.7	["7"]
35	$ME \to USS$	Start DTMF 1.8	["8"]
36	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.3.1	[Command performed successfully]
39	$UICC \to ME$	PROACTIVE UICC SESSION	
33		ENDED	
40	$User \to ME$	End the call	
•	•	•	

PROACTIVE COMMAND: SEND DTMF 4.3.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
_	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	B0	02
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.3.2

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

## Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
-	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09					

# TERMINAL RESPONSE: SEND DTMF 4.3.1

#### Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

# Coding:

27.22.4.24.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

27.22.4.24.4 SEND DTMF (support of Text Attribute – Large Font Size)

27.22.4.24.4.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.24.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.4.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.4.4 Method of test

27.22.4.24.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.4.2 Procedure

Expected Sequence 4.4 (SEND DTMF, with text attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.4.1	
5	$ME \rightarrow UICC$	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND	
7	$ME \to USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with large font size]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
15	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
16	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
17	$ME \rightarrow USS$	Start DTMF 1.10	["0"]
18	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
19	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
20	$User \to ME$	End the call	
21	$User \to ME$	Set up a call to "+0123456789"	
22	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT message from the USS.	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.4.2	
25	$ME \to UICC$	FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.4.2	
27	$ME \to USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with normal font size]
28	$ME \to USS$	Start DTMF 1.1	["1"]
29	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
30	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
34	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
35	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
36	$ME \to USS$	Start DTMF 1.9	["9"]
37	$ME \to USS$	Start DTMF 1.10	["0"]
38	$ME \to UICC$	TERMINAL RESPONSE: SEND DTMF 4.4.1	[Command performed successfully]
39	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
40	$User \to ME$	End the call	
41	$User \to ME$	Set up a call to "+0123456789"	
42	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
43	$USS \to ME$	The ME receives the CONNECT message from the USS.	
44	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.4.1	

45	$ME \rightarrow UICC$	   FETCH	l I
46	UICC → ME	PROACTIVE COMMAND: SEND	
		DTMF 4.4.1	
47	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with large font
		Do not locally generate audible	size]
		DTMF tones and play them to the	
		user.	
48	$ME \to USS$	Start DTMF 1.1	["1"]
49	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
50	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
51	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
52	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
53	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
54	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.4.1	[Command performed successfully]
59	$UICC \to ME$	PROACTIVE UICC SESSION	
39		ENDED	
60	User $\rightarrow$ ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	$ME \rightarrow USS$	The ME attempts to set up a call to	
		"+0123456789"	
63	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
64	$UICC \to ME$	PROACTIVE COMMAND	
0.5		PENDING: SEND DTMF 4.4.3	
65	ME → UICC	FETCH	
66	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.4.3	
67	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with normal font
		Do not locally generate audible	size]
		DTMF tones and play them to the	_
1		user.	
68	$ME \to USS$	Start DTMF 1.1	["1"]
69	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
70	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
71	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
72	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
73	ME → USS	Start DTMF 1.6	["6"]
74	ME → USS	Start DTMF 1.7	["7"]
75 76	$ME \rightarrow USS$	Start DTMF 1.8 Start DTMF 1.9	["8"]
76 77	ME → USS	Start DTMF 1.9 Start DTMF 1.10	["9"] ["0"]
78	$ME \to USS$ $ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
10	IVIE -> UICC	DTMF 4.4.1	[Command pendinied successibility]
79	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
80	$User \to ME$	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.4.1

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	04
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.4.2

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.4.3

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 3" DTMF String: "1234567890"

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
·	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.4.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00

## 27.22.4.24.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.24.4.5 SEND DTMF (support of Text Attribute – Small Font Size)

27.22.4.24.4.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.5.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.5.4 Method of test

#### 27.22.4.24.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

27.22.4.24.4.5.4.2 Procedure

# Expected Sequence 4.5 (SEND DTMF, with text attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$User \rightarrow ME$	Set up a call to "+0123456789"	
2	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.5.1	
5	$ME \rightarrow UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.5.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with small font size]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
10	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
11	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.5.1	[Command performed successfully]
19	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
20	$User \to ME$	End the call	
21	$User \to ME$	Set up a call to "+0123456789"	
22	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT message from the USS.	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.5.2	
25	$ME \rightarrow UICC$	FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.5.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with normal font size]
28	$ME \to USS$	Start DTMF 1.1	["1"]
29	$ME \to USS$	Start DTMF 1.2	["2"]
30	$ME \to USS$	Start DTMF 1.3	["3"]
31	$ME \to USS$	Start DTMF 1.4	["4"]
32	$ME \to USS$	Start DTMF 1.5	["5"]
33	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
34	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
35	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
36	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
37	$ME \rightarrow USS$	Start DTMF 1.10	["0"]
38	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.5.1	[Command performed successfully]
39	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
40	$User \to ME$	End the call	
41	$User \to ME$	Set up a call to "+0123456789"	
42	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.5.1	

45	$ME \rightarrow UICC$	   FETCH	l I
46	UICC → ME	PROACTIVE COMMAND: SEND	
		DTMF 4.5.1	
47	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with small font
		Do not locally generate audible	size]
		DTMF tones and play them to the	
		user.	
48	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
49	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
50	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
51	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
52	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
53	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
59	$UICC \to ME$	DTMF 4.5.1 PROACTIVE UICC SESSION	
39		ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to	
	/ 555	"+0123456789"	
63	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
64	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DTMF 4.5.3	
65	$ME \rightarrow UICC$	FETCH	
66	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.5.3	
67	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with normal font
	, 001.1	Do not locally generate audible	size]
		DTMF tones and play them to the	•
		user.	
68	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
69	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
70	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
71	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
72	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
73	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
74	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
75	ME → USS	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]
77	ME → USS	Start DTMF 1.10	["0"]
78	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.5.1	[Command performed successfully]
79	$UICC \to ME$	PROACTIVE UICC SESSION	
1		ENDED	
80	User $\rightarrow$ ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.5.1

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	80
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.5.2

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.5.3

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

585

TERMINAL RESPONSE: SEND DTMF 4.5.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV: 81 03 01		82 02 82	81 83 01 0	00
-------------------	--	----------	------------	----

## 27.22.4.24.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.24.4.6 SEND DTMF (support of Text Attribute – Bold On)

27.22.4.24.4.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.6.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the bold text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.6.4 Method of test

27.22.4.24.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

27.22.4.24.4.6.4.2 Procedure

# Expected Sequence 4.6 (SEND DTMF, with text attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.6.1	
5	$ME \rightarrow UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.6.1	
7	$ME \rightarrow USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with bold on]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	$ME \to USS$	Start DTMF 1.2	["2"]
10	$ME \to USS$	Start DTMF 1.3	["3"]
11	$ME \to USS$	Start DTMF 1.4	["4"]
12	$ME \to USS$	Start DTMF 1.5	["5"]
13	$ME \rightarrow USS$		["6"]
14	$ME \to USS$	Start DTMF 1.7	["7"]
15	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
19	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
20	User $\rightarrow$ ME	End the call	
21	User $\rightarrow$ ME	Set up a call to "+0123456789"	
22	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT message from the USS.	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.6.2	
25	$ME \rightarrow UICC$	FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.6.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with bold off]
28	$ME \to USS$	Start DTMF 1.1	["1"]
29	$ME \to USS$	Start DTMF 1.2	["2"]
30	$ME \to USS$	Start DTMF 1.3	["3"]
31	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
32	$ME \to USS$	Start DTMF 1.5	["5"]
33	$ME \to USS$	Start DTMF 1.6	["6"]
34	$ME \to USS$	Start DTMF 1.7	["7"]
35	$ME \to USS$	Start DTMF 1.8	["8"]
36	$ME \to USS$	Start DTMF 1.9	["9"]
37	$ME \to USS$	Start DTMF 1.10	["0"]
38	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
39	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
40	$User \to ME$	End the call	
41	$User \to ME$	Set up a call to "+0123456789"	
42	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.6.1	

45	$ME \rightarrow UICC$	FETCH	
46	$UICC \rightarrow ME$	PROACTIVE COMMAND: SEND	
		DTMF 4.6.1	
47	$ME \to USER$		[Alpha identifier is displayed with bold on]
		Do not locally generate audible	
		DTMF tones and play them to the	
		user.	
48	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
49	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
50	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
51	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
52	ME → USS	Start DTMF 1.5	["5"]
53	ME → USS	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
59	$UICC \to ME$	PROACTIVE UICC SESSION	
33	OICC → IVIL	ENDED	
60	User $\rightarrow$ ME	End the call	
61	User $\rightarrow$ ME	Set up a call to "+0123456789"	
62	$ME \to USS$	The ME attempts to set up a call to	
		"+0123456789"	
63	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
64	$UICC \to ME$	PROACTIVE COMMAND	
0.5	ME IIIOO	PENDING: SEND DTMF 4.6.3	
65	ME → UICC	FETCH PROACTIVE COMMAND: SEND	
66	$UICC \to ME$	DTMF 4.6.3	
67	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with bold off]
	, 00Lit	Do not locally generate audible	[
		DTMF tones and play them to the	
		user.	
68	$ME \to USS$	Start DTMF 1.1	["1"]
69	$ME \to USS$	Start DTMF 1.2	["2"]
70	$ME \to USS$	Start DTMF 1.3	["3"]
71	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
72	$ME \to USS$	Start DTMF 1.5	["5"]
73	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
74	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
75	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]
77	ME → USS	Start DTMF 1.10	["0"]
78	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
79	$UICC \to ME$	PROACTIVE UICC SESSION	
1 _		ENDED	
80	$User \to ME$	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.6.1

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	10
	B4	00										

#### PROACTIVE COMMAND: SEND DTMF 4.6.2

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.6.3

Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 3" DTMF String: "1234567890"

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.6.1

Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

#### Coding:

В	ER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00

## 27.22.4.24.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.24.4.7 SEND DTMF (support of Text Attribute – Italic On)

27.22.4.24.4.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.7.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the italic text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.7.4 Method of test

#### 27.22.4.24.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

27.22.4.24.4.7.4.2 Procedure

# Expected Sequence 4.7 (SEND DTMF, with text attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments						
1	$User \rightarrow ME$	Set up a call to "+0123456789"							
2	$ME \to USS$	The ME attempts to set up a call to "+0123456789"							
3	$USS \to ME$	The ME receives the CONNECT message from the USS.							
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.7.1							
5	$ME \to UICC$	FETCH							
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.7.1							
7	$ME \to USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with italic on]						
8	$ME \to USS$	Start DTMF 1.1	["1"]						
9	$ME \to USS$	Start DTMF 1.2	["2"]						
10	$ME \to USS$	Start DTMF 1.3	["3"]						
11	$ME \rightarrow USS$	Start DTMF 1.4	["4"]						
12	$ME \rightarrow USS$	Start DTMF 1.5	["5"]						
13	$ME \rightarrow USS$	Start DTMF 1.6	["6"]						
14	ME → USS	Start DTMF 1.7	["7"]						
15	$ME \rightarrow USS$	Start DTMF 1.8	["8"]						
16	$ME \rightarrow USS$	Start DTMF 1.9	["9"]						
17	ME → USS	Start DTMF 1.10	["0"]						
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.7.1	[Command performed successfully]						
19	$UICC \to ME$	PROACTIVE UICC SESSION ENDED							
20	$User \to ME$	End the call							
21	$User \to ME$	Set up a call to "+0123456789"							
22	$ME \to USS$	The ME attempts to set up a call to "+0123456789"							
23	$USS \to ME$	The ME receives the CONNECT message from the USS.							
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.7.2							
25	$ME \rightarrow UICC$	FETCH							
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.7.2							
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with italic off]						
28	$ME \to USS$	Start DTMF 1.1	["1"]						
29	$ME \rightarrow USS$	Start DTMF 1.2	["2"]						
30	$ME \rightarrow USS$	Start DTMF 1.3	["3"]						
31	$ME \to USS$	Start DTMF 1.4	["4"]						
32	$ME \to USS$	Start DTMF 1.5	["5"]						
33	$ME \to USS$	Start DTMF 1.6	["6"]						
34	$ME \to USS$	Start DTMF 1.7	["7"]						
35	$ME \to USS$	Start DTMF 1.8	["8"]						
36	$ME \to USS$	Start DTMF 1.9	["9"]						
37	$ME \to USS$	Start DTMF 1.10	["0"]						
38	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.7.1	[Command performed successfully]						
39	$UICC \to ME$	PROACTIVE UICC SESSION ENDED							
40	$User \to ME$	End the call							
41	$User \to ME$	Set up a call to "+0123456789"							
42	$ME \to USS$	The ME attempts to set up a call to "+0123456789"							
43	$USS \to ME$	The ME receives the CONNECT message from the USS.							
44	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.7.1							

45 46	$\begin{array}{c} ME \to UICC \\ UICC \to ME \end{array}$	FETCH PROACTIVE COMMAND: SEND	
40	UICC → ME	DTMF 4.7.1	
47	$ME \to USER$		[Alpha identifier is displayed with italic on]
		Do not locally generate audible DTMF tones and play them to the	
		user.	
48	$ME \to USS$	Start DTMF 1.1	["1"]
49	$ME \to USS$	Start DTMF 1.2	["2"]
50	$ME \to USS$	Start DTMF 1.3	["3"]
51	$ME \to USS$	Start DTMF 1.4	["4"]
52	$ME \to USS$	Start DTMF 1.5	["5"]
53	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
54	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56 57	ME → USS	Start DTMF 1.10	["9"]
57 58	$ME \rightarrow USS$ $ME \rightarrow UICC$	Start DTMF 1.10 TERMINAL RESPONSE: SEND	["0"] [Command performed successfully]
36	IVIE → UICC	DTMF 4.7.1	[Confinant performed successibility]
59	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
60	$User \to ME$	End the call	
61	$User \to ME$	Set up a call to "+0123456789"	
62	$ME \rightarrow USS$	The ME attempts to set up a call to	
62	LICC - ME	"+0123456789" The ME receives the CONNECT	
63	$USS \to ME$	message from the USS.	
64	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DTMF 4.7.3	
65	$ME \to UICC$	FETCH	
66	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.7.3	
67	$ME \to USER$		[Alpha identifier is displayed with italic off]
		Do not locally generate audible	
		DTMF tones and play them to the	
68	$ME \to USS$	user. Start DTMF 1.1	["1"]
69	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
70	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
71	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
72	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
73	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
74	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
75	$ME \to USS$	Start DTMF 1.8	["8"]
76	$ME \to USS$	Start DTMF 1.9	["9"]
77	$ME \to USS$	Start DTMF 1.10	["0"]
78	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
70		DTMF 4.7.1	
79	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
80	$User \to ME$	End the call	
	3001 / IVIL	1	

## PROACTIVE COMMAND: SEND DTMF 4.7.1

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	20
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.7.2

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.7.3

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 3" DTMF String: "1234567890"

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
·	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

595

TERMINAL RESPONSE: SEND DTMF 4.7.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00

## 27.22.4.24.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

27.22.4.24.4.8 SEND DTMF (support of Text Attribute – Underline On)

27.22.4.24.4.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.8.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the underline text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.8.4 Method of test

#### 27.22.4.24.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

27.22.4.24.4.8.4.2 Procedure

# Expected Sequence 4.8 (SEND DTMF, with text attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$User \rightarrow ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.8.1	
5	$ME \rightarrow UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.8.1	
7	$ME \rightarrow USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with underline on]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	$ME \to USS$	Start DTMF 1.2	["2"]
10	$ME \to USS$	Start DTMF 1.3	["3"]
11	$ME \to USS$	Start DTMF 1.4	["4"]
12	$ME \to USS$	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.8.1	[Command performed successfully]
19	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
20	$User \to ME$	End the call	
21	$User \to ME$	Set up a call to "+0123456789"	
22	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT message from the USS.	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.8.2	
25	$ME \rightarrow UICC$	FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.8.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with underline off]
28	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
29	$ME \to USS$	Start DTMF 1.2	["2"]
30	$ME \to USS$	Start DTMF 1.3	["3"]
31	$ME \to USS$	Start DTMF 1.4	["4"]
32	$ME \to USS$	Start DTMF 1.5	["5"]
33	$ME \to USS$	Start DTMF 1.6	["6"]
34	$ME \to USS$	Start DTMF 1.7	["7"]
35	$ME \to USS$	Start DTMF 1.8	["8"]
36	$ME \to USS$	Start DTMF 1.9	["9"]
37	$ME \to USS$	Start DTMF 1.10	["0"]
38	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.8.1	[Command performed successfully]
39	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
40	$User \to ME$	End the call	
41	$User \to ME$	Set up a call to "+0123456789"	
42	ME → USS	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.8.1	

45	$ME \rightarrow UICC$	   FETCH	l I
46		PROACTIVE COMMAND: SEND	
		DTMF 4.8.1	
47	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with underline
		Do not locally generate audible	on]
		DTMF tones and play them to the	
		user.	
48	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
49	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
50	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
51	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
52	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
53	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
54	$ME \rightarrow USS$	Start DTMF 1.7	["7"]
55	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
56	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
57	$ME \rightarrow USS$	Start DTMF 1.10	["0"]
58	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
	LUCO ME	DTMF 4.8.1	
59	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to	
02	IVIL -> 000	"+0123456789"	
63	$USS \to ME$	The ME receives the CONNECT	
	7	message from the USS.	
64	$UICC \to ME$	PROAČTIVE COMMAND	
		PENDING: SEND DTMF 4.8.3	
65	$ME \rightarrow UICC$	FETCH	
66	$UICC \to ME$	PROACTIVE COMMAND: SEND	
67	ME LICED	DTMF 4.8.3 Display "Send DTMF"	[Alpha identifier is displayed with underline
07	$ME \rightarrow USER$	Do not locally generate audible	[Alpha identifier is displayed with underline off]
		DTMF tones and play them to the	Onj
		user.	
68	$ME \to USS$	Start DTMF 1.1	["1"]
69	$ME \rightarrow USS$	Start DTMF 1.2	["2"]
70	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
71	$ME \to USS$	Start DTMF 1.4	["4"]
72	$ME \to USS$	Start DTMF 1.5	["5"]
73	$ME \rightarrow USS$	Start DTMF 1.6	["6"]
74	$ME \to USS$	Start DTMF 1.7	["7"]
75	$ME \to USS$	Start DTMF 1.8	["8"]
76	$ME \to USS$	Start DTMF 1.9	["9"]
77	$ME \to USS$	Start DTMF 1.10	["0"]
78	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
1		DTMF 4.8.1	
79	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
80	User $\rightarrow$ ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.8.1

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	40
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.8.2

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
identifier: "Send DTMF 2"

Alpha identifier: "Se DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.8.3

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 3" DTMF String: "1234567890"

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.8.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

В	ER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00

## 27.22.4.24.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

27.22.4.24.4.9 SEND DTMF (support of Text Attribute – Strikethrough On)

27.22.4.24.4.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.9.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.9.4 Method of test

27.22.4.24.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

27.22.4.24.4.9.4.2 Procedure

# Expected Sequence 4.9 (SEND DTMF, with text attribute – Strikethrough On)

2	Step	Direction	MESSAGE / Action	Comments
VSS → ME	-	$User \to ME$	Set up a call to "+0123456789"	
USS → ME	2	$ME \to USS$		
Me → UICC → ME				
VICC → ME	3	$USS \to ME$		
PENDING: SEND DTMF 4.9.1				
ME → UICC	4	$UICC \rightarrow ME$		
Company   Com	_			
The Fig.   The Fig.   The Me   The M				
ME → USS   Display "Send DTMF"   Donot locally generate audible DTMF tones and play them to the user.   ME → USS   Start DTMF 1.1   [*1*]	6	$UICC \to ME$		
Do not locally generate audible	7	ME HOED		
DTMF tones and play them to the user.	1	ME → USER		
Sar DTMF 1.1   [11]   [12]   [12]   [13]   [13]   [13]   [14]				onj
ME → USS   Start DTMF 1.1   [*1*]   [*2*]				
ME → USS   Start DTMF 1.2   ["2"]   ["3"]	8	MF → USS		["1"]
10				
11				
12				
13				
14				
15				
16				
ME → USS   Start DTMF 1.10   ["0"]   [Command performed successfully]				
ME → UICC   TERMINAL RESPONSE: SEND   DTMF 4.9.1				
19				
19	10	ME → UICC		[Confinant penornied successfully]
ENDED	10	LIICC \ ME	_	
User → ME	13	OICC - IVIE		
21	20	llser → MF		
22         ME → USS         The ME attempts to set up a call to "+0/123456789"           23         USS → ME         The ME receives the CONNECT message from the USS.           24         UICC → ME         PROACTIVE COMMAND PENDING: SEND DTMF 4.9.2           25         ME → UICC         FETCH PROACTIVE COMMAND: SEND DTMF 4.9.2           26         UICC → ME         PROACTIVE COMMAND: SEND DTMF 4.9.2           27         ME → USS Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.         [Alpha identifier is displayed with strikethrooff]           28         ME → USS Start DTMF 1.1         ["1"]           29         ME → USS Start DTMF 1.2         ["2"]           30         ME → USS Start DTMF 1.3         ["3"]           31         ME → USS Start DTMF 1.4         ["4"]           32         ME → USS Start DTMF 1.5         ["5"]           33         ME → USS Start DTMF 1.6         ["6"]           34         ME → USS Start DTMF 1.8         ["8"]           36         ME → USS Start DTMF 1.9         ["9"]           37         ME → USS Start DTMF 1.10         ["0"]           38         ME → USS Start DTMF 1.9         ["0"]           39         UICC → ME         End the call           40         User → ME				
#-0123456789" The ME receives the CONNECT message from the USS. PROACTIVE COMMAND PENDING: SEND DTMF 4.9.2 FETCH DICC → ME  WE → USER  ME → USER  ME → USS Start DTMF 1.2 Start DTMF 1.3 ME → USS Start DTMF 1.4 Start DTMF 1.5 ME → USS ME → USS Start DTMF 1.6 ME → USS Start DTMF 1.6 ME → USS Start DTMF 1.7 Start DTMF 1.7 ME → USS Start DTMF 1.7 ME → USS Start DTMF 1.7 ME → USS Start DTMF 1.7 ME → USS Start DTMF 1.7 ME → USS Start DTMF 1.7 ME → USS Start DTMF 1.7 ME → USS Start DTMF 1.9 ME → USS Start DTMF 1.10 ME → USS Start DTMF 1.10 TERMINAL RESPONSE: SEND DTMF 4.9.1 DTMF 4.9.1 ME → USS ME				
USS → ME		WIE 7 000		
Discription   Discription	23	$USS \to ME$		
25         ME → UICC         PENDING: SEND DTMF 4.9.2         FETCH           26         UICC → ME         PROACTIVE COMMAND: SEND DTMF 4.9.2         [Alpha identifier is displayed with strikethre off]           27         ME → USER         Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.         [Alpha identifier is displayed with strikethre off]           28         ME → USS         Start DTMF 1.1         ["1"]           29         ME → USS         Start DTMF 1.2         ["2"]           30         ME → USS         Start DTMF 1.3         ["3"]           31         ME → USS         Start DTMF 1.4         ["4"]           32         ME → USS         Start DTMF 1.5         ["5"]           33         ME → USS         Start DTMF 1.6         ["6"]           34         ME → USS         Start DTMF 1.7         ["7"]           35         ME → USS         Start DTMF 1.8         ["8"]           36         ME → USS         Start DTMF 1.10         ["0"]           37         ME → USS         Start DTMF 1.10         ["0"]           38         ME → USS         Start DTMF 1.10         ["0"]           40         User → ME         End the call           41         User → ME				
25         ME → UICC         FETCH PROACTIVE COMMAND: SEND DTMF 4.9.2         Image: Command of the comma	24	$UICC \to ME$	PROACTIVE COMMAND	
26         UICC → ME         PROACTIVE COMMAND: SEND DTMF 4.9.2         [Alpha identifier is displayed with strikethre off]           27         ME → USER         Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.         [Alpha identifier is displayed with strikethre off]           28         ME → USS Start DTMF 1.1         ["1"]           29         ME → USS Start DTMF 1.2         ["2"]           30         ME → USS Start DTMF 1.3         ["3"]           31         ME → USS Start DTMF 1.4         ["4"]           32         ME → USS Start DTMF 1.5         ["5"]           33         ME → USS Start DTMF 1.6         ["6"]           34         ME → USS Start DTMF 1.7         ["7"]           35         ME → USS Start DTMF 1.9         ["8"]           36         ME → USS Start DTMF 1.10         ["9"]           37         ME → USS Start DTMF 1.10         ["0"]           38         ME → USS Start DTMF 1.9         ["0"]           39         UICC → ME         Set up a call to "+0123456789"           40         User → ME Set up a call to "+0123456789"           41         User → ME Set up a call to "+0123456789"           43         USS → ME WE receives the CONNECT message from the USS.           44         UICC → ME			PENDING: SEND DTMF 4.9.2	
DTMF 4.9.2 Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.  28		$ME \rightarrow UICC$		
ME → USER	26	$UICC \to ME$		
Do not locally generate audible DTMF tones and play them to the user.   Start DTMF 1.1   ["1"]				
DTMF tones and play them to the user.	27	$ME \rightarrow USER$		[Alpha identifier is displayed with strikethrough
28       ME → USS       Start DTMF 1.1       ["1"]         29       ME → USS       Start DTMF 1.2       ["2"]         30       ME → USS       Start DTMF 1.3       ["3"]         31       ME → USS       Start DTMF 1.4       ["4"]         32       ME → USS       Start DTMF 1.5       ["5"]         33       ME → USS       Start DTMF 1.6       ["6"]         34       ME → USS       Start DTMF 1.7       ["7"]         35       ME → USS       Start DTMF 1.9       ["8"]         36       ME → USS       Start DTMF 1.10       ["9"]         37       ME → USS       Start DTMF 1.10       ["0"]         38       ME → UICC       DTMF 4.9.1       ["0"]         39       UICC → ME       PROACTIVE UICC SESSION ENDED       [Command performed successfully]         40       User → ME       Set up a call to "+0123456789"       [The ME attempts to set up a call to "+0123456789"         41       USS → ME       "The ME receives the CONNECT message from the USS.         44       UICC → ME       PROACTIVE COMMAND				off]
28       ME → USS       Start DTMF 1.1       ["1"]         29       ME → USS       Start DTMF 1.2       ["2"]         30       ME → USS       Start DTMF 1.3       ["3"]         31       ME → USS       Start DTMF 1.4       ["4"]         32       ME → USS       Start DTMF 1.5       ["5"]         33       ME → USS       Start DTMF 1.6       ["6"]         34       ME → USS       Start DTMF 1.7       ["7"]         35       ME → USS       Start DTMF 1.8       ["8"]         36       ME → USS       Start DTMF 1.10       ["9"]         37       ME → USS       Start DTMF 1.10       ["0"]         38       ME → UICC       TERMINAL RESPONSE: SEND DTMF 4.9.1       [Command performed successfully]         39       UICC → ME       End the call       Set up a call to "+0123456789"       [Command performed successfully]         40       User → ME       Set up a call to "+0123456789"       [The ME attempts to set up a call to "+0123456789"         43       USS → ME       The ME receives the CONNECT message from the USS.         44       UICC → ME       PROACTIVE COMMAND				
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	20	ME LICO		   ["4 "]
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$				
31       ME → USS       Start DTMF 1.4       ["4"]         32       ME → USS       Start DTMF 1.5       ["5"]         33       ME → USS       Start DTMF 1.6       ["6"]         34       ME → USS       Start DTMF 1.7       ["7"]         35       ME → USS       Start DTMF 1.8       ["8"]         36       ME → USS       Start DTMF 1.9       ["9"]         37       ME → USS       Start DTMF 1.10       ["0"]         38       ME → UICC       TERMINAL RESPONSE: SEND DTMF 4.9.1       [Command performed successfully]         39       UICC → ME       PROACTIVE UICC SESSION ENDED       [Command performed successfully]         40       User → ME       Set up a call to "+0123456789"       [The ME attempts to set up a call to "+0123456789"         42       ME → USS       The ME attempts to set up a call to "+0123456789"       The ME receives the CONNECT message from the USS.         43       USC → ME       PROACTIVE COMMAND				
32  ME → USS  Start DTMF 1.5  ["5"]  33  ME → USS  Start DTMF 1.6  ["6"]  34  ME → USS  Start DTMF 1.7  ["7"]  35  ME → USS  Start DTMF 1.8  ["8"]  36  ME → USS  Start DTMF 1.9  ["9"]  37  ME → USS  Start DTMF 1.10  ["0"]  38  ME → UICC  TERMINAL RESPONSE: SEND  ["0"]  39  UICC → ME  PROACTIVE UICC SESSION  ["0"]  40  User → ME  Set up a call to "+0123456789"  41  User → ME  Set up a call to "+0123456789"  42  ME → USS  The ME attempts to set up a call to "+0123456789"  43  USS → ME  The ME receives the CONNECT  ["5"]  44  UICC → ME  PROACTIVE COMMAND				
33       ME → USS       Start DTMF 1.6       ["6"]         34       ME → USS       Start DTMF 1.7       ["7"]         35       ME → USS       Start DTMF 1.8       ["8"]         36       ME → USS       Start DTMF 1.9       ["9"]         37       ME → USS       Start DTMF 1.10       ["0"]         38       ME → UICC       TERMINAL RESPONSE: SEND DTMF 4.9.1       [Command performed successfully]         39       UICC → ME       PROACTIVE UICC SESSION ENDED       [Command performed successfully]         40       User → ME       Set up a call to "+0123456789"       [The ME attempts to set up a call to "+0123456789"         42       ME → USS       The ME attempts to set up a call to "+0123456789"         43       USS → ME       The ME receives the CONNECT message from the USS.         44       UICC → ME       PROACTIVE COMMAND				
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$				
35 ME → USS 36 ME → USS 37 ME → USS 38 ME → UICC 39 UICC → ME 40 User → ME 41 User → ME 41 USS → ME 42 ME → USS 43 UICC → ME 44 UICC → ME 45 UICC → ME 46 UICC → ME 47 USS → ME 48 UICC → ME 49 UICC → ME 40 USS → ME 40 USS → ME 41 USS → ME 42 ME → USS 43 USS → ME 44 UICC → ME 45 IT N=18 ["8"] ["8"] ["9"] ["0"] [Command performed successfully] ["0"] [Command performed successfully] ["0"] ["0"] [The ME accesses on a call to "+0123456789" ["10"] [10"				
36 ME → USS Start DTMF 1.9 37 ME → USS Start DTMF 1.10 38 ME → UICC TERMINAL RESPONSE: SEND DTMF 4.9.1 39 UICC → ME PROACTIVE UICC SESSION ENDED End the call 40 User → ME Set up a call to "+0123456789" 41 USER → ME AUSS The ME attempts to set up a call to "+0123456789" 42 ME → USS → ME The ME receives the CONNECT message from the USS. 44 UICC → ME PROACTIVE COMMAND				
37 ME → USS ME → UICC TERMINAL RESPONSE: SEND DTMF 4.9.1  39 UICC → ME PROACTIVE UICC SESSION ENDED 40 User → ME HIGH Set up a call to "+0123456789" 41 USer → ME AUSS ME → USS ME AUSS → ME The ME receives the CONNECT message from the USS.  44 UICC → ME PROACTIVE COMMAND				
38 ME → UICC TERMINAL RESPONSE: SEND DTMF 4.9.1  39 UICC → ME PROACTIVE UICC SESSION ENDED  40 User → ME End the call  41 User → ME Set up a call to "+0123456789"  42 ME → USS The ME attempts to set up a call to "+0123456789"  43 USS → ME The ME receives the CONNECT message from the USS.  44 UICC → ME PROACTIVE COMMAND				
JTMF 4.9.1 PROACTIVE UICC SESSION ENDED  User → ME User → ME User → ME Set up a call to "+0123456789" The ME attempts to set up a call to "+0123456789"  USS → ME UICC → ME UICC → ME UICC → ME UICC → ME UICC → ME UICC → ME UICC → ME UICC → ME UICC → ME DTMF 4.9.1 PROACTIVE UICC SESSION ENDED End the call Set up a call to "+0123456789" The ME attempts to set up a call to "+0123456789" The ME receives the CONNECT message from the USS. PROACTIVE COMMAND				
<ul> <li>39 UICC → ME PROACTIVE UICC SESSION ENDED</li> <li>40 User → ME End the call</li> <li>41 User → ME Set up a call to "+0123456789"</li> <li>42 ME → USS The ME attempts to set up a call to "+0123456789"</li> <li>43 USS → ME The ME receives the CONNECT message from the USS.</li> <li>44 UICC → ME PROACTIVE COMMAND</li> </ul>	30	IVIE → UICC		[Command performed successfully]
40 User → ME ENDED 41 User → ME Set up a call to "+0123456789" 42 ME → USS The ME attempts to set up a call to "+0123456789" 43 USS → ME The ME receives the CONNECT message from the USS. 44 UICC → ME PROACTIVE COMMAND	30	LUCC ME		
40 User → ME 41 User → ME 42 ME → USS  43 USS → ME 44 UICC → ME  44 Find the call  Set up a call to "+0123456789"  The ME attempts to set up a call to "+0123456789"  The ME receives the CONNECT message from the USS.  PROACTIVE COMMAND	53			
<ul> <li>41 User → ME</li></ul>	40	User → MF		
<ul> <li>42 ME → USS The ME attempts to set up a call to "+0123456789"</li> <li>43 USS → ME The ME receives the CONNECT message from the USS.</li> <li>44 UICC → ME PROACTIVE COMMAND</li> </ul>				
<ul> <li>43 USS → ME</li></ul>				
<ul> <li>43 USS → ME The ME receives the CONNECT message from the USS.</li> <li>44 UICC → ME PROACTIVE COMMAND</li> </ul>	12	IVIL -> UUU		
message from the USS.  44 UICC → ME PROACTIVE COMMAND	43	$USS \to MF$		
44 UICC → ME PROACTIVE COMMAND		JUD / IVIL		
	44	$UICC \to ME$		
ן ווייס איני איני איני איני איני איני איני א			PENDING: SEND DTMF 4.9.1	

45	$ME \rightarrow UICC$	leetch	1
46	$UICC \to ME$	PROACTIVE COMMAND: SEND	
40	OICC → IVIE	DTMF 4.9.1	
47	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with strikethrough
	INIE / OOLIK	Do not locally generate audible	on]
		DTMF tones and play them to the	5
		user.	
48	$ME \to USS$	Start DTMF 1.1	["1"]
49	$ME \to USS$	Start DTMF 1.2	["2"]
50	$ME \to USS$	Start DTMF 1.3	["3"]
51	$ME \to USS$	Start DTMF 1.4	["4"]
52	$ME \to USS$	Start DTMF 1.5	["5"]
53	$ME \to USS$	Start DTMF 1.6	["6"]
54	$ME \to USS$	Start DTMF 1.7	["7"]
55	$ME \to USS$	Start DTMF 1.8	["8"]
56	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
57	$ME \to USS$	Start DTMF 1.10	["0"]
58	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DTMF 4.9.1	
59	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	$ME \rightarrow USS$	The ME attempts to set up a call to "+0123456789"	
63	$USS \to ME$	The ME receives the CONNECT	
		message from the USS.	
64	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DTMF 4.9.3	
65	$ME \rightarrow UICC$	FETCH	
66	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		DTMF 4.9.3	
67	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with strikethrough]
		Do not locally generate audible	off]
		DTMF tones and play them to the	
68	$ME \to USS$	user. Start DTMF 1.1	["1"]
69	$ME \rightarrow USS$	Start DTMF 1.1	["2"]
70	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
71	$ME \rightarrow USS$	Start DTMF 1.4	["4"]
72	$ME \rightarrow USS$	Start DTMF 1.5	["5"]
73	$ME \rightarrow USS$	Start DTMF 1.6	
74	$ME \rightarrow USS$	Start DTMF 1.7	["6"] ["7"]
75	$ME \rightarrow USS$	Start DTMF 1.8	["8"]
76	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
77	$ME \rightarrow USS$	Start DTMF 1.10	["0"]
78	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
'	WIL / 0100	DTMF 4.9.1	[Serminal de perfermed adocessiany]
79	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
80	$User \to ME$	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.9.1

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	80B
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.9.2

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

#### PROACTIVE COMMAND: SEND DTMF 4.9.3

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
·	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

605

TERMINAL RESPONSE: SEND DTMF 4.9.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

_													
I	BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00

## 27.22.4.24.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.24.4.10 SEND DTMF (support of Text Attribute – Foreground and Background Colour)

27.22.4.24.4.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.10.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.10.4 Method of test

27.22.4.24.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

## 27.22.4.24.4.10.4.2 Procedure

# Expected Sequence 4.10 (SEND DTMF, with text attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$User \rightarrow ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.10.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND	
		DTMF 4.10.1	
7	$ME \rightarrow USER$	Display "Send DTMF"	[Alpha identifier is displayed with foreground
		Do not locally generate audible DTMF tones and play them to the user.	and background colour according to the text attribute configuration]
8	$ME \rightarrow USS$	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	$ME \rightarrow USS$	Start DTMF 1.9	["9"]
17	$ME \rightarrow USS$	Start DTMF 1.10	[["0"]
18	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DTMF 4.10.1	[Command performed successfully]
19	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
20	$User \to ME$	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
23	$USS \to ME$	The ME receives the CONNECT message from the USS.	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 4.10.2	
25	$ME \rightarrow UICC$	FETCH	
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 4.10.2	
27	$ME \rightarrow USER$	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with ME"s default foreground and background colour]
28	ME → USS	Start DTMF 1.1	["1"]
29	$ME \rightarrow USS$	Start DTMF 1.2	[ ' ] ["2"]
30	$ME \rightarrow USS$	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
39	UICC → ME	DTMF 4.10.1 PROACTIVE UICC SESSION	
40	$User \to ME$	ENDED End the call	

## PROACTIVE COMMAND: SEND DTMF 4.10.1

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.10.2

## Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"

## Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09					

## TERMINAL RESPONSE: SEND DTMF 4.10.1

#### Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.24.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

## 27.22.4.24.5 SEND DTMF (UCS2 Display in Chinese)

#### 27.22.4.24.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in:

- ISO/IEC 10646. [17].

## 27.22.4.24.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.24.5.4 Method of test

#### 27.22.4.24.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.24.5.4.2 Procedure

## Expected Sequence 5.1 (SEND DTMF, successful, UCS2 text in Chinese)

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$	The ME attempts to set up a call to "+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 5.1.1	
5	$ME \rightarrow UICC$	FETCH	
6	$UICC \to ME$	PROACTIVE COMMAND: SEND DTMF 5.1.1	
7	$ME \to USER$	Display "你好"	["Hello" in Chinese]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	$ME \to USS$	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
12	$UICC \to ME$	DTMF 5.1.1 PROACTIVE UICC SESSION ENDED	
13	$User \to ME$	End the call	

## PROACTIVE COMMAND: SEND DTMF 5.1.1

Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Text: "你好"
DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	14	81	03	01	14	00	82	02	81	83	85
·	05	80	4F	60	59	7D	AC	02	C1	F2		

## TERMINAL RESPONSE: SEND DTMF 5.1.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successful

BER-TLV:   81   03   01   14   00	82 02	82 81	83	01	00	ĺ
-----------------------------------	-------	-------	----	----	----	---

## 27.22.4.24.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

## 27.22.4.24.6 SEND DTMF (UCS2 Display in Katakana)

## 27.22.4.24.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in:

- ISO/IEC 10646. [17].

## 27.22.4.24.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.24.6.4 Method of test

#### 27.22.4.24.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.24.6.4.2 Procedure

## Expected Sequence 6.1 (SEND DTMF, successful, UCS2 text)

Step	Direction	MESSAGE / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to USS$		
_		"+0123456789"	
3	$USS \to ME$	The ME receives the CONNECT	
4	LUCO ME	message from the USS.	
4	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DTMF 6.1.1	
5	$ME \rightarrow UICC$		
6		PROACTIVE COMMAND: SEND	
		DTMF 6.1.1	
7	$ME \rightarrow USER$		[Character in Katakana]
8	$ME \to USS$	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	$ME \to USS$	Start DTMF 1.2	["2"]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DTMF 6.1.1	
12	$UICC \to ME$	PROACTIVE UICC SESSION	
4.0		ENDED	
13	User $\rightarrow$ ME	End the call	

#### PROACTIVE COMMAND: SEND DTMF 6.1.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: UICC
Destination device: Network

Alpha Identifier

Text: "ル"

DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	12	81	03	01	14	00	82	02	81	83	85
	03	80	30	EB	AC	02	C1	F2				

## TERMINAL RESPONSE: SEND DTMF 6.1.1

Logically:

Command details

Command number:

Command type: SEND DTMF

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successful

Coding:

BER-TLV: 81 03	01   14   00	82 02 82	81 83	01 00
----------------	--------------	----------	-------	-------

## 27.22.4.24.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.25 LANGUAGE NOTIFICATION

## 27.22.4.25.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.25.2 Conformance Requirement

The ME shall conclude the command by sending TERMINAL RESPONSE (OK) to the UICC, as soon as possible after receiving the LANGUAGE NOTIFICATION proactive UICC command.

- TS 31.111 [15] clause 6.4.25 and clause 6.6.25.

## 27.22.4.25.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the LANGUAGE NOTIFICATION proactive UICC command.

### 27.22.4.25.4 Method of Test

27.22.4.25.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

### 27.22.4.25.4.2 Procedure

### **Expected Sequence 1.1 (LANGUAGE NOTIFICATION)**

See ETSI TS 102 384 [26] in subclause 27.22.4.25.4.2, Expected Sequence 1.1.

### **Expected Sequence 1.2 (LANGUAGE NOTIFICATION)**

See ETSI TS 102 384 [26] in subclause 27.22.4.25.4.2, Expected Sequence 1.2.

### 27.22.4.25.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 and 1.2.

### 27.22.4.26 LAUNCH BROWSER

### 27.22.4.26.1 LAUNCH BROWSER (No session already launched)

### 27.22.4.26.1.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.26.1.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15 and clause 8.31.

### 27.22.4.26.1.3 Test purpose

To verify that when the ME is in idle state, it launches properly the browser session required in LAUNCH BROWSER, and returns a successful result in the TERMINAL RESPONSE command.

### 27.22.4.26.1.4 Method of test

### 27.22.4.26.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is in idle mode.

### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

### 27.22.4.26.1.4.2 Procedure

## Expected Sequence 1.1 (LAUNCH BROWSER, connect to the default URL)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
		1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 1.1.1	if not already launched", no null alpha id.]
4	$ME \rightarrow USER$	ME displays the alpha identifier	
5	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 1.1.1	
7	ME→USS	The ME attempts to launch the	
		session with the default browser	
		parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		browser session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	

### PROACTIVE COMMAND: LAUNCH BROWSER 1.1.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL"

### Coding:

BER-TLV:	D0	18	81	03	01	15	00	82	02	81	82	31
	00	05	0B	44	65	66	61	75	6C	74	20	55
	52	4C										

#### TERMINAL RESPONSE: LAUNCH BROWSER 1.1.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 15 00 82 02 82 81 83 01 00
--

## Expected Sequence 1.2 (LAUNCH BROWSER, connect to the specified URL, alpha identifier length=0)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
_		1.2.1	
2	, 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to defined URL, "launch browser, if
		LAUNCH BROWSER 1.2.1	not already launched, alpha identifier
			length=0]
4	$ME \rightarrow USER$	No information should be	
_		displayed.	
5	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME		[Command parformed augeocafully]
О	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 1.2.1	[Command performed successibility]
7	ME→USS	The ME attempts to connect the	
'	WIE→USS	URL specified in the LAUNCH	
		BROWSER command.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
	0.00 /	ENDED	
9	$USER \to ME$	The user verifies that the URL is	
		properly connected.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	

### PROACTIVE COMMAND: LAUNCH BROWSER 1.2.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC Destination device: ME

URL <a href="http://xxx.yyy.zzz">http://xxx.yyy.zzz</a> (Note: this URL shall be different from the default URL, but it

can be reached from the gateway defined by default in the browser parameters of the

mobile)

Alpha Identifier empty

Coding:

BER-TLV:	D0	1F	81	03	01	15	00	82	02	81	82	31
_	12	68	74	74	70	3A	2F	2F	78	78	78	2E
	79	79	79	2E	7A	7A	7A	05	00			

### TERMINAL RESPONSE: LAUNCH BROWSER 1.2.1

Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
DEIX IEV.	0.	00		10	00	02	02	02	0.	00	0 1	00

## Expected Sequence 1.3 (LAUNCH BROWSER, Browser identity, no alpha identifier)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
		1.3.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 1.3.1	if not already launched, browser identity]
4	$ME \to USER$	ME may display a default message	
		of its own.	
5	$USER \to ME$	The user may confirm the launch	[option: user confirmation]
		browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 1.3.1	
7	$ME { ightarrow} USS$	The ME attempts to connect the	
		default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		browser session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	

### PROACTIVE COMMAND: LAUNCH BROWSER 1.3.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
Browser Identity default
URL empty

Coding::

BER-TLV:	D0	0E	81	03	01	15	00	82	02	81	82	30
	01	00	31	00								

### TERMINAL RESPONSE: LAUNCH BROWSER 1.3.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	0.3	01	15	00	82	02	82	81	83	01	00

## Expected Sequence 1.4 (LAUNCH BROWSER, only GPRS bearer specified and gateway/proxy identity, GPRS supported by USS)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode, GPRS supported by USS, GPRS supported by the ME and activated, the terminal might need to be configured with an entry linking the Gateway/Proxy Identity in the proactive command with the corresponding connectivity parameters in the mobile]
2		PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.4.1 FETCH	
3	11.12	PROACTIVE COMMAND: LAUNCH BROWSER 1.4.1	[connect to the default URL, "launch browser, if not already launched, 1 bearer specified, gateway/proxy id specified]
4	$ME \to USER$	ME may display a default message	
5	$USER \to ME$	The user may confirm the launch browser.	[option: user confirmation]
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 1.4.1	[Command performed successfully]
7	ME→USS	The ME attempts to connect the default URL using the requested bearer and proxy identity	
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	$USER \to ME$	The user verifies that the browser session is properly established with the required bearer. Then he/she ends the navigation. The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 1.4.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty
Bearer GPRS

Gateway/Proxy id

DCSunpacked, 8 bits data

Text string abc.def.ghi.jkl (different from the default IP address)

Coding::

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	32	01	03	0D	10	04	61	62	63	2E	64
	65	66	2F	67	68	69	2F	64	6B	6C		

TERMINAL RESPONSE: LAUNCH BROWSER 1.4.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 15 00 82 02 82 81 83 01 00

Expected Sequence 1.5 Void

27.22.4.26.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4

27.22.4.26.2 LAUNCH BROWSER (Interaction with current session)

27.22.4.26.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.2.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

27.22.4.26.2.3 Test purpose

To verify that when the ME is already busy in a browser session, it launches properly the browser session required in LAUNCH BROWSER, and returns a successful result in the TERMINAL RESPONSE.

27.22.4.26.2.4 Method of test

27.22.4.26.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to a Wap gateway is required. The default browser parameters (IP address, gateway/proxy identity, called number...) of the tested mobile shall be properly filled to access that gateway.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in browser parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

### 27.22.4.26.2.4.2 Procedure

## Expected Sequence 2.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL)

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser	[Browser is in use, the current session is not
1	$UICC \to ME$	session (not default URL). PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.1.1	secured]
2	$ME \to UICC$	FETCH	
3		PROACTIVE COMMAND: LAUNCH BROWSER 2.1.1	[connect to the default URL, "use the existing browser", no null alpha id.]
4	$ME \to USER$	ME displays the alpha identifier	
5	$USER \to ME$	The user confirms the launch	[user confirmation]
		browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 2.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	$USER \to ME$	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation	
		with the default URL.	

### PROACTIVE COMMAND: LAUNCH BROWSER 2.1.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL"

### Coding:

BER-TLV:	D0	18	81	03	01	15	02	82	02	81	82	31
	00	05	0B	44	65	66	61	75	6C	74	20	55
	52	4C										

### TERMINAL RESPONSE: LAUNCH BROWSER 2.1.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00

## Expected Sequence 2.2 (LAUNCH BROWSER, close the existing browser session and launch new browser session, connect to the default URL)

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser session (not default URL)	[Browser is in use, the current session is not secured]
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.2.1	
2	$ME \to UICC$	1=	
3	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 2.2.1	[connect to the default URL, "close the existing browser session and launch new browser session", no null alpha id.]
4	$ME \to USER$	ME displays the alpha identifier	
5	$USER \to ME$	The user confirms the launch browser.	[user confirmation]
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 2.2.1	[Command performed successfully]
7	ME→USS	The ME closes the existing session and attempts to launch the session with the default browser parameters and the default URL.	[The UE has the option of maintaining the currently active PDP Context]
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	$USER \to ME$	The user verifies that the default URL is connected.	
		Then he/she ends the navigation.	

### PROACTIVE COMMAND: LAUNCH BROWSER 2.2.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: close the existing browser session and launch new browser session

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL"

## Coding:

BER-TLV:	D0	18	81	03	01	15	03	82	02	81	82	31
	00	05	0B	44	65	66	61	75	6C	74	20	55
	52	4C										

### TERMINAL RESPONSE: LAUNCH BROWSER 2.2.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: close the existing browser session and launch new browser session

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	03	82	02	82	81	83	01	00
	• .						~-		<b>.</b>		• .	

## Expected Sequence 2.3 (LAUNCH BROWSER, if not already launched)

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser	[Browser is in use, the current session is not
1	$UICC \to ME$	session (not default URL) PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.3.1	secured]
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
4	$ME \to UICC$		if not already launched] [ME unable to process command - browser unavailable]
5	$UICC \to ME$	PROACTIVE UICC SESSION	•
6	$USER \to ME$	ENDED The user verifies that the default URL has not been connected. Then he/she ends the navigation. The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 2.3.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Coding:

BER-TLV:	D0	0B	81	03	01	15	00	82	02	81	82	31
· · · · · · · · · · · · · · · · · · ·	00											

### TERMINAL RESPONSE: LAUNCH BROWSER 2.3.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Launch browser generic error code

Additional data Browser unavailable

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	02	26
	02											

### 27.22.4.26.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

### 27.22.4.26.3 LAUNCH BROWSER (UCS2 display in Cyrillic)

27.22.4.26.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.3.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

### 27.22.4.26.3.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.3.4 Method of test

### 27.22.4.26.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

the default browser parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

### 27.22.4.26.3.4.2 Procedure

## Expected Sequence 3.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Cyrillic)

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser	[Browser is in use, the current session is not
1	$UICC \to ME$	session (not default URL) PROACTIVE COMMAND PENDING: LAUNCH BROWSER 3.1.1	secured]]
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 3.1.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]
4	$ME \to USER$	ME displays the alpha identifier "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
5	$USER \to ME$	The user confirms the launch browser.	[user confirmation]
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 3.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	$USER \to ME$	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

## PROACTIVE COMMAND: LAUNCH BROWSER 3.1.1

### Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier

Data coding scheme: UCS2 (16 bits) Text: "ЗДРАВСТВУЙТЕ"

## Coding:

BER-TLV:	D0	26	81	03	01	15	02	82	02	81	82	31
	00	05	19	80	04	17	04	14	04	20	04	10
	04	12	04	21	04	22	04	12	04	23	04	19
	04	22	04	15								

## TERMINAL RESPONSE: LAUNCH BROWSER 3.1.1

### Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00

### 27.22.4.26.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequence 3.1.

## 27.22.4.26.4 LAUNCH BROWSER (icons support)

27.22.4.26.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.4.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

### 27.22.4.26.4.3 Test purpose

To verify that the ME performs a proper user confirmation with an icon identifier, launches the browser session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.4.4 Method of test

27.22.4.26.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in browser parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

### 27.22.4.26.4.4.2 Procedure

## Expected Sequence 4.1A (LAUNCH BROWSER, use the existing browser, icon not self explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	[Browser is in use, the current session is not
		PENDING: LAUNCH BROWSER	secured]]
		4.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "use the existing
		LAUNCH BROWSER 4.1.1	browser", no null alpha id.]
4	$ME \to USER$	ME displays the alpha identifier	["Not self explan."]
		and the icon	
5	$USER \to ME$	The user confirms the launch	[user confirmation]
		browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 4.1.1 A	
7	ME→USS	The ME does not close the existing	
		session and attempts to connect	
		the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		URL is connected; and the	
		previous URL can be retrieved.	
		Then he/she ends the navigation	
		with the default URL.	

## PROACTIVE COMMAND: LAUNCH BROWSER 4.1.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Not self explan."

Icon identifier:

 $\begin{array}{ll} \text{Icon qualifier:} & \text{not self-explanatory} \\ \text{Icon identifier:} & \text{record 1 in } EF_{\text{(IMG)}} \\ \end{array}$ 

## Coding:

BER-TLV:	D0	21	81	03	01	15	02	82	02	81	82	31
	00	05	10	4E	6F	74	20	73	65	6C	66	20
	65	78	70	6C	61	6 <sup>E</sup>	2 <sup>E</sup>	1E	02	01	01	

### TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 A

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME Destination device: UICC Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00

## Expected Sequence 4.1B (LAUNCH BROWSER, use the existing browser, icon not self explanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	[Browser is in use, the current session is not
		PENDING: LAUNCH BROWSER	secured]]
		4.1.1	
2	/ 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "use the existing
			browser", no null alpha id.]
4	$ME \rightarrow USER$	ME displays the alpha identifier	["Not self explan."]
		Without the icon	
5	$USER \to ME$	The user confirms the launch	[user confirmation]
		browser.	
6	$ME \rightarrow UICC$		[Command performed successfully but
		BROWSER 4.1.1 B	requested icon could not be displayed]
7	$ME { ightarrow} USS$	The ME does not close the existing	
		session and attempts to connect	
		the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		URL is connected; and the	
		previous URL can be retrieved.	
		Then he/she ends the navigation	
		with the default URL.	

TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 B

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully but requested icon could not be displayed

Coding:

BER-T	LV:	81	03	01	15	02	82	02	82	81	83	01	04	
-------	-----	----	----	----	----	----	----	----	----	----	----	----	----	--

## Expected Sequence 4.2A (LAUNCH BROWSER, use the existing browser, icon self explanatory, successful)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	[Browser is in use, the current session is not
		PENDING: LAUNCH BROWSER	secured]]
		4.2.1	
2	L / 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "use the existing
			browser", alpha id. In UCS2]
4		ME displays only the icon	["Self explan."]
5	$USER \to ME$	The user confirms the launch	[user confirmation]
		browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 4.2.1 A	
7	ME→USS	The ME does not close the existing	
		session and attempts to connect	
		the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
	LICED ME	ENDED	
9	$USER \to ME$	The user verifies that the default	
		URL is connected; and the previous URL can be retrieved.	
		Then he/she ends the navigation	
		with the default URL.	
		with the delatit ONL.	

### PROACTIVE COMMAND: LAUNCH BROWSER 4.2.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Self explan."

Icon identifier:

 $\begin{array}{ll} \mbox{Icon qualifier:} & \mbox{self-explanatory} \\ \mbox{Icon identifier:} & \mbox{record 1 in } \mbox{EF}_{(IMG)} \\ \end{array}$ 

## Coding:

BER-TLV:	D0	1D	81	03	01	15	02	82	02	81	82	31
	00	05	0C	53	65	6C	66	20	65	78	70	6C
	61	6 <sup>೬</sup>	2 <sup>೬</sup>	1F	02	00	01					

## TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 A

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00

## Expected Sequence 4.2B (LAUNCH BROWSER, use the existing browser, icon self explanatory, requested icon could not be displayed)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	[Browser is in use, the current session is not
		PENDING: LAUNCH BROWSER	secured]]
		4.2.1	
2	L / 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "use the existing
			browser", alpha id. In UCS2]
4	$ME \rightarrow USER$	ME displays only the alpha	["Self explan."]
		identifier	
5	$USER \to ME$	I.	[user confirmation]
_		browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	
		BROWSER 4.2.1 B	[Command performed successfully but
_			requested icon could not be displayed]
7	ME→USS	The ME does not close the existing	
		session and attempts to connect	
		the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
9	LICED ME	ENDED The user verifies that the default	
9	$USER \to ME$		
		URL is connected; and the previous URL can be retrieved.	
		Then he/she ends the navigation	
		with the default URL.	
		with the delauit ORL.	

TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 B

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully but requested icon could not be displayed

Coding:

BER-TLV: 81 03 01 15 02 82 02 82 81 83 01 04

27.22.4.26.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.1A to 4.2B.

27.22.4.26.5 LAUNCH BROWSER (support of Text Attribute)

27.22.4.26.5.1 LAUNCH BROWSER (support of Text Attribute – Left Alignment)

27.22.4.26.5.1.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.26.5.1.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111[15] clause 5.2, clause 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

### 27.22.4.26.5.1.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the left alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

### 27.22.4.26.5.1.4 Method of test

### 27.22.4.26.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

## 27.22.4.26.5.1.4.2 Procedure

# Expected Sequence 5.1 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	-
		PENDING: LAUNCH BROWSER	
		5.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.1.1	if not already launched", no null alpha id]
4	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with left
			alignment]
5	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.1.1	
7	$ME { ightarrow} USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established.	
		Then he/she ends the navigation.	
10	11100 145	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER 15.1.2	
11	$ME \to UICC$	FETCH	
12	$UICC \rightarrow ME$	PROACTIVE COMMAND:	connect to the default URL, "launch browser,
12	OICC → IVIE	LAUNCH BROWSER 5.1.2	if not already launched", no null alpha id]
13	$ME \rightarrow USER$	ME displays the alpha identifier	[Message shall be formatted without left
13	WE → USEK	lvic displays the alpha identifier	alignment. Remark: If left alignment is the
			ME"s default alignment as declared in table
			A.2/18, no alignment change will take place]
14	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
15	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.1.1	·
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
18	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 5.1.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	00	B4		

### PROACTIVE COMMAND: LAUNCH BROWSER 5.1.2

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.1.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00

## 27.22.4.26.5.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.1.

27.22.4.26.5.2 LAUNCH BROWSER (support of Text Attribute – Center Alignment)

27.22.4.26.5.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.2.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

### 27.22.4.26.5.2.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the center alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.2.4 Method of test

27.22.4.26.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

27.22.4.26.5.2.4.2 Procedure

# Expected Sequence 5.2 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	-
		PENDING: LAUNCH BROWSER	
		5.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.2.1	if not already launched", no null alpha id]
4	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with center
			alignment]
5	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.2.1	
7	$ME { ightarrow} USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
		5.2.2	
11	ME → UICC	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
40	ME HOED	LAUNCH BROWSER 5.2.2	if not already launched", no null alpha id]
13	$ME \rightarrow USER$	ME displays the alpha identifier	[Message shall be formatted without center
			alignment. Remark: If center alignment is the ME"s default alignment as declared in table
			A.2/18, no alignment change will take place]
14	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
14	USER → IVIE	launch browser.	
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
13	IVIL -> UICC	BROWSER 5.2.1	
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION	
	3.00 / IVIL	ENDED	
18	$USER \rightarrow ME$	The user verifies that the default	
	- <del> </del>	Wap session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 5.2.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	01	B4		

### PROACTIVE COMMAND: LAUNCH BROWSER 5.2.2

Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.2.1

Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00

## 27.22.4.26.5.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.2.

27.22.4.26.5.3 LAUNCH BROWSER (support of Text Attribute – Right Alignment)

27.22.4.26.5.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.3.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

### 27.22.4.26.5.3.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the right alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.3.4 Method of test

27.22.4.26.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

## 27.22.4.26.5.3.4.2 Procedure

# Expected Sequence 5.3 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.3.1	-
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.3.1	if not already launched", no null alpha id]
4	$ME \rightarrow USER$	ME displays the alpha identifier	[alpha identifier is displayed with right alignment]
5	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1	[Command performed successfully]
7	$ME { ightarrow} USS$	The ME attempts to launch the	
		session with the default Wap	
_		parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	$USER \to ME$	The user verifies that the default	
	OOLIK / WIL	Wap session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
11	$ME \rightarrow UICC$	5.3.2 FETCH	
12	$VICC \rightarrow ME$	PROACTIVE COMMAND:	connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.3.2	if not already launched", no null alpha id]
13	$ME \rightarrow USER$	ME displays the alpha identifier	[Message shall be formatted without right
			alignment. Remark: If right alignment is the
			ME"s default alignment as declared in table
			A.2/18, no alignment change will take place]
14	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
15	$ME \rightarrow UICC$		[Command performed successfully]
	WE 7 0100	BROWSER 5.3.1	[command ponomica decederany]
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
18	$USER \to ME$	The user verifies that the default	
10	USEN → IVIE	Wap session is properly	
		lestablished.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 5.3.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	02	B4		

### PROACTIVE COMMAND: LAUNCH BROWSER 5.3.2

Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1

Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	I 81	03	I ()1	15	00	82	02	82	I 81	l 83	I ()1	00
	0 1	00	0 1		00	U_	U_	U_	0 1	00	0 1	00

## 27.22.4.26.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.3.

27.22.4.26.5.4 LAUNCH BROWSER (support of Text Attribute – Large Font Size)

27.22.4.26.5.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.5.4.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.&&& [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

### 27.22.4.26.5.4.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the large font size text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.4.4 Method of test

#### 27.22.4.26.5.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

## 27.22.4.26.5.4.4.2 Procedure

# Expected Sequence 5.4 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
	ME LUCC	5.4.1 FETCH	
2	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND:	connect to the default URL, "launch browser,
	OICC - IVIL	LAUNCH BROWSER 5.4.1	if not already launched", no null alpha id]
4	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with large font
_			size]
5	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
6	$ME \rightarrow UICC$		[Command performed successfully]
	W.E 7 0.00	BROWSER 5.4.1	[Command pomentical dassessimily]
7	$ME{ ightarrow}USS$	The ME attempts to launch the	
		session with the default Wap	
	LUCC ME	parameters and the default URL. PROACTIVE UICC SESSION	
8	$UICC \to ME$	ENDED	
9	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established.	
		Then he/she ends the navigation. The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
	0.00 /	PENDING: LAUNCH BROWSER	
		5.4.2	
11	ME → UICC	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 5.4.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	$ME \rightarrow USER$	ME displays the alpha identifier	alpha identifier is displayed with normal font
	WE 7 OOLK		size]
14	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
4.5	ME	launch browser.	
15	$ME \rightarrow UICC$	BROWSER 5.4.1	[Command performed successfully]
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
18	$USER \to ME$	The user verifies that the default	
	OOLIT / IIIL	Wap session is properly	
		established.	
		Then he/she ends the navigation.	
19	$UICC \to ME$	The ME returns in idle mode. PROACTIVE COMMAND	
	OIOO / IVIE	PENDING: LAUNCH BROWSER	
		5.4.1	
20	ME → UICC	FETCH	Facility of the state of the st
21	$UICC \to ME$		[connect to the default URL, "launch browser, if not already launched", no null alpha id]
22	$ME \rightarrow USER$	ME displays the alpha identifier	alpha identifier is displayed with large font
	/ 00		size]
23	$USER \to ME$		[option: user confirmation]
24	ME LUCC	launch browser.	[Command performed successfully]
24	$ME \rightarrow UICC$	BROWSER 5.4.1	[Command performed successfully]
25	ME□USS	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
26	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
ı l		10-0	ı

27	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.3	
29	$ME \to UICC$	FETCH	
30	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 5.4.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with normal font size]
32	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
33	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1	[Command performed successfully]
34	$ME \to USS$	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
36	$USER \to ME$	The user verifies that the default Wap session is properly established.	
		Then he/she ends the navigation. The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 5.4.1

### Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	04	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.4.2

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC

Destination device: ME URL empty Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

### Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.4.3

### Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 3"

### Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1

## Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
	0.	00	0.		00	02	02	02	0.	00	0.	00

## 27.22.4.26.5.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.4.

27.22.4.26.5.5 LAUNCH BROWSER (support of Text Attribute – Small Font Size)

27.22.4.26.5.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.5.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

### 27.22.4.26.5.5.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the small font size text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.5.4 Method of test

27.22.4.26.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

## 27.22.4.26.5.5.4.2 Procedure

# Expected Sequence 5.5 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.1	_
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
4	$ME \to USER$	LAUNCH BROWSER 5.5.1 ME displays the alpha identifier	if not already launched", no null alpha id] [alpha identifier is displayed with small font
5	$USER \to ME$	The user may have to confirm the launch browser.	size] [option: user confirmation]
6	$ME \to UICC$		[Command performed successfully]
7	ME→USS	The ME attempts to launch the session with the default Wap	
8	$UICC \to ME$	parameters and the default URL. PROACTIVE UICC SESSION ENDED	
9	$USER \to ME$	The user verifies that the default Wap session is properly	
10	$UICC \to ME$	established. Then he/she ends the navigation. The ME returns in idle mode. PROACTIVE COMMAND PENDING: LAUNCH BROWSER	
11	$ME \to UICC$	5.5.2 FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND:	connect to the default URL, "launch browser,
13	ME → USER	LAUNCH BROWSER 5.5.2 ME displays the alpha identifier	if not already launched", no null alpha id] [alpha identifier is displayed with normal font
14	$USER \to ME$	The user may have to confirm the launch browser.	size] [option: user confirmation]
15	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1	[Command performed successfully]
16	$ME \rightarrow USS$	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
18	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
19	$UICC \to ME$	The ME returns in idle mode. PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.1	
20	$ME \to UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
22	$ME \to USER$	LAUNCH BROWSER 5.5.1 ME displays the alpha identifier	if not already launched", no null alpha id] [alpha identifier is displayed with small font size]
23	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
24	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1	[Command performed successfully]
25	ME□USS	The ME attempts to launch the session with the default Wap	
26	$UICC \to ME$	parameters and the default URL. PROACTIVE UICC SESSION ENDED	

27	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.3	
29	$ME \to UICC$	FETCH	
30	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 5.5.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with normal font size]
32	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
33	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1	[Command performed successfully]
34	$ME \to USS$	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
36	$USER \to ME$	The user verifies that the default Wap session is properly established.	
		Then he/she ends the navigation. The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 5.5.1

### Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	08	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.5.2

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC

Destination device: ME URL empty Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

### Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.5.3

### Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 3"

### Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1

## Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

## Coding:

	BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
--	----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.26.5.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.5.

27.22.4.26.5.6 LAUNCH BROWSER (support of Text Attribute – Bold on)

27.22.4.26.5.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.6.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

### 27.22.4.26.5.6.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the bold text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.6.4 Method of test

27.22.4.26.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

27.22.4.26.5.6.4.2 Procedure

# Expected Sequence 5.6 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
2	$ME \rightarrow UICC$	5.6.1 FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
	OIOO IVIL	LAUNCH BROWSER 5.6.1	if not already launched", no null alpha id]
4	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with bold on]
5	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
7	ME→USS	BROWSER 5.6.1 The ME attempts to launch the	
'	WL →000	session with the default Wap	
		parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED '6' II I I I I I	
9	$USER \to ME$	The user verifies that the default Wap session is properly	
		lestablished.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER 5.6.2	
11	$ME \rightarrow UICC$	FETCH	
12		PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
	0100 / III.	LAUNCH BROWSER 5.6.2	if not already launched", no null alpha id]
13	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with bold off]
14	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
15	ME . LUCC	launch browser.	[Command performed augeografully]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1	[Command performed successfully]
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
18	$USER \to ME$	The user verifies that the default	
	OOLIN IVIL	Wap session is properly	
		established.	
		Then he/she ends the navigation.	
10	LUCO ME	The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER	
		5.6.1	
20	$ME \to UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
	ME	LAUNCH BROWSER 5.6.1	if not already launched", no null alpha id
22 23	ME → USER	ME displays the alpha identifier The user may have to confirm the	[alpha identifier is displayed with bold on] [option: user confirmation]
23	$USER \to ME$	launch browser.	[option: user committation]
24	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
	/ 0.00	BROWSER 5.6.1	, , , , , , , , , , , , , , , , , , , ,
25	ME□USS	The ME attempts to launch the	
		session with the default Wap	
26	$UICC \to ME$	parameters and the default URL. PROACTIVE UICC SESSION	
20		ENDED	
ı 1			ı

	27	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
	28	$UICC \to ME$	The ME returns in idle mode. PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.3	
	29	$ME \rightarrow UICC$	FETCH	
	30	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 5.6.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
	31	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with bold off]
	32	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
	33	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1	[Command performed successfully]
	34	$ME \to USS$	The ME attempts to launch the session with the default Wap parameters and the default URL.	
	35	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
	36	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
L			The ME returns in idle mode.	

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.6.1

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	10	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.6.2

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC Destination device: ME

URL empty Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
_	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.6.3

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 3"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
·	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00

# 27.22.4.26.5.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.6.

27.22.4.26.5.7 LAUNCH BROWSER (support of Text Attribute – Italic On)

27.22.4.26.5.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.7.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

## 27.22.4.26.5.7.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the italic text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.7.4 Method of test

27.22.4.26.5.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

# 27.22.4.26.5.7.4.2 Procedure

# Expected Sequence 5.7 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER	
		5.7.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.7.1	if not already launched", no null alpha id]
4 5		ME displays the alpha identifier The user may have to confirm the	[alpha identifier is displayed with italic on] [option: user confirmation]
5	$USER \to ME$	launch browser.	[option: user commutation]
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
7	ME HOO	BROWSER 5.7.1	
7	$ME \rightarrow USS$	The ME attempts to launch the session with the default Wap	
		parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		Wap session is properly established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER 5.7.2	
11	$ME \rightarrow UICC$	FETCH	
12		PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.7.2	if not already launched", no null alpha id]
13		ME displays the alpha identifier	[alpha identifier is displayed with italic off]
14	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
15	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.7.1	
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
18	$USER \to ME$	The user verifies that the default	
		Wap session is properly established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
20	$ME \to UICC$	5.7.1  FETCH	
21	$UICC \rightarrow ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.7.1	if not already launched", no null alpha id]
22	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with italic on]
23	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
24	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
	, 0.00	BROWSER 5.7.1	
25	ME□USS	The ME attempts to launch the	
		session with the default Wap	
26	$UICC \to ME$	parameters and the default URL. PROACTIVE UICC SESSION	
		ENDED	
. '		•	•

27	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.3	
29	$ME \to UICC$	FETCH	
30	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 5.7.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with italic off]
32	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
33	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1	[Command performed successfully]
34	$ME \to USS$	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
36	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.7.1

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	20	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.7.2

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC Destination device: ME

URL empty Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.7.3

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 3"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00

# 27.22.4.26.5.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.7.

27.22.4.26.5.8 LAUNCH BROWSER (support of Text Attribute – Underline On)

27.22.4.26.5.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.8.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.8.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the underline text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.8.4 Method of test

27.22.4.26.5.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

# 27.22.4.26.5.8.4.2 Procedure

# Expected Sequence 5.8 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER 5.8.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.8.1	if not already launched", no null alpha id]
4		ME displays the alpha identifier	[alpha identifier is displayed with underline on]
5	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.8.1	
7	$ME \rightarrow USS$	The ME attempts to launch the	
		session with the default Wap parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
	J. J. J. J. J. J. J. J. J. J. J. J. J. J	ENDED	
9	$USER \to ME$	The user verifies that the default	
		Wap session is properly established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
11	$ME \to UICC$	5.8.2 FETCH	
12		PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.8.2	if not already launched", no null alpha id]
13		ME displays the alpha identifier	[alpha identifier is displayed with underline off]
14	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.8.1	[[
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION	
	OIOO / IVIE	ENDED	
18	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established. Then he/she ends the navigation.	
		The ME returns in idle mode.	
19	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
20	$ME \to UICC$	5.8.1 FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.8.1	if not already launched", no null alpha id]
22	$ME \rightarrow USER$	ME displays the alpha identifier	[alpha identifier is displayed with underline on]
23	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
24	$ME \to UICC$	launch browser. TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
-	.vi.L / 0100	BROWSER 5.8.1	L =
25	ME□USS	The ME attempts to launch the	
		session with the default Wap	
26	$UICC \to ME$	parameters and the default URL. PROACTIVE UICC SESSION	
		ENDED	
. '		•	· '

27	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.3	
29	$ME \rightarrow UICC$	FETCH	
30		PROACTIVE COMMAND: LAUNCH BROWSER 5.8.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with underline off]
32	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
33	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1	[Command performed successfully]
34	$ME \to USS$	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
36	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.8.1

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	40	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.8.2

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC Destination device: ME

URL empty Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.8.3

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 3"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
·	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

# TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 15 00 82 02 82 81 83	01	00
--	----	----

# 27.22.4.26.5.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.8.

27.22.4.26.5.9 LAUNCH BROWSER (support of Text Attribute – Strikethrough On)

27.22.4.26.5.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.9.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.9.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the strikethrough text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.9.4 Method of test

27.22.4.26.5.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

# 27.22.4.26.5.9.4.2 Procedure

# Expected Sequence 5.9 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
		5.9.1	
2		FETCH	f ( ) ( ) ( ) ( ) ( ) ( ) ( ) ( ) ( ) (
3	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1	[connect to the default URL, "launch browser,
4	$ME \rightarrow USER$	ME displays the alpha identifier	if not already launched", no null alpha id] [alpha identifier is displayed with strikethrough
	WIE → USEK	lvic displays the alpha identifier	on]
5	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.9.1	
7	$ME{ o}USS$	The ME attempts to launch the	
		session with the default Wap	
8	$UICC \to ME$	parameters and the default URL. PROACTIVE UICC SESSION	
	OICC → IVIE	ENDED	
9	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established.	
		Then he/she ends the navigation.	
10	LIIOO ME	The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER	
		5.9.2	
11	$ME \rightarrow UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.9.2	if not already launched", no null alpha id]
13	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with strikethrough
1 4	LICED ME		off]
14	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
15	$ME \rightarrow UICC$		[Command performed successfully]
		BROWSER 5.9.1	, , , , , , , , , , , , , , , , , , , ,
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap	
47	LIIOO ME	parameters and the default URL. PROACTIVE UICC SESSION	
17	$UICC \to ME$	ENDED	
18	$USER \to ME$	The user verifies that the default	
	OOLIT 7 IIIL	Wap session is properly	
		established.	
		Then he/she ends the navigation.	
10	LIIOO ME	The ME returns in idle mode. PROACTIVE COMMAND	
19	$UICC \to ME$	PENDING: LAUNCH BROWSER	
		5.9.1	
20	$ME \rightarrow UICC$	FETCH	
21	$UICC \to ME$		[connect to the default URL, "launch browser,
			if not already launched", no null alpha id]
22	$ME \rightarrow USER$	ME displays the alpha identifier	[alpha identifier is displayed with strikethrough
22	LICED . ME	The user may have to confirm the	on] [option: user confirmation]
23	$USER \to ME$	The user may have to confirm the launch browser.	ilobiion. asei communationi
24	$ME \rightarrow UICC$		[Command performed successfully]
	, 0.00	BROWSER 5.9.1	L
25	ME□USS	The ME attempts to launch the	
		session with the default Wap	
00		parameters and the default URL.	
26	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
ı l		ILINDED	l l

27	$USER \to ME$	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
28	$UICC \to ME$	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.3	
29	$ME \rightarrow UICC$	FETCH	
30	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 5.9.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	$ME \rightarrow USER$	ME displays the alpha identifier	[alpha identifier is displayed with strikethrough off]
32	$USER \to ME$	The user may have to confirm the launch browser.	[option: user confirmation]
33	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1	[Command performed successfully]
34	$ME \rightarrow USS$	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
36	$USER \to ME$	The user verifies that the default Wap session is properly established.	
		Then he/she ends the navigation. The ME returns in idle mode.	

# PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1

## Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

# Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
_	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	80	B4		

# PROACTIVE COMMAND: LAUNCH BROWSER 5.9.2

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC

Destination device: ME URL empty Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

# PROACTIVE COMMAND: LAUNCH BROWSER 5.9.3

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 3"

## Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

### TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1

# Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

# Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
	0.	00	0.		00	02	02	02	0.	00	0.	00

# 27.22.4.26.5.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.9.

27.22.4.26.5.10 LAUNCH BROWSER (support of Text Attribute – Foreground and Background Colour)

27.22.4.26.5.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.10.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

27.22.4.26.5.10.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the foreground and background colour text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.10.4 Method of test

27.22.4.26.5.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

The ME is in idle mode.

# 27.22.4.26.5.10.4.2 Procedure

# Expected Sequence 5.10 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
		5.10.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.10.1	if not already launched", no null alpha id]
4	$ME \rightarrow USER$	ME displays the alpha identifier	[alpha identifier is displayed with foreground
			and background colour according to the text
			attribute configuration]
5	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.10.1	, , , , , , , , , , , , , , , , , , , ,
7	ME→USS	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
9	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	
10	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: LAUNCH BROWSER	
		5.10.2	
11	$ME \to UICC$	FETCH	
12	$UICC \to ME$	PROACTIVE COMMAND:	[connect to the default URL, "launch browser,
		LAUNCH BROWSER 5.10.2	if not already launched", no null alpha id]
13	$ME \to USER$	ME displays the alpha identifier	[alpha identifier is displayed with ME"s default
			foreground and background colour]
14	$USER \to ME$	The user may have to confirm the	[option: user confirmation]
		launch browser.	
15	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH	[Command performed successfully]
		BROWSER 5.10.1	
16	$ME \to USS$	The ME attempts to launch the	
		session with the default Wap	
		parameters and the default URL.	
17	$UICC \to ME$	PROACTIVE UICC SESSION	
		ENDED	
18	$USER \to ME$	The user verifies that the default	
		Wap session is properly	
		established.	
		Then he/she ends the navigation.	
		The ME returns in idle mode.	

# PROACTIVE COMMAND: LAUNCH BROWSER 5.10.1

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

 $\begin{array}{ccc} Source \ device: & UICC \\ Destination \ device: & ME \\ URL & empty \\ Alpha \ Identifier & "Default \ URL \ 1" \end{array}$ 

Text Attribute

Formatting position: 0 Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	00	B4		

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.10.2

Logically:

Command details

Command number:

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
·	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

## TERMINAL RESPONSE: LAUNCH BROWSER 5.10.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00

## 27.22.4.26.5.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.10.

# 27.22.4.26.6 LAUNCH BROWSER (UCS2 Display in Chinese)

27.22.4.26.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.6.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.26.6.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.6.4 Method of test

27.22.4.26.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The mobile is busy in a Wap session, the user navigates in pages different from the URL defined by default in Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

## 27.22.4.26.6.4.2 Procedure

# Expected Sequence 6.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Chinese)

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a Wap	[Browser is in use, the current session is not
1	$UICC \to ME$	session (not default URL). PROACTIVE COMMAND PENDING: LAUNCH BROWSER 6.1.1	secured]]
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 6.1.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]
4	$ME \to USER$	ME displays the alpha identifier "你好"	["Hello" in Chinese]
5	$USER \to ME$	The user confirms the launch browser.	[user confirmation]
6	$ME \to UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 6.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

# PROACTIVE COMMAND: LAUNCH BROWSER 6.1.1

## Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER command qualifier: use the existing browser

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier

Data coding scheme: UCS2 (16 bits)

Text: "你好"

# Coding:

BER-TLV:	D0	12	81	03	01	15	02	82	02	81	82	31
	00	05	05	80	4F	60	59	7D				

# TERMINAL RESPONSE: LAUNCH BROWSER 6.1.1

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00
DLIX-ILV.	01	03	01	10	02	02	02	02	01	ಂ	01	00

### 27.22.4.26.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

# 27.22.4.26.7 LAUNCH BROWSER (UCS2 Display in Katakana)

27.22.4.26.7.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.26.7.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.26.7.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.7.4 Method of test

#### 27.22.4.26.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The mobile is busy in a Wap session, the user navigates in pages different from the URL defined by default in Wap parameters.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

## 27.22.4.26.7.4.2 Procedure

# Expected Sequence 7.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Katakana)

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a Wap	[Browser is in use, the current session is not
1	$UICC \to ME$	session (not default URL). PROACTIVE COMMAND PENDING: LAUNCH BROWSER 7.1.1	secured]]
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: LAUNCH BROWSER 7.1.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]
4	$ME \rightarrow USER$	ME displays the alpha identifier "ル"	[Character in Katakana]
5	$USER \to ME$	The user confirms the launch browser.	[user confirmation]
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: LAUNCH BROWSER 7.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

#### PROACTIVE COMMAND: LAUNCH BROWSER 7.1.1

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: UICC
Destination device: ME
URL empty

Alpha Identifier

Data coding scheme: UCS2 (16 bits)

Text: "ル"

# Coding:

BER-TLV:	D0	10	81	03	01	15	02	82	02	81	82	31
	00	05	03	80	30	EB						

# TERMINAL RESPONSE: LAUNCH BROWSER 7.1.1

# Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER
Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00

# 27.22.4.26.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

## 27.22.4.27 OPEN CHANNEL

27.22.4.27.1 Void

27.22.4.27.2 Open Channel (related to GPRS)

27.22.4.27.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.27.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111[15] clause 5.2, clauses 6.4.27 and 6.6.27, clause 8.6, clause 8.7, clause 9.2, clause 8.2, clause 8.15, clause 8.31 and clause 8.70...

## 27.22.4.27.2.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (OK); or
- TERMINAL RESPONSE (Command performed with modification); or
- TERMINAL RESPONSE (User did not accept the proactive command);
- TERMINAL RESPONSE (ME currently unable to process command);

to the UICC after the ME receives the OPEN CHANNEL proactive command. The TERMINAL RESPONSE sent back to the UICC is the result of the ME and the network capabilities against requested parameters by the UICC.

## 27.22.4.27.2.4 Method of test

#### 27.22.4.27.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP ContextDch, as specified in TS 34.123-3 [27], clause 8.10 for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Prior to test case execution the apparatus supplier shall have provided the "Preferred buffer size supported by the terminal for Open Channel command" as requested in table A.2/29.

Pre-condition for successful execution of expected sequence 2.1:

If the terminal does not support the execution of an Open Channel (GPRS) command when no Network Access Name TLV is present in the proactive command and when no default Access Point Name is set in the terminal configuration (s.a. table A.1/48), then "TestGp.rs" shall be set and activated as default Access Point Name in the terminal configuration prior to execution of the proactive command in expected sequence 2.1.

#### 27.22.4.27.2.4.2 Procedure

# Expected Sequence 2.1 (OPEN CHANNEL, immediate link establishment, GPRS, no local address, no alpha identifier, no network access name)

Step	Direction	MESSAGE / Action	Comments
1	$USER \to ME$		[see initial conditions]
		terminal configuration if required	
2	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		OPEN CHANNEL 2.1.1	
3	$ME \rightarrow UICC$	FETCH	
4	$UICC \to ME$	PROACTIVE COMMAND : OPEN	
		CHANNEL 2.1.1	
5	$ME \rightarrow user$	The ME may display channel opening	
		information	
6	$ME \rightarrow USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN	[Command performed successfully]
		CHANNEL 2.1.1A	
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 2.1.1B	

#### PROACTIVE COMMAND: OPEN CHANNEL 2.1.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC

Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400
Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

#### Coding:

BER-TLV:	D0	36	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	05	78
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

### TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

#### Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

# Expected Sequence 2.2 (OPEN CHANNEL, immediate link establishment GPRS, no alpha identifier, with network access name)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 2.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 2.2.1	
4	$ME \rightarrow user$	The ME may display channel opening information	
5	$ME \rightarrow USS$	PDP context activation request	
6	$USS \to ME$	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 2.2.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 2.2.1B	

#### PROACTIVE COMMAND: OPEN CHANNEL 2.2.1

# Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03 Delay Class: 04 Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	05	78
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

## TERMINAL RESPONSE: OPEN CHANNEL 2.2.1A

#### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer Description:

Bearer Type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size 1400

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 2.2.1B

Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Bearer Description:

Bearer Type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

# Expected Sequence 2.3 (OPEN CHANNEL, immediate link establishment, GPRS, with alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 2.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 2.3.1	
4	$ME \rightarrow user$	Confirmation phase with alpha ID	'Open ID'
5	user $\rightarrow$ ME	The user confirms	
6	$ME \rightarrow USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A	[Command performed successfully]
		or TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B	

## PROACTIVE COMMAND: OPEN CHANNEL 2.3.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC
Destination device: ME
Alpha Identifier Open ID

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31

Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4B	81	03	01	40	01	82	02	81	82	05
	07	4F	70	65	6E	20	49	44	35	07	02	03
	04	03	04	1F	02	39	02	05	78	47	0A	06
	54	65	73	74	47	70	02	72	73	0D	08	F4
	55	73	65	72	4C	6F	67	0D	08	F4	55	73
	65	72	50	77	64	3C	03	01	AD	9C	3E	05
	21	01	01	01	01							

# Expected Sequence 2.4 (OPEN CHANNEL, immediate link establishment, GPRS, with null alpha identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL	
		2.4.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 2.4.1	
4	$ME \rightarrow user$	Confirmation phase	[The ME should not give any information]
5	$user \to ME$	The user confirms	[Only if the ME asks for user confirmation]
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \to UICC$	TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A	[Command performed successfully]
		Or	
		TERMINAL RESPONSE:	
		OPEN CHANNEL 2.1.1B	

PROACTIVE COMMAND: OPEN CHANNEL 2.4.1

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Alpha Identifier Null

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31

Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Other Address

Length: 00
Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level Transport format: UDP

Port number: 44444
Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	46	81	03	01	40	01	82	02	81	82	05
	00	35	07	02	03	04	03	04	1F	02	39	02
	05	78	47	0A	06	54	65	73	74	47	70	02
	72	73	3E	00	0D	08	F4	55	73	65	72	4C
	6F	67	0D	08	F4	55	73	65	72	50	77	64
	3C	03	01	AD	9C	3E	05	21	01	01	01	01

# Expected Sequence 2.5 (OPEN CHANNEL, immediate link establishment, GPRS, command performed with modifications (buffer size) )

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL	
		2.5.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 2.5.1	
4	$ME \rightarrow user$	The ME may display channel	
		opening information	
5	$ME \to USS$	PDP context activation request	
6	$USS \to ME$	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed with modification]
		CHANNEL 2.5.1A	
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 2.5.1B	

PROACTIVE COMMAND: OPEN CHANNEL 2.5.1

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 65535 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	FF	FF
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

677

TERMINAL RESPONSE: OPEN CHANNEL 2.5.1A

Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed with modifications (07)

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: The buffer size TLV shall be attached and contain the value stated in table A.2/29

"Preferred buffer size supported by the terminal for Open Channel command".

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	07
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	Note 1										

Note1: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size

supported by the terminal for Open Channel command".

TERMINAL RESPONSE: OPEN CHANNEL 2.5.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed with modifications (07)

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: The buffer size TLV shall be attached and contain the value stated in table A.2/29

"Preferred buffer size supported by the terminal for Open Channel command".

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	07
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	Note 1										

Note1: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

# **Expected Sequence 2.6 Void**

# Expected Sequence 2.7A (OPEN CHANNEL, immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL	
		2.7.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 2.7.1	
4	$ME \rightarrow user$	Confirmation phase with alpha	[The ME shall display 'Open ID']
		ID	
5	user $\rightarrow$ ME	The user rejects	
6	$ME \to USS$	No PDP context activation	
		request is sent to the USS	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[User did not accept the proactive command]
		CHANNEL 2.7.1A	
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 2.7.1B	

# Expected Sequence 2.7B (OPEN CHANNEL, immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$		
		PENDING: OPEN CHANNEL	
		2.7.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 2.7.1	
4	$ME \rightarrow USS$	PDP context activation request	
5	$USS \to ME$	PDP context activation accept	
6	$ME \rightarrow user$	Confirmation phase with alpha	[The ME shall display 'Open ID']
		ID	
7	user $\rightarrow$ ME	The user rejects	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[User did not accept the proactive command]
		CHANNEL 2.7.1A	
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 2.7.1B	

## PROACTIVE COMMAND: OPEN CHANNEL 2.7.1

## Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP Port number: 44444

Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	4B	81	03	01	40	01	82	02	81	82	05
	07	4F	70	65	6E	20	49	44	35	07	02	03
	04	03	04	1F	02	39	02	05	78	47	0A	06
	54	65	73	74	47	70	02	72	73	0D	08	F4
	55	73	65	72	4C	6F	67	0D	08	F4	55	73
	65	72	50	77	64	3C	03	01	AD	9C	3E	05
	21	01	01	01	01							

#### TERMINAL RESPONSE: OPEN CHANNEL 2.7.1A

#### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: User did not accept the proactive command

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: Because the value depends in this case on the terminal's implementation, it shall be

ignored.

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	22
	35	07	02	03	04	03	04	1F	02	Note 1		

Note1: The buffer size TLV shall be present and because the value depends in this case on the terminal's

implementation, the value shall be ignored.

TERMINAL RESPONSE: OPEN CHANNEL 2.7.1B

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: User did not accept the proactive command

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: Because the value depends in this case on the terminal's implementation, it shall be

ignored.

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	22
	35	07	02	00	04	03	04	1F	02	Note 1		

Note1: The buffer size TLV shall be present and because the value depends in this case on the terminal's implementation, the value shall be ignored.

#### **Expected Sequence 2.8 Void**

27.22.4.27.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.8.

27.22.4.27.3 Open Channel (default bearer)

**TBD** 

27.22.4.27.4 Open Channel (Local Bearer)

**TBD** 

27.22.4.27.5 Open Channel (GPRS, support of Text Attribute)

27.22.4.27.5.1 Open Channel (GPRS, support of Text Attribute – Left Alignment)

27.22.4.27.5.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.1.3 Test purpose

To verify that the ME displays an alpha identifier according to the left alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.1.4 Method of test

27.22.4.27.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

**Bearer Parameters** 

Precedence Class: 03 Delay Class: 04 Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

# 27.22.4.27.5.1.4.2 Procedure

# Expected Sequence 5.1 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
		CHANNEL 5.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
		5.1.1	
4		Confirmation phase with alpha ID	[alpha identifier is displayed with left alignment]
5		The user confirms	
6		PDP context activation request	
7		PDP context activation accept	
8	$ME \rightarrow UICC$		[Command performed successfully]
		5.1.1A	
		OF	
		TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B	
9	LUCC ME	PROACTIVE COMMAND PENDING: CLOSE	
9	OICC → IVIE	CHANNEL 5.1.1	
10	$ME \rightarrow UICC$		
11		PROACTIVE COMMAND: CLOSE CHANNEL	
	0.00 /2	5.1.1	
12	$ME \rightarrow USS$	PDP context deactivation request	
13		PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
15	$UICC \to ME$		
		CHANNEL 5.1.2	
16	ME → UICC		
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
18	ME LIGED	5.1.2   Confirmation phase with alpha ID	[Message shall be formatted without left alignment.
10	IVIE -> USER	Commination phase with alpha 15	Remark: If left alignment is the ME"s default
			alignment as declared in table A.2/19, no alignment
			change will take place]
19	$USER \to ME$	The user confirms	
20	$ME \rightarrow USS$	PDP context activation request	
21	$USS \to ME$	PDP context activation accept	
22	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.1.1A	
		or	
		TERMINAL RESPONSE: OPEN CHANNEL	
22		5.1.1B	
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	$UICC \rightarrow ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
	OIOO → IVIL	5.1.1	
26	$ME \rightarrow USS$	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	

# PROACTIVE COMMAND: OPEN CHANNEL 5.1.1

Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level
Transport format: UDP
Port number: 44444

Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.1.2

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	80	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1

## Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel

Alpha Identifier "Close ID"

Coding:

BER-TLV:	D0	14	81	03	01	41	00	82	02	81	21
	85	08	43	6C	6F	73	65	20	49	44	

## TERMINAL RESPONSE: OPEN CHANNEL 5.1.1A

# Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B

Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: CLOSE CHANNEL 5.1.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.27.5.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.1.

27.22.4.27.5.2 Open Channel (GPRS, support of Text Attribute – Center Alignment)

27.22.4.27.5.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.27.5.2.3 Test purpose

To verify that the ME displays an alpha identifier according to the center alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.2.4 Method of test

27.22.4.27.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## 27.22.4.27.5.2.4.2 Procedure

# Expected Sequence 5.2 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
		CHANNEL 5.2.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.2.1	
4	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with center alignment]
5	$USER \to ME$	The user confirms	
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.2.1A	[Command performed successfully]
		OF	
		TERMINAL RESPONSE : OPEN CHANNEL 5.2.1B	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	$ME \rightarrow UICC$	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
12	$ME \rightarrow USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
4-		5.1.1	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
16	$ME \rightarrow UICC$	CHANNEL 5.2.2 FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL	
	OIGG / IVIL	5.2.2	
18	ME → USER	Confirmation phase with alpha ID	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/19, no alignment change will take place]
19	$USER \to ME$	The user confirms	
20	$ME \rightarrow USS$	PDP context activation request	
21	$USS \to ME$	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.2.1A or	[Command performed successfully]
		TERMINAL RESPONSE : OPEN CHANNEL 5.2.1B	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	$ME \rightarrow UICC$	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	$ME \to USS$	PDP context deactivation request	
27	$USS \to ME$	PDP context deactivation accept	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

# PROACTIVE COMMAND: OPEN CHANNEL 5.2.1

Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	01
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.2.2

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

TERMINAL RESPONSE: OPEN CHANNEL 5.2.1A

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.2.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

### Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

## 27.22.4.27.5.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.2.

27.22.4.27.5.3 Open Channel (GPRS, support of Text Attribute – Right Alignment)

27.22.4.27.5.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.27.5.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

# 27.22.4.27.5.3.3 Test purpose

To verify that the ME displays an alpha identifier according to the right alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.3.4 Method of test

27.22.4.27.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

**Bearer Parameters** 

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## 27.22.4.27.5.3.4.2 Procedure

# Expected Sequence 5.3 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
		CHANNEL 5.3.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.3.1	
4	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with right alignment]
5	$USER \to ME$	The user confirms	
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.3.1A	[Command performed successfully]
		OF	
		TERMINAL RESPONSE : OPEN CHANNEL 5.3.1B	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	$ME \rightarrow UICC$	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
12	$ME \to USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
4.5		5.1.1	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.3.2	
16	$ME \rightarrow UICC$	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL	
	0.00 /	5.3.2	
18	ME → USER	Confirmation phase with alpha ID	[Message shall be formatted without right alignment. Remark: If right alignment is the ME's default alignment as declared in table A.2/19, no alignment change will take place]
19	$USER \to ME$	The user confirms	
20	$ME \rightarrow USS$	PDP context activation request	
21	$USS \to ME$	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.3.1A	[Command performed successfully]
		or TERMINAL RESPONSE : OPEN CHANNEL 5.3.1B	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	$ME \rightarrow UICC$	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	$ME \to USS$	PDP context deactivation request	
27	$USS \to ME$	PDP context deactivation accept	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

PROACTIVE COMMAND: OPEN CHANNEL 5.3.1

Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	02
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.3.2

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level Transport format: UDP

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

TERMINAL RESPONSE: OPEN CHANNEL 5.3.1A

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.3.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

### Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

## 27.22.4.27.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.3.

27.22.4.27.5.4 Open Channel (GPRS, support of Text Attribute – Large Font Size)

27.22.4.27.5.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.27.5.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

# 27.22.4.27.5.4.3 Test purpose

To verify that the ME displays an alpha identifier according to the large font size text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.4.4 Method of test

27.22.4.27.5.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

**Bearer Parameters** 

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## 27.22.4.27.5.4.4.2 Procedure

# Expected Sequence 5.4 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
2	ME	CHANNEL 5.4.1	
2 3	$ME \rightarrow UICC$ $UICC \rightarrow ME$	FETCH PROACTIVE COMMAND : OPEN CHANNEL	
3	OICC → IVIE	5.4.1	
4	$ME \to USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with large font size]
5	$USER \to ME$	The user confirms	
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
		5.4.1B	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
10	$ME \rightarrow UICC$	CHANNEL 5.1.1 FETCH	
11	$UICC \rightarrow ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
12	$ME \to USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
	OIGG / IVIL	CHANNEL 5.4.2	
16	$ME \to UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
18	ME LICED	5.4.2 Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
19	$ME \rightarrow USER$ $USER \rightarrow ME$	The user confirms	[alpha luertiller is displayed with horitial fort size]
20	$ME \rightarrow USS$	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.4.1A	
		or TERMINAL RESPONSE : OPEN CHANNEL	
		15.4.1B	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
		CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	$ME \to USS$	PDP context deactivation request	
27	$USS \to ME$	PDP context deactivation accept	
28	$ME \to UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
20	LUCC ME	5.1.1	
29	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.4.1	
30	$ME \rightarrow UICC$	FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL	
60		5.4.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with large font size]
33 34	$\begin{array}{c} USER \to ME \\ ME \to USS \end{array}$	The user confirms PDP context activation request	
35	$USS \rightarrow ME$	PDP context activation accept	
36	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.4.1A	
		or	
		TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B	
l l	l	JO.T. 1D	ļ .

37	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	$ME \rightarrow UICC$	FETCH	
39	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL	
00	OICC - IVIL	5.1.1	
40	$ME \to USS$	PDP context deactivation request	
41	USS → ME	PDP context deactivation accept	
42	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
	WE 7 0100	5.1.1	[[online perioning succession]]
43	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 5.4.3	
44	$ME \to UICC$	FETCH	
45	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
		5.4.3	
46	$ME \to USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
47	$USER \to ME$	The user confirms	
48	$ME \to USS$	PDP context activation request	
49	$USS \to ME$	PDP context activation accept	
50	$ME \to UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.4.1A	
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
		5.4.1B	
51	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
50		CHANNEL 5.1.1	
52	$ME \rightarrow UICC$	FETCH	
53	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
E /	ME LICC	5.1.1	
54 55	$ME \rightarrow USS$	PDP context deactivation request	
55 56	USS → ME	PDP context deactivation accept	[Command performed everentially]
56	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	

## PROACTIVE COMMAND: OPEN CHANNEL 5.4.1

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	04
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.4.2

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05	l
	09	4F	70	65	6E	20	49	44	20	32	35	07	l
	02	03	04	03	04	1F	02	39	02	05	78	47	l
	0A	06	54	65	73	74	47	70	02	72	73	0D	l
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4	l
	55	73	65	72	50	77	64	3C	03	01	AD	9C	l
	3E	05	21	01	01	01	01	D0	04	00	09	00	l
	B4												l

## PROACTIVE COMMAND: OPEN CHANNEL 5.4.3

### Logically:

Command details

Command number:

Command type: **OPEN CHANNEL** 

Command qualifier: immediate link establishment

Device identities

Source device: **UICC** Destination device: ME

Alpha Identifier "Open ID 3"

Bearer

**GPRS** Bearer type:

Bearer parameter:

Precedence Class: 03 Delay Class: 04 Reliability Class: 03 Peak throughput class: 04 Mean throughput class: 31 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

UserLog (User login) Text String: UserPwd (User password) Text String:

UICC/ME interface transport level

Transport format: **UDP** Port number: 44444 Data destination address 01.01.01.01

# Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	80	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.4.1A

## Logically:

Command details

Command number:

**OPEN CHANNEL** Command type:

Command qualifier: immediate link establishment

Device identities

Source device: ME Destination device: **UICC**  Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.4.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

## 27.22.4.27.5.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.4.

27.22.4.27.5.5 Open Channel (GPRS, support of Text Attribute – Small Font Size)

27.22.4.27.5.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

### 27.22.4.27.5.5.3 Test purpose

To verify that the ME displays an alpha identifier according to the small font size text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.5.4 Method of test

27.22.4.27.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## 27.22.4.27.5.5.4.2 Procedure

# Expected Sequence 5.5 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
	NAT LUGG	CHANNEL 5.5.1	
2 3	ME → UICC	FETCH PROACTIVE COMMAND : OPEN CHANNEL	
3	$UICC \to ME$	5.5.1	
4	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with small font size]
5	$USER \to ME$	The user confirms	
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A	[Command performed successfully]
		or TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	$ME \to UICC$	FETCH	
11	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	$ME \to USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \to UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.5.2	
16	$ME \to UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.5.2	
18	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
19	USER $\rightarrow$ ME	The user confirms	
20	$ME \to USS$	PDP context activation request	
21	$USS \to ME$	PDP context activation accept	
22	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A	[Command performed successfully]
		or TERMINAL RESPONSE : OPEN CHANNEL	
		5.5.1B	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
		CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	$ME \to USS$	PDP context deactivation request	
27	$USS \to ME$	PDP context deactivation accept	
28	$ME \to UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
29	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.5.1	
30	$ME \rightarrow UICC$	FETCH	
31	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
32	$ME \to USER$	5.5.1 Confirmation phase with alpha ID	[alpha identifier is displayed with small font size]
33	$USER \to ME$	The user confirms	-
34	$\text{ME} \to \text{USS}$	PDP context activation request	
35	USS → ME	PDP context activation accept	[Common dispersion   C.   C.   C.   C.   C.   C.   C.   C
36	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
		5.5.1B	

37	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
00		CHANNEL 5.1.1	
38	$ME \rightarrow UICC$	FETCH	
39	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
40		5.1.1	
40	$ME \rightarrow USS$	PDP context deactivation request	
41	$USS \to ME$	PDP context deactivation accept	
42	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
43	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 5.5.3	
44	$ME \rightarrow UICC$	FETCH	
45	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
		5.5.3	
46	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
47	$USER \to ME$	The user confirms	
48	$ME \to USS$	PDP context activation request	
49	$USS \to ME$	PDP context activation accept	
50	$ME \to UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.5.1A	
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
		5.5.1B	
51	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
		CHANNEL 5.1.1	
52	$ME \to UICC$	FETCH	
53	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
54	$ME \to USS$	PDP context deactivation request	
55	$USS \to ME$	PDP context deactivation accept	
46	$ME \to UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	

## PROACTIVE COMMAND: OPEN CHANNEL 5.5.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level Transport format: UDP

Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	80
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.5.2

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05	i
	09	4F	70	65	6E	20	49	44	20	32	35	07	ı
	02	03	04	03	04	1F	02	39	02	05	78	47	ı
	0A	06	54	65	73	74	47	70	02	72	73	0D	ı
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4	ı
	55	73	65	72	50	77	64	3C	03	01	AD	9C	ı
	3E	05	21	01	01	01	01	D0	04	00	09	00	i
	B4												ì

## PROACTIVE COMMAND: OPEN CHANNEL 5.5.3

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 3"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	80	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.5.1A

## Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.5.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

27.22.4.27.5.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.5.

27.22.4.27.5.6 Open Channel (GPRS, support of Text Attribute – Bold On)

27.22.4.27.5.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.6.3 Test purpose

To verify that the ME displays an alpha identifier according to the bold text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.6.4 Method of test

27.22.4.27.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.6.4.2 Procedure

# Expected Sequence 5.6 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
		CHANNEL 5.6.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
	ME HOED	5.6.1	Felicle a delegation in all contents of wide to all the 1
4		Confirmation phase with alpha ID	[alpha identifier is displayed with bold on]
5		The user confirms	
6		PDP context activation request	
7		PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.6.1A	
		or TERMINAL RESPONSE : OPEN CHANNEL	
		5.6.1B	
9	LIICC → ME	PROACTIVE COMMAND PENDING: CLOSE	
	OIOO / IVIL	CHANNEL 5.1.1	
10	$ME \rightarrow UICC$		
11		PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
12	$ME \to USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 5.6.2	
16	$ME \rightarrow UICC$		
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
4.0		5.6.2	
18		Confirmation phase with alpha ID	[alpha identifier is displayed with bold off]
19		The user confirms	
20		PDP context activation request	
21		PDP context activation accept	
22	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.6.1A	
		or TERMINAL RESPONSE : OPEN CHANNEL	
		5.6.1B	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
	OIOO / IVIL	CHANNEL 5.1.1	
24	$ME \rightarrow UICC$		
25		PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
26	$ME \to USS$	PDP context deactivation request	
27			
28	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
29	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
00	NAE :::00	CHANNEL 5.6.1	
30		FETCH	
31	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
32	ME LIGED	5.6.1 Confirmation phase with alpha ID	[alpha identifier is displayed with bold on]
33		The user confirms	Taipha identifier is displayed with bold only
34		PDP context activation request	
35		PDP context activation accept	
36		TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
30	I IVIL → UICC	5.6.1A	[Communa performed successfully]
		or	
1		TERMINAL RESPONSE : OPEN CHANNEL	
		5.6.1B	
			·

37	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	$ME \rightarrow UICC$		
39		PROACTIVE COMMAND: CLOSE CHANNEL	
	0.00 /	5.1.1	
40	$ME \rightarrow USS$	PDP context deactivation request	
41	$USS \to ME$	PDP context deactivation accept	
42	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
43	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 5.6.3	
44	$ME \rightarrow UICC$		
45	$UICC \rightarrow ME$	PROACTIVE COMMAND : OPEN CHANNEL	
40		5.6.3	
46		Confirmation phase with alpha ID	[alpha identifier is displayed with bold off]
47		The user confirms	
48		PDP context activation request	
49		PDP context activation accept	
50	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.6.1A	
		or TERMINAL RESPONSE : OPEN CHANNEL	
		5.6.1B	
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE	
	OIOO / WIL	CHANNEL 5.1.1	
52	$ME \rightarrow UICC$		
53	UICC → ME		
		5.1.1	
54	$ME \rightarrow USS$	PDP context deactivation request	
55	$USS \to ME$	PDP context deactivation accept	
56	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	

## PROACTIVE COMMAND: OPEN CHANNEL 5.6.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	10
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.6.2

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05	i
	09	4F	70	65	6E	20	49	44	20	32	35	07	i
	02	03	04	03	04	1F	02	39	02	05	78	47	i
	0A	06	54	65	73	74	47	70	02	72	73	0D	i
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4	i
	55	73	65	72	50	77	64	3C	03	01	AD	9C	i
	3E	05	21	01	01	01	01	D0	04	00	09	00	i
	B4												ì

## PROACTIVE COMMAND: OPEN CHANNEL 5.6.3

### Logically:

Command details

Command number:

Command type: **OPEN CHANNEL** 

Command qualifier: immediate link establishment

Device identities

Source device: **UICC** Destination device: ME

Alpha Identifier "Open ID 3"

Bearer

**GPRS** Bearer type:

Bearer parameter:

Precedence Class: 03 Delay Class: 04 Reliability Class: 03 Peak throughput class: 04 Mean throughput class: 31 02 (IP)

Packet data protocol:

Buffer

Buffer size: 1400 Network access name: TestGp.rs

UserLog (User login) Text String: UserPwd (User password) Text String:

UICC/ME interface transport level

Transport format: **UDP** Port number: 44444 Data destination address 01.01.01.01

# Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	80	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.6.1A

## Logically:

Command details

Command number:

**OPEN CHANNEL** Command type:

Command qualifier: immediate link establishment

Device identities

Source device: ME Destination device: **UICC**  Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.6.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
·	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

27.22.4.27.5.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.6.

27.22.4.27.5.7 Open Channel (GPRS, support of Text Attribute – Italic On)

27.22.4.27.5.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.27.5.7.3 Test purpose

To verify that the ME displays an alpha identifier according to the italic text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.7.4 Method of test

27.22.4.27.5.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

# 27.22.4.27.5.7.4.2 Procedure

# Expected Sequence 5.7 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments				
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN					
2	ME	CHANNEL 5.7.1					
2 3	$ME \rightarrow UICC$ $UICC \rightarrow ME$	FETCH PROACTIVE COMMAND : OPEN CHANNEL					
3	OICC → IVIE	5.7.1					
4	$ME \to USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with italic on]				
5	$USER \to ME$	The user confirms					
6	$ME \to USS$	PDP context activation request					
7	$USS \to ME$	PDP context activation accept					
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A	[Command performed successfully]				
		or TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B					
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1					
10	$ME \to UICC$	FETCH					
11	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1					
12	$ME \to USS$	PDP context deactivation request					
13	$USS \to ME$	PDP context deactivation accept					
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]				
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.7.2					
16	$ME \to UICC$	FETCH					
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.7.2					
18	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with italic off]				
19	$USER \to ME$	The user confirms					
20	$ME \to USS$	PDP context activation request					
21	$USS \to ME$	PDP context activation accept					
22	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A	[Command performed successfully]				
		or					
		TERMINAL RESPONSE : OPEN CHANNEL					
		5.7.1B					
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE					
24	$ME \to UICC$	CHANNEL 5.1.1 FETCH					
25	$UICC \rightarrow ME$	PROACTIVE COMMAND: CLOSE CHANNEL					
		5.1.1					
26	$ME \rightarrow USS$	PDP context deactivation request					
27	USS → ME	PDP context deactivation accept	Command performed assessed that				
28	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]				
29	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.7.1					
30	$ME \to UICC$	FETCH					
31	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.7.1					
32	$ME \to USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with italic on]				
33	$USER \to ME$	The user confirms					
34	$ME \rightarrow USS$	PDP context activation request					
35	USS → ME	PDP context activation accept	[Command performed expenses with 1				
36	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A	[Command performed successfully]				
		or					
		TERMINAL RESPONSE : OPEN CHANNEL					
1 1		5.7.1B	l l				

37	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	ME → UICC	FETCH	
39	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
40	$ME \to USS$	PDP context deactivation request	
41	$USS \to ME$	PDP context deactivation accept	
42	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
43	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 5.7.3	
44	$ME \rightarrow UICC$	FETCH	
45	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
4.0		5.7.3	
46	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with italic off]
47	$USER \to ME$	The user confirms	
48	$ME \rightarrow USS$	PDP context activation request	
49	$USS \to ME$	PDP context activation accept	
50	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.7.1A	
		OF	
		TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B	
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE	
31		CHANNEL 5.1.1	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
54	$ME \rightarrow USS$	PDP context deactivation request	
55	USS → ME	PDP context deactivation accept	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	[25s Following agosoogan)]

## PROACTIVE COMMAND: OPEN CHANNEL 5.7.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	20
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.7.2

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05	
	09	4F	70	65	6E	20	49	44	20	32	35	07	
	02	03	04	03	04	1F	02	39	02	05	78	47	
	0A	06	54	65	73	74	47	70	02	72	73	0D	
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4	
	55	73	65	72	50	77	64	3C	03	01	AD	9C	
	3E	05	21	01	01	01	01	D0	04	00	09	00	
	B4												

## PROACTIVE COMMAND: OPEN CHANNEL 5.7.3

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 3"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

# Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	80	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.7.1A

## Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME Destination device: UICC Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.7.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

27.22.4.27.5.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.7.

27.22.4.27.5.8 Open Channel (GPRS, support of Text Attribute – Underline On)

27.22.4.27.5.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.27.5.8.3 Test purpose

To verify that the ME displays an alpha identifier according to the underline text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.8.4 Method of test

27.22.4.27.5.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## 27.22.4.27.5.8.4.2 Procedure

# Expected Sequence 5.8 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
2	ME	CHANNEL 5.8.1	
2 3	$ME \rightarrow UICC$ $UICC \rightarrow ME$	FETCH PROACTIVE COMMAND : OPEN CHANNEL	
3	OICC → IVIE	5.8.1	
4	$ME \to USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with underline on]
5	$USER \to ME$	The user confirms	
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.8.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
		5.8.1B	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
10	$ME \rightarrow UICC$	CHANNEL 5.1.1 FETCH	
11	$UICC \rightarrow ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
12	$ME \to USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
	OIGG / IVIL	CHANNEL 5.8.2	
16	$ME \to UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
18	$ME \to USER$	5.8.2 Confirmation phase with alpha ID	[alpha identifier is displayed with underline off]
19	$USER \rightarrow ME$	The user confirms	[alpha identifier is displayed with differifie on]
20	ME → USS	PDP context activation request	
21	$USS \rightarrow ME$	PDP context activation accept	
22	$ME \to UICC$	TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
		5.8.1A	
		or TERMINAL RESPONSE: OPEN CHANNEL	
		5.8.1B	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
		CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	$ME \to USS$	PDP context deactivation request	
27	$USS \to ME$	PDP context deactivation accept	
28	$ME \to UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
29	$UICC \to ME$	5.1.1   PROACTIVE COMMAND PENDING : OPEN	
29	OICC -> IVIE	CHANNEL 5.8.1	
30	$ME \to UICC$	FETCH	
31	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
60		5.8.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with underline on]
33 34	$\begin{array}{c} USER \to ME \\ ME \to USS \end{array}$	The user confirms PDP context activation request	
35	$USS \rightarrow ME$	PDP context activation accept	
36	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.8.1A	
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
1 1		5.8.1B	l l

37	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	$ME \to UICC$	FETCH	
39	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
		5.1.1	
40	$ME \to USS$	PDP context deactivation request	
41	$USS \to ME$	PDP context deactivation accept	
42	$ME \to UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
43	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 5.8.3	
44	$ME \to UICC$	FETCH	
45	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
		5.8.3	
46	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with underline off]
47	$USER \to ME$	The user confirms	
48	$ME \to USS$	PDP context activation request	
49	$USS \to ME$	PDP context activation accept	
50	$ME \to UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.8.1A	
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
F.4		5.8.1B	
51	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
52	ME	CHANNEL 5.1.1 FETCH	
53	ME → UICC	PROACTIVE COMMAND: CLOSE CHANNEL	
53	$UICC \to ME$	5.1.1	
54	$ME \to USS$	PDP context deactivation request	
55	USS → ME	PDP context deactivation request	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
50	IVIE → UICC	15.1.1	[Command performed successfully]
		0.1.1	

## PROACTIVE COMMAND: OPEN CHANNEL 5.8.1

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

724

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	40
	B4											

#### PROACTIVE COMMAND: OPEN CHANNEL 5.8.2

#### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05	i
	09	4F	70	65	6E	20	49	44	20	32	35	07	ı
	02	03	04	03	04	1F	02	39	02	05	78	47	ı
	0A	06	54	65	73	74	47	70	02	72	73	0D	ı
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4	ı
	55	73	65	72	50	77	64	3C	03	01	AD	9C	ı
	3E	05	21	01	01	01	01	D0	04	00	09	00	ı
	B4												ì

#### PROACTIVE COMMAND: OPEN CHANNEL 5.8.3

#### Logically:

Command details

Command number:

Command type: **OPEN CHANNEL** 

Command qualifier: immediate link establishment

Device identities

Source device: **UICC** Destination device: ME

Alpha Identifier "Open ID 3"

Bearer

**GPRS** Bearer type:

Bearer parameter:

Precedence Class: 03 Delay Class: 04 Reliability Class: 03 Peak throughput class: 04 Mean throughput class: 31 02 (IP)

Packet data protocol:

Buffer

Buffer size: 1400 Network access name: TestGp.rs

UserLog (User login) Text String: UserPwd (User password) Text String:

UICC/ME interface transport level

Transport format: **UDP** Port number: 44444 Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	80	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

### TERMINAL RESPONSE: OPEN CHANNEL 5.8.1A

## Logically:

Command details

Command number:

**OPEN CHANNEL** Command type:

Command qualifier: immediate link establishment

Device identities

Source device: ME Destination device: **UICC**  Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.8.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
·	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

27.22.4.27.5.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.8.

27.22.4.27.5.9 Open Channel (GPRS, support of Text Attribute – Strikethrough On)

27.22.4.27.5.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.27.5.9.3 Test purpose

To verify that the ME displays an alpha identifier according to the strikethrough text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.9.4 Method of test

27.22.4.27.5.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.9.4.2 Procedure

# Expected Sequence 5.9 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
	ME LUGG	CHANNEL 5.9.1	
2	ME → UICC	FETCH PROACTIVE COMMAND : OPEN CHANNEL	
3	$UICC \to ME$	5.9.1	
4	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough on]
5	$USER \to ME$	The user confirms	
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A	[Command performed successfully]
		or TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	$ME \to UICC$	FETCH	
11	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	$ME \to USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.9.2	
16	$ME \to UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.9.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough off]
19	USER → ME	The user confirms	
20	$ME \to USS$	PDP context activation request	
21	$USS \to ME$	PDP context activation accept	
22	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B	
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE	
	OIGG / WIE	CHANNEL 5.1.1	
24	$ME \to UICC$	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	$ME \rightarrow USS$	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
29	$UICC \to ME$	5.1.1 PROACTIVE COMMAND PENDING : OPEN	
30	ME → UICC	CHANNEL 5.9.1 FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL	
32	$ME \rightarrow USER$	5.9.1   Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough on]
33	USER → ME	The user confirms	[wipha adminor to dioplayed with difficultiough on]
34	ME → USS	PDP context activation request	
35	$USS \to ME$	PDP context activation accept	
36	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL	[Command performed successfully]
		5.9.1A	
		or TERMINAL RESPONSE : OPEN CHANNEL	
		5.9.1B	

37	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
		CHANNEL 5.1.1	
38	$ME \rightarrow UICC$	FETCH	
39	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
40		5.1.1	
40	$ME \rightarrow USS$	PDP context deactivation request	
41	$USS \to ME$	PDP context deactivation accept	
42	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	
43	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	
		CHANNEL 5.9.3	
44	$ME \rightarrow UICC$	FETCH	
45	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL	
40		5.9.3	
46	$ME \rightarrow USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough off]
47	$USER \to ME$	The user confirms	
48	$ME \rightarrow USS$	PDP context activation request	
49	$USS \to ME$	PDP context activation accept	
50	$ME \rightarrow UICC$	TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL	
		5.9.1B	
51	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE	
		CHANNEL 5.1.1	
52	$ME \to UICC$	FETCH	
53	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
	' ' ' ' ' ' '	5.1.1	
54	$ME \to USS$	PDP context deactivation request	
55	$USS \to ME$	PDP context deactivation accept	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
		5.1.1	, , , , , , , , , , , , , , , , , , , ,

#### PROACTIVE COMMAND: OPEN CHANNEL 5.9.1

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

730

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	80
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.9.2

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05	i
	09	4F	70	65	6E	20	49	44	20	32	35	07	ı
	02	03	04	03	04	1F	02	39	02	05	78	47	ı
	0A	06	54	65	73	74	47	70	02	72	73	0D	ı
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4	ı
	55	73	65	72	50	77	64	3C	03	01	AD	9C	ı
	3E	05	21	01	01	01	01	D0	04	00	09	00	ı
	B4												ì

#### PROACTIVE COMMAND: OPEN CHANNEL 5.9.3

#### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Alpha Identifier "Open ID 3"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	80	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

### TERMINAL RESPONSE: OPEN CHANNEL 5.9.1A

## Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.9.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

27.22.4.27.5.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.9.

27.22.4.27.5.10 Open Channel (GPRS, support of Text Attribute – Foreground and Background

Colour)

27.22.4.27.5.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.10.3 Test purpose

To verify that the ME displays an alpha identifier according to the foreground and background colour text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.10.4 Method of test

27.22.4.27.5.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## 27.22.4.27.5.10.4.2 Procedure

# Expected Sequence 5.10 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING : OPEN	
		CHANNEL 5.10.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.10.1	
4	$ME \to USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with foreground and background colour according to the text attribute]
5	$USER \to ME$	The user confirms	
6	$ME \to USS$	PDP context activation request	
7	$USS \to ME$	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.10.1A or	[Command performed successfully]
		TERMINAL RESPONSE : OPEN CHANNEL 5.10.1B	
9	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	$ME \rightarrow UICC$	FETCH	
11	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	$ME \rightarrow USS$	PDP context deactivation request	
13	$USS \to ME$	PDP context deactivation accept	
14	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.10.2	
16	$ME \to UICC$	FETCH	
17	$UICC \to ME$	PROACTIVE COMMAND : OPEN CHANNEL 5.10.2	
18	$ME \to USER$	Confirmation phase with alpha ID	[alpha identifier is displayed with ME"s default foreground and background colour]
19	$USER \to ME$	The user confirms	
20	$ME \rightarrow USS$	PDP context activation request	
21	USS → ME	PDP context activation accept	[O
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.10.1A or	[Command performed successfully]
		TERMINAL RESPONSE : OPEN CHANNEL 5.10.1B	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	$ME \to UICC$	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL	
26	ME LICO	5.1.1	
26 27	$\begin{array}{c} ME \to USS \\ USS \to ME \end{array}$	PDP context deactivation request PDP context deactivation accept	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE : CLOSE CHANNEL	[Command performed successfully]
20	IVIL -> UICC	5.1.1	[Sommand portormed duccessfully]

#### PROACTIVE COMMAND: OPEN CHANNEL 5.10.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC

Destination device: ME

Alpha Identifier "Open ID 1"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Text Attribute

Formatting position: 0 Formatting length: 9

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

#### PROACTIVE COMMAND: OPEN CHANNEL 5.10.2

#### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC
Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400 Network access name: TestGp.rs Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

TERMINAL RESPONSE: OPEN CHANNEL 5.10.1A

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.10.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

#### Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
_	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.10.

#### 27.22.4.28 CLOSE CHANNEL

## 27.22.4.28.1 CLOSE CHANNEL(normal)

## 27.22.4.28.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.28.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);

to the UICC after the ME receives the CLOSE CHANNEL proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

#### 27.22.4.28.1.4 Method of Test

#### 27.22.4.28.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

#### 27.22.4.28.1.4.2 Procedure

## **Expected sequence 1.1 (CLOSE CHANNEL, successful)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL	
		1.1.1	
2	, 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
_		opening information	
5	$ME \rightarrow USS$	PDP context activation request	
6		PDP context activation accept	
7	$ME \rightarrow UICC$		[Command performed successfully]
		CHANNEL 1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN	
8		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL	
9	$ME \rightarrow UICC$	FETCH	
10		PROACTIVE COMMAND:	
10	$UICC \to ME$	CLOSE CHANNEL 1.1.1	
11	$ME \to USS$	PDP context deactivation	
''	IVIE → USS	request	
12	$USS \to ME$	PDP context deactivation accept	
13			[Command performed successfully]
13	IVIE → UICC	CHANNEL 1.1.1	
<u> </u>		OHAMMEL I.I.I	

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

**BER-TLV** 

D0	42	81	03	01	40	01	82	02	81	82	35
07	02	03	04	03	04	1F	02	39	02	03	E8
47	0A	06	54	65	73	74	47	70	02	72	73
0D	08	F4	55	73	65	72	4C	6F	67	0D	08
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

#### TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

#### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1

Coding:

BER-TLV: D0 09 81 03 01 4	41 00	82	02	81	21	
---------------------------	-------	----	----	----	----	--

TERMINAL RESPONSE: CLOSE CHANNEL 1.1.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00

## **Expected sequence 1.2 (CLOSE CHANNEL, with an invalid channel identifier)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL	
_		1.1.1	
2	/ 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
_	ME 1100	opening information	
5		PDP context activation request	
6		PDP context activation accept	10 1 ( 1 ( 1 )
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	
		or TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
	OIOO / IVIL	PENDING: CLOSE CHANNEL	
		1.2.1	
9	$ME \to UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND:	
		CLOSE CHANNEL 1.2.1	
11	$ME \to UICC$	TERMINAL RESPONSE CLOSE	[Invalid channel number]
		CHANNEL 1.2.1	

## PROACTIVE COMMAND: CLOSE CHANNEL 1.2.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 2

Coding:

BER-TLV:	DΩ	09	81	03	01	41	00	82	02	81	22
DLIX ILV.	טט	00	O i	00	O I	71	00	02	02	O I	

TERMINAL RESPONSE: CLOSE CHANNEL 1.2.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Bearer Independent Protocol error Additional Result: Channel identifier not valid

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	02	3A
	03											

## Expected sequence 1.3 (CLOSE CHANNEL, on an already closed channel)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	See initial conditions
		OPEN CHANNEL 1.1.1	
2	/ 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel opening information	
5	$ME \rightarrow USS$	PDP context activation request	
6	$USS \to ME$	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or	[Command performed successfully]
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.1.1	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1	
11	$ME \rightarrow USS$	PDP context deactivation request	
12	$USS \to ME$	PDP context deactivation accept	
13	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 1.1.1	[Command performed successfully]
14	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.3.1	
15	$ME \rightarrow UICC$	FETCH	
16	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 1.3.1	
17	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 1.3.1A or	[Channel closed]
		TERMINAL RESPONSE CLOSE CHANNEL 1.3.1B	[Channel identifier invalid]

PROACTIVE COMMAND: CLOSE CHANNEL 1.3.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1

Coding:

BER-TLV:	D0	09	81	03	01	41	00	82	02	81	21

TERMINAL RESPONSE: CLOSE CHANNEL 1.3.1A

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Bearer Independent Protocol error

Additional Result: Channel closed

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	02	3A
	02											

TERMINAL RESPONSE: CLOSE CHANNEL 1.3.1B

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Bearer Independent Protocol error

Additional Result: Channel identifier invalid

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	02	3A
	03											

27.22.4.28.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

27.22.4.28.2 CLOSE CHANNEL (support of Text Attribute)

27.22.4.28.2.1 CLOSE CHANNEL (support of Text Attribute – Left Alignment)

27.22.4.28.2.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.1.4 Method of Test

27.22.4.28.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format: UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.28.2.1.4.2 Procedure

# Expected sequence 2.1 (CLOSE CHANNEL, with Text Attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL	
2	ME → UICC	1.1.1   FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
3		OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
		opening information	
5	$ME \to USS$	PDP context activation request	
6		PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL 2.1.1A	
		2.1.1A	
9	$ME \to UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND:	[alpha identifier is displayed with left
		CLOSE CHANNEL 2.1.1	alignment]
11	$ME \to USS$	PDP context deactivation	
12	$USS \to ME$	request PDP context deactivation accept	
13			[Command performed successfully]
		CHANNEL 2.1.1	
14	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL	
15	$ME \rightarrow UICC$	FETCH	
16	UICC → ME	PROACTIVE COMMAND:	
		OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel	
18	ME  o USS	opening information PDP context activation request	
19	$USS \rightarrow ME$	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	, , , , , , , , , , , , , , , , , , , ,
		or	
		TERMINAL RESPONSE: OPEN	
21	$UICC \to ME$	CHANNEL 1.1.1B PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL	
		2.1.2	
22	ME → UICC	FETCH	
23	$UICC \to ME$	PROACTIVE COMMAND:	[Message shall be formatted without left
		CLOSE CHANNEL 2.1.2	alignment. Remark: If left alignment is the ME"s default alignment as declared in table
			A.2/20, no alignment change will take place]
24	$ME \to USS$	PDP context deactivation	
		request	
25	USS → ME	PDP context deactivation accept	[Command parformed successfully]
26	$ME \rightarrow UICC$	CHANNEL 2.1.1	[Command performed successfully]
		O: // (1414EE Z. 1. 1	

PROACTIVE COMMAND: CLOSE CHANNEL 2.1.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.1.2

#### Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.1.1

#### Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 41 00 82 02 82 8 <sup>2</sup>	1 83	01	00
---	------	----	----

## 27.22.4.28.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

27.22.4.28.2.2 CLOSE CHANNEL (support of Text Attribute – Center Alignment)

27.22.4.28.2.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.2.4 Method of Test

27.22.4.28.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog

User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.28.2.2.4.2 Procedure

# Expected sequence 2.2 (CLOSE CHANNEL, with Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL	
		1.1.1	
2		FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
7	WIL → USLIX	opening information	
5	$ME \to USS$	PDP context activation request	
6		PDP context activation accept	
7	$ME \to UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
	0.00 / III.E	PENDING: CLOSE CHANNEL	
		2.2.1	
9		FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND:	[alpha identifier is displayed with center
11	ME LIGO	CLOSE CHANNEL 2.2.1	alignment]
11	$ME \rightarrow USS$	PDP context deactivation request	
12	$USS \to ME$	PDP context deactivation accept	
13	$ME \rightarrow UICC$		[Command performed successfully]
	/ 0.00	CHANNEL 2.2.1	[
14	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL	
15	ME IIIOO	1.1.1   FETCH	
16	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND:	
10	OICC → IVIE	OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel	
		opening information	
18	$ME \to USS$	PDP context activation request	
19	$USS \to ME$	PDP context activation accept	
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A lor	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
21	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL	
	ME	2.2.2	
22 23	ME → UICC	FETCH PROACTIVE COMMAND:	[Massage shall be formatted without costs:
23	$UICC \to ME$	CLOSE CHANNEL 2.2.2	[Message shall be formatted without center alignment. Remark: If center alignment is the
		OLOGE OF IT WINDER 2.2.2	ME"s default alignment as declared in table
			A.2/20, no alignment change will take place]
24	$ME \to USS$	PDP context deactivation	
		request	
25	USS → ME	PDP context deactivation accept	10
26	$ME \rightarrow UICC$		[Command performed successfully]
<u> </u>		CHANNEL 2.2.1	

PROACTIVE COMMAND: CLOSE CHANNEL 2.2.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	01	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.2.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21	ì
	85	0A	43	6C	6F	73	65	20	49	44	20	ı
	32											1

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.2.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	01	03	01	<i>4</i> 1	00	02	02	02	01	02	01	00
DEK-ILV.	01	03	UI	41	00	02	02	02	01	೦೦	UI	UU

## 27.22.4.28.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

27.22.4.28.2.3 CLOSE CHANNEL (support of Text Attribute – Right Alignment)

27.22.4.28.2.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.3.4 Method of Test

27.22.4.28.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog

User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.28.2.3.4.2 Procedure

# Expected sequence 2.3 (CLOSE CHANNEL, with Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	See initial conditions
		OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel opening	
5	ME LICC	information	
6	ME → USS	PDP context activation request PDP context activation accept	
7	$\begin{array}{c} USS \to ME \\ ME \to UICC \end{array}$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
,	INIE → DICC	CHANNEL 1.1.1A	[Command penomied successibility]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		CLOSE CHANNEL 2.3.1	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with right
4.4		CHANNEL 2.3.1	alignment]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	[Command performed successfully]
13	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.3.1	[Command performed successfully]
14	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
''		OPEN CHANNEL 1.1.1	
15	$ME \rightarrow UICC$	FETCH	
16	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel opening	
40		information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	[O
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
1		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
21	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
		CLOSE CHANNEL 2.3.2	
22		FETCH	
23	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[Message shall be formatted without right
		CHANNEL 2.3.2	alignment. Remark: If right alignment is
1			the ME"s default alignment as declared in table A.2/20, no alignment change will
1			take place
24	$ME \to USS$	PDP context deactivation request	Lano piacoj
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE	[Command performed successfully]
		CHANNEL 2.3.1	

# PROACTIVE COMMAND: CLOSE CHANNEL 2.3.1

## Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier

"Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	02	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.3.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32										

TERMINAL RESPONSE: CLOSE CHANNEL 2.3.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-ILV:   81   03   01   41   00   82   02   82   81   83   01   00	IDEK-ILV.		03	01	41	00	82	02	1 02	81		01	00
--	-----------	--	----	----	----	----	----	----	------	----	--	----	----

27.22.4.28.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

27.22.4.28.2.4 CLOSE CHANNEL (support of Text Attribute – Large Font Size)

27.22.4.28.2.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.4.4 Method of Test

#### 27.22.4.28.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.28.2.4.4.2 Procedure

# Expected sequence 2.4 (CLOSE CHANNEL, with Text Attribute – Large Font Size)

UICC → ME	Step	Direction	MESSAGE / Action	Comments
2	1	$UICC \to ME$		See initial conditions
3		ME		
OPEN CHANNEL 1.1.1  The ME may display channel opening information PDP context activation request USS → ME PDP context activation accept TREMINAL RESPONSE: OPEN CHANNEL 1.1.18  UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1  ME → UICC  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1  ME → USS → ME PDP context deactivation accept UICC → ME PROACTIVE COMMAND COMMAN			=	
ME → USER   The ME may display channel opening information   PDP context activation request   PDP context activation accept   TERMINAL RESPONSE: OPEN   CHANNEL 1.1.1A   or TERMINAL RESPONSE: OPEN   CHANNEL 1.1.1B   PROACTIVE COMMAND   PENDING: CLOSE CHANNEL 2.4.1     ME → UICC → ME   PDP context deactivation request   PDP context deactivation request   ICOmmand performed successfully   ICO → ME   ICO	3			
Department of the property	4	ME → USER		
Command performed successfully   Command performed successfully			opening information	
TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1  ME → USS → ME DPD context deactivation request PDP CHANNEL 2.4.1  ME → UICC → ME PROACTIVE COMMAND POPNOING: OPEN CHANNEL 2.4.1  ME → UICC → ME PDP context deactivation accept TERMINAL RESPONSE CLOSE CHANNEL 2.4.1  ME → UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  ME → UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  THE ME → USS → ME DPD context deactivation request PDP context deactivation request PDP context deactivation accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → USS → ME PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept P				
CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1  9 ME → UICC 10 UICC → ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1 11 ME → USS 12 USS → ME 13 ME → UICC 14 UICC → ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1 PP context deactivation request PDP context deactivation accept TERMINAL RESPONSE CLOSE CHANNEL 2.4.1 PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 FETCH PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 The ME may display channel opening information PDP context deactivation request PDP context deactivation accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A Or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → USS DPP context deactivation request PDP context deactivation accept (Icommand performed successfully) [Icommand performed successfully]				
or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1  9 ME → UICC → ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1  11 ME → USS DP Context deactivation request PDP context deactivation accept TERMINAL RESPONSE CLOSE CHANNEL 2.4.1  14 UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  15 ME → UICC HE PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  16 UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  17 ME → USSR POP context deactivation request Opening information PDP context deactivation request PDP context deactivation request PDP context deactivation accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A OF TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  21 UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  22 ME → UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  24 ME → USS DPP context deactivation request PDP context deactivation accept PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context de	7	$ME \rightarrow UICC$		[Command performed successfully]
TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1 FETCH UICC → ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1  ME → USS PDP context deactivation request PDP context deactivation accept TERMINAL RESPONSE CLOSE CHANNEL 2.4.1  ME → UICC ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1  TERMINAL RESPONSE CLOSE CHANNEL 2.4.1  ME → UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  ME → UICC → ME PROACTIVE COMMAND: OPEN CHANNEL 1.1.1  ME → USS PDP context deactivation request PDP context deactivation request PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation request PDP context deactivation accept PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation accept PDP context deactivation request PDP context deactivation request PDP context deactivation accept PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP co				
8			TERMINAL RESPONSE: OPEN	
PENDING: CLOSE CHANNEL 2.4.1 FETCH    OUICC → ME	8	$UICC \to ME$	_	
9 ME → UICC 10 UICC → ME 11 ME → USS 12 USS → ME 13 ME → UICC 14 UICC → ME 15 ME → UICC 16 UICC → ME 17 ME → USS 19 USS → ME 18 ME → USS 19 USS → ME 20 ME → UICC 18 ME → UICC 19 ME → UICC 10 UICC → ME 10 UICC → ME 11 ME → USS 19 USS → ME 20 ME → UICC 10 UICC → ME 21 UICC → ME 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 26 ME → UICC 27 ME → UICC 28 ME → UICC 29 ME → UICC 20 ME → UICC 20 ME → UICC 21 UICC → ME 21 UICC → ME 22 ME → UICC 23 USS → ME 24 ME → USS 25 USS → ME 26 ME → USS 27 PPP context deactivation request PDP context deactivation request PDP context deactivation request PCHANNEL 1.1.18 26 ME → UICC 27 ME → UICC 28 ME → UICC 29 ME → UICC 29 ME → UICC 29 ME → UICC 20 ME → UICC 20 ME → UICC 21 ME → UICC 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 26 ME → USS 27 PDP context deactivation request			PENDING: CLOSE CHANNEL	
UICC → ME  VICC → ME				
THE → USS → ME PDP context deactivation request PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept TERMINAL RESPONSE CLOSE CHANNEL 2.4.1  14 UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  15 ME → UICC FETCH PROACTIVE COMMAND: OPEN CHANNEL 1.1.1  17 ME → USER PDP context deactivation request PDP context deactivation request PDP context deactivation accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B  21 UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  22 ME → UICC FETCH PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  24 ME → USS PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation accept PDP context deactivation ac		/ 0.00	_	Talaba identifiar ia diaplacad with large fact
11 ME → USS 12 USS → ME 13 ME → UICC 14 UICC → ME 15 ME → UICC 16 UICC → ME 17 ME → USR 19 USS → ME 20 ME → UICC 21 UICC → ME 21 UICC → ME 21 UICC → ME 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 20 ME → USS 25 USS → ME 20 ME → UICC 21 ME → UICC 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 27 CHANNEL 2.4.2 28 PDP context deactivation request PROACTIVE COMMAND: Command performed successfully] 28 (CHANNEL 1.1.18 29 Command performed successfully] 20 (CHANNEL 1.1.14 21 (Command performed successfully) 21 (Command performed successfully) 22 (CHANNEL 1.1.16 23 (CHANNEL 1.1.18 24 (CHANNEL 2.4.2 25 (CHANNEL 2.4.2 26 (CHANNEL 2.4.2 27 (CHANNEL 2.4.2 28 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 21 (Command performed successfully) 21 (Command performed successfully) 22 (CHANNEL 1.1.18 23 (CHANNEL 2.4.2 24 (CHANNEL 2.4.2 25 (CHANNEL 2.4.2 26 (CHANNEL 2.4.2 27 (CHANNEL 2.4.2 28 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 21 (COMMAND PENDING: CLOSE CHANNEL 2.4.2 22 (CHANNEL 2.4.2 23 (CHANNEL 2.4.2 24 (CHANNEL 2.4.2 25 (CHANNEL 2.4.2 26 (CHANNEL 2.4.2 27 (CHANNEL 2.4.2 28 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 21 (COMMAND PENDING: CLOSE CHANNEL 2.4.2 22 (CHANNEL 2.4.2 23 (CHANNEL 2.4.2 24 (CHANNEL 2.4.2 25 (CHANNEL 2.4.2 26 (CHANNEL 2.4.2 27 (CHANNEL 2.4.2 28 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 21 (COMMAND PENDING: CLOSE (CHANNEL 2.4.2 22 (CHANNEL 2.4.2 23 (CHANNEL 2.4.2 24 (CHANNEL 2.4.2 25 (CHANNEL 2.4.2 26 (CHANNEL 2.4.2 27 (CHANNEL 2.4.2 28 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 21 (COMMAND 2.4.2 21 (COMMAND 2.4.2 21 (COMMAND 2.4.2 22 (CHANNEL 2.4.2 23 (CHANNEL 2.4.2 24 (CHANNEL 2.4.2 25 (CHANNEL 2.4.2 26 (CHANNEL 2.4.2 27 (CHANNEL 2.4.2 28 (CHANNEL 2.4.2 29 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2 20 (CHANNEL 2.4.2	10	UICC → ME		
12 USS → ME ME → UICC TERMINAL RESPONSE CLOSE CHANNEL 2.4.1  14 UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  15 ME → UICC FETCH  16 UICC → ME PROACTIVE COMMAND: OPEN CHANNEL 1.1.1  17 ME → USS PDP context deactivation request opening information pening information accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B  21 UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  22 ME → UICC  23 ME → UICC  24 ME → USS PDP context deactivation request PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  24 ME → USS PDP context deactivation request PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  24 ME → USS PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation request PDP context deactivation accept PDP context deactivation ac	11	$ME \rightarrow USS$		0.20]
UICC → ME    ME → UICC   ME   PROACTIVE COMMAND   PENDING: OPEN CHANNEL 1.1.1	12			
14 UICC → ME PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1  15 ME → UICC 16 UICC → ME 17 ME → USER 18 ME → USS 19 USS → ME 20 ME → UICC 16 UICC → ME 21 UICC → ME 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 25 USS → ME 26 PROACTIVE COMMAND: PROACTIVE COMMAND: PROACTIVE COMMAND: PROACTIVE COMMAND: PDP context deactivation request portion accept accept command performed successfully] (Command performed successfully) [Command performed successfully]	13	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE	[Command performed successfully]
PENDING: OPEN CHANNEL 1.1.1    15	1			
15 ME → UICC 16 UICC → ME 17 ME → USER 18 ME → USS 19 USS → ME 20 ME → UICC 21 UICC → ME 21 UICC → ME 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 26 ME → USS 27 DPP context deactivation request PROACTIVE COMMAND: (CHANNEL 1.1.18 PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2 28 ME → UICC 29 ME → UICC 20 ME → UICC 21 UICC → ME 21 UICC → ME 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 25 USS → ME 26 ME → USS 27 PDP context deactivation request PDP context deactivation accept PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2 28 PDP context deactivation request PDP context deactivation accept PDP context deactivation accept	14	$UICC \to ME$		
16 UICC → ME PROACTIVE COMMAND: 17 ME → USER 18 ME → USS 19 USS → ME 20 ME → UICC 21 UICC → ME 21 UICC → ME 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 27 DP Context deactivation request PROACTIVE COMMAND: 28 OPEN CHANNEL 1.1.1A 29 OF TERMINAL RESPONSE: OPEN CHANNEL 2.4.2 20 ME → UICC 21 UICC → ME 22 ME → UICC 23 UICC → ME 24 ME → USS 25 USS → ME 26 PDP context deactivation request PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2 26 PDP context deactivation request PDP context deactivation request PDP context deactivation accept PDP context deactivation accept PDP context deactivation accept	15	ME -> LIICC		
OPEN CHANNEL 1.1.1  The ME may display channel opening information  NE → USS USS → ME USS → ME OFEN CHANNEL 1.1.1  The ME may display channel opening information  PDP context deactivation request PDP context deactivation accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A OR TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B  PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → USS UICC → ME  PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  PDP context deactivation request PDP context deactivation request PDP context deactivation accept				
opening information PDP context deactivation request PDP context deactivation accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  ME → UICC  PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  PDP context deactivation request USS → ME  PDP context deactivation accept  DDP context deactivation accept		0.00 /=		
18	17	$ME \to USER$		
19 USS → ME DPP context deactivation accept TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  22 ME → UICC → ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  24 ME → USS CHANNEL 2.4.2  25 USS → ME DPP context deactivation request PDP context deactivation accept [alpha identifier is displayed with normal for size]	10	ME 1100		
20 ME → UICC TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B  21 UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  22 ME → UICC FETCH PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  24 ME → USS OPEN (CHANNEL 2.4.2) PDP context deactivation request DSS → ME PDP context deactivation accept [alpha identifier is displayed with normal for size]			<b> </b>	
CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME $\rightarrow$ UICC $\rightarrow$ ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  ME $\rightarrow$ UICC $\rightarrow$ ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  ME $\rightarrow$ USS $\rightarrow$ ME PDP context deactivation request PDP context deactivation accept			•	[Command performed successfully]
TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B  PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME $\rightarrow$ UICC FETCH  UICC $\rightarrow$ ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  ME $\rightarrow$ USS $\rightarrow$ ME PDP context deactivation request PDP context deactivation accept	20	IVIL -> 0100		[Command performed successfully]
CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  ME → UICC THANNEL 2.4.2  PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  ME → USS THE → US				
21 UICC → ME PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  22 ME → UICC TETCH PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  24 ME → USS TOWNS OF THE PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  PDP context deactivation request TOWNS OF THE PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  PDP context deactivation request TOWNS OF THE PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  PDP context deactivation request TOWNS OF THE PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2  [alpha identifier is displayed with normal for size]				
PENDING: CLOSE CHANNEL 2.4.2  22 ME $\rightarrow$ UICC FETCH  23 UICC $\rightarrow$ ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  24 ME $\rightarrow$ USS PDP context deactivation request PDP context deactivation accept	21	LUCC ME		
22 ME → UICC FETCH 23 UICC → ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2 24 ME → USS DPD context deactivation request PDP context deactivation accept [alpha identifier is displayed with normal for size]	21	OICC → IVIE		
23 UICC → ME PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2  24 ME → USS PDP context deactivation request PDP context deactivation accept PDP context deactivation accept				
CHANNEL 2.4.2  ME → USS   PDP context deactivation request   DSS → ME   PDP context deactivation accept   Size]	22	$ME \rightarrow UICC$	FETCH	
24 ME → USS PDP context deactivation request 25 USS → ME PDP context deactivation accept	23	$UICC \to ME$		[alpha identifier is displayed with normal font
25 USS → ME PDP context deactivation accept	24	ME		[SIZE]
· ·				
				[Command performed successfully]
CHANNEL 2.4.1	20	IVIL -> UICC		[Serminal performed adoptionally]
27 UICC → ME PROACTIVE COMMAND	27	$UICC \to ME$	PROACTIVE COMMAND	
PENDING: OPEN CHANNEL 1.1.1				
28 ME → UICC FETCH			_	
29 UICC → ME PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	29	UICC → MÉ		
30 ME → USER The ME may display channel	30	MF → USER		
opening information		/ 55210		
31 ME → USS PDP context activation request			PDP context activation request	
32 USS → ME PDP context activation accept	_		·	
33 ME → UICC TERMINAL RESPONSE: OPEN [Command performed successfully]	33	$ME \rightarrow UICC$		[Command performed successfully]
CHANNEL 1.1.1A				
TERMINAL RESPONSE: OPEN				
CHANNEL 1.1.1B			CHANNEL 1.1.1B	

34	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1	[alpha identifier is displayed with large font size]
37	$ME \rightarrow USS$	PDP context deactivation request	
38	$USS \to ME$	PDP context deactivation accept	
39	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.4.1	[Command performed successfully]
40	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	$ME \rightarrow UICC$	FETCH	
42	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	$ME \rightarrow USER$	The ME may display channel opening information	
44	$ME \to USS$	PDP context activation request	
45	$USS \to ME$	PDP context activation accept	
46	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
47	$UICC \to ME$	or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.3	
48	$ME \rightarrow UICC$	FETCH	
49	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 2.4.3	[alpha identifier is displayed with normal font size]
50	$ME \rightarrow USS$	PDP context deactivation request	
51	$USS \to ME$	PDP context deactivation accept	
52	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.4.1	[Command performed successfully]

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	04	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device:Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
_	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.4.3

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
_	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.4.1

Logically:

Command details

Command number:

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

27.22.4.28.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

27.22.4.28.2.5 CLOSE CHANNEL (support of Text Attribute – Small Font Size)

27.22.4.28.2.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.28.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to the small font size text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.5.4 Method of Test

27.22.4.28.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.28.2.5.4.2 Procedure

# Expected sequence 2.5 (CLOSE CHANNEL, with Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
	ME	PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$ $UICC \rightarrow ME$	FETCH PROACTIVE COMMAND:	
3	OICC → IVIE	OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
		opening information	
5		PDP context activation request	
6		PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
	0.00 / III.	PENDING: CLOSE CHANNEL	
		2.5.1	
9	/ 0.00	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1	[alpha identifier is displayed with small font
11	ME  o USS	PDP context deactivation request	size]
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE	[Command performed successfully]
		CHANNEL 2.5.1	, , , , , , , , , , , , , , , , , , , ,
14	$UICC \to ME$	PROACTIVE COMMAND	
4.5	ME IIIOO	PENDING: OPEN CHANNEL 1.1.1	
15 16	$ME \to UICC$ $UICC \to ME$	FETCH PROACTIVE COMMAND:	
10	OICC → IVIE	OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel	
		opening information	
18	$ME \to USS$	PDP context activation request	
19	$USS \to ME$	PDP context activation accept	
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
21	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL	
22	$ME \rightarrow UICC$	2.5.2 FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with normal font
		CHANNEL 2.5.2	size]
24	$ME \to USS$	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.5.1	[Command performed successfully]
27	$UICC \to ME$	PROACTIVE COMMAND	
-'		PENDING: OPEN CHANNEL 1.1.1	
28	$ME \to UICC$	FETCH	
29	$UICC \to ME$	PROACTIVE COMMAND:	
		OPEN CHANNEL 1.1.1	
30	$ME \rightarrow USER$	The ME may display channel opening information	
31	$ME \to USS$	PDP context activation request	
32	$USS \rightarrow ME$	PDP context activation accept	
33	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
1	I	OLIMINEE I.I.ID	ı

34	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1	[alpha identifier is displayed with small font size]
37	$ME \rightarrow USS$	PDP context deactivation request	
38	$USS \to ME$	PDP context deactivation accept	
39	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.5.1	[Command performed successfully]
40	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	$ME \rightarrow UICC$	FETCH	
42	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	$ME \rightarrow USER$	The ME may display channel opening information	
44	$ME \rightarrow USS$	PDP context activation request	
45	$USS \to ME$	PDP context activation accept	
46	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
47	UICC → ME	or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.3	
48	$ME \rightarrow UICC$	FETCH	
49	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 2.5.3	[alpha identifier is displayed with normal font size]
50	$ME \rightarrow USS$	PDP context deactivation request	
51	$USS \to ME$	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.5.1	[Command performed successfully]

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	08	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.5.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device:Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.5.3

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.5.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

27.22.4.28.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

27.22.4.28.2.6 CLOSE CHANNEL (support of Text Attribute – Bold On)

27.22.4.28.2.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.28.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.6.4 Method of Test

27.22.4.28.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.28.2.6.4.2 Procedure

# Expected sequence 2.6 (CLOSE CHANNEL, with Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
2	ME LUCC	PENDING: OPEN CHANNEL 1.1.1 FETCH	
3	$ME \to UICC$ $UICC \to ME$	PROACTIVE COMMAND:	
3	UICC → IVIE	OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
		opening information	
5	ME → USS	PDP context activation request	
6 7	USS → ME	PDP context activation accept	[Command performed augeografidle]
'	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL	
		2.6.1	
9	$ME \to UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with bold on]
		CHANNEL 2.6.1	
11		PDP context deactivation request	
12 13	$\begin{array}{c} USS \to ME \\ ME \to UICC \end{array}$	PDP context deactivation accept TERMINAL RESPONSE CLOSE	[Command performed successfully]
13	IVIE → UICC	CHANNEL 2.6.1	[Command performed successfully]
14	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel	
		opening information	
18		PDP context activation request	
19	USS → ME	PDP context activation accept	
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
21	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL 2.6.2	
22	$ME \to UICC$	FETCH	
23	$UICC \rightarrow ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with bold off]
		CHANNEL 2.6.2	
24	ME → USS	PDP context deactivation request	
25 26	$\begin{array}{c} USS \to ME \\ ME \to UICC \end{array}$	PDP context deactivation accept TERMINAL RESPONSE CLOSE	[Command performed successfully]
20	IVIE → UICC	CHANNEL 2.6.1	[Command penomica successfully]
27	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH	
29	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
30	$ME \rightarrow USER$	The ME may display channel	
		opening information	
31	$ME \rightarrow USS$	PDP context activation request	
32	USS → ME	PDP context activation accept	[Commond nonformed access ( !! ]
33	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	

34	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1	[alpha identifier is displayed with bold on]
37	$ME \rightarrow USS$	PDP context deactivation request	
38	$USS \to ME$	PDP context deactivation accept	
39	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.6.1	[Command performed successfully]
40	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	$ME \rightarrow UICC$	FETCH	
42	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	$ME \rightarrow USER$	The ME may display channel opening information	
44	$ME \rightarrow USS$	PDP context activation request	
45	$USS \to ME$	PDP context activation accept	
46	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
47	UICC → ME	or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with bold off]
		CHANNEL 2.6.3	
50	$ME \rightarrow USS$	PDP context deactivation request	
51	$USS \to ME$	PDP context deactivation accept	
52	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.6.1	[Command performed successfully]

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	10	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.6.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.6.3

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.6.1

Logically:

Command details

Command number:

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

27.22.4.28.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

27.22.4.28.2.7 CLOSE CHANNEL (support of Text Attribute – Italic On)

27.22.4.28.2.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.28.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.7.4 Method of Test

27.22.4.28.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format: UDP Port number: 44444

# 27.22.4.28.2.7.4.2 Procedure

# Expected sequence 2.7 (CLOSE CHANNEL, with Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
2	ME SUICO	PENDING: OPEN CHANNEL 1.1.1 FETCH	
3	$ME \to UICC$ $UICC \to ME$	PROACTIVE COMMAND:	
3	UICC → IVIE	OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
		opening information	
5	ME → USS	PDP context activation request	
6 7	USS → ME	PDP context activation accept	[Command performed augeografidle]
'	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL	
		2.7.1	
9	$ME \to UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with bold on]
		CHANNEL 2.7.1	
11		PDP context deactivation request	
12 13	$\begin{array}{c} USS \to ME \\ ME \to UICC \end{array}$	PDP context deactivation accept TERMINAL RESPONSE CLOSE	[Command performed successfully]
13	IVIE → UICC	CHANNEL 2.7.1	[Confinant performed successibility]
14	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel	
	, , , , ,	opening information	
18		PDP context activation request	
19	$USS \to ME$	PDP context activation accept	
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
21	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL 2.6.2	
22	$ME \to UICC$	FETCH	
23	$UICC \rightarrow ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with bold off]
		CHANNEL 2.7.2	
24	ME → USS	PDP context deactivation request	
25 26	$\begin{array}{c} USS \to ME \\ ME \to UICC \end{array}$	PDP context deactivation accept TERMINAL RESPONSE CLOSE	[Command performed successfully]
20	IVIE → UICC	CHANNEL 2.7.1	[Command penomica successfully]
27	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH PROACTIVE COMMAND:	
29	$UICC \to ME$	OPEN CHANNEL 1.1.1	
30	$ME \rightarrow USER$	The ME may display channel	
		opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	[Command parformed consecutivity]
33	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	

34	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1	[alpha identifier is displayed with bold on]
37	$ME \rightarrow USS$	PDP context deactivation request	
38	$USS \to ME$	PDP context deactivation accept	
39	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.7.1	[Command performed successfully]
40	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	$ME \rightarrow UICC$	FETCH	
42	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	$ME \rightarrow USER$	The ME may display channel opening information	
44	$ME \to USS$	PDP context activation request	
45	$USS \to ME$	PDP context activation accept	
46	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
47	$UICC \to ME$	or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.7.3	[alpha identifier is displayed with bold off]
50	$ME \rightarrow USS$	PDP context deactivation request	
51	USS → ME	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.7.1	[Command performed successfully]

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	20	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.7.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.7.3

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.7.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

27.22.4.28.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

27.22.4.28.2.8 CLOSE CHANNEL (support of Text Attribute – Underline On)

27.22.4.28.2.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.28.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.8.4 Method of Test

27.22.4.28.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.28.2.8.4.2 Procedure

# Expected sequence 2.8 (CLOSE CHANNEL, with Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$		See initial conditions
		PROACTIVE COMMAND	
		PENDING: OPEN CHANNEL 1.1.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$		
	WE 7 OOLK	opening information	
5	$ME \to USS$	PDP context activation request	
6	$USS \to ME$	PDP context activation accept	
7	$ME \to UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	
		or TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: CLOSE CHANNEL	
		2.8.1	
9		FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with underline on]
11	$ME \to USS$	CHANNEL 2.8.1 PDP context deactivation request	
12	$USS \rightarrow ME$	PDP context deactivation accept	
13	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE	[Command performed successfully]
		CHANNEL 2.8.1	, , , , , , , , , , , , , , , , , , , ,
14	$UICC \to ME$		
		PROACTIVE COMMAND	
15	$ME \to UICC$	PENDING: OPEN CHANNEL 1.1.1 FETCH	
16	$UICC \to ME$	PROACTIVE COMMAND:	
	0.00 / III.	OPEN CHANNEL 1.1.1	
17	$ME \to USER$	The ME may display channel	
40	ME 1100	opening information	
18 19	$ME \to USS$ $USS \to ME$	PDP context activation request PDP context activation accept	
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
	WIE 7 0100	CHANNEL 1.1.1A	[Command performed edecederany]
		or	
		TERMINAL RESPONSE: OPEN	
21	LUCC ME	CHANNEL 1.1.1B	
21	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL	
		2.8.2	
22	$ME \to UICC$	FETCH	
23	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with underline off]
0.4	ME 1100	CHANNEL 2.8.2	
24 25	$ME \to USS$ $USS \to ME$	PDP context deactivation request PDP context deactivation accept	
26	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE	[Command performed successfully]
20	WL → 0100	CHANNEL 2.8.1	[Command performed decectorally]
27	$UICC \to ME$		
		PROACTIVE COMMAND	
20	ME LUCO	PENDING: OPEN CHANNEL 1.1.1 FETCH	
28 29	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND:	
23	OIOO - IVIE	OPEN CHANNEL 1.1.1	
30	$ME \to USER$	The ME may display channel	
		opening information	
31	ME → USS	PDP context activation request	
32	$USS \to ME$	PDP context activation accept	

33	$ME \to UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
34	$UICC \to ME$	or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1	[alpha identifier is displayed with underline on]
37	$ME \rightarrow USS$	PDP context deactivation request	
38	$USS \to ME$	PDP context deactivation accept	
39	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.8.1	[Command performed successfully]
40	$UICC \to ME$	DDC A OTIVE COMMAND	
		PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	ME → UICC	FETCH	
42	UICC → ME	PROACTIVE COMMAND:	
		OPEN CHANNEL 1.1.1	
43	$ME \rightarrow USER$	The ME may display channel	
44	$ME \rightarrow USS$	opening information PDP context activation request	
45	USS → ME	PDP context activation accept	
46	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
47	UICC → ME	PROACTIVE COMMAND	
''	OIGG / WIE	PENDING: CLOSE CHANNEL	
		2.8.3	
48	ME → UICC	FETCH	
49	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 2.8.3	[alpha identifier is displayed with underline off]
50	$ME \to USS$	PDP context deactivation request	
51	$USS \to ME$	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.8.1	[Command performed successfully]

# PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1

# Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

# Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	40	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.8.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
·	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.8.3

Logically:

Command details

Command number:

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

TERMINAL RESPONSE: CLOSE CHANNEL 2.8.1

Logically:

Command details

Command number:

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

ER-TLV: 81 03 01	41 0	00 82		82	81	83	01	00	ĺ
------------------	------	-------	--	----	----	----	----	----	---

#### 27.22.4.28.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

27.22.4.28.2.9 CLOSE CHANNEL (support of Text Attribute – Strikethrough On)

27.22.4.28.2.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.9.4 Method of Test

27.22.4.28.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level Transport format:UDP Port number: 44444

# 27.22.4.28.2.9.4.2 Procedure

# Expected sequence 2.9 (CLOSE CHANNEL, with Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
2	ME SUICO	PENDING: OPEN CHANNEL 1.1.1 FETCH	
3	$ME \to UICC$ $UICC \to ME$	PROACTIVE COMMAND:	
3	UICC → IVIE	OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
		opening information	
5	ME → USS	PDP context activation request	
6 7	USS → ME	PDP context activation accept	[Command performed augeografidle]
'	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL	
		2.9.1	
9	$ME \to UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with strikethrough
	ME LIGO	CHANNEL 2.9.1	on]
11		PDP context deactivation request PDP context deactivation accept	
12 13	$\begin{array}{c} USS \to ME \\ ME \to UICC \end{array}$	TERMINAL RESPONSE CLOSE	[Command performed successfully]
13	IVIL -> UICC	CHANNEL 2.9.1	[Sommand ponomined successfully]
14	$UICC \to ME$	PROACTIVE COMMAND	
4.5		PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel	
		opening information	
18		PDP context activation request	
19	USS → ME	PDP context activation accept	10
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
<b>.</b> .		CHANNEL 1.1.1B	
21	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL	
		2.9.2	
22	$ME \to UICC$	FETCH	
23	$UICC \to ME$	PROACTIVE COMMAND: CLOSE	[alpha identifier is displayed with strikethrough
0.4	ME 1100	CHANNEL 2.9.2	off]
24 25	ME → USS	PDP context deactivation request	
25 26	$\begin{array}{c} USS \to ME \\ ME \to UICC \end{array}$	PDP context deactivation accept TERMINAL RESPONSE CLOSE	[Command performed successfully]
20	IVIL -> UICC	CHANNEL 2.9.1	[Sommand ponomina adoptioning]
27	$UICC \to ME$	PROACTIVE COMMAND	
00	ME :::00	PENDING: OPEN CHANNEL 1.1.1	
28 29	$ME \to UICC$ $UICC \to ME$	FETCH PROACTIVE COMMAND:	
29	UICC → ME	OPEN CHANNEL 1.1.1	
30	$ME \rightarrow USER$	The ME may display channel	
		opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	[Command performed successfully]
33	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
1		CHANNEL 1.1.1B	

34	$UICC \to ME$	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1	[alpha identifier is displayed with strikethrough on]
37	$ME \rightarrow USS$	PDP context deactivation request	
38	$USS \to ME$	PDP context deactivation accept	
39	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.9.1	[Command performed successfully]
40	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	$ME \rightarrow UICC$	FETCH	
42	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	$ME \rightarrow USER$	The ME may display channel opening information	
44	$ME \rightarrow USS$	PDP context activation request	
45	$USS \to ME$	PDP context activation accept	
46	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
47	$UICC \to ME$	or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.3	
48	$ME \rightarrow UICC$	FETCH	
49	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 2.9.3	[alpha identifier is displayed with strikethrough off]
50	$ME \rightarrow USS$	PDP context deactivation request	_
51	$USS \to ME$	PDP context deactivation accept	
52	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.9.1	[Command performed successfully]

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	80	В4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.9.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.9.3

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

TERMINAL RESPONSE: CLOSE CHANNEL 2.9.1

Logically:

Command details

Command number:

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

778

27.22.4.28.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

27.22.4.28.2.10 CLOSE CHANNEL (support of Text Attribute – Foreground and Background Colour)

27.22.4.28.2.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.28.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.10.4 Method of Test

27.22.4.28.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.28.2.10.4.2 Procedure

# Expected sequence 2.10 (CLOSE CHANNEL, with Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel opening information	
5	$ME \to USS$	PDP context activation request	
6	$USS \to ME$	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
8	$UICC \to ME$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.10.1	
9		FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 2.10.1	[alpha identifier is displayed with foreground and background colour according to the text attribute configuration]
11	$ME \to USS$	PDP context deactivation request	
12	$USS \to ME$	PDP context deactivation accept	
13	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.10.1	[Command performed successfully]
14	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	$ME \rightarrow UICC$	FETCH	
16	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	$ME \rightarrow USER$	The ME may display channel opening information	
18	$ME \to USS$	PDP context activation request	
19	$USS \to ME$	PDP context activation accept	
20	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
21	$UICC \to ME$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.10.2	
22	$ME \to UICC$	FETCH	
23	$UICC \to ME$	PROACTIVE COMMAND: CLOSE CHANNEL 2.10.2	[alpha identifier is displayed with ME"s default foreground and background colour]
24	$ME \to USS$	PDP context deactivation request	
25	$USS \to ME$	PDP context deactivation accept	
26	$ME \rightarrow UICC$	TERMINAL RESPONSE CLOSE CHANNEL 2.10.1	[Command performed successfully]

# PROACTIVE COMMAND: CLOSE CHANNEL 2.10.1

# Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC

Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
_	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.10.2

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: UICC Destination device: Channel 1

Alpha Identifier "Close ID 2"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.10.1

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

RF	R-TLV:	81	03	01	<i>Δ</i> 1	00	82	02	82	81	83	01	00
D	IK-ILV.	01	03	υı	41	UU	02	02	02	01	03	UI	UU

# 27.22.4.28.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

#### 27.22.4.29 RECEIVE DATA

#### 27.22.4.29.1 RECEIVE DATA (NORMAL)

#### 27.22.4.29.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (ME currently unable to process command); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);

to the UICC after the ME receives the RECEIVE DATA proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

#### 27.22.4.29.1.4 Method of test

#### 27.22.4.29.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 51.010-1 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

#### **GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog

User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.29.1.4.2 Procedure

# Expected sequence 1.1 (RECEIVE DATA, already opened channel)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	$ME \to UICC$	TERMINAL RESPONSE: SET UP EVENT LIST	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	$ME \rightarrow USER$	The ME may display channel opening information	
9	$ME \to USS$	PDP context activation request	
10	$USS \to ME$	PDP context activation accept	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	$ME \rightarrow USS$	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	$USS \to ME$	Transfer of 1000 Bytes of data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1	(1000 Bytes of data in the ME buffer)
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.1	
20	$ME \rightarrow UICC$	FETCH	
21	$UICC \to ME$		200 Bytes
22	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 1.1.1	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
24	ME	DATA 1.1.2	
24		FETCH   PROACTIVE COMMAND: RECEIVE DATA 1.1.2	200 Bytes
25 26		PROACTIVE COMMAND: RECEIVE DATA 1.1.2 TERMINAL RESPONSE: RECEIVE DATA 1.1.2	200 Dyles
27	$UICC \rightarrow ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 1.1.3	
28	$ME \rightarrow UICC$	FETCH	
29		PROACTIVE COMMAND: RECEIVE DATA 1.1.3	200 Bytes
30	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 1.1.3	·
31	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.4	
32	$ME \rightarrow UICC$	FETCH	
33	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 1.1.4	200 Bytes
34	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 1.1.4	
35	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.5	
36	$ME \rightarrow UICC$	FETCH	
37		PROACTIVE COMMAND: RECEIVE DATA 1.1.5	200 Bytes
38	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 1.1.5	

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

#### Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: ME

Event list Data available

#### Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	09										

#### TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

#### Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

#### Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

# PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

# Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level Transport format: UDP Port number: 44444
Data destination address 01.01.01.01

Coding:

**BER-TLV** 

D0	42	81	03	01	40	01	82	02	81	82	35
07	02	03	04	03	04	1F	02	39	02	03	E8
47	0A	06	54	65	73	74	47	70	02	72	73
0D	08	F4	55	73	65	72	4C	6F	67	0D	80
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

#### PROACTIVE COMMAND: SEND DATA 1.1.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	21	B6
	80	00	01	02	03	04	05	06	07			

#### TERMINAL RESPONSE: SEND DATA 1.1.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

#### ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1

Logically:

Event list

Event: Data available

Device identities

Source device: ME
Destination device: UICC

Channel status

Channel status: Channel 1 open, link established

Channel Data Length

Channel data length: FF (more than 255 bytes are available)

Coding:

BER-TLV:	D6	0E	99	01	09	82	02	82	81	B8	02	81
	00	B7	01	FF								

#### PROACTIVE COMMAND: RECEIVE DATA 1.1.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	01	42	00	82	02	81	21	B7
	01	C8										

#### PROACTIVE COMMAND: RECEIVE DATA 1.1.2

Logically:

Command details

Command number: 2

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	02	42	00	82	02	81	21	B7
	01	C8										

#### PROACTIVE COMMAND: RECEIVE DATA 1.1.3

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	03	42	00	82	02	81	21	B7
	01	C8										

#### PROACTIVE COMMAND: RECEIVE DATA 1.1.4

Logically:

Command details

Command number: 4

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	04	42	00	82	02	81	21	B7
	01	C8										

#### PROACTIVE COMMAND: RECEIVE DATA 1.1.5

Logically:

Command details

Command number: 5

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	05	42	00	82	02	81	21	B7
·	01	C8										

#### TERMINAL RESPONSE: RECEIVE DATA 1.1.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

# Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

TERMINAL RESPONSE: RECEIVE DATA 1.1.2

Logically:

Command details

Command number: 2

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel Data : C8 C9 CA .. FF 00 01 .. 8F (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	02	42	00	82	02	82	81	83	01	00
	B6	81	C8	C8	C9	CA		FF	00	01	02	
	8F	B7	01	FF								ļ

TERMINAL RESPONSE: RECEIVE DATA 1.1.3

Logically:

Command details

Command number: 3

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel Data : 90 91 .. FF 00 01 – 57 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	03	42	00	82	02	82	81	83	01	00
_	B6	81	C8	90	91	92		FF	00	01	02	
	57	B7	01	FF								

TERMINAL RESPONSE: RECEIVE DATA 1.1.4

Logically:

Command details

Command number: 4

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully
Channel Data: 58 59 .. FF 00 01 .. 1F (200 Bytes of data)

Channel data length: C8

Coding:

BER-TLV:	81	03	04	42	00	82	02	82	81	83	01	00
	B6	81	C8	58	59	5A		FF	00	01	02	
	1F	B7	01	C8								

#### TERMINAL RESPONSE: RECEIVE DATA 1.1.5

Logically:

Command details

Command number: 5

Command type: RECEIVE DATA
Command qualifier: RFUDevice identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Channel Data: 20 21 .. E7 (200 Bytes of data)

Channel data length: 00

Coding:

BER-TLV:	81	03	05	42	00	82	02	82	81	83	01	00
	B6	81	C8	20	21	22		E7	B7	01	00	

# 27.22.4.29.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

# 27.22.4.29.2 RECEIVE DATA (support of Text Attribute)

27.22.4.29.2.1 RECEIVE DATA (support of Text Attribute – Left Alignment)

27.22.4.29.2.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.29.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.1.4 Method of test

#### 27.22.4.29.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP Port number: 44444

27.22.4.29.2.1.4.2 Procedure

# **Expected sequence 2.1 (RECEIVE DATA, with Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
		1.1.1 PENDING	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	$ME \to UICC$	TERMINAL RESPONSE: SET UP EVENT LIST	
7	IVIL -> OICC	1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
		CHANNEL 1.1.1	
6	ME → UICC	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	$ME \rightarrow USER$	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
''	WIE 7 0100	1.1.1A	[Command ponomica caccessiany]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
12	ME LUCC	DATA 1.1.1	
13 14	ME → UICC	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	$ME \to USS$	Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
	2 / 000	channel 1	[ [ [ [ [ [ [ [ [ [ [ [ [ [ [ [ [ [ [
16	$ME \to UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
		(immediate) 1.1.1	
17	$USS \to ME$	Transfer of 400 Bytes data to the ME through	
		channel 1 using the ME's port number, which was retrieved in step 15	
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data	(400 Bytes of data in the ME buffer)
10	IVIL -> OICC	available 2.1.1ENVELOPE (Data Available)	(400 Bytes of data in the ME buller)
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
	0.00 7 1.1.2	DATA 2.1.1	
20	$ME \to UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.1.1	200 Bytes with alpha identifier is
			displayed with left alignment
22	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.1.1	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
24	ME . LUCC	DATA 2.1.2	
24	ME → UICC	FETCH	200 Putos with alpha identifier shall be
25	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.1.2	200 Bytes with alpha identifier shall be formatted without left alignment.
			Remark: If left alignment is the ME"s
			default alignment as declared in table
			A.2/21, no alignment change will take
			place
26	$ME \to UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.1.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Logically:

Event list

Event: Data available

Device identities

Source device: ME
Destination device: UICC

Channel status

Channel status: Channel 1 open, link established

Channel Data Length

Channel data length: FF (more than 255 bytes are available)

Coding:

BER-TLV:	D6	0E	99	01	09	82	02	82	81	B8	02	81
	00	B7	01	FF								

## PROACTIVE COMMAND: RECEIVE DATA 2.1.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85	
	0E	52	65	63	65	69	76	65	20	44	61	74	
	61	20	31	B7	01	C8	D0	04	00	0E	00	B4	

# PROACTIVE COMMAND: RECEIVE DATA 2.1.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

## Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.1.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

## 27.22.4.29.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

27.22.4.29.2.2 RECEIVE DATA (support of Text Attribute – Center Alignment)

27.22.4.29.2.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.29.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.29.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.2.4 Method of test

27.22.4.29.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

## **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

#### **GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.29.2.2.4.2 Procedure

# Expected sequence 2.2 (RECEIVE DATA, with Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
		1.1.1 PENDING	
2	$ME \rightarrow UICC$		
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	ME LUCC	1.1.1 TERMINAL RESPONSE: SET UP EVENT LIST	
4	ME → UICC	1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
	0.00 /	CHANNEL 1.1.1	
6	$ME \rightarrow UICC$	FETCH	
7		PROACTIVE COMMAND: OPEN CHANNEL	
		1.1.1	
8	$\begin{array}{c} ME \to \\ USER \end{array}$	The ME may display channel opening information	
9	$ME \rightarrow USS$	PDP context activation request	
10		PDP context activation accept	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
		1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN CHANNEL	
12	LUCC ME	1.1.1B PROACTIVE COMMAND PENDING: SEND	
12	OICC - IVIE	DATA 1.1.1	
13	ME → UICC		
14		PROACTIVE COMMAND: SEND DATA	
	0.00 /	(immediate) 1.1.1	
15	$ME \rightarrow USS$	Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
		channel 1	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
47		(immediate) 1.1.1	
17	$USS \to ME$		
		channel 1 using the ME's port number, which was retrieved in step 15	
18	ME -> LIICC	ENVELOPE: EVENT DOWNLOAD - Data	(400 Bytes of data in the ME buffer)
10	IVIL -> 0100	available 2.1.1	(100 Bytos of data in the ME Buller)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.2.1	
20	$ME \rightarrow UICC$		
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.2.1	
		TERMINAL RESPONSE RESENTERATION	displayed with center alignment
22		TERMINAL RESPONSE: RECEIVE DATA 2.2.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE	
24	$ME \rightarrow UICC$	DATA 2.2.2	
25		PROACTIVE COMMAND: RECEIVE DATA 2.2.2	200 Bytes with alpha identifier shall be
		TO TO THE CONTINUE TO THE DATA 2.2.2	formatted without center alignment.
			Remark: If center alignment is the
			ME"s default alignment as declared in
			table A.2/21, no alignment change will
			take place
26	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.2.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

# PROACTIVE COMMAND: RECEIVE DATA 2.2.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	01	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.2.2

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.2.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

ME

Source device:
Destination device:

UICC

Result

General Result: Command performed successfully

Channel Data: 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

## Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
·	B6	81	C8	00	01	02		C7	B7	01	FF	

## 27.22.4.29.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

27.22.4.29.2.3 RECEIVE DATA (support of Text Attribute – Right Alignment)

27.22.4.29.2.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

# 27.22.4.29.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.3.4 Method of test

## 27.22.4.29.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

27.22.4.29.2.3.4.2 Procedure

# Expected sequence 2.3 (RECEIVE DATA, with Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
		1.1.1 PENDING	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST	
	IVIL 70100	1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
		CHANNEL 1.1.1	
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
0		1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	[Company of manifestrated acceptable]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	
		(immediate) 1.1.1	
15	$ME \rightarrow USS$	Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
16	ME → UICC	channel 1 TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
10		(immediate) 1.1.1	[Command penormed successiony]
17	$USS \to ME$	Transfer of 400 Bytes data to the ME through	
		channel 1 using the ME's port number, which was	
		retrieved in step 15	
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data	(400 Bytes of data in the ME buffer)
		available 2.1.1	
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
20	ME . IIICC	DATA 2.3.1 FETCH	
20 21	ME → UICC		200 Bytes with alpha identifier is
21	$UICC \to ME$	PROACTIVE COMMAND. RECEIVE DATA 2.3.1	displayed with right alignment
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.3.1	alsplayed with right aligninent
23	$UICC \rightarrow ME$	PROACTIVE COMMAND PENDING: RECEIVE	
	JIOO / IVIL	DATA 2.3.2	
24	$ME \rightarrow UICC$	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.3.2	200 Bytes with alpha identifier shall be
			formatted without right alignment.
			Remark: If right alignment is the ME"s
			default alignment as declared in table
			A.2/21, no alignment change will take
26	ME LUCC	TERMINAL RESPONSE: RECEIVE DATA 2.3.1	place
20	$ME \rightarrow UICC$	TERMINAL NEOF ONOL. RECEIVE DATA 2.3.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

# PROACTIVE COMMAND: RECEIVE DATA 2.3.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
_	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	02	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.3.2

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.3.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully Channel Data: 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
·	B6	81	C8	00	01	02		C7	B7	01	FF	

## 27.22.4.29.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

27.22.4.29.2.4 RECEIVE DATA (support of Text Attribute – Large Font Size)

27.22.4.29.2.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

# 27.22.4.29.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.4.4 Method of test

## 27.22.4.29.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
GPRS Parameters

Network access name: TestGp.rs

User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.29.2.4.4.2 Procedure

# Expected sequence 2.4 (RECEIVE DATA, with Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
_		1.1.1 PENDING	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	ME . IIICC	1.1.1  TERMINAL RESPONSE: SET UP EVENT LIST	
4	$ME \rightarrow UICC$	1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
		CHANNEL 1.1.1	Coo mindi conditions
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
		1.1.1	
8	$ME \rightarrow USER$	The ME may display channel opening information	
9	$ME \rightarrow USS$	PDP context activation request	
10	$USS \to ME$	PDP context activation accept	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
		1.1.1A	
		or TERMINAL RESPONSE: OPEN CHANNEL	
		11.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
	OIGG 7 WIE	DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	
		(immediate) 1.1.1	
15	$ME \rightarrow USS$	Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
		channel 1	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
17	LICC . ME	(immediate) 1.1.1 Transfer of 800 Bytes data to the ME through	
17	$USS \to ME$	channel 1 using the ME's port number, which was	
		retrieved in step 15	
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data	(800 Bytes of data in the ME buffer)
		available 2.1.1	,
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.4.1	
20	ME → UICC	FETCH	000 5 4 34 44 44 47
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.4.1	200 Bytes with alpha identifier is
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	displayed with large font size
23	$UICC \rightarrow ME$	PROACTIVE COMMAND PENDING: RECEIVE	
20		DATA 2.4.2	
24	$ME \rightarrow UICC$	FETCH	
25	$UICC \rightarrow ME$	PROACTIVE COMMAND: RECEIVE DATA 2.4.2	200 Bytes with alpha identifier is
			displayed with normal font size
26	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	
27	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
66		DATA 2.4.1	
28	ME → UICC	FETCH	200 Didge with alaka idaa (f
29	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.4.1	200 Bytes with alpha identifier is displayed with large font size
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	uispiayeu with large 10Ht Size
31	$UICC \rightarrow ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.4.3	
32	$ME \rightarrow UICC$	FETCH	
33	$UICC \rightarrow ME$		200 Bytes with alpha identifier is
			displayed with normal font size
34	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.4.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Large Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	04	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.4.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

# Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.4.3

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

## TERMINAL RESPONSE: RECEIVE DATA 2.4.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

## 27.22.4.29.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

27.22.4.29.2.5 RECEIVE DATA (support of Text Attribute – Small Font Size)

27.22.4.29.2.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.29.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to small font size the text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.5.4 Method of test

#### 27.22.4.29.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP Port number: 44444

# 27.22.4.29.2.5.4.2 Procedure

# Expected sequence 2.5 (RECEIVE DATA, with Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST	Comments
2	ME → UICC	1.1.1 PENDING FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST	
4	$ME \to UICC$	TERMINAL RESPONSE: SET UP EVENT LIST	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6 7	$ME \to UICC$ $UICC \to ME$	FETCH PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	$ME \rightarrow USER$	The ME may display channel opening information	
9	$ME \to USS$	PDP context activation request	
10	$USS \to ME$	PDP context activation accept	
11	$ME \to UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	$USS \to ME$	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	$ME \to UICC$	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(800 Bytes of data in the ME buffer)
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.1	
20 21	$\begin{array}{c} ME \to UICC \\ UICC \to ME \end{array}$	FETCH PROACTIVE COMMAND: RECEIVE DATA 2.5.1	200 Bytes with alpha identifier is
	0.00 / <u>-</u>		displayed with small font size
22 23		TERMINAL RESPONSE: RECEIVE DATA 2.5.1 PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.2	
24	$ME \to UICC$	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.5.2	200 Bytes with alpha identifier is displayed with normal font size
26 27	$ME \to UICC$ $UICC \to ME$	TERMINAL RESPONSE: RECEIVE DATA 2.5.1 PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.1	
28 29	$\begin{array}{c} ME \to UICC \\ UICC \to ME \end{array}$	FETCH PROACTIVE COMMAND: RECEIVE DATA 2.5.1	200 Bytes with alpha identifier is
23	OICC -> IVIE	TOTO TIVE GOIVINAND. NEGLIVE DATA 2.5.1	displayed with small font size
30	$ME \to UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.5.1	
31	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.3	
32	$ME \to UICC$	FETCH	
33	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.5.3	200 Bytes with alpha identifier is displayed with normal font size
34	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.5.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.5.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Small Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	08	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.5.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

# Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.5.3

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.5.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

27.22.4.29.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

27.22.4.29.2.6 RECEIVE DATA (support of Text Attribute – Bold On)

27.22.4.29.2.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.29.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.6.4 Method of test

27.22.4.29.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

27.22.4.29.2.6.4.2 Procedure

# Expected sequence 2.6 (RECEIVE DATA, with Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
_		1.1.1 PENDING	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	ME LUCC	1.1.1  TERMINAL RESPONSE: SET UP EVENT LIST	
4	$ME \rightarrow UICC$	1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
	OIGG / WIE	CHANNEL 1.1.1	oce ministration of the state o
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
		1.1.1	
8	$ME \rightarrow USER$	The ME may display channel opening information	
9	$ME \rightarrow USS$	PDP context activation request	
10	$USS \to ME$	PDP context activation accept	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
		1.1.1A	
		OF	
		TERMINAL RESPONSE: OPEN CHANNEL	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
12	OICC - WIL	DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	
		(immediate) 1.1.1	
15	$ME \rightarrow USS$	Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
		channel 1	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
17	LIGO ME	(immediate) 1.1.1	
17	$USS \to ME$	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was	
		retrieved in step 15	
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data	(800 Bytes of data in the ME buffer)
	,	available 2.1.1	(555 = 555
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.6.1	
20	$ME \rightarrow UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.6.1	200 Bytes with alpha identifier is
00	NAT 11100	TERMINIAL DECRONOS: DECENTS DATA O CA	displayed with bold on
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.2	
24	ME → UICC	FETCH	
25	$VICC \rightarrow ME$	PROACTIVE COMMAND: RECEIVE DATA 2.6.2	200 Bytes with alpha identifier is
	3.00 / WL		displayed with bold off
26	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	
27	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.6.1	
28	$ME \rightarrow UICC$	FETCH	
29	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.6.1	200 Bytes with alpha identifier is
20	ME	TERMINIAL DESCRIPTION OF A TABLE A	displayed with bold on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	
31	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.3	
32	ME → UICC	FETCH	
33	$UICC \to ME$		200 Bytes with alpha identifier is
	JIJJ → IVIE		displayed with bold off
34	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.6.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
_	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	10	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.6.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

# Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.6.3

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

## TERMINAL RESPONSE: RECEIVE DATA 2.6.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

27.22.4.29.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

27.22.4.29.2.7 RECEIVE DATA (support of Text Attribute – Italic On)

27.22.4.29.2.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.29.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.7.4 Method of test

## 27.22.4.29.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

27.22.4.29.2.7.4.2 Procedure

# Expected sequence 2.7 (RECEIVE DATA, with Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
_		1.1.1 PENDING	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	ME . IIICC	1.1.1  TERMINAL RESPONSE: SET UP EVENT LIST	
4	$ME \rightarrow UICC$	1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
	OIOO / IVIL	CHANNEL 1.1.1	eco miliar containone
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
		1.1.1	
8	$ME \rightarrow USER$	The ME may display channel opening information	
9	$ME \rightarrow USS$	PDP context activation request	
10	$USS \to ME$	PDP context activation accept	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
		1.1.1A	
		or TERMINAL RESPONSE: OPEN CHANNEL	
		11.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
'-	OIOO / IVIL	DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	
		(immediate) 1.1.1	
15	$ME \to USS$	Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
		channel 1	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
17	LICC . ME	(immediate) 1.1.1 Transfer of 800 Bytes data to the ME through	
17	$USS \to ME$	channel 1 using the ME's port number, which was	
		retrieved in step 15	
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data	(800 Bytes of data in the ME buffer)
		available 2.1.1ENVELOPE	,
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.7.1	
20	ME → UICC	FETCH	000 5 4 34 44 44 47
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.7.1	200 Bytes with alpha identifier is
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	displayed with italic on
23	$UICC \rightarrow ME$	PROACTIVE COMMAND PENDING: RECEIVE	
20		DATA 2.7.2	
24	$ME \rightarrow UICC$	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.7.2	200 Bytes with alpha identifier is
			displayed with italic off
26	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	
27	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
00	NAE :	DATA 2.7.1	
28	ME → UICC	FETCH	200 Didge with alpha identification
29	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.7.1	200 Bytes with alpha identifier is displayed with italic on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	uispiayeu with italic on
31	$UICC \rightarrow ME$	PROACTIVE COMMAND PENDING: RECEIVE	
"	JIOO / IVIL	DATA 2.7.3	
32	$ME \rightarrow UICC$	FETCH	
33	$UICC \rightarrow ME$		200 Bytes with alpha identifier is
			displayed with italic off
34	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.7.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
_	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	20	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.7.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

# Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
_	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.7.3

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.7.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

27.22.4.29.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

27.22.4.29.2.8 RECEIVE DATA (support of Text Attribute – Underline On)

27.22.4.29.2.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.29.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.8.4 Method of test

27.22.4.29.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP Port number: 44444

27.22.4.29.2.8.4.2 Procedure

# Expected sequence 2.8 (RECEIVE DATA, with Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
		1.1.1 PENDING	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP EVENT LIST	
-	IVIE → UICC	1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
		CHANNEL 1.1.1	
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
		1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	[Company of montones of acceptable]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	
15	ME LICE	(immediate) 1.1.1 Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
13	$ME \rightarrow USS$	Ichannel 1	[10 retrieve ivic s port ridiriber]
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
		(immediate) 1.1.1	, , ,
17	$USS \to ME$	Transfer of 800 Bytes data to the ME through	
		channel 1 using the ME's port number, which was	
40		retrieved in step 15	(000 LB (
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(800 kBytes of data in the ME buffer)
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
10	OICC - WIL	DATA 2.8.1	
20	$ME \rightarrow UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.8.1	200 Bytes with alpha identifier is
			displayed with underline on
22		TERMINAL RESPONSE: RECEIVE DATA 2.8.1	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
24	ME LUCC	DATA 2.8.2 FETCH	
25	$\begin{array}{c} ME \to UICC \\ UICC \to ME \end{array}$		200 Bytes with alpha identifier is
23		NOACTIVE COMMAND: RECEIVE DATA 2.0.2	displayed with underline off
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.8.1	
27	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.8.1	
28	$ME \rightarrow UICC$	FETCH	
29	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.8.1	200 Bytes with alpha identifier is
20	ME	TERMINIAL DECRONICE: DECENTE DATA OCA	displayed with underline on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.8.1	
31	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.3	
32	ME → UICC	FETCH	
33	$VICC \rightarrow ME$		200 Bytes with alpha identifier is
	5155 72		displayed with underline off
34	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.8.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.8.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	40	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.8.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

# Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.8.3

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

## TERMINAL RESPONSE: RECEIVE DATA 2.8.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
_	B6	81	C8	00	01	02		C7	B7	01	FF	

27.22.4.29.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

27.22.4.29.2.9 RECEIVE DATA (support of Text Attribute – Strikethrough On)

27.22.4.29.2.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.29.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.9.4 Method of test

27.22.4.29.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

27.22.4.29.2.9.4.2 Procedure

# Expected sequence 2.9 (RECEIVE DATA, with Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
_		1.1.1 PENDING	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
4	ME LUCC	1.1.1  TERMINAL RESPONSE: SET UP EVENT LIST	
4	$ME \rightarrow UICC$	1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
		CHANNEL 1.1.1	oce miliai conditions
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
		1.1.1	
8	$ME \rightarrow USER$	The ME may display channel opening information	
9	$ME \rightarrow USS$	PDP context activation request	
10	$USS \to ME$	PDP context activation accept	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
		1.1.1A	
		OF	
		TERMINAL RESPONSE: OPEN CHANNEL	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
12	OICC - WIL	DATA 1.1.1	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	
		(immediate) 1.1.1	
15	$ME \rightarrow USS$	Transfer of 8 Bytes of data to the USS through	[To retrieve ME's port number]
		channel 1	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
17	LIGO ME	(immediate) 1.1.1	
17	$USS \to ME$	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was	
		retrieved in step 15	
18	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Data	(800 Bytes of data in the ME buffer)
	,	available 2.1.1	(555 = 555
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.9.1	
20	$ME \rightarrow UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.9.1	200 Bytes with alpha identifier is
00	NAT 11100	TERMINIAL DECRONOS: DECENTS DATA COA	displayed with strikethrough on
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	
23	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.2	
24	ME → UICC	FETCH	
25	UICC → ME		200 Bytes with alpha identifier is
	3.00 / WL		displayed with strikethrough off
26	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	
27	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
		DATA 2.9.1	
28	$ME \rightarrow UICC$	FETCH	
29	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA 2.9.1	200 Bytes with alpha identifier is
20	ME LUGG	TEDMINIAL DECOMPCE DECEME DATA CO. 4	displayed with strikethrough on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	
31	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.3	
32	ME → UICC	FETCH	
33	$UICC \to ME$		200 Bytes with alpha identifier is
	JIJJ → IVIE		displayed with strikethrough off
34	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	, ,

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.9.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

1

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	80	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.9.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

PROACTIVE COMMAND: RECEIVE DATA 2.9.3

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.9.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

27.22.4.29.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

27.22.4.29.2.10 RECEIVE DATA (support of Text Attribute – Foreground and Background Colour)

27.22.4.29.2.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.29.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.29.2.10.4 Method of test

27.22.4.29.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP Port number: 44444

## 27.22.4.29.2.10.4.2 Procedure

# Expected sequence 2.10 (RECEIVE DATA, with Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
		1.1.1 PENDING	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST	
1	ME	1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
	0100 / IIIL	CHANNEL 1.1.1	
6	$ME \to UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
		1.1.1	
8		The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
4.0		DATA 1.1.1	
13	ME → UICC	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	$ME \rightarrow USS$		[To retrieve ME's port number]
1.0	WIE 7000	channel 1	[10 Totalovo ME o port Hambor]
16	$ME \to UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
		(immediate) 1.1.1	
17	$USS \to ME$	Transfer of 400 Bytes data to the ME through	
		channel 1 using the ME's port number, which was	
18	$ME \to UICC$	retrieved in step 15 ENVELOPE: EVENT DOWNLOAD - Data	(400 Bytes of data in the ME buffer)
10	INIE → UICC	available 2.1.1	(400 Bytes of data in the ME buller)
19	$UICC \to ME$	PROACTIVE COMMAND PENDING: RECEIVE	
	· ··· <del>-</del>	DATA 2.10.1	
20	$ME \to UICC$	FETCH	
21	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA	200 Bytes with alpha identifier is
		2.10.1	displayed with foreground and
22	ME LUCC	TERMINAL RESPONSE: RECEIVE DATA 2.10.1	background colour
23	$ME \rightarrow UICC$ $UICC \rightarrow ME$	PROACTIVE COMMAND PENDING: RECEIVE	
23	OICC -> IVIE	DATA 2.10.2	
24	$ME \to UICC$	FETCH	
25	$UICC \to ME$	PROACTIVE COMMAND: RECEIVE DATA	200 Bytes with alpha identifier is
		2.10.2	displayed with ME"s default foreground
			and background colour
26	$ME \rightarrow UICC$	TERMINAL RESPONSE: RECEIVE DATA 2.10.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

#### PROACTIVE COMMAND: RECEIVE DATA 2.10.1

Logically:

Command details

Command number:

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0 Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.10.2

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.10.1

Logically:

Command details

Command number: 1

Command type: RECEIVE DATA

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel Data: 00 01 02 .. C7 (200 Bytes of data)

Channel data length: FF

#### Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02		C7	B7	01	FF	

## 27.22.4.29.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

#### 27.22.4.30 SEND DATA

# 27.22.4.30.1 SEND DATA (normal)

27.22.4.30.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.30.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

# 27.22.4.30.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (ME currently unable to process command); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);
- TERMINAL RESPONSE (Proactive USIM session terminated by the user);

to the UICC after the ME receives the SEND DATA proactive command. The TERMINAL RESPONSE sent back to the UICC is the result of the ME and the network capabilities against requested parameters by the UICC.

### 27.22.4.30.1.4 Method of test

#### 27.22.4.30.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

#### **GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format: UDP Port number: 44444

Data destination address 01.01.01.01

#### 27.22.4.30.1.4.2 Procedure

# Expected sequence 1.1 (SEND DATA, immediate mode)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	, , ,	
		opening information	
5		PDP context activation request	
6		PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN	
	11100 ME	CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
9	$ME \to UICC$	FETCH	
10		PROACTIVE COMMAND: SEND	
10	$UICC \to ME$		
11	ME  o USS	DATA (immediate) 1.1.1 Transfer of 8 Bytes of data to the	
' '	IVI⊏ → USS	USS through channel 1	
12	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
12	INIE → UICC	DATA (immediate) 1.1.1	[Continuate performed successfully]
		Dittirt (illilliculate) 1.1.1	

## PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV

D0	42	81	03	01	40	01	82	02	81	82	35
07	02	03	04	03	04	1F	02	39	02	03	E8
47	0A	06	54	65	73	74	47	70	02	72	73
0D	08	F4	55	73	65	72	4C	6F	67	0D	80
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

### Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

## PROACTIVE COMMAND: SEND DATA 1.1.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Coding:

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	21	B6
	08	00	01	02	03	04	05	06	07			

### TERMINAL RESPONSE: SEND DATA 1.1.1

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

# Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

# **Expected sequence 1.2 (SEND DATA, Store mode)**

		PROACTIVE COMMAND PENDING:	
2 M			
2   M			See initial conditions
_	/ 0.00	FETCH	
3 U		PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4 MI		The ME may display channel opening	
4   1011		information	
5 N		PDP context activation request	
6 U		PDP context activation accept	
		TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8 U		PROACTIVE COMMAND PENDING:	
		SEND DATA 1.2.1	
9 M	$1E \rightarrow UICC$	FETCH	
10 U		PROACTIVE COMMAND: SEND	Send 500 Bytes of data (200 + 200 + 100)
,,   ,,		DATA (store mode) 1.2.1	10 1 1 1 1 1
11 M		TERMINAL RESPONSE: SEND DATA (store mode) 1.2.1	[Command performed successfully]
12 U		PROACTIVE COMMAND PENDING:	
'-   "		SEND DATA 1.2.2	
13 M	$1E \rightarrow UICC$	FETCH	
14 U			[200 Bytes]
1,5 1,4		DATA (store mode) 1.2.2	10 1 1 1 1 1
15 M		TERMINAL RESPONSE: SEND DATA (store mode) 1.2.2	[Command performed successfully]
16 U		PROACTIVE COMMAND PENDING:	
		SEND DATA 1.2.3	
17 M		FETCH	
18 U			[100 Bytes]
1		DATA (Immediate mode) 1.2.3	
19 N		Transfer of 500 Bytes of data to the	
20 M		USS through channel 1 TERMINAL RESPONSE: SEND	[Command performed successfully]
20   101		DATA (Immediate mode) 1.2.3	[Command performed successfully]

# PROACTIVE COMMAND: SEND DATA 1.2.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 00 01 .. C7 (200 Bytes of data)

BE	R-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
		B6	81	C8	00	01		C7					

TERMINAL RESPONSE: SEND DATA 1.2.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
<u> </u>	B7	01	FF									

#### PROACTIVE COMMAND: SEND DATA 1.2.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: C8 C9 .. FF 00 01 .. 8F (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	C8	C9		FF	00	01		8F	

TERMINAL RESPONSE: SEND DATA 1.2.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

#### PROACTIVE COMMAND: SEND DATA 1.2.3

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Immediate mode

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 90 91 .. F3 (100 Bytes of data)

Coding:

BER-TLV:	D0	6F	81	03	01	43	01	82	02	81	21	B6
	64	90	91		F3							

### TERMINAL RESPONSE: SEND DATA 1.2.3

Logically:

Command details

Command number:

Command type: SEND DATA
Command qualifier: Immediate mode

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
•	B7	01	FF									

# Expected sequence 1.3 (SEND DATA, Store mode, Tx buffer fully used)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN	See initial conditions
'	0.00 /	CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL	
	0.00 / 1.1.2	1.1.1	
4	ME → USER	The ME may display channel opening	
		information	
5	$ME \to USS$	PDP context activation request	
6		PDP context activation accept	
7		TERMINAL RESPONSE: OPEN CHANNEL	[Command performed successfully]
		1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		DATA 1.3.1	
9		FETCH	0 14000 B + (14 1 1 + (000
10	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (store	Send 1000 Bytes of data by packet of 200
11	ME LUCC	mode) 1.3.1 TERMINAL RESPONSE: SEND DATA (store	Bytes [Command performed successfully]
''	$ME \rightarrow UICC$	mode) 1.3.1	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
'-	0100 7 1112	DATA 1.3.2	
13	$ME \rightarrow UICC$		
14		PROACTIVE COMMAND: SEND DATA (store	[200 Bytes]
		mode) 1.3.2	, , ,
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (store	[Command performed successfully]
		mode) 1.3.2	
16	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
1		DATA 1.3.3	
17		FETCH	
18	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (store	[200 Bytes]
40	ME	mode) 1.3.3	
19	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3	[Command performed successfully]
20	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
20		DATA 1.3.4	
21	$ME \rightarrow UICC$	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA (store	[200 Bytes]
1		mode) 1.3.4	7
23	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (store	[Command performed successfully]
		mode) 1.3.4	
24	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		DATA 1.3.5	
25	ME → UICC	FETCH	[000 But al
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	[200 Bytes]
27	ME LICC	(immediate) 1.3.5 Transfer of 1000 Bytes of data to the USS	
27	$ME \rightarrow USS$	through channel 1	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
	WIL / 0100	(immediate) 1.3.5	[ Straine performed adoptionally]

# PROACTIVE COMMAND: SEND DATA 1.3.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA Command qualifier: Store mode

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	00	01	02		C7				

TERMINAL RESPONSE: SEND DATA 1.3.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

PROACTIVE COMMAND: SEND DATA 1.3.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: C8 C9 CA .. FF 00 01 .. 8F (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	C8	C9	CA		FF	00	02		8F

TERMINAL RESPONSE: SEND DATA 1.3.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

#### PROACTIVE COMMAND: SEND DATA 1.3.3

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 90 91 .. FF 00 01 .. 57 (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
_	B6	81	C8	90	91		FF	00	01		57	

#### TERMINAL RESPONSE: SEND DATA 1.3.3

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

## PROACTIVE COMMAND: SEND DATA 1.3.4

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 58 59 .. FF 00 01 .. 1F (200 Bytes of data)

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	58	59		FF	00	01		1F	

TERMINAL RESPONSE: SEND DATA 1.3.4

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Store mode

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: 200 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
_	B7	01	C8									

#### PROACTIVE COMMAND: SEND DATA 1.3.5

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 20 21 .. E7 (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	01	82	02	81	21
	B6	81	C8	20	21		E7					

TERMINAL RESPONSE: SEND DATA 1.3.5

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

# Expected sequence 1.4 (SEND DATA, 2 consecutive SEND DATA Store mode)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$		See initial conditions
		CHANNEL 1.1.1	
2	ME → UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel opening linformation	
5	$ME \to USS$	PDP context activation request	
6		PDP context activation accept	
7	$ME \rightarrow UICC$		[Command performed successfully]
		1.1.1A or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8		PROACTIVE COMMAND PENDING: SEND DATA 1.3.1	
9	ME → UICC		0 14000 B / / / / / / / / / / / / / / / / /
10	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	Send 1000 Bytes of data by packet of 200 Bytes
11	$ME \rightarrow UICC$	(store mode) 1.3.1 TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1	[Command performed successfully]
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		DATA 1.3.2	
13	ME → UICC		[200 D. 41
14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2	[200 Bytes]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2	[Command performed successfully]
16	$UICC \to ME$	PROÁCTIVE COMMAND PENDING: SEND DATA 1.3.3	
17		FETCH	
18	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	[200 Bytes]
19	$ME \rightarrow UICC$	(store mode) 1.3.3 TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3	[Command performed successfully]
20	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.3.4	
21		FETCH	
22	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	[200 Bytes]
23	$ME \rightarrow UICC$	(store mode) 1.3.4 TERMINAL RESPONSE: SEND DATA (store mode) 1.3.4	[Command performed successfully]
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND	
		DATA 1.3.5	
25		FETCH	1000 D / 1
26	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (immediate) 1.3.5	[200 Bytes]
27	$ME \rightarrow USS$	Transfer of 1000 Bytes of data to the USS through channel 1	
28	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (immediate) 1.3.5	[Command performed successfully]
29	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.3.1	
30		FETCH	
31	UICC → ME	PROACTIVE COMMAND: SEND DATA	Send 1000 Bytes of data by packet of 200 Bytes
32	$ME \rightarrow UICC$	(store mode) 1.3.1 TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1	[Command performed successfully]
33	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.3.2	
34	$ME \rightarrow UICC$	FETCH	
35	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2	[200 Bytes]
36	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2	[Command performed successfully]

37	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.3.3	
38	$ME \rightarrow UICC$		
39		PROACTIVE COMMAND: SEND DATA (store mode) 1.3.3	[200 Bytes]
40	$ME \to UICC$	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3	[Command performed successfully]
41	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 1.3.4	
42	$ME \rightarrow UICC$	FETCH	
43	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	[200 Bytes]
		(store mode) 1.3.4	
44	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA (store	[Command performed successfully]
		mode) 1.3.4	
45	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND	
		DATA 1.3.5	
46	$ME \rightarrow UICC$	FETCH	
47	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	[200 Bytes]
		(immediate) 1.3.5	
48	$ME \to USS$	Transfer of 1000 Bytes of data to the USS	
		through channel 1	
49	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
		(immediate) 1.3.5	

# Expected sequence 1.5 (SEND DATA, immediate mode with a bad channel identifier)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
		opening information	
5	$ME \rightarrow USS$	PDP context activation request	
6		PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 1.5.1	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	
		DATA (immediate) 1.5.1	
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Invalid channel number]
		DATA (immediate) 1.5.1	

# PROACTIVE COMMAND: SEND DATA 1.5.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 2

Channel Data

Channel Data :  $00\ 01\ ...\ 07\ (8\ Bytes\ of\ data)$ 

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	22	B6
	08	00	01	02	03	04	05	06	07			

TERMINAL RESPONSE: SEND DATA 1.5.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Bearer Independent Protocol error (3A)
Additional Result: Channel identifier not valid (03)

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	02	3A
	03											

## **Expected sequence 1.6 Void**

27.22.4.30.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.5.

27.22.4.30.2 SEND DATA (support of Text Attribute)

27.22.4.30.2.1 SEND DATA (support of Text Attribute – Left Alignment)

27.22.4.30.2.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.30.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.1.4 Method of test

27.22.4.30.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

27.22.4.30.2.1.4.2 Procedure

# **Expected sequence 2.1 (SEND DATA with Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	L / 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
4	ME LIGED	CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel opening information	
5	$ME \to USS$	PDP context activation request	
6		PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN	[Command performed successfully]
	/ 0.00	CHANNEL 1.1.1A	,,
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 2.1.1	
9	ME → UICC	FETCH	
10		PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with left
10		DATA 2.1.1	alignment]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.1.1	
12	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.1.2	
13	L / 0.00	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND	[Message shall be formatted without left
		DATA 2.1.2	alignment. Remark: If left alignment is the ME"s default alignment as declared in table
			A.2/22, no alignment change will take place]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
	, 5.50	DATA (immediate) 2.1.1	[

PROACTIVE COMMAND: SEND DATA 2.1.1

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold On, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
_	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

#### PROACTIVE COMMAND: SEND DATA 2.1.2

#### Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07		

## TERMINAL RESPONSE: SEND DATA 2.1.1

### Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## 27.22.4.30.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

27.22.4.30.2.2 SEND DATA (support of Text Attribute – Center Alignment)

27.22.4.30.2.2.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.30.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.2.4 Method of test

#### 27.22.4.30.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04

Mean throughput class: 31 Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

27.22.4.30.2.2.4.2 Procedure

# Expected sequence 2.2 (SEND DATA with Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
_		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
_	ME UOO	opening information	
5		PDP context activation request	
6	USS → ME	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
	OIOO / IVIL	PENDING: SEND DATA 2.2.1	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with center
		DATA 2.2.1	alignment]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.2.1	
12	$UICC \to ME$		
_	, 0.00	. = . *	
14	$UICC \to ME$		
		DATA 2.2.2	
15	ME VIICC	TERMINAL RESPONSE: SEND	
13	IVIE → UICC		[Continuate performed successfully]
12 13 14	$\begin{array}{c} \text{UICC} \rightarrow \text{ME} \\ \text{ME} \rightarrow \text{UICC} \\ \text{UICC} \rightarrow \text{ME} \end{array}$		[Message shall be formatted without cent alignment. Remark: If center alignment is ME"s default alignment as declared in tak A.2/22, no alignment change will take pla [Command performed successfully]

# PROACTIVE COMMAND: SEND DATA 2.2.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Center Alignment, Normal Font, Bold On, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	01	B4								

### PROACTIVE COMMAND: SEND DATA 2.2.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	80	00	01	02	03	04	05	06	07		

## TERMINAL RESPONSE: SEND DATA 2.2.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	F									

# 27.22.4.30.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

27.22.4.30.2.3 SEND DATA (support of Text Attribute – Right Alignment)

27.22.4.30.2.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.30.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.3.4 Method of test

27.22.4.30.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

# 27.22.4.30.2.3.4.2 Procedure

# Expected sequence 2.3 (SEND DATA with Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \rightarrow ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
5	ME LIGO	opening information	
_	ME → USS	PDP context activation request	
6 7	USS → ME	PDP context activation accept TERMINAL RESPONSE: OPEN	[Command parformed augeocafully]
/	$ME \rightarrow UICC$	CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1B	
8	$UICC \rightarrow ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.3.1	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with right
		DATA 2.3.1	alignment]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.3.1	
12	$UICC \to ME$	PROACTIVE COMMAND	
13	ME LUCC	PENDING: SEND DATA 2.3.2	
14	/ 0.00	FETCH PROACTIVE COMMAND: SEND	[Manage aboll he formatted without right
14	$UICC \to ME$	DATA 2.3.2	[Message shall be formatted without right alignment. Remark: If right alignment is the
		DATA 2.3.2	ME"s default alignment as declared in table
			A.2/22, no alignment change will take place]
15	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.3.1	

## PROACTIVE COMMAND: SEND DATA 2.3.1

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Right Alignment, Normal Font, Bold On, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	80	00	01	02	03	04	05	06	07	D0	04
	00	0B	02	B4								

#### PROACTIVE COMMAND: SEND DATA 2.3.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.3.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

27.22.4.30.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

27.22.4.30.2.4 SEND DATA (support of Text Attribute – Large Font Size)

27.22.4.30.2.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.30.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.4.4 Method of test

27.22.4.30.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format: UDP Port number: 44444

Data destination address 01.01.01.01

# 27.22.4.30.2.4.4.2 Procedure

# Expected sequence 2.4 (SEND DATA with Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
_	ME 1100	opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	[O
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.4.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with large
	0.00 /	DATA 2.4.1	font size]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.4.1	
12	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.4.2	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with normal
		DATA 2.4.2	font size]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
40		DATA (immediate) 2.4.1	
16	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 2.4.1	
17	ME → UICC	FETCH	
18	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with large
10		DATA 2.4.1	font size
19	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
10	IVIL 70100	DATA (immediate) 2.4.1	[Command ponomica saccessiany]
20	$UICC \to ME$	PROACTIVE COMMAND	
	0.00 /	PENDING: SEND DATA 2.4.3	
21	$ME \rightarrow UICC$	FETCH	
22	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with normal
		DATA 2.4.3	font size]
23	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
<u> </u>		DATA (immediate) 2.4.1	

# PROACTIVE COMMAND: SEND DATA 2.4.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11 Formatting mode: Left Alignment, Large Font, Bold On, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	В6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	04	B4								

#### PROACTIVE COMMAND: SEND DATA 2.4.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	В6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

### PROACTIVE COMMAND: SEND DATA 2.4.3

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	В6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.4.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

### Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

856

#### 27.22.4.30.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

27.22.4.30.2.5 SEND DATA (support of Text Attribute – Small Font Size)

27.22.4.30.2.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.30.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

## 27.22.4.30.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to the small font size text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.5.4 Method of test

27.22.4.30.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01 27.22.4.30.2.5.4.2 Procedure

# Expected sequence 2.5 (SEND DATA with Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
	ME LIGED	CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel opening information	
5	$ME \to USS$	PDP context activation request	
6	$USS \rightarrow ME$	PDP context activation request	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
'	IVIE → UICC	CHANNEL 1.1.1A or TERMINAL	
		RESPONSE: OPEN CHANNEL	
		1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.5.1	
9	$ME \to UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with small
		DATA 2.5.1	font size]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
40	LU00 ME	DATA (immediate) 2.5.1	
12	$UICC \to ME$	PROACTIVE COMMAND PENDING: SEND DATA 2.5.2	
13	$ME \to UICC$	FETCH	
14		PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with normal
'-	OIOO IVIL	DATA 2.5.2	font size]
15	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.5.1	, , ,
16	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.5.1	
17	$ME \rightarrow UICC$	FETCH	
18	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with small
4.0		DATA 2.5.1	font size]
19	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
20	LUCC ME	DATA (immediate) 2.5.1 PROACTIVE COMMAND	
20	$UICC \to ME$	PENDING: SEND DATA 2.5.3	
21	$ME \rightarrow UICC$	FETCH	
22	$UICC \rightarrow ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with normal
	SIOO - IVIL	DATA 2.5.3	font size]
23	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.5.1	

PROACTIVE COMMAND: SEND DATA 2.5.1

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Small Font, Bold On, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
_	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	08	B4								

#### PROACTIVE COMMAND: SEND DATA 2.5.2

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	В6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

## PROACTIVE COMMAND: SEND DATA 2.5.3

#### Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.5.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

27.22.4.30.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

27.22.4.30.2.6 SEND DATA (support of Text Attribute – Bold On)

27.22.4.30.2.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.30.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.6.4 Method of test

27.22.4.30.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

#### **GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format: UDP Port number: 44444

Data destination address 01.01.01.01

# 27.22.4.30.2.6.4.2 Procedure

# Expected sequence 2.6 (SEND DATA with Text Attribute – Bold On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
_	ME 1100	opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
8	UICC → ME	PROACTIVE COMMAND	
"	OICC - IVIL	PENDING: SEND DATA 2.6.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with Bold
	OIOO / IVIL	DATA 2.6.1	on]
11	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.6.1	, , ,
12	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.6.2	
13	$ME \rightarrow UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with bold
		DATA 2.6.2	off]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
40		DATA (immediate) 2.6.1	
16	$UICC \to ME$	PROACTIVE COMMAND	
17	ME	PENDING: SEND DATA 2.6.1 FETCH	
18	ME → UICC		Colone identifier shall be displayed with hold
10	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA 2.6.1	[alpha identifier shall be displayed with bold on]
19	ME → UICC	TERMINAL RESPONSE: SEND	[Command performed successfully]
13	IVIE - OICC	DATA (immediate) 2.6.1	[Command performed successibility]
20	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.6.3	
21	$ME \rightarrow UICC$	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with bold
		DATA 2.6.3	off]
23	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.6.1	

# PROACTIVE COMMAND: SEND DATA 2.6.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
_	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	10	B4								

#### PROACTIVE COMMAND: SEND DATA 2.6.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	В6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

### PROACTIVE COMMAND: SEND DATA 2.6.3

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	В6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.6.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

### Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

27.22.4.30.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

27.22.4.30.2.7 SEND DATA (support of Text Attribute – Italic On)

27.22.4.30.2.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.30.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.7.4 Method of test

27.22.4.30.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

**Bearer Parameters** 

Precedence Class: 03

Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

27.22.4.30.2.7.4.2 Procedure

# Expected sequence 2.7 (SEND DATA with Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments			
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions			
		PENDING: OPEN CHANNEL 1.1.1				
2	$ME \rightarrow UICC$	FETCH				
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN				
		CHANNEL 1.1.1				
4	$ME \rightarrow USER$	The ME may display channel				
_		opening information				
5	ME → USS	PDP context activation request				
6	USS → ME	PDP context activation accept				
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]			
		CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL				
		1.1.1B				
8	$UICC \to ME$	PROACTIVE COMMAND				
		PENDING: SEND DATA 2.7.1				
9	$ME \to UICC$	FETCH				
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with Italic			
		DATA 2.7.1	on]			
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]			
		DATA (immediate) 2.7.1				
12	$UICC \to ME$	PROACTIVE COMMAND				
40		PENDING: SEND DATA 2.7.2				
13	ME → UICC	FETCH	Fallanda di da matifica a alca di la adica da constato da disconstato di constato  14	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA 2.7.2	[alpha identifier shall be displayed with italic off]
15	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]			
13	IVIE → UICC	DATA (immediate) 2.7.1				
16	$UICC \to ME$	PROACTIVE COMMAND				
	0.00 / III.	PENDING: SEND DATA 2.7.1				
17	$ME \rightarrow UICC$	FETCH				
18	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with italic			
		DATA 2.7.1	on]			
19	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]			
		DATA (immediate) 2.7.1				
20	$UICC \to ME$	PROACTIVE COMMAND				
0.4	ME	PENDING: SEND DATA 2.7.3				
21	ME → UICC	FETCH	Talaba identifies aball he dienleved with its ii-			
22	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA 2.7.3	[alpha identifier shall be displayed with italic off]			
23	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]			
23	IVIE → UICC	DATA (immediate) 2.7.1	[Command performed successfully]			
L		Dittit (illilliculate) Z.I.I				

PROACTIVE COMMAND: SEND DATA 2.7.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	80	00	01	02	03	04	05	06	07	D0	04
	00	0B	20	B4								

#### PROACTIVE COMMAND: SEND DATA 2.7.2

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

## PROACTIVE COMMAND: SEND DATA 2.7.3

#### Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	В6	08	00	01	02	03	04	05	06	07	_	_

TERMINAL RESPONSE: SEND DATA 2.7.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

#### 27.22.4.30.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

27.22.4.30.2.8 SEND DATA (support of Text Attribute – Underline On)

27.22.4.30.2.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.30.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.8.4 Method of test

27.22.4.30.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.30.2.8.4.2 Procedure

# Expected sequence 2.8 (SEND DATA with Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
_		opening information	
5	$ME \rightarrow USS$	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
"	OICC - IVIL	PENDING: SEND DATA 2.8.1	
9	$ME \rightarrow UICC$	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
	OIOO / IVIL	DATA 2.8.1	underline on]
11	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.8.1	
12	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.8.2	
13	$ME \to UICC$	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
		DATA 2.8.2	underline off]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
40		DATA (immediate) 2.8.1	
16	$UICC \to ME$	PROACTIVE COMMAND	
17	ME LUCC	PENDING: SEND DATA 2.8.1 FETCH	
18	$ME \to UICC$ $UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
10	OICC → IVIE	DATA 2.8.1	[alpha identifier shall be displayed with underline on]
19	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
13	IVIL -> OICC	DATA (immediate) 2.8.1	[Command performed successfully]
20	$UICC \to ME$	PROACTIVE COMMAND	
	OIOO / IVIL	PENDING: SEND DATA 2.8.3	
21	$ME \to UICC$	FETCH	
22	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
	. –	DATA 2.8.3	underline off]
23	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.8.1	·

## PROACTIVE COMMAND: SEND DATA 2.8.1

# Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	40	B4								

#### PROACTIVE COMMAND: SEND DATA 2.8.2

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	В6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

#### PROACTIVE COMMAND: SEND DATA 2.8.3

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	В6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.8.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

#### Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

27.22.4.30.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

27.22.4.30.2.9 SEND DATA (support of Text Attribute – Strikethrough On)

27.22.4.30.2.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.30.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.9.4 Method of test

27.22.4.30.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol:02 (IP)

**GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01 27.22.4.30.2.9.4.2 Procedure

# Expected sequence 2.9 (SEND DATA with Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
_		opening information	
5		PDP context activation request	
6	$USS \to ME$	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
		CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL	
		1.1.1B	
8	$UICC \to ME$	PROACTIVE COMMAND	
	OIOO IVIL	PENDING: SEND DATA 2.9.1	
9	$ME \rightarrow UICC$	FETCH	
10		PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
		DATA 2.9.1	strikethrough on]
11	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.9.1	
12	$UICC \to ME$	PROACTIVE COMMAND	
4.0		PENDING: SEND DATA 2.9.2	
13	, 0.00	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
15	ME . LUCC	DATA 2.9.2 TERMINAL RESPONSE: SEND	strikethrough off] [Command performed successfully]
15	$ME \to UICC$	DATA (immediate) 2.9.1	[Confinant penormed successiony]
16	$UICC \to ME$	PROACTIVE COMMAND	
10		PENDING: SEND DATA 2.9.1	
17	$ME \to UICC$	FETCH	
18	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
		DATA 2.9.1	strikethrough on]
19	$ME \to UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.9.1	
20	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.9.3	
21	ME → UICC	FETCH	
22	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
23	ME LUCC	DATA 2.9.3 TERMINAL RESPONSE: SEND	strikethrough off] [Command performed successfully]
23	$ME \rightarrow UICC$	DATA (immediate) 2.9.1	[Command pendimed successibily]
<u> </u>		DATA (	

PROACTIVE COMMAND: SEND DATA 2.9.1

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
-	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	80	B4								

#### PROACTIVE COMMAND: SEND DATA 2.9.2

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	В6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

## PROACTIVE COMMAND: SEND DATA 2.9.3

#### Logically:

Command details

Command number:

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

#### Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.9.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
_	B7	01	FF									

27.22.4.30.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

27.22.4.30.2.10 SEND DATA (support of Text Attribute – Foreground and Background Colour)

27.22.4.30.2.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.30.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.10.4 Method of test

27.22.4.30.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

#### **GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format: UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.30.2.10.4.2 Procedure

# Expected sequence 2.10 (SEND DATA with Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
		CHANNEL 1.1.1	
4	$ME \rightarrow USER$	The ME may display channel	
5	ME UOO	opening information	
_	ME → USS	PDP context activation request	
6 7	USS → ME	PDP context activation accept	[Company on the support of a company of the last
/	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL	[Command performed successfully]
		RESPONSE: OPEN CHANNEL	
		1.1.1B	
8	$UICC \rightarrow ME$	PROACTIVE COMMAND	
	OIOO / WIL	PENDING: SEND DATA 2.10.1	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with
		DATA 2.10.1	foreground and background colour according
			to the text attribute configuration]
11	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.10.1	
12	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SEND DATA 2.10.2	
13	/ 0.00	FETCH	
14	$UICC \to ME$	PROACTIVE COMMAND: SEND	[alpha identifier shall be displayed with ME"s
15	ME	DATA 2.10.2	default foreground and background colour]
15	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND	[Command performed successfully]
		DATA (immediate) 2.10.1	

## PROACTIVE COMMAND: SEND DATA 2.10.1

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
_	0B	53	65	6E	64	20	44	61	74	61	20	31
	В6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

PROACTIVE COMMAND: SEND DATA 2.10.2

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	В6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.10.1

## Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

#### 27.22.4.30.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

## 27.22.4.31 GET CHANNEL STATUS

## 27.22.4.31.1 Definition and applicability

See clause 3.2.2.

# 27.22.4.31.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

# 27.22.4.31.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC after the ME receives the GET STATUS proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

#### 27.22.4.31.4 Method of test

#### 27.22.4.31.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

#### **GPRS** Parameters

Network access name: TestGp.rs

User login: UserLog User password: UserPwd UICC/ME interface transport level

Transport format: UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.31.4.2 Procedure

## Expected sequence 1.1 (GET STATUS, without any BIP channel opened)

For that test, no channel has been opened.

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: GET CHANNEL	
		STATUS 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: GET	
		STATUS 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE GET	[Command performed successfully]
		STATUS 1.1.1 A	
		Or	
		TERMINAL RESPONSE: GET	
		STATUS 1.1.1B	
		Or	
		TERMINAL RESPONSE: GET	
		STATUS 1.1.1C	

PROACTIVE COMMAND: GET STATUS 1.1.1

Logically:

Command details

Command number:

Command type: GET STATUS

1

Command qualifier: RFU

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV: D0 09	81 03	01 44 C	00 82 02	81 82
----------------	-------	---------	----------	-------

## TERMINAL RESPONSE: GET STATUS 1.1.1A

Logically:

Command details

Command number: 1

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: ME Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00

#### TERMINAL RESPONSE: GET STATUS 1.1.1B

Logically:

Command details

Command number: 1

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel status: No Channel available, link not established or PDP context not activated

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	B8	02	00	00								

# TERMINAL RESPONSE: GET STATUS 1.1.1C

Logically:

Command details

Command number:

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: ME

Destination device: SIM

Result

General Result: Command performed successfully

Channel status

Channel 1 status: Channel identifier 1, Link not established or PDP context not activated

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

.

.

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	Note1											

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. Each channel status TLV coding shall indicate the corresponding channel identifier and shall state "Link not established or PDP context not activated". As an example, if the mobile supports two channels then the corresponding channel status data objects coding would be: 'B8 02 01 00 B8 02 02 00'.

# Expected sequence 1.2 (GET STATUS, with a BIP channel currently opened)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL	
		1.1.1	
2	/ 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
1	1100	CHANNEL 1.1.1	
4		PDP context activation request	
5		PDP context activation accept	[O
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL	[Command performed successfully]
		RESPONSE: OPEN CHANNEL	
		1.1.1B	
7	$UICC \to ME$	PROACTIVE COMMAND	
'	0.00 /	PENDING: GET CHANNEL	
		STATUS 1.2.1	
8	$ME \rightarrow UICC$	FETCH	
9	$UICC \to ME$	PROACTIVE COMMAND: GET	
		STATUS 1.2.1	
10	$ME \rightarrow UICC$	TERMINAL RESPONSE GET	[Command performed successfully]
		STATUS 1.2.1 A	
		Or	
		TERMINAL RESPONSE: GET	
		STATUS 1.2.1B	

#### PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

## Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV

D0	42	81	03	01	40	01	82	02	81	82	35
07	02	03	04	03	04	1F	02	39	02	03	E8
47	0A	06	54	65	73	74	47	70	02	72	73
0D	08	F4	55	73	65	72	4C	6F	67	0D	08
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

# PROACTIVE COMMAND: GET STATUS 1.2.1

# Logically:

Command details

Command number: 1

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	44	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

# TERMINAL RESPONSE: GET STATUS 1.2.1A

#### Logically:

Command details

Command number: 1

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel status: Channel 1 open, link established or PDP context activated

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
_	B8	02	81	00								

TERMINAL RESPONSE: GET STATUS 1.2.1B

Logically:

Command details

Command number: 1

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: ME Destination device: SIM

Result

General Result: Command performed successfully

Channel status

Channel 1 status: Channel identifier 1 open, Link established or PDP context activated

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

.

.

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	Note1											

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. The channel status TLV coding of the opened channel shall state "Link established or PDP context activated". Each other channel status TLV coding shall indicate the corresponding channel identifier and shall state "Link is not established or PDP context not activated". As an example, if the mobile supports two channels and channel 1 is opened then the corresponding channel status data objects coding would be : 'B8 02 81 00 B8 02 02 00'.

# Expected sequence 1.3 (GET STATUS, after a link dropped)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	[Command performed successfully]
5	$UICC \to ME$	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	$ME \rightarrow USS$	PDP context activation request	
9		PDP context activation accept	
10	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
11		DROP LINK	
12	$ME \rightarrow UICC$	ENVELOPE EVENT DOWNLOAD: CHANNEL STATUS 1.3.1	[Link dropped]
13		PROACTIVE COMMAND PENDING: GET STATUS 1.3.1	
14	$ME \rightarrow UICC$		
15		PROACTIVE COMMAND: GET STATUS 1.3.1	
16	$ME \rightarrow UICC$	TERMINAL RESPONSE: GET STATUS 1.3.1A Or	[Command performed successfully]
		TERMINAL RESPONSE: GET STATUS 1.3.1B Or	
		TERMINAL RESPONSE: GET STATUS 1.3.1C	
		TERMINAL RESPONSE: GET STATUS 1.3.1D Or	
		TERMINAL RESPONSE: GET STATUS 1.3.1E	

TERMINAL RESPONSE: GET STATUS 1.3.1A

Same as TERMINAL RESPONSE: GET STATUS 1.1.1A

TERMINAL RESPONSE: GET STATUS 1.3.1B

Same as TERMINAL RESPONSE: GET STATUS 1.1.1B

TERMINAL RESPONSE: GET STATUS 1.3.1C

Same as TERMINAL RESPONSE: GET STATUS 1.1.1C

TERMINAL RESPONSE: GET STATUS 1.3.1D

Logically:

Command details

Command number:

Command type: GET Command qualifier: RFU **GET STATUS** 

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel status: Channel 1, link dropped

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	B8	02	01	05								

TERMINAL RESPONSE: GET STATUS 1.3.1E

Logically:

Command details

Command number: 1

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: ME Destination device: SIM

Result

General Result: Command performed successfully

Channel status

Channel 1 status: Channel identifier 1, link dropped

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

•

.

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
'-	B8	02	01	05	Note1							

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. Each channel status TLV coding except that one for which the link was dropped by the SS shall indicate the corresponding channel identifier and shall state "Link not established or PDP context not activated". As an example, if the mobile supports two channels then the corresponding channel status data objects coding would be: 'B8 02 01 05 B8 02 02 00'.

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Channel Status

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82
	99	01	0A								

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## ENVELOPE EVENT DOWNLOAD: CHANNEL STATUS 1.3.1

Logically:

Event list

Event list: Channel Status

Device identities

Source device: ME
Destination device: UICC

Channel status

Channel status: Channel 1, link dropped

Coding:

BER-TLV:	D6	0B	99	01	0A	82	02	82	81	B8	02	01
	05											

PROACTIVE COMMAND: GET STATUS 1.3.1

Logically:

Command details

Command number:

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	44	00	82	02	81	82
DEIX IEV.		00	0.	00	0.		00	02	02	0.	02

# 27.22.4.31.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

## 27.22.5 Data Download to UICC

## 27.22.5.1 SMS-PP Data Download

## 27.22.5.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.5.1.2 Conformance requirement

The ME shall support the Proactive UICC: SMS-PP Data Download facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 7.1, clause 8.1, clause 8.7, clause 8.13 and clause 11.
- TS 31.115 [28] clause 4.
- TS 23.038 [7] clause 4..

# 27.22.5.1.3 Test purpose

To verify that the ME transparently passes the "data download via SMS Point-to-point" messages to the UICC.

To verify that the ME returns the RP-ACK message back to the USS, if the UICC responds with '90 00' or '91 XX'.

To verify that the ME returns the RP-ERROR message back to the system Simulator, if the UICC responds with '62 XX' or '63 XX'.

To verify that the ME returns the response data from the UICC back to the USS in the TP-User-Data element of the RP-ACK message, if the UICC returns response data'.

## 27.22.5.1.4 Method of Test

## 27.22.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The "data download via SMS-PP" service is available in the USIM Service Table.

27.22.5.1.4.2 Procedure

# **Expected Sequence 1.1 (void)**

# **Expected Sequence 1.2 (SMS-PP Data Download, General Data Coding, Acknowledgement)**

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	SMS-PP Data Download Message	
2	ME → USER	1.2.1 The ME shall not display the message or alert the user of a short message waiting.	
3	$ME \to UICC$	ENVELOPE: SMS-PP DOWNLOAD 1.2.2	
4	$UICC \to ME$	SMS-PP Data Download UICC Acknowledgement 1.2.4	[SW1 / SW2 of '90 00'
5	ME → USS	SMS-PP Data Download UICC Acknowledgement 1.2.4 in the TP-User-Data element of the RP-ACK message. The values of protocol identifier and data coding scheme in RP-ACK shall be as in the original message.	

# **Expected Sequence 1.3 (SMS-PP Data Download, General Data Coding, FETCH, MORE TIME)**

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	SMS-PP Data Download Message	
2	$ME \to USER$	1.3.1 The ME shall not display the message or alert the user of a	
3	$ME \to UICC$	short message waiting ENVELOPE: SMS-PP DOWNLOAD 1.3.2	[SW1 / SW2 of '91 0B']
4	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: MORE TIME 1.3.4	
5	/ 000	RP-ACK	
6	$ME \rightarrow UICC$		
7	$UICC \to ME$	PROACTIVE COMMAND: MORE	
8	$ME \to UICC$	TIME 1.3.4 TERMINAL RESPONSE: MORE TIME 1.3.5	
9	$UICC \to ME$	PROACTIVE UICC SESSION ENDED	

PROACTIVE COMMAND: MORE TIME 1.3.4

Logically:

Command details

Command number: 1

Command type: MORE TIME

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	02	00	82	02	81	82

TERMINAL RESPONSE: MORE TIME 1.3.5

## Logically:

Command details

Command number:

Command type: MORE TIME

Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

#### Coding:

BER-TLV:	81	03	01	02	00	82	02	82	81	83	01	00

## **Expected Sequence 1.4 (void)**

## SMS-PP (Data Download) Message 1.2.1 / 1.3.1

## Logically:

## SMS TPDU

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC
TP-RP TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI TP-UD field contains only the short message
TP-SRI A status report will not be returned to the SME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "1234"

TP-PID (U)SIM Data download

TP-DCS

Coding Group General Data Coding Compression Text is uncompressed

Message Class Class 2 (U)SIM Specific Message

Alphabet 8 bit data

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 13

TP-UD "Short Message"

#### Coding:

Coding	04	04	91	21	43	7F	16	89	10	10	00	00
	00	00	0D	53	68	6F	72	74	20	4D	65	73
	73	61	67	65								

## ENVELOPE: SMS-PP DOWNLOAD 1.2.2 / 1.3.2

## Logically:

## SMS-PP Download

Device identities

Source device: Network
Destination device: UICC

Address

TON International number

NPI "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

**SMS TPDU** 

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC

TP-RPTP-Reply-Path is not set in this SMS-DELIVER

TP-UDHI TP-UD field contains only the short message TP-SRI A status report will not be returned to the SME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan" Address value "1234"

TP-PID (U)SIM Data download

TP-DCS

Coding Group General Data Coding Compression Text is uncompressed

Message Class Class 2 (U)SIM Specific Message

Alphabet 8 bit data

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 13

TP-UD "Short Message"

#### Coding:

BER-TLV:	D1	2D	82	02	83	81	06	09	91	11	22	33
	44	55	66	77	F8	8B	1C	04	04	91	21	43
	7F	16	89	10	10	00	00	00	00	0D	53	68
	6F	72	74	20	4D	65	73	73	61	67	65	

## **Expected Sequence 1.5 (void)**

## Expected Sequence 1.6 (SMS-PP Data Download, with Data Coding / Message Class)

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	SMS-PP Data Download Message	
		1.6.1	
2	ME	The ME shall not display the	
		message or alert the user of a	
		short message waiting	
3	$ME \rightarrow UICC$	ENVELOPE: SMS-PP	
		DOWNLOAD 1.6.2	
4	$UICC \to ME$	SW1 / SW2 of '90 00'	
5	$ME \to USS$	RP-ACK	

#### SMS-PP (Data Download) Message 1.6.1

#### Logically:

**SMS TPDU** 

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC
TP-RP TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI TP-UD field contains only the short message
TP-SRI A status report will not be returned to the SME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "1234"

TP-PID (U)SIM Data download

TP-DCS

Coding Group Data Coding / Message Class

Message Coding 8 bit data

Message Class Class 2 (U)SIM Specific Message

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 13

TP-UD "Short Message"

Coding:

Coding	04	04	91	21	43	7F	F6	89	10	10	00	00
	00	00	0D	53	68	6F	72	74	20	4D	65	73
	73	61	67	65								

ENVELOPE: SMS-PP DOWNLOAD 1.6.2

Logically:

SMS-PP Download

Device identities

Source device: Network
Destination device: UICC

Address

TON International number

NPI "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC

TP-RPTP-Reply-Path is not set in this SMS-DELIVER

TP-UDHI TP-UD field contains only the short message TP-SRI A status report will not be returned to the SME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan" Address value "1234"

TP-PID (U)SIM Data download

TP-DCS

Coding Group Data Coding / Message Class

Message Coding 8 bit data

Message Class Class 2 (U)SIM Specific Message

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 13

TP-UD "Short Message"

Coding:

BER-TLV:	D1	2D	82	02	83	81	06	09	91	11	22	33
	44	55	66	77	F8	8B	1C	04	04	91	21	43
	7F	F6	89	10	10	00	00	00	00	0D	53	68
	6F	72	74	20	4D	65	73	73	61	67	65	

## **Expected Sequence 1.7 (SMS-PP Data Download error)**

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	SMS-PP Data Download Message	
2	ME → USER	1.2.1 The ME shall not display the message or alert the user of a short message waiting.	
3	$ME \rightarrow UICC$	ENVELOPE: SMS-PP DOWNLOAD 1.2.2	[SW1 / SW2 of '62 xx" or "63 xx"]
4	$UICC \to ME$	SMS-PP Data Download UICC Acknowledgement 1.2.4	
5	$ME \rightarrow UICC$	Retrieve RP-Error information provided by the USIM	
6	ME → USS	SMS-PP Data Download UICC Acknowledgement 1.2.4 in the TP-User-Data element of the RP-ERROR message. The values of protocol identifier and data coding scheme in RP-ERROR shall be as in the original message.	

SMS-PP Data Download UICC Acknowledgement 1.2.4

Coding:

Coding	50	68	69	6C	20	48	6F	6F	6B	65	72
--------	----	----	----	----	----	----	----	----	----	----	----

## Expected Sequence 1.8 (SMS-PP Data Download, General Data Coding, User Data Header payload)

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	SMS-PP Data Download Message	
		1.8.1	
2	ME	The ME shall not display the	
		message or alert the user of a	
		short message waiting	
3	$ME \rightarrow UICC$	ENVELOPE: SMS-PP	
		DOWNLOAD 1.8.2	
4	$UICC \to ME$	SW1 / SW2 of '90 00'	
5	$ME \to USS$	RP-ACK	

SMS-PP (Data Download) Message 1.8.1

Logically:

SMS TPDU

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC TP-RP TP-Reply-Path is not set in this SMS-DELIVER

TP-UDHI TP-UD field contains user data header and a short message

TP-SRI A status report will not be returned to the SME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "1234"

TP-PID (U)SIM Data download

TP-DCS

Coding Group Data Coding / Message Class

Message Coding 8 bit data

Message Class Class 2 (U)SIM Specific Message

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 30

TP-UD

TP-UDHL

IEI (U)SIM Toolkit Security Headers

IEIL 0

SM (8 bit data)

Command Packet Length: 25 Command Header Identifier: 0 Command Header Length: 13

Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity

Ciphering Key Identifier: Algorithm known implicitly by both entities
Key Identifier: Algorithm known implicitly by both entities

Toolkit Application Reference: Proprietary Toolkit Application

Counter: 1

Padding Counter: 0 (no padding is necessary)
Secure Data: 10 octets set to 'DC' (dummy data)

Coding:

Coding	44	04	91	21	43	7F	F6	89	10	10	00	00
	00	00	1E	02	70	00	00	19	00	0D	00	00
	00	00	BF	FF	00	00	00	00	00	01	00	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC			

## ENVELOPE: SMS-PP DOWNLOAD 1.8.2

## Logically:

SMS-PP Download

Device identities

Source device: Network
Destination device: UICC

Address

TON International number

NPI "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-DELIVER

TP-MMS No more messages waiting for the MS in this SC TP-RP TP-Reply-Path is not set in this SMS-DELIVER

TP-UD field contains user data header and a short message

TP-SRI A status report will not be returned to the SME

TP-OA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "1234"

TP-PID (U)SIM Data download

**TP-DCS** 

Coding Group Data Coding / Message Class

Message Coding 8 bit data

Message Class Class 2 (U)SIM Specific Message

TP-SCTS: 01/01/98 00:00:00 +0

TP-UDL 30

TP-UD

TP-UDHL 2

IEI (U)SIM Toolkit Security Headers

IEIL 0

SM (8 bit data)

Command Packet Length: 25 Command Header Identifier: 0 Command Header Length: 13

Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity

Ciphering Key Identifier: Algorithm known implicitly by both entities Key Identifier: Algorithm known implicitly by both entities

Toolkit Application Reference: Proprietary Toolkit Application

Counter: 1

Padding Counter: 0 (no padding is necessary)
Secure Data: 10 octets set to 'DC' (dummy data)

#### Coding:

BER-TLV:	D1	3E	82	02	83	81	06	09	91	11	22	33
	44	55	66	77	F8	8B	2D	44	04	91	21	43
	7F	F6	89	10	10	00	00	00	00	1E	02	70
	00	00	19	00	0D	00	00	00	00	BF	FF	00
	00	00	00	00	01	00	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC								

# 27.22.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.2 to 1.8.

## 27.22.5.2 Cell Broadcast Data Download

## 27.22.5.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.5.2.2 Conformance requirement

The ME shall support the Proactive UICC: Cell Broadcast Data Download facility as defined in:

- TS 31.111 [15] clause 5, clause 7.1.2, clause 8.5, clause 8.7 and clause 11.
- TS 31.115 [28] clause 5.
- TS 23.038 [7] clause 5.

## 27.22.5.2.3 Test purpose

To verify that the ME transparently passes the "data download via Cell Broadcast" messages to the UICC, which contain a message identifier found in  $EF_{CBMID}$ .

## 27.22.5.2.4 Method of Test

#### 27.22.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as Toolkit default with the following exeception:

EF PL shall contain an entry indicating "English".

A USS setting up only a GERAN or PCS 1900 cell shall be used for Expected sequence 1.1, 1.7 and 1.3.

A USS setting up only a UTRAN cell shall be used on and expected sequence 1.4, 1.5 and 1.6.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.5.2.4.2 Procedure

# Expected Sequence 1.1 (Cell Broadcast Data Download (GSM), ENVELOPE(CELL BROADCAST DOWNLOAD), ME does not display message)

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	CELL BROADCAST 1.1	Message identifier '10 01'
2	$ME \rightarrow UICC$	ENVELOPE (CELL	
		BROADCAST DOWNLOAD) 1.1	
3	$UICC \to ME$	SW1, SW2 '90 00'	

## Cell Broadcast Message 1.1

## Logically:

Message Content

Serial Number

Geographical scope: Cell wide, normal display mode

Message code: 1
Update number: 1
Message Identifier: "1001"

Data coding Scheme

Message Coding: English, language using the GSM 7 bit default alphabet

Page Parameter

Total number of pages: 1 Page number: 1

Content of message: "Cell Broadcast "...

#### Coding:

Coding	C0	11	10	01	01	11	C3	32	9B	0D	12	CA
	DF	61	F2	38	3C	A7	83	40	20	10	08	04
	02	81	40	20	10	08	04	02	81	40	20	10
	08	04	02	81	40	20	10	08	04	02	81	40
	20	10	08	04	02	81	40	20	10	08	04	02
	81	40	20	10	08	04	02	81	40	20	10	08
	04	02	81	40	20	10	80	04	02	81	40	20
	10	08	04	02								

## ENVELOPE: CELL BROADCAST DOWNLOAD 1.1

#### Logically:

Cell Broadcast Download

Device identities

Source device: Network
Destination device: UICC

Cell Broadcast page

Serial Number

Geographical scope: Cell wide, normal display mode

Message code: 1
Update number: 1
Message Identifier: "1001"

Data coding Scheme

Message Coding: English, language using the GSM 7 bit default alphabet

Page Parameter

Number of pages: 1 Page number: 1

Content of message: "Cell Broadcast "...

#### Coding:

BER-TLV:	D2	5E	82	02	83	81	8C	58	C0	11	10	01
	01	11	C3	32	9B	0D	12	CA	DF	61	F2	38
	3C	A7	83	40	20	10	08	04	02	81	40	20
	10	08	04	02	81	40	20	10	08	04	02	81
	40	20	10	08	04	02	81	40	20	10	08	04
	02	81	40	20	10	08	04	02	81	40	20	10
	08	04	02	81	40	20	10	08	04	02	81	40
	20	10	08	04	02	81	40	20	10	08	04	02

# **Expected Sequence 1.2 (void)**

# Expected Sequence 1.3 (Cell Broadcast (GSM), ME may display the message)

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	CELL BROADCAST 1.2	Message identifier '03 E7'
2a	ME → USER	ME may display the message	
2b	ME → UICC	ME shall not download the CB	
		message to the UICC using	
		ENVELOPE (CELL BROADCAST	
		DOWNLOAD)	
3	USER → ME	The user shall use a MMI dependent	[only if message has not been displayed in
		procedure to initiate the display of	step 2a]
		the received CB message	
4	ME → USER	ME displays the message	[only if message has not been displayed in
			step 2a]

## Cell Broadcast Message 1.2

## Logically:

Message Content

Serial Number

Geographical scope: Cell wide, normal display mode

Message code: 1
Update number: 1
Message Identifier: "03E7"

Data coding Scheme

Message Coding: English, language using the GSM 7 bit default alphabet

Page Parameter

Total number of pages: 1 Page number: 1

Content of message: "Cell Broadcast".

# Coding:

Coding	C0	11	03	E7	01	11	C3	32	9B	0D	12	CA
·	DF	61	F2	38	3C	A7	83	40	20	10	80	04
	02	81	40	20	10	08	04	02	81	40	20	10
	08	04	02	81	40	20	10	08	04	02	81	40
	20	10	08	04	02	81	40	20	10	08	04	02
	81	40	20	10	08	04	02	81	40	20	10	08
	04	02	81	40	20	10	08	04	02	81	40	20
	10	08	04	02								

# Expected Sequence 1.4 ( Cell Broadcast (UMTS), ENVELOPE (CELL BROADCAST DOWNLOAD), ME does not display message)

TBD

# Expected Sequence 1.5 ( Cell Broadcast (UMTS), ENVELOPE (CELL BROADCAST DOWNLOAD), FETCH, MORE TIME, ME does not display message)

**TBD** 

## Expected Sequence 1.6 (Cell Broadcast (UMTS), ME displays message)

**TBD** 

# Expected Sequence 1.7 (Cell Broadcast (GSM),, ENVELOPE(CELL BROADCAST DATA DOWNLOAD), FETCH, MORE TIME, ME does not display message, User Data Header Payload)

Step	Direction	MESSAGE / Action	Comments
1	$USS \to ME$	CELL BROADCAST Message	Message identifier '10 01'
		1.7	
2	$ME \rightarrow UICC$	ENVELOPE (CELL	
		BROADCAST DOWNLOAD) 1.7	
3	$UICC \to ME$	PROACTIVE COMMAND	SW1/SW2 '61 0B'
		PENDING: MORE TIME 1.2	
4	$ME \rightarrow UICC$	FETCH 1.2	
5	$UICC \to ME$	PROACTIVE COMMAND:MORE	
		TIME 1.2	
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: MORE	
		TIME 1.2	
7	$UICC \to ME$	SW1/SW2 '90 00'	UICC session ended

## CELL BROADCAST Message 1.7

## Logically:

Message Content

Serial Number

Geographical scope: Cell wide, normal display mode

Message code: 1
Update number: 1
Message Identifier: "1001"

Data coding Scheme

Message Coding: 8 bit data

Message class: Class 2 (U)SIM specific message

Page Parameter

Total number of pages: 1 Page number: 1

Secured User Header (Content of message)

TP-UDHL 2

IEI (U)SIM Toolkit Security Headers

IEIL 0
Command Packet Length: 77
Command Header Identifier: 0
Command Header Length: 13

Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity

Ciphering Key Identifier: Algorithm known implicitly by both entities Key Identifier: Algorithm known implicitly by both entities

Toolkit Application Reference: Proprietary Toolkit Application

Counter:

Padding Counter: 0 (no padding is necessary)

Secure Data: 62 octets set to "DC" (dummy data)

Coding:

Coding	C0	11	10	01	96	11	02	70	00	00	4D	00
	0D	00	00	00	00	BF	FF	00	00	00	00	00
	01	00	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC								

#### ENVELOPE: CELL BROADCAST DOWNLOAD 1.7

#### Logically:

Cell Broadcast Download

Device identities

Source device: Network
Destination device: UICC

Cell Broadcast page

Serial Number

Geographical scope: Cell wide, normal display mode

Message code: 1
Update number: 1
Message Identifier: "1001"

Data coding Scheme

Message Coding: 8 bit data (Message with User Data Header (UDH) structure)

Message class: Class 2 (U)SIM specific message

Page Parameter

Number of pages: 1 Page number: 1

Secured User Header (Content of message)

TP-UDHL 2

IEI (U)SIM Toolkit Security Headers

IEIL 0
Command Packet Length: 77
Command Header Identifier: 0
Command Header Length: 13

Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity

Ciphering Key Identifier: Algorithm known implicitly by both entities
Key Identifier: Algorithm known implicitly by both entities

Toolkit Application Reference: Proprietary Toolkit Application

Counter: 1

Padding Counter: 0 (no padding is necessary)
Secure Data: 62 octets set to "DC" (dummy data)

## Coding:

BER-TLV:	D2	5E	82	02	83	81	8C	58	C0	11	10	01
	96	11	02	70	00	00	4D	00	0D	00	00	00
	00	BF	FF	00	00	00	00	00	01	00	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC
	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC	DC

PROACTIVE COMMAND: MORE TIME 1.2

Logically:

Command details

Command number: 1

Command type: MORE TIME

Command qualifier: "00"

Device identities

Source device: UICC Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	02	00	82	02	81	82

TERMINAL RESPONSE: MORE TIME 1.2

Logically:

Command details

Command number: 1

Command type: MORE TIME Command qualifier: "00"

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	02	00	82	02	82	81	83	01	00
DEIX IEV.	01	00	01	02	00	02	02	02	01	00	01	00

# 27.22.5.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.7.

# 27.22.6 CALL CONTROL BY USIM

# 27.22.6.1 Procedure for Mobile Originated calls

## 27.22.6.1.1 Definition and applicability

See clause 3.2.2.

# 27.22.6.1.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in:

- TS 31.111 [15] clause 7.3

## 27.22.6.1.3 Test purpose

To verify that for all call set-up attempts , even those resulting from a SET UP CALL proactive UICC command, the ME shall first pass the call set-up details (dialled digits and associated parameters) to the UICC, using the ENVELOPE (CALL CONTROL).

To verify that if the UICC responds with '90 00', the ME shall set up the call with the dialled digits and other parameters as sent to the UICC.

To verify that if the UICC returns response data, the ME shall use the response data appropriately to set up the call as proposed, not set up the call, or set up a call using the data supplied by the UICC.

To verify that, in the case where the initial call set-up request results from a proactive SET UP CALL, if the call control result is "not allowed" or "allowed with modifications", the ME shall inform the UICC using TERMINAL RESPONSE "interaction with call control by UICC or MO short message control by UICC, action not allowed".

To verify that it is possible for the UICC to request the ME to set up an emergency call by supplying the number "112" as the response data.

## 27.22.6.1.4 Method of tests

#### 27.22.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and USS and has performed the location update procedure.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as USIM Application Toolkit default with the following exception:

The call control service is available in the USIM Service Table.

## 27.22.6.1.4.2 Procedure

# Expected Sequence 1.1 (CALL CONTROL BY USIM , set up call attempt by user, the USIM responds with '90 00')

Step	Direction	Message / Action	Comments				
1	$User \to ME$	Set up a call to					
		"+01234567890123456789"					
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for 3GPP parameters]				
		1.1.1A	[Option B shall apply for PCS1900				
		Or	parameters]				
		ENVELOPE CALL CONTROL					
		1.1.1B					
3	$UICC \to ME$	90 00					
4	$ME \to USS$	The ME sets up the call without	[Set up call to "+01234567890123456789"				
		modification					

#### **ENVELOPE CALL CONTROL 1.1.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell IDRNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

# Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

#### **ENVELOPE CALL CONTROL 1.1.1B**

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
'	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

# Expected Sequence 1.2 (CALL CONTROL BY USIM, set up call attempt by user, allowed without modification)

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to	
		"+01234567890123456789"	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.2.1 A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.2.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 1.2.1	[Call control result: "Allowed, no
			modification"]
4	$ME \rightarrow USS$		[Set up call to "+01234567890123456789"]
		modification	

#### **ENVELOPE CALL CONTROL 1.2.1A**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-	TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
		76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
		F1	10	00	01	00	01	Note 6	Note 4				

# ENVELOPE CALL CONTROL 1.2.1B

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)

Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

## CALL CONTROL RESULT 1.2.1

Logically:

Call control result : '00' = Allowed, no modification

Coding:

BER-TLV: 00 00

# Expected Sequence 1.3A (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, allowed without modification)

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET	[This test applies to MEs asking for user
		UP CALL 1.3.1 PENDING	confirmation before sending the
			ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 1.3.1	[Set up call to "+012340123456"]
4	$ME \rightarrow USER$	ME displays "+012340123456" during user confirmation phase.	
5	$USER \to ME$	The user confirms the call set up	[user confirmation]
6	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL 1.3.1A	[Option A shall apply for GERAN/UTRAN parameters]
		or ENVELOPE CALL CONTROL 1.3.1B	[Option B shall apply for PCS1900 parameters]
7	$UICC \to ME$	CALL CONTROL RESULT 1.3.1	[Call control result: "Allowed, no modification"]
8	$ME \rightarrow USS$	The ME sets up the call without modification	[Set up call to "+012340123456"]
9	$ME \rightarrow UICC$		[command performed successfully]

# Expected Sequence 1.3 B (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, allowed without modification)

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET	[This test applies to MEs asking for user
		UP CALL 1.3.1 PENDING	confirmation after sending the
			ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET	[Set up call to "+012340123456"]
		UP CALL 1.3.1	
4	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.3.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.3.1B	
5	$UICC \to ME$	CALL CONTROL RESULT 1.3.1	[Call control result: "Allowed, no
			modification"]
6	$ME \rightarrow USER$	ME displays "+012340123456"	
		during user confirmation phase.	
7	$USER \to ME$	The user confirms the call set up	[user confirmation]
8	$ME \rightarrow USS$	The ME sets up the call without	[Set up call to "+012340123456"]
		modification	
9	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	[command performed successfully]
		CALL 1.3.1	

## PROACTIVE COMMAND: SET UP CALL 1.3.1

## Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "+012340123456"

Address

TON: International

NPI: "ISDN / telephone numbering plan"

Dialling number string "012340123456"

# Coding:

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

# ENVELOPE CALL CONTROL 1.3.1A

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	Note 5	00	F1	10
	00	01	00	01	Note 6	Note 4					

#### **ENVELOPE CALL CONTROL 1.3.1B**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
-	04	21	43	65	Note 2	Note 3	13	07	00	11	10
	00	01	00	01	Note 4						

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

#### CALL CONTROL RESULT 1.3.1

# Logically:

Call control result : '00' = Allowed, no modification

BER-TLV: 00 00

TERMINAL RESPONSE: SET UP CALL 1.3.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

# Expected Sequence 1.4 (CALL CONTROL BY USIM, set up call attempt by user, not allowed)

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to	
		"+01234567890123456789"	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.4.1 A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.4.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 1.4.1	[Call control result: "not Allowed"]
4	$ME \to USS$	The ME does not set up the call	

#### **ENVELOPE CALL CONTROL 1.4.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "+01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

#### **ENVELOPE CALL CONTROL 1.4.1B**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "+01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

- Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.
- Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.
- Note 3: Subaddress may be present at this place. If present, it may take up several octets.
- Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.
- Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

# CALL CONTROL RESULT 1.4.1

Logically:

Call control result: '01' = not Allowed

Coding:

BER-TLV: 01 00

# Expected Sequence 1.5A (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, not allowed)

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 1.5.1 PENDING	[This test applies to MEs asking for user confirmation before sending the
		OT CALL TOTAL ENDING	ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET	[Set up call to "+012340123456"
4	$ME \rightarrow USER$	UP CALL 1.5.1 ME displays "+012340123456"	
	WL → OOLK	during user confirmation phase.	
5	$USER \to ME$	The user confirms the call set up	[user confirmation]
6	$ME \to UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.5.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.5.1B	
7	$UICC \to ME$	CALL CONTROL RESULT 1.5.1	[Call control result: "Not Allowed"]
8	$ME \to UICC$	TERMINAL RESPONSE: SET UP	[Permanent Problem - Interaction with
		CALL 1.5.1	Call Control by USIM]
9	$ME \to USS$	The ME does not set up the call	

# Expected Sequence 1.5 B (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, not allowed)

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET	[This test applies to MEs asking for user
		UP CALL 1.5.1 PENDING	confirmation after sending the
			ENVELOPE CALL CONTROL command]
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET	[Set up call to "+012340123456"
		UP CALL 1.5.1	
4	$ME \to UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.5.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.5.1B	
5	$UICC \to ME$	CALL CONTROL RESULT 1.5.1	[Call control result: "Not Allowed"]
			[No user confirmation phase because
			Call Control has disallowed the request]
6	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	[Permanent Problem - Interaction with
		CALL 1.5.1	Call Control by USIM]
7	$ME \to USS$	The ME does not set up the call	

# PROACTIVE COMMAND: SET UP CALL 1.5.1

# Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "+012340123456"

Address

TON: International

NPI: "ISDN / telephone numbering plan"

Dialling number string "012340123456"

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

#### **ENVELOPE CALL CONTROL 1.5.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	Note 5	00	F1	10
	00	01	00	01	Note 6	Note 4					

#### **ENVELOPE CALL CONTROL 1.5.1B**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

BER-T	LV:	D4	Note 1	02	02	82	81	06	07	91	10	32
		04	21	43	65	Note 2	Note 3	13	07	00	11	10
		00	01	00	01	Note 4						

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

#### CALL CONTROL RESULT 1.5.1

Logically:

Call control result: '01' = not Allowed

Coding:

BER-TLV: 01 00

TERMINAL RESPONSE: SET UP CALL 1.5.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Interaction with call control by USIM or MO short message control by USIM,

permanent problem

Additional information: Action not allowed

BER-TLV:	81	03	01	10	00	82	02	82	81	83	02	39
	01											

# Expected Sequence 1.6 (CALL CONTROL BY USIM, set up call attempt by user, allowed with modifications)

Step	Direction	Message / Action	Comments
1	$User \rightarrow ME$	Set up a call to	
		"+01234567890123456789"	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.6.1 A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.6.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 1.6.1	[Call control result: "Allowed with
			modifications", ]
4	$ME \rightarrow USS$	The ME sets up the call to	
		"+010203"	

#### **ENVELOPE CALL CONTROL 1.6.1A**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-T	LV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
		76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
		F1	10	00	01	00	01	Note 6	Note 4				

# **ENVELOPE CALL CONTROL 1.6.1B**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001) Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
_	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

## CALL CONTROL RESULT 1.6.1

## Logically:

Call control result: '02' = Allowed with modifications

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "010203"

# Coding:

BER-TLV:	02	06	86	04	91	10	20	30

# Expected Sequence 1.7A (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, allowed with modifications)

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET	[This test applies to MEs asking for user
		UP CALL 1.7.1 PENDING	confirmation before sending the
			ENVELOPE CALL CONTROL command]
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET	[Set up call to "+012340123456"]
		UP CALL 1.7.1	
4	$ME \to USER$	ME displays "+012340123456"	
		during user confirmation phase.	
5	$USER \to ME$	The user confirms the call set up	[user confirmation]
6	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.7.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.7.1B	
7	$UICC \to ME$	CALL CONTROL RESULT 1.7.1	[Call control result: "Allowed with
			modifications"]
8	$ME \rightarrow USS$	The ME sets up the call to	
_		"+01111111111"	
9	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	[command performed successfully]
		CALL 1.7.1	

# Expected Sequence 1.7 B (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, allowed with modifications)

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 1.7.1 PENDING	[This test applies to MEs asking for user confirmation after sending the ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	•
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP CALL 1.7.1	[Set up call to "+012340123456"]
4	$ME \to UICC$	ENVELOPE CALL CONTROL 1.7.1A	[Option A shall apply for GERAN/UTRAN parameters]
		or ENVELOPE CALL CONTROL 1.7.1B	[Option B shall apply for PCS1900 parameters]
5	$UICC \to ME$	CALL CONTROL RESULT 1.7.1	[Call control result: "Allowed with modifications"]
6	$ME \to USER$	ME displays "+012340123456" during user confirmation phase.	
7	$USER \to ME$	The user confirms the call set up	[user confirmation]
8	$ME \to USS$	The ME sets up the call to "+0111111111111"	[call is set up to modified address]
9	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP CALL 1.7.1	[command performed successfully]

#### PROACTIVE COMMAND: SET UP CALL 1.7.1

## Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: '+012340123456"

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "012340123456"

# Coding:

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

## **ENVELOPE CALL CONTROL 1.7.1A**

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	Note 5	00	F1	10
	00	01	00	01	Note 6	Note 4					

#### **ENVELOPE CALL CONTROL 1.7.1B**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
-	04	21	43	65	Note 2	Note 3	13	07	00	11	10
	00	01	00	01	Note 4						

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### CALL CONTROL RESULT 1.7.1

# Logically:

Call control result: '02' = Allowed with modifications

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01111111111"

Coding:

BER-TLV:	02	09	86	07	91	10	11	11	11	11	11
	~-			• .							

TERMINAL RESPONSE: SET UP CALL 1.7.1

Logically:

Command details

Command number:

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 10 00 82 02	82 81	83 01	00	
-------------------------------	-------	-------	----	--

# Expected Sequence 1.8 (CALL CONTROL BY USIM, set up call attempt by user, allowed with modifications: emergency call)

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to	
		"+01234567890123456789"	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL 1.8.1A	[Option A shall apply for GERAN/UTRAN
		or	parameters]
		ENVELOPE CALL CONTROL 1.8.1B	[Option B shall apply for PCS1900
			parameters
3	$UICC \to ME$	CALL CONTROL RESULT 1.8.1	[Call control result: "Allowed with
			modifications"]
4	$ME \to USS$	The ME sets up an emergency call;	

## **ENVELOPE CALL CONTROL 1.8.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
_	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

#### ENVELOPE CALL CONTROL 1.8.1B

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
_	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

# CALL CONTROL RESULT 1.8.1

Logically:

Call control result Allowed, with modification

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Address value "112"

BER-TLV:
----------

# Expected Sequence 1.9 (CALL CONTROL BY USIM, set up call attempt by user, allowed with modifications: number in EF<sub>ECC</sub>)

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to	
		"+01234567890123456789"	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL 1.9.1A	[Option A shall apply for GERAN/UTRAN
		or	parameters]
		ENVELOPE CALL CONTROL 1.9.1B	[Option B shall apply for PCS1900
			parameters]
3	$UICC \to ME$	CALL CONTROL RESULT 1.9.1	[Call control result: "Allowed with
			modifications"]
4		The ME sets up call with the dialled	
		digits "1020". The ME does not set	
		up an emergency call, but stes up a	
		normal call	

## **ENVELOPE CALL CONTROL 1.9.1A**

# Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

# Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

#### **ENVELOPE CALL CONTROL 1.9.1B**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

## CALL CONTROL RESULT 1.9.1

## Logically:

Call control result Allowed, with modification

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Address value "1020"

Coding:

BER-TLV:	02	05	86	03	81	01	02

# Expected Sequence 1.10 (CALL CONTROL BY USIM , set up call attempt by user to an emergency call)

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to "112"	
2	$ME \to UICC$	The ME does not send any ENVELOPE CALL CONTROL	
3	$ME \to USS$	The ME sets up an emergency call	

# Expected Sequence 1.11 (CALL CONTROL BY USIM , set up call through call register, the USIM responds with '90 00')

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed by call control in its register.

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to	
		"+01234567890123456789"	
2	$ME \to UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.1.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.1.1B	
3	$UICC \to ME$	90 00	
4	$ME \to USS$	The ME sets up the call without	[Set up call to "+01234567890123456789"]
		modification	
5	$USER \to ME$	End Call.	
6	$USER \to ME$	Recall the last dialled number	
7	$ME \to UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		1.1.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.1.1B	
8	$UICC \to ME$	90 00	
9	$ME \to USS$	The ME sets up the call without	[Set up call to "+01234567890123456789"]
		modification	
10	$USER \to ME$	End Call.	

# Expected Sequence 1.12 (CALL CONTROL BY USIM, set up call through call register, allowed without modification)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed by call control in its register.

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.2.1A or ENVELOPE CALL CONTROL 1.2.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	$UICC \to ME$	CALL CONTROL RESULT 1.2.1	[Call control result: "Allowed, no modification"]
4	$ME \to USS$	The ME sets up the call without modification	[Set up call to "+01234567890123456789"]
5	$User \to ME$	End the call then call the last dialled number	
6	ME → UICC	ENVELOPE CALL CONTROL 1.2.1A or ENVELOPE CALL CONTROL 1.2.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
7	$UICC \to ME$	CALL CONTROL RESULT 1.2.1	
8	$ME \rightarrow USS$	The ME sets up the call without modification	[Set up call to "+01234567890123456789"]

# Expected Sequence 1.13 (CALL CONTROL BY USIM, set up call through call register, not allowed)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers not allowed by call control in its register.

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to	
		"+01234567890123456789"	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	Option A shall apply for GERAN/UTRAN
		1.4.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.4.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 1.4.1	[Call control result: "not Allowed"]
4	$ME \to USS$	The ME does not set up the call	
5	$User \to ME$	The user calls the last dialled	
		number	
6	$ME \to UICC$	ENVELOPE CALL CONTROL	Option A shall apply for GERAN/UTRAN
		1.4.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		1.4.1B	
7	$UICC \to ME$	CALL CONTROL RESULT 1.4.1	[Call control result: "not Allowed"]
8	$ME \to USS$	The ME does not set up the call	

# Expected Sequence 1.14 (CALL CONTROL BY USIM, set up call through call register, allowed with modifications)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed with modification by call control in its register.

Step	Direction	Message / Action	Comments
1	$User \to ME$	Set up a call to "+0123456789"	
2	$ME \to UICC$	ENVELOPE CALL CONTROL 1.6.1A	[Option A shall apply for GERAN/UTRAN parameters]
		or ENVELOPE CALL CONTROL	[Option B shall apply for PCS1900 parameters]
		1.6.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 1.6.1	[Call control result: "Allowed with modifications"]
4	$ME \to USS$	The ME sets up the call to "+010203"	-
5	$User \to ME$	End call and then set up a call to "+01234567890123456789"	
6	$ME \to UICC$	ENVELOPE CALL CONTROL 1.6.1A	[Option A shall apply for GERAN/UTRAN parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
7	$UICC \to ME$	CALL CONTROL RESULT 1.6.1	[Call control result: "Allowed with modifications"]
8	$ME \to USS$	The ME sets up the call to "+010203"	•

# 27.22.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.14.

# 27.22.6.2 Procedure for Supplementary (SS) Services

# 27.22.6.2.1 Definition and applicability

See clause 3.2.2.

# 27.22.6.2.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in the following technical specifications:

- TS 31.111 [15] clause 7.3.1.2.

## 27.22.6.2.3 Test purpose

To verify that the ME first pass the supplementary service control string corresponding to the supplementary service operation to the USIM, using the ENVELOPE (CALL CONTROL) command.

To verify that, if the UICC responds with '90 00', the ME shall send the supplementary service operation with the information as sent to the UICC.

To verify that, if the UICC returns response data, the ME shall use the response data appropriately to send the supplementary service operation as proposed, not send the SS operation, or instead send the USS operation using the data supplied by the UICC.

#### 27.22.6.2.4 Method of tests

#### 27.22.6.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as USIM Application Toolkit default with the following exception:

The call control service is available in the USIM Service Table.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

#### 27.22.6.2.4.2 Procedure

## Expected Sequence 2.1 (CALL CONTROL BY USIM, send SS, the USIM responds with '90 00')

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user selects the facility of the	
		ME which requires an	
		unconditional call forward	
		supplementary service operation	
		to be sent to the network (System	
		Simulator).	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		2.1.1A	parameters
		or	Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters
		2.1.1B	[ '
3	$UICC \rightarrow ME$	90 00	
4	ME → USS	REGISTER 2.1A	[The ME sends the supplementary
	/ 555	or	service operation with the information as
		REGISTER 2.1B	sent to the UICC1
5	$USS \to ME$	RELEASE COMPLETE (SS	
		RETURN RESULT) 2.1	

# ENVELOPE CALL CONTROL 2.1.1A

#### Logically:

Device identities

Source device: ME
Destination device: UICC

SS String

TON/NPI: "FF"
Dialling number string "\*21\*\*10#"

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

#### Coding:

BER-TLV:	D4	Note1	82	02	82	81	89	05	FF	2A	A1	1A
	B0	13	Note 2	00	F1	10	00	01	00	01	Note 3	

Note 1: Length of BER-TLV is '14' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### **ENVELOPE CALL CONTROL 2.1.1B**

#### Logically:

Device identities

Source device: ME Destination device: UICC

SS String

TON/NPI: "FF"
Dialling number string "\*21\*\*10#"

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D4	14	82	02	82	81	89	05	FF	2A	A1	1A
	B0	13	07	00	11	10	00	01	00	01		

## **REGISTER 2.1A**

Logically (only SS argument):

## ACTIVATE SS ARGUMENT

SS-Code:

- Call Forwarding Unconditional

TeleserviceCode

- All Tele Services

Coding:

Codina	30	06	04	01	21	83	01	00		

## **REGISTER 2.1B**

Logically (only SS argument):

#### ACTIVATE SS ARGUMENT

SS-Code:

- Call Forwarding Unconditional

TeleserviceCode

- All Tele Services

LongFTN Supported

Coding:

Coding	30	08	04	01	21	83	01	00	84	00	

# RELEASE COMPLETE (SS RETURN RESULT) 2.1

Logically (only from operation code):

# ACTIVATE SS RETURN RESULT

ForwardingInfo

SS-Code

- Call Forwarding Unconditional

ForwardFeatureList

ForwardingFeature

TeleserviceCode

- All Tele Services

SS-Status

- state ind.: operative

provision ind.: provisionedregistration ind.: registered

- activation ind.: active

Coding	0C	A0	0D	04	01	21	30	08	30	06	83	01
	00	84	01	07								

# Expected Sequence 2.2 (CALL CONTROL BY USIM, send SS, allowed without modifications)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user selects the facility of the	
		ME which requires an	
		unconditional call forward	
		supplementary service operation	
		to be sent to the network (System	
		Simulator).	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	Option A shall apply for GERAN/UTRAN
		2.2.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		2.2.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 2.2.1	[Call control result: "Allowed without modifications"]
4	$ME \rightarrow USS$	REGISTER 2.1A	The ME sends the supplementary service
		or	operation with the information as sent to
		REGISTER 2.1B	the UICC
5	$USS \to ME$	RELEASE COMPLETE (SS	
		RETURN RESULT) 2.1	

#### **ENVELOPE CALL CONTROL 2.2.1A**

# Logically:

Device identities

Source device: ME
Destination device: UICC

SS String

TON/NPI: "FF"

Dialling number string "\*21\*\*10#"

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	89	05	FF	2A	A1	1A
·	B0	13	Note 2	00	F1	10	00	01	00	01	Note 3	

Note 1: Length of BER-TLV is '14' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

# ENVELOPE CALL CONTROL 2.2.1B

## Logically:

Device identities

Source device: ME
Destination device: UICC

SS String

TON/NPI: "FF"

Dialling number string "\*21\*\*10#"

Location Information

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D4	14	82	02	82	81	89	05	FF	2A	A1	1A
	B0	13	07	00	11	10	00	01	00	01		

#### CALL CONTROL RESULT 2.2.1

Logically:

Call control result Allowed, no modifications

Coding:

BER-TLV: 00 00

# Expected Sequence 2.3 (CALL CONTROL BY USIM, send SS, not allowed)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user selects the facility of the	
		ME which requires an	
		unconditional call forward	
		supplementary service operation	
		to be sent to the network (System	
		Simulator).	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		2.3.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		2.3.1B	
3		CALL CONTROL RESULT 2.3.1	[Call control result: "Not Allowed"]
4	$ME \rightarrow USS$	The ME does not send the	
		supplementary service operation	

#### **ENVELOPE CALL CONTROL 2.3.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

SS String

TON/NPI: "FF" Dialling number string "\*21#"

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	89	03	FF	2A	B1	13
	Note 2	00	F1	10	00	01	00	01	Note 3			

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

# **ENVELOPE CALL CONTROL 2.3.1B**

Logically:

Device identities

Source device: ME
Destination device: UICC

SS String

TON/NPI: "FF"
Dialling number string "\*21#"

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D4	12	82	02	82	81	89	03	FF	2A	B1	13
	07	00	11	10	00	01	00	01				

## **CALL CONTROL RESULT 2.3.1**

Logically:

Call control result Not Allowed

Coding:

BER-TLV: 01 00

# Expected Sequence 2.4 (CALL CONTROL BY USIM, send SS, allowed with modifications)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user selects the facility of the	
		ME which requires an	
		unconditional call forward	
		supplementary service operation	
		to be sent to the network (System	
		Simulator).	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		2.4.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		2.4.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 2.4.1	[Call control result: "Allowed with modifications"]
4	$ME \to USS$	REGISTER 2.4A	[The ME sends the supplementary
		or	service operation with the information as
		REGISTER 2.4B	sent by the UICC]
5	$USS \to ME$	RELEASE COMPLETE (SS	
		RETURN RESULT) 2.4	

# **ENVELOPE CALL CONTROL 2.4.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

SS String

TON/NPI: "FF" Dialling number string "\*21#"

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	89	03	FF	2A	B1	13
	Note 2	00	F1	10	00	01	00	01	Note 3			

926

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

# ENVELOPE CALL CONTROL 2.4.1B

## Logically:

Device identities

Source device: ME
Destination device: UICC

SS String

TON/NPI: "FF" Dialling number string "\*21#"

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

# Coding:

BER-TLV:	D4	12	82	02	82	81	89	03	FF	2A	B1	13
·	07	00	11	10	00	01	00	01				

#### **CALL CONTROL RESULT 2.4.1**

# Logically:

Call control result Allowed, with modifications

SS String

TON/NPI "FF" SS String "\*#21#"

Coding:

BER-TLV: 02	06	89	04	FF	BA	12	FB
-------------	----	----	----	----	----	----	----

# **REGISTER 2.4A**

Logically (only SS argument):

## INTERROGATE SS ARGUMENT

SS-Code

- Call Forwarding Unconditional

BER-TLV	30	03	04	01	21

#### **REGISTER 2.4B**

Logically (only SS argument):

#### INTERROGATE SS ARGUMENT

SS-Code

- Call Forwarding Unconditional

LongFTN Supported

Coding:

BER-TLV 30	05	04	01	21	84	00
------------	----	----	----	----	----	----

## RELEASE COMPLETE (SS RETURN RESULT) 2.4

Logically (only from operation code):

#### INTERROGATE SS RESULT

Call Forwarding Unconditional

SS-Status

- state ind .: operative

provision ind.: provisionedregistration ind.: registeredactivation ind.: not active

Coding:

BER-TLV	80	01	06						
---------	----	----	----	--	--	--	--	--	--

# 27.22.6.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.4.

# 27.22.6.3 Interaction with Fixed Dialling Number (FDN)

# 27.22.6.3.1 Definition and applicability

See clause 3.2.2.

# 27.22.6.3.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in:

- TS 31.111 [15] clause 7.3.1.4.

# 27.22.6.3.3 Test purpose

To verify that the ME checks that the number entered through the MMI is on the FDN list.

To verify that, if the MMI input does not pass the FDN check, the call shall not be set up.

To verify that, if the MMI input does pass the FDN check, the ME shall pass the dialled digits and other parameters to the UICC, using the ENVELOPE (CALL CONTROL) command.

To verify that, if the UICC responds with "allowed, no modification", the ME shall set up the call as proposed.

To verify that, if the UICC responds with "not allowed", the ME shall not set up the call.

To verify that, if the UICC responds with "allowed with modifications", the ME shall set up the call in accordance with the response from the UICC. If the modifications involve changing the dialled digits, the ME shall not re-check this modified number against the FDN list.

## 27.22.6.3.4 Method of tests

#### 27.22.6.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as SIM Application Toolkit default with the following exceptions:

The call control service is available in the USIM Service Table.

Fixed Dialling Number service is enabled.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

#### 27.22.6.3.4.2 Procedure

# Expected Sequence 3.1 (CALL CONTROL BY USIM, set up a call not in EF<sub>FDN</sub>)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up a call to "4321"	
2	$ME \rightarrow UICC$	The ME does not send the ENVELOPE (CALL CONTROL)	
		command to the USIM.	
3	$ME \rightarrow USS$	The ME does not set up the call.	

# Expected Sequence 3.2 (CALL CONTROL BY USIM, set up a call in EF<sub>FDN</sub>, the USIM responds with '90 00')

Step	Direction	Message / Action	Comments	
1	$User \to ME$	The user sets up a call to "123"		
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN	
		3.2.1A	parameters]	
		or	[Option B shall apply for PCS1900	
		ENVELOPE CALL CONTROL	parameters]	
		3.2.1B		
3	$UICC \to ME$	90 00		
4	$ME \to USS$	The ME sets up the call without	[Set up call to "123"]	
		modification		

929

#### **ENVELOPE CALL CONTROL 3.2.1A**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	Note 3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

#### **ENVELOPE CALL CONTROL 3.2.1B**

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)

Cell ID Cell Identity Value (0001) Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	Note 3	13	07	00	11	10	00	01	00	01	Note 4	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

# Expected Sequence 3.3 (CALL CONTROL BY USIM, set up a call in EF<sub>FDN</sub>, Allowed without modifications)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up a call to "9876"	
2	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		3.3.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL 3.3.1B	parameters]
3	$UICC \to ME$	CALL CONTROL RESULT 3.3.1	[Call control result: "Allowed without modifications"]
4		The ME sets up the call without modification	[Set up call to "9876"]

## **ENVELOPE CALL CONTROL 3.3.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "9876" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

# Coding:

	BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
-		Note 3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

#### **ENVELOPE CALL CONTROL 3.3.1B**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "9876" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note 3	13	07	00	11	10	00	01	00	01	Note 4	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### **CALL CONTROL RESULT 3.3.1**

Logically:

Call control result Allowed, no modifications

Coding:

BER-TLV: 00 00

# Expected Sequence 3.4 (CALL CONTROL BY USIM, set up a call in EF<sub>FDN</sub>, Not Allowed)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up a call to "9876"	
2	$ME \to UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		3.4.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		3.4.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 3.4.1	[Call control result: "Not Allowed"]
4	$ME \to USS$	The ME does not set up the call	

## **ENVELOPE CALL CONTROL 3.4.1A**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "9876" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note 3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

## **ENVELOPE CALL CONTROL 3.4.1B**

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "9876" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note 3	13	07	00	11	10	00	01	00	01	Note 4	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

# **CALL CONTROL RESULT 3.4.1**

#### Logically:

Call control result Not Allowed

BER-TLV: 01 00

# Expected Sequence 3.5 (CALL CONTROL BY USIM , set up a call in $\mathsf{EF}_\mathsf{FDN}$ , Allowed with modifications)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up a call to "9876"	
2	$ME \to UICC$	ENVELOPE CALL CONTROL 3.5.1A	[Option A shall apply for GERAN/UTRAN parameters]
		or	Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL 3.5.1B	parameters]
3	$UICC \to ME$		[Call control result: "Allowed with modifications"]
4	$ME \to USS$	The ME sets up the call with data sent by the UICC	[Set up call to "3333"]

#### **ENVELOPE CALL CONTROL 3.5.1A**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "9876" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

# Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

#### **ENVELOPE CALL CONTROL 3.5.1B**

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "9876" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note3	13	07	00	11	10	00	01	00	01	Note 4	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### **CALL CONTROL RESULT 3.5.1**

# Logically:

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Address value "3333"

## Coding:

BER-TLV:	02	05	86	03	81	33	33

## 27.22.6.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1 to 3.5.

# 27.22.6.4 Support of Barred Dialling Number (BDN) service

# 27.22.6.4.1 Definition and applicability

Barred Dialling Numbers (BDN) is a service defined for the USIM. An enabled BDN service results in call restrictions for the ME. The call restrictions are controlled by the Terminal. To ascertain the type of USIM and state of BDN the ME runs the BDN capability request procedure during UICC-Terminal initialisation. At the time an emergency call is setup using the emergency call code read from the  $EF_{ECC}$ , the Rel-4+ ME shall use the category of the emergency service indicated.

#### 27.22.6.4.2 Conformance requirement

- 1) Recognising the state of the USIM (BDN enabled) the ME shall perform the UICC initialisation procedure as specified.
- 2) The ME shall prevent call set-up to any number stored in EF<sub>BDN</sub> if BDN service is enabled.
- 3) The ME shall allow call set-up to any number stored in  $EF_{BDN}$  if BDN service is disabled.

- 4) Any change to the  $EF_{BDN}$  or  $EF_{EST}$  does request PIN2.
- 5) The ME allows call set-up of an emergency call, even if this number is stored in the USIM.

#### References:

- R99: TS 22.101[22], clause 8 and A.19;
- Rel-4: TS 22.101[22], clause 9 and A.20;
- Rel-5+: TS 22.101[22], clause 10 and A.21;
- TS 31.102[14], subclauses 4.2.44, 4.4.2.3, 5.1.1 and 5.3.2;
- TS 24.008[10], subclause 10.5.4.33;
- TS 31.111[15], subclause 7.3.1.5

# 27.22.6.4.3 Test purpose

- To verify that the Terminal rejects call set-up to any number that has an entry in EF<sub>BDN</sub> if BDN service is enabled.
- 2) To verify that the Terminal allows call set-up to any number not stored in EF<sub>BDN</sub>.
- 3) To verify that the Terminal allows emergency call set-up even if the number is stored in EF<sub>BDN</sub>.
- 4) To verify that the Rel-4+ Terminal reads correctly the emergency service category stored in  $EF_{ECC}$
- 5) To verify that, if the UICC responds with "not allowed", the ME does not set up the call.
- 6) To verify that, if the UICC responds with "allowed, no modification", the ME shall set up the call (or the supplementary service operation) as proposed.
- 7) To verify that, if the UICC responds with "allowed with modifications", the ME sets up the call in accordance with the response from the UICC. If the modifications involve changing the dialled number the ME does not recheck this modified number against the FDN list when FDN is enabled.
- 8) To verify that updating EF BDN or changing the status of BDN service shall be performed by the use of second application PIN only.
- 9) To verify that the ME allows call set up to a BDN number if BDN service is disabled.

#### 27.22.6.4.4 Method of tests

## 27.22.6.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The call control service is available in the USIM Service Table.

The elementary files are coded as USIM Application Toolkit default with the following exceptions:

Barred Dialling Number service is enabled.

Fixed Dialling Number service is disabled.

Only prior to the execution of expected sequence 4.3 the FDN service shall be enabled.

The Second Application PIN (key reference 81) shall be enabled, but not verified.

Only in expected sequence 4.2B EF<sub>ECC</sub> shall be used with the following values:

EF<sub>ECC</sub> (Emergency Call Codes)

Logically: Emergency call code: "122";

Emergency call code alpha identifier: "TEST";

Emergency call Service Category: "Mountain Rescue".

Coding:	B1	B2	B3	B4	B5	B6	B7	B8
Hex	21	F2	FF	54	45	53	54	10

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

Mobile Country Code (MCC) = 001;

- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

## 27.22.6.4.4.2 Procedure

## Expected Sequence 4.1 (CALL CONTROL BY USIM, BDN service enabled)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up a call to	[Number as stored in record 1 of EF
		"+1357924680"	BDN]
2	$ME \to UICC$	ENVELOPE CALL CONTROL 4.1.1A	[Option A shall apply for GERAN/UTRAN
		or	parameters] [Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		4.1.1B	
3	$UICC \to ME$	CALL CONTROL RESULT 4.1.1	[Call control result: "Not Allowed"]
4 5	$ME \rightarrow USS$ $User \rightarrow ME$	The ME does not set up the call The user sets up a call to the	
3	OSeI → IVIE	number stored in record 1 of EF	
		ADN	
6	$ME \to UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		4.1.2A or	parameters] [Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		4.1.2B	
7	$UICC \to ME$	CALL CONTROL RESULT 4.1.2	[Call control result: "Allowed without
8	$ME \to USS$	The ME sets up the call without	modifications"]
	WL → USS	modification	
9	$User \to ME$	The user sets up a call to '123456'	
10	$ME \to UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		4.1.3A or	parameters] [Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		4.1.3B	
11	$UICC \to ME$	CALL CONTROL RESULT 4.1.2	[Call control result: "Allowed without
12	$ME \to USS$	The ME sets up the call without	modifications"]
'-	WE 7000	modification	
13	$User \to ME$	The user sets up a call to "1111"	
14	$ME \rightarrow UICC$	ENVELOPE CALL CONTROL	[Option A shall apply for GERAN/UTRAN
		4.1.4A or	parameters] [Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL	parameters]
		4.1.4B	
15	$UICC \to ME$	CALL CONTROL RESULT 4.1.3	[Call control result: "Allowed with modifications"]
16	$ME \to USS$	The ME sets up the call with data	[Set up call to "2222"]
		sent by the UICC	[555.0]
17	$User \to ME$	The user shall use a MMI	
		dependent procedure to initiate the disabling of the BDN service	
18	$ME \rightarrow User$	Ask for second application PIN	
	/ 555.	verification	
19	$User \to ME$	The user shall enter the second	
20	$ME \to UICC$	application PIN Update EF EST to disable BDN	
	IVIL -> UICC	service	
21	$UICC \to ME$	UICC responds with SW = '90 00'	
22	$ME \to User$	Indicate that the BDN service was	
23	$User \to ME$	disabled successfully The user uses the MMI to store	[The alpha identifier is not changed.]
		the directory number	[ aipha laohilloi lo not ollangea.]
		"+876543210" in EF <sub>BDN</sub> as barred	
24	ME	dialling number 1 (record 1).	
24 25	$ME \rightarrow UICC$ $UICC \rightarrow ME$	Update EF BDN UICC responds with SW = '90 00'	
26	ME → User	The user attempts to set up a call	
		to '+876543210'.	
27a	$ME \to UICC$	No Envelope call control is sent	

27b	$ME \to USS$	The ME sets up the call without	
		modification	

#### **ENVELOPE CALL CONTROL 4.1.1A**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON International

NPI "ISDN / telephone numbering plan"

Dialling number string "1357924680"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	06	91	31	75	29
	64	08	Note 2	13	Note 4	00	F1	10	00	01	00	01
	Note5	Note 3										

## ENVELOPE CALL CONTROL 4.1.1B

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON International

NPI "ISDN / telephone numbering plan"

Dialling number string "1357924680"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	06	91	31	75	29
	64	08	Note 2	13	07	00	11	10	00	01	00	01
	Note 3											

Note 1: Length of BER-TLV is '15' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### **ENVELOPE CALL CONTROL 4.1.2A**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
·	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3	

## ENVELOPE CALL CONTROL 4.1.2B

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001) Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	13	07	00	11	10	00	01	00	01	Note 3		

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### **ENVELOPE CALL CONTROL 4.1.3A**

#### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123456" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	04	81	21	43	65
	Note 2	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3

## ENVELOPE CALL CONTROL 4.1.3B

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123456" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	04	81	21	43	65
	Note 2	13	07	00	11	10	00	01	00	01	Note 3	

Note 1: Length of BER-TLV is '13' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'.

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### **ENVELOPE CALL CONTROL 4.1.4A**

### Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "1111" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	11	11	Note 2
<u> </u>	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3	

## ENVELOPE CALL CONTROL 4.1.4B

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "1111" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	11	11	Note 2
	13	07	00	11	10	00	01	00	01	Note 3		

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

## CALL CONTROL RESULT 4.1.1

Logically:

Call control result Not Allowed

Coding:

BER-TLV: 01 00

## CALL CONTROL RESULT 4.1.2

Logically:

Call control result Allowed, no modifications

Coding:

BER-TLV: 00 00

## CALL CONTROL RESULT 4.1.3

Logically:

Call control result Allowed with modifications

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Address value "2222"

Coding:

BER-TLV: 02 05 86 03 81 22 22

# Expected Sequence 4.2A (CALL CONTROL BY USIM, BDN service enabled, interaction with emergency call codes, R99 only)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up an emergency call to an emergency number stored in the terminal.	The used emergency number shall be one of the emergency call codes, which are available when a SIM/USIM is present, according to TS 22.101[22], subclause 8 is used (i.e. "112", or "911").
2a	$ME \to UICC$	No Envelope call control is sent	, ,
2b	$ME \to USS$	The ME shall allow an emergency call by indicating the call setup as "Emergency Call'.	
3	$User \to ME$	End the emergency call.	

# Expected Sequence 4.2B (CALL CONTROL BY USIM, BDN service enabled, interaction with emergency call codes, Rel-4+)

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up an emergency call to an emergency number stored in the terminal.	The used emergency number shall be one of the emergency call codes, which are available when a SIM/USIM is present, according to TS 22.101[22], subclause 9 (Rel-4) or 10 (Rel-5+) is used (i.e. "112", or "911").
2a	$ME \to UICC$	No Envelope call control is sent	
2b	$ME \to USS$	The ME shall allow an emergency call by indicating the call setup as "Emergency Call'.	
3	$User \to ME$	End the emergency call.	
4	$User \to ME$	The user sets up an emergency call to an emergency number stored in the USIM.	
5a	$ME \to UICC$	No Envelope call control is sent	
5b	$ME \rightarrow USS$	The ME shall allow an emergency call by sending the emergency service category correctly as 'Mountain Rescue'.	
6	$User \to ME$	End the emergency call.	

# Expected Sequence 4.3 (CALL CONTROL BY USIM , FDN and BDN enabled, set up a call in $\mathsf{EF}_\mathsf{FDN}$ , Allowed with modifications)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up a call to "123"	
2	$ME \to UICC$	ENVELOPE CALL CONTROL 4.3.1A	[Option A shall apply for GERAN/UTRAN parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE CALL CONTROL 4.3.1B	parameters]
3	$UICC \to ME$	CALL CONTROL RESULT 4.3.1	[Call control result: "Allowed with modifications"]
4	$ME \to USS$	The ME sets up the call with data sent by the UICC	[Set up call to "24680"the ME does not re-check this modified number against the FDN list]

#### **ENVELOPE CALL CONTROL 4.3.1A**

## Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3	

#### **ENVELOPE CALL CONTROL 4.3.1B**

Logically:

Device identities

Source device: ME
Destination device: UICC

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "123" Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

#### Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	13	07	00	11	10	00	01	00	01	Note 3		

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

### CALL CONTROL RESULT 4.3.1

Logically:

Call control result Allowed with modifications

Address

TON Unknown

NPI "ISDN / telephone numbering plan"

Address value "24680"

Coding:

BER-TLV:   02   06   86   04   81   42   86   F0	

## 27.22.6.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.3.

# 27.22.6.5 Barred Dialling Number (BDN) service handling for terminals not supporting BDN

## 27.22.6.5.1 Definition and applicability

Barred Dialling Numbers (BDN) is a service defined for the USIM. An enabled BDN service results in call restrictions for the ME. The call restrictions are controlled by the Terminal. If BDN is enabled, an ME which does not support Call Control shall allow emergency calls but shall not allow MO-CS calls.

## 27.22.6.5.2 Conformance requirement

- 1) Recognising the state of the USIM (BDN enabled) the ME shall perform the UICC initialisation procedure as specified.
- 2) The ME shall prevent MO-CS call set-up to any number except to emergency call numbers if the BDN service is enabled.

#### References:

- Rel-5+: TS 22.101[22], clause 10 and A.21;

TS 31.102[14], subclauses 4.2.44, 4.4.2.3, 5.1.1.2 and 5.3.2;

TS 31.111[15], subclause 7.3.1.5

## 27.22.6.5.3 Test purpose

- 1) To verify that the Terminal rejects MO-CS call set-up to any number except to emergency call numbers if BDN service is enabled.
- 2) To verify that the Terminal allows emergency call set-up even if the BDN service is enabled.

#### 27.22.6.5.4 Method of tests

#### 27.22.6.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The call control service is available in the USIM Service Table.

The elementary files are coded as USIM Application Toolkit default with the following exceptions:

Barred Dialling Number service is enabled.

#### 27.22.6.5.4.2 Procedure

## Expected Sequence 5.1 (CALL CONTROL BY USIM, BDN service enabled, ME not supporting BDN)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user sets up a call to "+1357924680"	[Number as stored in record 1 of EF BDN]
2a	$ME \to UICC$	No ENVELOPE CALL CONTROL is sent	
2b	$ME \to USS$	The ME does not set up the call	
3	$User \to ME$	The user sets up a call to the number stored in record 1 of EF ADN	
4a	$ME \to UICC$	No ENVELOPE CALL CONTROL is sent	
4b	$ME \to USS$	The ME does not set up the call	
5	$User \to ME$	The user sets up an emergency call to "112"	
6a	$ME \to UICC$	No ENVELOPE CALL CONTROL is sent	
6b	$ME \to USS$	The ME sets up the emergency call to "112"	
7	$User \to ME$	The user shall terminate the emergency call after 5 seconds. The ME returns to idle mode.	

## 27.22.7 EVENT DOWNLOAD

## 27.22.7.1 MT Call Event

27.22.7.1.1 MT Call Event (normal)

27.22.7.1.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.1.1.2 Conformance requirement

The ME shall support the EVENT: MT Call event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

## 27.22.7.1.1.3 Test purpose

To verify that the ME informs the UICC that an Event: MT Call has occurred using the ENVELOPE (EVENT DOWNLOAD - MT Call) command.

## 27.22.7.1.1.4 Method of test

## 27.22.7.1.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

## 27.22.7.1.1.4.2 Procedure

## **Expected Sequence 1.1 (EVENT DOWNLOAD -MT Call event)**

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
		1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		EVENT LIST 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
		EVENT LIST 1.1.1	
5		CALL SET UP without CLI	[MT Call Set Up Without CLI]
6	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD	
		- MT Call 1.1.1	
7		CALL DISCONNECT	
8	$USS \to ME$	CALL SET UP with CLI	[MT Call Set Up With CLI]
9	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD	
		- MT Call 1.1.2	
10	$USS \to ME$	CALL DISCONNECT	

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: MT call

Coding:

BER-TI	LV:	D0	0C	81	03	01	05	00	82	02	81	82	99
		01	00										

## TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

## **EVENT DOWNLOAD - MT CALL 1.1.1**

Logically:

Event list: MT call event

Device identities

Source device: Network
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Coding:

BER-TLV: D6 0A	19 01	00 82	02 83	81	1C	01	00
----------------	-------	-------	-------	----	----	----	----

## EVENT DOWNLOAD - MT CALL 1.1.2

Logically:

Event list: MT call event

Device identities

Source device: Network
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Address:

TON Unknown

NPI "ISDN / telephone numbering plan"

Dialling number string "9876"

Coding:

BER-TLV:	D6	0F	19	01	00	82	02	83	81	1C	01	00
· <u> </u>	86	03	81	89	67							

#### 27.22.7.1.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.2 Call Connected Event

## 27.22.7.2.1 Call Connected Event (MT and MO call)

## 27.22.7.2.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.2.1.2 Conformance requirement

The ME shall support the EVENT: Call Connected event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

## 27.22.7.2.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Connected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Connected) command.

27.22.7.2.1.4 Method of test

27.22.7.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

#### 27.22.7.2.1.4.2 Procedure

## **Expected Sequence 1.1 (EVENT DOWNLOAD -CALL CONNECTED)**

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
		1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[EVENT: Call Connected active]
		EVENT LIST 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
		EVENT LIST 1.1.1	
5	$USS \to ME$	SETUP	[MT Call] Ti = 0
6	$USER \to ME$	Accept Call Set Up	
7	,	CONNECT	
8	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD	
		- Call Connected 1.1.1	
9	$USS \to ME$	DISCONNECT	
10	$USER \to ME$	Initiate Call to "123"	
11	$ME \to USS$	SETUP	[MO Call] Ti = 0
12	$USS \to ME$	CONNECT	
13	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD	
		- Call Connected 1.1.2	
14	$USER \to ME$	End Call	
15	$ME \to USS$	DISCONNECT	

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Connected

## Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
_	01	01										

## TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 05 00 82 02 82 81 83 01 00

#### **EVENT DOWNLOAD - CALL CONNECTED 1.1.1**

Logically:

Event list: Call connected

Device identities

Source device: ME
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

Coding:

BER-TLV: D6 0A 19 01 01 82 02 82 81 1C 01 80

#### **EVENT DOWNLOAD - CALL CONNECTED 1.1.2**

Logically:

Event list: Call connected

Device identities

Source device: Network
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

Coding:

BER-TLV: D6 0A 19 01 01 82 02 83 81 1C 01 80

27.22.7.2.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

27.22.7.2.2 Call Connected Event (ME supporting SET UP CALL)

27.22.7.2.2.1 Definition and applicability

See clause 3.2.2.

27.22.7.2.2.2 Conformance requirement

Additionally the ME shall support the SET UP CALL Proactive UICC Command as defined in:

- TS 31.111 [15] clause 7.5, clause 6.4.13 and clause 6.6.12.

27.22.7.2.2.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Connected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Connected) command.

27.22.7.2.2.4 Method of test

27.22.7.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

## 27.22.7.2.4.2 Procedure

## Expected Sequence 2.1 (EVENT DOWNLOAD -CALL CONNECTED, ME supporting SET UP CALL)

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
		2.1.1	
2	/ 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[EVENT: Call Connected active]
		EVENT LIST 2.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
5	$UICC \to ME$	EVENT LIST 2.1.1 PROACTIVE COMMAND	
5	OICC → IVIE	PENDING: SET UP CALL 2.1.1	
6	ME → UICC	FETCH	
7	, 0.00	PROACTIVE COMMAND: SET UP	ISAT Call
	OIOO / IVIL	CALL 2.1.1	[e/ii can]
8	$ME \rightarrow USER$	ME displays "+012340123456"	ME BEHAVIOUR: SET UP CALL
		during the user confirmation	
		phase.	
9	$USER \to ME$	Confirm call set up	
10	$ME \to USS$	SETUP	Ti=0
11	000 /	CONNECT	
12	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
1.0		CALL 2.1.1	
13	$ME \rightarrow UICC$	ENVELOPE: CALL CONNECTED	
		2.1.1	

## PROACTIVE COMMAND: SET UP EVENT LIST 2.1.1

Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

TERMINAL RESPONSE: SET UP EVENT LIST 2.1.1

Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

#### PROACTIVE COMMAND: SET UP CALL 2.1.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: UICC
Destination device: Network

Alpha identifier: "+012340123456"

Address

TON: International

NPI: "ISDN / telephone numbering plan"

Dialling number string "012340123456"

Coding:

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

#### TERMINAL RESPONSE: SET UP CALL 2.1.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: Only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00	
----------	----	----	----	----	----	----	----	----	----	----	----	----	--

### EVENT DOWNLOAD - CALL CONNECTED 2.1.1

Logically:

Event list: Call connected

Device identities

Source device: Network
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

Coding:

BER-TLV: D6 0A	19 01 01	82 02 83	81 1C	01 80
----------------	----------	----------	-------	-------

## 27.22.7.2.2.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 2.1'.

## 27.22.7.3 Call Disconnected Event

## 27.22.7.3.1 Call Disconnected Event

## 27.22.7.3.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.3.1.2 Conformance requirement

The ME shall support the EVENT: Call Disconnected event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

## 27.22.7.3.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Disconnected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Disconnected) command.

## 27.22.7.3.1.4 Method of test

## 27.22.7.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

## 27.22.7.3.1.4.2 Procedure

## Expected Sequence 1.1 (EVENT DOWNLOAD -CALL DISCONNECTED)

$ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	ected active]
$ \begin{array}{ c c c c c c c c c c c c c c c c c c c$	ected active]
$ \begin{array}{ c c c c c c c c c c c c c c c c c c c$	ected active]
3 UICC → ME PROACTIVE COMMAND: SET UP [EVENT: Call Disconne	ected active]
EVENT LIST 1.1.1	ected active]
4 ME → UICC TERMINAL RESPONSE: SET UP	
EVENT LIST 1.1.1	
5 USS $\rightarrow$ ME SETUP [incoming call] Ti=0	
6 USER → ME Accept Call Set Up	
7 USS $\rightarrow$ ME RELEASE [MT RELEASE]	
8 ME→ UICC ENVELOPE: CALL DISCONNECTED 1.1.1	
9 USS → ME SETUP [incoming call ] Ti=0	
10 USER → ME Accept Call Set Up	
11 USS → ME RELEASE COMPLETE   MT RELEASE COMP	OI ETE1
12 ME→ UICC ENVELOPE: CALL	
DISCONNECTED 1.1.1	
13 USS → ME SETUP [incoming call ] Ti=0	
14 USER → ME Accept Call Set Up	
15 USER → ME End Call	
16 ME → USS DISCONNECT [MO DISCONNECT]	
17 ME → UICC ENVELOPE: CALL	
DISCONNECTED 1.1.2A	
or	
ENVELOPE: CALL	
DISCONNECTED 1.1.2B	
or	
ENVELOPE: CALL	
DISCONNECTED 1.1.2C	
18 USS $\rightarrow$ ME SETUP [incoming call] Ti=0	
19 USER → ME Accept Call Set Up	
20 USS → ME DISCONNECT [MT DISCONNECT + 0	CAUSE: normal call
clearing ]	
21 ME→ UICC ENVELOPE: CALL DISCONNECTED 1.1.3A	
or	
ENVELOPE: CALL	
DISCONNECTED 1.1.3B	
22 USS → ME SETUP Ti=0	
23 USER → ME Accept Call Set Up	
24 USS TX POWER to XX   [RADIO LINK FAILURI	E1
25 ME→ UICC ENVELOPE: CALL	•
DISCONNECTED 1.1.4A or 1.1.4B	

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

## Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Call Disconnected

## Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	02										

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.1

Logically:

Event list: Call Disconnected

Device identities

Source device: Network
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)

Cause:

Coding:

BER-TLV:	D6	0A	19	01	02	82	02	83	81	1C	01	00

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2A

Logically:

Event list: Call Disconnected

Device identities

Source device: ME Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

Coding:

BER-TLV:	D6	0A	19	01	02	82	02	82	81	1C	01	80

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2B

Logically:

Event list: Call Disconnected

Device identities

Source device: ME
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

Cause: normal call clearing

Coding:

BER-TLV:	D6	0E	19	01	02	82	02	82	81	1C	01	80
	9A	02	60	90								

#### EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2C

Logically:

Event list: Call Disconnected

Device identities

Source device: ME
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

Cause: normal call clearing

Coding:

BER-TLV:	D6	0E	19	01	02	82	02	82	81	1C	01	80
	9A	02	E0	90								

### EVENT DOWNLOAD - CALL DISCONNECTED 1.1.3A

Logically:

Event list: Call Disconnected

Device identities

Source device: Network
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Cause: normal call clearing

Coding:

BER-TLV:	D6	0E	19	01	02	82	02	83	81	1C	01	00	
	9A	02	60	90									

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.3B

Logically:

Event list: Call Disconnected

Device identities

Source device: Network
Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Cause: normal call clearing

## Coding:

BER-TLV:	D6	0E	19	01	02	82	02	83	81	1C	01	00
	9A	02	E0	90								

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.4A

Logically:

Event list: Call Disconnected

Device identities

Source device: ME Destination device: **UICC** 

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 1 (bit 8)

Cause: radio link failure

Coding:

BER-TLV:	D6	0C	19	01	02	82	02	82	81	1C	01	80
	9A	00										

#### EVENT DOWNLOAD - CALL DISCONNECTED 1.1.4B

Logically:

Event list: Call Disconnected

Device identities

Source device: ME Destination device: **UICC** 

Transaction identifier:

Ti value: 0 (bit 5-7) Ti flag: 0 (bit 8)

Cause:

radio link failure

Coding:

BER-TLV:	D6	0C	19	01	02	82	02	82	81	1C	01	00
	9A	00										

#### 27.22.7.3.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

#### 27.22.7.4 **Location Status Event**

#### 27.22.7.4.1 Location Status Event (normal)

#### 27.22.7.4.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.4.1.2 Conformance requirement

The ME shall support the EVENT: Location Status event as defined in:

- TS 31.111 [15] clause 7.5 and clause 6.4.16.

## 27.22.7.4.1.3 Test purpose

To verify that the ME informs the UICC that an Event: MM\_IDLE state has occurred using the ENVELOPE (EVENT DOWNLOAD - Location Status) command.

#### 27.22.7.4.1.4 Method of test

## 27.22.7.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

Two cells are defined. Cell 1 has location area code 1 and cell 2 has location area code 2.

MS is in service on Cell 1.

## 27.22.7.4.1.4.2 Procedure

## **Expected Sequence 1.1(EVENT DOWNLOAD -LOCATION STATUS)**

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND	
		PENDING: SET UP EVENT LIST	
		1.1.1	
2	/ 0.00	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		EVENT LIST 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	
_	1100	EVENT LIST 1.1.1	
5	USS	Cell 1 is switched off	
6	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.1	
7	USS	Cell 2 is switched on after Location	
<b>'</b>	033	Status 'No service' has been	
		received in step 6	
8	ME	ME performs cell reselection to cell	
		2	
9	$ME \rightarrow USS$	LOCATION UPDATING	The ME is CS and/or PS registered
		REQUEST or ROUTING AREA	depending on its capabilities
		UPDATE REQUEST	
10	$USS \to ME$	LOCATION UPDATING ACCEPT	
		or ROUTING AREA UPDATE	
		ACCEPT	
11	$ME \rightarrow USS$	TMSI REALLOCATION	
		COMPLETE or ROUTING AREA	
40	ME 11100	UPDATE COMPLETE	Continue A alcall accepts for OFDANI/LITDANI
12	$ME \rightarrow UICC$	ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.2A	[Option A shall apply for GERAN/UTRAN parameters]
		or	Option B shall apply for PCS1900
		ENVELOPE: EVENT DOWNLOAD	parameters]
		- Location Status 1.1.2B	[Note: The inclusion of the location
		2000.001.000.00	information is optional: (If location status
			indicates normal status)

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

## Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Location status

## Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	03										

## TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

## Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

## **EVENT DOWNLOAD - LOCATION STATUS 1.1.1**

Logically:

Event list: Location status

Device identities

Source device: ME
Destination device: UICC
Location status: No service

Coding:

BER-TLV:	D6	0A	19	01	03	82	02	82	81	1B	01	02	
----------	----	----	----	----	----	----	----	----	----	----	----	----	--

### **EVENT DOWNLOAD - LOCATION STATUS 1.1.2A**

Logically:

Event list: Location status

Device identities

Source device: ME Destination device: UICC

Location status: normal service

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0002)

Cell ID Cell Identity Value (0002)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

BER-TLV:	D6	Note 1	19	01	03	82	02	82	81	1B	01	00
	13	Note	00	F1	10	00	02	00	02	Note		

Note 1: Depending on the presence of the Extended Cell Identity Value the length is '13' or '15'

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

## **EVENT DOWNLOAD - LOCATION STATUS 1.1.2B**

Logically:

Event list: Location status

Device identities

Source device: ME
Destination device: UICC

Location status: normal service

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0002) Cell ID Cell Identity Value (0002)

Coding:

BER-TLV:	D6	13	19	01	03	82	02	82	81	1B	01	00
	13	07	00	11	10	00	02	00	02			

## 27.22.7.4.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.5 User Activity Event

## 27.22.7.5.1 User Activity Event (normal)

## 27.22.7.5.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.5.1.2 Conformance Requirement

The ME shall support the EVENT DOWNLOAD -USER ACTIVITY as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.16, clause 6.8, clause 6.6.16, clause 6.11, clause 7.5, clause 8.6 and clause 8.25.

## 27.22.7.5.1.3 Test purpose

To verify that the ME performed correctly the procedure of USER ACTIVITY EVENT.

## 27.22.7.5.1.4 Method of Test

## 27.22.7.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.7.5.1.4.2 Procedure

## **Expected Sequence 1.1 (EVENT DOWNLOAD -USER ACTIVITY)**

See ETSI TS 102 384 [26] in subclause 27.22.7.5.1.4.2, Expected Sequence 1.1.

## 27.22.7.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.6 Idle screen available event

## 27.22.7.6.1 Idle Screen Available (normal)

## 27.22.7.6.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.6.1.2 Conformance requirement

The ME shall support the EVENT: IDLE SCREEN AVAILABLE event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

## 27.22.7.6.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Idle Screen Available has occurred using the ENVELOPE (EVENT DOWNLOAD - IDLE SCREEN AVAILABLE) command.

#### 27.22.7.6.1.4 Method of test

#### 27.22.7.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.7.6.1.4.2 Procedure

## Expected Sequence 1.1 (EVENT DOWNLOAD - IDLE SCREEN AVAILABLE)

See ETSI TS 102 384 [26] in subclause 27.22.7.6.1.4.2, Expected Sequence 1.1.

27.22.7.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

#### 27.22.7.7 Card reader status event

## 27.22.7.7.1 Card Reader Status (normal)

## 27.22.7.7.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.7.1.2 Conformance requirement

The ME shall support the EVENT: Call Card Reader Status event as defined in:

- TS 31.111 [15] clause 4.7, clause 4.9, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, clause 8.25, clause 8.33, annex F, annex G, clause 8.25 and clause 8.7.

## 27.22.7.7.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Card Reader Status has changed using the ENVELOPE (EVENT DOWNLOAD - Card Reader Status) command.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

27.22.7.7.1.4 Method of test

27.22.7.7.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

#### 27.22.7.7.1.4.2 Procedure

# Expected Sequence 1.1 (EVENT DOWNLOAD, Card reader status, Card reader 1, card reader attached, no card inserted)

See ETSI TS 102 384 [26] in subclause 27.22.7.7.1.4.2, Expected Sequence 1.1.

27.22.7.7.1.5 Test requirement

The behaviour of the test is as defined in expected Sequence 1.1.

## 27.22.7.7.2 Card Reader Status(detachable card reader)

## 27.22.7.7.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.7.2.2 Conformance requirement

The ME shall support the EVENT: Call Card Reader Status event as defined in:

- TS 31.111 [15] clause 4.7, clause 4.9, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, clause 8.25, clause 8.33, annex F, annex G, clause 8.25 and clause 8.7.

## 27.22.7.7.2.3 Test purpose

To verify that the ME informs the UICC that an Event: Card Reader Status has changed using the ENVELOPE (EVENT DOWNLOAD - Card Reader Status) command.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen as an example.

27.22.7.7.2.4 Method of test

27.22.7.7.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

#### 27.22.7.7.2.4.2 Procedure

# Expected Sequence 2.1 (EVENT DOWNLOAD, Detachable reader, Card reader 1, detachable card reader not attached, no card inserted)

See ETSI TS 102 384 [26] in subclause 27.22.7.7.2.4.2, Expected Sequence 2.1.

27.22.7.7.2.5 Test requirement

The behaviour of the test is as defined in expected Sequence 2.1.

## 27.22.7.8 Language selection event

## 27.22.7.8.1 Language selection event (normal)

## 27.22.7.8.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.8.1.2 Conformance requirement

The ME shall support the EVENT: LANGUAGE SELECTION event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

#### 27.22.7.8.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Language selection has occurred using the ENVELOPE (EVENT DOWNLOAD - LANGUAGE SELECTION ) command.

#### 27.22.7.8.1.4 Method of test

#### 27.22.7.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The current language shall have been set to English. Another language has to be supported, German is an example.

#### 27.22.7.8.1.4.2 Procedure

## **Expected Sequence 1.1 (EVENT DOWNLOAD - LANGUAGE SELECTION)**

See ETSI TS 102 384 [26] in subclause 27.22.7.8.1.4.2, Expected Sequence 1.1.

27.22.7.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.9 Browser termination event

## 27.22.7.9.1 Browser termination (normal)

## 27.22.7.9.1.1 Definition and applicability

This test is only applicable to ME's that support the EVENT: browser termination event driven information.

## 27.22.7.9.1.2 Conformance requirement

The ME shall support the EVENT: Browser termination event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, , clause 8.25, clause 8.51, annex F and clause 8.7.

## 27.22.7.9.1.3 Test purpose

To verify that the ME informs the UICC of an Event: Browser termination using the ENVELOPE (EVENT DOWNLOAD - Browser Termination) command.

This test applies for MEs which have a browser.

27.22.7.9.1.4 Method of test

27.22.7.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

A valid access to a Wap gateway is required. The default browser parameters (IP address, gateway/proxy identity, called number...) of the tested mobile shall be properly filled to access that gateway.

The Bearer Parameters defined in 27.22.4.26.1.4.1 shall be used.

## 27.22.7.9.1.4.2 Procedure

## **Expected Sequence 1.1 (EVENT DOWNLOAD - Browser termination)**

Step	Direction	Message / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND: SET UP	
		EVENT LIST 1.1.1 PENDING	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: SET UP	[EVENT: Browser termination Status]
		EVENT LIST 1.1.1	
4	$ME \rightarrow UICC$	TERMINAL RESPONSE: SET UP	[Successfully]
		EVENT LIST 1.1.1	
5	User→ME	Launch the browser with the URL	
		selected by the user	
6	ME→USS	The ME attempts to launch the	
		session with the default browser	
		parameters and the URL selected	
_		by the user.	
7	User→ME	Stop the session and the browser.	
8	$ME \rightarrow UICC$	ENVELOPE: BROWSER	
		TERMINATION 1.1.1	

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC Destination device: ME

Event list

Event 1: Browser termination

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82
	99	01	80								

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

## Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

### Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

#### ENVELOPE: EVENT DOWNLOAD BROWSER TERMINATION 1.1.1

## Logically:

Event list

Event 1: Browser termination

Device identities

Source device: ME
Destination device: UICC

Browser termination cause: User termination

Coding:

BER-TLV:	D6	0A	99	01	80	82	02	82	81	B4	01	00	Ì
----------	----	----	----	----	----	----	----	----	----	----	----	----	---

## 27.22.7.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.7.10 Data available event

## 27.22.7.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

Additionally the ME shall support ENVELOPE (EVENT DOWNLOAD - Data available).

## 27.22.7.10.3 Test purpose

To verify that the ME shall send an ENVELOPE (EVENT DOWNLOAD - Data available) to the UICC after the ME receives a packet of data from the server by the BIP channel previously opened.

#### 27.22.7.10.4 Method of test

## 27.22.7.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure. The UICC must have sent the SET UP EVENT LIST to the ME to supply a set of events (event Data available).

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

### GPRS Parameters

Network access name: TestGp.rs User login: UserLog

User password: UserPwd UICC/ME interface transport level

Transport format:UDP Port number: 44444

Data destination address 01.01.01.01

## 27.22.7.10.4.2 Procedure

## **Expected sequence 1.1 (EVENT DOWNLOAD - Data available)**

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	See initial conditions
		OPEN CHANNEL 1.1.1	
2	$ME \rightarrow UICC$	FETCH	
3	$UICC \to ME$	PROACTIVE COMMAND: OPEN	[Command performed successfully]
		CHANNEL 1.1.1	
4	$ME \to USER$	The ME may display channel opening	
_		information	
5	$ME \rightarrow USS$	PDP context activation request	
6	$USS \to ME$	PDP context activation accept	
7	$ME \rightarrow UICC$	TERMINAL RESPONSE: OPEN	
		CHANNEL 1.1.1A	
		or	
		TERMINAL RESPONSE: OPEN	
8	LUCO ME	CHANNEL 1.1.1B PROACTIVE COMMAND PENDING:	
0	$UICC \to ME$	SEND DATA 1.1.1	
9	$ME \rightarrow UICC$	FETCH	
10	$UICC \to ME$	PROACTIVE COMMAND: SEND DATA	
10	OICC -> IVIE	(immediate) 1.1.1	
11	$ME \rightarrow USS$	Transfer of 8 Bytes of data to the USS	[To retrieve ME's port number]
''	IVIL -> 000	through channel 1	[10 Totalovo ME o port Hambor]
12	$ME \rightarrow UICC$	TERMINAL RESPONSE: SEND DATA	[Command performed successfully]
	/ 0.00	(immediate) 1.1.1	, , , , , , , , , , , , , , , , , , , ,
13	$USS \to ME$	Data sent through the BIP channel	
		using the ME's port number, which was	
		retrieved in step 11	
14	$ME \to UICC$	ENVELOPE 1.1.1 (Event-Data	
		Available)	

## PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

## Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC
Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

## Coding:

BER-TLV

D0	42	81	03	01	40	01	82	02	81	82	35
07	02	03	04	03	04	1F	02	39	02	03	E8
47	0A	06	54	65	73	74	47	70	02	72	73
0D	80	F4	55	73	65	72	4C	6F	67	0D	80
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details

Command number:

**OPEN CHANNEL** Command type:

Command qualifier: immediate link establishment

Device identities

Source device: ME Destination device: **UICC** 

Result

General Result: Command performed successfully

Channel identifier 1 and link established or PDP context activated Channel status

Bearer description

Bearer type: **GPRS** 

Bearer parameter:

Precedence Class: 03 Delay Class: 04 Reliability Class: 03 Peak throughput class: 04 Mean throughput class: 31 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
•	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	F8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details

Command number:

**OPEN CHANNEL** Command type:

Command qualifier: immediate link establishment

Device identities

Source device: ME Destination device: **UICC** 

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: **GPRS** 

Bearer parameter:

Precedence Class: 00 Delay Class: 04 Reliability Class: 03 Peak throughput class: 04 Mean throughput class: 31 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							_

#### PROACTIVE COMMAND: SEND DATA 1.1.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: UICC
Destination device: Channel 1

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	21	B6
·	08	00	01	02	03	04	05	06	07			

## TERMINAL RESPONSE: SEND DATA 1.1.1

Logically:

Command details

Command number: 1

Command type: SEND DATA
Command qualifier: Send Immediately

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									_

## ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1

Logically:

Event list

Event: Data available

Device identities

Source device: ME
Destination device: UICC

Channel status

Channel status: Channel 1 open, link established

Channel Data Length

Channel data length: 8 Bytes available in Rx buffer

Coding:

BER-TLV:	D6	0E	99	01	09	82	02	82	81	B8	02	81
	00	B7	01	80								

## 27.22.7.10.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.11 Channel Status event

## 27.22.7.11.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.11.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

Additionally the ME shall support ENVELOPE (EVENT DOWNLOAD - Channel Status).

## 27.22.7.11.3 Test purpose

To verify that the ME shall send an ENVELOPE (EVENT DOWNLOAD - Channel Status) to the UICC after the link dropped between the NETWORK and the ME.

## 27.22.7.11.4 Method of test

#### 27.22.7.11.4.1 Initial conditions

The ME is connected to the USIM Simulator and the System Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

#### **Bearer Parameters**

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

#### **GPRS** Parameters

Network access name: TestGp.rs User login: UserLog User password: UserPwd

# UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

#### 27.22.7.11.4.2 Procedure

# Expected sequence 1.1 (EVENT DOWNLOAD - Channel Status on a link dropped)

Step	Direction	MESSAGE / Action	Comments
1	$UICC \to ME$	PROACTIVE COMMAND PENDING:	
	I	SET UP EVENT LIST 1.1.1	
2	$ME \to UICC$	FETCH	
3	$UICC \to ME$		[EVENT: channel status]
	1	EVENT LIST 1.1.1	
4	$ME \rightarrow UICC$		[command performed successfully]
	1	EVENT LIST 1.1.1	
5	$UICC \to ME$		See initial conditions
	l	OPEN CHANNEL 1.1.1	
6	$ME \rightarrow UICC$	FETCH	
7	$UICC \to ME$	PROACTIVE COMMAND: OPEN	
	1	CHANNEL 1.1.1	
8	$ME \to USER$	The ME may display channel opening information	
9	$ME \to USS$	PDP context activation request	
10	$USS \to ME$	PDP context activation accept	
11	$ME \to UICC$	TERMINAL RESPONSE: OPEN	[Command performed successfully]
	İ	CHANNEL 1.1.1A	
	1	or	
	I	TERMINAL RESPONSE: OPEN	
	I	CHANNEL 1.1.1B	
12	$USS \to ME$	Link dropped	
13	$ME \to UICC$	ENVELOPE 1.1.1 (Event-Channel	
	<u> </u>	Status)	

### PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

# Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC
Destination device: ME

Event list

Event 1: Channel Status

# Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82
	99	01	0A								

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

#### Logically:

Command details

Command number:

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

#### Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00

#### PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

### Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000 Network access name: TestGp.rs

Text String: UserLog (User login)
Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

#### Coding:

#### BER-TLV

D0	42	81	03	01	40	01	82	02	81	82	35
07	02	03	04	03	04	1F	02	39	02	03	E8
47	0A	06	54	65	73	74	47	70	02	72	73
0D	08	F4	55	73	65	72	4C	6F	67	0D	08
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

### Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

#### TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

#### Logically:

Command details

Command number:

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

#### Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

#### ENVELOPE: EVENT DOWNLOAD - Channel Status 1.1.1

## Logically:

Event list

Event: Channel Status

Device identities

Source device: ME
Destination device: UICC

Channel status

Channel status: Channel 1, link dropped

Coding:

BER-TLV:	D6	0B	99	01	0A	82	02	82	81	B8	02	01
·	05											_

#### 27.22.7.11.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

# 27.22.7.12 Access Technology Change event

**TBD** 

#### 27.22.7.13 Local Connection event

TBD

## 27.22.7.14 Network search mode change event

**TBD** 

# 27.22.7.15 Browsing status event

**TBD** 

# 27.22.8 MO SHORT MESSAGE CONTROL BY USIM

# 27.22.8.1 Definition and applicability

See clause 3.2.2.

# 27.22.8.2 Conformance requirement

The ME shall support the MO SEND SHORT MESSAGE CONTROL facility as defined in:

- TS 31.111 [15] clause 7.3.2.

The ME shall also support the SEND SMS facitily as specified in

- TS 31.111 [15] clause 6.4.10

# 27.22.8.3 Test purpose

To verify that for all SMS sending attempts, even those resulting from a SEND SHORT MESSAGE proactive UICC command, the ME shall first pass the RP\_destination\_address of the service center and the TP\_Destination\_Address to the UICC, using the ENVELOPE (MO Short Message CONTROL).

To verify that if the UICC responds with '90 00', the ME shall send the SMS with the address unchanged.

To verify that if the UICC responds with '93 00', the ME shall not send the SMS and may retry the command.

To verify that if the UICC returns response data, the ME shall use the response data appropriately to send the SM as proposed, not send the SM, or send the SM using the data supplied by the UICC.

To verify that, in the case where the initial SM request results from a proactive SEND SHORT MESSAGE, if the MO SMS CONTROL result is "not allowed" or "allowed with modifications", the ME shall inform the UICC using TERMINAL RESPONSE "interaction with call control by UICC or MO short message control by USIM, action not allowed".

#### 27.22.8.4 Method of tests

#### 27.22.8.4.1 Initial conditions

The ME is connected to the System Simulator and the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The MO SMS control service is available in the USIM Service Table.

The SMS service center address in the ME shall be set to '+112233445566778' prior to the execution of the tests.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

#### 27.22.8.4.2 Procedure

# Expected Sequence 1.1 (MO SM CONTROL BY USIM, with Proactive command, Allowed, no modification')

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND	
		SHORT MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT	
		MESSAGE 1.1.1	
4	ME -> USER	Display "Send SM"	[Alpha Identifier]
5	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL	[Option A shall apply for GERAN/UTRAN
		1.1.1A	parameters]
		Or	[Option B shall apply for PCS1900
		ENVELOPE: MO SHORT MESSAGE CONTROL	parameters]
		1.1.1B	
6	UICC -> ME	MO SMS CONTROL RESULT 1.1.1	[ 'Allowed, no modification']
7	ME -> USS	Send SMS-PP Message 1.1	[The ME sends the SM containing SMS-PP
			(SEND SHORT MESSAGE) Message 1.1
			without modification]
8		SMS RP-ACK	
9	ME -> UICC	TERMINAL RESPONSE: SEND SHORT	
		MESSAGE 1.1.1	

#### PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1

#### Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Send SM"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data
Message class class 0
TP-UDL 12

TP-UD "Test Message"

#### Coding:

BER-TLV:	D0	37	81	03	01	13	00	82	02	81	83	85
	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65			

#### SMS-PP (SEND SHORT MESSAGE) Message 1.1

#### Logically:

**SMS RPDU** 

RP-Originator Address not used RP-Destination SMSC Address

TON International number

NPI "ISDN / telephone numbering plan"

Address value "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

**TP-DCS** 

Message coding 8-bit data Message class class 0 TP-UDL 12

TP-UD "Test Message"

#### Coding:

Coding	00	09	91	11	22	33	44	55	66	77	F8	18
	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

#### ENVELOPE MO SHORT MESSAGE CONTROL 1.1.1A

#### Logically:

Device identities

Source device: ME
Destination device: UICC

**RP** Destination Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string '112233445566778'

**TP Destination Address** 

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string '012345678'

**Location Information** 

MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

#### Coding:

Coding	D5	Note 1	02	02	82	81	06	09	91	11	22
	33	44	55	66	77	F8	06	06	91	10	32
	54	76	F8	13	Note 2	00	F1	10	00	01	00
	01	Note 3									

Note 1: Length of BER-TLV is '20' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### ENVELOPE MO SHORT MESSAGE CONTROL 1.1.1B

#### Logically:

Device identities

Source device: ME
Destination device: UICC

**RP** Destination Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string '112233445566778'

**TP Destination Address** 

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string '012345678'

**Location Information** 

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D5	20	02	02	82	81	06	09	91	11	22
_	33	44	55	66	77	F8	06	06	91	10	32
	54	76	F8	13	07	00	11	10	00	01	00
	01										

979

#### MO SHORT MESSAGE CONTROL RESULT 1.1.1

Logically:

MO Short Message control result : '00' = Allowed, no modification

Coding:

BER-TLV: 00 00

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1

Logically:

Command details

Command number:

Command type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00

# Expected Sequence 1.2 (MO SM CONTROL BY USIM, with user SMS, Allowed, no modification')

Step	Direction	Message / Action	Comments
1	USER -> ME	The user makes a SMS with the user data 'Test Message' and sends it to +012345678.	[The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2.
2	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A or ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC -> ME	MO SHORT MESSAGE CONTROL RESULT 1.1.1	[ 'Allowed, no modification']
4	ME -> USS	Send SMS-PP Message 1.2	[The ME sends the SM containing SMS- PP (SEND SHORT MESSAGE) Message 1.2 without modification]
5	USS -> ME	SMS RP-ACK	-

#### SMS-PP (SEND SHORT MESSAGE) Message 1.2

#### Logically:

**SMS RPDU** 

RP-Originator Address not used RP-Destination SMSC Address

TON International number

NPI "ISDN / telephone numbering plan"

Address value "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD value shall not be verified TP-VPF value shall not be verified TP-RP value shall not be verified TP-UDHI value shall not be verified TP-SRR value shall not be verified

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

Coding:

Coding	00	09	91	11	22	33	44	55	66	77	F8	Note 1
	Note 2	01	09	91	10	32	54	76	F8	Note 3		

Note 1: Octet shall not be verified

Note 2: Only the TP-MTI bits shall be verified

Note 3: The remaining octets shall not be verified

# Expected Sequence 1.3 (MO SM CONTROL BY USIM, with Proactive command, Not allowed')

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND SHORT	
		MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1	
4	ME -> USER	Display "Send SM"	[The display of the Alpha Identifier
			shall not be verified]
5	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A	[Option A shall apply for
		or	GERAN/UTRAN parameters]
		ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B	[Option B shall apply for
			PCS1900 parameters]
6	UICC -> ME	MO SHORT MESSAGE CONTROL RESULT 1.3.1	[ 'not Allowed']
7	ME -> UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1	Permanent Problem - Interaction
			with Call Control or MO short
			message control by USIM ]
8	ME→ USS	The ME does not send the Short Message	

MO SHORT MESSAGE CONTROL RESULT 1.3.1

Logically:

MO Short Message control result : '01' = Not Allowed

Coding:

BER-TLV: 01 00

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1

Logically:

Command details

Command number: 01

Command Type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Interaction with call control or MO-SM by USIM permanent problem

Additional information: Action not allowed

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	02	39
	01											

# Expected Sequence 1.4 (MO SM CONTROL BY USIM, with user SMS, Not allowed')

Step	Direction	Message / Action	Comments
1	USER -> ME	The user makes a SMS with the user data 'Test	[The data entered and the ME settings
		Message' and sends it to +012345678.	shall lead to the same SMS-TPDU as
			defined in SMS-PP (SEND SHORT
			MESSAGE) Message 1.2.
2	ME -> UICC	ENVELOPE : MO SHORT MESSAGE CONTROL	[Option A shall apply for GERAN/UTRAN
		1.1.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE : MO SHORT MESSAGE CONTROL	parameters]
		1.1.1B	
3	UICC -> ME	MO SM CONTROL RESULT 1.3.1	[ 'Not allowed']
4	$ME \rightarrow USS$	The ME does not send the Short Message	

# Expected Sequence 1.5 (MO SM CONTROL BY USIM, with Proactive command, Allowed with modifications')

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND SHORT	
		MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT MESSAGE	Send SMS to '+012345678'
		1.1.1	
4	ME -> USER	Display "Send SM"	[Alpha Identifier]
5	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL	[Option A shall apply for GERAN/UTRAN
		1.1.1A	parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE: MO SHORT MESSAGE CONTROL	parameters]
		1.1.1B	
6	UICC -> ME	MO SM CONTROL RESULT 1.5.1	['Allowed with modifications']
7	ME -> USS	Send SMS-PP Message 1.5	[The ME sends the SM containing SMS-
			PP (SEND SHORT MESSAGE) Message
			1.5 with the data provided by the UICC to
			the changed Service Center Address
			'+112233445566779' ]
8	USS -> ME	SMS RP-ACK	
9	ME -> UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE	
		1.5.1	

# MO SHORT MESSAGE CONTROL RESULT 1.5.1

Logically:

MO Short Message control result : '02' = Allowed with modifications

RP Destination\_Address of the Service Center TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string: '112233445566779'

TP Destination Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string: '012345679'

Coding:

02	13	86	09	91	11	22	33	44	55	66
77	F9	86	06	91	10	32	54	76	F9	

SMS-PP (SEND SHORT MESSAGE) Message 1.5

Logically:

SMS RPDU

RP-Originator Address not used RP-Destination SMSC Address

TON International number

NPI "ISDN / telephone numbering plan"

Address value "112233445566779"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345679"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data
Message class class 0
TP-UDL 12

TP-UD "Test Message"

#### Coding:

Coding	00	09	91	11	22	33	44	55	66	77	F9	18
	01	01	09	91	10	32	54	76	F9	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1

Logically:

Command details

Command number: 01

Command Type: SEND SHORT MESSAGE packing not required

Device identities

Source device: ME
Destination device: UICC

Result

General Result: Command performed successfully

#### Coding:

BFR-TI V·	81	03	01	13	00	82	02	82	81	83	01	00

# Expected Sequence 1.6 (MO SM CONTROL BY USIM, with user SMS, Allowed with modifications')

Step	Direction	Message / Action	Comments
1	USER -> ME	The user makes a SMS with the user data 'Test	[The data entered and the ME settings
		Message' and sends it to +012345678.	shall lead to the same SMS-TPDU as
			defined in SMS-PP (SEND SHORT
			MESSAGE) Message 1.2.
2	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL	[Option A shall apply for GERAN/UTRAN
		1.1.1A	parameters]
		or	Option B shall apply for PCS1900
		ENVELOPE: MO SHORT MESSAGE CONTROL	parameters]
		1.1.1B	
3	UICC -> ME	MO SM CONTROL RESULT 1.5.1	[ 'Allowed with modifications']
4	ME-> USS	Send SMS-PP Message 1.6	The ME sends the SM containing SMS-
			PP (SEND SHORT MESSAGE) Message
			1. 6 with the data provided by the UICC to
			the changed Service Center Address
			+112233445566779']
5	USS -> ME	SMS RP-ACK	

#### SMS-PP (SEND SHORT MESSAGE) Message 1.6

# Logically:

**SMS RPDU** 

RP-Originator Address not used RP-Destination SMSC Address

TON International number

NPI "ISDN / telephone numbering plan"

Address value "112233445566779"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD value shall not be verified TP-VPF value shall not be verified TP-RP value shall not be verified TP-UDHI value shall not be verified TP-SRR value shall not be verified

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345679"

Coding:

Coding	00	09	91	11	22	33	44	55	66	77	F9	Note 1
	Note 2	01	09	91	10	32	54	76	F9	Note 3		

Note 1: Octet shall not be verified.

Note 2: Only the TP-MTI bits shall be verified.

Note 3: The remaining octets shall not be verified.

# Expected Sequence 1.7 (MO SM CONTROL BY USIM, with Proactive command, the USIM responds with '90 00', Allowed, no modification)

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1	Send SMS to '+012345678'
4	ME -> USER	Display "Send SM"	[Alpha Identifier]
5	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A or ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
6	UICC -> ME	90 00	
7	ME ->USS	Send SMS-PP	[The ME sends the SM containing SMS- PP (SEND SHORT MESSAGE) Message 1.1 without modification]
8	USS -> ME	SMS RP-ACK	_
9	ME -> UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1	

# Expected Sequence 1.8 (MO SM CONTROL BY USIM, Send Short Message attempt by user, the USIM responds with '90 00', Allowed, no modification)

Step	Direction	Message / Action	Comments
1	$User \to ME$	The user makes a SMS with the user data 'Test	[The data entered and the ME settings
			shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2.
2	$ME \to UICC$		[Option A shall apply for GERAN/UTRAN parameters]
		or	[Option B shall apply for PCS1900
		ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B	parameters]
3	$UICC \to ME$	90 00	
4	$ME \to USS$	Send SMS-PP	[The ME sends the SM containing SMS- PP (SEND SHORT MESSAGE) Message 1.2 without modification]
5	USS -> ME	SMS RP-ACK	

Expected Sequence 1.9void

# 27.22.8.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.9.

# 27.22.9 Handling of command number

# 27.22.9.1 Definition and applicability

See clause 3.2.2.

# 27.22.9.2 Conformance requirement

The ME shall support the facility as defined in ETSI TS 102 223 [16] clause 6.5.1, clause 6.8 and clause 8.6

# 27.22.9.3 Test purpose

To verify that the ME sends a Terminal Response with the Command number equivalent to the value in the corresponding proactive command.

# 27.22.9.4 Method of tests

# 27.22.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

The ME shall support the DISPLAY TEXT command.

#### 27.22.9.4.2 Procedure

# Expected Sequence 1.1 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, successful)

See ETSI TS 102 384 [26] in subclause 27.22.9.4.2, Expected Sequence 1.1.

# 27.22.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1

# Annex A (normative): Details of Test-SIM (TestSIM)

The TestSIM shall be able to present the following data:

#### ANSWER TO RESET

#### Logically:

TS (Initial character):

T0 (Format character): '86' (Following interface characters: TD(1), number of historical characters: 6)

TD1: '00' (Following interface characters: none, Transfer protocol: T=0)

T1: 91 T2: 99 T3: 00 12 T4: T5: C1 T6: 00

#### Coding:

Coding: 3B 86	6 00 91	99 00	12 C1	00
---------------	---------	-------	-------	----

- 1. For a successful outcome of the command "Select MasterFile" the TestSIM shall send SW1/SW2 "9F 1B".
- 2. For a successful outcome of the command "Get Response with Length 1B" on the MasterFile the TestSIM shall respond:

RFU: '00 00' Not allocated memory: '653 bytes' File ID: Master File MF

Type of file:

RFU: 00 00 22 FF 01' Length of following data: 14 bytes'

File characteristics:

Clock Stop: Not allowed Min. frequency for GSM algorithm: 13/8 MHz

3V Technology SIM Technology identification:

disabled

DFs in current directory: EFs in current directory: 8 Number of CHV and admin. Codes: 3 00 RFU byte 18:

CHV1 status:

3 False representations remaining: 000 RFU-bits 7-5: Secret code: Initialized

Unlock CHV1 status:

False representations remaining: 10 RFU-bits 7-5: 000 Secret code: Initialized

CHV2 status:

False representations remaining: 3 RFU-bits 7-5: 000 Initialized Secret code:

Unlock CHV2 status:

10 False representations remaining: 000 RFU-bits 7-5: Secret code: Initialized RFU bytes 23:

Reserved for admin. management: 00 83 00 FF

Status Words

SW1 / SW2: Normal ending of command

#### Coding:

Coding	00	00	02	8D	3F	00	01	00	00	22	FF	01
	0E	9B	02	08	03	00	83	8A	83	8A	00	00
	83	00	FF	90	00							

1. For a successful outcome of the command "Select GSM" the TestSIM shall send SW1/SW2 "9F 1B".

2. For a successful outcome of the command "Select PLMN" the TestSIM shall send SW1/SW2 "9F 0F".

3. EF<sub>PLMN</sub> Information:

RFU-Bytes 1-2: 00 00 File size: 102 bytes File ID: 6F30

Type of File: Elementary file

Byte 8

RFU: 00

Access Condition:

UPDATE: CHV1
READ/SEEK: CHV1
RFU-bits 4-1: 1111
INCREASE: NEVER
INVALIDATE: NEVER
REHABILITATE: NEVER

File Status:

Invalidation status: File not invalidated

Readable/updateable: Not readable/updatable when invalidated

RFU-bits 8-4, 2: 0000 0
Length of following data: 2 bytes
Structure: Transparent

Length of record: 00

The initial coding of the  $\text{EF}_{\text{PLMN}}$  shall be FF FF ... FF (logically: Empty).

# Annex B (normative): Details of terminal profile support

**Table E.1: TERMINAL PROFILE support** 

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
1	1.1	Profile Download	TS 31.111 §5.2	R99	М		PD_Pro_Dvnl
2	1.2	SMS-PP data download	TS 31.111 §5.2	R99	М		PD_SMS_PP
3	1.3	Cell Broadcast data download	TS 31.111 §5.2	R99	M		PD_CB
4	1.4	Menu selection	TS 31.111 §5.2	R99	C267 AND C268		PD_Menu_sel
5	1.5	Bit =1 if SMS-PP data Download supported	TS 31.111 §5.2	R99	M		PD_SMS_PP
6	1.6	Timer expiration	TS 31.111 §5.	R99	М		PD_TExpir
7	1.7	Bit=1 if Call control supported	TS 31.111 §5.2.	R99	C270		PD_CC
8	1.8	Bit=1 if Call control supported	TS 31.111 §5.2	R99	C270		PD_CC
9	2.1	Command result	TS 31.111 §5.2	R99	М		PD_Cmd_Res
10	2.2	Call Control by USIM	TS 31.111 §5.2	R99	C270		PD_CC
11	2.3	Bit=1 if Call control supported	TS 31.111 §5.2	R99	C270		PD_CC
12	2.4	MO short message control by USIM	TS 31.111 §5.2	R99	M		PD_MO_SMS_CC
13	2.5	Bit=1 if Call control supported	TS 31.111 §5.2	R99	C270		PD_CC
14	2.6	UCS2 Entry supported	TS 31.111 §5.2	R99	C203 AND C268		PD_UCS2_entry
15	2.7	UCS2 Display supported	TS 31.111 §5.2	R99	C204 AND C267		PD_UCS2_Display
16	2.8	Bit=1 if Display Text supported	TS 31.111 §5.2	R99	C267		PD_Display_Text
17	3.1	DISPLAY TEXT	TS 31.111 §5.2	R99	C267		PD_Display_Text
18	3.2	GET INKEY	TS 31.111 §5.2	R99	C267 AND C268		PD_Get_Inkey
19	3.3	GET INPUT	TS 31.111 §5.2	R99	C267 AND C268		PD_Get_Input
20	3.4	MORE TIME	TS 31.111 §5.2	R99	М		PD_More_Time
21	3.5	PLAY TONE	TS 31.111 §5.2 TS 11.14, 5	R99	C269		PD_Play_Tone
22	3.6	POLL INTERVAL	TS 31.111 §5.2 TS 11.14, 5	R99	M		PD_Poll_interval
23	3.7	POLLING OFF	TS 31.111 §5.2	R99	М		PD_Polling_Off
24	3.8	REFRESH	TS 31.111 §5.2	R99	М		PD_Refresh
25	4.1	SELECT ITEM	TS 31.111 §5.2	R99	C267 AND C268		PD_Select_Item
26	4.2	SEND SHORT MESSAGE		R99	М		PD_Send_SMS
27	4.3	SEND SS	TS 31.111 §5.2	R99	М		PD_Send_SS
28	4.4	SEND USSD	TS 31.111 §5.2	R99	М		PD_Send_USSD
29	4.5	SET UP CALL	TS 31.111 §5.2	R99	C267 AND C268 AND C270		PD_SetUp_Call

Item	Byte.bit		Ref.	Release	Status	Support	Mnemonic
30	4.6	SET UP MENU	TS 31.111 §5.2	R99	C267 AND C268		PD_SetUp_Menu
31	4.7	PROVIDE LOCAL INFORMATION (LOCI & IMEI)	TS 31.111 §5.2	R99	M		PD_Provide_Local
32	4.8	PROVIDE LOCAL INFORMATION (NMR)	TS 31.111 §5.2	R99	M		PD_Provide_Local_N MR
33	5.1	SET UP EVENT LIST	TS 31.111 §5.2	R99	М		PD_Setup_Evt_List
34	5.2	Event: MT call	TS 31.111 §5.2	R99	C270		PD_MT_Call
35	5.3	Event: Call connected	TS 31.111 §5.2	R99	C270		PD_Call_Conn
36	5.4	Event: Call disconnected	TS 31.111 §5.2	R99	C270		PD_Call_Disc
37	5.5	Event: Location status	TS 31.111 §5.2	R99	M		PD_Loc_Status
38	5.6	Event: User activity	TS 31.111 §5.2	R99	C268		PD_User_Act
39	5.7	Event: Idle screen available	TS 31.111 §5.2	R99	C267		PD_Idle_Scr_Avail
40	5.8	Event: Card reader status	TS 31.111 §5.2	R99	C206		PD_Evt_Rdr_Status
41	6.1	Event: Language selection	TS 31.111 §5.2	R99	C271		PD_Lang_Select
42	6.2	Event: Browser Termination	TS 31.111 §5.2	R99	C212 AND C267 AND C268		PD_Browser_Term
43	6.3	Event: Data available	TS 31.111 §5.2	R99	C223		PD_Data_Avail
44	6.4	Event: Channel status	TS 31.111 §5.2	R99	C223		PD_Evt_Ch_Status
45	6.5	Event:Access Technology Change	TS 31.111 §5.2	Rel-4	M		PD_Evt_ATC
46	6.6	Event: Display Parameters Changed	TS 31.111 §5.2	Rel-4	C218 AND C267		PD_Disp_Resiz
47	6.7	Event: Local Connection	TS 31.111 §5.2	Rel-4	C224		PD_Evt_LC
48	6.8	Event: Network Search Mode Change	TS 31.111 §5.2	Rel-6	M		PD_Evt_NSMC
49	7.1	POWER ON CARD	TS 31.111 §5.2	R99	C206		PD_C_On
50		POWER OFF CARD	TS 31.111 §5.2	R99	C206		PD_C_Off
51	7.3	PERFORM CARD APDU	TS 31.111 §5.2	R99	C206		PD_C_APDU
52	7.4	GET READER STATUS (Card reader status)	TS 31.111 §5.2	R99	C206		PD_Get_Rdr_Status
53	7.5	GET READER STATUS (Card reader identifier)	TS 31.111 §5.2	R99	C208		PD_Get_Rdr_Id
54	7.6	RFU	TS 31.111 §5.2	R99	Х		PD_RFU_54
55	7.7	RFU	TS 31.111 §5.2	R99	X		PD_RFU_55
56	7.8	RFU	TS 31.111 §5.2	R99	Х		PD_RFU_56
57	8.1	TIMER MANAGEMENT (start, stop)	TS 31.111 §5.2	R99	M		PD_Timer_Mgt_Start _Stop
58	8.2	TIMER MANAGEMENT (get current value)	TS 31.111 §5.2	R99	M		PD_Timer_Val
59	8.3	PROVIDE LOCAL INFORMATION (date, time and time zone)	TS 31.111 §5.2	R99	M		PD_Provide_Local_D _Time
60	8.4	Bit=1 if Get Inkey	TS 31.111 §5.2	R99	C268		PD_Get_Inkey
61	8.5	SET UP IDLE MODE TEXT	TS 31.111 §5.2	R99	C267		PD_Stup_Id_Mod_Tx t
62	8.6	RUN AT COMMAND (i.e. class "b" is supported)	TS 31.111 §5.2	R99	C209		PD_Run_AT
63	8.7	Bit=1 if Set UpCall	TS 31.111 §5.2	R99	C267 AND C268 AND C270		PD_SetUp_Call
64	8.8	Bit=1 if Call Control	TS 31.111 §5.2	R99	C270		PD_CC
65	9.1	Bit=1 if Display Text	TS 31.111 §5.2	R99	C267		PD_Display_Text
66	9.2	SEND DTMF command	TS 31.111 §5.2	R99	C270		PD_Send_DTMF

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
67	9.3	Bit = 1 if Provide Local	TS 31.111 §5.2	R99	М		_Provide_Local
		Information (NMR)					
		supported					
68	9.4	PROVIDE LOCAL	TS 31.111 §5.2	R99	M	PC	_Provide_Local_L
	0.5	INFORMATION (language)	TO 04 444 0T 0	500		S	
69	9.5	PROVIDE LOCAL	TS 31.111 §5.2	R99	М	l I.	_Provide_Local_T
		INFORMATION (Timing Advance)				A	
70	9.6	LANGUAGE	TS 31.111 §5.2	R99	C271	Dr	
10	3.0	NOTIFICATION	10 01.111 30.2	103	0271		Lang_nom
71	9.7	LAUNCH BROWSER	TS 31.111 §5.2	R99	C212	PC	Launch_Brws
			· ·		AND		
					C267		
					AND		
70	0.0	DDOMBE LOCAL	TO 04 444 SE 0	D-L4	C268	DE	N Danidala II a a l A
72	9.8	PROVIDE LOCAL INFORMATION (Access	TS 31.111 §5.2	Rel-4	М		)_Provide_Local_A
		Technology)				'	
73	10.1	Soft keys support for	TS 31.111 §5.2	R99	C213	PC	_Softkey_Select_I
		SELECT ITEM			02.0	ter	•
74	10.2	Soft Keys support for SET	TS 31.111 §5.2	R99	C213		_Softkey_SetUp
		UP MENU	_			_N	1enu .
75	10.3	RFU	TS 31.111 §5.2	R99	Х		)_RFU_75
76	10.4	RFU	TS 31.111 §5.2	R99	Х		)_RFU_76
77	10.5	RFU	TS 31.111 §5.2	R99	Х		)_RFU_77
78	10.6	RFU	TS 31.111 §5.2	R99	Х		)_RFU_78
79	10.7	RFU	TS 31.111 §5.2	R99	X		)_RFU_79
80	10.8	RFU	TS 31.111 §5.2	R99	X		)_RFU_80
81	11.1	Maximum number of soft	TS 31.111 §5.2	R99	C214	PL	_Max_SoftKey
82	11.2	keys available ('FF' = RFU)  Maximum number of soft	TS 31.111 §5.2	R99	C214	Dr	D_Max_SoftKey
02	11.2	keys available ('FF' = RFU)	13 31.111 93.2	N99	0214		_iviax_SoftNey
83	11.3	Maximum number of soft	TS 31.111 §5.2	R99	C214	PC	_Max_SoftKey
		keys available ('FF' = RFU)			0		
84	11.4	Maximum number of soft	TS 31.111 §5.2	R99	C214	PD	_Max_SoftKey
		keys available ('FF' = RFU)					
85	11.5	Maximum number of soft	TS 31.111 §5.2	R99	C214	PC	_Max_SoftKey
- 00	44.0	keys available ('FF' = RFU)	TO 04 444 05 0	D00	004.4		May O-fild
86	11.6	Maximum number of soft	TS 31.111 §5.2	R99	C214	PL	_Max_SoftKey
87	11.7	keys available ('FF' = RFU)  Maximum number of soft	TS 31.111 §5.2	R99	C214	Dr	D_Max_SoftKey
07	11.7	keys available ('FF' = RFU)	10 01.111 90.2	133	0214		iviax_Softicey
88	11.8	Maximum number of soft	TS 31.111 §5.2	R99	C214	PD	Max_SoftKey
		keys available ('FF' = RFU)					,
89	12.1	OPEN CHANNEL	TS 31.111 §5.2	R99	C223		_Open_Ch
90	12.2	CLOSE CHANNEL	TS 31.111 §5.2	R99	C223		_Close_Ch
91	12.3	RECEIVE DATA	TS 31.111 §5.2	R99	C223		)_Rx_Data
92	12.4	SEND DATA	TS 31.111 §5.2	R99	C223		Send_Data
93	12.5	GET CHANNEL STATUS	TS 31.111 §5.2	R99	C223		O_Get_Ch_Status
94	12.6	SERVICE SEARCH	TS 31.111 §5.2	Rel-4	C224		)_Serv_Search
95	12.7	GET SERVICE	TS 31.111 §5.2	Rel-4	C224	PD	_Get_Serv_Info
96	12.8	INFORMATION DECLARE SERVICE	TS 31.111 §5.2	Rel-4	C224	Dr	D_Declare_Serv
97	13.1	CSD supported by ME	TS 31.111 §5.2	R99	C224		D_Declare_Serv D_CSD
98	13.2	GPRS supported by ME	TS 31.111 §5.2	R99	C222		)_GPRS
99	13.3	Bluetooth supported by	TS 31.111 §5.2	Rel-4	C225		)_BT
L	<u> </u>	terminal				<u>                                     </u>	
100	13.4		TS 31.111 §5.2	Rel-4	C226		)_IrDA
101	13.5	RS232 Supported by	TS 31.111 §5.2	Rel-4	C227	PD	)_RS232
		terminal		_			
102	13.6	Number of channels	TS 31.111 §5.2	R99	C257	PC	_Nb_Channel
400	40.7	supported by ME	TO 04 444 05 0	D00	0057		NIL OF THE P
103	13.7	Number of channels supported by ME	TS 31.111 §5.2	R99	C257	PD	D_Nb_Channel
<u> </u>	<u> </u>	Subboured by ME	<u> </u>		<u> </u>	<u> </u>	

104 105	13.8		Ref.	Release		
		Number of channels supported by ME	TS 31.111 §5.2	R99	Status C257	Support Mnemonic PD_Nb_Channel
106	14.1	Number of characters supported down the ME	TS 31.111 §5.2	R99	C274	PD_Nb_Char
100	14.2	Number of characters supported down the ME	TS 31.111 §5.2	R99	C274	PD_Nb_Char
107	14.3	Number of characters supported down the ME	TS 31.111 §5.2	R99	C274	PD_Nb_Char
108	14.4	Number of characters supported down the ME	TS 31.111 §5.2	R99	C274	PD_Nb_Char
109	14.5	Number of characters supported down the ME	TS 31.111 §5.2	R99	C274	PD_Nb_Char
110	14.6	No display capability (i.e class "ND" is indicated)	TS 31.111 §5.2	Rel-8	C267	PD_Type_ND
111	14.7	No keypad available (i.e. class "NK" is indicated)	TS 31.111 §5.2	Rel-8	C268	PD_Type_NK
112	14.8	Screen Sizing Parameters	TS 31.111 §5.2	R99	C216	PD_Screen_Siz
113	15.1	Number of characters supported across the ME display	TS 31.111 §5.2	R99	C274	PD_Nb_Char_Disp
114	15.2	Number of characters supported across the ME display	TS 31.111 §5.2	R99	C274	PD_Nb_Char_Disp
115	15.3	Number of characters supported across the ME display	TS 31.111 §5.2	R99	C274	PD_Nb_Char_Disp
116	15.4	Number of characters supported across the ME display	TS 31.111 §5.2	R99	C274	PD_Nb_Char_Disp
117	15.5	Number of characters supported across the ME display	TS 31.111 §5.2	R99	C274	PD_Nb_Char_Disp
118	15.6	Number of characters supported across the ME display	TS 31.111 §5.2	R99	C274	PD_Nb_Char_Disp
119	15.7	Number of characters supported across the ME display	TS 31.111 §5.2	R99	C274	PD_Nb_Char_Disp
120	15.8	Variable size fonts Supported	TS 31.111 §5.2	R99	C274	PD_Var_Font
121	16.1	Display can be resized	TS 31.111 §5.2	R99	C218	PD_Disp_Resiz
122	16.2	Text Wrapping supported	TS 31.111 §5.2	R99	C273	PD_Txt_Wrap
123	16.3	Text Scrolling supported	TS 31.111 §5.2	R99	C273	PD_Txt_Scroll
124	16.4	Text attributes supported	TS 31.111 §5.2	Rel-5	C228	PD_Text_Attrib
125	16.5	RFU	TS 11.14, 5	R96	X	PD_RFU_125
126	16.6	Width reduction when in a	TS 31.111 §5.2	R99	C217	PD_Width_Reduc
127	16.7	menu Width reduction when in a menu	TS 31.111 §5.2	R99	C217	PD_Width_Reduc
128	16.8	Width reduction when in a menu	TS 31.111 §5.2	R99	C217	PD_Width_Reduc
129	17.1	TCP, UICC in client mode	TS 31.111 §5.2	R99	C220	PD_TCP
130	17.2	UDP, UICC in client mode	TS 31.111 §5.2	R99	C221	PD_UDP
131	17.3	TCP, UICC in server mode (i.e. class "k" is supported)	TS 31.111 §5.2	Rel-7	C262	PD_TCP_UICC_ServerMode
132	17.4	TCP, Terminal in server mode (i.e. class "k" is supported)	TS 31.111 §5.2	Rel-7	C263	PD_TCP_Terminal_S erverMode
133	17.5	UDP, Terminal in server mode (i.e. class "k" is supported)	TS 31.111 §5.2	Rel-7	C264	PD_UDP_Terminal_ ServerMode
134	17.6	RFU	TS 31.111 §5.2	R99	Х	PD_RFU_134
135		RFU	TS 31.111 §5.2	R99	Х	PD_RFU_135
136	17.8	HSDPA supported by ME	TS 31.111 §5.2	Rel-6	C258	PD_ HSDPA

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
137	18.1	DISPLAY TEXT (Variable time out)	TS 31.111 §5.	2 Rel-4	C229		PD_Disp_Var_Timeo ut
138	18.2	GET INKEY (help is supported while waiting for immediate response or	TS 31.111 §5.	2 Rel-4	C231		PD_Get_Inkey_Help
		variable time out)			_		
139	18.3 18.4	USB supported by ME GET INKEY (Variable time out)	TS 31.111 §5.	2 Rel-4 2 Rel-4	C232 C229 AND C267 AND C268		PD_USB PD_Get_Inkey_Var_ Timeout
141	18.5	Reserved for 3GPP2: PROVIDE LOCAL INFORMATION (ESN)	TS 31.111 §5.	2 R99	X		Reserved
142	18.6	CALL CONTROL on GPRS	TS 31.111 §5.	2 Rel-5	C242		PD_CC_GPRS
143	18.7	PROVIDE LOCAL INFORMATION (IMEISV)	TS 31.111 §5.	2 Rel-6	М		PD_Provide_Local_S V
144	18.8	PROVIDE LOCAL INFORMATION (search mode change)	TS 31.111 §5.	2 Rel-6	М		PD_Provide_Local_S MC
145	19.1	Protocol Version	TS 31.111 §5.	2 R99	Х		Reserved
146	19.2	Protocol Version	TS 31.111 §5.		Х		Reserved
147	19.3	Protocol Version	TS 31.111 §5.	2 R99	Х		Reserved
148	19.4	Protocol Version	TS 31.111 §5.		Х		Reserved
149	19.5	RFU	TS 31.111 §5.		Х		PD_RFU_149
150	19.6	RFU	TS 31.111 §5.		Х		PD_RFU_150
151	19.7	RFU	TS 31.111 §5.		X		PD_RFU_151
152	19.8	RFU	TS 31.111 §5.	.2 R99	Х		PD_RFU_152
153	20.1	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
154	20.2	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
155	20.3	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
156	20.4	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
157	20.5	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
158	20.6	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
159	20.7	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
160	20.8	Reserved by TIA/EIA/IS- 820 [25]	TS 31.111 §5.		Х		Reserved
161	21.1	WML browser supported	TS 31.111 §5.		C233 AND C267		PD_WML
162	21.2	XHTML browser supported	TS 31.111 §5.	2 Rel-6	C234 AND C267		PD_XHTML
163	21.3	HTML browser supported	TS 31.111 §5.	2 Rel-6	C235 AND C267		PD_HTML
164	21.4	CHTML browser supported	TS 31.111 §5.	2 Rel-6	C236 AND C267		PD_CHTML
165	21.5	RFU	TS 31.111 §5.	2 R99	X		PD_RFU_165
166	21.6	RFU	TS 31.111 §5.		X		PD_RFU_166
167	21.7	RFU	TS 31.111 §5.		Х		PD_RFU_167
168	21.8	RFU	TS 31.111 §5.	.2 R99	Х		PD_RFU_168
169	22.1	Support of UTRAN PS with extended parameters	TS 31.111 §5.	2 Rel-6	C259		PD_UTRAN_PS_Ext _Param


Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	
170	22.2	PROVIDE LOCAL	TS 31.111 §5.2	Rel-6	C239		PD_Provide_Local_B
		INFORMATION (Battery					att
171	20.2	state) if class 'g' supported PLAY TONE (Melody	TS 31.111 §5.2	Dalic	0044		DD M T Tongs
171	22.3	tones & themed tones	15 31.111 95.2	Rel-6	C241		PD_M_T_Tones
		supported)					
172	22.4	Multi-media in SET UP	TS 31.111 §5.2	Rel-6	C240		PD_Xmedia_Call
		CALL supported (if class 'h'					
		supported)					
173	22.5	Toolkit-initiated GBA	TS 31.111 §5.2	Rel-6	C266		PD_Toolkit_GBA
174	22.6	RETRIEVE	TS 31.111 §5.2	Rel-6	C238		PD_Retrieve_MMS
		MULTIMEDIA MESSAGE, (if class "j" is supported)					
175	22.7	SUBMIT MULTIMEDIA	TS 31.111 §5.2	Rel-6	C238		PD_Submit_MMS
		MESSAGE, (if class "j" is	30.2				
		supported)					
176	22.8	DISPLAY	TS 31.111 §5.2	Rel-6	C238		PD_Display_MMS
		MULTIMEDIA MESSAGE,			AND		
177	23.1	(if class "j" is supported) SET FRAMES supported	TS 31.111 §5.2	Rel-6	C267 C237		PD_Set_Frames
177	23.1	(if class 'i' supported)	13 31.111 93.2	Kel-0	0237		FD_Set_Flailles
178	23.2	GET FRAMES STATUS	TS 31.111 §5.2	Rel-6	C237		PD Get Frames Sta
		supported (if class 'i'		110.0	020.		t
		supported)					
179	23.3		TS 31.111 §5.2	Rel-6	C238		PD_MMS_Notificatio
		(if class "j" is					n
180	23.4	supported) Alpha Identifier in	TS 31.111 §5.2	Rel-7	C267		PD_Refresh_Alphald
160	23.4	REFRESH command	13 31.111 95.2	Kei-7	0207		entifier
		supported by					Citation
		terminal					
181	23.5	Geographical Location	TS 31.111 §5.2	Rel-8	C265		PD_Geo_Loaction_R
		Reporting (if class "n" is					eporting
182	23.6	supported) Reserved for 3GPP2:	TS 31.111 §5.2	Rel-6	Х		Reserved
102	23.0	PROVIDE LOCAL	13 31.111 95.2	Kei-o	^		Reserved
		INFORMATION (MEID)					
183	23.7	PROVIDE LOCAL	TS 31.111 §5.2	Rel-6	М		PD_Provide_Local_N
		INFORMATION (UTRAN					MR
101	00.0	NMR)	TO 04 444 0F 0	5.10	0070		DD 1100D DD
184	23.8	USSD Data Download and	18 31.111 §5.2	Rel-6	C272		PD_USSD_DD
185	24.1	application mode  Maximum number of	TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
103	24.1	frames supported (if class	10 31.111 33.2	IXEI-0	0230		D_Wax_Flames
		'i' supported)					
186	24.2	Maximum number of	TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
		frames supported (if class					
197	24.3	'i' supported) Maximum number of	TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
187	24.3	frames supported (if class	13 31.111 85.2	rei-6	U200		FD_INIAX_FIAMES
		'i' supported)					
188	24.4	Maximum number of	TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
		frames supported (if class					
		'i' supported)					
189	24.5	RFU	TS 31.111 §5.2	R99	X	-	PD_RFU_189
190 191	24.6 24.7	RFU RFU	TS 31.111 §5.2 TS 31.111 §5.2	R99 R99	X		PD_RFU_190 PD_RFU_191
191	24.7	RFU	TS 31.111 §5.2	R99	X		PD_RFU_191 PD_RFU_192
193	25.1	Event: browsing status	TS 31.111 §5.2	Rel-6	C267		PD_Browser_Stat
			. 5 5 30.2		AND		
					C268		
194	25.2	Event: MMS Transfer	TS 31.111 §5.2	Rel-6	C238		PD_MMS
		status (if class "j" is					
L	<u> </u>	supported)		1	<u> </u>		<u>I</u>

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support Mnemonic
195	25.3	Event Frame parameters changed (if class 'i' supported)	TS 31.111 §5.2	Rel-6	C237	PD_Event_Frames
196	25.4	Event: I-WLAN Access status (if class "e" is supported)	TS 31.111 §5.2	Rel-7	C260	PD_RFU_Event_I- WLAN
197	25.5	Event: Network Rejection	TS 31.111 §5.2	Rel-8	М	PD_Event_NW_Reje
198	25.6	Reserved by ETSI TS 102 230 [16]	TS 31.111 §5.2	Rel-7	0	PD_Reserved
199	25.7	RFU	TS 31.111 §5.2	R99	Х	PD_RFU_199
200	25.8	RFU	TS 31.111 §5.2	R99	Х	PD_RFU_200
201	26.1	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_201
202	26.2	RFU	TS 31.111 §5.2	Rel-6	Х	PD_RFU_202
203	26.3	RFU	TS 31.111 §5.2	Rel-6	Х	PD_RFU_203
204	26.4	RFU	TS 31.111 §5.2	Rel-6	Х	PD_RFU_204
205	26.5	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_205
206	26.6	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_206
207	26.7	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_207
208	26.8 27.1	RFU RFU	TS 31.111 §5.2	Rel-6 Rel-6	X	PD_RFU_208 PD_RFU_209
209	27.1	RFU	TS 31.111 §5.2 TS 31.111 §5.2	Rel-6	X	PD_RFU_210
211	27.3	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_211
212	27.4	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_212
213	27.5	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_213
214	27.6	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_214
215	27.7	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_215
216	27.8	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_216
217	28.1	Alignment left supported	TS 31.111 §5.2	Rel-5	C243	PD_Text_Attrib_Left
218	28.2	Alignment center supported	TS 31.111 §5.2	Rel-5	C244	PD_Text_Attrib_Cent er
219	28.3	Alignment right supported	TS 31.111 §5.2	Rel-5	C245	PD_Text_Attrib_Righ t
220	28.4	Font size normal supported	TS 31.111 §5.2	Rel-5	C246	PD_Text_Attrib_Nor mal
221	28.5	Font size large supported	TS 31.111 §5.2	Rel-5	C247	PD_Text_Attrib_Larg e
222	28.6	Font size small supported	TS 31.111 §5.2	Rel-5	C248	PD_Text_Attrib_Smal
223	28.7	RFU	TS 31.111 §5.2	Rel-6	Х	PD_RFU_223
224	28.8	RFU	TS 31.111 §5.2	Rel-6	X	PD_RFU_224
225	29.1	Style normal supported	TS 31.111 §5.2	Rel-5	C249	PD_Text_Attrib_Styl_ Norm
226	29.2	Style bold supported	TS 31.111 §5.2	Rel-5	C250	PD_Text_Attrib_Styl_ Bold
227	29.3	Style italic supported	TS 31.111 §5.2	Rel-5	C251	PD_Text_Attrib_Styl_ Italic
228	29.4	Style underlined supported	TS 31.111 §5.2	Rel-5	C252	PD_Text_Attrib_Styl_ Underl
229	29.5	Style strikethrough supported	TS 31.111 §5.2	Rel-5	C253	PD_Text_Attrib_Styl_ Strik
230	29.6	Style text foreground colour supported	TS 31.111 §5.2	Rel-5	C254	PD_Text_Attrib_Styl_ Text_Fore
231	29.7	Style text background colour supported	TS 31.111 §5.2	Rel-5	C255	PD_Text_Attrib_Styl_ Text_Back
232	29.8	RFU	TS 31.111 §5.2	Rel-6	Х	PD_RFU_224
233	30.1	I-WLAN bearer support (if class "e" is supported)	TS 31.111 §5.2	Rel-7	C260	PD_I-WLAN
234	30.2	Proactive UICC: PROVIDE LOCAL INFORMATION (WSID of the current I-WLAN connection)	TS 31.111 §5.2	Rel-7	C260	PD_Provide_Local_ WSID_WLAN

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
235	30.3	TERMINAL APPLICATIONS (i.e. class "k" is supported)	TS 31.111 §5.2	Rel-7	C261		PD_Terminal_Applic ations
236	30.4	"Steering of Roaming" REFRESH support	TS 31.111 §5.2	Rel-7	М		PD_Steering_Of_Ro aming
237	30.5	RFU	TS 31.111 §5.2	Rel-7	Χ		PD_RFU_237
238	30.6	Proactive UICC: Geographical Location Request (if class "n" is supported)	TS 31.111 §5.2	Rel-8	C265		PD_Geo_Loaction_R equest
239	30.7	Reserved by ETSI TS 102 230 [16]	TS 31.111 §5.2	Rel-8	0		PD_Reserved
240	30.8	"Steering of Roaming for I-WLAN" REFRESH support	TS 31.111 §5.2	Rel-8	C260		PD_Steering_Of_Ro aming _I-WLAN

C201	[void]	[void]
C202	[void]	[void]

C203	IF A.1/3 THEN M	O_Ucs2_Entry
C204	IF A.1/15 THEN M	O_Ucs2_Disp
C205 C206	[void] IF A.1/7 THEN M	[void] O_Dual_Slot
C207	IF A.1/12 THEN M	O_BIP_CSD
C208	IF (A.1/7 AND A.1/8) THEN M	O_Dual_Slot AND O_Detach_Rdr
C209 C210	IF A.1/9 THEN M [void]	O_Run_At [void]
C211	[void]	[void]
C212 C213	IF A.1/10 THEN M IF (A.1/11 AND A.1/85) THEN M for at least one of the bits 1 - 2 of	O_LB O_Softkey AND O_No_Type_NK
	byte 10	
C214	IF C213 THEN M for at least one, but not for all of the bits 1 - 8 of byte 11	O_Softkey AND O_No_Type_NK (parameters)
0045	•	Void
C215 C216	Void IF (A.1/13 AND A.1/84) THEN M ELSE O.1	O_Scr_Siz AND O_No_Type_ND O_Scr_Siz AND O_No_Type_ND (parameters)
C217	IF C216 THEN bit values "0" / "1" allowed ELSE O.1	O_Scr_Resiz AND O_No_Type_ND
C218	IF (A.1/14 AND A.1/84) THEN M ELSE O.1	O_Scr_Resiz AND O_No_Type_ND (parameters)
C219	IF (A.1/14 AND A.1/84) THEN bit values "0" / "1" allowed ELSE O.1	O TOP
	IF A.1/18 THEN M	O_TCP O_UDP
C220	IF A.1/17 THEN M	O_BIP_GPRS
C221 C222	IF A.1/21 THEN M IF (C207 OR C222 OR C224) THEN M	O_BIP_CSD OR O_BIP_GPRS OR (O_BIP_Local AND (BIP_BT OR BIP_IrDA OR
C223	,	BIP_RS232 OR BIP_USB))
		O_BIP_Local AND (BIP_BT OR BIP_IrDA OR BIP_RS232 OR BIP_USB))
0001	IF (A1.26 AND (A.1/27 OR A.1/28 OR	O_BIP_Local AND O_BIP_BT
C224	A.1/29 OR A.1/30)) THEN M	O_BIP_Local AND O_BIP_IrDA O_BIP_Local AND O_BIP_RS232
0225	IF (A.1/26 AND A1.27) THEN M	(O_TAT_AL OR O_TAT_AC OR O_TAT_AR
C225 C226	IF (A.1/26 AND A1.28) THEN M IF (A.1/26 AND A1.29) THEN M	OR O_TAT_FSN OR O_TAT_FSL OR O_TAT_FSS OR O_TAT_SN OR O_TAT_SB
C227	IF ((A1./50 OR A.1/51 OR A.1/52 OR A.1/53 OR A.1/54 OR A.1/55	OR O_TAT_SI OR O_TAT_SU OR O_TAT_SS
C228	OR A.1/56 OR A.1/57 OR A.1/58 OR A.1/59 OR A.1/60 OR A.1/61 OR A.1/62) AND A.1/84) THEN M	OR O_TAT_STFC OR O_TAT_STFB) AND O_No_Type_ND
		O_Duration AND O_No_Type_ND
		O_lmm_Resp AND O_No_Type_NK O_Help AND ((O_Duration AND
	IF (A.1/24 AND A.1/84) THEN M	O_No_Type_ND) OR
C229	IF (A.1/23 AND A.1/85) THEN M	(O_Imm_Resp AND O_No_Type_NK)) O_BIP_Local AND O_USB
C230	IF (C229 OR C230) AND A1.5 THEN M	O_WML
C231		O_XHTML O_HTML
	15 (A 4/00 AND A 4/00) TUENLA	O_CHTML
	IF (A.1/26 AND A.1/30) THEN M IF A.1/31 THEN M	O_Frames AND O_No_Type_ND O_MMS
C232	IF A.1/32 THEN M	O_Batt
C233 C234	IF A.1/33 THEN M IF A.1/34 THEN M	O_Xmedia Call AND O_No_Type_ND AND O_No_Type_NK AND O_No_Type_NS
C235	IF (A.1/37 AND A.1/84) THEN M ELSE O.1	O_M_T_Tones AND O_No_Type_NA
C236 C237	IF A.1/38 THEN M IF A.1/35 THEN M	O_CC_GPRS AND O_No_Type_ND O_TAT_AL AND O_No_Type_ND
C238	IF (A.1/36 AND A.1/84 AND A.1/85 AND A.1/87) THEN M	O_TAT_AC AND O_No_Type_ND
C239 C240		O_TAT_AR AND O_No_Type_ND O_TAT_FSN AND O_No_Type_ND
	IF (A.1/82 AND A.1/86) THEN M ELSE O.1	O_TAT_FSL AND O_No_Type_ND
	IF (A.1/16 AND A.1/84) THEN M ELSE O.1	O_TAT_FSS AND O_No_Type_ND O_TAT_SN AND O_No_Type_ND
C241		O_TAT_SB AND O_No_Type_ND
C242	IF (A.1/50 AND A.1/84) THEN M ELSE O.1 IF (A.1/51 AND A.1/84) THEN M ELSE O.1	O_TAT_SI AND O_No_Type_ND O_TAT_SU AND O_No_Type_ND
	IF (A.1/52 AND A.1/84) THEN M ELSE O.1	O_TAT_SS AND O_No_Type_ND
C243 C244	IF (A.1/53 AND A.1/84) THEN M ELSE O.1 IF (A.1/54 AND A.1/84) THEN M ELSE O.1	O_TAT_STFC AND O_No_Type_ND OR O_TAT_STFB AND O_No_Type_ND
C245 C246	IF (A.1/55 AND A.1/84) THEN M ELSE O.1 IF (A.1/56 AND A.1/84) THEN M ELSE O.1	O_Frames AND O_No_Type_ND
C247	IF (A.1/57 AND A.1/84) THEN M ELSE O.1	O_BIP_CSD OR O_BIP_GPRS OR
C248 C249	IF (A.1/58 AND A.1/84) THEN M ELSE O.1 IF (A.1/59 AND A.1/84) THEN M ELSE O.1	(O_BIP_Local AND (BIP_BT OR BIP_IrDA OR BIP_RS232 OR BIP_USB))
C250	IF (A.1/60 AND A.1/84) THEN M ELSE O.1	O_HSDPA
C251 C252	IF (A.1/61 AND A.1/84) THEN M ELSE O.1	O_UTRAN_PS_Ext_Param O_I-WLAN
C253	IF (A.1/62 AND A.1/84) THEN M ELSE O.1	O_Terminal_Applications
C254	IF C237 THEN M for at least one of the bits 1 - 4 of byte 24	O_TCP_UICC_ServerMode O_TCP_Terminal_ServerMode
C255	IF (C207 OR C222 OR C224) THEN M for at least one of the bits 6 -	O_UDP_Terminal_ServerMode
C256	8 of byte 13	O_Geo_Location_Discovery O_Toolkit_GBA
		O_No_Type_ND
C257	IF A.1/66 THEN M IF A.1/67 THEN M	O_No_Type_NK O_No_Type_NA
	IF A.1/70 THEN M	O_No_Type_NS
C258	IF A.1/71 THEN M IF A.1/72 THEN M	O_No_Type_NL O_USSD_Data_DL
C259	IF A.1/72 THEN M	O_No_Type_ND
C260 C261	IF A.1/73 THEN M IF A.1/81 THEN M	O_No_Type_ND
C262	IF A.1/83 THEN M	
	ETSI	
•		



# Annex C (informative): Change history

CP-doc	CR	REV	Meeting	SUBJECT	CAT	NEW_VERS
TP-050016		-	2.0.0	Approved TP-27, March 2005		6.0.0
CP-050144		-	CT-28	Correction of coding in MT Call Event	F	6.1.0
CP-050144		-	CT-28	Correction of applicability table	F	6.1.0
CP-050144		-	CT-28	Essential Corrections	F	6.1.0
CP-050144		-	CT-28	Correction of coding in MT Call Event	F	6.1.0
CP-050144		-	CT-28	Removal of GET RESPONSE references	F	6.1.0
CP-050447		-	CT-29	Rel-6: Correction of release dependent EF values	F	6.2.0
CP-050447		-	CT-29	Correction of applicability and terminal profile support tables	F	6.2.0
CP-050447		-	CT-29	Correction of EF_BDN coding	F	6.2.0
CP-050447		-	CT-29	Incorrect Dialling Number string in clause 27.22.4.13.1 SEQ 1.9 for PCS 1900	F	6.2.0
CP-050447		-	CT-29	Essential corrections in display icons Setup Menu and Select Item	f	6.2.0
CP-050447		-	CT-29	Incorrect Ti Flag value for SET UP 1.4.1 in clause 27.22.4.16.1	F	6.2.0
CP-050447		-	CT-29	Correction of TP-MR (TP Message Reference) of the SMS SUBMIT TPDU submitted to the USS (Network)	F	6.2.0
CP-050447	0013	-	CT-29	Corrections in the Logical description and BER encoding in clause 27.22.6.2 and 27.22.4.11	F	6.2.0
CP-050447	0014	-	CT-29	Incorrect DCS in SMS-CB data download tests	F	6.2.0
CP-050447	0015	-	CT-29	Essential Corrections in clause 27.22.8 MO SHORT MESSAGE CONTROL BY USIM	F	6.2.0
CP-050447	0016	-	CT-29	Introduction of BDN tests for terminals not supporting BDN	В	6.2.0
CP-050447	0017	-	CT-29	Essential Corrections	F	6.2.0
CP-050447	0018	-	CT-29	Incorrect SMS-PP 1.4.1 TPDU in clause 27.22.4.22.1	F	6.2.0
CP-050447	0019	-	CT-29	Missing interactions in Bearer Independent Protocol test cases	F	6.2.0
CP-050447	0020	-	CT-29	Correction of Refresh tests	F	6.2.0
CP-050447		-	CT-29	Applicability of TC 27.22.4.7.1 and TCs related to FDN and BDN	F	6.2.0
CP-050447		-	CT-29	Essential correction to Terminal Profile table E.1	F	6.2.0
CP-050447		-	CT-29	Correction of CB message identifier	F	6.2.0
CP-050447	0025	-	CT-29	Rel-6: Addition of new UCS2 Tests	В	6.2.0
CP-050447	0027	-	CT-29	Incorrect Coding of SMS-PP (Data download) Message in clause 27.22.4.7.1 and 27.22.5.1	F	6.2.0
_	-	-	-	2005-10: Editorial corrections due to the CRs approved at CP-29	-	6.2.1
CP-050495	0028	_	CT-30	Correction of Send SS (UCS2) tests	F	6.3.0
CP-050495		_	CT-30	Essential Corrections in clause 27.22.4.11	F	6.3.0
CP-050495		-	CT-30	Corrections to Select Item (icons support)	F	6.3.0
CP-050495	0031	-	CT-30	27.22.7.4.1 Location Status Event (normal)	F	6.3.0
CP-050495	0032	-	CT-30	Essential Corrections of Set Up Menu test	F	6.3.0
CP-050495	0033	-	CT-30	Correction of applicability table and related addition of missing test sequences	F	6.3.0
CP-050495	0034	-	CT-30	Correction in SMS-PP 1.4.1 TPDU of clause 27.22.4.22.1	F	6.3.0
CP-050495	0035	-	CT-30	Essential Corrections of SMS-PP download message in Refresh test case	F	6.3.0
CP-050495	0036	-	CT-30	Essential Correction in MO SHORT MESSAGE CONTROL BY USIM Deletion of sequence 1.9	F	6.3.0
CP-050495	0037	_	CT-30	Deletion of SEQ 1.3 in clause 27.22.4.13.1	F	6.3.0
CP-060013		_	CT-31	Deletion of Send Data test sequence	F	6.4.0
CP-060013			CT-31	Essential correction of Provide Local Information (IMEI) test	F	6.4.0
CP-060013		-	CT-31	Essential Correction in SEQ 1.8 of clause 27.22.8	F	6.4.0
CP-060013		-	CT-31	Essential correction on 27.22.7.3.1 Call Disconnected Event	F	6.4.0
CP-060013		-	CT-31	Essential correction of Channel Data length in clause 27.22.4.30	F.	6.4.0
CP-060014		-	CT-31	Essential Corrections in clause 27.22.4.11	F	6.4.0
CP-060014		-	CT-31	Essential Corrections in clause 27.22.8 MO SHORT MESSAGE CONTROL BY SIM	F	6.4.0
CP-060014	0049	-	CT-31	Essential correction in SEQ 1.4 of clause 27.22.4.11.1 SEND SS (normal)	F	6.4.0
CP-060014	0047	-	CT-31	Essential corrections of Run AT Command tests	F	6.4.0
CP-060014		-	CT-31	Essential corrections to SET UP CALL test sequences	F.	6.4.0
CP-060015		-	CT-31	Essential Correction in TERMINAL RESPONSE coding of clause 27.22.4.31	F	6.4.0
CP-060015	0056	-	CT-31	Essential corrections to Timer Expiration tests	F	6.4.0
CP-060015		-	CT-31	BER-TLV suppressions	F.	6.4.0
CP-060157		-	CT-31	Add SMS PP Data Download RP-ERROR Test Case	В	6.4.0
CP-060022		-	CT-31	Essential Correction in SEQ 1.7 of clause 27.22.4.13.1	F	6.4.0
CP-060022		_	CT-31	Essential correction of Refresh test	F	6.4.0
CP-060022		-	CT-31	Essential correction of Channel Data length in Result TLV of clause 27.22.4.30	F	6.4.0
CP-060022	0060	-	CT-31	CR 31.124 Rel-6: Insertion of missing REFRESH (IMSI changing	F	6.4.0
J. 000022	5550	l		15. Comment of the control of the co	<u>'</u>	J. 1.0

CP-doc	CR	REV	Meeting	SUBJECT	CAT	NEW_VERS
CD 000000	0057		OT 24	procedure) test cases	F	0.4.0
CP-060022 CP-060241		-	CT-31 CT-32	Essential corrections of references  Proposal to the TS 31.124 Split by referencing the relevant USAT Test	F	6.4.0 6.5.0
CP-060241	0062	-	CT-32	procedures to TS 102 384 Essential corrections on test cases 27.22.6.3 and 27.22.6.4 using record 2 in EF FDN		6.5.0
CP-060241	0063	-	CT-32	Essential corrections on TC 27.22.6.4 sequence 4.1		6.5.0
CP-060241	0064	-	CT-32	Essential corrections on SEND SHORT MESSAGE test cases		6.5.0
CP-060241		=	CT-32	Essential correction of text attributes tests		6.5.0
CP-060241		-	CT-32	Definition of appropriate QoS in BIP test cases related to GPRS for 3G		6.5.0
CP-060241		-	CT-32	Essential correction of Refresh test in 27.22.7.4.2, seq. 2.4		6.5.0
CP-060241		-	CT-32	Essential corrections of RUN AT Command tests		6.5.0
CP-060241		-	CT-32	Essential correction of tables B.1 and E.1	_	6.5.0
CP-060242		-	CT-32	Essential Correction in REGISTER 1.2B message coding of clause 27.22.4.11.1 SEND SS (normal)	F	6.5.0
CP-060242		-	CT-32	Essential correction of 27.22.4.13.1 SET UP CALL, seq 1.4	F	6.5.0
CP-060242		-	CT-32	Essential correction of second card reader test applicability	F	6.5.0
CP-060242 CP-060242		-	CT-32 CT-32	Correction of TON/NPI coding for Call Control Test case Essential corrections on 27.22.4.11.1 sequence. 1.2	F F	6.5.0 6.5.0
CP-060242		-  -	CT-32	Essential correction of BIP tests	F	6.5.0
CP-060389		1	CT-32	Wrong reference inside test requirement of TC 27.22.7.2.2	F	6.6.0
CP-060389		1	CT-33	Essential corrections of applicability table	F	6.6.0
CP-060389		1	CT-33	Essential correction of IMEISV coding for Provide Local Information	F.	6.6.0
CP-060389		1	CT-33	Essential corrections of text attribute tests for Send USSD and Close	F	6.6.0
CP-060389	0090	1	CT-33	Proposal to the TS 31.124 Split by referencing the relevant USAT Test	F	6.6.0
OD 000000	0004	4	OT 00	procedures to TS 102 384	-	0.00
CP-060389 CP-060389		1	CT-33 CT-33	Correction to the UCS2 coding in Setup Call test Essential correction of RUN AT Command for text attribute tests	F F	6.6.0 6.6.0
CP-060389		1	CT-33	Correction of RECEIVE DATA tests	F	6.6.0
CP-060389		1	CT-33	Correction of terminology for USIM Service Table	F	6.6.0
CP-060389		1	CT-33	Correction of 2 <sup>nd</sup> alpha identifier usages in SET UP CALL tests	F	6.6.0
CP-060389		1	CT-33	Correction of various typographical errors	F	6.6.0
CP-060389		1	CT-33	Essential corrections to OPEN CHANNEL text attribute test sequences	F	6.6.0
CP-060389		1	CT-33		F	6.6.0
CP-060389	0076	1	CT-33	Essential corrections on PROVIDE LOCAL INFORMATION test sequences	F	6.6.0
CP-060389	0800	2	CT-33	Essential corrections on test sequences using the TLV data object Location Information	F	6.6.0
CP-060389	0100	2	CT-33	Essential corrections to SET UP CALL (UCS2 Display) test sequences	F	6.6.0
CP-060389	0081	3	CT-33	Essential corrections to REFRESH(normal) test sequence	F	6.6.0
CP-060389	0102	1	CT-33	Essential corrections to SEND SS display tests concerning longForwardedToNumber	F	6.6.0
CP-060475	0086	1	CT-33		F	6.6.0
CP-060475		2	CT-33	Corrections to SET UP CALL test case 27.22.4.13.1	F	6.6.0
CP-060475	0099	1	CT-33	Essential corrections to SEND SS concerning longForwardedToNumber	F	6.6.0
CP-060475		2	CT-33	Corrections to MO SHORT MESSAGE CONTROL BY USIM tests	F	6.6.0
CP-060517		1	CT-33	Essential corrections Set Up Call, seq. 1.9	F	6.6.0
CP-060540		-	CT-34	Correction of APN Coding in Open Channel test case	F	6.7.0
CP-060540			CT-34	Essential corrections of BIP entries in table E.1	F	6.7.0
CP-060540		2	CT-34	Essential correction of Result TLV handling	F	6.7.0
CP-060540		-	CT-34	Essential correction of expected sequence in OPEN CHANNEL test case		6.7.0
CP-060727		-	CT-34	Some of the Applicability table content is missing when printed or in Print Layout mode		6.7.0
CP-060727		1	CT-34	Correction to SET UP CALL	F	6.7.0
CP-060727		-	CT-34	Correction to SEND SS	F	6.7.0
CP-060727		1	CT-34	Addition of REFRESH USIM Application Reset	В	6.7.0
CP-060727		-	CT-34	Essential corrections on SEND SS (UCS2 display) test cases	F	6.7.0
CP-060727		-	CT-34	Essential corrections on REFRESH TC 27.22.4.7.1	F	6.7.0
CP-060727		I	CT-34	Corrections in the interpretation of Katakana Character	F	6.7.0
CP-070063		-	CT-35	Essential correction of 27.22.5.2	F	6.8.0
CP-070063		1	CT-35	Essential correction of Terminal Profile Support table	F	6.8.0
CP-070063 CP-070065			CT-35 CT-35	Essential correction of 27.22.4.13.1 Expected Sequence 1.7 Essential correction of 27.22.4.7, seq. 1.7	F F	6.8.0 6.8.0
CP-070065		<u>-</u>	CT-35	Essential correction of 27.22.4.7, seq. 1.7 Essential correction of TC 27.22.7.4.1	F	6.8.0
CP-070065		-  -	CT-35	CR implementation error correction for 27.22.6.2 SEQ 2.2	F	6.8.0
CP-070065		<del> </del>	CT-35	CR implementation error correction for 27.22.6.2 SEQ 2.2	F	6.8.0
CP-070065		1	CT-35	Essential clarification of Network Simulator selection	F	6.8.0
CP-070065		1	CT-35	Essential correction of 27.22.4.7.2 SEQ 2.2	F	6.8.0
CP-070065		2	CT-35	Addition of new expected sequence to the SMS-PP Data Download test	C	6.8.0
1 3000				case		

CP-doc	CR	REV	Meeting	SUBJECT	CAT	NEW_VERS
CP-070065	0125	2	CT-35	Addition of a new expected sequence to the SMS-CB Data Download	F	6.8.0
				test case		
CP-070297	0127	2	CT-36	Essential correction of test case applicability	F	6.9.0
CP-070297		-	CT-36	Correction of 27.22.4.2 applicability	F	6.9.0
CP-070297	0129	1	CT-36	Essential correction of test case applicability for 27.22.6.1	Α	6.9.0
CP-070297		1	CT-36	Essential correction on 27.22.8	Α	6.9.0
CP-070297		-	CT-36	Essential correction on 27.22.5.1	F	6.9.0
CP-070297		-	CT-36	Essential correction on 27.22.4.11.1 sequence. 1.4 B	F	6.9.0
CP-070297	0133	-	CT-36	Correction of reference to ISO/IEC 7816-3	A	6.9.0
-	-	-	2007-06	Update to Rel-7 version (MCC)	-	7.0.0
CP-070610		1	CT-37	Essential Correction to 27.22.6.2	F	7.1.0
CP-070619		-	CT-37	Essential correction of variable timeout test case applicability	F	7.1.0
CP-070610		-	CT-37	Essential correction to 27.22.4.13.1, seq. 1.9	F	7.1.0
CP-070619		-	CT-37	Essential Correction to 27.22.6.1, Seq. 1.1	F	7.1.0
CP-070619		-	CT-37	Essential correction of references	F	7.1.0
CP-070619		1	CT-37	Essential correction of 27.22.4.13.1, sequence 1.7	F	7.1.0
CP-070619		1	CT-37	Test Cases dependant on Radio Access Clarification	F	7.1.0
CP-070619		-	CT-37	Essential correction of 27.22.4.7.1, sequence 1.6	F	7.1.0
CP-070843	0145	1	CT-38	Essential correction of 27.22.8, sequence 1.3 in order to remove verification of the Alpha Identifier	Α	7.2.0
CP-070843	0154	1	CT-38	Essential correction of 27.22.4.7.1, sequence 1.6 caring of the missing requirements in TS 31.111	Α	7.2.0
CP-070843	0146	1	CT-38	Essential correction of 27.22.4.26.2.4.2, seq. 2.2 in order to remove the possibility of retrieving a deleted previously visited URL	Α	7.2.0
CP-070843	0155	-	CT-38	Correction to add optional support of Call Hold Supplementary Service	Α	7.2.0
CP-070847		-	CT-38		F	7.2.0
CP-070847		-	CT-38	Essential correction on test case 27.22.4.5.1	F	7.2.0
CP-070847	0150	-	CT-38	Definition of test sequence 1.7 in test case 27.22.4.15	F	7.2.0
CP-070847	0151	-	CT-38	Definition of test sequence 1.12 and 1.13 in test case 27.22.4.15	F	7.2.0
CP-070847	0152	-	CT-38	Essential correction on test case 27.22.4.28.2.1 correcting wrong	F	7.2.0
				implementation of CR 0078 rev1 in C6-060547		
CP-070847	0148	1	CT-38	Introduction of Rel-7 test case applicability	F	7.2.0
CP-080172	0156	-	CT-39	Essential correction to 27.22.4.15	F	7.3.0
CP-080172		-	CT-39	Essential correction of 27.22.8, seq. 1.3	F	7.3.0
CP-080172	0158	1	CT-39	Essential correction regarding terminal capabilities	F	7.3.0
CP-080172	0159	-	CT-39	Essential correction to network dependency of several tests	F	7.3.0
CP-080388	0160	1	CT-40	Essential correction of icon test case applicability	F	7.4.0
CP-080388	0161	2	CT-40	Essential correction to 27.22.6.4	F	7.4.0
CP-080388	0163	3	CT-40	Essential correction of test case applicability of 27.22.6.2 and 27.22.4.11	F	7.4.0
CP-080588		_	CT-41	Essential correction of TC 27.22.4.12.1 Seq. 1.6	F	7.5.0
CP-080588			CT-41	Essential correction of test case applicability	F	7.5.0
CP-080588		-	CT-41	Essential correction of TC 27.22.7.8.1	F	7.5.0
CP-080906	0168	-	CT-42	Essential correction of TC 27.22.6.5 seq. 5.1 applicability	F	7.6.0
CP-080906		-	CT-42	Essential correction of bearer parameters in browser tests	F	7.6.0
CP-080948	0170	3	CT-42	Pre-conditions for Launch browser	Α	7.6.0
CP-080948	0171	-	CT-42	Essential correction of 27.22.4.26.2 Seq. 2.2	Α	7.6.0
	-	-	SP-42	Upgrade to Rel-8	-	8.0.0
CP-080194	0173	1	CT-43	Inclusion of Rel-8 test case applicability and Rel-8 feature indication in the terminal profile content	F	8.1.0
CP-080194	0174		CT-43	Essential correction of tables B.1 and E.1	F	8.1.0
CP-080194		1	CT-43	Essential correction to BIP tests - usage of ME's default channel identifier	A	8.1.0
CP-090459	0175	2	CT-44	Introduction of steering of roaming test cases	В	8.2.0
CP-090459 CP-090460		3 1	CT-44		F	8.2.0
01 -030400	0111		01-44	USAT capabilities	'	0.2.0

# History

Document history					
V8.0.0	February 2009	Publication			
V8.1.0	April 2009	Publication			
V8.2.0	July 2009	Publication			