PRODUCT :
 2.0"
 TFT

 MODEL NO. :
 HT020K1QC36S

 VERSION:
 V1. 2

 DATE :
 2015/3/08

CUSTOMER:_____

SPECIFICATION

FOR

HT020K1QC36S

V 1.2

| Customer Confirmation column | | | | | | | |
|---|--|---|---|--|--|--|--|
| Approved | by: | _Dept.: | _Data: | | | | |
| Please retur you receive of this spec | rn one of the copies of the this document. If it is not cification document. | specifications with your signa t returned, we will assume that | ture to us within two weeks after you agree to the entire contents | | | | |

| HaoRan Display Confirmation column | | | | | | | |
|------------------------------------|-----------------------|-------------|-------------|--|--|--|--|
| Design: | Check: | Approval: | | | | | |
| | Shenzhen HaoRan Displ | ay Co., Ltd | | | | | |
| 08/3/2015 | 1/17 | | Version 1.2 | | | | |
| | | | | | | | |

CONTENTS

| No. | ITEM | PAGE |
|------|-------------------------------|------|
| | COVER | 1 |
| | CONTENTS | 2 |
| | RECORD OF REVISIONS | 3 |
| 1.0 | COMPOSITION | 4 |
| 2.0 | MECHANICAL SPECIFICATIONS | 4 |
| 3.0 | ELECTRICAL SPECIFICATIONS | 5 |
| 4.0 | DIMENSIONAL DIAGRAM | 6 |
| 5.0 | TERMINAL FUNCTIONS | 7 |
| 6.0 | BLOCK DIAGRAM | 8 |
| 7.0 | OPTICAL CHARACTERISTICS | 9 |
| 8.0 | RELIABILITY | 13 |
| 9.0 | STANDARDS OF INSPECTION ITEMS | 14 |
| 10.0 | PRECAUTIONS | 15 |
| 11.0 | FINAL REMARKS | 16 |

RECORDE OF REVISIONS

| VERSION NO. | REVISION DETA | PAGE | DESCRIPTION |
|----------------|------------------|------|-------------------------|
| 1.0 | 2014/3/26 | 16 | NEW RELEASED |
| 1.1 | 2014/6/08 | 16 | MODIFY THE OUTLINE SIZE |
| 1.2 | 2015/3/08 | 16 | MODIFY THE BACKLIGHT |

1.0 COMPOSITION

| Display type: | [176(RGB) ×220 Dots, TFT LCD Module] |
|------------------------|--------------------------------------|
| View Direction: | [6 O'clock] |
| Backlight: | [LED B/L White] |
| Driver IC: | [ILI9225G] |
| Operating temperature: | [-20~+70°C] |
| Storage temperature: | [-30~+80°C] |

2.0 MECHANICAL SPECIFICATIONS

| ITEM | STANDARD VALUES | UNITS |
|-------------------|-----------------|--------|
| LCD type | 2.0" TFT | |
| Pixel arrangement | 176(RGB)×220 | pixels |
| Module size | 37.68×51.3×2.45 | mm |
| Active area | 31.68 × 39.6 | mm |
| Pixel Pitch | 180×180 | um |
| Viewing direction | 6 O'clock | |

3.0 ELECTRICAL SPECIFICATIONS

3.1 TFT-LCD Module Characteristics

| ITEM | SYMBOL | CONDITIONS | MIN | ТҮР | MAX | UNITS |
|--------------------------|--------|------------|------------------|-----|-------------------------|-------|
| Power-supply Voltage | VDD | Ta = 25 °C | 2.3 | 2.8 | 3.3 | |
| DC/DC Super Voltage | VCI | Ta = 25 °C | 2.3 | 2.8 | 3.3 | V |
| Input Valtaga | VIH | H level | $0.8 \times VDD$ | _ | VDD | |
| niput vonage | VIL | L level | VSS | | $0.2 \times \text{VDD}$ | |
| Supply Current For Logic | IDD | VDD= 2.8V | | 3 | | mA |
| LCD Frame Frequency | FLM | | | 60 | | Hz |

3.2 Backlight Characteristics

| ITEM | SYMBOL | CONDITIONS | MIN | ТҮР | MAX | UNITS |
|-----------------|--------|------------|------|------|-----|-------|
| Forward voltage | VF | | | 3.2 | | V |
| Uniformity | AVG | IF=30mA | 80 | 85 | _ | % |
| Luminance | Lv | | 3800 | 4200 | _ | Cd/m2 |

4.0 DIMENSIONAL DIAGRAM



PRODUCT SPECIFICATION

5.0 TERMINAL FUNCTIONS

| Pin | Symbol | I/O | Description |
|-------|-------------|-----|------------------------------|
| 1~8 | DB15~DB8 | I/O | Parallel interface data bus |
| 9 | GND | Ι | System Ground |
| 10~17 | DB7~DB0 | I/O | Parallel interface data bus |
| 18 | IOVCC | | Power supply voltage |
| 19 | VCI/VCC | Ι | Power supply voltage |
| 20 | /RD | Ι | Read signal |
| 21 | /WR | Ι | Write signal |
| 22 | RS | Ι | Data/command Register select |
| 23 | /CS | Ι | Chip select |
| 24 | /RESET | Ι | Reset signal |
| 25 | IMO | Ι | Mcu interface select |
| 26 | GND | Ι | System Ground |
| 27 | LEDA | Ι | Backlight unit(+) |
| 28~30 | LEDK1~LEDK3 | Ι | Backlight unit(-) |
| 31 | YU(NC) | Ι | Touch panel unit |
| 32 | YD(NC) | Ι | Touch panel unit |
| 33 | XR(NC) | Ι | Touch panel unit |
| 34 | XL(NC) | Ι | Touch panel unit |
| 35 | NC | Ι | No connection |
| 36 | NC | Ι | No connection |

6.0 BLOCK DIAGRAM



7.0 OPTICAL CHARACTERISTICS

7.1 Measurement Parameter

| ITEM | | SYMBOL | | CONDITIONS | MIN | ТҮР | MAX | UNITS |
|-------------------------------------|-------------------------|---------------------------------|----------------|--|-------|-------|-------|-------------------|
| Viewing Angle | | Hor | θL | | - | 45 | - | |
| | | | θR | $C/R \ge 10$ | - | 45 | - | |
| | | Her | φH | B/L On | - | 30 | - | Deg |
| | | • | φL | | - | 60 | - | |
| Luminance Of White(Center Point) | | , | Y _L | | - | 250 | - | cd/m ² |
| Contrast Ratio | | 0 | C/R | | 150 | 250 | - | - |
| Response Time | Rising: T _R | T _R + T _F | | | _ | 30 | 50 | ms |
| | Falling: T _F | | | $\phi = 0$ $\theta = 0^{\circ}$ Normal | | | | |
| | White | | | | 0.278 | 0.308 | 0.338 | |
| | wine - | у | | | 0.316 | 0.346 | 0.376 | |
| | Red | Del | X | Viewing Angle B/L On | 0.603 | 0.633 | 0.663 | |
| Color | Ked | | у | | 0.299 | 0.329 | 0.359 | |
| Chromaticity | Green | | X | | 0.264 | 0.294 | 0.324 | |
| | Gitteli | | У | | 0.546 | 0.576 | 0.606 | |
| | Blue | | X | | 0.103 | 0.133 | 0.163 | |
| | Diuc | | у | | 0.092 | 0.122 | 0.152 | |

7.2 Measurement System

Notes:

- Definition of Contrast Ratio (CR): The contrast ratio can be calculated by the following expression. Contrast Ratio (CR) = L63 / L0 L63: Luminance of gray level 63 L 0: Luminance of gray level 0 CR = CR (10) CR (X) is corresponding to the Contrast Ratio of the point X at Figure 4
- 2. Surface luminance is the center point across the LCD surface 500mm from the surface with all pixels displaying white. For more information see FIG 1.
- 3. Response time is the time required for the display to transition from white to black (Rising Time, Tr) and from black to white (Falling Time, Tf). For additional information see FIG 2.
- 4. Viewing angle is the angle at which the contrast ratio is greater than 10. The angles are determined for the horizontal or x axis and the vertical or y axis with respect to the z axis which is normal to the LCD surface. For more information see FIG 3.

FIG. 1 Measurement Set-Up:

The LCD module should be stabilized at a given temperature for 20 minutes to avoid abrupt temperature change during measuring. In order to stabilize the luminance, the measurement should be executed after lighting Backlight for 20 minutes in a windless room.



FIG. 2 The definition of Response Time



FIG. 3 The definition of Viewing Angle

Use Fig. 1(Test Procedure) under Measurement System to measure the contrast from the measuring direction specified by the conditions as the following figure.



FIG.4



8.0 RELIABILITY

| ITEM | CONDITIONS | CRITERIA |
|----------------------------|-----------------------------------|---|
| High temperature operation | 70°C±2°C for120 hours | |
| Low temperature operation | -20 °C \pm 2°C for 120 hours | |
| High humidity storage | 50 °C \pm 5°C, 90 % RH for | |
| | 120 hours | |
| High temperature storage | 80 °C \pm 2°C for 200 hours | |
| Low temperature storage | -30 °C \pm 2°C for 200 hours | |
| Temperature cycling | -20 °C±2°C (30 min) | |
| | $\downarrow\uparrow$ | |
| | 25 °C±2°C (5 min) | No defect in cosmetic |
| | $\downarrow\uparrow$ | |
| | 70 °C±2°C (30 min) | |
| | Cycles: 10 | |
| Vibration | Frequency: 10Hz | Total current |
| | ~55Hz~10Hz | consumption below |
| | Amplitude: 1.5mm | double of initial value. |
| | Each Direction (X, Y, Z): | |
| | 3hours (Packing condition) | |
| Hitting durability | 250,000 times min. (Tip | |
| | R12.5) 250g,60 次/1min | |
| Pen sliding durability | 100,000 times min. (Tip | |
| | R0.8mm) 250g, 60mm/s | |
| | | |

Note:

- 1) The test samples should be applied to only one test item.
- 2) Sample size for each test item is 5~10pcs.
- 3) For Damp Proof Test, pure water(Resistance>1M Ω) should be used.
- 4) In case of malfunction defect caused by ESD damage, if it would be recovered to normal state after resetting, it would be judged as a good part.
- 5) EL evaluation should be excepted from reliability test with humidity and temperature: Some defects such as black spot/blemish can happen by natural chemical reaction with humidity and fluorescence EL has.
- 6) After the reliability test, the test samples should be inspected after 2 hours at least.
- 7) Functional test is OK. Missing segment, shorts, unclear segment, non display, display abnormally, liquid crystal leak are not allowed.
- 8) After testing, the current Idd should be within initial value ±20%.

No low temperature bubbles ,end seal loose and fall, frame rainbow, ACF bubble growing are allowable in the appearance test.

9.0 STANDARDS OF INSPECTION ITEMS

| Product condition 1.1 The part number is inconsistent with work order of product Major 01 1.2 Mixed product types Major 02 quantity The quantity is inconsistent with work order of product Major 03 Outline dimension product dimension and structure must conform to structure diagram Major 04 electrical test 4.1 Missing line character and icon. Major 04 assembled in inverse direction or no display Major 04 4.1 Missing line character and icon. Major 04 4.1 CD viewing angle defect. Major 05 Black or white dot. scratch. contamination Round type: B area 06 Inter type Round type: Don't count Don't count 06 Inter type Inter type: Inter type: Don't count Minor 06 Inter type Inter type: Inter type: Inter type: Inter type: Minor 07 Touch Panel Inter type: Inter type: Inter type: Don't count Major 08 Backligh | NO | Item | | Crit | erion | | | Level | | |
|--|--------------------|------------------------------|---|------------------------------------|---------------|-------------------|-------------|---------------------------------------|--|--|
| 01 1.2 Mixed product types Major 02 quantity The quantity is inconsistent with work order of product Major 03 Outline dimension product dimension and structure must conform to structure diagram Major 04 4.1 Missing line character and icon. Major 04 4.1 Missing line character and icon. Major 04 4.1 CD viewing angle defect. Major 05 Black or white dot, scratch, contamination Round type: Major Major 05 Black or white dot, scratch, contamination Round type: Don't count Don't count 06 \checkmark 1, with the type: Intertype: Intertype: Don't count Minor 06 \checkmark 1, with the type: Intertype: Intertype: Intertype: Minor 06 \checkmark 1, No function. A area B area Don't count Don't count Minor 07 Touch Panel Intertype must match type in specification sheet. Major 08 Backlight clements 8.1 Light leaks to induce deficiency lightness . Major 09 Flexible Printed Circuit 8.1 Light leaks to induce deficiency lightness . Major <td></td> <td>Product condition</td> <td>1.1 The part nu</td> <td>mber is inconsister</td> <td>t with work</td> <td>order of produc</td> <td>et</td> <td>Major</td> | | Product condition | 1.1 The part nu | mber is inconsister | t with work | order of produc | et | Major | | |
| $\begin{array}{ c c c c c c c c c c c c c c c c c c c$ | 01 | | 1.2 Mixed proc | luct types | | | | Major | | |
| 02 quantity The quantity is inconsistent with work order of product Major 03 Outline dimension product dimension and structure must conform to structure diagram Major 04 electrical test 4.1 Missing line character and icon. Major 04 4.2 No function or no display Major 04 4.3 Display malfunction Major 4.3 Display malfunction Major 4.4 LCD viewing angle defect. Major 05 Back or white dot. scratch. contamination Round type: 06 $\phi \leq 0.15mm$ Don't count 07 χ_x Don't count 08 $\mu \approx \psi$ Λ 07 Touch Panel 7.1 No function. 08 Backlight elements 7.1 No function. 08 Backlight elements 8.1 Light leaks to induce deficiency lightness . Major 09 Flexible Printed Circuit 9.3 Aper oral circuits in components on FPC. Major 09 Flexible Printed Circuit 9.3 Apat of circuits in components on FPC. Major 9.4 The crack is in circuits in components | | | 1.3 assembled | in inverse direction | on | | | Major | | |
| 03 Outline dimension product dimension and structure must conform to structure diagram Major 04 electrical test 4.1 Missing line character and icon. Major 04 4.3 Display malfunction Major 4.3 Display malfunction Major 4.4 LCD viewing angle defect. Major 05 Black or white dot, scratch, contamination Round type Round type: B area | 02 | quantity | The quantity is | inconsistent with | work order | r of product | | Major | | |
| $ \begin{array}{c c c c c c c c c c c c c c c c c c c $ | 03 | Outline dimension | product dimens | sion and structure n | nust conform | n to structure di | agram | Major | | |
| 04 4.2 No function or no display Major 05 4.2 No function or no display Major 05 Black or white dot, scratch, contamination Round type $\Phi=(X+Y)/2$ Round type: Dimension (diameter : Φ) A cceptance (Q'ty) 06 $\Phi=(X+Y)/2$ Dimension (diameter : Φ) A cceptance (Q'ty) Minor 06 $I_{X,Y}$ Ine type Don't count Don't count Minor 06 $I_{X,Y}$ Ine type: Ine type: Ine type: Minor Minor 06 $I_{X,Y}$ Ine type: Ine type: Ine type: Minor Minor 06 $I_{X,Y}$ Ine type: Ine type: Ine type: Minor Minor 06 $I_{X,Y}$ Ine type: Ine type: Ine type: Minor Minor 06 $I_{X,Y}$ Ine type: Ine type: Ine type: Minor Minor 07 Touch Panel Ine type: Ine type in specification sheet. Major 08 Backlight elements 8.1 Light leaks to induce deficiency lightness . Major 08 Backlight elements 8.2 Backlight dosan | | electrical test | 4.1 Missing lin | e character and ico | n. | | | Major | | |
| $\begin{array}{ c c c c c c c c c c c c c c c c c c c$ | 04 | | 4.2 No function | n or no display | | | | Major | | |
| | | | 4.3 Display ma | lfunction | | | | Major | | |
| Black or white dot, scratch, contamination Round type $\Phi = (X+Y)/2$ Round type: Dimension (diameter : Φ)Acceptance (Q'ty) A areaMinor0 $\Phi \le 0.15mm$ Don't countDon't countMinor0 $\Phi \le 0.25mm$ 0Don't countMinor0 $\Phi \ge 0.25mm$ $\Phi \ge 0.25mm$ Don't countMinor0 $\Phi \ge 0.25mm$ $0.05mm$ Don't countMinor0 $\Phi \ge 0.25mm$ $0.05mm$ 2 Don't count0 $\Phi \ge 0.35mm$ $0.05mm$ 2 Don't count1 $E \ge 25mm$ $0.03mm < W \le 0.05mm$ 2 Don't count0 $Touch$ Panel7.1 No function.Major0Touch Panel7.2 The circuitry type must match type in specification sheet.Major0 $T \ge 0.5mm$ $T \ge 0.5mm$ Major0 $R = Reklight$ elements8.1 Light leaks to induce deficiency lightnessMajor0 $R = Reklight$ elements8.1 Light leaks to induce deficiency lightnessMajor0 $R = Reklight$ elements8.1 Light leaks to induce deficiency lightnessMajor0 $R = Reklight$ elements $R = Reklight doesn't light or color is wrong.R = Reklight $ | | | 4.4 LCD viewi | 4.4 LCD viewing angle defect. | | | | | | |
| $\begin{array}{c c c c c c c c c c c c c c c c c c c $ | | Black or white | Round type: | Round type: | | | | | | |
| dot, scratch, contamination Round type $\Phi=(X+Y)/2$ $Distribution (diameter 1.47)$ A areaB area Don't count05Round type $\Phi=(X+Y)/2$ $\Phi \equiv 0.15mm$ Don't countDon't countDon't count0 $\Phi \equiv 0.15mm$ 0Don't countDon't countMinor0 $\Phi \equiv 0.25mm$ 0Don't countDon't countMinor06 \downarrow \downarrow \downarrow \downarrow \downarrow \downarrow 06 \downarrow \downarrow \downarrow \downarrow \downarrow \downarrow 07 \downarrow \downarrow \downarrow \downarrow \downarrow \downarrow \downarrow 07Touch Panel7.1 No function. A area B area $=$ \downarrow \downarrow 08 $Backlight$ elements8.1 Light leaks to induce deficiency lightnessMajor09Flexible Printed Circuit9.1 FPC PIN type is inconsistent with specification sheet.Major09 P P P P P P 09 P P P P P P 00 P P P P P P 00 P | | | Dimension (diameter : Φ) Acceptance (Q'ty) A area B area | | | | | | | |
| 05containation Round type $\Phi = (X+Y)/2$ $\Delta \equiv 0.15 \text{mm}$ $\Phi \equiv 0.25 \text{mm}$ Don't countDon't countMinor0 $\Phi \ge 0.25 \text{mm}$ 0Don't count $\Phi \ge 0.25 \text{mm}$ 0Don't countMinor06 \downarrow_X 06 \downarrow_X | | dot, scratch, | Dimensio | | A area | | B area | | | |
| $\begin{array}{c c c c c c c c c c c c c c c c c c c $ | 05 | contamination | Φ≦ | 0.15mm | Don't cou | unt | Don't count | Minor | | |
| $\begin{array}{c c c c c c c c c c c c c c c c c c c $ | 05 | Round type $\Phi^{-}(X+Y)/2$ | 0.15mm< | $\langle \Phi \ge 0.20 \text{mm}$ | 2 | | Don't count | WIIIOI | | |
| $\begin{array}{ c c c c c } \hline & & & & & & & & & & & & & & & & & & $ | $\Psi = (X + Y)/2$ | | Φ> | 0.25mm | 0 | | Don't count | | | |
| $ \begin{array}{ c c c c } & \label{eq:constraint} \begin{tabular}{ c c c c c } & \ & \ & \ & \ & \ & \ & \ & \ & \ & $ | | y x | | | | | | | | |
| $\begin{array}{ c c c c c c } 06 & & & & & & & & & & & & & & & & & & $ | | Line type | Line type: | | | | | | | |
| $\begin{array}{c c c c c c c c c c c c c c c c c c c $ | | .* w | Length | Length Width | | Acceptance (Q'ty) | | | | |
| 06 1 | | | | $W \leq 0.02$ | | A area | B area | Minor | | |
| $\begin{array}{c c c c c c c c c c c c c c c c c c c $ | 06 | \sim 4° | I < 2 E mm | W = 0.05 mm | 1 05mm | Don t count | Don't count | i i i i i i i i i i i i i i i i i i i | | |
| 07 Touch Panel 7.1 No function. Major 07 Touch Panel 7.1 No function. Major 7.2 The circuitry type must match type in specification sheet. Major 7.3 Appearance inspection as the glass. Major 08 8.1 Light leaks to induce deficiency lightness . Major 8.2 Backlight elements 8.2 Backlight doesn't light or color is wrong. Major 8.3 Illumination source flickers when lit. Major 09 Flexible Printed Circuit 9.1 FPC PIN type is inconsistent with specification sheet. Major 09 Flexible Printed Circuit 9.3 A part of circuits in components on FPC. Major 09 9.3 A part of circuits in circuits of FPC. Major | | → _L ← | L = 2.5 mm | $0.03\text{IIIII} \le W \equiv 0.$ | 05mm | 1 | Don't count | | | |
| 07Touch Panel7.1 No function.Major07Touch Panel7.2 The circuitry type must match type in specification sheet.Major088.1 Light leaks to induce deficiency lightness .Major088.2 Backlight elements8.1 Light leaks to induce deficiency lightness .Major088.3 Illumination source flickers when lit.Major099.1 FPC PIN type is inconsistent with specification sheet.Major099.2 Short circuits in components on FPC.Major099.3 A part of circuits in components on FPC.Major099.4 The crack is in circuits of FPC.Major | | | L= 3.0 | W > 0.05 mm | | Asro | und type | | | |
| 07Touch Panel7.1 No function.Major07Touch Panel7.2 The circuitry type must match type in specification sheet.Major087.3 Appearance inspection as the glass.Major088.1 Light leaks to induce deficiency lightnessMajor088.2 Backlight elements8.1 Light leaks to induce deficiency lightnessMajor8.3 Illumination source flickers when lit.Major099.1 FPC PIN type is inconsistent with specification sheet.Major099.1 FPC PIN type is inconsistent with specification sheet.Major9.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | | | | W > 0.05mm | 1 | 11010 | und type | | | |
| 07Touch Panel7.2 The circuitry type must match type in specification sheet.Major087.3 Appearance inspection as the glass.Major088.1 Light leaks to induce deficiency lightnessMajor088.2 Backlight elements8.2 Backlight doesn't light or color is wrong.Major8.3 Illumination source flickers when lit.Major099.1 FPC PIN type is inconsistent with specification sheet.Major099.2 Short circuits in components on FPC.Major9.4 The crack is in circuits of FPC.Major | | | 7.1 No function | 1. | | | | Major | | |
| 087.3 Appearance inspection as the glass.Major08Backlight elements8.1 Light leaks to induce deficiency lightnessMajor8.2 Backlight doesn't light or color is wrong.Major8.3 Illumination source flickers when lit.Major8.4 he contamination of backlight as NO.05.Minor9.1 FPC PIN type is inconsistent with specification sheet.Major9.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | 07 | Touch Panel | 7.2 The circuit | ry type must match | type in spec | cification sheet. | | Major | | |
| 08Backlight elements8.1 Light leaks to induce deficiency lightnessMajor8.2 Backlight doesn't light or color is wrong.Major8.3 Illumination source flickers when lit.Major8.4 he contamination of backlight as NO.05.Minor9.1 FPC PIN type is inconsistent with specification sheet.Major9.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | | | 7.3 Appearance inspection as the glass. | | | | | | | |
| 08Backlight elements8.2 Backlight doesn't light or color is wrong.Major8.2 Backlight doesn't light or color is wrong.8.2 Backlight doesn't light or color is wrong.Major8.3 Illumination source flickers when lit.Major8.4 he contamination of backlight as NO.05.Minor9.1 FPC PIN type is inconsistent with specification sheet.Major9.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | 00 | | 8.1 Light leaks to induce deficiency lightness . | | | | | | | |
| elements8.3 Illumination source flickers when lit.Major8.4 he contamination of backlight as NO.05.Minor099.1 FPC PIN type is inconsistent with specification sheet.Major9.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | 08 | Backlight | 8.2 Backlight d | loesn't light or cold | r is wrong. | | | Major | | |
| 098.4 he contamination of backlight as NO.05.Minor099.1 FPC PIN type is inconsistent with specification sheet.Major9.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | | elements | 8.3 Illumination | n source flickers w | hen lit. | | | Major | | |
| 099.1 FPC PIN type is inconsistent with specification sheet.Major099.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | | | 8.4 he contamin | nation of backlight | as NO.05. | | | Minor | | |
| 099.2 Short circuits in components on FPC.Major9.3 A part of circuits in components on FPC is missing or wrong9.3 A part of circuits in components on FPC is missing or wrongMajor9.4 The crack is in circuits of FPC.Major | | | 9.1 FPC PIN ty | pe is inconsistent v | with specific | ation sheet. | | Major | | |
| Flexible Printed Circuit 9.3 A part of circuits in components on FPC is missing or wrong Major 9.4 The crack is in circuits of FPC. Major | 09 | | 9.2 Short circuit | its in components of | n FPC. | | | Major | | |
| 9.4 The crack is in circuits of FPC. Major | | Flexible Printed | 9.3 A part of ci | rcuits in componen | ts on FPC is | s missing or wro | ong | Major | | |
| | | Circuit | 9.4 The crack i | s in circuits of FPC | • | | | Major | | |

08/3/2015

10.0 PRECAUTIONS

10.1 Static charge

Since this LCD module contains CMOS LSIs that are sensitive to static charge, care must be taken when handling it.

10.2 Power on sequence

- 1. Input signals should not be applied to the LCD module before the logic system voltage has reached the specified voltage. If the above sequence is not kept the LCD module might be permanently damaged.
- 2. When connecting the power supply, connect the LCD bias voltage after connecting the logic system voltage.
- 3. When disconnecting the power supply, disconnect the logic system voltage *after* the LCD bias voltage.
- 4. It is recommended to connect a serial resistor or fuse to the LCD bias power supply of the system, as a current limiter. The value of the resistor depends on the kind of LCD used, but is typically $50 \sim 100 \Omega$.

10.3 Operation

- It is essential to drive the LCD within the specified voltage limits, since a higher driving voltage than allowed causes a shorter LCD lifetime. Under these circumstances, electrochemical reactions will result in undesirable deterioration of the LCD.
- 2. The response time of the LC fluid is considerably longer at low temperatures than in the normal operating temperature range. On the other hand, the LCD will show a dark blue color at high temperatures. Those phenomena do not indicate a malfunction or defect of the LCD. Back at normal temperatures, the LCD will return to its original behavior.
- 3. If the display area is pressed hard during operation, some abnormal display patterns might appear. However, the display will resume normal operation after turning the module off and on.
- 4. Moisture on the terminals could cause an electrochemical reaction resulting in an open terminal connection. If the environmental temperature is higher than 40°C, it is required that the relative humidity is 50% or less.

10.4 Packaging

- 1. Do not leave the product in a place of high humidity for a long period. For storage in a location where the temperature is 35°C or higher, special care to protect the product from high humidity is required. A combination of high temperature and high humidity may cause polarization degradation and damage as well. Please keep the temperature and humidity within the specified range for storing.
- 2. Since LCD panels tend to be easily damaged, they should be handled with full care. Avoid any contact with materials that have a hardness of more than 2H.
- 3. Adhesives used for adhering upper/lower polarizers and aluminum plates are made of organic substances that will deteriorate by chemical reactions with for example chemicals such as acetone, toluene, ethanol, and isopropylalcohol. Please prevent the use of these chemicals and contact us when it is necessary for you to use other chemicals.
- 4. Immediately wipe off saliva or water drops from the display area with an absorbent cotton cloth, without scrubbing it. If adhered for a long period, such particles might cause deformation or faded color.
- 5. Moisture deposited on the display surface and contact terminals due to low temperatures will be a cause for polarizer damage, stains, and dirt. Before use, such panels should be slowly warmed up to a temperature that is higher than

room temperature.

- 6. Touching the display area and contact terminals with bare hands is harmful to polarizer and may lead to poor insulation at the terminals.
- 7. The glass is fragile and can be cracked or chipped easily by handling, in particular on near its edge. Please prevent sudden shocks or exposing the glass to other sorts of stress.

10.5 Long-term storage

For long-term storage the following methods are highly recommended:

- 1. Store the product in a polyethylene bag with a sealed opening to prevent fresh air entering from the outside. Placing it with a desiccant is not necessary.
- 2. Store the product in a dark place, with the temperature in the range from 0 \degree to 35 \degree .
- 3. Keep the sensitive polarizer surface of the LCD panels clear of any contact. We recommend using the container that was used by SPACE DISPLAY to deliver the products.

10.6 Cleaning of the product

To clean the product make sure to use absorbent cotton cloth or other soft material like chamois. Make sure to rub it gently, and do not use chemicals when cleaning.

11.0 FINAL REMARKS

- 1. The above specifications are the binding criteria for HaoRan display's outgoing quality inspection.
- 2. The customer is kindly requested to inform HaoRan display Technology as soon as possible on any questions, remarks, and disagreements regarding these specifications.
- 3. HaoRan display is not responsible for damage to its products due to neglect of the precautions as described in the previous chapter.

n CLASSIFICATION INFORMATION

<u>H T 020 K1 QC 36 S</u>

(1) (2) (3) (4) (5) (6) (7)

- (1) Brand: SHENZHEN HAORAN DISPLAY CO., LTD
- (2) Display Type: C \rightarrow Character Type, G \rightarrow Graphic Type, T \rightarrow TFT Type
- ③ LCD Size: 2.0inch
- ④ Model Serials No.
- **(5)** LCD Resolution:

| QQ→QQVGA | QC→QCIF | QV→QVGA | HV→HVGA |
|----------|---------|---------|---------|
| WQ→WQVGA | WV→WVGA | QH→QHD | HD→HD |

- (6) Number Of Interface.
- ⑦ Touch Panel Type:

 $S \rightarrow$ Without Touch Panel; $T \rightarrow$ Resistive Touch Panel;

 $C \rightarrow Capacitive Touch Panel;$